



Sun Cluster 3.1 Data Service for BroadVision One-To-One Enterprise

Sun Microsystems, Inc.
4150 Network Circle
Santa Clara, CA 95054
U.S.A.

Part No: 817-1542
May 2003, Revision A

Copyright 2003 Sun Microsystems, Inc. 4150 Network Circle, Santa Clara, CA 95054 U.S.A. All rights reserved.

This product or document is protected by copyright and distributed under licenses restricting its use, copying, distribution, and decompilation. No part of this product or document may be reproduced in any form by any means without prior written authorization of Sun and its licensors, if any. Third-party software, including font technology, is copyrighted and licensed from Sun suppliers.

Parts of the product may be derived from Berkeley BSD systems, licensed from the University of California. UNIX is a registered trademark in the U.S. and other countries, exclusively licensed through X/Open Company, Ltd.

Sun, Sun Microsystems, the Sun logo, docs.sun.com, AnswerBook, AnswerBook2, and Solaris are trademarks, registered trademarks, or service marks of Sun Microsystems, Inc. in the U.S. and other countries. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. in the U.S. and other countries. Products bearing SPARC trademarks are based upon an architecture developed by Sun Microsystems, Inc.

The OPEN LOOK and Sun™ Graphical User Interface was developed by Sun Microsystems, Inc. for its users and licensees. Sun acknowledges the pioneering efforts of Xerox in researching and developing the concept of visual or graphical user interfaces for the computer industry. Sun holds a non-exclusive license from Xerox to the Xerox Graphical User Interface, which license also covers Sun's licensees who implement OPEN LOOK GUIs and otherwise comply with Sun's written license agreements.

Federal Acquisitions: Commercial Software—Government Users Subject to Standard License Terms and Conditions.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.

Copyright 2003 Sun Microsystems, Inc. 4150 Network Circle, Santa Clara, CA 95054 U.S.A. Tous droits réservés.

Ce produit ou document est protégé par un copyright et distribué avec des licences qui en restreignent l'utilisation, la copie, la distribution, et la décompilation. Aucune partie de ce produit ou document ne peut être reproduite sous aucune forme, par quelque moyen que ce soit, sans l'autorisation préalable et écrite de Sun et de ses bailleurs de licence, s'il y en a. Le logiciel détenu par des tiers, et qui comprend la technologie relative aux polices de caractères, est protégé par un copyright et licencié par des fournisseurs de Sun.

Des parties de ce produit pourront être dérivées du système Berkeley BSD licenciés par l'Université de Californie. UNIX est une marque déposée aux Etats-Unis et dans d'autres pays et licenciée exclusivement par X/Open Company, Ltd.

Sun, Sun Microsystems, le logo Sun, docs.sun.com, AnswerBook, AnswerBook2, et Solaris sont des marques de fabrique ou des marques déposées, ou marques de service, de Sun Microsystems, Inc. aux Etats-Unis et dans d'autres pays. Toutes les marques SPARC sont utilisées sous licence et sont des marques de fabrique ou des marques déposées de SPARC International, Inc. aux Etats-Unis et dans d'autres pays. Les produits portant les marques SPARC sont basés sur une architecture développée par Sun Microsystems, Inc.

L'interface d'utilisation graphique OPEN LOOK et Sun™ a été développée par Sun Microsystems, Inc. pour ses utilisateurs et licenciés. Sun reconnaît les efforts de pionniers de Xerox pour la recherche et le développement du concept des interfaces d'utilisation visuelle ou graphique pour l'industrie de l'informatique. Sun détient une licence non exclusive de Xerox sur l'interface d'utilisation graphique Xerox, cette licence couvrant également les licenciés de Sun qui mettent en place l'interface d'utilisation graphique OPEN LOOK et qui en outre se conforment aux licences écrites de Sun.

CETTE PUBLICATION EST FOURNIE "EN L'ETAT" ET AUCUNE GARANTIE, EXPRESSE OU IMPLICITE, N'EST ACCORDEE, Y COMPRIS DES GARANTIES CONCERNANT LA VALEUR MARCHANDE, L'APTITUDE DE LA PUBLICATION A REpondre A UNE UTILISATION PARTICULIERE, OU LE FAIT QU'ELLE NE SOIT PAS CONTREFAISANTE DE PRODUIT DE TIERS. CE DENI DE GARANTIE NE S'APPLIQUERAIT PAS, DANS LA MESURE OU IL SERAIT TENU JURIDIQUEMENT NUL ET NON AVENU.



030314@5533



Contents

Preface 5

Installing and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise 11

Sun Cluster HA for BroadVision One-To-One Enterprise Overview 12

Task Map: Installing and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise 13

Planning the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration 14

Configuration Restrictions 14

Configuration Requirements 15

Standard Data Service Configurations 15

Configuration Considerations 18

Configuration Planning Questions 18

Preparing the Nodes and Disks 19

▼ How to Prevent a Server-Port Conflict 19

Installing and Configuring the BroadVision One-To-One Enterprise Software, the Database, and the HTTP Server 20

▼ How to Install and Configure Sun Cluster HA for DBMS 20

▼ How to Install and Configure Your HTTP Server 20

▼ How to Install and Configure the BroadVision One-To-One Enterprise Software 21

▼ How to Configure and Verify the BroadVision One-To-One Enterprise Software, Database, and HTTP Server Installation 22

Installing the Sun Cluster HA for BroadVision One-To-One Enterprise Package 28

▼ How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages 28

Registering and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise	29
Sun Cluster HA for BroadVision One-To-One Enterprise Extension Properties	29
▼ How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise	32
▼ How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration	34
▼ How to Connect the Command Center to BroadVision One-To-One Enterprise Servers	35
Examples – Installing, Configuring, and Administering Sun Cluster HA for BroadVision One-To-One Enterprise	36
Example One – Installation and Configuration	37
Example Two – Administration Commands	38
Alternative Configuration	39
▼ Alternative Configuration: How to Configure and Verify the BroadVision One-To-One Enterprise, Database, and HTTP Server Installation	39
▼ Alternative Configuration: How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages	43
▼ Alternative Configuration: How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise	44
▼ Alternative Configuration: How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation	46
Understanding Sun Cluster HA for BroadVision One-To-One Enterprise Fault Monitor	47
Interaction Manager Fault Monitoring	47
Sun Cluster HA for BroadVision One-To-One Enterprise Fault Probes	48
Understanding BroadVision One-To-One Enterprise Functionality	48
Index	51

Preface

The Sun Cluster 3.1 Data Service for BroadVision One-To-One Enterprise contains procedures to install and configure Sun Cluster HA for BroadVision One-To-One Enterprise.

This document is intended for system administrators with extensive knowledge of Sun software and hardware. Do not use this document as a planning or presales guide. Before reading this document, you should have already determined your system requirements and purchased the appropriate equipment and software.

The instructions in this document assume knowledge of the Solaris™ operating environment and expertise with the volume manager software used with Sun Cluster.

UNIX Commands

This document contains information on commands specific to installing and configuring Sun Cluster data services. It might not contain information on basic UNIX® commands and procedures, such as shutting down the system, booting the system, and configuring devices. For that information, see one or more of the following:

- Online documentation for the Solaris software environment
- Solaris operating environment man pages
- Other software documentation that you received with your system

Typographic Conventions

Typeface or Symbol	Meaning	Examples
AaBbCc123	The names of commands, files, and directories; on-screen computer output	Edit your file. Use <code>ls -a</code> to list all files. % You have mail.
AaBbCc123	What you type, when contrasted with on-screen computer output	% su Password:
<i>AaBbCc123</i>	Book titles, new words or terms, words to be emphasized	Read Chapter 6 in the <i>User's Guide</i> . These are called <i>class</i> options. You <i>must</i> be superuser to do this.
	Command-line variable; replace with a real name or value	To delete a file, type <code>rm filename</code> .

Shell Prompts

Shell	Prompt
C shell	<i>machine_name%</i>
C shell superuser	<i>machine_name#</i>
Bourne shell and Korn shell	\$
Bourne shell and Korn shell superuser	#

Related Documentation

Application	Title	Part Number
Installation	<i>Sun Cluster 3.1 Software Installation Guide</i>	816-3388
Data Services Installation and Configuration	<i>Sun Cluster 3.1 Data Service Planning and Administration Guide</i>	817-1526
	<i>Sun Cluster 3.1 Data Service for Apache</i>	817-1532
	<i>Sun Cluster 3.1 Data Service for BroadVision One-To-One Enterprise</i>	817-1542
	<i>Sun Cluster 3.1 Data Service for Domain Name Service (DNS)</i>	817-1533
	<i>Sun Cluster 3.1 Data Service for Netbackup</i>	817-1538
	<i>Sun Cluster 3.1 Data Service for Network File System (NFS)</i>	817-1534
	<i>Sun Cluster 3.1 Data Service for Oracle</i>	817-1527
	<i>Sun Cluster 3.1 Data Service for Oracle Parallel Server/Real Application Clusters</i>	817-1535
	<i>Sun Cluster 3.1 Data Service for SAP</i>	817-1536
	<i>Sun Cluster 3.1 Data Service for SAP liveCache</i>	817-1539
	<i>Sun Cluster 3.1 Data Service for Siebel</i>	817-1540
	<i>Sun Cluster 3.1 Data Service for Sun ONE Application Server</i>	817-1530
	<i>Sun Cluster 3.1 Data Service for Sun ONE Directory Server</i>	817-1529
	<i>Sun Cluster 3.1 Data Service for Sun ONE Message Queue</i>	817-1531
	<i>Sun Cluster 3.1 Data Service for Sun ONE Web Server</i>	817-1528
	<i>Sun Cluster 3.1 Data Service for Sybase ASE</i>	817-1537
<i>Sun Cluster 3.1 Data Service for WebLogic Server</i>	817-1537	
<i>Sun Cluster 3.1 Data Service for DHCP</i>	817-1716	
<i>Sun Cluster 3.1 Data Service for Samba</i>	817-1715	
<i>Sun Cluster 3.1 Data Service for WebSphere MQ</i>	817-1714	

Application	Title	Part Number
	<i>Sun Cluster 3.1 Data Service for WebSphere MQ Integrator</i>	817-1713
Hardware	<i>Sun Cluster 3.x Hardware Administration Manual</i>	817-0168
	Sun Cluster 3.x Data Service Collection at http://docs.sun.com/db/coll/1024.1	
API development	<i>Sun Cluster 3.1 Data Services Developer's Guide</i>	816-3385
Administration	<i>Sun Cluster 3.1 5/03 System Administration Guide</i>	816-3384
Cluster concepts	<i>Sun Cluster 3.1 Concepts Guide</i>	816-3383
Error Messages	<i>Sun Cluster 3.1 Error Messages Guide</i>	816-3382
Man Pages	<i>Sun Cluster 3.1 Reference Manual</i>	816-5251
Release notes	<i>Sun Cluster 3.1 Data Service 5/03 Release Notes</i>	817-1790
	<i>Sun Cluster 3.1 Release Notes</i>	816-5317
	<i>Sun Cluster 3.1 Release Notes Supplement</i>	816-3381

Sun Documentation Online

The docs.sun.comSM Web site enables you to access Sun technical documentation on the Web. You can browse the docs.sun.com archive or search for a specific book title or subject at <http://docs.sun.com>.

Help

If you have problems installing or using Sun Cluster, contact your service provider and provide the following information:

- Your name and E-mail address (if available)
- Your company name, address, and phone number
- The model and serial numbers of your systems
- The release number of the operating environment (for example, Solaris 8)
- The release number of Sun Cluster (for example, Sun Cluster 3.0)

Use the following commands to gather information about each node on your system for your service provider.

Command	Function
<code>prtconf -v</code>	Displays the size of the system memory and reports information about peripheral devices.
<code>psrinfo -v</code>	Displays information about processors.
<code>showrev -p</code>	Reports which patches are installed.
<code>prtdiag -v</code>	Displays system diagnostic information.
<code>scinstall -pv</code>	Displays Sun Cluster release and package version information.

Also have available the contents of the `/var/adm/messages` file.

Installing and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise

This chapter contains the procedures on how to install and configure Sun Cluster HA for BroadVision One-To-One Enterprise.

This chapter contains the following procedures.

- “How to Prevent a Server-Port Conflict” on page 19
- “How to Install and Configure Sun Cluster HA for DBMS” on page 20
- “How to Install and Configure Your HTTP Server” on page 20
- “How to Install and Configure the BroadVision One-To-One Enterprise Software” on page 21
- “How to Configure and Verify the BroadVision One-To-One Enterprise Software, Database, and HTTP Server Installation” on page 22
- “How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages” on page 28
- “How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise” on page 32
- “How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration” on page 34
- “How to Connect the Command Center to BroadVision One-To-One Enterprise Servers” on page 35
- “Alternative Configuration: How to Configure and Verify the BroadVision One-To-One Enterprise, Database, and HTTP Server Installation” on page 39
- “Alternative Configuration: How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages” on page 43
- “Alternative Configuration: How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise” on page 44
- “Alternative Configuration: How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation” on page 46

Configure Sun Cluster HA for BroadVision One-To-One Enterprise back-end servers as a failover data service. Configure Sun Cluster HA for BroadVision One-To-One Enterprise Interaction Managers as a scalable data service. See the *Sun Cluster 3.1*

Concepts Guide document and “Planning for Sun Cluster Data Services” in *Sun Cluster 3.1 Data Service Planning and Administration Guide* for general information about data services, resource groups, resources, and other related topics.

Sun Cluster HA for BroadVision One-To-One Enterprise Overview

Use the information in this section to understand how Sun Cluster HA for BroadVision One-To-One Enterprise makes BroadVision One-To-One Enterprise highly available.

For conceptual information on failover and scalable services, see the *Sun Cluster 3.1 Concepts Guide*.

Sun Cluster HA for BroadVision One-To-One Enterprise provides fault monitoring and automatic failover for the BroadVision One-To-One Enterprise servers. This data service uses fault monitoring and automatic failover to eliminate single points of failure in a BroadVision One-To-One Enterprise site.

TABLE 1-1 Protection of BroadVision One-To-One Enterprise Site Components

BroadVision One-To-One Enterprise site component	Protected by
BroadVision One-To-One Enterprise database	Sun Cluster HA for Oracle or Sun Cluster HA for Sybase ASE
BroadVision One-To-One Enterprise Interaction Managers	Sun Cluster HA for BroadVision One-To-One Enterprise (scalable configuration)
BroadVision One-To-One Enterprise back-end servers	Sun Cluster HA for BroadVision One-To-One Enterprise (failover configuration)
HTTP servers	Sun Cluster HA for Sun ONE Web Server or Sun Cluster HA for Apache

Task Map: Installing and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise

Table 1–2 lists the tasks for installing and configuring Sun Cluster HA for BroadVision One-To-One Enterprise. Perform these tasks in the order that they are listed.

TABLE 1–2 Task Map: Installing and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise

Task	For Instructions, Go To ...
Plan the BroadVision One-To-One Enterprise installation and configuration	Chapter 1 of <i>Sun Cluster 3.1 Data Service for BroadVision One-To-One Enterprise</i> “Planning the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration” on page 14
Prepare the nodes and disks	“How to Prevent a Server-Port Conflict” on page 19
Install and configure the BroadVision One-To-One Enterprise software, the HTTP servers, and the database	“How to Install and Configure Sun Cluster HA for DBMS” on page 20 “How to Install and Configure Your HTTP Server” on page 20 “How to Install and Configure the BroadVision One-To-One Enterprise Software” on page 21 ¹ “How to Configure and Verify the BroadVision One-To-One Enterprise Software, Database, and HTTP Server Installation” on page 22
Install the Sun Cluster HA for BroadVision One-To-One Enterprise packages	“How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages” on page 28
Register and configure Sun Cluster HA for BroadVision One-To-One Enterprise	“How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise” on page 32 “How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration” on page 34

group with n logical hostnames, proceed to “Alternative Configuration” on page 39. Follow the procedures that are listed in “Alternative Configuration” on page 39 to complete the installation. Otherwise, continue to “How to Configure and Verify the BroadVision One-To-One Enterprise Software, Database, and HTTP Server Installation” on page 22.

TABLE 1-2 Task Map: Installing and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise (Continued)

Task	For Instructions, Go To ...
Connect the Command Center to BroadVision One-To-One Enterprise servers	"How to Connect the Command Center to BroadVision One-To-One Enterprise Servers" on page 35
Understand Sun Cluster HA for BroadVision One-To-One Enterprise fault monitor information	"Understanding Sun Cluster HA for BroadVision One-To-One Enterprise Fault Monitor" on page 47
Understand BroadVision One-To-One Enterprise functionality	"Understanding BroadVision One-To-One Enterprise Functionality" on page 48

Planning the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration

This section contains the information you need to plan your Sun Cluster HA for BroadVision One-To-One Enterprise installation and configuration.

Configuration Restrictions



Caution – Your data service configuration might not be supported if you do not observe these restrictions.

Use the restrictions in this section to plan the installation and configuration of Sun Cluster HA for BroadVision One-To-One Enterprise. This section provides a list of software and hardware configuration restrictions that apply to Sun Cluster HA for BroadVision One-To-One Enterprise.

For restrictions that apply to all data services, see the *Sun Cluster 3.1 Release Notes*.

- Use a BroadVision One-To-One Enterprise software version that is qualified with Sun Cluster 3.1.

Configuration Requirements



Caution – Your data service configuration might not be supported if you do not adhere to these requirements.

Use the requirements in this section to plan the installation and configuration of Sun Cluster HA for BroadVision One-To-One Enterprise. These requirements apply to Sun Cluster HA for BroadVision One-To-One Enterprise only. You must meet these requirements before you proceed with your Sun Cluster HA for BroadVision One-To-One Enterprise installation and configuration.

For requirements that apply to all data services, see “Identifying Data Service Special Requirements” on page 3.

- Install the BroadVision One-To-One Enterprise software on the cluster file system.
- Create a BroadVision user that is identical on all of the cluster nodes.
- Install all of the necessary patches that are supplied by BroadVision to enable the BroadVision One-To-One Enterprise software to run in the Sun Cluster environment.
- Configure the Interaction Managers, back-end servers, and root hosts in the `$BV1TO1_VAR/etc/bv1to1.conf` configuration file, as shown in “Standard Data Service Configurations” on page 15.
- Start your database before you start the BroadVision One-To-One Enterprise servers.

Standard Data Service Configurations

Use the standard configurations in this section to plan the installation and configuration of Sun Cluster HA for BroadVision One-To-One Enterprise. Sun Cluster HA for BroadVision One-To-One Enterprise supports the standard configurations in this section. Sun Cluster HA for BroadVision One-To-One Enterprise might support additional configurations. However, you must contact your Enterprise Services representative for information on additional configurations.

- “Cluster With Multiple Resource Groups for the BroadVision One-To-One Enterprise Software” on page 16
- “Alternative Configuration: Cluster With One Resource Group for the BroadVision One-To-One Enterprise Back-End and Root Host Servers” on page 17

For all of the supported configurations, set up your highly available database and HTTP server to match “Sun Cluster HA for DBMS and HTTP Server Configuration” on page 16.

Sun Cluster HA for DBMS and HTTP Server Configuration

Configure Sun Cluster HA for DBMS and HTTP server as follows.

- Configure Sun Cluster HA for Oracle or Sun Cluster HA for Sybase ASE to use a logical hostname.
- Configure Sun Cluster HA for Sun ONE Web Server or Sun Cluster HA for Apache to use a logical hostname (for failover configuration) or to use a shared address (for scalable configuration).

Cluster With Multiple Resource Groups for the BroadVision One-To-One Enterprise Software

Configure the BroadVision One-To-One Enterprise root host, back-end, and Interaction Manager processes as follows.

- Configure the root host resource to use one logical hostname in one resource group.
- Configure back-end resources to use the remaining logical hostnames in multiple resource groups.
- Configure the Interaction Manager resource on one of the following locations.
 - All of the cluster nodes.
 - All of the cluster private hostnames. See the *Sun Cluster 3.1 Software Installation Guide for details* on cluster interconnect and private hostnames.

Figure 1–1 illustrates a sample configuration that meets these guidelines.




FIGURE 1–1 Sample Configuration: Cluster With Three Logical Hostnames Configured Into Separate Resource Groups

Note – Configure Interaction Manager resources on all of the cluster nodes or on all of the cluster private hostnames. If you configure the Interaction Managers on all of the cluster private hostnames, set up the HTTP servers on the same cluster. Alternatively, if you configure the Interaction Managers on all of the cluster nodes, the HTTP servers can be set up outside of the cluster.

Alternative Configuration: Cluster With One Resource Group for the BroadVision One-To-One Enterprise Back-End and Root Host Servers

Depending on the flexibility and granularity of administration that you require for each back-end resource, you can configure Sun Cluster HA for BroadVision One-To-One Enterprise back-end servers to use only one resource group. To set up this alternative configuration, configure the BroadVision One-To-One Enterprise root host, back-end, and Interaction Manager processes as follows.

- Configure root host and all of the back-end resources to use n logical hostnames inside of the same failover resource group.
- Configure the Interaction Manager resource on one of the following locations.
 - All of the cluster nodes.
 - All of the cluster private hostnames. See the *Sun Cluster 3.1 Software Installation Guide* for details on cluster interconnect and private hostnames.

This configuration, which Figure 1–2 illustrates, requires alternative steps. See “Alternative Configuration” on page 39 for more information.




FIGURE 1–2 Sample Configuration: Cluster With Three Logical Hostnames Configured Into One Resource Group

Note – Configure Interaction Manager resources on all of the cluster nodes or on all of the cluster private hostnames. If you configure the Interaction Managers on all of the cluster private hostnames, set up the HTTP servers on the same cluster. Alternatively, if you configure the Interaction Managers on all of the cluster nodes, the HTTP servers can be set up outside of the cluster.

Configuration Considerations

Use the information in this section to plan the installation and configuration of Sun Cluster HA for BroadVision One-To-One Enterprise. The information in this section encourages you to think about the impact your decisions have on the installation and configuration of Sun Cluster HA for BroadVision One-To-One Enterprise.

- **BroadVision user home directory** – Create an identical BroadVision user (*bvuser*) on all of the cluster nodes. Place the BroadVision user home directory on the cluster file system. Direct all of the BroadVision users on all of the cluster nodes to the same home directory.
- **BroadVision One-To-One Enterprise software** – Install the BroadVision One-To-One Enterprise software on the cluster file system so that all of the cluster nodes can access the same BroadVision One-To-One Enterprise binaries and configuration files.

Configuration Planning Questions

Use the questions in this section to plan the installation and configuration of Sun Cluster HA for BroadVision One-To-One Enterprise. Insert the answers to these questions into the data service worksheets in the *Sun Cluster 3.1 Release Notes*. See “Configuration Considerations” on page 18 for information that might apply to these questions.

- Will you run Sun Cluster HA for BroadVision One-To-One Enterprise as a failover or as a scalable data service?
- If you run Sun Cluster HA for BroadVision One-To-One Enterprise as a scalable service, what nodes will host the scalable service?
- What resource groups will you use for network addresses and application resources and the dependencies between them?
- What is the logical hostname (for failover services) or shared address (for scalable services) for clients that will access the data service?
- Where will the system configuration files reside?
See “Determining the Location of the Application Binaries” on page 3 of the *Sun Cluster 3.1 Data Service for BroadVision One-To-One Enterprise* for the advantages and disadvantages of placing the BroadVision One-To-One Enterprise binaries on the local file system as opposed to the cluster file system.

Preparing the Nodes and Disks

This section contains the procedures you need to prepare the nodes and disks.

▼ How to Prevent a Server-Port Conflict

Use this procedure to prepare for the installation and configuration of Sun Cluster HA for BroadVision One-To-One Enterprise.

By default, the `orbix` daemon chooses an available port number that the `IT_DAEMON_SERVER_BASE` and `IT_DAEMON_SERVER_RANGE` properties specify for use by a server that the daemon launches. When a client attempts to connect to a server for the first time, the client asks the `orbix` daemon for the port number. Then the client connects to the port that the `orbix` daemon specifies. If failover occurs after the client asks the `orbix` daemon for the port number but before the client connects to that port, the client might connect to the wrong server.

This procedure provides you two options to prevent a server-port conflict.

1. Which option do you prefer?

- Configure the `IT_LOCAL_SERVER_BASE` property for each host
If yes, proceed to Step 2
- Add the `iiop_port` parameter to each process entry in the `bv1to1.conf` file
If yes, skip to Step 3

2. Configure the `IT_LOCAL_SERVER_BASE` property for each host so that ports that the `orbix` daemon assigns on different nodes will never overlap. For example, if you configure BroadVision One-To-One Enterprise servers and the Interaction Manager to run on cluster nodes A, B, and C, the `bv1to1.conf` file will have the following entries.

```
export
...
IT_DAEMON_SERVER_RANGE = "200";
...
site bv
{
...
node A {
export IT_LOCAL_SERVER_BASE = "1300";
...
}
node B {
export IT_LOCAL_SERVER_BASE = "1500";      # 1300 + 200
```

```

    ...
  }
  node C {
    export IT_LOCAL_SERVER_BASE = "1700";      # 1500 + 200
    ...
  }
  ...
}

```

3. Add the `iiop_port` parameter to each process entry in the `bv1to1.conf` file, and ensure that no two server-port entries conflict. The `iiop_port` is an undocumented parameter of the BroadVision One-To-One Enterprise server that specifies which port a server should use. For example, the following process entry defines the `cntddb` server on port 1305.

```
process cntddb { parameter iiop_port = "1305"; }
```

C++ CORBA servers support the `iiop_port` parameter. For Java servers, you must upgrade to BroadVision One-To-One Enterprise 6.0AB or later versions.

Installing and Configuring the BroadVision One-To-One Enterprise Software, the Database, and the HTTP Server

This section contains the procedures you need to install and configure the BroadVision One-To-One Enterprise software, the database software, the HTTP software.

▼ How to Install and Configure Sun Cluster HA for DBMS

See *Sun Cluster 3.1 Data Service for Oracle* to install Sun Cluster HA for Oracle or *Sun Cluster 3.1 Data Service for Sybase ASE* to install Sun Cluster HA for Sybase ASE.

▼ How to Install and Configure Your HTTP Server

If Sun ONE Web Server is your HTTP server, follow the instructions in *Sun Cluster 3.1 Data Service for Sun ONE Web Server* to configure Sun Cluster HA for Sun ONE Web Server. If Apache Web Server is your HTTP server, follow the instructions in *Sun Cluster 3.1 Data Service for Apache* to configure Sun Cluster HA for Apache.

▼ How to Install and Configure the BroadVision One-To-One Enterprise Software

Use this procedure to install and configure the BroadVision One-To-One Enterprise software and how to enable the BroadVision One-To-One Enterprise software to run in the Sun Cluster environment.

1. Follow the guidelines that are listed in “Planning the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration” on page 14 and “Configuration Considerations” on page 18.
2. Follow the instructions in the *BroadVision One-To-One Enterprise Installation and Administration Guide* to install the BroadVision One-To-One Enterprise software on the cluster file system.

Note – Install the BroadVision One-To-One Enterprise software only once, on the cluster file system, from any cluster node.

3. Configure the `$BV1TO1_VAR/etc/bv1to1.conf` file.

Table 1–3 summarizes possible configurations in the `$BV1TO1_VAR/etc/bv1to1.conf` file for the BroadVision One-To-One Enterprise components. See “Standard Data Service Configurations” on page 15 and the instructions in the *BroadVision One-To-One Enterprise Installation and Administration Guide* for details.

TABLE 1–3 Configuring the `$BV1TO1_VAR/etc/bv1to1.conf` File

BroadVision One-To-One Enterprise component	Where to configure
Root host	Logical hostname
Back-end servers	Logical hostname
Interaction Managers	All of the cluster nodes or all of the cluster private hostnames ¹

See the *Sun Cluster 3.1 Software Installation Guide* for details on cluster interconnect and private hostnames.

Note – If you configure the Interaction Managers on all of the cluster private hostnames, set up the HTTP servers on the same cluster. Alternatively, if you configure the Interaction Managers on all of the cluster nodes, the HTTP servers can be set up outside of the cluster.

Note – Configure your cluster so that BroadVision One-To-One Enterprise back-end servers can access the database from any cluster node.

Where to Go From Here

Depending on the flexibility and granularity of administration that you require for each back-end resource, you can set up your failover resource groups in one of the following ways.

- Set up multiple failover resource groups to use multiple logical hostnames. If you plan to use this option, go to “How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration” on page 34.
- Set up one failover resource group to use n logical hostnames and to contain all of the back-end and root host resources. If you plan to use this option, proceed to “Alternative Configuration” on page 39. Follow the procedures throughout “Alternative Configuration” on page 39 to complete the installation.

Note – See “Standard Data Service Configurations” on page 15 for more information.

▼ How to Configure and Verify the BroadVision One-To-One Enterprise Software, Database, and HTTP Server Installation

Use this procedure to test starting and stopping the back-end processes on all of the nodes on which the back-end host and root host can run in a failover configuration. Additionally, perform this procedure to test the BroadVision One-To-One Enterprise Interaction Managers that you configured in the cluster.

Depending on the flexibility and granularity of administration that you require for each back-end resource, you can set up your failover resource groups in one of the following ways.

- Set up multiple failover resource groups to use multiple logical hostnames. If you plan to use this option, proceed to Step 1.
- Set up one failover resource group to use n logical hostnames and to contain all of the back-end and root host resources. If you plan to use this option, go to “Alternative Configuration” on page 39. Follow the procedures throughout “Alternative Configuration” on page 39 to complete the installation.

Note – See “Standard Data Service Configurations” on page 15 for more information.

1. **To contain the BroadVision One-To-One Enterprise root host resource, create a failover resource group that uses the root host logical hostname.**

```
# scrgadm -a -g root-host-resource-group [-h nodelist]
```

`-g root-host-resource-group` Specifies the name of the resource group that uses the root host logical hostname and contains the BroadVision root host resource. The name of the root host resource group can be your choice but must be unique for resource groups within the cluster.

`[-h nodelist]` Specifies an optional, comma-separated list of physical node names or IDs that identify potential masters. The order here determines the order in which the Resource Group Manager (RGM) considers primary nodes during failover.

2. **Create failover resource groups for the root host and back-end processes.**

Run the `scrgadm(1M)` command to configure n failover resource groups for back-end processes that are configured on n logical hostnames.

```
# scrgadm -a -g back-end-resource-group-1 [-h nodelist]
# scrgadm -a -g back-end-resource-group-2 [-h nodelist]
# scrgadm -a -g back-end-resource-group-3 [-h nodelist]
...
# scrgadm -a -g back-end-resource-group-n [-h nodelist]
```

`-g back-end-resource-group` Specifies the name of the resource group that contains the back-end logical hostname and resource. The name of the back-end resource group can be your choice but must be unique for resource groups within the cluster.

3. **Verify that you have added all of the logical hostnames that you use to your name service database.**

Additionally, add all of the logical hostnames that you use to the `/etc/inet/hosts` file on each cluster node. Therefore, if the name service goes down, the nodes can still find the name-to-address mapping on their local hosts file.

4. **Run the `scrgadm` command to add the logical hostname that each of the resource groups that you have created can use.**

```
# scrgadm -a -L -g root-host-resource-group -l root-host-logical-hostname-1 [-n netiflist]
# scrgadm -a -L -g back-end-resource-group-1 -l back-end-logical-hostname-1 [-n netiflist]
# scrgadm -a -L -g back-end-resource-group-2 -l back-end-logical-hostname-2 [-n netiflist]
...
# scrgadm -a -L -g back-end-resource-group-n -l back-end-logical-hostname-n [-n netiflist]
```

- l *root-host-logical-hostname* Specifies the logical hostname (failover IP address) that the root host resource group uses.
- l *back-end-logical-hostname* Specifies the logical hostname that each back-end resource group uses.
- [-n *netiflist*] Specifies an optional, comma-separated list that identifies the IP Networking Multipathing groups that are on each node. Each element in *netiflist* must be in the form of *netif@node*. *netif* can be given as an IP Networking Multipathing group name, such as *sc_ipmp0*. The node can be identified by the node name or node ID, such as *sc_ipmp0@1* or *sc_ipmp@phys-schost-1*.

Note – Sun Cluster does not currently support using the adapter name for *netif*.

5. Create a scalable resource group for the Interaction Managers.

- ```
scrgadm -a -g im-resource-group -y Maximum primaries=m -y Desired primaries=n
```
- g *im-resource-group* Specifies the name of the scalable resource group that contains the Interaction Managers. This name can be your choice but must be unique for resource groups within the cluster.
  - y *Maximum primaries=m* Specifies the maximum number of active primary nodes allowed for this resource group. If you do not assign a value to this property, the default is 1.
  - y *Desired primaries=n* Specifies the desired number of active primary nodes allowed for this resource group. If you do not assign a value to this property, the default is 1.

### 6. From one cluster node, run the `scswitch(1M)` command to move the failover resource groups into the managed state and bring them online.

```
scswitch -Z -g root-host-resource-group
scswitch -Z -g back-end-resource-group-1
scswitch -Z -g back-end-resource-group-2
...
scswitch -Z -g back-end-resource-group-n
```



---

**Note** – You do not need to bring the scalable resource group online because the scalable resource group does not yet contain resources. You must bring failover resource groups online because the BroadVision One-To-One Enterprise back-end processes cannot start if the logical hostname resource is unavailable.

---

**7. Check that the database is accessible.**

See your database documentation for details.

**8. Ensure that you have configured the database to enable BroadVision One-To-One Enterprise back-end servers to access the database from any cluster node.**

See your database documentation for details.

**9. As the BroadVision user, log in to the cluster node that hosts the root host resource group.**

**10. Follow the steps in the *BroadVision One-To-One Enterprise Installation and Administration Guide* to run the following BroadVision commands.**

a. Set the `BV_LOCAL_HOST` environment variable as *root-host-logical-hostname*.

b. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.

c. Run the `bvconf bootstrap` command on the root host to initialize the BroadVision One-To-One Enterprise installation.

---

**Note** – Do not run the `bvconf` command as superuser.

---

```
% bvconf bootstrap -r root-host-logical-hostname
```

d. Set the `BV_LOCAL_HOST` environment variable as *back-end-logical-hostname* or *im-hostname*.

e. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.

f. Ensure that the `/etc/opt/BVSNsmgr` directory exists and has write and execute permissions.

g. For each back-end host and Interaction Manager host, run the `bvconf execute` command to configure and start the BroadVision One-To-One Enterprise processes.

```
% bvconf execute -local -var shared -r root-host-logical-hostname
```

**11. Run the BroadVision command `bvconf gateway` to generate gateway configuration files for the HTTP gateway applications.**

This command generates the files and writes them to the `$BV1TO1_VAR/etc/appName.cfg` file.

```
% bvconf gateway -A appName
```

`-A appName` Specifies the gateway application name, which is defined in the `$BV1TO1_VAR/etc/bv1to1.conf` configuration file. See the *BroadVision One-To-One Enterprise Installation and Administration Guide* for details.

**12. Copy the gateway application configuration file to the `/etc/opt/BVSNsmgr` directory on each of the cluster nodes that runs HTTP instances.**

---

**Note** – Ensure that you copy the gateway application configuration file with the extension `.cfg`.

---

See the *BroadVision One-To-One Enterprise Installation and Administration Guide* for details.

**13. Configure and start the HTTP servers.**

See your HTTP server documentation for details. Additionally, see the *BroadVision One-To-One Enterprise Installation and Administration Guide* for information on HTTP server configuration.

**14. From a BroadVision client, connect to the BroadVision site, and check the installation.**

**15. If the BroadVision One-To-One Enterprise software is functioning correctly, perform the following steps to shut down the Interaction Managers, back-end processes, and root host processes.**

**a. Shut down the Interaction Managers.**

- i. Set the `BV_LOCAL_HOST` environment variable as `im-hostname`.
- ii. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.
- iii. Run the following command.

```
bvconf shutdown -local
```

**b. Shut down the back-end processes.**

- i. Set the `BV_LOCAL_HOST` environment variable as `back-end-logical-hostname`.

ii. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.

iii. Run the following command.

```
bvconf shutdown -local
```

c. Shut down the root host processes.

i. Set the `BV_LOCAL_HOST` environment variable as `root-host-logical-hostname`.

ii. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.

iii. Run the following command.

```
bvconf shutdown -local
```

16. Run the `scswitch` command to switch the resource groups to another cluster node, such as `node2`.

```
scswitch -z -g root-host-resource-group -h node2
scswitch -z -g back-end-resource-group-1 -h node2
scswitch -z -g back-end-resource-group-2 -h node2
...
scswitch -z -g back-end-resource-group-n -h node2
```

17. Restart the BroadVision One-To-One Enterprise software on `node2`.

18. Connect to the cluster from a BroadVision client, and check that the BroadVision One-To-One Enterprise software functions correctly.

19. Repeat Step 15 through Step 18 on all of the potential primaries of the BroadVision One-To-One Enterprise resource groups.

## Where to Go From Here

After you verify the BroadVision One-To-One Enterprise software, database, and HTTP server installation, go to “How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages” on page 28.

---

# Installing the Sun Cluster HA for BroadVision One-To-One Enterprise Package

This section contains the procedure you need to install the Sun Cluster HA for BroadVision One-To-One Enterprise packages.

## ▼ How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages

Use this procedure to install the Sun Cluster HA for BroadVision One-To-One Enterprise packages. You need the Sun Cluster Agents CD-ROM to perform this procedure. This procedure assumes that you did not install the data service packages during your initial Sun Cluster installation. If you installed the Sun Cluster HA for BroadVision One-To-One Enterprise packages as part of your initial Sun Cluster installation, proceed to “Registering and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise” on page 29 to install and configure Sun Cluster HA for BroadVision One-To-One Enterprise. Otherwise, use this procedure to install the Sun Cluster HA for BroadVision One-To-One Enterprise packages. Perform this procedure on all nodes that can run Sun Cluster HA for BroadVision One-To-One Enterprise.

- 1. Load the Sun Cluster Agents CD-ROM into the CD-ROM drive.**
- 2. Run the `scinstall` utility with no options.**

This step starts the `scinstall` utility in interactive mode.
- 3. Choose the menu option, Add Support for New Data Service to This Cluster Node.**

The `scinstall` utility prompts you for additional information.
- 4. Provide the path to the Sun Cluster Agents CD-ROM.**

The utility refers to the CD as the “data services cd.”
- 5. Specify the data service to install.**

The `scinstall` utility lists the data service that you selected and asks you to confirm your choice.
- 6. Exit the `scinstall` utility.**
- 7. Unload the CD from the drive.**

## Where to Go From Here

When you finish the Sun Cluster HA for BroadVision One-To-One Enterprise package installation, go to “How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise” on page 32.

---

# Registering and Configuring Sun Cluster HA for BroadVision One-To-One Enterprise

This section contains the procedures you need to configure Sun Cluster HA for BroadVision One-To-One Enterprise.

## Sun Cluster HA for BroadVision One-To-One Enterprise Extension Properties

Use the extension properties in Table 1–4 to create your resources. Use the command line `scrgadm -x parameter=value` to configure extension properties when you create your resource. Use the procedure in Chapter 13 of the Sun Cluster 3.1 Data Service for BroadVision One-To-One Enterprise to configure the extension properties if you have already created your resources. You can update some extension properties dynamically. You can update others, however, only when you create or disable a resource. The Tunable entries indicate when you can update each property. See Appendix A of the Sun Cluster 3.1 Data Service for BroadVision One-To-One Enterprise for details on all Sun Cluster properties.

**TABLE 1-4** Sun Cluster HA for BroadVision One-To-One Enterprise Extension Properties

| <b>Property Category</b>                                 | <b>Property Name</b> | <b>Description</b>                                                                                                                           |
|----------------------------------------------------------|----------------------|----------------------------------------------------------------------------------------------------------------------------------------------|
| BroadVision<br>One-To-One<br>Enterprise<br>configuration | BVUSER               | The BroadVision user UNIX ID. Replace <i>bvuser</i> with your preferred username.<br><br><b>Default:</b> None<br><b>Tunable:</b> At creation |
|                                                          | BV1TO1_VAR           | The environment variable that is set as <i>bvuser</i> .<br><br><b>Default:</b> None<br><b>Tunable:</b> At creation                           |

**TABLE 1-4** Sun Cluster HA for BroadVision One-To-One Enterprise Extension Properties  
(Continued)

| Property Category | Property Name          | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
|-------------------|------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Probe             | Monitor_retry_interval | The time (in minutes) over which the Resource Group Manager (RGM) counts fault monitor failures. The number of times that the fault monitor fails can exceed the value that the extension property Monitor_retry_count specifies. If the number of failures exceeds the value of Monitor_retry_count within the time period that Monitor_retry_interval specifies, the Process Monitor Facility (PMF) does not restart the fault monitor.<br><b>Default:</b> 2<br><b>Tunable:</b> Any time |
|                   | Monitor_retry_count    | The number of PMF restarts that the Sun Cluster software allows for the fault monitor.<br><b>Default:</b> 4<br><b>Tunable:</b> Any time                                                                                                                                                                                                                                                                                                                                                    |
|                   | Probe_timeout          | The time-out value in seconds for the probes.<br><b>Default:</b> 180<br><b>Tunable:</b> Any time                                                                                                                                                                                                                                                                                                                                                                                           |

**TABLE 1-4** Sun Cluster HA for BroadVision One-To-One Enterprise Extension Properties  
(Continued)

| Property Category | Property Name     | Description                                                                                                                                                                                                                                                                                                                                                                                                       |
|-------------------|-------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Daemons           | START_ORB_SERVERS | Type Boolean. By default, the data service starts the <code>orbix</code> daemon and all of the BroadVision daemons in the resource. The <code>orbix</code> daemon starts the <code>orbix</code> servers whenever needed. If you want the data service to start the <code>orbix</code> servers, set this property to <code>TRUE</code> .<br><br><b>Default:</b> <code>FALSE</code><br><br><b>Tunable:</b> Any time |

## ▼ How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise

Use this procedure to register and configure Sun Cluster HA for BroadVision One-To-One Enterprise.

---

**Note** – Before you start Sun Cluster HA for BroadVision One-To-One Enterprise, check that your database is accessible.

---

1. Shut down all of the BroadVision One-To-One Enterprise servers, including the root host, back-end, and Interaction Manager servers.

---

**Note** – Perform this step after you test the BroadVision One-To-One Enterprise installation.

---

2. Run the `ps(1)` command to check that all of the BroadVision One-To-One Enterprise processes and the `orbix` daemon (`orbixd`) are stopped on all of the cluster nodes.
3. Become superuser on one cluster node.



4. Run the `scrgadm` command to register the resource type for Sun Cluster HA for BroadVision One-To-One Enterprise.

```
scrgadm -a -t SUNW.bv
```

- a Adds the resource type for the data service.
- t SUNW.bv Specifies the resource type name that is predefined for your data service.

5. Run the `scrgadm` command to create the root host, back-end, and Interaction Manager resources.

- a. Create root host and back-end resources in the failover resource groups that you created in Step 2 of “How to Configure and Verify the BroadVision One-To-One Enterprise Software, Database, and HTTP Server Installation” on page 22.

---

**Note** – The `bvuser` and `BV1TO1_VAR` should be the same for all of the resources.

---

```
scrgadm -a -j root-host-resource -g root-host-resource-group -t SUNW.bv -x BVUSER=bvuser
-x BV1TO1_VAR=path-to-bv1to1_var-directory
scrgadm -a -j back-end-resource-1 -g back-end-resource-group-1 -t SUNW.bv -x BVUSER=bvuser
-x BV1TO1_VAR=path-to-bv1to1_var-directory
scrgadm -a -j back-end-resource-2 -g back-end-resource-group-2 -t SUNW.bv -x BVUSER=bvuser
-x BV1TO1_VAR=path-to-bv1to1_var-directory
...
scrgadm -a -j back-end-resource-n -g back-end-resource-group-n -t SUNW.bv -x BVUSER=bvuser
-x BV1TO1_VAR=path-to-bv1to1_var-directory
```

- j `root-host-resource`  
Specifies the name of the root host resource.
- x `BVUSER=bvuser`  
Specifies your BroadVision username.
- x `BV1TO1_VAR=path-to-bv1to1_var-directory`  
Specifies the path to the `$BV1TO1_VAR` directory.
- j `back-end-resource-n`  
Specifies the name of the back-end resource.

- b. Create the Interaction Manager resource in the scalable resource group.

---

**Note** – The `bvuser` and `BV1TO1_VAR` should be the same for all of the resources.

---

```
scrgadm -a -j im-resource -g im-resource-group -t SUNW.bv -x BVUSER=bvuser /
-x BV1TO1_VAR=path-to-bv1to1_var-directory
```

- j `im-resource` Specifies the name of the Interaction Manager resource.

6. Run the `scswitch` command to enable and bring online the resource groups that now include the BroadVision One-To-One Enterprise resources.

```
scswitch -z -g root-host-resource-group
scswitch -z -g back-end-resource-group-1
scswitch -z -g back-end-resource-group-2
...
scswitch -z -g back-end-resource-group-n
scswitch -z -g im-resource-group
```

## ▼ How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation and Configuration

Use this procedure to verify that you installed and configured Sun Cluster HA for BroadVision One-To-One Enterprise correctly.

1. From a web browser, log in to an application that you have configured with the BroadVision One-To-One Enterprise software.
2. Log in to the node that hosts the root host resource group.
3. Become the BroadVision user.
4. Shut down the root host processes.
  - a. Set the `BV_LOCAL_HOST` environment variable as `root-host-logical-hostname`.
  - b. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.
  - c. Run the following BroadVision command.

```
bvconf shutdown -local
```

---

**Note** – The Sun Cluster HA for BroadVision One-To-One Enterprise fault monitors will restart the root host.

---

5. Ensure that your web browser connection to BroadVision One-To-One Enterprise is still active.
6. Run the `scswitch` command to switch the root host resource group to another cluster node, such as `node2`.

```
scswitch -z -g root-host-resource-group -h node2
```

7. Ensure that your web browser connection to BroadVision One-To-One Enterprise is still active.
8. Repeat Step 2 through Step 7 for each back-end resource group.

## Where to Go From Here

You have completed your Sun Cluster HA for BroadVision One-To-One Enterprise installation and configuration. See the following sections for supplemental information.

- “Examples – Installing, Configuring, and Administering Sun Cluster HA for BroadVision One-To-One Enterprise” on page 36
- “Sun Cluster HA for BroadVision One-To-One Enterprise Extension Properties” on page 29
- “Understanding Sun Cluster HA for BroadVision One-To-One Enterprise Fault Monitor” on page 47
- “Understanding BroadVision One-To-One Enterprise Functionality” on page 48

## ▼ How to Connect the Command Center to BroadVision One-To-One Enterprise Servers

Use this procedure to connect the Command Center to BroadVision One-To-One Enterprise servers that are configured on a cluster. This procedure provides you two options to connect the Command Center to BroadVision One-To-One Enterprise servers.

1. **Which option do you prefer?**
  - Force the Dynamic Control Center (DCC) to use POOP instead of IIOP  
If yes, proceed to Step 2
  - Set the `IT_LOCAL_ADDR_LIST` property to include the IP addresses of all of the cluster nodes and logical hostnames  
If no, skip to Step 3
2. **Force the Dynamic Control Center (DCC) to use POOP instead of IIOP. To do so, set the value of the `My Computer/HKEY_CURRENT_USER/Software/BroadVision/Dynamic Control Center/4.2/Options/Use IIOP` Windows registry entry to 0.**
3. **Set the `IT_LOCAL_ADDR_LIST` property to include the IP addresses of all of the cluster nodes and logical hostnames that will run the `orbix` daemon.**

## Example - Connecting Command Center to Sun Cluster HA for BroadVision One-To-One Enterprise

This example uses the following sample IP addresses to add to the `bv1to1.conf` file.

```
root host 10.10.102.225
back-end host 10.10.102.226
Interaction Manager host 10.10.102.222
Interaction Manager host 10.10.102.223
```

Based on these sample IP addresses, add the following line to the `bv1to1.conf` file, under the global `export` section, before the `IT_DAEMON_PORT` property.

```
IT_LOCAL_ADDR_LIST = "127.0.0.1"
 + "10.10.102.222"
 + "10.10.102.223"
 + "10.10.102.225"
 + "10.10.102.226"
 ;
```

---

**Note** – DCC cannot recover from a failover. Contact BroadVision One-To-One Enterprise support for more information.

---

---

## Examples – Installing, Configuring, and Administering Sun Cluster HA for BroadVision One-To-One Enterprise

“Example One – Installation and Configuration” on page 37 and “Example Two – Administration Commands” on page 38 show how to install, configure, and administer Sun Cluster HA for BroadVision One-To-One Enterprise. The following tables list cluster information and BroadVision One-To-One Enterprise configuration information. This information applies to both of the examples.

**TABLE 1-5** Examples – Cluster Information

---

|                   |                              |
|-------------------|------------------------------|
| Node names        | phys-schost-1, phys-schost-2 |
| Logical hostnames | schost-1, schost-2           |

---

**TABLE 1-5** Examples – Cluster Information (Continued)

|                 |                                                                                                                                                                              |
|-----------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Resource groups | root-host-resource-group (for root host resources),<br>back-end-resource-group (for back-end resources),<br>im-resource-group (for Interaction Manager resources)            |
| Resources       | root-host-resource (the BroadVision root host resource),<br>back-end-resource (the BroadVision back-end resource),<br>im-resource (BroadVision Interaction Manager resource) |

**TABLE 1-6** Examples – BroadVision Configuration Information

|                       |                                       |
|-----------------------|---------------------------------------|
| BV User               | BVUSER (on all of the cluster nodes)  |
| BV1TO1_VAR directory  | /global/broadvision/bvuser/bv1to1_var |
| Root host             | schost-1                              |
| Back-end host         | schost-2                              |
| Interaction Manager 1 | phys-schost-1                         |
| Interaction Manager 2 | phys-schost-2                         |

## Example One – Installation and Configuration

This example illustrates how to install and configure the data service.

(Register the BroadVision resource type.)

```
phys-schost-1:> scrgadm -a -t SUNW.bv
```

(Create failover resource groups for the back-end and root host processes.)

```
phys-schost-1:> scrgadm -a -g root-host-resource-group
```

```
phys-schost-1:> scrgadm -a -g back-end-resource-group
```

(Create a scalable resource group for the Interaction Manager processes.)

```
phys-schost-1:> scrgadm -a -g im-resource-group -y Maximum primaries=2 /
-y Desired primaries=2
```

(Add logical hostnames to the failover resource groups.)

```
phys-schost-1:> scrgadm -a -L -g root-host-resource-group -l schost-1
```

```
phys-schost-1:> scrgadm -a -L -g back-end-resource-group -l schost-2
```

(Create root host, back-end, and Interaction Manager resources.)

```
phys-schost-1:> scrgadm -a -j root-host-resource -g root-host-resource-group /
```

```
-t SUNW.bv -x BVUSER=bvuser -x BV1TO1_VAR=/global/broadvision/bvuser/bt1to1_var
```

```
phys-schost-1:> scrgadm -a -j back-end-resource -g back-end-resource-group /
```

```
-t SUNW.bv -x BVUSER=bvuser -x BV1TO1_VAR=/global/broadvision/bvuser/bt1to1_var
```

```
phys-schost-1:> scrgadm -a -j im-resource -g im-resource-group -t SUNW.bv /
```

```
-x BVUSER=bvuser -x BV1TO1_VAR=/global/broadvision/bvuser/bt1to1_var
```

(Bring all of the resource groups online.)

```
phys-schost-1:> scswitch -Z -g root-host-resource-group
```

```
phys-schost-1:> scswitch -Z -g back-end-resource-group
phys-schost-1:> scswitch -Z -g im-resource-group
```

## Example Two – Administration Commands

This example lists some common administration commands that you might wish to run.

*(Check the status of the resource groups.)*

```
phys-schost-1:> scstat -g
```

*(Note: All of the BroadVision Interaction Manager 1, root host, and back-end processes should run on phys-schost-1. Interaction Manager 2 processes must run on phys-schost-2.)*

*(Test failover. Switch the root-host-resource-group and the back-end-resource-group to another node.)*

```
phys-schost-1:> scswitch -z -g root-host-resource-group -h phys-schost-2
phys-schost-1:> scswitch -z -g back-end-resource-group -h phys-schost-2
```

*(Note: All of the BroadVision root host and back-end processes should now run on phys-schost-2.)*

*(Because the Maximum and Desired primaries are set to 2, the Interaction Manager runs on the two cluster nodes. Shut down Interaction Manager 2, which runs on phys-schost-2.)*

```
phys-schost-1:> scswitch -z -g im-resource-group -h phys-schost-1
```

*(Shut down all of the resource groups.)*

```
phys-schost-1:> scswitch -F -g root-host-resource-group
phys-schost-1:> scswitch -F -g back-end-resource-group
phys-schost-1:> scswitch -F -g im-resource-group
```

*(Remove and disable all of the BroadVision resources and resource groups.)*

```
phys-schost-1:> scswitch -n -j root-host-resource
phys-schost-1:> scswitch -n -j back-end-resource
phys-schost-1:> scswitch -n -j im-resource
phys-schost-1:> scswitch -n -j schost-1
phys-schost-1:> scswitch -n -j schost-2
phys-schost-1:> scrgadm -r -j root-host-resource
phys-schost-1:> scrgadm -r -j back-end-resource
phys-schost-1:> scrgadm -r -j im-resource
phys-schost-1:> scrgadm -r -j schost-1
phys-schost-1:> scrgadm -r -j schost-2
phys-schost-1:> scrgadm -r -j root-host-resource-group
phys-schost-1:> scrgadm -r -j back-end-resource-group
phys-schost-1:> scrgadm -r -j im-resource-group
```

*(Remove the resource type.)*

```
phys-schost-1:> scrgadm -r -t SUNW.bv
```

---

## Alternative Configuration

Depending on the flexibility and granularity of administration that you require for each back-end resource, you can set up only one failover resource group to use *n* logical hostnames and to contain all of the back-end and root host resources.

---

**Note** – See “Alternative Configuration: Cluster With One Resource Group for the BroadVision One-To-One Enterprise Back-End and Root Host Servers” on page 17 for an illustration of this alternative configuration.

---

To set up this alternative configuration, perform the following procedures.

- “Alternative Configuration: How to Configure and Verify the BroadVision One-To-One Enterprise, Database, and HTTP Server Installation” on page 39
- “Alternative Configuration: How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages” on page 43
- “Alternative Configuration: How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise” on page 44
- “Alternative Configuration: How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation” on page 46

---

**Note** – With these procedures, you set up two resource groups. One failover resource group contains root host and back-end resources. One scalable resource group contains the Interaction Manager resource. Throughout the alternative configuration procedures, the failover resource group that contains root host and back-end resources is denoted as *failover-resource-group*.

---

### ▼ Alternative Configuration: How to Configure and Verify the BroadVision One-To-One Enterprise, Database, and HTTP Server Installation

Perform this procedure to test starting and stopping the back-end processes on all of the nodes on which the back-end host and root host can run in a failover configuration. Additionally, perform this procedure to test the BroadVision One-To-One Enterprise Interaction Managers that you configured in the cluster.

1. **Create a failover resource group to contain the BroadVision One-To-One Enterprise back-end and root host resources.**

```
scrgadm -a -g failover-resource-group [-h nodelist]
 -g failover-resource-group Specifies the name of the resource group that contains the
 back-end and root host logical hostnames and resources.
 The name of the failover resource group can be your
 choice but must be unique for resource groups within the
 cluster.
 [-h nodelist] Specifies an optional, comma-separated list of physical
 node names or IDs that identify potential masters. The
 order here determines the order in which the Resource
 Group Manager (RGM) considers primary nodes during
 failover.
```

## 2. Verify that you have added all of the logical hostnames that you use to your name service database.

Additionally, add all of the logical hostnames that you use to the `/etc/inet/hosts` file on each cluster node. Therefore, if the name service goes down, the nodes can still find the name-to-address mapping on their local hosts file.

## 3. Run the `scrgadm(1M)` command to add the logical hostnames that the failover resource group will use.

```
scrgadm -a -L -g failover-resource-group -l root-host-logical-hostname-1 [-n netiflist]
scrgadm -a -L -g failover-resource-group -l back-end-logical-hostname-1 [-n netiflist]
scrgadm -a -L -g failover-resource-group -l back-end-logical-hostname-2 [-n netiflist]
...
scrgadm -a -L -g failover-resource-group -l back-end-logical-hostname-n [-n netiflist]
 -l root-host-logical-hostname Specifies the logical hostname that the root host
 resource uses.
 -l back-end-logical-hostname-n Specifies the logical hostname that each back-end
 resource uses.
 [-n netiflist] Specifies an optional, comma-separated list that
 identifies the IP Networking Multipathing groups
 that are on each node. The netiflist must represent all
 of the nodes in the resource group's nodelist. If you
 do not specify this option, the scrgadm command
 attempts to discover a network adapter on the
 subnet that the hostname list identifies for each
 nodelist node.
```

## 4. Create a scalable resource group for the Interaction Managers.

```
scrgadm -a -g im-resource-group -y Maximum primaries=n -y Desired primaries=n
 -g im-resource-group Specifies the name of the scalable resource group
 that contains the Interaction Managers. This name
 can be your choice but must be unique for resource
 groups within the cluster.
```



- y Maximum primaries=*m* Specifies the maximum number of active primary nodes allowed for this resource group. If you do not assign a value to this property, the default is 1.
- y Desired primaries=*n* Specifies the desired number of active primary nodes allowed for this resource group. If you do not assign a value to this property, the default is 1.

**5. From one cluster node, run the `scswitch(1M)` command to move the failover resource group into the managed state and bring it online.**

```
scswitch -Z -g failover-resource-group
```

---

**Note** – You do not need to bring the scalable resource group online because the scalable resource group does not yet contain resources. You must bring the failover resource group online because the BroadVision One-To-One Enterprise back-end processes cannot start if the logical hostname resource is unavailable.

---

**6. Check that the database is accessible.**

See your database documentation for details.

**7. Ensure that you have configured the database to enable BroadVision One-To-One Enterprise back-end servers to access the database from any cluster node.**

See your database documentation for details.

**8. As the BroadVision user, log in to the cluster node that hosts the failover resource group.**

**9. Follow the steps in the *BroadVision One-To-One Enterprise Installation and Administration Guide* to run the following BroadVision commands.**

- a. Set the `BV_LOCAL_HOST` environment variable as *root-host-logical-hostname*.
- b. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.
- c. Run the `bvconf bootstrap` command on the root host to initialize the BroadVision One-To-One Enterprise installation.

---

**Note** – Do not run the `bvconf` command as superuser.

---

```
% bvconf bootstrap -r root-host-logical-hostname
```

- d. Set the `BV_LOCAL_HOST` environment variable as *back-end-logical-hostname* or *in-hostname*.

- e. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.
- f. For each back-end host and Interaction Manager host, run the `bvconf execute` command to configure and start the BroadVision One-To-One Enterprise installation.

```
% bvconf execute -local -var shared -r root-host-logical-hostname
```

**10. Run the BroadVision command `bvconf gateway` to generate gateway configuration files for the HTTP gateway applications.**

This command generates the files and writes them to the `$BV1TO1_VAR/etc/appName.cfg` file.

```
% bvconf gateway -A appName
```

`-A appName` Specifies the gateway application name, which is defined in the `$BV1TO1_VAR/etc/bv1to1.conf` configuration file. See the *BroadVision One-To-One Enterprise Installation and Administration Guide* for details.

**11. Copy the gateway application configuration file to the `/etc/opt/BVSNsmgr` directory on each of the cluster nodes that runs HTTP instances.**

---

**Note** – Ensure that you copy the gateway application configuration file with the extension `.cfg`.

---

See the *BroadVision One-To-One Enterprise Installation and Administration Guide* for details.

**12. Configure and start the HTTP servers.**

See your HTTP server documentation for details. Additionally, see the *BroadVision One-To-One Enterprise Installation and Administration Guide* for information on HTTP server configuration.

**13. From a BroadVision client, connect to the BroadVision site, and check the installation.**

**14. If the BroadVision One-To-One Enterprise software is functioning correctly, perform the following steps to shut down the Interaction Managers, back-end processes, and root host processes.**

**a. Shut down the Interaction Managers.**

- i. Set the `BV_LOCAL_HOST` environment variable as `im-hostname`.
- ii. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.

iii. Run the following command.

```
bvconf shutdown -local
```

b. Shut down the back-end processes.

i. Set the `BV_LOCAL_HOST` environment variable as *back-end-logical-hostname-n*.

ii. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.

iii. Run the following command.

```
bvconf shutdown -local
```

c. Shut down the root host processes.

i. Set the `BV_LOCAL_HOST` environment variable as *root-host-logical-hostname*.

ii. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.

iii. Run the following command.

```
bvconf shutdown -local
```

15. Run the `scswitch` command to switch the failover resource group to another cluster node, such as *node2*.

```
scswitch -z -g failover-resource-group -h node2
```

16. Restart the BroadVision One-To-One Enterprise software.

17. Connect to the cluster from a BroadVision client, and check that the BroadVision One-To-One Enterprise software functions correctly.

18. Repeat Step 15 through Step 18 on all of the potential primaries of the BroadVision One-To-One Enterprise resource groups.

## ▼ Alternative Configuration: How to Install Sun Cluster HA for BroadVision One-To-One Enterprise Packages

Use this procedure to install the Sun Cluster HA for BroadVision One-To-One Enterprise packages. You need the Sun Cluster Agents CD-ROM to perform this procedure. This procedure assumes that you did not install the data service packages during your initial Sun Cluster installation. If you installed the Sun Cluster HA for

BroadVision One-To-One Enterprise packages as part of your initial Sun Cluster installation, proceed to “Alternative Configuration: How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise” on page 44 to install and configure Sun Cluster HA for BroadVision One-To-One Enterprise. Otherwise, use this procedure to install the Sun Cluster HA for BroadVision One-To-One Enterprise packages. Perform this procedure on all nodes that can run Sun Cluster HA for BroadVision One-To-One Enterprise.

1. **Load the Sun Cluster Agents CD-ROM into the CD-ROM drive.**
2. **Run the `scinstall` utility with no options.**  
This step starts the `scinstall` utility in interactive mode.
3. **Choose the menu option, Add Support for New Data Service to This Cluster Node.**  
The `scinstall` utility prompts you for additional information.
4. **Provide the path to the Sun Cluster Agents CD-ROM.**  
The utility refers to the CD as the “data services cd.”
5. **Specify the data service to install.**  
The `scinstall` utility lists the data service that you selected and asks you to confirm your choice.
6. **Exit the `scinstall` utility.**
7. **Unload the CD from the drive.**

## ▼ Alternative Configuration: How to Register and Configure Sun Cluster HA for BroadVision One-To-One Enterprise

To register and configure Sun Cluster HA for BroadVision One-To-One Enterprise, perform the following steps.

---

**Note** – Before you start Sun Cluster HA for BroadVision One-To-One Enterprise, check that your database is accessible.

---

1. **Shut down all of the BroadVision One-To-One Enterprise servers, including the root host, back-end, and Interaction Manager servers.**

---

**Note** – Perform this step after you test the BroadVision One-To-One Enterprise installation.

---

2. Run the `ps(1)` command to check that all of the BroadVision One-To-One Enterprise processes and the `orbix` daemon (`orbixd`) are stopped on all of the cluster nodes.
3. Become superuser on one cluster node.
4. Run the `scrgadm` command to register the resource type for Sun Cluster HA for BroadVision One-To-One Enterprise.

```
scrgadm -a -t SUNW.bv
```

-a Adds the resource type for the data service.

-t `SUNW.bv` Specifies the resource-type name that is predefined for your data service.

5. Run the `scrgadm` command to create the root host, back-end, and Interaction Manager resources.

- a. Set the `Network_resources_used` property for each resource to point to the proper logical hostname.

If you created two or more back-end resources in one resource group, and you do not set the `Network_resources_used` property, the validate method will fail.

```
scrgadm -a -j root-host-resource -g failover-resource-group -t SUNW.bv
-y Network_resources_used=root-host-logical-hostname -x BVUSER=bvuser
-x BV1TO1_VAR=path-to-bv1to1_var-directory
scrgadm -a -j back-end-resource-1 -g failover-resource-group -t SUNW.bv
-y Network_resources_used=back-end-logical-hostname-1 -x BVUSER=bvuser
-x BV1TO1_VAR=path-to-bv1to1_var-directory
...
scrgadm -a -j back-end-resource-n -g failover-resource-group -t SUNW.bv
-y Network_resources_used=back-end-logical-hostname-n -x BVUSER=bvuser
-x BV1TO1_VAR=path-to-bv1to1_var-directory
```

- j `root-host-resource`  
Specifies the name of the root host resource.
- x `BVUSER=bvuser`  
Specifies your BroadVision username.
- x `BV1TO1_VAR=path-to-bv1to1_var-directory`  
Specifies the path to the `$BV1TO1_VAR` directory.
- j `back-end-resource-n`  
Specifies the name of the back-end resource.

---

**Note** – You should have created all of the logical hostnames that were defined in the `Network_resource_used` property in the failover resource group (see Step 3 of the procedure, “Alternative Configuration: How to Configure and Verify the BroadVision One-To-One Enterprise, Database, and HTTP Server Installation” on page 39).

---

- b. Create the Interaction Manager resource in the scalable resource group that you created in Step 4 of the procedure, “Alternative Configuration: How to Configure and Verify the BroadVision One-To-One Enterprise, Database, and HTTP Server Installation” on page 39.

```
scrgadm -a -j im-resource -g im-resource-group -t SUNW.bv
```

```
-x BVUSER=bvuser -x BV1TO1_VAR=path-to-bv1to1_var-directory
```

```
-j im-resource Specifies the name of the Interaction Manager resource.
```

6. Run the `scswitch` command to enable the resource group that now includes the BroadVision One-To-One Enterprise back-end and root host resources.

```
scswitch -Z -g failover-resource-group
```

```
scswitch -Z -g im-resource-group
```

## ▼ Alternative Configuration: How to Verify the Sun Cluster HA for BroadVision One-To-One Enterprise Installation

Perform the following steps to verify the Sun Cluster HA for BroadVision One-To-One Enterprise installation.

1. From a web browser, log in to an application that you have configured with the BroadVision One-To-One Enterprise software.
2. Log in to the node that hosts the failover resource group.
3. Become the BroadVision user.
4. Shut down the root host processes.
  - a. Set the `BV_LOCAL_HOST` environment variable as `root-host-logical-hostname`.
  - b. Source the `bv1to1.conf.sh` file or the `bv1to1.conf.csh` file, depending on the shell that you use.
  - c. Run the following BroadVision command.

```
bvconf shutdown -local
```

---

**Note** – The Sun Cluster HA for BroadVision One-To-One Enterprise fault monitors will restart the root host.

---

5. Ensure that your web browser connection to BroadVision One-To-One Enterprise is still active.
6. Run the `scswitch` command to switch the failover resource group to another cluster node, such as `node2`.  

```
scswitch -z -g failover-resource-group -h node2
```
7. Ensure that your web browser connection to BroadVision One-To-One Enterprise is still active.

---

## Understanding Sun Cluster HA for BroadVision One-To-One Enterprise Fault Monitor

The Sun Cluster HA for BroadVision One-To-One Enterprise fault monitor checks BroadVision One-To-One Enterprise back-end and Interaction Manager process health. BroadVision One-To-One Enterprise process health impacts BroadVision One-To-One Enterprise resources' failure history, which in turn drives the fault monitor's actions. For each BroadVision One-To-One Enterprise resource, fault monitor actions include no action, restart, or failover.

### Interaction Manager Fault Monitoring

For Interaction Manager resources, failover happens only when both of the following conditions are met.

- The value of the desired primaries is less than the value of the maximum primaries.
- One of the nodes is unavailable.

After failover, the fault monitor will not restart the resource on any cluster node if both of the following conditions occur.

- The values of the maximum primaries and desired primaries of the Interaction Manager resource group are the same.
- The fault monitor has completed restarting the Interaction Manager resource the number of times that the `Retry_count` property specifies.

## Sun Cluster HA for BroadVision One-To-One Enterprise Fault Probes

The fault monitors for each BroadVision One-To-One Enterprise resource (root host, back-end host, and Interaction Manager host) monitor the following processes.

- **The `orbix` daemon (`orbixd`), which is common for all of the BroadVision One-To-One Enterprise resources** – The probes use the `ps(1)` command to ensure that `orbixd` is functioning. If `orbixd` is not functioning, the probe considers the failure as complete, and the Resource Group Manager (RGM) restarts the `orbix` daemon.

The `orbix` daemon is started with the checkpoint feature. Therefore, the BroadVision One-To-One Enterprise servers, which the previous instance of `orbixd` started, continue to run with the new instance of `orbixd`.

- **The BroadVision One-To-One Enterprise daemons that you have configured in the resource** – If `orbixd` is healthy, the probe uses the BroadVision command `bvconf ps` to ensure that the BroadVision One-To-One Enterprise daemons are functioning. If BroadVision One-To-One Enterprise daemons are not functioning, the RGM restarts the resource, which restarts all of the configured daemons.

---

## Understanding BroadVision One-To-One Enterprise Functionality

This section contains information on expected behavior with Sun Cluster HA for BroadVision One-To-One Enterprise.

- **The One-To-One database fails and the back-end hosts fail over** – If the database fails and the back-end hosts fail over before the database comes back online, the BroadVision One-To-One Enterprise resources cannot come online on any cluster node. When you successfully restart the database, start the BroadVision One-To-One Enterprise resources again.



- **The hosts in the startup order are offline** – BroadVision One-To-One Enterprise resources must be started in a particular order. The BroadVision command `bvconf bootstrap` lists this order. If both of the following conditions occur, the BroadVision One-To-One Enterprise processes that are configured on the hostname in the resource group will not start.
  - Any of the resources in the startup order are offline.
  - You start a BroadVision One-To-One Enterprise resource that is listed after the offline resources in the startup order.

If both of these conditions occur, the resource group will come online, but the processes will not start. The probe will wait for the resource group in the startup order to come online before the probe starts the BroadVision One-To-One Enterprise processes for this resource.

- **The BroadVision and Oracle resource groups fail over at the same time** – If you use Oracle, and the BroadVision One-To-One Enterprise backend resource groups and the Oracle resource group fail over at the same time, some BroadVision daemons might fail to restart. These daemons will fail to restart while the Oracle database is restarting. The BroadVision One-To-One Enterprise resource will attempt to restart the failed daemons until it succeeds.



# Index

---

## A

adding

*See* modifying

alternative configuration, Sun Cluster HA for  
BroadVision One-To-One Enterprise, 39

## B

BroadVision One-To-One Enterprise

configuring, 22

installation

for DBMS, 20

installing BroadVision One-To-One  
software, 21

installing HTTP server, 20

preparing the nodes, 19

preventing a server-port conflict, 19

verifying, 22

configuration

Sun Cluster HA for BroadVision One-To-One  
Enterprise, 15

alternative, 39

alternative configuration, 17

DBMS and HTTP server configuration, 16

multiple resource groups, 16

configuring

BroadVision One-To-One Enterprise, 22

Sun Cluster HA for BroadVision One-To-One  
Enterprise, 32

## C

changing

*See* modifying

command center, Sun Cluster HA for Sun  
Cluster HA for BroadVision One-To-One  
Enterprise, 35

commands

prtconf -v, 9

prtdiag -v, 9

psrinfo -v, 9

showrev -p, 9

## D

- deleting
  - See* modifying
- disabling
  - See* stopping
- displaying
  - See* listing

## E

- editing
  - See* modifying
- enabling
  - See* starting
- executing
  - See* starting
- extension properties
  - Sun Cluster HA for BroadVision One-To-One Enterprise
    - BV1TO1\_VAR, 32
    - BVUSER, 32
    - Monitor\_retry\_count, 32
    - Monitor\_retry\_interval, 32
    - Probe\_timeout, 32
    - START\_ORB\_SERVERS, 32

## F

- fault monitor, Sun Cluster HA for BroadVision One-To-One Enterprise, 47

## I

- installing
  - BroadVision One-To-One Enterprise, 20, 21, 22
  - Sun Cluster HA for BroadVision One-To-One Enterprise, 28

## O

- overview, Sun Cluster HA for BroadVision One-To-One Enterprise, 12

## P

- printing
  - See* listing
- prtconf -v command, 9
- psrinfo -v command, 9
- pv command, 9

## R

- registering, Sun Cluster HA for BroadVision One-To-One Enterprise, 32
- running
  - See* enabling

## S

- Sun Cluster HA for BroadVision One-To-One Enterprise
  - configuration
    - alternative, 39
    - alternative configuration, 17
    - considerations, 18
    - DBMS and HTTP server configuration, 16
    - multiple resource groups, 16
    - planning, 14
    - planning questions, 18
    - requirements, 15
    - standard, 15
  - expected behavior, 48
  - extension properties
    - BV1TO1\_VAR, 32
    - BVUSER, 32
    - Monitor\_retry\_count, 32
    - Monitor\_retry\_interval, 32
    - Probe\_timeout, 32
    - START\_ORB\_SERVERS, 32
  - fault monitor, 47
  - installation
    - connecting command center, 35
    - planning, 14
    - Sun Cluster HA for BroadVision One-To-One Enterprise packages, 28
    - verifying, 34
  - overview, 12
  - registering and configuring, 32
  - task map, 13

Sun Cluster HA for Sun Cluster for BroadVision  
One-To-One Enterprise  
configuration  
restrictions, 14

## **T**

task map, Sun Cluster HA for BroadVision  
One-To-One Enterprise, 13  
turning off  
*See* disabling  
turning on  
*See* enabling

## **U**

`/usr/cluster/bin/scinstall -pv`, 9

## **V**

verifying, Sun Cluster HA for Sun Cluster HA  
for BroadVision One-To-One Enterprise, 34

