



Sun StorEdge™ Network 2 Gb FC Switch-64 Release Notes

Sun Microsystems, Inc.
4150 Network Circle
Santa Clara, CA 95054 U.S.A.
650-960-1300

Part No. 817-0977-11
April 2003, Revision A

Submit comments about this document at: <http://www.sun.com/hwdocs/feedback>

Copyright 2003 Sun Microsystems, Inc., 4150 Network Circle, Santa Clara, California 95054, U.S.A. All rights reserved.

Sun Microsystems, Inc. has intellectual property rights relating to technology embodied in the product that is described in this document. In particular, and without limitation, these intellectual property rights may include one or more of the U.S. patents listed at <http://www.sun.com/patents> and one or more additional patents or pending patent applications in the U.S. and in other countries.

This document and the product to which it pertains are distributed under licenses restricting their use, copying, distribution, and decompilation. No part of the product or of this document may be reproduced in any form by any means without prior written authorization of Sun and its licensors, if any.

Third-party software, including font technology, is copyrighted and licensed from Sun suppliers.

Parts of the product may be derived from Berkeley BSD systems, licensed from the University of California. UNIX is a registered trademark in the U.S. and in other countries, exclusively licensed through X/Open Company, Ltd.

Sun, Sun Microsystems, the Sun logo, AnswerBook2, Sun StorEdge, docs.sun.com, and Solaris are trademarks or registered trademarks of Sun Microsystems, Inc. in the U.S. and in other countries.

All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. in the U.S. and in other countries. Products bearing SPARC trademarks are based upon an architecture developed by Sun Microsystems, Inc.

The OPEN LOOK and Sun™ Graphical User Interface was developed by Sun Microsystems, Inc. for its users and licensees. Sun acknowledges the pioneering efforts of Xerox in researching and developing the concept of visual or graphical user interfaces for the computer industry. Sun holds a non-exclusive license from Xerox to the Xerox Graphical User Interface, which license also covers Sun's licensees who implement OPEN LOOK GUIs and otherwise comply with Sun's written license agreements.

U.S. Government Rights—Commercial use. Government users are subject to the Sun Microsystems, Inc. standard license agreement and applicable provisions of the FAR and its supplements.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.

Copyright 2003 Sun Microsystems, Inc., 4150 Network Circle, Santa Clara, California 95054, Etats-Unis. Tous droits réservés.

Sun Microsystems, Inc. a les droits de propriété intellectuelle relatant à la technologie incorporée dans le produit qui est décrit dans ce document. En particulier, et sans la limitation, ces droits de propriété intellectuelle peuvent inclure un ou plus des brevets américains énumérés à <http://www.sun.com/patents> et un ou les brevets plus supplémentaires ou les applications de brevet en attente dans les Etats-Unis et dans les autres pays.

Ce produit ou document est protégé par un copyright et distribué avec des licences qui en restreignent l'utilisation, la copie, la distribution, et la décompilation. Aucune partie de ce produit ou document ne peut être reproduite sous aucune forme, par quelque moyen que ce soit, sans l'autorisation préalable et écrite de Sun et de ses bailleurs de licence, s'il y ena.

Le logiciel détenu par des tiers, et qui comprend la technologie relative aux polices de caractères, est protégé par un copyright et licencié par des fournisseurs de Sun.

Des parties de ce produit pourront être dérivées des systèmes Berkeley BSD licenciés par l'Université de Californie. UNIX est une marque déposée aux Etats-Unis et dans d'autres pays et licenciée exclusivement par X/Open Company, Ltd.

Sun, Sun Microsystems, le logo Sun, AnswerBook2, Sun StorEdge, docs.sun.com, et Solaris sont des marques de fabrique ou des marques déposées de Sun Microsystems, Inc. aux Etats-Unis et dans d'autres pays.

Toutes les marques SPARC sont utilisées sous licence et sont des marques de fabrique ou des marques déposées de SPARC International, Inc. aux Etats-Unis et dans d'autres pays. Les produits portant les marques SPARC sont basés sur une architecture développée par Sun Microsystems, Inc.]

L'interface d'utilisation graphique OPEN LOOK et Sun™ a été développée par Sun Microsystems, Inc. pour ses utilisateurs et licenciés. Sun reconnaît les efforts de pionniers de Xerox pour la recherche et le développement du concept des interfaces d'utilisation visuelle ou graphique pour l'industrie de l'informatique. Sun détient une licence non exclusive de Xerox sur l'interface d'utilisation graphique Xerox, cette licence couvrant également les licenciées de Sun qui mettent en place l'interface d'utilisation graphique OPEN LOOK et qui en outre se conforment aux licences écrites de Sun.

LA DOCUMENTATION EST FOURNIE "EN L'ÉTAT" ET TOUTES AUTRES CONDITIONS, DECLARATIONS ET GARANTIES EXPRESSES OU TACITES SONT FORMELLEMENT EXCLUES, DANS LA MESURE AUTORISEE PAR LA LOI APPLICABLE, Y COMPRIS NOTAMMENT TOUTE GARANTIE IMPLICITE RELATIVE A LA QUALITE MARCHANDE, A L'APTITUDE A UNE UTILISATION PARTICULIERE OU A L'ABSENCE DE CONTREFAÇON.



Contents

Quick Installation	2
Notes and New Features	3
Baseline Software Package	3
Performing a Hot Swap Using SANbox Manager on SB2-32/64	3
Switch Firmware Download	4
IOStreamGuard	4
Alarm Thresholds	4
Smart Zoning Activation	5
Remove 'Brocade Mode'	5
SNMP 4.0 FA MIB	5
Firmware Naming Convention	5
SNMP Trap Changes	6
SANSurfer Fabric View	6
Bugs	7
Service Contact Information	8

Sun StorEdge Network 2 Gb FC Switch-64 Release Notes

This document contains important information about the Sun StorEdge™ Network 2 Gb FC Switch-64 that was not available at the time the product documentation was published. Review this document so that you are aware of issues or requirements that can impact the installation and operation of the Sun StorEdge Network 2 Gb FC Switch-64.

Note – For detailed information about the Sun StorEdge Network 2 Gb FC Switch-64 and its installation and management, refer to the documents at:

http://www.sun.com/products-n-solutions/hardware/docs/Network_Storage_Solutions/SAN/index.html

and click **Other Documentation**.

Quick Installation

This is the first release of the Sun StorEdge Network 2 Gb FC Switch-64. The supported firmware for this switch is 1.5.0.7 (released in this package) or higher and the supported GUI is 1.05.14 (released with package SUNWsmgr2, VERSION=2.1, REV=2003.03.05.14.20) or later.

1. **Make sure you are logged in as root.**
 - If you are doing the install for the first time, go directly to Step 5.
 - If you currently have a version of SUNWsmgr2 on your system, proceed to Step 2.
2. **Check for any patches, related to the previous SUNWsmgr2 package by typing:**

```
# showrev -p | grep 112429
Patch: 112429-08 Obsoletes: Requires: Incompatibles: Packages:
SUNWsmgr2
```

3. **Remove any previous patch(es) with the patchrm command.**

The patch found in the above example should be removed by typing:

```
# patchrm 112429-08
```

4. **Remove the earlier SUNWsmgr2 package by typing:**

```
# pkgrm SUNWsmgr2
```

5. **Access the directory where the new SUNWsmgr2 package is to be installed.**

6. **Add the new package by typing:**

```
# pkgadd -d SUNWsmgr2_2.1.2003.03.05.14.20
```

7. **Start the SANbox Manager by typing:**

```
# /usr/opt/SUNWsmgr2/bin/SANbox_Manager
```

Note – All the Sun StorEdge Network 2G FC Switches (Switch-8, Switch-16, and Switch-64) share the same firmware (version 1.5.0.7 or later) with this release.

Notes and New Features

This section contains information about the following topics:

- “Baseline Software Package” on page 3
- “Performing a Hot Swap Using SANbox Manager on SB2-32/64” on page 3
- “Switch Firmware Download” on page 4
- “IOStreamGuard” on page 4
- “Alarm Thresholds” on page 4
- “Smart Zoning Activation” on page 5
- “Remove ‘Brocade Mode’” on page 5
- “SNMP 4.0 FA MIB” on page 5
- “Firmware Naming Convention” on page 5
- “SNMP Trap Changes” on page 6
- “SANSurfer Fabric View” on page 6

Baseline Software Package

The Sun StorEdge Network 2 Gb FC Switch-64 is released with the following software package installed:

SUNWsmgr2 VERSION=2.1, REV=2003.03.05.14.20

Performing a Hot Swap Using SANbox Manager on SB2-32/64

When performing a hot-swap procedure using the SANbox Manager it is strictly recommended that the user do so from a direct SANbox Manager session to the switch—through an Entry switch management session and not through an Inband switch management session. Trying to perform a hot-swap procedure through an Inband switch management session can result in unpredictable behavior.

Using a Telnet session for a hot swap procedure is also permissible.

Switch Firmware Download

When downloading firmware using the SANbox Manager, you should do so from a direct SANbox Manager session with the switch. This means you use an Entry Switch Management Session instead of an Inband Switch Management Session. The latter might result in a longer download time.

Using FTP to download and a Telnet session to activate the switch firmware image is also permissible.

IOStreamGuard

IOStreamGuard is disabled on the switch by default. Enabling IOStreamGuard on a port results in Register State Change Notifications (RSCNs) being blocked to the device connected to the port. If this device is a host, the host cannot determine when a new target joins or leaves the fabric. Therefore, enabling IOStreamGuard is not recommended for host ports for normal configurations.

Alarm Thresholds

The Alarm Threshold Configuration screen allows for monitoring the switch ports for certain counters, such as logins. If a switch port increments these counters too rapidly, the threshold monitoring sends the port offline.

Note – Once placed offline, the port will *not* return to online status until you take action to return it.

Configure the threshold monitoring set point values to send a port offline as desired. For more information, refer to “Managing Alarms” in the *SANbox2-64 Switch Management User’s Manual*, 875-3409.

Each counter threshold can be enabled and disabled with the `set config threshold` command. The counter thresholds include:

- CRC errors
- Decode errors
- ISL bounces
- Logins (to the fabric)
- Logouts (from the fabric)
- Loss of synchronization

If the Enable All Alarm Thresholds feature is enabled for decode errors and the decode error threshold is exceeded three times, the sample window (the default sample window of 10 seconds changes to 30 seconds), the user port is disabled and an alarm is generated. To recover the disabled port, perform one of the following:

- Set the port state online
- Reset the port
- Reset the Sun StorEdge Network 2 Gb FC Switch-64

Refer “Managing Alarms” in the *SANbox2-64 Switch Management User’s Manual*, 875-3409 for more information on Configuring Alarms.

Smart Zoning Activation

Activation of a zoneset causes RSCNs to be generated only in the affected zone(s).

Remove ‘Brocade Mode’

Only active zone sets are propagated per the FC-SW2 specification.

SNMP 4.0 FA MIB

Support for the SNMP 4.0 FA MIB has been added.

Firmware Naming Convention

An extra digit was added to firmware version 1.5.0.7 with the Sun StorEdge Network 2 Gb FC Switch-64.

SNMP Trap Changes

The connUnitEventTrap is replaced with the following:

- connUnitStatusChange
- connUnitDeletedTrap
- connUnitSensorStatusChange
- connUnitPortStatusChange

SANsurfer Fabric View

I/O traffic errors can now be monitored in real time on a per-port basis.

- Set graph-polling interval—the user can set the update rate for how often to poll.
- Can graph bytes or frames.

For more information, refer to *SANbox2-64 Switch Management User's Manual*, 875-3409.

Bugs

Bugs appear late in the test cycle when there is not enough time to correct them for the current release.

- **Bug 4819523:** When you click the Cancel button in the HotSwap wizard in the 64-port switch SANbox Manager, the switch can hang.

Workaround:

- Do not terminate the hot swap once it is started.
- If necessary, power-cycle the switch to recover.
- **Bug 4819531:** On performing a “HotSwap - insert Blade,” if the blade is not fully installed, error messages result. The generated error message does not indicate the problem.

Workaround: Make sure that the blade is installed correctly before performing “blade insert.”

- **Bug 4821346:** Using the Storage Automated Diagnostic Environment with a large fabric, you see that some of the switches return an error message similar to the following:

```
ERR: Skipping ip sseqa-31.ebay.sun.com because type(Couldn't
detect a device at IP: 10.4.51.83), class(ERR) or wwn() is blank
```

Workaround: Manually add the switch by using the Storage Automated Diagnostic Environment feature under Admin → General Maintenance → Add Devices.

- **Bug 4822128:** The I/O stream might fail during fault injection, and the host can lose its link to some of the devices.

Workaround: Reset the port that has the apparently missing devices.

- **Bug 4825899:** The switch Nameserver loses login to a TL_Port. This occurs while doing an error injection on the HBA side. The devices goes offline and using SANbox Manager shows that the switch TL_Port is online. There is no entry shown in Nameserver in the SANbox Manager for the switch TL_Port.

Workaround: Reset the port or the switch to recover.

- **Bug 4832041:** If a port is taken offline and then returned to online using the API, sometimes it might not come back online.

Workaround: Bring the port back online using the SANbox Manager, or reset the port.

Service Contact Information

If you need help installing or using this product within the U.S., call 1-800-USA-4SUN, or go to:

<http://www.sun.com/service/contacting/index.html>