

**Oracle®Communications
Policy Management**

Troubleshooting Reference

Release 11.1

E53442 Revision 01

May 2014

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, the following notice is applicable:

U.S. GOVERNMENT RIGHTS Programs, software, databases, and related documentation and technical data delivered to U.S. Government customers are "commercial computer software" or "commercial technical data" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, duplication, disclosure, modification, and adaptation shall be subject to the restrictions and license terms set forth in the applicable Government contract, and, to the extent applicable by the terms of the Government contract, the additional rights set forth in FAR 52.227-19, Commercial Computer Software License (December 2007). Oracle America, Inc., 500 Oracle Parkway, Redwood City, CA 94065.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Xeon are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Opteron, the AMD logo, and the AMD Opteron logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information on content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services.

Table of Contents

Chapter 1: Introduction.....	31
About this Guide.....	32
How This Guide Is Organized.....	32
Scope and Audience.....	32
Documentation Admonishments.....	33
Customer Care Center.....	33
Emergency Response.....	36
Related Publications.....	36
Locate Product Documentation on the Customer Support Site.....	37
Chapter 2: Incidents, Notifications, and Logs Overview.....	38
About Incidents.....	39
About Notifications.....	39
About Logs.....	39
Trace Log.....	40
Syslog.....	40
The SMPP Log.....	40
The SMTP Log.....	40
Configuring Log Settings.....	40
Chapter 3: Trace Log Notifications.....	44
Expanded List.....	45
1 - Initialized the scheduled tasks Event Log.....	45
2 - OSSi collector establishing connection to <i>type</i>	45
3 - Error occurred during OSSi collector run: <i>type</i>	45
4 - Starting OSSi collector run.....	46
5 - OSSi collector run completed.....	46
6 - OSSi collector run aborted.....	46
7 - OSSi collector error reading configuration file: <i>file-name</i>	47
8 - OSSi collector established connection.....	47
9 - OSSi collector could not establish connection <i>host port</i>	47
10 - OSSi collector did not find CMTS nodes for <i>CMTS</i>	48
11 - OSSi collector did not find subscribers for CMTS <i>node</i>	48

12 - OSSI collector did not find configuration parameter: <i>parameter-name</i>	48
13 - Error validating <i>field</i>	49
14 - Data Collector started.....	49
21 - Starting Subnet SNMP Collector task.....	49
22 - SNMP timeout while collecting Subnet data from CMTS <i>name</i>	50
23 - SNMP error <i>type</i> while collecting Subnet data from CMTS <i>name</i>	50
24 - Skipping Subnet collection from CMTS <i>name</i> because the SNMP community string is empty.....	50
25 - Classifier not active for subscribers request ignored.....	51
26 - Classifier already active for exit subscriber IP.....	51
38 - Subnet SNMP Collector Task Status CMTSs.....	51
39 - Finishing Subnet SNMP Collector task.....	52
41 - Starting Service Class SNMP Collector task.....	52
42 - SNMP timeout while collecting Service Class data from CMTS <i>name</i>	52
43 - SNMP error <i>type</i> while collecting Service Class data from CMTS <i>name</i>	53
44 - Skipping Service Class collection from CMTS <i>name</i> because the SNMP community string is empty.....	53
50 - HTTP request success for <i>IP address</i>	53
58 - Service Class SNMP Collector Task Status.....	54
59 - Finishing Service Class SNMP Collector task.....	54
61 - Starting Subscriber SNMP Collector task.....	55
62 - SNMP timeout while collecting Subscriber data from CMTS <i>name</i>	55
63 - SNMP error <i>type</i> while collecting Subscriber data from CMTS <i>name</i>	55
64 - Invalid cable modem MAC address <i>MAC-address</i> retrieved from CMTS <i>name</i>	56
65 - Invalid cable modem IP address <i>ip-address</i> for MAC <i>MAC-address</i> retrieved from CMTS <i>name</i>	56
66 - Invalid CPE IP address <i>ip-address</i> behind cable modem <i>MAC-address</i> retrieved from CMTS <i>name</i>	56
68 - Skipping Subscriber collection from CMS <i>name</i> because the SNMP community string is empty.....	57
70 - SOAP request failure.....	57
78 - Subscriber SNMP Collector Task Status.....	57
79 - Finishing Subscriber SNMP Collector task.....	58
80 - SOAP request success for <i>IP address</i>	58
81 - Starting CMTS Distributor task.....	58
82 - Error while sending CMTS data to Policy Server: <i>name</i>	59
98 - CMTS Distributor Task Status Policy Server.....	59
99 - Finishing CMTS Distributor task.....	59
100 - Established policy server connection to <i>IP address</i>	60
101 - Starting Subscriber Distributor task.....	60

102 - Error while deleting Subscriber data from Policy Server: <i>name</i>	60
103 - Error while updating CMTS data on Policy Server: <i>name</i>	61
104 - Error while sending <i>Reconfigure</i> message to Policy Server: <i>name</i>	61
105 - Error while sending <i>Refresh Channels</i> message to Policy Server: <i>name</i>	61
106 - Error while sending <i>Refresh Accounts</i> message to Policy Server: <i>name</i>	62
107 - Error while sending Tier data to Policy Server: <i>name</i>	62
108 - Error while sending Channel data to Policy Server: <i>name</i>	62
118 - Subscriber Distributor Task Status.....	63
119 - Finishing Subscriber Distributor task.....	63
121 - Starting OSSI Distributor task.....	63
122 - Error occurred during OSSI distributor run: <i>type</i>	64
123 - OSSI distributor run aborted.....	64
124 - Error connection to Remote MA: <i>host-name</i>	64
125 - Error updating Accounts to remote MA: <i>host-name</i>	65
126 - Error updating CMTSs to remote MA: <i>host-name</i>	65
127 - Error updating Tiers to remote MA: <i>host-name</i>	66
128 - Error updating Entitlements to remote MA: <i>host-name</i>	66
139 - Finishing OSSI Distributor task.....	66
141 - Starting CMTS MA Collector task.....	67
142 - Error while collecting CMTS data from Management Agent: <i>name</i>	67
157 - CMTS MA Collector task status.....	67
158 - CMTS MA Collector Task Status.....	68
159 - Finishing CMTS MA Collector Task.....	68
161 - Starting PCMM Routing Distribution task.....	68
177 - PCMM Distribution Task Status.....	69
178 - PCMM Distribution Task Status.....	69
179 - Finishing PCMM Routing Distribution task.....	69
180 - Task <i>task - name</i> was run manually.....	70
201 - Start Healthchecker task.....	70
205 - Apply RC configuration to MPE (HostName: <i>hostname</i>) executed by <i>user</i> \n Total execution time <i>time</i> millisecond.....	70
219 - Finishing Healthchecker task.....	71
220 - Starting AlertAging task.....	71
239 - Finishing AlertAging task.....	71
240 - Starting OM Statistics task.....	72
241 - OM Statistics collection complete and data is available for request.....	72
243 - OM Statistics Task was unable to connect to MPE. UID: <i>UID1\nUID2</i>	72
244 - OM Stats task missing stats.....	73
245 - OM Stats task missing unable to retrieve MPE from the database.....	73
247 - OM Statistics Task error detected while retrieving statistics from MPE.....	73
248 - OM Statistics Task failed to retrieve statistics from MPE: <i>name</i>	74

249 - OM Statistics retrieved an incomplete set of statistics from MPE.....	74
250 - OM Statistics Task failed to retrieve proxy from MPE.....	74
251 - OM Statistics Task error retrieving statistics from MPE: <i>name</i> Request attempt: <i>n</i> Error: <i>text</i>	75
252 - BoD Database backup failed due to no IP address.....	75
253 - BoD Database backup started.....	75
254 - BoD Database backup finished.....	76
256 - OM Statistics Task completed successfully.....	76
257 - OM Statistics task completed with a warning.....	76
258 - OM Statistics task failed.....	77
259 - Finishing OM Statistics task.....	77
260 -The BoD cluster has reinitialized.....	77
261 - Bad wget exit status <i>Status Code</i> for MPE <i>Name</i>	78
276 - Statistics Rsync Cleanup task completed successfully.....	78
278 - Statistics Rsync Cleanup Task failed.....	78
279 - Finished Statistics Rsync Cleanup Task.....	79
280 - Starting Subscription Aging Task.....	79
289 - Finishing Subscription Aging Task.....	79
300 - BoD sending.....	80
301 - BoD Received Message.....	80
302 - BoD request to 1 has timed out.....	80
303 - Starting quota aging task.....	81
304 - Finishing quota aging task.....	81
310 - Incorrect XML syntax in PCMM.....	81
311 - Missing required fields for services.....	82
312 - Incorrect XML syntax in Diameter services file.....	82
313 - Services or service indexes already exists.....	82
314 - Same services or service indexes used multiple times.....	83
400 - MAC Translation failed due to connection failure for session ID	83
401 - Starting Stats Files Generator Task.....	83
402 - Stats Files Generator Task completed successfully.....	84
403 - Stats Files Generator Task failed #1, 2, 3, or 4.....	84
404 - Finishing Stats Files Generator Task.....	84
405 - Stats Files Generator Task was not executed successfully.....	85
406 - Sync utility failed to sync stats files to mates. Reason: <i>reason</i>	85
407 - Stats Files Generator Task has removed some files which were not synced to remote servers (...).	86
408 - Stats Files Generator task was not configured any stats type.....	86
500 - RDR: Start message received for Service Index <i>index</i>	86
501 - BOD RDR Unmapped Skip.....	87
502 - <i>task name</i> Task completed successfully.....	87

503 - <i>task name</i> Task failed. \n <i>error message</i>	87
504 - Finishing <i>task name</i> Task.....	88
505 - The Local Repository does not exist, you need to check whether Stats Files Generator Task was executed successfully or not.....	88
506 - <i>task name</i> Task still failed for sync local repository to remote server (<i>IP Address/Hostname</i>) after <i>retry count</i> times.....	88
507 - <i>task name</i> Task was successful for sync local repository to remote server (<i>IP address/Hostname</i>) after <i>retry count</i> times.....	89
508 - RDR: Parsing Failed.....	89
509 - RDR: Dropping RDR Service Index.....	90
510 - RDR: Stop message received for Service Index.....	90
512 - Dropping RDR bucket.....	90
513 - RDR: Skipping unmapped RDR, Bucket Id.....	91
514 - RDR: Quota message received for Bucket Id.....	91
515 - RDR: Quota message processing.....	91
550 - OSSI XML Interface request initiated.....	92
552 - Error while sending Account data to Policy Server.....	92
553 - XML Export results.....	92
554 - XML export failure.....	93
555 - XML request complete.....	93
600 - Invalid login threshold.....	93
620 - Push of pending account updates initiated.....	94
621 - Push done.....	94
625 - Subscriber accounts initiated.....	94
626 - Re-application of subscriber accounts completed.....	95
653 - Apply name to MPE.....	95
1001 - CMTS conn lost clear.....	95
1002 - CMTS conn lost.....	96
1003 - AM conn lost clear.....	96
1004 - PCMM: Lost connection with AM <i>id</i> , Clear and Set.....	96
1010 - PCMM: Received <i>msg-type</i> from AM <i>id</i>	97
1011 - PCMM: Sending <i>msg-type</i> to <i>id</i>	97
1012 - PCMM: Received message.....	97
1013 - PCMM: Sending <i>msg-type</i> to AM <i>id</i>	98
1014 - PCMM: Failed (<i>num attempts</i>) to send <i>msg-type</i> event message to <i>id</i>	98
1015 - PCMM: Successfully sent <i>msg-type</i> event message to <i>id</i>	99
1016 - PCMM: Failover initiated for RKS <i>id</i> , reverting to <i>id</i>	99
1017 - Failed (TOO BUSY) to send <i>msg-type</i> event message to <i>id</i>	99
1020 - PCMM: Rejecting <i>msg-type</i> - no PEP available for SubID <i>IP</i> ; trap will be sent to NM.....	100
1021 - PCMM: Rejecting <i>msg-type</i> - invalid gate ID <i>gateid</i>	100

1022 - PCMM: Rejecting <i>msg-type</i> - AMID mismatch - request <i>msg-amid</i> doesn't match gate MPE-AMID.....	101
1023 - PCMM: Rejecting <i>msg-type</i> - SubId mismatch - request <i>msg-id</i> doesn't match gate <i>mpe-id</i>	101
1024 - PCMM: Rejecting <i>msg-type</i> - Unrecognized Subscriber <i>id</i>	102
1025 - PCMM: Rejecting <i>msg-type</i> - Unauthorized AmID <i>id</i>	102
1026 - PCMM: Rejecting <i>msg-type</i> - Unrecognized Service Class Name <i>name</i>	102
1027 - PCMM: Rejecting <i>msg-type</i> - Incompatible Envelopes - <i>env-type</i> ENV exceeds <i>env-type</i> ENV.....	103
1028 - PCMM: Rejecting <i>msg-type</i> - Classifier count exceeds CMTS limit.....	104
1029 - PCMM: Rejecting <i>msg-type</i> - I/O Error while sending to <i>id</i>	104
1051 - Rejected by Policy.....	104
1101 - DQOS: Established connection to <i>id</i> , Clear and Set.....	105
1102 - DQOS: Lost connection to <i>id</i>	105
1104 - DQOS: Lost connection with CMS <i>id</i> , Clear and Set.....	105
1110 - DQOS: Received <i>msg-type</i> from CMS <i>id</i>	106
1111 - DQOS: Sending <i>msg-type</i> to <i>id</i>	106
1112 - DQOS: Received <i>msg-type</i> from <i>id</i> <i>msg-contents</i>	106
1113 - DQOS: Sending <i>msg-type</i> to CMS <i>id</i>	107
1120 - DQOS: Rejecting <i>msg-type</i> - no CMTS available for SubID <i>id</i>	107
1121 - DQOS: Rejecting <i>msg-type</i> - invalid gate id <i>id</i>	108
1123 - DQOS: Rejecting <i>msg-type</i> - SubId mismatch - request <i>msg-id</i> doesn't match gate <i>mpe-id</i>	108
1124 - DQOS: Rejecting <i>msg-type</i> - Unrecognized Subscriber <i>id</i>	108
1129 - DQOS: Rejecting <i>msg-type</i> - DQOS I/O Error while sending to <i>id</i>	109
1150 - DQOS: Rejecting <i>msg-type</i> - Rejected by policy name.....	109
1204 - SPC DQOS: Lost connection with CMS <i>id</i>	110
1209 - SPC DQOS: Deleting gate <i>gateid</i> , T1 Timer expired.....	110
1210 - SPC DQOS: Received <i>msg-type</i> from CMS <i>id</i> <i>msg-contents</i>	110
1213 - SPC DQOS: Sending <i>msg-type</i> to CMS <i>id</i>	111
1221 - SPC DQOS: Rejecting <i>msg-type</i> - invalid global session id <i>globalsessionid</i>	111
1231 - SPC DQOS: Rejecting <i>msg-type</i> - invalid ingress id <i>ingressid</i>	111
1232 - SPC DQOS: Rejecting <i>msg-type</i> - no path to root zone for ingress id <i>ingressid</i>	112
1233 - SPC DQOS: Dropping <i>msg-type</i> - invalid gate id <i>gateid</i>	112
1370 - IP already static.....	113
1401 - Diameter: Transport connection opened with peer <i>peer_id</i>	113
1402 - Diameter: Transport connection closed with the peer <i>peer</i>	113
1403 - Diameter: Transport connection disconnected by the peer <i>peer</i>	114
1404 - Diameter: Sent msg to peer <i>peer_id</i> connection <i>conn_id</i>	114
1405 - Diameter: Received msg from peer <i>peer_id</i> connection <i>conn_id</i>	114

1406 - Diameter: Error processing message msg from peer <i>peer_id</i> connection <i>conn_id</i>	115
1407 - Diameter: Peer id (<i>connection_id</i>) status changed from <i>previous_status</i> to <i>new_status</i>	115
1408 - Diameter: New connection rejected.....	116
1409 - Diameter: Rejecting <i>msg_type</i> from <i>peer_id - con_id</i> AVP(s) not found in request <i>request_details</i>	116
1410 - Diameter: Response timeout for <i>msg_type</i> sent to <i>conn_id msg_details</i>	116
1411 - Diameter: Received Duplicate message <i>msg_type</i> from <i>conn_id msg_details</i>	117
1412 - Diameter: Sent { <i>type</i> } to { <i>destination</i> } in { <i>connection ID</i> } mes { <i>message</i> }.....	117
1413 - Diameter: Received { <i>type</i> } from { <i>sender</i> } in { <i>connection ID</i> } ms { <i>message</i> }	117
1414 - Diameter: SCTP path on association ID address ADDR_CONFIRMED/ADDR_UNREACHABLE/ADDR_AVAILABLE.....	118
1420 - Diameter: Rejecting <i>application_request</i> - no PCEF available for subscriber.....	118
1421 - Diameter: No default QoS profile defined for media <i>type</i>	119
1440 - Diameter: Rejecting request for subscriber <i>sub_id</i> - No Network Element found for node <i>node_id</i>	119
1441 - Diameter: Rule <i>rule</i> failed for subscriber <i>sub_id xxx</i> - Rule failure code <i>code</i>	119
1442 - Diameter: Rule <i>rule</i> retry <i>x</i> of <i>y</i> for subscriber <i>sub_id xxx</i> Next retry in <i>z</i> seconds.....	120
1443 - Diameter: Rule <i>rule</i> retry failed after <i>n</i> attempts for subscriber <i>sub_id xxx</i>	120
1444 - Diameter: PCC rule <i>rule</i> retry canceled for subscriber <i>sub_id xxx</i>	121
1445 - Diameter: PCC rule <i>rule</i> retry aborted for subscriber <i>sub_id xxx</i> - Too many retries in progress (<i>n</i> attempts).....	121
1446 - Diameter: The maximum number of PDN connections has been exceeded for subscriber <i>ID</i>	121
1447 - Diameter: Too many sessions.....	122
1450 - SceGX: No SCE Profile or Default Profile set for subscriber <i>subscriber</i>	122
1470 - Begin diameter session binding cleanup task.....	122
1471 - End of database iterations.....	123
1472 - End of diameter session binding cleanup task.....	123
1473 - PCMM:Finished iterating the database. Starting to send GateInfos.....	123
1474 - PCMM:Starting cleanup task.....	124
1475 - PCMM: Completed session cleanup.....	124
1476 - Diameter: Completed session cleanup list built.....	124
1477 - PCMM:Completed session cleanup list built.....	125
1600 - DBPLUGIN: No matches for <i>criteria</i>	125
1601 - LDAP: Established Connection to <i>srv</i>	125
1602 - LDAP: Closing connection to <i>srv</i>	126
1605 - LDAP: Attempted connection to 0 failed, reason: 1.....	126

1610 - LDAP: Search failure for <i>ID</i> due to the following error: <i>error message</i>	126
1611 - LDAP: Searching for <i>stype: criteria</i>	127
1612 - LDAP: Search results for <i>stype filter</i> are <i>results</i>	127
1613 - LDAP: No matches for <i>stype filter</i>	127
1614 - LDAP: Multiple matches for <i>stype filter</i>	128
1615 - LDAP: Unexpected search failure for <i>stype filter</i> , reason: <i>msg</i>	128
1617 - LDAP: Detailed description of LDAP modification to be initiated.....	128
1619 - LDAP: Unexpected modify failure for <i>process ID key</i> , reason: <i>message</i>	129
1620 - LDAP: Operation queue <i>process ID</i> in distress. Queue capacity exceeds <i>event message</i>	129
1621 - LDAP: Operation queue <i>process ID</i> has cleared and is no longer in distress. Capacity is below <i>event message</i>	129
1622 - LDAP: Operation queue <i>process ID</i> is currently at 100% and will begin rejecting new LDAP Modify requests.....	130
1623 - LDAP: Modify failure. Unable to modify <i>fields</i> at <i>distinguished name</i> due to the following error: <i>message</i>	130
1624 - LDAP: Modify failure. Unable to perform modify due to the following error: <i>message</i>	131
1626 - LDAP: Update unsuccessful: <i>message</i>	131
1630 - DHCP unexpected event ID set.....	131
1631 - DHCP unable to bind event ID.....	132
1632 - DHCP response timeout.....	132
1633 - DHCP bad relay address.....	132
1634 - DHCP bad primary address.....	133
1635 - DHCP bad secondary address.....	133
1641 - Searching for <i>ID</i>	133
1642 - Search CPE by IP result.....	134
1661 - Sh:Peer Realm <i>detailed message</i>	134
1662 - Sh:Bad <i>primary/secondary address reason</i>	134
1663 - Sh:Searching for <i>peer ID: query</i>	135
1664 - Sh:Search results for <i>query peer ID</i> are: <i>error message</i>	135
1665 - Sh:No matches for <i>peer ID query</i>	135
1666 - Sh:Unexpected search failure on <i>peer ID</i>	136
1667 - Sh:Subscribing for <i>sub type name: element</i>	136
1668 - Sh:Subscription results for <i>user ID type element</i> are: <i>response</i>	136
1669 - Sh:Unexpected subscription failure for <i>user ID type element</i> , reason: <i>response</i>	137
1670 - Sh:Unsubscribing for <i>sub type name: element</i>	137
1671 - Sh:Unsubscription results <i>user ID type element</i> are: <i>response</i>	137
1672 - Sh:Unexpected unsubscription failure <i>user ID type element</i> are: <i>response</i>	138
1673 - Sh:Received notification: <i>results</i>	138

1674 - Sh:Updating User Error.....	138
1675 - Sh:Update failure.....	139
1676 - Sh:Update out-of-sync.....	139
1681 - MSR: Established connection to <i>ip:port</i>	139
1682 - MSR: Closing Connection to <i>ip:port</i>	140
1683 - MSR: Connection to the MSR server at the specified IP address was closed unexpectedly.....	140
1684 - MSR: Closing a secondary MSR connection to revert to a primary connection.....	140
1685 - MSR: Connection attempt to MSR server failed.....	141
1686 - MSR: Searching for <i>type: key</i>	141
1687 - MSR: Searching for <i>type: key</i>	141
1690 - MSR: Unexpected search failure for <i>type key</i> , reason: <i>msg</i>	142
1691 - MSR: Updating <i>type: key</i>	142
1692 - MSR: Update result for <i>type key</i> are: <i>result</i>	142
1693 - MSR: Unexpected update failure for <i>type key</i> , reason: <i>msg</i>	143
1694 - MSR: Subscribing for <i>type: key</i>	143
1695 - MSR: Subscription results for <i>type key</i> are: <i>results</i>	143
1696 - MSR: Unexpected subscription failure for <i>type key</i> , reason: <i>msg</i>	144
1697 - MSR: Unsubscribing for <i>type: key</i>	144
1698 - MSR: Unsubscription results for <i>type key</i> are: <i>result</i>	144
1699 - MSR: Unexpected unsubscription failure for <i>type key</i> , reason: <i>msg</i>	145
1711 - COPS-PR: Received <i>msg-type</i> from <i>id</i>	145
1801 - PCMM lost connection.....	145
1805 - PCMM no connection to PCEF.....	146
2198 - SMPP: Switched back to primary SMSC.....	146
2199 - SMPP: Lost connection to primary SMSC.....	146
2210 - MGPI: Reached max upstream gates.....	147
2211 - MGPI: Reached maximum GPI on all upstream gates.....	147
2212 - MGPI: Incrementing GPI for gate ID, am ID and subscriber	147
2213 - MGPI: Decrementing GP for gate ID, am ID, and subscriber.....	148
2300 - TOD: Time period(s) changed from <i>prev_time_periods</i> to <i>new_time_periods</i>	148
2301 - TOD: Transition to time period(s) <i>new_time_periods</i> started.....	148
2302 - TOD: Transition to time period(s) <i>new_time_periods</i> was still in progress when time periods changed. transition aborted.....	149
2303 - TOD: Transition to time period(s) <i>new_time_periods</i> successfully completed.....	149
2304 - TOD: Transition to time period(s) <i>new_time_periods</i> failed to complete normally.....	149
2305 - TOD: Transition to time period(s) <i>new_time_periods</i> was aborted.....	150

2306 - TOD:Transition to time period(s) <i>current time periods</i> was invoked by the operator.....	150
2549 - SMS:SMSR internal queue is full: <i>queue name</i>	150
2550 - SMS:SMS Relay is not enabled to receive message. <i>optional additional details</i>	151
2551 - SMS:Configured SMS Relay endpoint: <i>SMS end point</i>	151
2552 - SMS:Sent to id: <i>ID</i> using SMS Relay defined at <i>end point</i> Message: <i>message</i>	151
2553 - SMS:Unable to send SMS to <i>ID</i> . Invalid Billing Day <i>billing day</i> configured.....	152
2555 - SMS:Error sending SMS to <i>ID</i> using SMS Relay defined at <i>end point</i> Message: <i>message</i>	152
2556 - SMS:Unable to send SMS to <i>response message</i> using SMS Relay defined at <i>end point ID</i>	152
2557 - SMS:Unable to send SMS to <i>user ID</i> . User's MSISDN could not be found.....	153
2558 - SMS: Connection is established to the SMSC.....	153
2559 - SMS: Connection is lost to the SMSC.....	153
2560 - SMTP:SMTP functionality is not enabled to send message.....	154
2561 - SMTP: Configured endpoint.....	154
2562 - SMTP:Sent to subscriber id using SMS Relay defined at Subject.....	154
2563 - SMTP: Error sending SMTP message to {0} using SMS Relay.....	155
2564 - SMTP: Unable to send SMTP message using SMS Relay defined.....	155
2565 - SMTP:Connection has been closed to MTA <i>IP Address</i>	155
2566 - SMTP:Connection established to MTA <i>IP Address</i>	156
2567 - SMTP: Error attempting to establish a new connection to <i>mta</i> Error: <i>error</i>	156
2611 - MSR: Received notification: <i>msg</i>	156
2700 - New DRA binding created.....	157
2701 - DRA binding released between subscriber and MPE device.....	157
2702 - Existing binding found.....	158
2703 - MRA did not find binding information for subscriber.....	158
2704 - Binding Release Task <i>STARTED</i> <i>COMPLETED</i> <i>ABORTED</i>	158
2705 - Duplicate bindings have been detected for <i>list_of_user_ids</i> on <i>list_of_MRAs</i>	159
2706 - Binding cleanup task has been started.....	159
2707 - RADIUS:Sent <i>message code</i> [<i>accounting status type</i> / <i>pocket ID</i>] to session <i>ID.message</i>	159
2708 - Binding cleanup task is finished and processed 0 stale bindings, 1 duplicate bindings, and 2 stale sessions.....	160
2710 - RADIUS:Stopping communication for <i>port number</i>	160
2900 - ADMISSION: System is in busy state because <i>resource name</i> : <i>criteria admission criteria</i>	160
2901 - ADMISSION: System is in normal state.....	161

2902 - ADMISSION: Monitored resource <i>resource-name</i> is in busy state: criteria threshold.....	161
2903 - ADMISSION: Monitored resource <i>resource-name</i> is in normal state: criteria threshold.....	161
2904 - Diameter/RADIUS protocol is in a busy state.....	162
2905 - Diameter/RADIUS protocol is in a normal state.....	162
3000 - Trace log rate limit.....	163
3100 - Certificate <i>x</i> expires in <i>n</i> days	163
3101 - Certificate <i>x</i> has expired.....	163
4000 - Policy Action generated critical alarm.....	164
4001 - Policy Action generated major alarm.....	164
4002 - Policy Action generated minor alarm.....	164
4048 - CAC: Gate delete error, gate ID = <i>n</i>	165
4063 - CAC: Session context format error for session - removing.....	165
4080 - CAC: Error locating session in CAC database: <i>error-message</i>	165
4154 - CAC: This blade is now active.....	166
4155 - CAC: This blade is now inactive. Canceling any synchronization in progress	166
4156 - CAC: Unknown response from gate delete request	166
4157 - CAC: Exception while deleting gate id <i>id</i>	167
4163 - CAC: Forcing synchronization with Tandberg server at <i>ip-address</i>	167
4184 - CAC: Seachange/Tandberg reserve of session id on ip-address complete	167
4185 - CAC: Seachange/Tandberg release of session id complete.....	168
4208 - CAC: Seachange/Tandberg reserve of duplicate session <i>id</i> on <i>ip-address</i> complete: status <i>status</i> , duration <i>time</i> ms.....	168
4300 - RC <i>ip-address</i> Unreachable.....	169
4301 - RC <i>ip-address</i> Reachable.....	169
4302 - RC <i>ip-address</i> Unreachable - operation: <i>operation</i>	169
4303 - Can not download log file from MPE.....	170
4550 - Policy Trace <i>name</i> : <i>message</i>	170
4551 - Policy Trace <i>name</i> : <i>message</i>	170
4552 - Policy Trace <i>name</i> : <i>message</i>	171
4560 - Policy Action Trace: <i>message</i>	171
4561 - Policy Action Trace: <i>message</i>	171
4562 - Policy Action Trace: <i>message</i>	172
4563 - Policy Action Trace: <i>message</i>	172
4564 - Policy Action Trace: <i>message</i>	172
4565 - Policy Action Trace: <i>message</i>	173
4566 - Policy Action Trace: <i>message</i>	173
4567 - Policy Action Trace: <i>message</i>	173

4600 - MPE or MRA rejects a secondary connection.....	174
4601 - MPE or MRA reverts from a secondary connection to a primary connection.....	174
4602 - More than one server in a cluster is Active at a time.....	174
4603 - Max primary site failure threshold reached.....	175
4604 - Policy Cluster Offline Failure.....	175
4610 - <i>Sh Connections operation</i> Successful for MPEs' name, Failed for MPEs' name.....	176
4700 - Upgrade Manager command return message: <i>message</i>	176
6000 - Wireline Subact Log.....	176
6102 - Gx-Plus: Learnt new endpoint <i>id</i> , <i>x</i> from gateway <i>y</i>	177
6103 - CAC: Exception while <i>Seachange/Tandberg</i> sync operation with <i>url</i> terminated CAC session ID <i>id</i>	177
6105 - PCMM syntax error.....	178
6200 - NAC: Abnormal delete of session.....	178
6201 - NAC: Normal delete of session.....	178
6202 - NAC: Allowed session.....	179
6203 - NAC: Rejecting <i>msg-type</i> - no path available from <i>SUB-IP</i> to <i>SERVER-IP</i>	179
6204 - NAC: Rejecting <i>msg-type</i> - subscriber with address <i>SUB-IP</i> is unknown (session ID <i>VoD-ID</i>).....	180
6205 - NAC: Allowing <i>msg-type</i> - subscriber with unknown address <i>SUB-IP</i> (session ID <i>VoD-ID</i>).....	180
6206 - NAC: No account information for subscriber <i>SUB-IP</i> (session ID <i>VoD-ID</i>).....	181
6207 - NAC: Subscriber with address <i>SUB-IP</i> is unknown (session ID <i>VoD-ID</i>).....	181
6208 - NAC: Rejecting <i>msg-type</i> - Rejected by policy <i>name</i>	181
6209 - NAC: Both static and dynamic definitions for subscriber IP address <i>SUB-IP</i> , using dynamic definition.....	182
6210 - NAC: Could not find BRAS endpoint <i>endpoint</i> in path <i>path</i> - rejecting.....	182
6211 - BRAS: COPS-PR declared an IP address (<i>ip</i>) already defined as static in account <i>account</i>	183
6400 - BRAS: Transmit buffer for <i>n</i> extended from <i>x</i> to <i>y</i>	183
6401 - BRAS: Transmit buffer for <i>id</i> shrunk from <i>x</i> to <i>y</i>	183
6402 - BRAS: Transmit buffer overflow for <i>n</i> : space needed = 1, available = 2.....	184
6403 - COPS-PR: Connection accepted from gateway IP <i>ip-address</i> , port <i>port</i>	184
6404 - COPS-PR: Lost connection with gateway <i>id</i>	185
6405 - COPS-PR: Rejecting OPN message from <i>id</i> . Unknown gateway.....	185
6406 - COPS-PR: BRAS IP <i>x</i> , port <i>y</i> no longer associated with this MPE. Closing connection.....	185
6407 - COPS-PR: Received <i>msg-type</i> from <i>id</i>	186
6408 - COPS-PR: Sending <i>msg-type</i> to <i>id</i>	186
6409 - COPS-PR: Starting full state synchronization with gateway <i>n</i>	187
6410 - COPS-PR: Full state synchronization with gateway <i>n</i> has completed.....	187

6411 - COPS-PR: Learnt new endpoint from <i>ip-address</i> , <i>y</i> from gateway <i>ip-address</i>	187
6412 - COPS-PR: Deleting endpoint <i>ip-addressss</i> , <i>sub-id</i> due to DRQ from gateway <i>ip-address</i>	188
6413 - COPS-PR: Deleting stale entry for IP <i>ip-address</i> , <i>sub-id</i> from gateway <i>ip-address</i>	188
6414 - COPS-PR: ERX <i>x</i> requests fast synchronization with Policy Server <i>n</i>	188
6415 - Gx-Plus: Received CCR-I, session ID <i>x</i> subid <i>y</i> from <i>id</i>	189
6416 - Gx-Plus: Received CCR-T, session ID <i>x</i> from <i>id</i>	189
6417 - Handling ack: Endpoint Ip; Gx Subscriber Id; Router Address.....	190
6418 - Gx-Plus: Start state synchronization with gateway <i>id</i>	190
6419 - Gx-Plus: State synchronization with gateway <i>id</i> has completed.....	190
6420 - Gx-Plus: Drop all the bras endpoints and diameter sessions because of cold reboot from gateway <i>id</i>	191
6421 - Gx-Plus: Deleting endpoint <i>n</i> , <i>x</i> due to CCR-T from gateway <i>id</i>	191
6422 - Gx-Plus: Deleting stale entry for IP <i>n</i> , <i>x</i> from gateway <i>id</i>	192
6423 - Gx-Plus: Received warm reboot message from gateway <i>id</i>	192
6424 - Gx-Plus: Received AYT message from gateway <i>id</i>	192
6425 - Gx-Plus: Received AWD message from gateway <i>id</i>	193
6426 - COPS-PR: Dropping <i>msg-type</i> from <i>id</i> - <i>reason</i>	193
6427 - BRAS: Scrubber logout IP Addr; Sub Id; Router Addr.....	194
7001 - CAC: Exception while recreating Tandberg session.....	194
7002 - CAC: Recreating Tandberg session <i>id</i> due to synch operation with <i>url</i>	194
7003 - CAC: Failed to recreate Tandberg session <i>id</i> due to sync with <i>url</i>	195
7010 - CAC: Exception while reading local session ID list.....	195
7011 - CAC: Failed to create CAC session ID <i>id</i>	195
7013 - CAC: Exception while sync operation terminated CAC session ID <i>id</i>	196
7014 - CAC: Attempt to remove nonexistent session ID <i>id</i> failed.....	196
7015 - CAC: Failed to release resources for session ID <i>id</i>	197
7019 - CAC: Created CAC session ID <i>id</i> due to request from VoD server at <i>server-ip</i>	197
7023 - CAC: Processing reconfiguration request.....	197
7025 - CAC: Gate set error <i>x</i>	198
7027 - NAC: Send error reply. Session, <i>x</i>	198
7031 - CAC: Exception while writing session <i>x</i> into database.....	198
7032 - CAC: Exception while reserving resources for <i>id</i> : <i>error-message</i>	199
7034 - CAC: Locally removing session <i>id</i> due to synchronization mismatch with <i>Seachange/Tandberg</i> server at <i>ip-address</i>	199
7035 - CAC: Locally removing session <i>id</i> due to synchronization timeout with <i>Seachange/Tandberg</i> server at <i>ip-address</i>	200

7036 - CAC: Requesting removal of session <i>id</i> from <i>Seachange/Tandberg</i> server at <i>ip-address</i> due to synchronization mismatch.....	200
7038 - CAC: This blade is now active.....	200
7039 - CAC: This blade is now inactive. Canceling any synchronization in progress.....	201
7047 - CAC: Starting synchronization with <i>server-url</i>	201
7048 - CAC: Synchronization with <i>server-url</i> complete.....	201
7052 - CAC: Failed to reserve resources for <i>x</i>	202
7054 - CAC: Rejecting create of session ID <i>id</i> from server at <i>ip-address</i> : duplicate session.....	202
7055 - CAC: Tandberg session ID <i>id</i> missing in session list on Tandberg server. Issuing specific query to <i>url</i>	203
7056 - CAC: Tandberg session ID <i>id</i> still missing in session list on Tandberg server at <i>url</i> - scheduling removal.....	203
7057 - CAC: Keepalive status request from Tandberg server at <i>ip-address</i>	203
7058 - CAC: Session list status request from <i>Seachange/Tandberg</i> server at <i>ip-address</i>	204
7059 - CAC: Session detail status request from Tandberg server at <i>ip-address</i> for session ID <i>id</i>	204
7060 - CAC: Version status request from Tandberg server at <i>ip-address</i>	205
7063 - CAC: No keepalive response from Tandberg server at <i>url</i>	205
7064 - CAC: Exception while releasing session <i>id</i> from Tandberg server.....	205
7065 - CAC: Tandberg server requesting release of session ID <i>id</i>	206
7066 - CAC: No version status response from Tandberg server at <i>url</i>	206
7067 - CAC: Version report from Tandberg server at <i>url</i>	206
7068 - CAC: Invalid version report from Tandberg server at <i>url</i>	207
7069 - CAC: Sending keepalive request to Tandberg server at <i>url</i>	207
7070 - CAC: Received keepalive response from Tandberg server at <i>url</i>	207
7071 - CAC: Sync mismatch with <i>Seachange/Tandberg</i> server at <i>ip-address</i> : VoD server has <i>n</i> sessions missing on MPE.....	208
7072 - CAC: Sync mismatch with <i>Seachange/Tandberg</i> server at <i>ip-address</i> : MPE has # session <i>id</i> missing on VoD server.....	208
7073 - CAC: Session <i>id</i> from <i>ip-address</i> rejected due to invalid bit rate (<i>bit-rate</i>).....	209
7075 - CAC: Failed to create CAC session ID <i>id</i> from VoD Server at <i>server-ip</i> for subscriber IP <i>sub-ip:status</i>	209
7078 - CAC: Error requesting session list from <i>Seachange/Tandberg</i> server at <i>url</i>	209
7078 - CAC: Unknown response from gate delete request.....	210
7079 - CAC: Forcing synchronization with <i>Seachange/Tandberg</i> server at <i>url</i>	210
7080 - CAC: Starting synchronization with <i>Seachange/Tandberg</i> server at <i>url</i>	211
7081 - CAC: Synchronization with <i>Seachange/Tandberg</i> server at <i>url</i> complete.....	211

7082 - CAC: Max sync failures with <i>Seachange/Tandberg</i> server at <i>ip-address</i> : removing <i>n</i> sessions.....	211
7083 - CAC: <i>Seachange/Tandberg</i> reserve of duplicate session <i>id</i> on <i>ip-address</i> complete: status <i>status</i> , duration <i>time</i> ms.....	212
7084 - CAC: Sync with <i>Seachange/Tandberg</i> at <i>ip-address</i> : VoD server has # session <i>id</i>	212
7085 - CAC: Sync with <i>Seachange/Tandberg</i> at <i>ip-address</i> : MPE has # session <i>id</i>	213
7101 - ADMISSION: MediationSOAP: Busy: criteria <i>trigger</i>	213
7102 - ADMISSION: MediationSOAP: Normal: criteria <i>trigger</i>	213
7103 - ADMISSION: MediationSOAP: Resource <i>name</i> new condition <i>trigger</i> of the criteria <i>specification</i>	214
7104 - ADMISSION: MediationSOAP: Resource <i>name</i> new condition <i>trigger</i> of the criteria <i>specification</i>	214
7105 - ADMISSION: MediationSOAP is in a <i>level</i> state.....	214
7541 - SYNC VERIFY REPORTS SUCCESS.....	215
7542 - SYNC VERIFY REPORTS FAIL.....	215
7561 - SYNC EXCEPTION OCCURRED WHILE PROCESS SYNC RESPONSE <i>type</i>	215
8021 - BoD failure HTTP.....	216
8024 - BoD classifier already active HTTP.....	216
8025 - BoD classifier not active HTTP.....	216
8050 - BoD success HTTP.....	217
8070 - BoD failure SOAP.....	217
8080 - BoD success SOAP.....	217
8103 - Policy server connection dropped from server address. BoD has scheduled policy server reconnect task.....	218
8100 - BoD establish connection Policy Server.....	218
8104 - BoD disconnect connection Policy Server.....	218
8105 - BoD disconnect connection failure Policy Server.....	219
8106 - BoD establish connection failure Policy Server.....	219
8250 - BoD start session cleanup task.....	219
8251 - BoD complete session cleanup task.....	220
8300 - BoD send message.....	220
8301 - BoD receive message.....	220
8302 - BoD request timeout.....	221
8320 - BoD PCMM create session failed.....	221
8321 - BoD PCMM delete session failed.....	221
8400 - BoD MAC translation failed due to sessionID connection failed.....	222
8401 - BoD MAC translation succeeded.....	222
8402 - BoD MAC translation failed due to no IP address for session ID.....	222
8403 - BoD MAC translation failed due to response failed for sessionID.....	223

8404 - BoD MAC translation failed due to incorrect MAC translation URL for sessionID.....	223
8405 - BoD MAC translation failed due to MAC address connection failure.....	223
8406 - BoD MAC translation failed due to no IP address for MAC address.....	224
8407 - BoD MAC translation failed due to response failed for MAC address.....	224
8408 - BoD MAC translation failed due to incorrect MAC translation URL for MAC Address.....	225
8411 - BoD session notification return success.....	225
8412 - BoD session notification return other status.....	225
8413 - BoD session notification expire.....	226
8414 - BoD session notification retry.....	226
8420 - Statistics of Discovered IPv6 subnets were filtered for each CMTS.....	226
8421 - Statistics of Discovered IPv6 subnets were filtered for all CMTS.....	227
8422 - Statistics of Discovered IPv6 subnets were aggregated for each CMTS.....	227
8423 - Statistics of Discovered IPv6 subnets were aggregated for all CMTS.....	227
8424 - IPv6 subnet settings deployed to MA successfully.....	228
8425 - IPv6 subnet settings were deployed to some MA failed.....	228
8500 - MA server started.....	228
8501 - BoD HTTP Request Failed.....	229
8502 - BoD Classifier Active.....	229
8503 - BoD: Policy Server connection dropped.....	229
8504 - BoD: Disconnected policy server connection.....	230
8505 - BoD: Disconnection failure from policy server.....	230
8506 - BoD connection failure.....	230
8507 - BoD auto delete started.....	231
8508 - BoD auto delete ended.....	231
8509 - BoD sending debug information.....	231
8510 - BoD received information.....	232
8511 - BoD received warning.....	232
8512 - BoD MAC translation succeeded.....	232
8513 - BoD MAC translation IP failure.....	233
8514 - BoD MAC translation failure due to response parse failure.....	233
8515 - BoD MAC translation failure due to incorrect MAC Translation URL for session ID.....	233
8516 - BoD MAC translation failure due to connection failure for MAC address.....	234
8517 - MAC Translation failed due to no IP Address returned for MAC address.....	234
8518 - MAC Translation failed due to response parse failure for MAC address.....	234
8519 - MAC Translation failed due to incorrect MAC Translation URL for MAC Translation URL.....	235
8520 - RDR: Failed to parse service index.....	235
8521 - RDR: Client or Server has closed the socket connection.....	236

8522 - RDR: Error starting RDR service on port.....	236
8523 - RDR: port busy.....	236
8524 - RDR: Fatal error starting RDR service on port.....	237
8525 - RDR: Start message processing.....	237
8526 - RDR: Stop message processing.....	237
8527 - RDR: Start message processing	238
8528 - Edge QAM Device discovered.....	238
8529 - PCMM: Sending <i>msg-type</i> to AM <i>id</i>	238
8530 - PCMM: Received <i>msg-type</i> from <i>id</i>	239
8531 - DQOS: Sending <i>msg-type</i> to CMS <i>id</i>	239
8532 - SPC DQOS: Sending <i>msg-type</i> to CMS <i>id</i>	240
8534 - RDR: Quota message processing.....	240
8535 - RDR: Quota message processing information.....	240
8600 - BoD invalid sessionID.....	241
8601 - BoD PCMM request rejected.....	241
8602 - BoD PCMM mode not enabled.....	241
8603 - BoD Diameter mode not enabled.....	242
8700 - BoD admission protocol busy event.....	242
8701 - BoD admission protocol clear event.....	242
8702 - BoD admission component busy event.....	243
8703 - OMStats task failed.....	243
8704 - BoD PCMM too busy set.....	243
10000 - ADS: Analytics Data Stream connection to <i>Analytics Client ID</i> has been established for Channel: <i>Channel Type</i> , ex <i>Policy Event Version</i> : <i>ADS Interface Version</i> Connection established to the MPE from an Analytics client.....	244
10001 - ADS: Analytics Data Stream connection to <i>Analytics Client ID</i> was closed.....	244
10002 - ADS: Lost Analytics Data Stream connection to <i>Analytics Client ID</i>	244
10003 - ADS: Error processing Analytics Data Stream message received from <i>Analytics Client ID</i>	245
10004 - ADS: Error sending Analytics Data Stream message to <i>Analytics Client ID</i>	245
10005 - ADS: Analytics Data Stream encountered an error.....	245
10006 - Sy: Received notification from <i>Sy Identity</i> message: <i>Diameter message</i>	246
10007 - Sy: Peer Realm is undefined	246
10008 - Sy: Primary address is undefined	246
10009 - Sy: Searching <i>Sy Identity</i> for subscriber: <i>Subscriber IDs</i>	247
10010 - Sy: Search results from peer <i>Sy Identity</i> for subscriber <i>Subscriber IDs</i> are: <i>Policy Counter values</i>	247
10012 - Sy: Search failure on <i>Sy Identity</i> : <i>Diameter Error Code</i> subscriber <i>Subscriber IDs</i>	247

10014 - Sy:Policy Action failure attempting to send <i>SLR Request Type</i> SLR to <i>Sy data source name</i> on MPE <i>MPE name</i> for subscriber: <i>Subscriber ID : Error Message</i>	248
10020 - CMP started.....	248
10021 - Import XML add.....	248
10022 - Import XML update.....	249
10023 - Import XML delete.....	249
10024 - Import XML fail.....	249
10025 - XML add fail.....	250
10026 - RC proxy apply2.....	250
10027 - RC proxy apply.....	251
10028 - RC proxy send.....	251
10029 - Starting Statistics Rsync Cleanup task.....	251
10031 - Diameter Service Invalid XML	252
10032 - Starting <i>task name</i> task.....	252
10033 - Task was successful for sync local repository to remote server.....	252
10036 - Retry fail.....	253
10037 - DBPLUGIN: No matches for <i>criteria</i> , search type <i>ID</i>	253
10038 - SMTP: SMTP functionality is not enabled to send message.....	253
10039 - RADIUS: Initilizing communications on port.....	254
10040 - RADIUS: Started listening on port.....	254
10041 - RADIUS:Dropping invalid message.....	254
10042 - RADIUS: Dropping message with bad MD5, probably bad password.....	255
10043 - RADIUS:Sent	255
10044 - Policy event.....	255
10045 - RADIUS:Start failed on port	256
10046 - RADIUS: Received <i>message code</i> / status type: <i>accounting type</i> <i>pocket ID</i> / <i>session ID</i> from <i>client address.message</i>	256
10048 - Diameter: SCTP path on association ID address ADDR_CONFIRMED/ADDR_UNREACHABLE/ADDR_AVAILABLE.....	256
10100 - Average session size exceeds the projected session size, current average session size.....	257
10101 - Average session size in below the projected session size.....	257
10102 - Session database size reached threshold percent of session database capacity.....	257
10103 - Session database size below threshold percent of session database capacity.....	258
10104 - Average binding size exceeds the projected binding size.....	258
10105 - Average binding size is below the projected binding size	259
10106 - Binding database size reached threshold percent of binding database capacity.....	259

10107 - Binding database size is below threshold percent of binding database capacity.....	259
10108 - Starting Replication Statistics task.....	260
10109 - Replication Statistics Task failed.....	260
10110 - Replication Statistics Task completed successfully.....	260
10111 - Finishing Replication Statistics task.....	261
10112 - Replication Statistics collection complete and data is available for request.....	261
10113 - Tx Conn Unavail Discard.....	261
10114 - Tx Per Conn Queue Full Discard.....	262
10120 - License Validation.....	262
10121 - Ev Conn Far End Close.....	262
15101 - MEDIATION SPR CONNECTION EXCEPTION.....	263
15102 - MEDIATION SPR CONNECTION TIMEOUT.....	263
15103 - MEDIATION SOAP PARAMETER ERROR.....	263
15104 - MEDIATION OPEN COMCOL ERROR.....	264
15105 - MEDIATION OPERATE COMCOL ERROR.....	264
15106 - MEDIATION SOAP RESULT ERROR.....	264
15107 - MEDIATION SPR CONNECTION REQUEST.....	265
15108 - MEDIATION SPR CONNECTION RESPONSE.....	265
15109 - MEDIATION SOAP REQUEST.....	265
15110 - SPR CONNECTION FAILED.....	266
15111 - SPR CONNECTION FAILED CLEAR.....	266
15112 - SPR LICENSE LIMIT SET.....	266
15113 - SPR LICENSE LIMIT CLEAR.....	267
15114 - SPR TIMEOUT ERROR.....	267
15115 - MEDIATION ADMISSION PROTOCOL BUSY EVENT.....	267
15116 - MEDIATION ADMISSION PROTOCOL CLEAR EVENT.....	268
15117 - MEDIATION ADMISSION COMPONENT BUSY EVENT.....	268
15118 - MEDIATION ADMISSION COMPONENT CLEAR EVENT.....	268
15119 - MEDIATION SOAP TOO BUSY SET/MEDIATION SOAP TOO BUSY CLEAR.....	269
15121 - SYNC SERVER ERROR.....	269
15122 - SYNC STOP SERVER ERROR.....	269
15123 - SYNC THREAD UNCAUGHT EXCEPTION.....	270
15124 - SYNC EXEC CMD FAIL.....	270
15125 - SYNC EXEC CMD ERROR.....	270
15126 - SYNC ACCEPT APP SYNC REQUEST.....	271
15127 - SYNC REJECT APP SYNC REQUEST.....	271
15128 - SYNC APP SYNC REQUEST EXCEPTION.....	271
15129 - SYNC APP SYNC RESPONSE.....	272

15130 - SYNC APP SYNC RESPONSE EXCEPTION.....	272
15131 - SYNC TOO BUSY REJECT REQUEST.....	272
15132 - SYNC INVALID REQUEST.....	273
15133 - SYNC HANDLE REQUEST EXCEPTION.....	273
15134 - SYNC ACCEPT SYNC REQUEST.....	273
15135 - SYNC OPEN COMCOL FAIL.....	274
15136 - SYNC CLOSE COMCOL FAIL.....	274
15137 - SYNC VERIFY SUCCESS.....	274
15138 - SYNC VERIFY FAIL.....	275
15139 - SYNC RESOLVE SUCCESS.....	275
15140 - SYNC RESOLVE FAIL.....	275
15141 - SYNC CREATE DATS SUCCESS.....	276
15142 - SYNC CREATE DATS FAIL.....	276
15143 - DO SYNC FAIL.....	276
15144 - SYNC CREATE SYNC RESPONSE.....	277
15145 - Sync: Exception occurred while processing sync response.....	277
15146 - SYNC DISK QUOTA EXCEED.....	277
15147 - SYNC DISK NO SPACE.....	278
15148 - SYNC DISK NO SPACE CLEAR.....	278
15200 - PM GEN STATS SYNC TASK START.....	278
15201 - PPM GEN STATS SYNC TASK SUCCESS.....	279
15202 - PM GEN STATS SYNC TASK FAIL.....	279
15203 - PM GEN STATS SYNC TASK END.....	279
15204 - PM STATS SYNC TASK START.....	280
15205 - PM STATS SYNC TASK SUCCESS.....	280
15206 - PM STATS SYNC TASK FAIL.....	280
15207 - PM STATS SYNC TASK END.....	281
15208 - PM STATS SYNC TASK REPOSITORY SUCCESS.....	281
15209 - PM STATS SYNC TASK REPOSITORY FAIL.....	281
17100 - MDF Soap Result Error.....	282
17102 - MDF Soap Parameter Error.....	282
17103 - MDF No QP Name Error.....	282
17104 - MDF Soap Illegal OPMD Change.....	283
17105 - MDF Soap Client Result Error.....	283
17106 - MDF Cannot Parse SDM Response.....	283
17107 - MDF IMSI Not In Range.....	284
17108 - MDF Soap Client Request.....	284
17109 - MDF Soap Client Response.....	284
17110 - MDF SPR Message.....	285
17111 - MDF Get Subscriber.....	285
17112 - MDF Illegal Notify Subscriber.....	285

17113 - MDF Soap Request.....	286
17114 - MDF Soap Response.....	286
17115 - MDF Out SPR Message.....	286
17116 - MDF IMSI Not In SPR.....	287
17118 - MDF IMSI In SPR.....	287
17119 - MDF IMSI In S-SPR.....	287
17120 - MDF DYQ Was Expired.....	288
17121 - MDF Quota Was Expired.....	288
40015 - Load is OK	288
40024 - Home reports blade is master.....	289
50008 - Home reports fully redundant.....	289
Chapter 4: Alarms and Events.....	290
Alarms formatting information.....	291
Alarm and Event Severity Levels.....	291
Platform (31000-32700).....	291
31000 - S/W Fault.....	291
31001 - S/W Status.....	292
31002 - Process Watchdog Failure.....	292
31003 - Thread Watchdog Failure.....	292
31100 - DB Replication Fault.....	293
31101 - DB Replication To Slave Failure.....	293
31102 - DB Replication From Master Failure.....	293
31103 - DB Replication Update Fault.....	293
31104 - DB Replication Latency Over Threshold.....	294
31105 - DB Merge Fault.....	294
31106 - DB Merge To Parent Failure.....	294
31107 - DB Merge From Child Failure.....	294
31108 - DB Merge Latency Over Threshold.....	295
31109 - Topology Config Error.....	295
31110 - DB Audit Fault.....	295
31111 - DB Merge Audit in Progress.....	296
31112 - DB Replication Update Log Transfer Timed Out.....	296
31113 - DB Replication Manually Disabled.....	296
31114 - DB Replication over SOAP has failed.....	296
31115 - DB Service Fault.....	297
31116 - Excessive Shared Memory.....	297
31117 - Low Disk Free.....	297
31118 - DB Disk Store Fault.....	297
31119 - DB Updatelog Overrun.....	298

31120 - DB Updatelog Write Fault.....	298
31121 - Low Disk Free Early Warning.....	298
31122 - Excessive Shared Memory Early Warning.....	299
31123 - ADIC Complete.....	299
31124 - ADIC Error.....	299
31125 - DB Durability Degraded.....	299
31126 - Audit Blocked.....	300
31127 - DB Replication Audit Complete	300
31128 - ADIC Found Error.....	300
31129 - ADIC Found Minor Issue.....	300
31130 - Network Health Warning.....	301
31140 - DB Perl Fault.....	301
31145 - DB SQL Fault.....	301
31146 - DB Mastership Fault.....	301
31147 - DB UpSyncLog Overrun.....	302
31148 - DB Lock Error Detected.....	302
31200 - Process Management Fault.....	302
31201 - Process Not Running.....	302
31202 - Unkillable Zombie Process.....	303
31206 - Process Mgmt Monitoring Fault.....	303
31207 - Process Resource Monitoring Fault.....	303
31208 - IP Port Server Fault.....	303
31209 - Hostname Lookup Failed.....	304
31213 - Process Scheduler Fault.....	304
31214 - Scheduled Process Fault.....	304
31215 - Process Resources Exceeded.....	305
31216 - SysMetric Configuration Error.....	305
31220 - HA Config Monitor Fault.....	305
31221 - HA Alarm Monitor Fault.....	305
31222 - HA Not Configured.....	306
31223 - HA Heartbeat Transmit Failure.....	306
31224 - HA Configuration Error.....	306
31225 - HA Service Start Failure.....	306
31226 - HA Availability Status Degraded.....	307
31227 - HA Availability Status Failed.....	307
31228 - HA Standby Server Offline.....	307
31229 - HA Score Changed.....	307
31230 - Recent Alarm Processing Fault.....	308
31231 - Platform Alarm Agent Fault.....	308
31232 - HA Late Heartbeat Warning.....	308
31233 - HA Secondary Path Down	308

31234 - Untrusted Time Upon Initialization	309
31235 - Untrusted Time After Initialization.....	309
31240 - Measurements Collection Fault.....	309
31250 - RE Port Mapping Fault.....	310
31260 - DB SNMP Agent.....	310
31270 - Logging Output.....	310
31280 - HA Active to Standby Transition.....	311
31281 - HA Standby to Active Transition.....	311
31282 - HA Management Fault.....	311
31283 - HA Server Offline.....	311
31284 - HA Remote Subscriber Heartbeat Warning.....	312
31290 - HA Process Status.....	312
31291 - HA Election Status.....	312
31292 - HA Policy Status.....	313
31293 - HA Resource Link Status.....	313
31294 - HA Resource Status.....	313
31295 - HA Action Status.....	313
31296 - HA Monitor Status.....	314
31297 - HA Resource Agent Info.....	314
31298 - HA Resource Agent Detail.....	314
31299 - HA Notification Status.....	314
31300 - HA Control Status.....	315
32113 - Uncorrectable ECC Memory Error.....	315
32114 - SNMP Get Failure.....	315
32115 - TPD NTP Daemon Not Synchronized Failure.....	316
32116 - TPD Server's Time Has Gone Backwards.....	316
32117 - TPD NTP Offset Check Failure.....	316
32300 – Server Fan Failure.....	316
32301 - Server Internal Disk Error.....	317
32302 – Server RAID Disk Error.....	317
32303 - Server Platform Error.....	317
32304 - Server File System Error.....	317
32305 - Server Platform Process Error.....	318
32307 - Server Swap Space Shortage Error.....	318
32308 - Server Provisioning Network Error.....	318
32312 - Server Disk Space Shortage Error.....	319
32313 - Server Default Route Network Error.....	319
32314 - Server Temperature Error.....	320
32315 – Server Mainboard Voltage Error.....	320
32316 – Server Power Feed Error.....	320
32317 - Server Disk Health Test Error.....	321

32318 - Server Disk Unavailable Error.....	321
32320 – Device Interface Error.....	321
32321 – Correctable ECC memory error.....	322
32322 – Power Supply A error.....	322
32323 – Power Supply B Error.....	322
32324 – Breaker panel Feed Error.....	323
32325 – Breaker Panel Breaker Error.....	323
32326 – Breaker Panel Monitoring Error.....	324
32327 – Server HA Keepalive Error.....	324
32331 – HP disk problem.....	325
32332 – HP Smart Array controller problem.....	325
32333 – HP hpacucliStatus utility problem.....	325
32335 - Switch Link Down Error.....	326
32336 – Half open socket limit.....	326
32339 - TPD Max Number Of Running Processes Error.....	326
32340 - TPD NTP Daemon Not Synchronized Error.....	327
32341 - TPD NTP Daemon Never Synchronized Error.....	327
32342 - TPD NTP Offset Check Error.....	327
32343 - TPD RAID disk problem.....	327
32344 - RAID controller problem.....	328
32345 - Server Upgrade snapshot(s) invalid.....	328
32346 - OEM hardware management service reports an error.....	328
32347 - The hwmgmtcliStatus daemon needs intervention.....	329
32500 – Server Disk Space Shortage Warning.....	329
32501 – Server Application Process Error.....	329
32502 – Server Hardware Configuration Error.....	329
32505 – Server Swap Space Shortage Warning.....	330
32506 – Server Default Router not Defined.....	330
32507 – Server Temperature Warning.....	330
32508 – Server Core File Detected.....	331
32509 – Server NTP Daemon Not Synchronized.....	331
32510 – CMOS Battery Voltage Low.....	331
32511 – Server Disk Self Test Warning.....	332
32512 – Device Warning.....	332
32513 – Device Interface Warning.....	332
32514 – Server Reboot Watchdog Initiated.....	332
32515 – Server HA Failover Inhibited.....	333
32516 – Server HA Active To Standby Transition.....	333
32517 – Server HA Standby To Active Transition.....	333
32518 – Platform Health Check Failure.....	334
32519 – NTP Offset Check Failure.....	334

32520 – NTP Stratum Check Failure.....	334
32521 – SAS Presence Sensor Missing.....	334
32522 – SAS Drive Missing.....	335
32524 – HP disk resync.....	335
32525 – Telco Fan Warning.....	335
32526 – Telco Temperature Warning.....	336
32527 – Telco Power Supply Warning.....	336
32528 – Invalid BIOS value.....	336
32529 – Server Kernel Dump File Detected.....	336
32530 – TPD Upgrade Fail Detected.....	337
32531 – Half Open Socket Warning.....	337
32532 – Server Upgrade Pending Accept/Reject.....	337
32533 -TPD Max Number Of Running Processes Warning.....	337
32534 -TPD NTP Source Is Bad Warning.....	338
32535 -TPD RAID disk resync.....	338
32536 - Server Upgrade Snapshot(s) warning.....	338
QBus Platform (70000-70999).....	339
70001 - QP_procmgr failed.....	339
70002 - QP Critical process failed.....	339
70003 - QP Non-critical process failed.....	340
70004 - QP Processes down for maintenance.....	340
Error Code Details for Alarms 70010 and 70011.....	340
70010 - QP Failed Server-backup Remote Archive Rsync.....	341
70011 - QP Failed System-backup Remote Archive Rsync.....	342
70012 - QP Failed To Create Server Backup.....	342
70013 - QP Failed To Create System Backup.....	342
70015 - VIP Route Add Failed.....	343
70020 - QP Master database is outdated.....	343
70021 - QP slave database is unconnected to the master.....	344
70022 - QP Slave database failed to synchronize.....	344
70023 - QP Slave database lagging the master.....	345
70024 - QP Slave database is prevented from synchronizing with the master.....	345
70025 - QP Slave database is a different version than the master.....	345
70026 - QP Server Symantec NetBackup Operation in Progress.....	346
70028 - QP Signaling Bonded Interface is Down.....	346
70029 - QP Peer Node Bonded Interface is Down.....	347
70030 - QP Backplane Bonded Interface is Down.....	347
Policy Server (71000-89999).....	347
71004 - AM CONN LOST.....	347
71101 - DQOS DOWNSTREAM CONNECTION CLOSED.....	348
71102 - MSC CONN LOST.....	348

71104 - DQOS AM CONNECTION CLOSED.....	349
71204 - SPC CONN CLOSED.....	349
71402 - TRANSPORT CLOSED.....	349
71403 - TRANSPORT DISCONNECTED.....	350
71408 - DIAMETER NEW CONN REJECTED.....	350
71414 - SCTP PATH STATUS CHANGED.....	351
71605 - LDAP CONN FAILED.....	351
71630 - DHCP UNEXPECTED EVENT ID.....	351
71631 - DHCP UNABLE TO BIND EVENT ID.....	352
71632 - DHCP RESPONSE TIMEOUT EVENT ID.....	352
71633 - BAD RELAY ADDRESS EVENT ID.....	352
71634 - DHCP BAD PRIMARY ADDRESS EVENT ID.....	353
71635 - DHCP BAD SECONDARY ADDRESS_EVENT ID.....	353
71684 - SPR CONNECTION CLOSED.....	354
71685 - MSR DB NOT REACHABLE.....	354
71702 - BRAS CONNECTION CLOSED.....	354
71703 - COPS UNKNOWN GATEWAY.....	355
71801 - PCMM NO PCEF.....	355
71805 - PCMM NOCONNECTION PCEF.....	355
72198 - SMSR SMSC SWITCHED TO PRIMARY.....	356
72199 - SMSR SMSC SWITCHED TO SECONDARY.....	356
72210 - PCMM REACHED MAX GATES EVENT ID.....	356
72211 - PCMM REACHED MAX GPI EVENT ID.....	357
72501 - SCE CONNECTION LOST.....	357
72549 - SMSR QUEUE FULL.....	358
72559 - SMSR SMSC CONN CLOSED.....	358
72565 - SMSR SMTP CONN CLOSED.....	358
72703 - RADIUS SERVER START FAILED.....	359
72904 - DIAMETER TOO BUSY.....	359
72905 - RADIUS TOO BUSY.....	359
74000 - POLICY CRITICAL ALARM.....	360
74001 - POLICY MAJOR ALARM.....	360
74002 - POLICY MINOR ALARM.....	360
74020 - DELETE EXPIRE FILES.....	361
74021 - FILE SYNCHRONIZATION FAILURE.....	361
74022 - FILES UPLOADING FAILURE.....	361
74602 - QP Multiple Active In Cluster Failure.....	362
74603 - QP Max Primary Cluster Failure Threshold.....	362
74604 - QP Policy Cluster Offline Failure.....	363
75000 - POLICY LIBRARY LOADING FAILED.....	363
75105 - Mediation SOAP load shedding set a busy state.....	364

75106 - SPR: Create connection to SPR <i>ip-address</i> failed.....	364
75107 - Sync: Backup folder disk quota exceeded. Disk quota: <i>percentage</i> , total usage: space used.....	364
75108 - No space left on device.....	365
75109 - The Mediation Server has achieved 80% of the maximum number of users in SPR.....	365
77904 - BOD PCMM TOO BUSY.....	365
77905 - BOD DIAMETER TOO BUSY.....	366
78000 - ADS CONNECTION LOST.....	366
78001 - RSYNC FAILED.....	366
79002 - SESS_SIZE_REACHED_THRESHOLD	367
79003 - AVERAGE_SESS_SIZE_EXCEED.....	367
79004 - BIND_SIZE_REACHED_THRESHOLD.....	368
79005 - AVERAGE_BIND_SIZE_EXCEED.....	368
79105 - MEDIATION_SOAP_TOO_BUSY.....	368
79106 - SPR_CONNECTION_FAILED.....	369
79107 - MEDIATION_DISK_QUOTA_EXCEED.....	369
79108 - MEDIATION_DISK_NO_SPACE.....	369
79109 - SPR_LICENSE_LIMIT.....	370
80001 - QP DB State Transition.....	370
80002 - QP MySQL Relay Log Dropped.....	370
80003 - QP MySQL Database Level Advertisement.....	371
82704 - BINDING RELEASE TASK.....	371
84004 - POLICY INFO EVENT.....	372
86001 - APPLICATION IS READY.....	372
86100 - CMP USER LOGIN.....	372
86101 - CMP USER LOGIN FAILED.....	373
86102 - CMP USER LOGOUT.....	373
86200 - CMP USER PROMOTED SERVER.....	373
86201 - CMP USER DEMOTED SERVER.....	374
86300 - SH ENABLE FAILED.....	374
86301 - SH DISABLE FAILED.....	374

Appendix A: Possible Result Codes during Rx-to-PCMM operation.....	376
Error Codes and Conditions	377
Glossary.....	379

List of Tables

Table 1: Admonishments.....	33
Table 2: Error Code and Meaning - Alarms 70010/70011.....	340
Table 3: PCMM Error codes to Diameter Result-Codes mapping.....	377
Table 4: Non-PCMM Error Conditions to Diameter Result-Codes Mapping.....	378

Chapter 1

Introduction

Topics:

- *About this Guide.....32*
- *How This Guide Is Organized.....32*
- *Scope and Audience.....32*
- *Documentation Admonishments.....33*
- *Customer Care Center.....33*
- *Emergency Response.....36*
- *Related Publications.....36*
- *Locate Product Documentation on the Customer Support Site.....37*

Introduction provides a content overview of this guide with a brief summary about incidents, notifications, and the ID ranges for alarms and events. It also includes Tekelec contact information and how to locate product documentation on the Tekelec Customer Support site.

About this Guide

The *Policy Management Troubleshooting Reference* compiles all available notifications, including any alarms or events generated by the system or a Policy action. Alarms alert an operator to action, while events provide information about an expected incident and can be used for debugging purposes. These notifications are sent from different areas of the Policy Management system and are stored for active viewing or historical purposes.

The *Policy Management Troubleshooting Reference* provides all available notifications that do not generate an alarm. Notifications use a 3-, 4-, or 5-digit ID, such as 401, 1683, or 10001.

Alarms and events are grouped under an ID range, which is associated with the type of alarm or event:

- 31000 - 32700 Tekelec Platform
- 70000 - 70999 QBus Platform (QP)
- 71000 - 89999 Policy Server

How This Guide Is Organized

The information in this guide is presented in the following order:

- *Introduction*
- *Incidents, Notifications, and Logs Overview*
 - *About Incidents*
 - *About Notifications*
 - *About Logs*
- *Trace Log Notifications*
- *Alarms and Events*
 - *Alarms formatting information*
 - *Alarm and Event Severity Levels*
 - *Platform (31000-32700)*
 - *QBus Platform (70000-70999)*
 - *Policy Server (71000-89999)*

Scope and Audience

This guide is intended for trained and qualified system operators and administrators who are responsible for managing a Policy Management system.

Documentation Admonishments

Admonishments are icons and text throughout this manual that alert the reader to assure personal safety, to minimize possible service interruptions, and to warn of the potential for equipment damage.

Table 1: Admonishments

Icon	Description
 DANGER	Danger: (This icon and text indicate the possibility of <i>personal injury</i> .)
 WARNING	Warning: (This icon and text indicate the possibility of <i>equipment damage</i> .)
 CAUTION	Caution: (This icon and text indicate the possibility of <i>service interruption</i> .)
 TOPPLE	Topple: (This icon and text indicate the possibility of <i>personal injury</i> and <i>equipment damage</i> .)

Customer Care Center

Oracle's Tekelec Customer Care Center is your initial point of contact for all product support needs. A representative takes your call or email, creates a Customer Service Request (CSR) and directs your requests to the Technical Assistance Center (TAC). Each CSR includes an individual tracking number. Together with TAC Engineers, the representative will help you resolve your request.

The Customer Care Center is available 24 hours a day, 7 days a week, 365 days a year, and is linked to TAC Engineers around the globe.

TAC Engineers are available to provide solutions to your technical questions and issues 7 days a week, 24 hours a day. After a CSR is issued, the TAC Engineer determines the classification of the trouble. If a critical problem exists, emergency procedures are initiated. If the problem is not critical, normal support procedures apply. A primary Technical Engineer is assigned to work on the CSR and provide a solution to the problem. The CSR is closed when the problem is resolved.

Technical Assistance Centers are located around the globe in the following locations:

Related - Global

Email (All Regions): support@tekelec.com

- **USA and Canada**

Phone:

1-888-367-8552 (toll-free, within continental USA and Canada)

1-919-460-2150 (outside continental USA and Canada)

TAC Regional Support Office Hours:

8:00 a.m. through 5:00 p.m. (GMT minus 5 hours), Monday through Friday, excluding holidays

- **Caribbean and Latin America (CALA)**

Phone:

+1-919-460-2150

TAC Regional Support Office Hours (except Brazil):

10:00 a.m. through 7:00 p.m. (GMT minus 6 hours), Monday through Friday, excluding holidays

- **Argentina**

Phone:

0-800-555-5246 (toll-free)

- **Brazil**

Phone:

0-800-891-4341 (toll-free)

TAC Regional Support Office Hours:

8:00 a.m. through 5:48 p.m. (GMT minus 3 hours), Monday through Friday, excluding holidays

- **Chile**

Phone:

1230-020-555-5468

- **Colombia**

Phone:

01-800-912-0537

- **Dominican Republic**

Phone:

1-888-367-8552

- **Mexico**

Phone:

001-888-367-8552

- **Peru**

Phone:

0800-53-087

- **Puerto Rico**

Phone:

1-888-367-8552

- **Venezuela**

Phone:

0800-176-6497

- **Europe, Middle East, and Africa**

Regional Office Hours:

8:30 a.m. through 5:00 p.m. (GMT), Monday through Friday, excluding holidays

- **Signaling**

Phone:

+44 1784 467 804 (within UK)

- **Software Solutions**

Phone:

+33 3 89 33 54 00

- **Asia**

- **India**

Phone:

+91-124-465-5098 or +1-919-460-2150

TAC Regional Support Office Hours:

10:00 a.m. through 7:00 p.m. (GMT plus 5 1/2 hours), Monday through Saturday, excluding holidays

- **Singapore**

Phone:

+65 6796 2288

TAC Regional Support Office Hours:

9:00 a.m. through 6:00 p.m. (GMT plus 8 hours), Monday through Friday, excluding holidays

Emergency Response

In the event of a critical service situation, emergency response is offered by Oracle's Tekelec Customer Care Center 24 hours a day, 7 days a week. The emergency response provides immediate coverage, automatic escalation, and other features to ensure that the critical situation is resolved as rapidly as possible.

A critical situation is defined as a problem with the installed equipment that severely affects service, traffic, or maintenance capabilities, and requires immediate corrective action. Critical situations affect service and/or system operation resulting in one or several of these situations:

- A total system failure that results in loss of all transaction processing capability
- Significant reduction in system capacity or traffic handling capability
- Loss of the system's ability to perform automatic system reconfiguration
- Inability to restart a processor or the system
- Corruption of system databases that requires service affecting corrective actions
- Loss of access for maintenance or recovery operations
- Loss of the system ability to provide any required critical or major trouble notification

Any other problem severely affecting service, capacity/traffic, billing, and maintenance capabilities may be defined as critical by prior discussion and agreement with Oracle's Tekelec Customer Care Center.

Related Publications

The Policy Management product set includes the following publications, which provide information for the configuration and use of Policy Management products in the following environments:

Cable

- *Feature Notice*
- *Cable Release Notes*
- *Roadmap to Hardware Documentation*
- *CMP Cable User's Guide*
- *Troubleshooting Reference*
- *SNMP User's Guide*
- *OSSI XML Interface Definitions Reference*
- *Platform Configuration User's Guide*
- *Bandwidth on Demand Application Manager User's Guide*
- *PCMM specification PKT-SP-MM-I06* (third-party document, used as reference material for PCMM)

Wireless

- *Feature Notice*
- *Wireless Release Notes*
- *Roadmap to Hardware Documentation*
- *CMP Wireless User's Guide*

- *Multi-Protocol Routing Agent User's Guide*
- *Troubleshooting Reference*
- *SNMP User's Guide*
- *OSSI XML Interface Definitions Reference*
- *Analytics Data Stream Reference*
- *Platform Configuration User's Guide*
- *Message Distribution Function Reference*

Wireline

- *Feature Notice*
- *Wireline Release Notes*
- *Roadmap to Hardware Documentation*
- *CMP Wireline User's Guide*
- *Troubleshooting Reference*
- *SNMP User's Guide*
- *OSSI XML Interface Definitions Reference*
- *Platform Configuration User's Guide*

Locate Product Documentation on the Customer Support Site

Oracle customer documentation is available on the web at the Oracle Technology Network (OTN) site, <http://docs.oracle.com>. You do not have to register to access these documents. Viewing these files requires Adobe Acrobat Reader, which can be downloaded at www.adobe.com.

1. Log into the Oracle Customer Support site at <http://docs.oracle.com>.
2. Under **Applications**, click the link for **Communications**.
The **Oracle Communications Documentation** window opens with Tekelec shown near the top.
3. Click **Oracle Communications Documentation for Tekelec Products**.
4. Navigate to your Product and then the Release Number, and click the **View** link (the **Download** link will retrieve the entire documentation set).
5. To download a file to your location, right-click the PDF link and select **Save Target As**.

Chapter 2

Incidents, Notifications, and Logs Overview

Topics:

- *About Incidents.....39*
- *About Notifications.....39*
- *About Logs.....39*

An incident is an occurrence in the system that was triggered by the system or a policy action. An incident sends a notification, which is a message about the incident, to a log so it can be tracked and stored to be viewed by the operator.

Incidents, Notifications, and Logs Overview describes the concepts of incidents, notifications, and logs, and provides a procedure for configuring log settings.

About Incidents

There are two types of incidents:

- **System incident:** an occurrence in the system, such as establishing a connection to a remote server. The system incident is further divided into platform-level and application-level incidents. Platform-level system incidents send alarms and events; application-level system incidents send trace log notifications, and in some cases, alarms and events.
- **Policy Action incident:** Occurs when an operator uses policy actions to generate notifications based on policy execution. Policy Action incidents can send trace log notifications, syslog notifications, and alarms and events.

The incident definition contains details about all notifications, such as trace log severity, message text, and alarm/event information.

Incidents can generate notifications. An example incident is "establishing a connection to a remote server." Some incidents can generate more than one type of notification -- for example, a trace log notification and an alarm. The ID indicates the source of the alarm or event as shown in the ID ranges below:

- 31000 - 32700 Tekelec Platform alarms and events
- 70000 - 70999 QBus Platform (QP) alarms and events
- 71000 - 79999 Policy Server alarms
- 80000 - 89999 Policy Server events

About Notifications

A notification is a message sent by an incident. There are various logging mechanisms that receive these notifications, as well as an alarm system to notify operators of issues that may need action. Notifications may generate a trace log, syslog, and/or an alarm or event.

About Logs

Log files receive various types of notifications and log them for historical purposes.

There are several types of logs:

- Trace Log
- Syslog
- SMPP Log
- SMTP Log

Trace Log

The Trace Log is an application-level system notification used to trace and debug application-level incidents, and is available on the Logs tab of the Policy Server Configuration (Administration) page and the MRA Configuration (Administration) page. The Trace Log page displays:

- General application notifications
- Policy Application notifications
- Policy server notifications
- Policy action notifications that generate Trace Log entries

The log entries provide an incident ID and a severity level of Warning, Info, or Debug.

Each Policy server has a distinct and separate set of Trace Log notifications for incidents that occurred on that server. Use the CMP to view the Trace Log notifications from a different server in a cluster. Select the appropriate server from the list at the top of the Trace Log Viewer page.

Syslog

The Syslog receives notifications only from Policy actions. Syslog notifications are directed to a remote syslog host, and the log supports five destinations. Syslog info appears on the MPE Logs tab of the MPE Configuration page.

The SMPP Log

The SMPP log is a policy action-generated notification that contains all Short Message Peer-to-Peer Protocol notifications sent by the MPE device as well as delivery receipts from a Short Message Service Center (SMSC) server. In SMPP or XML mode, SMPP info appears on the MPE Logs tab of the MPE Configuration page, under the **SMS Log Configuration** heading. You can configure the severity of messages that are written to the SMPP log as well as set a forwarding address.

The SMTP Log

The SMTP log contains all Simple Mail Transfer Protocol messages sent by the MPE device, as well as any ACK messages received from a mail transfer agent (MTA). In SMPP or XML mode, SMTP Log info appears on the MPE Logs tab of the MPE Configuration page, under the **SMTP Log Configuration** heading. You can configure the severity of messages that are written to the SMTP log.

Configuring Log Settings

From the **Logs** tab you can configure the log settings for the servers in a cluster. To configure log settings:

1. From the **Logs** tab, click **Modify**.
The editable fields open in the work area.
2. In the **Modify Trace Log Settings** section of the page, configure the Trace Log Level.

This setting indicates the minimum severity of messages that are recorded in the trace log. These severity levels correspond to the syslog message severities from RFC 3164. Adjusting this setting

allows new notifications, at or above the configured severity, to be recorded in the trace log. The levels are:

- **Emergency** — Provides the least amount of logging, recording only notification of events causing the system to be unusable.
- **Alert** — Action must be taken immediately in order to prevent an unusable system.
- **Critical** — Events causing service impact to operations.
- **Error** — Designates error events which may or may not be fatal to the application.
- **Warning** (the default) — Designates potentially harmful situations.
- **Notice** — Provides messages that may be of significant interest that occur during normal operation.
- **Info** (the default) — Designates informational messages highlighting overall progress of the application.
- **Debug** — Designates information events of lower importance.



Caution: Before changing the default logging level, consider the implications. Lowering the trace log level setting from its default value (for example, from "Warning" to "Info") causes more notifications to be recorded in the trace log and can adversely affect performance. On the other hand, raising the log level setting (for example, from "Warning" to "Alert") causes fewer notifications to be recorded in the trace log, and could cause you to miss important notifications.

3. For Wireline only, configure the maximum trace log file size (in KB).

The system will maintain up to this number of trace log files, removing old files when it reaches this limit. The choices are 512, 1,024, 2,048, 4,096, 8,192, 16,384, or 32,678 KB. The default is 2,048 KB.

4. For Wireline only, configure the maximum trace log file count. The system manages rotation of log files automatically.

The range is 2–8 files. The default is 8 files.

5. For Wireline, only, configure the trace log forwarding settings. You can direct notifications to up to five remote systems. For each system, enter the following:

- a) **Hostname/IP Addresses** — Remote system hostname or IPv4 address.



Caution: Forwarding addresses are not checked for loops. If you forward events on System A to System B, and then forward events on System B back to System A, a message flood can result, causing dropped packets.

- b) **Severity** — Filters the severity of notifications that are written to the log:

- **Emergency** — Provides the least amount of logging, recording only notification of events causing the system to be unusable.
- **Alert** — Action must be taken immediately in order to prevent an unusable system.
- **Critical** — Events causing service impact to operations.
- **Error** — Designates error events which may or may not be fatal to the application.
- **Warning** — Designates potentially harmful situations.
- **Notice** — Provides messages that may be of significant interest that occur during normal operation.
- **Info** (the default) — Designates informational messages highlighting overall progress of the application.

- **Debug** — Designates information events of lower importance.

6. For Wireline only, In the **Modify Log Forwarding Configuration** section of the page, select **Enable Policy Log Forwarding** to forward the policy log to remote locations.

7. In the **Modify Policy Syslog Forwarding Settings** section of the page, configure the syslog forwarding settings. You can direct notifications to up to five remote systems. For each system, enter the following:

- a) **Hostname/IP Addresses** — Remote system hostname or IPIPV4 address.

Caution: Forwarding addresses are not checked for loops. If you forward events on System A to System B, and then forward events on System B back to System A, a message flood can result, causing dropped packets.

- b) **Facility** — Select from Local0 (the default) to Local7.
- c) **Severity** — Filters the severity of notifications that are written to syslog:
 - **Emergency** — Provides the least amount of logging, recording only notification of events causing the system to be unusable.
 - **Alert** — Action must be taken immediately in order to prevent an unusable system.
 - **Critical** — Events causing service impact to operations.
 - **Error** — Designates error events which may or may not be fatal to the application.
 - **Warning** (the default) — Designates potentially harmful situations.
 - **Notice** — Provides messages that may be of significant interest that occur during normal operation.
 - **Info** (the default) — Designates informational messages highlighting overall progress of the application.
 - **Debug** — Designates information events of lower importance.

8. In the **Modify SMS Log Settings** section of the page (which only appears when in SMPP mode), configure the following:

- a) **SMPP Log Level** — Indicates the severity of messages that are written to the file SMPP.log. Adjusting this setting allows any new events, at or above the configured severity, to be written to the SMPP log.

Note: You can optionally enable the syslog forwarding address for new logs.

Valid levels are:

 - **OFF** — Turns off logging.
 - **ERROR** — Designates error events which may or may not be fatal.
 - **WARN** (the default) — Designates potentially harmful situations.
 - **INFO** — Designates informational messages highlighting overall progress.
 - **DEBUG** — Designates information events of lower importance.
 - **TRACE** — Designates informational events of very low importance.
 - **ALL** — Records all logging levels.

b) **SMPP Log Forwarding IP Addresses** — You can forward SMPP.log entries to multiple syslog servers.

9. In the **Modify SMTP Log Settings** section of the page (which only appears when in SMPP mode), configure the **SMTP Log Level**.

This setting indicates the minimum severity of messages that are recorded in the SMTP log. These severity levels correspond to the syslog message severities from RFC 3164. Adjusting this setting allows new notifications, at or above the configured severity, to be recorded in the SMTP log. The levels are:

- **OFF** — Turns off logging.
- **ERROR** — Designates error events which may or may not be fatal.
- **WARN** (the default) — Designates potentially harmful situations.
- **INFO** — Designates informational messages highlighting overall progress.
- **DEBUG** — Designates information events of lower importance.
- **TRACE** — Designates informational events of very low importance.
- **ALL** — Records all logging levels.

10. In the **Modify Session Synchronization Log Settings** section of the page, select **Enable Session Synchronization Log** to enable the session synchronization log.

The **Number of Session Synchronization Log Files** field appears. Enter the number of session synchronization log files. The system manages rotation of log files automatically. The range is 2–10 files. The default is 10 files.

11. When you finish, click **SaveOK** (or **Cancel** to discard your changes).

The log configurations are changed.

Chapter 3

Trace Log Notifications

Topics:

- *Expanded List.....45*

This section lists Trace Log notifications. The incident ID number is also the Trace Log notification ID number. Trace Log notifications may have more than one severity. Each severity is listed with its applicable action. Note that trace log codes for all modes are represented in this list (cable, wireline, and wireless).

Expanded List

1 - Initialized the scheduled tasks Event Log

Description: The CMP scheduler has initialized its interface to the event log.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

2 - OSSI collector establishing connection to *type*

Description: The OSSI Collector is trying to connect to a given database address.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

3 - Error occurred during OSSI collector run: *type*

Description: The application that collects information from the OSS has experienced an error.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the OSS database is online and available.

4 - Starting OSSI collector run

Description: The OSSI Collector task is starting its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

5 - OSSI collector run completed

Description: The OSSI Collector task has finished its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

6 - OSSI collector run aborted

Description: The application that collects information from the OSS has been cancelled due to user intervention.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

7 - OSSI collector error reading configuration file: *file-name*

Description: Specified configuration file is not present or not readable.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

8 - OSSI collector established connection

Description: The OSS Collector task has successfully connected to the OSS database.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

9 - OSSI collector could not establish connection *host port*

Description: The application that collects information from the OSS cannot connect to the OSS network element(s).

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the OSS database is online and available.

10 - OSSI collector did not find CMTS nodes for *CMTS*

Description: The OSSI Collector did not find CMTS nodes for CMTS.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

11 - OSSI collector did not find subscribers for CMTS *node*

Description: The OSSI Collector did not find subscribers for CMTS node.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

12 - OSSI collector did not find configuration parameter: *parameter-name*

Description: The given parameter (e.g., host name, username, or password) for the OSSI Collector task was not configured.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

13 - Error validating field

Description: The OSSI Collector task retrieved a field from the OSS database that's invalid (e.g., a malformed subnet address).

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check the field's value in the OSS database.

14 - Data Collector started

Description: The Data Collector has initialized and started.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

21 - Starting Subnet SNMP Collector task

Description: The Subnet SNMP Collector task is starting its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

22 - SNMP timeout while collecting Subnet data from CMTS *name*

Description: The application requesting the subnet data from the network element did not receive a response from the identified network element.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the network element is online and available.

23 - SNMP error *type* while collecting Subnet data from CMTS *name*

Description: The application requesting the subnet data from the network element received an unexpected response.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the network element is online and available.

24 - Skipping Subnet collection from CMTS *name* because the SNMP community string is empty

Description: The Subnet SNMP Collector task cannot poll the given CMTS because the SNMP community string is not configured for it.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

25 - Classifier not active for subscribers request ignored

Description: Classifier not active for subscribers request ignored.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

26 - Classifier already active for exit subscriber IP

Description: Classifier already active for exit subscriber IP.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

38 - Subnet SNMP Collector Task Status CMTSs

Processed: n , Failures: n , Subnets Discovered: n , Added: n , Updated: n , Removed: n , Elapsed time: t sec.

Description: The number of CMTSs processed and the number of subnets discovered by the Subnet SNMP Collector task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

39 - Finishing Subnet SNMP Collector task

Description: The Subnet SNMP Collector task finished its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

41 - Starting Service Class SNMP Collector task

Description: The Service Class SNMP Collector task is starting its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

42 - SNMP timeout while collecting Service Class data from CMTS *name*

Description: The application requesting the service class data from the network element did not receive a response from the identified network element.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the network element is online and available.

43 - SNMP error *type* while collecting Service Class data from CMTS *name*

Description: The application requesting the service class data from the network element received an unexpected response.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the network element is online and available.

44 - Skipping Service Class collection from CMTS *name* because the SNMP community string is empty

Description: The Service Class SNMP Collector task cannot poll the given CMTS because the SNMP community string is not configured for it.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

50 - HTTP request success for IP *address*

Description: HTTP request is successful for IP address.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

58 - Service Class SNMP Collector Task Status

CMTSs Processed: n , Failures: n ; Service Classes Discovered: n , Added: n , Updated: n , Removed: n , Elapsed time: t sec

Description: The number of CMTSs processed and the number of service classes discovered by the Service Class SNMP Collector task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

59 - Finishing Service Class SNMP Collector task

Description: The Service Class SNMP Collector task finished its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

61 - Starting Subscriber SNMP Collector task

Description: The Subscriber SNMP Collector task is starting its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

62 - SNMP timeout while collecting Subscriber data from CMTS *name*

Description: The application requesting the subscriber data from the network element did not receive a response from the identified network element.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the network element is online and available.

63 - SNMP error *type* while collecting Subscriber data from CMTS *name*

Description: The application requesting the subscriber data from the network element received an unexpected response.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the network element is online and available.

64 - Invalid cable modem MAC address *MAC-address* retrieved from CMTS *name*

Description: The Subscriber SNMP Collector task retrieved an invalid cable modem MAC address from the CMTS.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check the field's value in the network element.

65 - Invalid cable modem IP address *ip-address* for MAC *MAC-address* retrieved from CMTS *name*

Description: The Subscriber SNMP Collector task retrieved an invalid cable modem IP address from the CMTS.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check the field's value in the network element.

66 - Invalid CPE IP address *ip-address* behind cable modem *MAC-address* retrieved from CMTS *name*

Description: The Subscriber SNMP Collector task retrieved an invalid CPE IP address from the CMTS.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check the field's value in the network element.

68 - Skipping Subscriber collection from CMS *name* because the SNMP community string is empty

Description: The Subscriber SNMP Collector task cannot poll the given CMTS because the SNMP community string is not configured for it.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

70 - SOAP request failure

Description: SOAP request fails 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

78 - Subscriber SNMP Collector Task Status

CMTSs Processed: *n*, Failures: *n*; Accounts Discovered: *n*, Added: *n*, Updated: *n*, Removed: *n*, Elapsed time: *t* sec.

Description: The number of CMTSs processed and the number of accounts discovered by the Subscriber SNMP Collector task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

79 - Finishing Subscriber SNMP Collector task

Description: The Subscriber SNMP Collector task finished its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

80 - SOAP request success for IP address

Description: SOAP request is successful for IP address (variable {0}).

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

81 - Starting CMTS Distributor task

Description: The CMTS Distributor task is starting its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

82 - Error while sending CMTS data to Policy Server: *name*

Description: The CMP cannot connect to the policy server to push the network element data.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

98 - CMTS Distributor Task Status Policy Server

CMTS processed: *n*, Added: *n*, Updated: *n*, Removed: *n*, Elapsed time: *t* sec.

Description: The number of CMTSs processed by the CMTS Distributor task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

99 - Finishing CMTS Distributor task

Description: The CMTS Distributor task finished its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

100 - Established policy server connection to *IP address*

Description: Established policy server connection is successful for IP address.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

101 - Starting Subscriber Distributor task

Description: The Subscriber Distributor task is starting its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

102 - Error while deleting Subscriber data from Policy Server: *name*

Description: The CMP cannot connect to the policy server to modify the subscriber data.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

103 - Error while updating CMTS data on Policy Server: *name*

Description: The CMP cannot connect to the policy server to modify the network element data.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

104 - Error while sending *Reconfigure* message to Policy Server: *name*

Description: The CMP cannot communicate a new configuration for the policy server.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

105 - Error while sending *Refresh Channels* message to Policy Server: *name*

Description: Communication problem between CMP/management agent and the policy server during a data refresh of a channel info change request.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

106 - Error while sending *Refresh Accounts* message to Policy Server: *name*

Description: Request for change to account information failed sending to policy server from the CMP.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

107 - Error while sending Tier data to Policy Server: *name*

Description: The subscriber/account tier information configured in the CMP did not push successfully to the policy server.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

108 - Error while sending Channel data to Policy Server: *name*

Description: The channel information for the respective network element was not communicated to the appropriate policy server from the CMP.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the policy server is online and available.

118 - Subscriber Distributor Task Status

CMTSs: n , Accounts processed: n , Added: n , Updated: n , Removed: n , Elapsed time: t sec.

Description: The number of CMTSs and accounts processed by the Subscriber Distributor task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

119 - Finishing Subscriber Distributor task

Description: The Subscriber Distributor task finished its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

121 - Starting OSSI Distributor task

Description: The OSSI Distributor task is starting its scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

122 - Error occurred during OSSI distributor run: *type*

Description: Failed to send data to the Management Agents.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#)

123 - OSSI distributor run aborted

Description: A user cancelled the distribution of the OSS information within the CMP to the appropriate Management Agents.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

124 - Error connection to Remote MA: *host-name*

Description: The CMP could not establish a connection to the Management Agent.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the Management Agent is online and available.

125 - Error updating Accounts to remote MA:*host-name*

Description: The CMP cannot connect to the Management Agent in order to update account information..

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the Management Agent is online and available.

126 - Error updating CMTSs to remote MA: *host-name*

Description: The CMP cannot connect to the Management Agent in order to update the network element information.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the Management Agent is online and available.

127 - Error updating Tiers to remote MA: *host-name*

Description: The CMP cannot connect to the Management Agent in order to update the subscriber tier information.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the Management Agent is online and available.

128 - Error updating Entitlements to remote MA: *host-name*

Description: The CMP cannot connect to the Management Agent in order to update subscriber entitlement information.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the Management Agent is online and available.

139 - Finishing OSSI Distributor task

Description: The OSSI Distributor task is completing a scheduled run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

141 - Starting CMTS MA Collector task

Description: The CMTS MA Collector task is starting its run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

142 - Error while collecting CMTS data from Management Agent: *name*

Description: The CMP cannot collect the assigned network element information from the Management Agent.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check that the Management Agent is online and available.

157 - CMTS MA Collector task status

MA, CMTS processed: *n*, Updated: *n*, Skipped: *n*, Elapsed time: *t* sec.

Description: The CMP displays the CMTS MA Collector task status.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

158 - CMTS MA Collector Task Status

MA processed: n , CMTS processed: n , Updated: n , Skipped: n , Elapsed time: t sec.

Description: The CMTS MA Collector task results are displayed.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

159 - Finishing CMTS MA Collector Task

Description: The CMTS MA Collector task is ending.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

161 - Starting PCMM Routing Distribution task

Description: The PCMM routing distribution task is starting.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

177 - PCMM Distribution Task Status

MPE: n , Status: $status-number$, Elapsed time: t sec.

Description: The PCMM distribution task displays the status of the MPE.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

178 - PCMM Distribution Task Status

MPEs processed: n , Updated: n , Failed: n , Elapsed time: t sec.

Description: The CMP displays the status of the PCMM Distribution task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specific cause.

179 - Finishing PCMM Routing Distribution task

Description: The PCMM routing distribution task is ending.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

180 - Task *task - name* was run manually

Description: The operator ran the specified task manually.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

If the message indicates any failures, check the system logs for specified cause.

201 - Start Healthchecker task

Description: HealthChecker task is starting its run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

205 - Apply RC configuration to MPE (HostName: *hostname*) executed by *user* \n Total execution time *time* millisecond

Description: Apply RC Configuration to MPE

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: RC

Group: Resource Controller Task

Recovery:

No action required.

219 - Finishing Healthchecker task

Description: Healthchecker task is completing its run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

220 - Starting AlertAging task

Description: The AlertAging task is starting its run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

239 - Finishing AlertAging task

Description: The AlertAging task is ending its run.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

240 - Starting OM Statistics task

Description: Starting OM Statistics task

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

241 - OM Statistics collection complete and data is available for request

Description: Data has been saved and is available for OSSI requests, prior to final cleanup tasks.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

243 - OM Statistics Task was unable to connect to MPE. UID: *UID1\nUID2*

Description: OM Statistics Task was unable to connect to MPE. UID: *UID1\nUID2*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

244 - OM Stats task missing stats

Description: OM Statistics Task was unable to retrieve statistics from MPE: *mpe* at hostname: *hostname* 1; *error*: 2.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

245 - OM Stats task missing unable to retrieve MPE from the database

Description: OM Statistics Task was unable to retrieve MPE from the database. UID: 0

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

247 - OM Statistics Task error detected while retrieving statistics from MPE

Description: OM Statistics Task error detected while retrieving statistics from MPE: 0. Request attempt: 1

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

248 - OM Statistics Task failed to retrieve statistics from MPE: *name*

Description: OM Statistics Task failed to retrieve statistics from MPE: *0*. Request attempt: *1*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

249 - OM Statistics retrieved an incomplete set of statistics from MPE

Description: OM Statistics retrieved an incomplete set of statistics from MPE: *mpe ID*. Request Attempt: *# of requests*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

250 - OM Statistics Task failed to retrieve proxy from MPE

Description: OM Statistics Task failed to retrieve proxy from MPE: *0*. Request attempt: *1*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

251 - OM Statistics Task error retrieving statistics from MPE: *name* Request attempt: *n*

Error: *text*

Description: OM Statistics Task error retrieving statistics from MPE: *name*. Request attempt: *n* Error: *text*

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

252 - BoD Database backup failed due to no IP address

Description: BoD database back failed due to no IP address

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

253 - BoD Database backup started

Description: BoD Database backup started.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

254 - BoD Database backup finished

Description: BoD Database backup finished running.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

256 - OM Statistics Task completed successfully

Description: OM Statistics task completed successfully.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Collection Task

Recovery:

No action required.

257 - OM Statistics task completed with a warning

Description: OM Statistics Task completed with a warning; *warning message*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

258 - OM Statistics task failed

Description: OM Statistics task failed: *failure message*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

259 - Finishing OM Statistics task

Description: Finishing OM Statistics task.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

260 -The BoD cluster has reinitialized

Description: The BoD cluster has reinitialized. The indicated blade is now the primary blade.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

261 - Bad wget exit status *Status Code* for MPE Name

Description: Invalid status occurred on exit from wget.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

276 - Statistics Rsync Cleanup task completed successfully

Description: Statistics Rsync Cleanup task completed successfully.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

278 - Statistics Rsync Cleanup Task failed

error-msg

Description: Statistics Rsync Cleanup Task failed.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

279 - Finished Statistics Rsync Cleanup Task

Description: Finished Statistics Rsync Cleanup Task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

280 - Starting Subscription Aging Task

Description: Starting Subscription Aging Task

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

289 - Finishing Subscription Aging Task

Description: Finishing Subscription Aging Task

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

300 - BoD sending

Description: The BoD is sending using the following variables *0, 1, or 2*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

No action required.

301 - BoD Received Message

Description: The BoD has received *Device-Watchdog-Request (DWR)* message from *origin host*

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

302 - BoD request to 1 has timed out

Description: The BoD request to 1 has timed out.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

303 - Starting quota aging task

Description: Starting quota aging task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

304 - Finishing quota aging task

Description: Finishing quota aging task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

310 - Incorrect XML syntax in PCMM

Description: Incorrect XML syntax in PCMM

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

311 - Missing required fields for services

Description: Missing required fields for services {0}\n*Details:*\n{1}

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

312 - Incorrect XML syntax in Diameter services file

Description: Incorrect XML syntax in Diameter services file {0}\n{1}.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

313 - Services or service indexes already exists

Description: Services or service indexes already exists *n**Details:*\n{0}.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

314 - Same services or service indexes used multiple times

Description: Same services or service indexes used multiple times *nDetails*: \n{0}.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

400 - MAC Translation failed due to connection failure for session ID

Description: MAC Translation failed due to connection failure for session ID {0}: MAC address: {1} {2}

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

401 - Starting Stats Files Generator Task

Description: Starting Stats Files Generator Task in the DC process, which generates stats files from OSSI query.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

402 - Stats Files Generator Task completed successfully

Description: Stats Files Generator Task was completed successfully in the DC process.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

403 - Stats Files Generator Task failed #1, 2, 3, or 4

Description: Error log indicating stats files generator task #1, 2, 3, or 4 failed. A Warning trace log is generated for troubleshooting.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Use content of trace log to troubleshoot error.

404 - Finishing Stats Files Generator Task

Description: Info log generated at the completion of a stats files generator task. To verify these stat files, navigate to the local repository defined in this task configuration.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

405 - Stats Files Generator Task was not executed successfully

Description: Stats Files Generator Task was not executed successfully. There is not an enabled and non-empty *Host Name/IP Address* of Stats Files Synchronization Task.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

406 - Sync utility failed to sync stats files to mates. Reason: *reason*

Description: Error log generated when the sync utility failed to sync stats files to mates. The reason for failure is listed in log message.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

1. Based on the failure message, check the server exchange SSH Key in CMP site1 Cluster and site2 Cluster.
2. Check the network connection status to other servers in both Clusters.

407 - Stats Files Generator Task has removed some files which were not synced to remote servers (...)

Description: Warning log generated when a stats files generator task has removed some files which were not synced to remote servers, which includes remote server IP address. Stats files are kept for the period of time defined in the task setting. If these stats files have always been synced to the remote server, this task raises a Warning trace log.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check status of starting stats files synchronization #1,2,3, and 4, and ensure the Enabled stats were configured normally and successfully.

408 - Stats Files Generator task was not configured any stats type

Description: Stats Files Generator Task was not configured any stats type.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

500 - RDR: Start message received for Service Index *index*

Description: RDR: Start message received for Service Index: *index*.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: RDR

Group: RDR

Recovery:

Contact the Tekelec [Customer Care Center](#).

501 - BOD RDR Unmapped Skip

Description: BOD RDR Unmapped Skip

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

502 - *task name* Task completed successfully

Description: Info log generated upon the successful completion of the stats files synchronization for task. The task name suffix number indicates different synchronization tasks.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

503 - *task name* Task failed. \n *error message*

Description: Error log generated when stats files synchronization task fails; cause of failure is listed in log title. The task name suffix number indicates the synchronization task during which the failure occurred.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Use content of trace log to troubleshoot error.

504 - Finishing *task name* Task

Description: Info log generated when the stats files synchronization process has finished.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

505 - The Local Repository does not exist, you need to check whether Stats Files Generator Task was executed successfully or not

Description: Error log generated when the local repository does not exist; check whether stats files generator task was executed successfully or not.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Determine whether or not the stats files generator task was executed.

506 - *task name* Task still failed for sync local repository to remote server (IP Address/Hostname) after *retry count* times

Description: Error log generated when a stats files synchronization task fails to sync local repository to a remote server after three retries.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

1. Determine if the remote server supports an SSH protocol connection.
2. Check the network connection status of the remote server.

507 - *task name* Task was successful for sync local repository to remote server (*IP address/Hostname*) after retry *count* times

Description: Warning log generated when a stats files synchronization task successfully syncs the local repository to a remote server after two retries.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Check the network connection status of the remote server.

508 - RDR: Parsing Failed

Description: RDR: Parsing Failed: *ID* from *RDR*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

No action required.

509 - RDR: Dropping RDR Service Index

Description: RDR: Dropping RDR *error message*, Service Index: *index* from RDR.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

No action required.

510 - RDR: Stop message received for Service Index

Description: RDR: Stop message received for Service Index for the following variable 0.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

512 - Dropping RDR bucket

Description: RDR: : Dropping RDR *error message*, Bucket Id: *Bucket ID* from RDR.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

No action required.

513 - RDR: Skipping unmapped RDR, Bucket Id

Description: RDR: Skipping unmapped RDR, Bucket Id: *Bucket ID* from RDR.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

No action required.

514 - RDR: Quota message received for Bucket Id

Description: RDR: Quota message received for Bucket Id *Bucket ID*.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#)

515 - RDR: Quota message processing

Description: RDR: Quota message processing variable *variable*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: RDR

Group: RDR

Recovery:

Contact the Tekelec [Customer Care Center](#)

550 - OSSI XML Interface request initiated

Description: OSSI XML Interface request initiated by variable *variable*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSSI

Recovery:

No action required.

552 - Error while sending Account data to Policy Server

Description: Error while sending Account data to Policy Server: *policy server*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Subscriber

Recovery:

Contact the Tekelec [Customer Care Center](#).

553 - XML Export results

Description: XML export *type*: Export executed by *username* \n\ Status *success* \n Total export count: *total count*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSSI

Recovery:

No action required.

554 - XML export failure

Description: XML export type Export executed by *username*. \n *Status: success* \n *Failure Log Message:error msg.*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSS1

Recovery:

No action required.

555 - XML request complete

Description: OSS1 XML Interface request completed in *execution time* by:*username* , *results of import*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSS1

Recovery:

No action required.

600 - Invalid login threshold

Description: User "*username*" (1) has hit the invalid login threshold.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: Subscriber

Recovery:

Contact the Tekelec [Customer Care Center](#).

620 - Push of pending account updates initiated

Description: Push of pending account updates initiated by: *username*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Subscriber

Recovery:

No action required.

621 - Push done

Description: Push of pending account updates completed by: *username* \n *status* \n Total execution time *execution time*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Subscriber

Recovery:

No action required.

625 - Subscriber accounts initiated

Description: Subscriber accounts initiated by: *username* for *group*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Subscriber

Recovery:

No action required.

626 - Re-application of subscriber accounts completed

Description: Reapply of subscriber accounts completed by: *username* for MPE *mpe name* \n *status* \n Total execution time *execution time*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Subscriber

Recovery:

No action required.

653 - Apply name to MPE

Description: Apply change of: 1 to MPE (HostName:0) From 2 to 3.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Configuration

Recovery:

No action required.

1001 - CMTS conn lost clear

Description: PCMM: Estblished connection to 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

Contact the Tekelec [Customer Care Center](#).

1002 - CMTS conn lost

Description: PCMM: Lost connection to 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

Contact the Tekelec [Customer Care Center](#).

1003 - AM conn lost clear

Description: PCMM: Connection accepted from AM 0.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

No action required.

1004 - PCMM: Lost connection with AM *id*, Clear and Set

Description: The MPE device lost a connection from the specified application manager (AM) or upstream policy server (PCMM Router).

Note: Because of protocol limitations, the MPE device cannot distinguish between an AM and a PCMM router, so it always identifies the incoming connection as an AM.

Severity: Error, Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: PCMM

Recovery:

1. Check availability of the AM.
2. Check the AM log for a recent failover or other operation(s) that can interrupt communications.
3. If the AM has not failed, make sure the path from the AM to the MPE device (port 3918) is operational.

1010 - PCMM: Received *msg-type* from AM *id**msg-contents***Description:** The specified message type was received from the specified AM (or upstream policy server).**Severity:** Info**Notification:** Trace Log**Alarm:** No**Trap:** No**Server:** MPE**Group:** PCMM**Recovery:**

No action required.

1011 - PCMM: Sending *msg-type* to *id**msg-contents***Description:** The specified message type was sent to the specified CMTS (or downstream policy server).**Severity:** Info**Notification:** Trace Log**Alarm:** No**Trap:** No**Server:** MPE**Group:** PCMM**Recovery:**

No action required.

1012 - PCMM: Received message**Description:** PCMM: Received 0 from 1 and 2.**Severity:** Warning**Notification:** Trace Log

Alarm: No

Trap: No

Server: CME

Group: NA

Recovery:

Contact the Tekelec [Customer Care Center](#).

1013 - PCMM: Sending *msg-type* to AM *id*

Description: PCMM: Received 0 from 1 and 2.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Recovery:

Contact the Tekelec [Customer Care Center](#).

1014 - PCMM: Failed (*num attempts*) to send *msg-type* event message to *id*

msg-contents

Description: A PCMM event message could not be transmitted to the specified record keeping server (RKS).

Note: The last attempt that fails is logged as an error. If there are additional retries to be attempted then this is logged as a Warning.

Severity: Warn, Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. Check the configuration and availability of the RKS.
2. Ensure the network path from the MPE device to the RKS is available.

1015 - PCMM: Successfully sent *msg-type* event message to *id*

msg-contents

Description: A PCMM event message was successfully sent to the specified RKS.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Recovery:

No action required.

1016 - PCMM: Failover initiated for RKS *id*, reverting to *id*

Description: The system has lost communication with the primary RKS, and is attempting to establish a connection with the secondary RKS. The identities of both the primary and secondary RKSs are specified.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. Check the configuration and availability of the RKS.
2. Ensure the network path from the MPE device to the RKS is operational.

1017 - Failed (TOO BUSY) to send *msg-type* event message to *id*

msg-contents

Description: The MPE device is unable to send an event message to the specified RKS because the send queue is too full.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE**Group:** PCMM**Recovery:**

This is normal behavior under heavy PCMM load. It can also occur if there is a communication problem with the RKS because the send queue may fill while the retry messages are being sent.

1020 - PCMM: Rejecting *msg-type* - no PEP available for SubID IP; trap will be sent to NM

Description: A PCMM message was received with the specified subscriber IP address but there is no configured CMTS (or downstream policy server) to handle this request.

Note: The request will be rejected with a PCMM error code of 13 (Invalid SubscriberID).

Severity: Warn**Notification:** Trace Log**Alarm:** Yes**Trap:** No**Server:** MPE**Group:** PCMM**Recovery:**

1. Check the configuration of the CMTSs associated with this MPE device. Make sure that there is a CMTS configured with a subnet for the specified subscriber AND make sure that this CMTS is associated with this MPE device.
2. Check the configuration of the AM sending the message to make sure it is sending the request to the correct MPE device.

1021 - PCMM: Rejecting *msg-type* - invalid gate ID *gateid*

Description: A PCMM message was received with a GateID that does not correspond to any sessions in the MPE database. This checking is only performed if the CMP has enabled Gate checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 2 (Unknown GateID).

Severity: Warn**Notification:** Trace Log**Alarm:** Yes**Trap:** No**Server:** MPE**Group:** PCMM**Recovery:**

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the flow of messages between the AM, the MPE device, and the CMTS to determine if there are errors in the message forwarding.

1022 - PCMM: Rejecting *msg-type* - AMID mismatch - request *msg-amid* doesn't match gate MPE-AMID

Description: A PCMM message was received with an AMID that does not match the AMID for the corresponding session in the MPE database. This checking is only performed if the CMP has enabled Gate checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 14 (Unauthorized AMID).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the flow of messages between the AM and the MPE device to determine if there are errors in the message processing.

1023 - PCMM: Rejecting *msg-type* - SubId mismatch - request *msg-id* doesn't match gate *mpe-id*

Description: A PCMM message was received with a Subscriber ID that does not correspond to a provisioned subscriber in the MPE database of known subscribers (CPEs). This checking is only performed if the CMP has enabled Gate checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 13 (Invalid SubscriberID).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the flow of messages between the AM and the MPE device to determine if there are errors in the message processing.

1024 - PCMM: Rejecting *msg-type* - Unrecognized Subscriber *id*

Description: A PCMM message was received with a Subscriber ID that does not correspond to a provisioned subscriber in the MPE database of known subscribers (CPEs). This checking is only performed if the CMP has enabled Subscriber checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 13 (Invalid SubscriberID).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the OSS system you are using to provision subscribers for the MPE device to make sure that this subscriber is provisioned.

1025 - PCMM: Rejecting *msg-type* - Unauthorized AmID *id*

Description: A PCMM message was received with an AMID that does not correspond to any known Application in the MPE device. This checking is only performed if the CMP has enabled AMID checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 14 (Unauthorized AMID).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the application definitions in the CMP and make sure that this AMID is associated with the appropriate application.
3. Make sure that the application is also associated with this MPE device in the CMP.

1026 - PCMM: Rejecting *msg-type* - Unrecognized Service Class Name *name*

Description: A PCMM message was received with a Service Class Name that does not correspond to any service class that is known to exist for the CMTS to which this message is being sent. This checking

is only performed if the CMP has enabled Gate Data checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 11 (Undefined Service Class).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the set of Service Class names that are provisioned for the CMTS in the CMP and make sure that the specified name is included.
3. Make sure the set of Service Class names in the CMP is consistent with the set of values on the actual CMTS.
4. Make sure that the AM is sending the correct value.

1027 - PCMM: Rejecting *msg-type* - Incompatible Envelopes -*env-type* ENV exceeds *env-type* ENV

Description: A PCMM message was received with incompatible Authorized, Reserved and Committed envelopes (QOS parameter specifications). This checking is only performed in the CMP has enabled Gate Data checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 12 (Incompatible Envelope).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the configuration of the AM because this is an indication that it is requesting parameters that violate the protocol specification.

1028 - PCMM: Rejecting *msg-type* - Classifier count exceeds CMTS limit

Description: A PCMM message was received with more classifiers than the provisioned limit for the CMTS to which this message is being sent. This checking is performed only if the CMP has enabled Gate Data checking for the MPE device (by default this is off).

Note: The request will be rejected with a PCMM error code of 15 (Number of Classifiers not Supported).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

1. If you do not want this checking to be performed, disable it in the CMP.
2. Check the Classifier Limit that is provisioned for the CMTS in the CMP and make sure that it is consistent with the actual CMTS.
3. Make sure your AM is configured to make requests that do not exceed the CMTS limit.

1029 - PCMM: Rejecting *msg-type* - I/O Error while sending to *id*

Description: There was no PCMM session connection to the target CMTS (or downstream policy server).

Note: The request will be rejected with a PCMM error code of 255, and a subcode of 211.

Severity: Error

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: PCMM

Recovery:

Check the network connectivity between systems.

1051 - Rejected by Policy

Description: Rejecting 0 - Rejected by Policy \1\.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CME

Group: NA

Recovery:

Contact the Tekelec [Customer Care Center](#).

1101 - DQOS: Established connection to *id*, Clear and Set

Description: A new connection was established to the specified CMTS or downstream policy server.

Severity: Error, Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: DQOS

Recovery:

Contact the Tekelec [Customer Care Center](#).

1102 - DQOS: Lost connection to *id*

Description: The connection was lost to the specified CMTS or downstream policy server.

Severity: Error, Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: DQOS

Recovery:

1. Check configuration and availability of the network element.
2. Check the network element for a reboot or other service interruption.
3. If the element has not failed, make sure the network path from the MPE device to the element (port 3918) is operational.

1104 - DQOS: Lost connection with CMS *id*, Clear and Set

Description: The MPE device lost a connection from the specified CMS.

Severity: Error, Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: DQOS

Recovery:

Check availability of the CMS.

1110 - DQOS: Received *msg-type* from CMS *id*

Description: The specified message type was received from the specified CMS.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: DQOS

Recovery:

No action required.

1111 - DQOS: Sending *msg-type* to *id*

Description: The specified message type was sent to the specified CMTS.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: DQOS

Recovery:

No action required.

1112 - DQOS: Received *msg-type* from *id* *msg-contents*

Description: The specified message type was received from the specified CMTS.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: DQOS

Recovery:

This message is logged at the information level when the DQOS message is an error message such as GAtSetErr, GateDeleteErr, or GateInfoErr, and logged at the Info level when the message is an ACK such as GateSetAck, GateInfoAck, or GateDeleteAck.

1113 - DQOS: Sending *msg-type* to CMS *id*

Description: The specified message type was sent to the specified CMS.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: DQOS

Recovery:

This message is logged at the Warning level when the DQOS message is an error message such as GAtSetErr, GateDeleteErr, or GateInfoErr, and logged at the Info level when the message is an ACK such as GateSetAck, GateInfoAck, or GateDeleteAck.

1120 - DQOS: Rejecting *msg-type* - no CMTS available for SubID *id*

Description: A DQOS message was received with the specified subscriber IP address but there is no configured CMTS to handle this request.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: DQOS

Recovery:

Check the configuration of the CMTSs associated with this MPE device. Make sure that there is a CMTS configured with a subnet for the specified subscriber AND make sure that this CMTS is associated with this MPE device.

1121 - DQOS: Rejecting *msg-type* - invalid gate id *id*

Description: A DQOS message was received with a GateID that does not correspond to any session in the MPE database. This checking is only performed if the CMP has enabled Gate checking for the MPE device (by default this is off).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: DQOS

Recovery:

If you do not want this checking to be performed, disable it in the CMP.

1123 - DQOS: Rejecting *msg-type* - SubId mismatch - request *msg-id* doesn't match gate *mpe-id*

Description: A DQOS message was received with a Subscriber ID that does not match the Subscriber ID for the corresponding session in the MPE database. This checking is only performed if the CMP has enabled Gate checking for the MPE device (by default this is off).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: DQOS

Recovery:

If you do not want this checking to be performed, disable it in the CMP.

1124 - DQOS: Rejecting *msg-type* - Unrecognized Subscriber *id*

Description: A DQOS message was received with a Subscriber ID that does not correspond to a provisioned subscriber in the MPE database of known subscribers (CPEs). This checking is only performed if the CMP has enabled Subscriber checking for the MPE device (by default this is off).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: DQOS

Recovery:

If you do not want this checking to be performed, disable it in the CMP.

1129 - DQOS: Rejecting *msg-type* - DQOS I/O Error while sending to *id*

Description: An unexpected I/O error was encountered while trying to send the specified message to a CMTS.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: DQOS

Recovery:

1. Check the logs for further details on the I/O error.
2. Check the availability of the destination CMTS and the operational status of the network to the CMTS.

1150 - DQOS: Rejecting *msg-type* - Rejected by policy name

Description: There was no PCMM session connection to the target CMTS (or downstream policy server).

Note: The request will be rejected with a PCMM error code of 255, and a subcode of 211.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: DQOS

Recovery:

Check the network connectivity between systems.

1204 - SPC DQOS: Lost connection with CMS *id*

Description: The MPE device lost a connection from the specified CMS.

Severity: Error, Error

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

1. Check availability of the CMS.
2. Check the CMS log for a recent failover or other operation(s) that can interrupt communications.
3. If the CMS has not failed, make sure the path from the CMS to the MPE device (port 2126) is operational.

1209 - SPC DQOS: Deleting gate *gateid*, T1 Timer expired

Description: The specified gate was deleted because it did not transition from the RESERVED state to the COMMITTED state before the T1 Timer expired.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

Check the logs and status in the CMS to determine why the gate did not get committed. This may be a normal situation in which the call was aborted before it was fully set up.

1210 - SPC DQOS: Received *msg-type* from CMS *id* *msg-contents*

Description: The specified message type was received from the specified CMS.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

Contact the Tekelec [Customer Care Center](#).

1213 - SPC DQOS: Sending *msg-type* to CMS *id*

Description: The specified message type was received from the specified CMS.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

Contact the Tekelec [Customer Care Center](#).

1221 - SPC DQOS: Rejecting *msg-type* - invalid global session id *globalsessionid*

Description: The MPE device received a request to perform an operation on a global session (call) that does not exist in the MPE database.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

1. This is usually an indication that there is a protocol error or communication problem between an MPE device and a CMS.
2. If there was a recent failover or communication interruption it is possible that one of the devices may have data that is not complete.

1231 - SPC DQOS: Rejecting *msg-type* - invalid ingress id *ingressid*

Description: The MPE device received a request to set up a gate for a zone that does not exist (as specified by the ingress ID in the request).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

Ensure that the topology information in the MPE device is up-to-date and consistent with the topology information in the CMS that issued the request.

1232 - SPC DQOS: Rejecting *msg-type* - no path to root zone for ingress id *ingressid*

Description: The MPE device received a request to set up a gate for a zone that does not have a valid path to the root zone.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

Although in theory this is possible, it should not happen unless there is a problem in the configuration of the network topology. Verify that the network topology is defined correctly.

1233 - SPC DQOS: Dropping *msg-type* - invalid gate id *gateid*

Description: The MPE device received a request that referenced the specified gate ID and an unrelated session (via the GlobalSessionID).

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: SPC DQOS

Recovery:

1. This is usually an indication that there is a protocol error or communication problem between an MPE device and a CMS.
2. If there was a recent failover or communication interruption, it is possible that one of the devices may have data that is not complete.

1370 - IP already static

Description: BRAS:COPS-PR declared an IP address *0* already defined as static in account *1*.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

Contact the Tekelec [Customer Care Center](#).

1401 - Diameter: Transport connection opened with peer *peer_id*

Description: A transport level connection (such as TCP) has been established with a Diameter peer.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

No action required.

1402 - Diameter: Transport connection closed with the peer *peer*

Description: Connection to the network element or HSS is closed by peer *0*, where *0* is the IP address of the peer + port.

Severity: Error, Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE, MRA

Group: Diameter

Recovery:

Verify that the peer is online (although the connection can recover on its own on the next retry attempt).

1403 - Diameter: Transport connection disconnected by the peer *peer*

Description: Connection to network element or HSS is disconnected by peer *0*, where *0* is the IP address of the peer + port.

Severity: Error, Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE, MRA

Group: Diameter

Recovery:

Verify that the peer is online (although the connection can recover on its own on the next retry attempt).

1404 - Diameter: Sent msg to peer *peer_id* connection *conn_id*

Description: A Diameter message has been sent to a peer.

Severity:

- Warning - when message contains an error
- Info - for Debug normal messages
- Debug - for Diameter Watchdog requests and answers

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

No action required.

1405 - Diameter: Received msg from peer *peer_id* connection *conn_id*

Description: A Diameter message has been sent to a peer.

Severity:

- Warning - when message contains an error
- Info - for Debug normal messages
- Debug - for Diameter Watchdog requests and answers

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

No action required.

1406 - Diameter: Error processing message msg from peer *peer_id* connection *conn_id*

Description: An error occurred while processing a received message.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

No action required.

1407 - Diameter: Peer id (*connection_id*) status changed from *previous_status* to *new_status*

Diameter: Peer id (*connection_id*) status changed from *previous_status* to *new_status*

Description: The status of a Diameer peer has changed. This event is usually generated after a connection has been established and capability exchange has occurred.

Severity:

- Notice - after a connection has been established and capability exchange has occurred
- Warning - after a connection was torn down with a peer

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

No action required.

1408 - Diameter: New connection rejected

Description: A Diameter peer (identified by its Diameter Identity) attempted to establish a connection with the Camiant device although it already has a valid connection. The Diameter protocol allows only one connection from a particular peer.

Severity: Error, Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE, MRA

Group: Diameter

Recovery:

Check connectivity with peer; contact the Tekelec [Customer Care Center](#).

1409 - Diameter: Rejecting *msg_type* from *peer_id - con_id* AVP(s) not found in request *request_details*

Description: Request was rejected by the Policy Management device as it was missing an AVP that was required for the processing of the request based on the corresponding Diameter application procedures and current session state.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

Check the peer configuration to identify the reason the AVP was not included in the request.

1410 - Diameter: Response timeout for *msg_type* sent to *conn_id msg_details*

Description: A response message was not received for the request sent to the destination host.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

If the problem persists, contact Customer Support.

1411 - Diameter: Received Duplicate message *msg_type* from *conn_id* *msg_details*

Description: The received message was discarded because it was received previously by another message containing the same Diameter End-to-End Identifier from the same origin host.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

If the problem persists, contact Customer Support.

1412 - Diameter: Sent *{type}* to *{destination}* in *{connection ID}* mes *{message}*

Description: A Diameter message was sent.

Severity:

- Info - for Debug normal messages
- Debug - for Diameter Watchdog requests and answers
- Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

If the problem persists, contact Customer Support.

1413 - Diameter: Received *{type}* from *{sender}* in *{connection ID}* ms *{message}*

Description: A Diameter message was received.

Severity:

- Info - got Debug normal messages
- Debug - for Diameter Watchdog requests and answers

- Debug - for Diameter Watchdog requests and answers

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

If the problem persists, contact Customer Support.

1414 - Diameter: SCTP path on association ID address

ADDR_CONFIRMED/ADDR_UNREACHABLE/ADDR_AVAILABLE

Description: An SCTP path is unavailable. An info level message is generated when a backup or non-primary path is confirmed by the SCTP association. An error level message is generated when one of the paths fails, whether it is a primary or non-primary path. A notice level message is generated when a path that previously failed recovers.

Severity: Error

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

If the problem persists, contact Customer Support.

1420 - Diameter: Rejecting *application_request* - no PCEF available for subscriber

Description: Request from an application function (such as P-CSCF) was rejected by the MPE device as there was no corresponding session with the PCEF (such as a GGSN) for the subscriber.

Severity: Error, Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

Check the provided subscriber identification and IP address and verify that it corresponds to a subscriber who is attached to the network.

1421 - Diameter: No default QoS profile defined for media *type*

Description: The MPE device received a request (such as Rx) from an application to set up policy rules on the enforcement device, but the application function did not provide enough information in the request for the device to derive corresponding quality of service parameters, and there are no default profiles configured in the device for the corresponding media type.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

Check the MPE device configuration for Diameter AF default QoS profiles and add a default QoS profile for the media type in question. Verify the reason why the application function did not provide enough info to the device within the application request.

1440 - Diameter: Rejecting request for subscriber *sub_id* - No Network Element found for node *node_id*

Description: The MPE device rejected a request (such as Gx) from an enforcement device (such as a GGSN) because it did not recognize it as a “known” network element.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

Check the MPE device configuration and verify that the enforcement device is configured as a Network Element and associated with the MPE device. Also, verify that the Network Element's Diameter identity is configured.

1441 - Diameter: Rule *rule* failed for subscriber *sub_id* *xxx* - Rule failure code *code*

Description: A PCEF Charging-Rule-Report indicated that installation of the specified PCC rule for the specified subscriber and Diameter session failed with the specified failure code. If the PCEF reports failure to install multiple rules for the same reason, the MPE device generates a single event with multiple rule names.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

No actions are required.

1442 - Diameter: Rule *rule* retry *x* of *y* for subscriber *sub_id* *xxx* Next retry in *z* seconds.

Description: The MPE device retry installation of the specified PCC rule for the specified subscriber and Diameter session in the specified number of seconds.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

No actions are required.

1443 - Diameter: Rule *rule* retry failed after *n* attempts for subscriber *sub_id* *xxx*

Description: Installation of the specified PCC rule failed the maximum configured number of times for the specified subscriber and Diameter session.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

Check network connectivity, and if necessary adjust configuration values.

1444 - Diameter: PCC rule *rule* retry canceled for subscriber *sub_id* *xxx*

Description: Retrying installation of the specified PCC rule was canceled for the specified subscriber and Diameter session. This can happen because the rule was removed as the result of a policy action.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

No actions are required.

1445 - Diameter: PCC rule *rule* retry aborted for subscriber *sub_id* *xxx* - Too many retries in progress (*n* attempts)

Description: A rule installation retry cannot be initiated because the maximum number of simultaneous retries has been reached.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

If necessary, adjust configuration values.

1446 - Diameter: The maximum number of PDN connections has been exceeded for subscriber *ID*

Description: The maximum number of PDN connections has been exceeded for a subscriber.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Diameter

Recovery:

No actions are required

1447 - Diameter: Too many sessions

Description: Diameter: The maximum number of secondary sessions has been exceeded for the same IP-CAN session association for subscriber *subscriber ID*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

No action required.

1450 - SceGX: No SCE Profile or Default Profile set for subscriber *subscriber*

Description: For the given subscriber, there was no SCE Package ID set either via an SCE Traffic Profile in policy or via the Diameter PCEF Default Profile.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

Ensure all subscribers have an SCE Traffic Profile applied to their CCRi request, either via policy or by selecting an SCE Traffic Profile as the Diameter PCEF Default Profile.

1470 - Begin diameter session binding cleanup task

Description: The diameter session binding cleanup task has begun.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

No action required.

1471 - End of database iterations

Description: The database iterations (listing the potential number of stale sessions identified for cleanup) have ended.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

No action required.

1472 - End of diameter session binding cleanup task

Description: The purging process has started and the diameter session binding cleanup task has ended.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter

Recovery:

No action required.

1473 - PCMM:Finished iterating the database. Starting to send GateInfos

Description: Rejecting 0 - Rejected by Policy \1\.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CPE

Group: NA

Recovery:

No action required.

1474 - PCMM:Starting cleanup task

Description: PCMM: Starting cleanup task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

No action required.

1475 - PCMM: Completed session cleanup

Description: PCMM: Completed session cleanup.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

No action required.

1476 - Diameter: Completed session cleanup list built

Description: Diameter: Completed session cleanup list built.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

No action required.

1477 - PCMM:Completed session cleanup list built

Description: PCMM: Completed session cleanup list built.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

No action required.

1600 - DBPLUGIN: No matches for *criteria*

Description: DbPlugin search request did not find any results

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

No actions are required

1601 - LDAP: Established Connection to *srv*

Description: A new connection to the indicated server was established.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required.

1602 - LDAP: Closing connection to *srv*

Description: The connection to the indicated server was closed.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required.

1605 - LDAP: Attempted connection to *0* failed, reason: 1

Description: The connection to the indicated server failed for the reason specified.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

Check LDAP data source configuration to verify proper connection information is provided.

1610 - LDAP: Search failure for *ID* due to the following error: *error message*

Description: LDAP search failure due to an error.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1611 - LDAP: Searching for *stype: criteria*

Description: A search is being performed for the search type *stype* using the indicated criteria.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required.

1612 - LDAP: Search results for *stype filter* are *results*

Description: Displays the results of the search request (if matches found).

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required.

1613 - LDAP: No matches for *stype filter*

Description: A search returned no results.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

With multiple data sources, an individual data source might not return any results.

1614 - LDAP: Multiple matches for *stype filter*

Description: A search returned multiple results.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

Verify that the search criteria should have resulted in multiple matches. If necessary, correct the LDAP configuration.

1615 - LDAP: Unexpected search failure for *stype filter*, reason: *msg*

Description: A search was terminated because of an unexpected exception

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

Verify that the search criteria should have resulted in multiple matches. If necessary, correct the LDAP configuration.

1617 - LDAP: Detailed description of LDAP modification to be initiated

Description: This is a detailed description of the LDAP modification to be initiated. Example - Modify Entry for *Processor ID* (for example *UserByE164*); LDAP Processor: *Processor ID* Entry DN: *LDAP DN* Attribute: *LDAP Attribute* Value: *new value*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No action required.

1619 - LDAP: Unexpected modify failure for *process ID* key, reason: *message*

Description: Unexpected LDAP modify failure.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1620 - LDAP: Operation queue *process ID* in distress. Queue capacity exceeds *event message*

Description: An LDAP operations queue is in distress and has exceeded capacity.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1621 - LDAP: Operation queue *process ID* has cleared and is no longer in distress. Capacity is below *event message*

Description: An LDAP message queue is no longer in distress

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1622 - LDAP:Operation queue *process ID* is currently at 100% and will begin rejecting new LDAP Modify requests

Description: An LDAP message queue is at 100% capacity and will reject new LDAP modify requests.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1623 - LDAP:Modify failure. Unable to modify *fields at distinguished name* due to the following error: *message*

Description: Unable to initiate an LDAP modify operation on the specific External Field specified by the user. Example - Modify failure. Unable to modify *External Field Name* at *LDAP DN* due to the following error: *reason*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1624 - LDAP:Modify failure. Unable to perform modify due to the following error: *message*

Description: Unable to initiate an LDAP modify operation because the LDAP data source does not support this operation. Example - Modify failure. Unable to perform modify due to the following error: Data source is not configured with External Fields and will not support this update.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1626 - LDAP:Update unsuccessful: *message*

Description: Successful LDAP update.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1630 - DHCP unexpected event ID set

Description: DHCP: Unexpected problem: 0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

Contact the Tekelec [Customer Care Center](#).

1631 - DHCP unable to bind event ID

Description: DHCP:Unable to bind to port 0 for listening.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

Contact the Tekelec [Customer Care Center](#).

1632 - DHCP response timeout

Description: DHCP: Timeout waiting for response from 0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

Contact the Tekelec [Customer Care Center](#).

1633 - DHCP bad relay address

Description: DHCP: Bad relay address 0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

1634 - DHCP bad primary address

Description: DHCP: Bad primary address 0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

Contact the Tekelec [Customer Care Center](#).

1635 - DHCP bad secondary address

Description: DHCP: Bad secondary address 0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

Contact the Tekelec [Customer Care Center](#).

1641 - Searching for ID

Description: Searching for event ID 1.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

No action required.

1642 - Search CPE by IP result

Description: *message type*: Result for: *IP address, cpe mac address, xid: agent mac address*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

No action required.

1661 - Sh:Peer Realm *detailed message*

Description: SH bad realm configured

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1662 - Sh:Bad primary/secondary address reason

Description: SH bad IP address configured

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1663 - Sh:Searching for *peer ID: query*

Description: Started search for user in Diameter Peer HSS

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1664 - Sh:Search results for *query peer ID are: error message*

Description: Search results for user from Diameter Peer HSS

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1665 - Sh:No matches for *peer ID query*

Description: No results found for user from Diameter Peer HSS

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1666 - Sh:Unexpected search failure on *peer ID*

Description: Unexpected SH search failure.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1667 - Sh:Subscribing for *sub type name: element*

Description: SH: Subscribing for user profile change notifications for a user.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1668 - Sh:Subscription results for *user ID type element are: response*

Description: Subscription results for user from Diameter Peer HSS.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1669 - Sh:Unexpected subscription failure for *user ID type element*, reason: *response*

Description: SH: Unexpected subscription failure.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1670 - Sh:Unsubscribing for *sub type name: element*

Description: SH: Unsubscribing for user profile change notifications for a user.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1671 - Sh:Unsubscription results *user ID type element* are: *response*

Description: SH: Unsubscription results for user from Diameter Peer HSS.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1672 - Sh:Unexpected unsubscription failure *user ID type element are: response*

Description: SH: Unexpected unsubscription failure.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1673 - Sh:Received notification: *results*

Description: SH: Received a notification

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: LDAP

Recovery:

No actions are required

1674 - Sh:Updating User Error

Description: SH: Updating user *peer ID: query, error updating.*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

No action required.

1675 - Sh:Update failure

Description: SH: Update results for *subscriber ID: peer ID* are: *too many out-of-sync retries*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

Contact the Tekelec [Customer Care Center](#).

1676 - Sh:Update out-of-sync

Description: SH: Update out_of_sync for *subscriber ID: peer ID*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

No action required.

1681 - MSR: Established connection to *ip:port*

Description: A new connection to the server at the specified IP address was established.

Severity: Info, Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1682 - MSR: Closing Connection to *ip:port*

Description: The connection to the server at the specified IP address was closed.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1683 - MSR: Connection to the MSR server at the specified IP address was closed unexpectedly

Description: Connection to the MSR server at the specified IP address was closed unexpectedly.

Severity: Info

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: MSR

Recovery:

Check if the peer is online.

1684 - MSR: Closing a secondary MSR connection to revert to a primary connection

Description: Closing a secondary MSR connection to revert to a primary connection. Occurs when flipping back from secondary to primary MRA connection.

Severity: Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: MSR

Recovery:

Self recovery; no action required.

1685 - MSR: Connection attempt to MSR server failed

Description: Connection attempt to the MSR server at the specified IP address failed for the specified reason.

Severity: Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: MSR

Recovery:

MSR connectivity issue; verify that the peer is online.

1686 - MSR: Searching for *type: key*

Description: A search is being performed for the search type *type* using the specified key.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1687 - MSR: Searching for *type: key*

Description: Search result for *type key* is: *result*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1690 - MSR: Unexpected search failure for *type key*, reason: *msg*

Description: A search was terminated for the specified unexpected reason.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

Check the cause of the exception and check the MSR configuration for any errors that might have caused the problem.

1691 - MSR: Updating *type: key*

Description: An update is being performed for the update type *type* using the specified key.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1692 - MSR: Update result for *type key are: result*

Description: The results of the update request.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1693 - MSR: Unexpected update failure for *type key*, reason: *msg*

Description: An update was terminated for the specified unexpected reason

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

Check the cause of the exception and check the MSR configuration for any errors that might have caused the problem.

1694 - MSR: Subscribing for *type: key*

Description: A subscription is being performed for the subscription type *type* using the specified key.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1695 - MSR: Subscription results for *type key* are: *results*

Description: The results of the subscription request.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1696 - MSR: Unexpected subscription failure for *type key*, reason: *msg*

Description: A subscription was terminated for the specified unexpected reason.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

Check the cause of the exception and check the MSR configuration for any errors that might have caused the problem.

1697 - MSR: Unsubscribing for *type: key*

Description: An unsubscription is being performed for the subscription type *type* using the specified key.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1698 - MSR: Unsubscription results for *type key* are: *result*

Description: The results of the unsubscription request.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

1699 - MSR: Unexpected unsubscription failure for *type key*, reason: *msg*

Description: An unsubscription was terminated for the specified unexpected reason.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

Check the cause of the exception and check the MSR configuration for any errors that might have caused the problem.

1711 - COPS-PR: Received *msg-type* from *id*

Description: An unsubscription was terminated for the specified unexpected reason.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

Check the cause of the exception and check the MSR configuration for any errors that might have caused the problem.

1801 - PCMM lost connection

Description: DSMCC: Lost connection with Session Manager at 0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Recovery:

Contact the Tekelec [Customer Care Center](#).

1805 - PCMM no connection to PCEF

Description: PCMM: No connection to PCEF. Host name 0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Recovery:

Contact the Tekelec [Customer Care Center](#).

2198 - SMPP: Switched back to primary SMSC

Description: SMPP: Switched back to primary SMSC *IP/hostname*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMPP

Recovery:

Contact the Tekelec [Customer Care Center](#).

2199 - SMPP: Lost connection to primary SMSC

Description: SMPP: Lost connection to primary SMSC *IP/hostname* Switched to secondary SMSC *IP/hostname*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMPP

Recovery:

Contact the Tekelec [Customer Care Center](#).

2210 - MGPI: Reached max upstream gates

Description: MGPI: 0 Reached max upstream gates.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MGPI

Recovery:

Contact the Tekelec [Customer Care Center](#).

2211 - MGPI: Reached maximum GPI on all upstream gates

Description: MGPI: 0 Reached maximum GPI on all upstream gates.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MGPI

Recovery:

Contact the Tekelec [Customer Care Center](#).

2212 - MGPI: Incrementing GPI for gate ID, am ID and subscriber

Description: MGPI: Incrementing GPI for gate ID: 0, am ID: 1, and subscriber: 2 to 3.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MGPI

Recovery:

No actions required.

2213 - MGPI: Decrementing GP for gate ID, am ID, and subscriber

Description: MGPI: Decrementing GPI for gate ID: 0, am ID: 1, and subscriber: 2 to 3.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MGPI

Recovery:

No actions required.

2300 - TOD: Time period(s) changed from *prev_time_periods* to *new_time_periods*

Description: The current time period has changed. (This may not affect any sessions).

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Time-of-Day

Recovery:

No actions are required.

2301 - TOD: Transition to time period(s) *new_time_periods* started.

Description: A time period transition has started.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Time-of-Day

Recovery:

No actions are required.

2302 - TOD: Transition to time period(s) *new_time_periods* was still in progress when time periods changed. transition aborted.

Description: A time period transition has started occurred before a previous transition was completed.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Time-of-Day

Recovery:

No actions are required.

2303 - TOD: Transition to time period(s) *new_time_periods* successfully completed.

Description: A time period transition has finished, and all affected sessions have been updated accordingly.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Time-of-Day

Recovery:

No actions are required.

2304 - TOD: Transition to time period(s) *new_time_periods* failed to complete normally.

Description: A time period transition was not completed due to a communication failure with the policy enforcement device.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Time-of-Day

Recovery:

No actions are required.

2305 - TOD: Transition to time period(s) *new_time_periods* was aborted

Description: An operator has manually aborted a time period transition.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Time-of-Day

Recovery:

No actions are required.

2306 - TOD:Transition to time period(s) *current time periods* was invoked by the operator.

Description: A transition to a time period was invoked by the operator.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Time-of-Day

Recovery:

No actions are required

2549 - SMS:SMSR internal queue is full: *queue name*.

Description: SMSR internal queue is full: *queue name*. Messages will be rejected until space becomes available.

Severity: Warning

Notification: Trace Log

Alarm: Yes - 72549

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required.

2550 - SMS:SMS Relay is not enabled to receive message. *optional additional details*

Description: SMS Relay is not enabled. Info level if occurs during reconfiguration, Warning level occurs if occurs during operation.

Severity: Info, Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required

2551 - SMS:Configured SMS Relay endpoint: *SMS end point*

Description: Configured SMS Relay endpoint.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required

2552 - SMS:Sent to id: *ID* using SMS Relay defined at *end point* Message:*message*

Description: Send message using SMS Relay.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required

2553 - SMS:Unable to send SMS to *ID*. Invalid Billing Day *billing day* configured.

Description: Unable to send SMS due to Invalid Billing Day.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required

2555 - SMS:Error sending SMS to *ID* using SMS Relay defined at *end point*

Message: *message*

Description: Error sending SMS using defined SMS Relay.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required

2556 - SMS:Unable to send SMS to *response message* using SMS Relay defined at *end point ID*

Description: Unable to send SMS using defined SMS Relay.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required

2557 - SMS:Unable to send SMS to *user ID*. User's MSISDN could not be found.

Description: Unable to send SMS due to User's MSISDN not found.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMS

Recovery:

No actions are required

2558 - SMS: Connection is established to the SMSC.

Description: Connection is established to the SMSC.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMPP

Recovery:

No actions are required.

2559 - SMS: Connection is lost to the SMSC.

Description: Connection is lost to the SMSC.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMPP

Recovery:

No actions are required.

2560 - SMTP:SMTP functionality is not enabled to send message

Description: SMTP:SMTP functionality is not enabled to send message.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

Contact the Tekelec [Customer Care Center](#).

2561 - SMTP: Configured endpoint

Description: SMTP: Configured endpoint *resource URL*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

No action required.

2562 - SMTP:Sent to subscriber id using SMS Relay defined at Subject

Description: SMTP:Sent to id: *subscriber ID* using SMS Relay defined at *IP/Hostname\n Subject subject*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

No action required.

2563 - SMTP: Error sending SMTP message to {0} using SMS Relay

Description: SMTP: Error sending SMTP message to *subscriber ID* using SMS Relay defined at *IP/hostname* \n *Subject: subject* \n *Message: error message*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

Contact the Tekelec [Customer Care Center](#).

2564 - SMTP: Unable to send SMTP message using SMS Relay defined

Description: SMTP: Unable to send SMTP message to *subscriber ID* using SMS Relay defined at *IP/hostname*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

Contact the Tekelec [Customer Care Center](#).

2565 - SMTP:Connection has been closed to MTA IP Address

Description: Connection is lost to the MTA.

Severity: Warning

Notification: Trace Log

Alarm: Yes - 72565

Trap: No

Server: MPE

Group: SMTP

Recovery:

No actions are required.

2566 - SMTP:Connection established to MTA IP Address

Description: SMTP:Connection established to MTA *IP Address*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

No actions are required.

2567 - SMTP: Error attempting to establish a new connection to *mta* Error:*error*

Description: SMTP: Could not establish connection to MTA *IP address*. Reported error message is *error*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

No actions are required.

2611 - MSR: Received notification: *msg*

Description: The specified notification was received from the MSR about a subscriber profile change.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MSR

Recovery:

No actions are required.

2700 - New DRA binding created

Description: A DRA new binding was created and an MPE device was selected for the subscriber's sessions.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2701 - DRA binding released between subscriber and MPE device

Description: A DRA binding was released between the named subscriber and MPE device because the subscriber's last session was terminated.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2702 - Existing binding found

Description: An existing binding was found (and possibly updated) between the named subscriber and MPE device.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2703 - MRA did not find binding information for subscriber

Description: The MRA did not find binding information for the named subscriber and has to either query another MRA device or respond to a requesting MRA device.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2704 - Binding Release Task *STARTED* | *COMPLETED* | *ABORTED*

Description: The MRA did not find binding information for the named subscriber and has to either query another MRA device or respond to a requesting MRA device.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2705 - Duplicate bindings have been detected for *list_of_user_ids* on *list_of_MRAs*

Description: The variable *list_of_user_ids* will contain a comma separated list of user ids and *list_of_MRAs* will be a comma separated list of identities of the MRAs that have the duplicate binding.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2706 - Binding cleanup task has been started

Description: Indicates that the cleanup task to look for stale sessions and suspect bindings has started or is currently running.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2707 - RADIUS:Sent message code [*accounting status type / pocket ID*] to session *ID.message*

Description: RADIUS: A response to a Radius Accounting message was successfully sent.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: RADIUS

Recovery:

No actions are required

2708 - Binding cleanup task is finished and processed 0 stale bindings, 1 duplicate bindings, and 2 stale sessions

Description: Indicates the cleanup task is now finished for its current cycle, and displays the number of stale bindings, duplicate bindings, and stale sessions detected.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: MRA

Recovery:

No actions are required.

2710 - RADIUS:Stopping communication for *port number*

Description: RADIUS: Stopping communication.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: RADIUS

Recovery:

No actions are required

2900 - ADMISSION: System is in busy state because *resource name*: criteria *admission criteria*

Description: The current system load is evaluated by an admission controller as exceeding admission criteria thresholds.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Load Admission

Recovery:

Typically, this condition returns to normal state. If it persists, contact Customer Support.

2901 - ADMISSION: System is in normal state

Description: The current system load is below clearing admission criteria thresholds and stability timeout is exceeded.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Load Admission

Recovery:

No actions are required.

2902 - ADMISSION: Monitored resource *resource-name* is in busy state: criteria *threshold*

Description: The load of the monitored resource is evaluated by an admission controller as exceeding the admission criteria threshold. This event carries only an informative value and can be disabled by the ResourceStateLog property.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Load Admission

Recovery:

Typically, this condition returns to normal state. If it persists, contact Customer Support.

2903 - ADMISSION: Monitored resource *resource-name* is in normal state: criteria *threshold*

Description: The load of the monitored resource is below the clearing criteria threshold. This event carries only an informative value and can be disabled by the ResourceStateLog property.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE, MRA

Group: Load Admission

Recovery:

No actions are required.

2904 - Diameter/RADIUS protocol is in a busy state

Description: Diameter/RADIUS protocol is in a busy state.

Severity: Error, Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE, MRA

Group: Load Admission

Recovery:

Self-recoverable when load drops below cleanup threshold; if persisted, identify the source of the high Diameter/RADIUS load.

2905 - Diameter/RADIUS protocol is in a normal state

Description: Diameter/RADIUS protocol is in a normal state.

Severity: Error

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE, MRA

Group: Load Admission

Recovery:

Self-recoverable when load drops below cleanup threshold; if persisted, identify the source of the high Diameter/RADIUS load.

3000 - Trace log rate limit

Description: The trace log has throttled 0 messages in the past 1 seconds.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NA

Recovery:

Contact the Tekelec [Customer Care Center](#).

3100 - Certificate x expires in n days

Description: The SSL certificate specified by x will expire in n days. Note: A 90-day SSL certificate is installed by default when a fresh software installation occurs on a system. The expiration of this certificate can cause this trace log code to be generated.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: Certificate Monitor

Recovery:

1. Delete the expiring SSL certificate using the Platcfg utility to prevent this warning message from being generated again. Platcfg procedures are available in the *Platform Configuration User Guide*.
2. If using https or encryption between servers, create a new certificate using the Platcfg utility.

3101 - Certificate x has expired

Description: The SSL certificate specified by x has expired. Note: A 90-day SSL certificate is installed by default when a fresh software installation occurs on a system. The expiration of this certificate can cause this trace log code to be generated.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: Certificate Monitor

Recovery:

1. Delete the expired SSL certificate using the Platcfg utility to prevent this warning message from being generated again. Platcfg procedures are available in the *Platform Configuration User Guide*.
2. If using https or encryption between servers, create a new certificate using the Platcfg utility.

4000 - Policy Action generated critical alarm

Description: Arbitrary alarm whose cause (and resolution) depends on the policy definition.

Severity: Critical, Notice

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Load Admission

Recovery:

Recovery is based on each individual case.

4001 - Policy Action generated major alarm

Description: Arbitrary alarm whose cause (and resolution) depends on the policy definition.

Severity: Error, Notice

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Load Admission

Recovery:

Recovery is based on each individual case.

4002 - Policy Action generated minor alarm

Description: Arbitrary alarm whose cause (and resolution) depends on the policy definition.

Severity: Warning, Notice

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Load Admission

Recovery:

Recovery is based on each individual case.

4048 - CAC: Gate delete error, gate ID = *n*

Description: An unexpected error is returned while trying to release resources.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

These resources are released later as part of the periodic scrubbing process.

4063 - CAC: Session context format error for session - removing

Description: CAC: Session context format error for session 0 - removing

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

Contact the Tekelec [Customer Care Center](#).

4080 - CAC: Error locating session in CAC database: *error-message*

Description: There was a problem reading the session database.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

4154 - CAC: This blade is now active

Gate ID = *gate-id* reply type=*reply-type*

Description: This blade is active.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

4155 - CAC: This blade is now inactive. Canceling any synchronization in progress

Gate ID = *gate-id* reply type=*reply-type*

Description: Indicates the primary blade has failed.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

4156 - CAC: Unknown response from gate delete request

Gate ID = *gate-id* reply type=*reply-type*

Description: There was an internal error while releasing resources.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

4157 - CAC: Exception while deleting gate id *id*

Gate ID = *gate-id* reply type=*reply-type*

Description: Exception while deleting gate id *id*

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

4163 - CAC: Forcing synchronization with Tandberg server at *ip-address*

Description: A manual synchronization is initiated by a user via the CMP.

Note: Superseded by event 7062.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

4184 - CAC: Seachange/Tandberg reserve of session id on ip-address complete

status: status, duration: time ms

Description: A session was successfully reserved.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

No action required.

4185 - CAC: Seachange/Tandberg release of session id complete

status: status, duration: time ms

Description: A session was successfully released.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

No action required.

4208 - CAC: Seachange/Tandberg reserve of duplicate session *id* on *ip-address* complete: status *status*, duration *time* ms

status: status, duration: time ms

Description: A session with a duplicate ID was successfully reserved.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Recovery:

No action required.

4300 - RC *ip-address* Unreachable

Description: The CMP to MPE connection has failed.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Load Admission

Recovery:

Policy execution INFO trace log

4301 - RC *ip-address* Reachable

Description: The CMP to MPE connection has been restored.

Severity: Info

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Load Admission

Recovery:

Policy execution INFO trace log

4302 - RC *ip-address* Unreachable - operation: *operation*

Description: The CMP to MPE connection failed during the specified operation.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Load Admission

Recovery:

1. Policy execution INFO trace log.
2. Contact the Tekelec [Customer Care Center](#).

4303 - Can not download log file from MPE

Description: Cannot download log file from Rc IP/hostname.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

4550 - Policy Trace *name: message*

Description: Policy generated Info level Trace Log notification.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy execution INFO trace log

4551 - Policy Trace *name: message*

Description: Policy generated Warning level Trace Log notification.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy execution WARN trace log

4552 - Policy Trace *name: message*

Description: Policy generated Debug level Trace Log notification.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy execution DEBUG trace log

4560 - Policy Action Trace: *message*

Description: Policy Action generated Emergency Trace Log notification.

Severity: Emergency

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log EMERGENCY action

4561 - Policy Action Trace: *message*

Description: Policy Action generated Alert Trace Log notification.

Severity: Alert

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log ALERT action

4562 - Policy Action Trace: *message*

Description: Policy Action generated Critical Trace Log notification.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log CRITICAL action

4563 - Policy Action Trace: *message*

Description: Policy Action generated Error Trace Log notification.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log ERROR action

4564 - Policy Action Trace: *message*

Description: Policy Action generated Warning Trace Log notification.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log WARNING action

4565 - Policy Action Trace: *message*

Description: Policy Action generated Notice Trace Log notification

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log NOTICE action

4566 - Policy Action Trace: *message*

Description: Policy Action generated Info Trace Log notification.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log INFO action

4567 - Policy Action Trace: *message*

Description: Policy Action generated Debug Trace Log notification.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Load Admission

Recovery:

Policy generated trace log DEBUG action

4600 - MPE or MRA rejects a secondary connection

Description: A Secondary connection has been rejected due to a Primary connection already existing from the same Diameter identity. This could indicate a split brain situation at the remote identity.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE, MRA

Group: Georedundancy

Recovery:

1. Fix network problems and restore connectivity.
2. Place one of the Active servers in the cluster into Forced Standby mode.
3. If alarm persists, contact the Tekelec [Customer Care Center](#).

4601 - MPE or MRA reverts from a secondary connection to a primary connection

Description: A connection has reverted from a Secondary connection to a Primary connection. While this could happen normally during a remote failover, it could also indicate a potential split brain situation at the remote cluster.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE, MRA

Group: Georedundancy

Recovery:

1. Fix network problems and restore connectivity.
2. Place one of the Active servers in the cluster into Forced Standby mode.
3. If alarm persists, contact the Tekelec [Customer Care Center](#).

4602 - More than one server in a cluster is Active at a time

Description: Multiple Active servers have been detected in the same cluster; this indicates that the cluster is in Split Brain.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: CMP

Group: Georedundancy

Recovery:

1. Fix network problems and restore connectivity.
2. Place one of the Active servers in the cluster into Forced Standby mode.
3. Contact the Tekelec [Customer Care Center](#).

4603 - Max primary site failure threshold reached

Description: Number of failed MPE Primary Sites has reached the threshold.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: CMP

Group: Georedundancy

Recovery:

1. When the failure count drops below the threshold value and stays below the threshold for 30 seconds, the alarm is cleared. (The 30 seconds delay prevents the alarm from being cleared too soon.)
2. If alarm doesn't clear automatically, contact the Tekelec [Customer Care Center](#).

4604 - Policy Cluster Offline Failure

Description: An MPE/MRA policy cluster is offline. None of the servers in this cluster are available (Active, Standby, or Spare).

Severity: Critical

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: CMP

Group: Georedundancy

Recovery:

1. When a server comes online (in Active, Standby, or Spare state), the alarm is cleared. Please check whether all servers are powered down or rebooted at that time.
2. If alarm doesn't clear automatically, contact the Tekelec [Customer Care Center](#).

4610 - *Sh Connections operation Successful for MPEs' name, Failed for MPEs' name*

Description: The CMP performed a global operation to enable (or disable) Sh on all MPE's with the results as specified (MPE's for which it was successful are listed; MPE's for which the operation failed are also listed).

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: Sh

Recovery:

If the operations failed for some MPEs then it can be retried. If repeated attempts fail then there may be other management issues with the associated MPEs and connectivity to those devices should be verified.

4700 - Upgrade Manager command return message: *message*

Description: Upgrade Manager executes command on remote server and gets the return message, then generates the Info Trace Log notification.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: Upgrade

Recovery:

No action required.

6000 - Wireline Subact Log

Description: The log describes the subscriber account information which can be associated to the vod reserve, release, etc.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: MPE

Deprecated ID:

Recovery:

Contact the Tekelec [Customer Care Center](#).

6102 - Gx-Plus: Learnt new endpoint *id*, *x* from gateway *y*

Description: The PCRF has learned a new subscriber endpoint with *id* as the IP address and *x* as the session ID from the gateway *y*. *y* refers to the remote GX-MX's IP address learned from the diameter socket connection, if the diameter connection exists. Otherwise, the GX-MX's NE diameter Identity is printed.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID: 1756

Recovery:

Contact the Tekelec [Customer Care Center](#).

6103 - CAC: Exception while *Seachange/Tandberg* sync operation with *url* terminated CAC session ID *id*

Description: This is an internal configuration error.

Note: Supersedes event 4068.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4201

Recovery:

Contact the Tekelec [Customer Care Center](#).

6105 - PCMM syntax error

Description: BoD received warning *error message* from *filename*.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Recovery:

Contact the Tekelec [Customer Care Center](#).

6200 - NAC: Abnormal delete of session

session-detail, Reason Code: *code*, Text: *reason text*

Description: Session deleted abnormally. An element-level stat in the MPE tracks total normal disconnects per network element. The CMP retrieves this stat as part of the current call for network element stats using the OM Stats Task.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1314

Recovery:

Contact the Tekelec [Customer Care Center](#).

6201 - NAC: Normal delete of session

session-detail

Description: The session is deleted normally. *session-detail* includes the Subscriber ID, the format of which changes depending on whether the subscriber has a dynamic or static IP address (static IP subscribers do not have the @BRAS on their ID). An element-level stat in the MPE tracks total normal disconnects per network element. The CMP retrieves this stat as part of the current call for network element stats using the OM Stats Task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1315

Recovery:

No action required.

6202 - NAC: Allowed session

session-detail

Description: The MPE allowed the session. Upon completion of each session request (blocked or allowed) from the VoD server, the MPE generates an Info level event log. The following data is provided within the message: reason code (if applicable), account id, subscriber data, network element name, full network path.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1316

Recovery:

No action required.

6203 - NAC: Rejecting *msg-type* - no path available from *SUB-IP* to *SERVER-IP*

Description: A request was received but there was no provisioned path that could be used to satisfy the endpoints in the request.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1320

Recovery:

1. Check the specified SUB-IP and Server-IP and determine if there is a path that should be used.
2. If such a path exists, make sure that the B-RAS in the path is actually associated with the MPE in the CMP.

6204 - NAC: Rejecting *msg-type* - subscriber with address *SUB-IP* is unknown (session ID *VoD-ID*)

Description: A subscriber without an associated account requested a VoD session. The session request was denied.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: NAC

Deprecated ID: 1321

Recovery:

1. Check to make sure that there is an account for the specified subscriber in the OSS.
2. Make sure that the name of the network element in the account is a B-RAS that is associated with the MPE in the CMP.

6205 - NAC: Allowing *msg-type* - subscriber with unknown address *SUB-IP* (session ID *VoD-ID*)

Description: A subscriber without an associated account requested a VoD session. The session request was allowed.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: NAC

Deprecated ID: 1322

Recovery:

Contact the Tekelec [Customer Care Center](#).

6206 - NAC: No account information for subscriber *SUB-IP* (session ID *VoD-ID*)

Description: A subscriber with dynamic IP address *SUB-IP* without an associated account requested a VoD session. The session request was denied.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1323

Recovery:

Contact the Tekelec [Customer Care Center](#).

6207 - NAC: Subscriber with address *SUB-IP* is unknown (session ID *VoD-ID*)

Description: A subscriber with an unknown IP address requested a VoD session. The subscriber does not have a static IP address assigned to it, and the subscriber's associated BRAS has not notified the MPE that it has attached to the network. If event 1324 is generated, either event 1321 or 1322 is also generated.

Severity: Warn

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1324

Recovery:

Contact the Tekelec [Customer Care Center](#).

6208 - NAC: Rejecting *msg-type* - Rejected by policy *name*

Description: The specified message was rejected by the specified policy rule.

The MPE returns a numeric code specified as part of a reject action to the VoD server. The reject code is configured on the CMP when a Policy is defined. This is available in the GUI as an additional action in the Policy definition dialog. The code itself must be an integer between 0-65535.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1350

Recovery:

1. Check the policy rule and the contents of the message to make sure it is operating as expected.
2. It may be helpful to increase the logging level of the policy log and then repeat this request to examine the details of the policy execution.

6209 - NAC: Both static and dynamic definitions for subscriber IP address *SUB-IP*, using dynamic definition

Description: In making a video request, a subscriber added a static IP address to an account, but the BRAS to which the subscriber is connected also assigned it a dynamic IP address.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1351

Recovery:

Either remove the static IP definition or configure the subscriber on the BRAS to have a static IP address.

6210 - NAC: Could not find BRAS endpoint *endpoint* in path *path* - rejecting

Description: An IP subnet pool is improperly associated with a newtwork element (For example, subnet 10.1.x.x is associated with NE1, but NE2 has assigned a subscriber in the same range.)

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: NAC

Deprecated ID:1352

Recovery:

Ensure that the IP subnet ranges do not overlap on the network elements.

6211 - BRAS: COPS-PR declared an IP address (*ip*) already defined as static in account account

Description: A subscriber attached to the network with a static IP address but the BRAS to which the subscriber is connected also assigned a dynamic IP address.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: BRAS

Deprecated ID: 1370

Recovery:

Either remove the static IP definition or configure the subscriber on the BRAS to have a static IP address.

6400 - BRAS: Transmit buffer for *n* extended from *x* to *y*

Description: The transmit buffer has extended from *x* to *y*. *n* refers to the remote ERX's IP address learned from the COPS socket connection.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: BRAS

Deprecated ID: 1740

Recovery:

Contact the Tekelec [Customer Care Center](#).

6401 - BRAS: Transmit buffer for *id* shrunk from *x* to *y*

Description: The transmit buffer has decreased from *x* to *y*. *id* refers the ERX's IP address learned from COPS socket connection.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: BRAS

Deprecated ID: 1741

Recovery:

Contact the Tekelec [Customer Care Center](#).

6402 - BRAS: Transmit buffer overflow for *n*: space needed = 1, available = 2

Description: Describes how the transmit buffer size is handled.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: BRAS

Deprecated ID: 1742

Recovery:

Contact the Tekelec [Customer Care Center](#).

6403 - COPS-PR: Connection accepted from gateway IP *ip-address*, port *port*

Description: A new COPS-PR connection was accepted from the specified gateway. *ip-address* refers to the remote ERX's IP address learned from the COPS socket connection, and *port* refers to the port.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1701

Recovery:

Contact the Tekelec [Customer Care Center](#).

6404 - COPS-PR: Lost connection with gateway *id*

Description: The MPE lost a connection from the gateway. *id* refers to the remote ERX's IP address learned from the COPS socket connection.

Severity: Error

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID:1702

Recovery:

1. Check availability of the gateway.
2. If the gateway has not failed, make sure the path from the gateway to the MPE is operational.

6405 - COPS-PR: Rejecting OPN message from *id*. Unknown gateway

Description: An unknown gateway is trying to establish a COPS-PR connection to the MPE. *id* refers to the remote ERX's IP address learned from the COPS socket connection, if it's retrieved. Otherwise, "unknown address" is printed.

Severity: Error

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID:1703

Recovery:

1. Check the configuration of the network elements in the CMP. There should be a B-RAS network element for this gateway and that B-RAS must be associated with this MPE.
2. Make sure that the configuration of the B-RAS network element is consistent with the provisioned information on the gateway. The network element name in the CMP must match the provisioned router name on the gateway.

6406 - COPS-PR: BRAS IP *x*, port *y* no longer associated with this MPE. Closing connection.

Description: BRAS IP *x*, port *y* no longer associated with this MPE. Closing connection.

Severity: Info

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1704

Recovery:

Contact the Tekelec [Customer Care Center](#).

6407 - COPS-PR: Received *msg-type* from *id*

Description: The specified message type was received from the specified gateway. *id* refers to the remote ERX's IP address learned from the COPS socket connection.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1711

Recovery:

No action required.

6408 - COPS-PR: Sending *msg-type* to *id*

Description: The specified message type was sent to the specified gateway. *id* refers the ERX's IP address learned from COPS socket connection.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1712

Recovery:

Contact the Tekelec [Customer Care Center](#).

6409 - COPS-PR: Starting full state synchronization with gateway n

Description: COPS-PR: Starting full state synchronization with gateway n

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1713

Recovery:

Contact the Tekelec [Customer Care Center](#).

6410 - COPS-PR: Full state synchronization with gateway n has completed

Description: COPS-PR: Full state synchronization with gateway n has completed

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1714

Recovery:

Contact the Tekelec [Customer Care Center](#).

6411 - COPS-PR: Learnt new endpoint from $ip\text{-}address, y$ from gateway $ip\text{-}address$

Description: COPS-PR: Learnt new endpoint from x, y from gateway n

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1715

Recovery:

Contact the Tekelec [Customer Care Center](#).

6412 - COPS-PR: Deleting endpoint *ip-addresss, sub-id* due to DRQ from gateway *ip-address*

Description: The MPE device deleted the endpoint *ip-addresss, sub-id* after the ERX device at *ip-address* sent a DRQ message.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1716

Recovery:

No action required.

6413 - COPS-PR: Deleting stale entry for IP *ip-address, sub-id* from gateway *ip-address*

Description: The MPE device deleted an endpoint *ip-address, sub-id* as stale.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1717

Recovery:

No action required.

6414 - COPS-PR: ERX *x* requests fast synchronization with Policy Server *n*

Description: COPS-PR: ERX *x* requests fast synchronization with Policy Server *n*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID: 1722

Recovery:

Contact the Tekelec [Customer Care Center](#).

6415 - Gx-Plus: Received CCR-I, session ID x subid y from id

Description: The PCRF received a credit control request for an initial request (CCR-I) with session ID x and sub id y from the gateway id . id refers to the remote GX-MX's IP address learned from the diameter socket connection, if the diameter connection exists. Otherwise, the GX-MX's NE Diameter Identity is printed.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID: 1750

Recovery:

Contact the Tekelec [Customer Care Center](#).

6416 - Gx-Plus: Received CCR-T, session ID x from id

Description: The gateway n sends a CCR-T with a session ID to indicate that a subscriber has logged out and its subscriber data should no longer be associated with an IP address. id refers to the remote GX-MX's IP address learned from the diameter socket connection, if the diameter connection exists. Otherwise, the GX-MX's NE Diameter Identity is printed.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID: 1751

Recovery:

Contact the Tekelec [Customer Care Center](#).

6417 - Handling ack: Endpoint Ip; Gx Subscriber Id; Router Address

Description: Handling acknowledgement.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID:1756

Recovery:

Contact the Tekelec [Customer Care Center](#).

6418 - Gx-Plus: Start state synchronization with gateway *id*

Description: The gateway *id* starts a state synchronization with the PCRF. *id* refers to the GX-MX's Host Name/IP Address configured in the GUI Network Elements tab, if it's set. Otherwise, it's empty.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID:1763

Recovery:

Contact the Tekelec [Customer Care Center](#).

6419 - Gx-Plus: State synchronization with gateway *id* has completed

Description: This event signals the completion of state synchronization between the gateway *id* and the PCRF. *id* refers to the GX-MX's IP address learned from the diameter socket connection, if the diameter connection exists. Otherwise, the GX-MX's NE Diameter Identity is printed.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID:1764

Recovery:

Contact the Tekelec [Customer Care Center](#).

6420 - Gx-Plus: Drop all the bras endpoints and diameter sessions because of cold reboot from gateway *id*

Description: When the PCRF receives a JSER from the GWR indicating a cold boot event, it purges all the sessions that were created by requests from the gateway *id*. *id* refers to the GX-MX's Host Name/IP Address configured in the GUI Network Elements tab, if it's set. Otherwise, it's empty.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID:1765

Recovery:

Contact the Tekelec [Customer Care Center](#).

6421 - Gx-Plus: Deleting endpoint *n, x* due to CCR-T from gateway *id*

Description: This event is generated when an endpoint is deleted from the PCRF database upon successfully processing a CCR-T message from the gateway *id*. *id* refers to the remote GX-MX's IP address learned from the diameter socket connection, if the diameter connection exists. Otherwise, the GX-MX's NE Diameter Identity is printed.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID:1766

Recovery:

Contact the Tekelec [Customer Care Center](#).

6422 - Gx-Plus: Deleting stale entry for IP n, x from gateway id

Description: Once the state sync is complete or upon receiving a discovery request, the PCRF performs a scrub operation, by which it deletes all the subscriber information for the gateway id , which was not reported by the gateway in the JSDA messages. This removes stale entries from the PCRF databases. id refers to the GX-MX's IP address the from the session logon.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID: 1767

Recovery:

Contact the Tekelec [Customer Care Center](#).

6423 - Gx-Plus: Received warm reboot message from gateway id

Description: When the gateway is warm-booted, the gateway id sends a JSER to indicate a warm boot event. id refers to the GX-MX's Host Name/IP Address configured in the GUI Network Elements tab, if it's set. Otherwise it's empty.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID: 1768

Recovery:

Contact the Tekelec [Customer Care Center](#).

6424 - Gx-Plus: Received AYT message from gateway id

Description: Occurs when the router receives no response from the PCRF. Can be caused by a broken connection, a PCRF failover, or a router cold boot. The appearance of this log implies the connection between the router and the PCRF has been recovered. id refers the GX-MX's Host Name / IP Address configured in the GUI Network Elements tab, if it's set. Otherwise, it's empty.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID:1769

Recovery:

Contact the Tekelec [Customer Care Center](#).

6425 - Gx-Plus: Received AWD message from gateway *id*

Description: This is the application watchdog event generated by the gateway *id* for the state synchronization application. *id* refers to the GX-MX's Host Name/IP Address configured in the GUI Network Elements tab if it's set. Otherwise, it's empty.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Gx-Plus

Deprecated ID:1770

Recovery:

Contact the Tekelec [Customer Care Center](#).

6426 - COPS-PR: Dropping *msg-type* from *id* - *reason*

Description: There was a protocol error while processing the specified COPS-PR message from the specified gateway. *Reason* provides a more detailed description of the specific protocol error that occurred.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID:1721

Recovery:

Contact the Tekelec [Customer Care Center](#).

6427 - BRAS: Scrubber logout IP Addr; Sub Id; Router Addr

Description: BRAS Scrubber Logout.

Severity: Info

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE

Group: COPS-PR

Deprecated ID:1721

Recovery:

Contact the Tekelec [Customer Care Center](#).

7001 - CAC: Exception while recreating Tandberg session

Description: An exception occurred in a VoD server.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4003

Recovery:

Contact the Tekelec [Customer Care Center](#).

7002 - CAC: Recreating Tandberg session *id* due to synch operation with *url*

Description: Session is being recreated.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4004

Recovery:

Contact the Tekelec [Customer Care Center](#).

7003 - CAC: Failed to recreate Tandberg session *id* due to sync with *url*

code=code, desc=description

Description: Failed to recreate Tandberg session *id* due to sync with *url*.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4005

Recovery:

Contact the Tekelec [Customer Care Center](#).

7010 - CAC: Exception while reading local session ID list

Description: This is an internal configuration error.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4065

Recovery:

Contact the Tekelec [Customer Care Center](#).

7011 - CAC: Failed to create CAC session ID *id*

Description: Could not create CAC session ID.

Note: Superseded by event 4200.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4066

Recovery:

Contact the Tekelec [Customer Care Center](#).

7013 - CAC: Exception while sync operation terminated CAC session ID *id*

Description: This is an internal configuration error.

Note: Superseded by event 4201.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4068

Recovery:

Contact the Tekelec [Customer Care Center](#).

7014 - CAC: Attempt to remove nonexistent session ID *id* failed

Description: The VoD server attempted to release a session that no longer exists (or never existed).

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4069

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

7015 - CAC: Failed to release resources for session ID *id*

Description: A gate could not be set from a rejected reserve request.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4070

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

7019 - CAC: Created CAC session ID *id* due to request from VoD server at *server-ip*

Description: The session ID was created successfully.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4096

Recovery:

No action required.

7023 - CAC: Processing reconfiguration request

Description: Processing reconfiguration request

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4110

Recovery:

Contact the Tekelec [Customer Care Center](#).

7025 - CAC: Gate set error x

Description: The MPE received a VoD request, but the subscriber IP address cannot be found in the COPS-PR table.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4113

Recovery:

Check your network configuration.

7027 - NAC: Send error reply. Session, x

Description: This is an internal configuration error.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4115

Recovery:

Contact the Tekelec [Customer Care Center](#).

7031 - CAC: Exception while writing session x into database

Description: This is an internal configuration error. x means session ID, if available.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4143

Recovery:

Contact the Tekelec [Customer Care Center](#).

7032 - CAC: Exception while reserving resources for *id: error-message*

Description: This is an internal configuration error.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4144

Recovery:

Contact the Tekelec [Customer Care Center](#).

7034 - CAC: Locally removing session *id* due to synchronization mismatch with Seachange/Tandberg server at *ip-address*

Description: The CAC AM has a session that is not on the VoD server. As a result, the session is removed and all associated resources are released.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4172

Recovery:

No action required.

7035 - CAC: Locally removing session *id* due to synchronization timeout with *Seachange/Tandberg* server at *ip-address*

Description: Specified session removed due to a synchronization timeout with server with the given address.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4173

Recovery:

No action required.

7036 - CAC: Requesting removal of session *id* from *Seachange/Tandberg* server at *ip-address* due to synchronization mismatch

Description: Requesting removal of the specified session due to a synchronization mismatch with server with the given address.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4175

Recovery:

No action required.

7038 - CAC: This blade is now active

Description: This blade is active.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4154

Recovery:

No action required.

7039 - CAC: This blade is now inactive. Canceling any synchronization in progress

Description: Indicates the primary blade has failed.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4155

Recovery:

Failover to secondary blade. If problem persists, contact the Tekelec [Customer Care Center](#).

7047 - CAC: Starting synchronization with *server-url*

Description: Synchronization is started between the MPE and a VoD server.

Note: Superseded by event 4205.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4164

Recovery:

No action required.

7048 - CAC: Synchronization with *server-url* complete

Status: *true/false*

Description: Synchronization is complete. If Status is True, the synchronization completed successfully. If Status is False, the synchronization is aborted after 20 minutes of retries.

Note: Superseded by event 4206.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4165

Recovery:

If synchronization continues to fail, contact the Tekelec [Customer Care Center](#).

7052 - CAC: Failed to reserve resources for *x*

Description: The request for resources for the session are denied.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4169

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

7054 - CAC: Rejecting create of session ID *id* from server at *ip-address*: duplicate session

Description: Rejecting create of session ID *id* from server at *ip-address*: duplicate session.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4177

Recovery:

Contact the Tekelec [Customer Care Center](#).

7055 - CAC: Tandberg session ID *id* missing in session list on Tandberg server. Issuing specific query to *url*

Description: Tandberg session ID *id* missing in session list on Tandberg server. Issuing specific query to *url*.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4178

Recovery:

No action required.

7056 - CAC: Tandberg session ID *id* still missing in session list on Tandberg server at *url* - scheduling removal

Description: Tandberg session ID *id* still missing in session list on Tandberg server at *url* - scheduling removal.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4179

Recovery:

No action required.

7057 - CAC: Keepalive status request from Tandberg server at *ip-address*

Description: Keep alive status request from Tandberg server at *ip-address*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4180

Recovery:

No action required.

7058 - CAC: Session list status request from *Seachange/Tandberg* server at *ip-address*

Description: Session list status request from *Seachange/Tandberg* server at *ip-address*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4181

Recovery:

No action required.

7059 - CAC: Session detail status request from Tandberg server at *ip-address* for session ID *id*

Description: Session detail status request from Tandberg server at *ip-address* for session ID *id*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4182

Recovery:

No action required.

7060 - CAC: Version status request from Tandberg server at *ip-address*

Description: Version status request from Tandberg server at *ip-address*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4183

Recovery:

No action required.

7063 - CAC: No keepalive response from Tandberg server at *url*

Description: No keepalive response from Tandberg server at *url*.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4188

Recovery:

Contact the Tekelec [Customer Care Center](#).

7064 - CAC: Exception while releasing session *id* from Tandberg server

Description: Exception while releasing session *id* from Tandberg server.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4189

Recovery:

No action required.

7065 - CAC: Tandberg server requesting release of session ID *id*

Code=*code*, Text=*desc*

Description: Tandberg server requesting release of session ID *id*, Code=*code*, Text=*desc*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4190

Recovery:

No action required.

7066 - CAC: No version status response from Tandberg server at *url*

Description: No version status response from Tandberg server at *url*.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4191

Recovery:

Contact the Tekelec [Customer Care Center](#).

7067 - CAC: Version report from Tandberg server at *url*

software: *sw-version*, interface: *int-version*

Description: Version report from Tandberg server at *url*, software: *sw-version*, interface: *int-version*

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4192

Recovery:

No action required.

7068 - CAC: Invalid version report from Tandberg server at *url*

Description: Invalid version report from Tandberg server at *url*

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4193

Recovery:

Contact the Tekelec [Customer Care Center](#).

7069 - CAC: Sending keepalive request to Tandberg server at *url*

Description: Sending keepalive request to Tandberg server at *url*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4194

Recovery:

No action required.

7070 - CAC: Received keepalive response from Tandberg server at *url*

code=*code*, text=*status*, duration *duration* ms

Description: Received a KeepAlive response from a Tandberg server with a status code of *code* and a status description of *status*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4195

Recovery:

No action required.

7071 - CAC: Sync mismatch with *Seachange/Tandberg* server at *ip-address*: VoD server has *n* sessions missing on MPE

Description: Sync mismatch with *Seachange/Tandberg* server at *ip-address*: VoD server has *n* sessions missing on MPE

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID:4196

Recovery:

No action required.

7072 - CAC: Sync mismatch with *Seachange/Tandberg* server at *ip-address*: MPE has # session *id* missing on VoD server

Description: Sync mismatch with *Seachange/Tandberg* server at *ip-address*: MPE has # session *id* missing on VoD server

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4197

Recovery:

Contact the Tekelec [Customer Care Center](#).

7073 - CAC: Session *id* from *ip-address* rejected due to invalid bit rate (*bit-rate*)

Description: Session *id* from *ip-address* rejected due to invalid bit rate (*bit-rate*)

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4198

Recovery:

Contact the Tekelec [Customer Care Center](#).

7075 - CAC: Failed to create CAC session ID *id* from VoD Server at *server-ip* for subscriber IP *sub-ip*: *status*

Description: Could not create CAC session ID.

Note: Supersedes event 4066.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4200

Recovery:

Contact the Tekelec [Customer Care Center](#).

7078 - CAC: Error requesting session list from *Seachange/Tandberg* server at *url*

Description: This is an internal configuration error.

Note: Supersedes event 4159.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4203

Recovery:

Contact the Tekelec [Customer Care Center](#).

7078 - CAC: Unknown response from gate delete request

Gate ID = *gate-id* reply type=*reply-type*

Description: There was an internal error while releasing resources.

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4156

Recovery:

If problem persists, contact the Tekelec [Customer Care Center](#).

7079 - CAC: Forcing synchronization with *Seachange/Tandberg* server at *url*

Description: A manual synchronization has been initiated by a user via the CMP.

Note: Supersedes event 4163.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4204

Recovery:

Contact the Tekelec [Customer Care Center](#).

7080 - CAC: Starting synchronization with *Seachange/Tandberg* server at *url*

Description: Synchronization has started between the MPE device and a VoD server.

Note: Supersedes event 4164.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4205

Recovery:

No action required.

7081 - CAC: Synchronization with *Seachange/Tandberg* server at *url* complete

Status = True/False

Description: Synchronization is complete. If Status is True, the synchronization completed successfully. If Status is False, the synchronization is aborted after 20 minutes of retries.

Note: Supersedes event 4165.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4206

Recovery:

If synchronization continues to fail, contact the Tekelec [Customer Care Center](#).

7082 - CAC: Max sync failures with *Seachange/Tandberg* server at *ip-address*: removing *n* sessions

Description: Synchronization timed out; *n* sessions were removed from the indicated server at the indicated IP address.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4207

Recovery:

No action required.

7083 - CAC: *Seachange/Tandberg reserve of duplicate session id on ip-address complete: status status, duration time ms*

Description: CAC: 0 reserve of duplicate session 1 on 2 complete: status 3, duration 4ms

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4208

Recovery:

Contact the Tekelec [Customer Care Center](#).

7084 - CAC: Sync with *Seachange/Tandberg* at *ip-address*: VoD server has # session id

Description: Sync with *Seachange/Tandberg* at *ip-address*: VoD server has # session id

Severity: Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: CAC

Deprecated ID: 4209

Recovery:

Contact the Tekelec [Customer Care Center](#).

7085 - CAC: Sync with *Seachange/Tandberg* at *ip-address*: MPE has # session *id***Severity:** Warn**Notification:** Trace Log**Alarm:** No**Trap:** No**Server:** MPE**Group:** CAC**Deprecated ID:** 4210**Recovery:**Contact the Tekelec [Customer Care Center](#).**7101 - ADMISSION: MediationSOAP: Busy: criteria *trigger*****Description:** Mediation is busy.**Severity:** Warning**Notification:** Trace Log**Alarm:** No**Trap:** No**Server:** Mediation**Group:** Provision**Recovery:**

No action required.

7102 - ADMISSION: MediationSOAP: Normal: criteria *trigger***Description:** Mediation is back to normal.**Severity:** Notice**Notification:** Trace Log**Alarm:** No**Trap:** No**Server:** Mediation**Group:** Provision**Recovery:**

No action required.

7103 - ADMISSION: MediationSOAP: Resource *name* new condition *trigger* of the criteria *specification*.

Description: The resource monitored by SOAP load shedding is busy. *Name* is the resource name, *trigger* is the criteria which triggers this resource to a busy state, and *specification* is the criteria of this resource.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

7104 - ADMISSION: MediationSOAP: Resource *name* new condition *trigger* of the criteria *specification*.

Description: The resource monitored by SOAP load shedding is back to normal. *Name* is the resource name, *trigger* is the criteria which triggers this resource to a normal state, and *specification* is the criteria of this resource.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

7105 - ADMISSION: MediationSOAP is in a *level* state

Description: The Mediation SOAP interface has a state of busy or normal.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

7541 - SYNC VERIFY REPORTS SUCCESS

Description: Sync: verify *type* success

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

7542 - SYNC VERIFY REPORTS FAIL

Description: Sync: Failed to verify *type*: *verify*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

7561 - SYNC EXCEPTION OCCURRED WHILE PROCESS SYNC RESPONSE *type*

Description: Sync: Exception occurred while process sync response: *type*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

8021 - BoD failure HTTP

Description: HTTP request failed: 0 \n1.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8024 - BoD classifier already active HTTP

Description: Classifier already active for: 0 - request ignored.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8025 - BoD classifier not active HTTP

Description: Classifier not active for: 0 - request ignored.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8050 - BoD success HTTP

Description: HTTP request success: 0.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8070 - BoD failure SOAP

Description: SOAP request failure: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8080 - BoD success SOAP

Description: SOAP request success: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8103 - Policy server connection dropped from server address. BoD has scheduled policy server reconnect task.

Description: Once a Policy server is not connected or the connection is broken for some reason, the BoD server will try to re-connect to the Policy server every 1 or 2 seconds, and log a WARNING message that the corresponding server is disconnected until the Policy server is connected again.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Restart or reboot the failed MPE via the CMP GUI, and make sure the MPE is online to provide service.

8100 - BoD establish connection Policy Server

Description: Established policy server connection to 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8104 - BoD disconnect connection Policy Server

Description: Disconnected Policy Server connection: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8105 - BoD disconnect connection failure Policy Server

Description: Disconnection failure from policy server 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8106 - BoD establish connection failure Policy Server

Description: Disconnection failure from policy server 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8250 - BoD start session cleanup task

Description: BoD session cleanup task starts.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8251 - BoD complete session cleanup task

Description: BoD has completed session cleanup task. # sessions stale sessions have been deleted. It is recommended you perform a database backup before the next auto-delete occurs.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8300 - BoD send message

Description: Sending 0 to 1 and 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8301 - BoD receive message

Description: Received 0 from 1 and 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8302 - BoD request timeout

Description: 0 request to 1 timed out

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8320 - BoD PCMM create session failed

Description: PCMM error encountered for creating session with duration = 0, this is a recoverable error, scheduling a retry for gate set, sessionId = 1, retry attempt 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8321 - BoD PCMM delete session failed

Description: PCMM error encountered for deleting session, scheduling a retry for gate deletion, sessionId = 0, retry attempt 1.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8400 - BoD MAC translation failed due to sessionID connection failed

Description: MAC Translation failed due to connection failure for session ID 0: MAC address: 1 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8401 - BoD MAC translation succeeded

Description: MAC Translation succeeded for session ID 0 on retry attempt 1 MAC address 2. Translated IP address 3.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8402 - BoD MAC translation failed due to no IP address for session ID

Description: MAC Translation failed due to no IP Address returned for session ID 0: MAC address 1 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8403 - BoD MAC translation failed due to response failed for sessionID

Description: MAC Translation failed due to response parse failure for session ID 0: MAC address 1 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8404 - BoD MAC translation failed due to incorrect MAC translation URL for sessionID

Description: MAC Translation failed due to incorrect MAC Translation URL for session ID 0: MAC translation URL 1 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8405 - BoD MAC translation failed due to MAC address connection failure

MAC Translation failed due to connection failure for MAC address: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8406 - BoD MAC translation failed due to no IP address for MAC address

MAC Translation failed due to no IP address for MAC address: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8407 - BoD MAC translation failed due to response failed for MAC address

MAC Translation failed due to parse failure for MAC address: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8408 - BoD MAC translation failed due to incorrect MAC translation URL for MAC Address

Description: MAC Translation failed due to incorrect MAC Translation URL for MAC Translation URL: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8411 - BoD session notification return success

Description: Notification for 0 is sent.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8412 - BoD session notification return other status

Description: Server returns 0 when notification out.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8413 - BoD session notification expire

Description: Notification expired: 0.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8414 - BoD session notification retry

Description: Notification retry 0.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8420 - Statistics of Discovered IPv6 subnets were filtered for each CMTS

Description: On CMP or DC, the discovered subnets were filtered on a certain CMTS, and show the number of subnets before and after the filtering.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP, DC

Group: N/A

Recovery:

No action required.

8421 - Statistics of Discovered IPv6 subnets were filtered for all CMTS

Description: On CMP or DC, the discovered subnets were filtered on all the CMTS, and show the number of subnets before and after the filtering.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP, DC

Group: N/A

Recovery:

No action required.

8422 - Statistics of Discovered IPv6 subnets were aggregated for each CMTS

Description: On CMP or DC, the discovered subnets were aggregated on a certain CMTS, and show the number of subnets before and after the aggregation.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP, DC

Group: N/A

Recovery:

No action required.

8423 - Statistics of Discovered IPv6 subnets were aggregated for all CMTS

Description: On CMP or DC, the discovered subnets were aggregated on all the CMTS, and show the number of subnets before and after the aggregation.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP, DC

Group: N/A

Recovery:

No action required.

8424 - IPv6 subnet settings deployed to MA successfully

Description: IPv6 subnet settings were deployed to all MAs successfully.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: N/A

Recovery:

No action required.

8425 - IPv6 subnet settings were deployed to some MA failed

Description: IPv6 subnet settings were deployed to some MAs failed.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: N/A

Recovery:

Reapply on corresponding MA by the content of trace log.

8500 - MA server started

Description: MA server has started.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

8501 - BoD HTTP Request Failed

Description: HTTP request failed: 0 \n1

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8502 - BoD Classifier Active

Description: Classifier already active for SUBIP=0; SUBPORT=1; DESTIP=2; DESTPORT=3 request ignored.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8503 - BoD: Policy Server connection dropped

Description: Policy Server has dropped connection from 0 1. BoD has scheduled policy server reconnect task.

Severity: Alert

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8504 - BoD: Disconnected policy server connection

Description: Disconnected policy server connection 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8505 - BoD: Disconnection failure from policy server

Description: Disconnection failure from policy server 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8506 - BoD connection failure

Description: Could not establish policy server connection to 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8507 - BoD auto delete started

Description: BoD has reached the maximum number of historic sessions (0) allowed in the BoD database. BoD is minimally auto-deleting the oldest 1 sessions to get back to this limit.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8508 - BoD auto delete ended

Description: BoD has completed the auto-deletion of the oldest historic sessions in the BoD database; 0 historic sessions have been deleted. It is recommended you perform a database backup to reduce the size of your database before the next auto-delete occurs.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8509 - BoD sending debug information

Description: BoD is sending debugging information 0 to 1 2

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8510 - BoD received information

Description: BoD received information 0 from 1 2

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8511 - BoD received warning

Description: BoD received warning 0 from 1 2

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8512 - BoD MAC translation succeeded

Description: MAC Translation succeeded for session ID 0 on retry attempt 1. MAC address: 2. Translated IP address: 3.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8513 - BoD MAC translation IP failure

Description: MAC Translation failed due to no IP Address returned for session ID 0: MAC address: 1 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8514 - BoD MAC translation failure due to response parse failure

Description: MAC Translation failed due to response parse failure for session ID 0: MAC address: 1 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8515 - BoD MAC translation failure due to incorrect MAC Translation URL for session ID

Description: MAC Translation failed due to incorrect MAC Translation URL for session ID 0: MAC Translation URL: {1 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8516 - BoD MAC translation failure due to connection failure for MAC address

Description: MAC Translation failed due to connection failure for MAC address: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8517 - MAC Translation failed due to no IP Address returned for MAC address

Description: MAC Translation failed due to no IP Address returned for MAC address: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8518 - MAC Translation failed due to response parse failure for MAC address

Description: MAC Translation failed due to response parse failure for MAC address: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8519 - MAC Translation failed due to incorrect MAC Translation URL for MAC Translation URL

Description: MAC Translation failed due to incorrect MAC Translation URL for MAC Translation URL: 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8520 - RDR: Failed to parse service index

Description: RDR: Failed to parse service index: 0. Skipping this RDR.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8521 - RDR: Client or Server has closed the socket connection

Description: RDR: Client or Server has closed the socket connection.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8522 - RDR: Error starting RDR service on port

Description: RDR: Error starting RDR service on port : 0. Error is: 1.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8523 - RDR: port busy

Description: RDR: port 0 busy, retrying. Attempt number: 1.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8524 - RDR: Fatal error starting RDR service on port

Description: RDR: Fatal error starting RDR service on port 0.

Severity: Critical

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8525 - RDR: Start message processing

Description: RDR: Start message processing 0.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8526 - RDR: Stop message processing

Description: RDR: Stop message processing 0.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8527 - RDR: Start message processing

Description: RDR: Start message processing 0.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8528 - Edge QAM Device discovered

Description: Edge QAM Device 0 discovered from the policy server 1.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8529 - PCMM: Sending *msg-type* to AM *id*

Description: The specified message type was sent to the specified AM (or upstream policy server).

Note: This message is logged at the Warning level when the PCMM message is an error message such as GateSetErr, GateDeleteErr, or GateInfoErr, and logged at the Info level when the message is an ACK such as GateSetAck, GateInfoAck, or GateDeleteAck.

Severity: Info, Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Deprecated ID: 1013

Recovery:

Contact the Tekelec [Customer Care Center](#).

8530 - PCMM: Received *msg-type* from *id*

Description: The specified message type was received from the specified CMTS (or downstream policy server).

Note: This message is logged at the Warning level when the PCMM message is an error message such as GateSetErr, GateDeleteErr, or GateInfoErr, and logged at the Info level when the message is an ACK such as GateSetAck, GateInfoAck, or GateDeleteAck.

Severity: Info, Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: PCMM

Deprecated ID: 1012

Recovery:

Contact the Tekelec [Customer Care Center](#).

8531 - DQOS: Sending *msg-type* to CMS *id*

Description: The specified message type was sent to the specified CMS.

Severity: Info, Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: DQOS

Deprecated ID: 1113

Recovery:

This message is logged at the Warning level when the DQOS message is an error message such as GAteSetErr, GateDeleteErr, or GateInfoErr, and logged at the Info level when the message is an ACK such as GateSetAck, GateInfoAck, or GateDeleteAck.

8532 - SPC DQOS: Sending *msg-type* to CMSid

Description: The specified message type was sent to the specified CMTS. If the message is reporting an error, then this message is logged at the Warning level, otherwise it is logged at the Info level.

Severity: Info, Warn

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SPC DQOS

Deprecated ID: 1213

Recovery:

Contact the Tekelec [Customer Care Center](#).

8534 - RDR: Quota message processing

Description: RDR: Quota message processing 0.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8535 - RDR: Quota message processing information

Description: RDR: Quota message processing information 0.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

No action required.

8600 - BoD invalid sessionID

Description: Cannot find session from COMCOL which SSID is invalid.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8601 - BoD PCMM request rejected

Description: Reject PCMM request by load shedding, request type is 0, reason is 1.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8602 - BoD PCMM mode not enabled

Description: Cannot find session from COMCOL which SSID is invalid.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8603 - BoD Diameter mode not enabled

Description: Diameter mode was not enabled! Can't handle diameter request 0 for session 1!

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8700 - BoD admission protocol busy event

Description: Admission: 0: Busy: criteria 1.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8701 - BoD admission protocol clear event

Description: Admission: 0: Normal: criteria 1.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8702 - BoD admission component busy event

Description: Admission: 3: Resource 0: new condition 1 of the criteria 2.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8703 - OMStats task failed

Description: BoD admission component clear event.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

8704 - BoD PCMM too busy set

Description: Admission: 0 is in a 1 state.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: BoD

Group: BoD

Recovery:

Contact the Tekelec [Customer Care Center](#).

10000 - ADS: Analytics Data Stream connection to *Analytics Client ID* has been established for Channel: *Channel Type*, ex Policy Event Version: *ADS Interface Version* Connection established to the MPE from an Analytics client

Description: Connection established to the MPE from an Analytics client.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: ADS

Recovery:

No action required.

10001 - ADS: Analytics Data Stream connection to *Analytics Client ID* was closed

Description: Connection between the MPE and Analytics client was closed.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: ADS

Recovery:

No action required.

10002 - ADS: Lost Analytics Data Stream connection to *Analytics Client ID*

Description: Connection between MPE and Analytics client was closed due to error.

Severity: Warning

Notification: Trace Log

Alarm: Yes - 78000

Trap: No

Server: MPE

Group: ADS

Recovery:

No action required.

10003 - ADS: Error processing Analytics Data Stream message received from *Analytics Client ID*

Description: Analytics Data Stream Request from Analytics Client resulted in error.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: ADS

Recovery:

No action required.

10004 - ADS: Error sending Analytics Data Stream message to *Analytics Client ID*

Description: Error occurred while sending Analytics Data Stream message from the MPE.

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: ADS

Recovery:

No action required.

10005 - ADS: Analytics Data Stream encountered an error

Description: Error occurred during Analytics Data Stream processing.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: ADS

Recovery:

No action required.

10006 - Sy: Received notification from *Sy Identity message: Diameter message*

Description: Indicates an SNR was received from the OCS and provides the message details.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No action required.

10007 - Sy: Peer Realm is undefined

Description: Undefined Realm in Sy configuration.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

Check the configured Realm for the connection.

10008 - Sy: Primary address is undefined

Description: Undefined Address in Sy configuration.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

Check the configured Address for the connection.

10009 - Sy: Searching *Sy Identity* for subscriber: *Subscriber IDs*

Description: Indicates a new SLR search has been started for the given subscriber.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No actions required.

10010 - Sy: Search results from peer *Sy Identity* for subscriber *Subscriber IDs* are: *Policy Counter values*

Description: Indicates a successful SLR/SLA lookup and details the contents.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No actions required.

10012 - Sy: Search failure on *Sy Identity*: *Diameter Error Code* subscriber *Subscriber IDs*

Description: Lookups that result in a failure response in the SLA that occur during a Sy SLR lookup with the OCS.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No actions required.

10014 - Sy:Policy Action failure attempting to send SLR Request Type SLR to *Sy data source name* on MPE *MPE name* for subscriber: *Subscriber ID* : *Error Message*

Description: The OCS message to *Sy data source name* for *Subscriber ID* initiated by policy action failed with *Error Message*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No actions required.

10020 - CMP started

Description: CMP Started.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSSI

Recovery:

No actions required.

10021 - Import XML add

Description: Import XML add *type*, executed by *user name*, \nSuccessful: *count* \nfailed: *count*, \ntotal execution time *execution time* millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSSI

Recovery:

No actions required.

10022 - Import XML update

Description: Import XML update 0, executed by 4, \nSuccessful: 1 \nfailed: 2, \ntotal execution time 3millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSSI

Recovery:

No actions required.

10023 - Import XML delete

Description: Import XML delete 0, executed by 4, \nSuccessful: 1 \nfailed: 2, \ntotal execution time 3millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSSI

Recovery:

No actions required.

10024 - Import XML fail

Description: Import XML fail 0, executed by 4, \nSuccessful: 1 \nfailed: 2, \ntotal execution time 3millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSS1

Recovery:

No actions required.

10025 - XML add fail

Description: Import XML add 0 to group executed by 4, \nSuccessful: 1 \nfailed: 2, \ntotal execution time 3millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP

Group: OSS1

Recovery:

No actions required.

10026 - RC proxy apply2

Description: Apply *data type* to MPE (HostName: *IP/hostname*), executed by *user name* \nTotal execution time *execution time* millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Configuration

Recovery:

No actions required.

10027 - RC proxy apply

Description: Apply *data type* to MPE (HostName: *IP/Hostname*), executed by *user name* \nTotal execution time *execution time* millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Configuration

Recovery:

No actions required.

10028 - RC proxy send

Description: Send message (*message* to MPE (HostName: *IP/hostname*), executed by *username* \nTotal execution time *execution time* millisecond.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: CMP/MPE

Group: Configuration

Recovery:

No actions required.

10029 - Starting Statistics Rsync Cleanup task

Description: Starting Statistics Rsync Cleanup task

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

10031 - Diameter Service Invalid XML

Description: Incorrect XML syntax in Diameter services files *filename* \n *error message* .

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

10032 - Starting *task name* task

Description: Starting *name* task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No actions required.

10033 - Task was successful for sync local repository to remote server

Description: *name* Task was successful for sync local repository to remote server *ip address* after retry *count* times.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

10036 - Retry fail

Description: Diameter:PCC rule *rulename* retry failed after *count* attempts for subscriber *subscriber ID* *Session ID*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Diameter Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

10037 - DBPLUGIN: No matches for *criteria*, search type *ID*

Description: DbPlugin search request did not find any results

Severity: Debug

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Data Source

Recovery:

No actions are required

10038 - SMTP: SMTP functionality is not enabled to send message

Description: SMTP: SMTP functionality is not enabled to send message.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SMTP

Recovery:

No actions required.

10039 - RADIUS: Initilizing communications on port

Description: RADIUS: Initilizing communications on port *port*.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Radius

Recovery:

No actions required.

10040 - RADIUS: Started listening on port

Description: RADIUS: Initilizing communications on port *port*.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Radius

Recovery:

No actions required.

10041 - RADIUS:Dropping invalid message

Description: RADIUS: Initilizing communications on port *port*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Radius

Recovery:

Contact the Tekelec [Customer Care Center](#).

10042 - RADIUS: Dropping message with bad MD5, probably bad password

Description: RADIUS:Dropping message with bad MD5, probably bad password in 0.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Radius

Recovery:

Contact the Tekelec [Customer Care Center](#).

10043 - RADIUS:Sent

Description: RADIUS: Initilizing communications on port *port*.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Radius

Recovery:

No actions required.

10044 - Policy event

Description: Policy event: *event message*

Severity: Info

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: SMTP

Recovery:

No actions required.

10045 - RADIUS:Start failed on port

Description: RADIUS:Start failed on port *port*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: RADIUS

Recovery:

Contact the Tekelec [Customer Care Center](#).

10046 - RADIUS: Received *message code / status type:accounting type* *packet ID / session ID* from *client address.message*

Description: RADIUS: Received RADIUS message.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: RADIUS

Deprecated ID: 2704

Recovery:

No actions are required

10048 - Diameter: SCTP path on association ID address

ADDR_CONFIRMED/ADDR_UNREACHABLE/ADDR_AVAILABLE

Description: An SCTP path is unavailable. An info level message is generated when a backup or non-primary path is confirmed by the SCTP association. An error level message is generated when one of the paths fails, whether it is a primary or non-primary path. A notice level message is generated when a path that previously failed recovers.

Severity: Info, Notice, Warning

Notification: Trace Log

Alarm: Yes

Trap: No

Server: MPE, MRA

Group: Diameter

Deprecated ID:1414

Recovery:

If the problem persists, contact Customer Support.

10100 - Average session size exceeds the projected session size, current average session size

Description: Average session size exceeds the projected session size *size*, current average session size: *size*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10101 - Average session size in below the projected session size

Description: Average session size is below the projected session size *size*, current average session size: *size*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10102 - Session database size reached threshold percent of session database capacity

Description: Session database size reached threshold percent of session database capacity *threshold*, current database session size percentage: %.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10103 - Session database size below threshold percent of session database capacity

Description: Session database size below threshold percent of session database capacity *threshold*, current database session size percentage: %.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MPE

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10104 - Average binding size exceeds the projected binding size

Description: Average binding size exceeds the projected binding size *size*, current average binding size: *size*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10105 - Average binding size is below the projected binding size

Description: Average binding size exceeds the projected binding size *size*, current average binding size: *size*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: MRA

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10106 - Binding database size reached threshold percent of binding database capacity

Description: Binding database size reached threshold percent of binding database capacity *threshold*, current binding database size percentage: *size*.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MRA

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10107 - Binding database size is below threshold percent of binding database capacity

Description: Binding database size is below threshold percent of binding database capacity *threshold*, current binding database size percentage: *size*.

Severity: Warning

Notification: Trace Log

Alarm: Yes

Trap: Yes

Server: MRA

Group: Admission Control

Recovery:

Contact the Tekelec [Customer Care Center](#).

10108 - Starting Replication Statistics task

Description: Starting Replication Statistics task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

10109 - Replication Statistics Task failed

Description: Replication Statistics Task failed. \n0.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

Contact the Tekelec [Customer Care Center](#).

10110 - Replication Statistics Task completed successfully

Description: Replication Statistics Task completed successfully.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

10111 - Finishing Replication Statistics task

Description: Finishing Replication Statistics task.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

10112 - Replication Statistics collection complete and data is available for request

Description: Replication Statistics collection complete and data is available for request.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

10113 - Tx Conn Unavail Discard

Description: The number of egress Diameter messages that were discarded by the CDL because the egress connection was unavailable.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

10114 - Tx Per Conn Queue Full Discard

Description: The number of egress Diameter messages that were discarded because the Per Connection Egress Message Queue was full.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: DC

Group: Data Collection Task

Recovery:

No action required.

10120 - License Validation

Alarm Type: LOG

Description: License key validation has been run.

Severity: Info

Instance:

HA Score: Normal

Auto Clear Seconds: 0

OID: tekelecLogLicenseValidation

Recovery:

No action required.

10121 - Ev Conn Far End Close

Alarm Type: LOG

Description: Number of times the far end closed the connection.

Severity: Info

Instance:

HA Score: Normal

Auto Clear Seconds: 0

OID: tekelecLogLicenseValidation

Recovery:

No action required.

15101 - MEDIATION SPR CONNECTION EXCEPTION

Description: Provision function SDM connection got exception.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

Contact the Tekelec [Customer Care Center](#).

15102 - MEDIATION SPR CONNECTION TIMEOUT

Description: Provision function SDM connection got exception.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

Contact the Tekelec [Customer Care Center](#).

15103 - MEDIATION SOAP PARAMETER ERROR

Description: SOAP interface request parameter error.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: MF

Recovery:

No action required.

15104 - MEDIATION OPEN COMCOL ERROR

Description: Provision function open COMCOL error.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

Contact the Tekelec [Customer Care Center](#).

15105 - MEDIATION OPERATE COMCOL ERROR

Description: Provision function operate COMCOL error.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

Contact the Tekelec [Customer Care Center](#).

15106 - MEDIATION SOAP RESULT ERROR

Description: SOAP interface response with any error code.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15107 - MEDIATION SPR CONNECTION REQUEST

Description: Request send to SPR.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15108 - MEDIATION SPR CONNECTION RESPONSE

Description: Request from SPR.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15109 - MEDIATION SOAP REQUEST

Description: SOAP request send from BOSS to MF.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15110 - SPR CONNECTION FAILED

Description: Create connection to SPR *ip* failed.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

Contact the Tekelec [Customer Care Center](#).

15111 - SPR CONNECTION FAILED CLEAR

Description: Create connection to SPR *ip* successfully.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15112 - SPR LICENSE LIMIT SET

Description: The Mediation Server reached 80% of the maximum number of users in SPR.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

Contact the Tekelec [Customer Care Center](#).

15113 - SPR LICENSE LIMIT CLEAR

Description: The Mediation Server is now below 80% of the maximum number of users in SPR.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15114 - SPR TIMEOUT ERROR

Description: The Mediation Server did not receive an SPR Handle Reply within the allotted time.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15115 - MEDIATION ADMISSION PROTOCOL BUSY EVENT

Description: The Mediation Server is busy.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15116 - MEDIATION ADMISSION PROTOCOL CLEAR EVENT

Description: The Mediation Server is no longer busy.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15117 - MEDIATION ADMISSION COMPONENT BUSY EVENT

Description: The resource monitored by SOAP load shedding is busy.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15118 - MEDIATION ADMISSION COMPONENT CLEAR EVENT

Description: The resource monitored by SOAP load shedding is no longer busy.

Severity: Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15119 - MEDIATION SOAP TOO BUSY SET/MEDIATION SOAP TOO BUSY CLEAR

Description: The SOAP interface state of the Mediation Server has either changed from normal (not busy) to busy or from busy to normal (not busy).

Severity: Warning/Notice

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action required.

15121 - SYNC SERVER ERROR

Description: Sync: Exception has occurred in sync server *server*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15122 - SYNC STOP SERVER ERROR

Description: Sync: Could not stop *server* component: *component*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15123 - SYNC THREAD UNCAUGHT EXCEPTION

Description: Sync: Sync thread *server* uncaught exception: *exception*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15124 - SYNC EXEC CMD FAIL

Description: Sync: Command *command* executes failure.

Severity: Fail

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15125 - SYNC EXEC CMD ERROR

Description: Sync: Exception occurred while executes command *type: command*.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15126 - SYNC ACCEPT APP SYNC REQUEST

Description: Sync: Accepted apply sync request: *request*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

15127 - SYNC REJECT APP SYNC REQUEST

Description: Sync: Sync busy at *request*, reject apply sync request.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

15128 - SYNC APP SYNC REQUEST EXCEPTION

Description: Sync: Exception occurred while process apply sync request: *request*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15129 - SYNC APP SYNC RESPONSE

Description: Sync: Received apply sync response: *type.response*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

15130 - SYNC APP SYNC RESPONSE EXCEPTION

Description: Sync: Exception occurred while process apply sync response: *type*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15131 - SYNC TOO BUSY REJECT REQUEST

Description: Sync: Sync server too busy, reject sync request: *type*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15132 - SYNC INVALID REQUEST

Description: Sync: Invalid sync request: *type*.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

15133 - SYNC HANDLE REQUEST EXCEPTION

Description: Sync: Exception occurred while process sync request: *type*.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15134 - SYNC ACCEPT SYNC REQUEST

Description: Sync: Accept sync request: *type*.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

15135 - SYNC OPEN COMCOL FAIL

Description: Sync: failed to open database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15136 - SYNC CLOSE COMCOL FAIL

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15137- SYNC VERIFY SUCCESS

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15138 - SYNC VERIFY FAIL

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15139 - SYNC RESOLVE SUCCESS

Description: Sync: Resolve conflict success.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

15140 - SYNC RESOLVE FAIL

Description: Sync: Failed to resolve conflict : *type*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15141 - SYNC CREATE DATS SUCCESS

Description: Sync: Create sync *type*-data files success.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

15142 - SYNC CREATE DATS FAIL

Description: Sync: Failed to create *type*-data files: *file*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15143 - DO SYNC FAIL

Description: Sync: Failed to do sync, *type*: *file*. All errors that occur during the sync procedure will report this trace log. Examples: (1) failover: already waited *integer* ms, but server is still not ready. (2) receiving: reports can't fully received during *integer* seconds. (3) timeout: task can't be completed during *integer* s. (4) failover: failed to do sync after failover, can't write data to *request file* . (5) failover: can't upload data: *reason*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15144 - SYNC CREATE SYNC RESPONSE

Description: Sync: create sync response: *type*

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15145 - Sync: Exception occurred while processing sync response

Description: Process sync response failed.

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

Contact the Tekelec [Customer Care Center](#).

15146 - SYNC DISK QUOTA EXCEED

Description: Sync: Backup folder disk quota exceeded. Disk quota: *quota*, total usage: *usage*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15147 - SYNC DISK NO SPACE

Description: Sync: No space left on device: *directory*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15148 - SYNC DISK NO SPACE CLEAR

Description: Disk space cleaned on device, disk space released.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Provision

Recovery:

No action.

15200 - PM GEN STATS SYNC TASK START

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15201 - PPM GEN STATS SYNC TASK SUCCESS

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15202 - PM GEN STATS SYNC TASK FAIL

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15203 - PM GEN STATS SYNC TASK END

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15204 - PM STATS SYNC TASK START

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15205 - PM STATS SYNC TASK SUCCESS

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15206 - PM STATS SYNC TASK FAIL

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15207 - PM STATS SYNC TASK END

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15208 - PM STATS SYNC TASK REPOSITORY SUCCESS

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

15209 - PM STATS SYNC TASK REPOSITORY FAIL

Description: Sync: failed to close database *type: database*

Severity: Error

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

Contact the Tekelec [Customer Care Center](#).

17100 - MDF Soap Result Error

Description: MDF: SOAP result error.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17102 - MDF Soap Parameter Error

Description: MDF: SOAP Request Parameter Error

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17103 - MDF No QP Name Error

Description: MDF: Cannot get quota profile name.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17104 - MDF Soap Illegal OPMD Change

Description: MDF: SOAP request illegal OPMD change.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17105 - MDF Soap Client Result Error

Description: MDF: SOAP client result error.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17106 - MDF Cannot Parse SDM Response

Description: MDF: SDM client cannot parse SDM response.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17107 - MDF IMSI Not In Range

Description: MDF: IMSI is not in the SPR IMSI range.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17108 - MDF Soap Client Request

Description: MDF: Send SOAP request from MDF with special userid.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17109 - MDF Soap Client Response

Description: MDF: Received SOAP response with special userid.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17110 - MDF SPR Message

Description: MDF: SPR message.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17111 - MDF Get Subscriber

Description: MDF: Get subscriber.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17112 - MDF Illegal Notify Subscriber

Description: MDF: Illegal notify subscriber.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17113 - MDF Soap Request

Description: MDF: SOAP request message.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17114 - MDF Soap Response

Description: MDF: SOAP response message.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17115 - MDF Out SPR Message

Description: MDF: SPR out message.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17116 - MDF IMSI Not In SPR

Description: MDF: IMSI is not in SPR IMSI range.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17118 - MDF IMSI In SPR

Description: MDF: IMSI is in SPR IMSI range.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17119 - MDF IMSI In S-SPR

Description: MDF: IMSI is in S-SPR IMSI range.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17120 - MDF DYQ Was Expired

Description: MDF: Discard expired dynamic quota.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

17121 - MDF Quota Was Expired

Description: MDF: Discard quota because its based-dynamic-quota is expired.

Severity: Warning

Notification: Trace Log

Alarm: No

Trap: No

Server: Mediation

Group: Sync

Recovery:

No action required.

40015 - Load is OK

Description: CPU load is okay.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No actions required.

40024 - Home reports blade is master

Description: Indicates the current blade is the master in the cluster.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No actions required.

50008 - Home reports fully redundant

Description: Indicates that replication between blades in one cluster is working correctly.

Severity: Info

Notification: Trace Log

Alarm: No

Trap: No

Server: MPE

Group: SY

Recovery:

No actions required.

Chapter 4

Alarms and Events

Topics:

- *Alarms formatting information.....291*
- *Alarm and Event Severity Levels.....291*
- *Platform (31000-32700).....291*
- *QBus Platform (70000-70999).....339*
- *Policy Server (71000-89999).....347*

Alarms and Events provides general alarm and event information, and lists the types of alarms and events that can occur on the system. Alarms and events are recorded in a database log table. Note that alarms for all modes are represented in this list (cable, wireline, and wireless).

Note: If you encounter an alarm not in this document, contact the Tekelec *Customer Care Center*.

Alarms formatting information

This section of the document provides information to help you understand why an alarm occurred and to provide a recovery procedure to help correct the condition that caused the alarm.

The information provided about each alarm includes:

- Alarm Type: the type of alarm that has occurred.
- Description: describes the reason for the alarm
- Default Severity: the severity of the alarm. This severity may vary, depending on user-defined and specific application settings.
- OID: alarm identifier that appears in SNMP traps
- Alarm ID: alarm identifier that is used internally
- Recovery: provides any necessary steps for correcting or preventing the alarm

Alarm and Event Severity Levels

Alarms can be one of three severity levels:

1. Critical
2. Major
3. Minor

Events note the occurrence of an expected condition and are logged in the Trace Log. Events have these severity levels:

1. Emergency
2. Alert
3. Critical
4. Error
5. Warning
6. Notice
7. Info
8. Debug

Platform (31000-32700)

This section provides information and recovery procedures for the Platform alarms, ranging from 31000-32700.

31000 - S/W Fault

Alarm Type: SW

Description: Program impaired by s/w fault

Default Severity: Minor

OID: comcolSwFaultNotify

Recovery:

1. Export event history for the given server and the given process.
2. Contact Tekelec [Customer Care Center](#).

31001 - S/W Status

Alarm Type: SW

Description: Program status

Default Severity: Info

OID: comcolSWStatusNotify

Recovery:

No action required.

31002 - Process Watchdog Failure

Alarm Type: SW

Description: Process watchdog timed out

Default Severity: Minor

OID: comcolProcWatchdogFailureNotify

Recovery:

1. Export event history for the given server and the given process.
2. Contact Tekelec [Customer Care Center](#).

31003 - Thread Watchdog Failure

Alarm Type: SW

Description: Thread watchdog timed out

Default Severity: Minor

OID: comcolThreadWatchdogFailureNotify

Recovery:

1. Export event history for the given server and the given process.
2. Contact Tekelec [Customer Care Center](#).

31100 - DB Replication Fault

Alarm Type: SW

Description: The DB replication process is impaired by a s/w fault.

Default Severity: Minor

OID: comcolDbReplicationFaultNotify

Recovery:

1. Export event history for the given server.
2. Contact Tekelec [Customer Care Center](#).

31101 - DB Replication To Slave Failure

Alarm Type: REPL

Description: DB replication to a slave DB has failed

Default Severity: Minor

OID: comcolDbRepToSlaveFailureNotify

Recovery:

1. Check network connectivity between the affected servers.
2. If there are no issues with network connectivity, contact the Tekelec [Customer Care Center](#).

31102 - DB Replication From Master Failure

Alarm Type: REPL

Description: DB replication from a master DB has failed

Default Severity: Minor

OID: comcolDbRepFromMasterFailureNotify

Recovery:

1. Check network connectivity between the affected servers.
2. If there are no issues with network connectivity, contact the Tekelec [Customer Care Center](#).

31103 - DB Replication Update Fault

Alarm Type: REPL

Description: DB replication process cannot apply update to DB

Default Severity: Minor

OID: comcolDbRepUpdateFaultNotify

Recovery:

1. Export event history for the given server and inetsync task.
2. Contact Tekelec [Customer Care Center](#).

31104 - DB Replication Latency Over Threshold

Alarm Type: REPL

Description: DB replication latency has exceeded thresholds

Default Severity: Minor

OID: comcolDbRepLatencyNotify

Recovery:

1. If this alarm is raised occasionally for short time periods (a couple of minutes or less), it may indicate network congestion or spikes of traffic pushing servers beyond their capacity. Consider re-engineering network capacity or subscriber provisioning.
2. If this alarm does not clear after a couple of minutes, contact Tekelec [Customer Care Center](#).

31105 - DB Merge Fault

Alarm Type: SW

Description: The DB merge process (inetmerge) is impaired by a s/w fault

Default Severity: Minor

OID: comcolDbMergeFaultNotify

Recovery:

1. Export event history for the given server and inetmerge task.
2. Contact Tekelec [Customer Care Center](#).

31106 - DB Merge To Parent Failure

Alarm Type: COLL

Description: DB merging to the parent Merge Node has failed

Default Severity: Minor

OID: comcolDbMergeToParentFailureNotify

Recovery:

1. Check network connectivity between the affected servers.
2. If there are no issues with network connectivity, contact the Tekelec [Customer Care Center](#).

31107 - DB Merge From Child Failure

Alarm Type: COLL

Description: DB merging from a child Source Node has failed

Default Severity: Minor

OID: comcolDbMergeFromChildFailureNotify

Recovery:

1. Check network connectivity between the affected servers.
2. If there are no issues with network connectivity, contact the Tekelec [Customer Care Center](#).

31108 - DB Merge Latency Over Threshold

Alarm Type: COLL

Description: DB Merge latency has exceeded thresholds

Default Severity: Minor

OID: comcolDbMergeLatencyNotify

Recovery:

1. If this alarm is raised occasionally for short time periods (a couple of minutes or less), it may indicate network congestion or spikes of traffic pushing servers beyond their capacity. Consider re-engineering network capacity or subscriber provisioning.
2. If this alarm does not clear after a couple of minutes, contact Tekelec [Customer Care Center](#)

31109 - Topology Config Error

Alarm Type: DB

Description: Topology is configured incorrectly

Default Severity: Minor

OID: comcolTopErrorNotify

Recovery:

1. This alarm may occur during initial installation and configuration of a server. No action is necessary at that time.
2. If this alarm occurs after successful initial installation and configuration of a server, contact the Tekelec [Customer Care Center](#).

31110 - DB Audit Fault

Alarm Type: SW

Description: The DB audit process (iaudit) is impaired by a s/w fault

Default Severity: Minor

OID: comcolDbAuditFaultNotify

Recovery:

1. Export event history for the given server and idbsvc task.
2. Contact Tekelec [Customer Care Center](#).

31111 - DB Merge Audit in Progress

Alarm Type: COLL

Description: DB Merge Audit between mate nodes in progress

Default Severity: Minor

OID: comcolDbMergeAuditNotify

Recovery:

No action required.

31112 - DB Replication Update Log Transfer Timed Out

Alarm Type: REPL

Description: DB Replicated data may not have transferred in the time allotted.

Default Severity: Minor

OID: comcolDbRepUpLogTransTimeoutNotify

Recovery:

No action required. Contact Tekelec [Customer Care Center](#) if this occurs frequently.

31113 - DB Replication Manually Disabled

Alarm Type: REPL

Description: Replication Manually Disabled

Default Severity: Minor

OID: comcolDbReplicationManuallyDisabledNotify

Recovery:

No action required.

31114 - DB Replication over SOAP has failed

Alarm Type: REPL

Description: DB replication of configuration data via SOAP has failed

Default Severity: Minor

OID: comcolDbReplicationSoapFaultNotify

Recovery:

1. Check network connectivity between the affected servers.
2. If there are no issues with network connectivity, contact the Tekelec [Customer Care Center](#).

31115 - DB Service Fault

Alarm Type: SW

Description: The DB service process (idbsvc) is impaired by a s/w fault

Default Severity: Minor

OID: comcolDbServiceFaultNotify

Recovery:

1. Export event history for the given server and idbsvc task.
2. Contact Tekelec [Customer Care Center](#).

31116 - Excessive Shared Memory

Alarm Type: MEM

Description: The amount of shared memory consumed exceeds configured thresholds

Default Severity: Major

OID: comcolExcessiveSharedMemoryConsumptionNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31117 - Low Disk Free

Alarm Type: DISK

Description: The amount of free disk is below configured thresholds

Default Severity: Major

OID: comcolLowDiskFreeNotify

Recovery:

1. Remove unnecessary or temporary files from partitions.
2. If there are no files known to be unneeded, contact Tekelec [Customer Care Center](#).

31118 - DB Disk Store Fault

Alarm Type: DISK

Description: Writing the database to disk failed

Default Severity: Minor

OID: comcolDbDiskStoreFaultNotify

Recovery:

1. Remove unnecessary or temporary files from partitions.

2. If there are no files known to be unneeded, contact Tekelec [Customer Care Center](#).
3. When configuring/reconfiguration a system, changing the NTP server and/or the OAM IP from initial configuration screen in platcfg without stopping the Policy application and COMCOL can cause this alarm. Resolution: Mark standby CMP cluster as "force-standby", and clear the COMCOL database to solve this issue. To avoid this alarm while changing the NTP server and/or OAM IP(s) is to:
 - a) Stop qp_procmgr and COMCOL services
 - b) Perform the NTP server / OAM IP change
 - c) Restart qp_procmgr and COMCOL services

31119 - DB Updatelog Overrun

Alarm Type: DB

Description: The DB update log was overrun increasing risk of data loss

Default Severity: Minor

OID: comcolDbUpdateLogOverrunNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31120 - DB Updatelog Write Fault

Alarm Type: DB

Description: A DB change cannot be stored in the updatelog

Default Severity: Minor

OID: comcolDbUpdateLogWriteFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31121 - Low Disk Free Early Warning

Alarm Type: DISK

Description: The amount of free disk is below configured early warning thresholds

Default Severity: Minor

OID: comcolLowDiskFreeEarlyWarningNotify

Recovery:

1. Remove unnecessary or temporary files from partitions that are greater than 80% full.
2. If there are no files known to be unneeded, contact Tekelec [Customer Care Center](#).

31122 - Excessive Shared Memory Early Warning

Alarm Type: MEM

Description: The amount of shared memory consumed exceeds configured early warning thresholds

Default Severity: Minor

OID: comcolExcessiveSharedMemoryConsumptionEarlyWarnNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31123 - ADIC Complete

Alarm Type: REPL

Description: ADIC found one or more errors that are not automatically fixable.

Default Severity: Info

OID: comcolDbRepAuditCompleteNotify

Recovery:

No action required.

31124 - ADIC Error

Alarm Type: REPL

Description: An ADIC detected errors.

Default Severity: Minor

OID: comcolDbRepAuditCmdErrNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31125 - DB Durability Degraded

Alarm Type: REPL

Description: DB durability has dropped below configured durability level

Default Severity: Major

OID: comcolDbDurabilityDegradedNotify

Recovery:

1. Check configuration of all servers, and check for connectivity problems between server addresses.
2. If the problem persists, contact Tekelec [Customer Care Center](#).

31126 - Audit Blocked

Alarm Type: REPL

Description: Site Audit Controls blocked an inter-site replication audit due to the number in progress per configuration.

Default Severity: Major

OID: comcolAuditBlockedNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31127 - DB Replication Audit Complete

Alarm Type: REPL

Description: DB replication audit completed.

Default Severity: Info

OID: comcolDbRepAuditComplete

Recovery:

No action required.

31128 - ADIC Found Error

Alarm Type: REPL

Description: ADIC found one or more errors that are not automatically fixable.

Default Severity: Major

OID: comcolDbADICError

Recovery:

Contact Tekelec [Customer Care Center](#).

31129 - ADIC Found Minor Issue

Alarm Type: REPL

Description: ADIC found one or more minor issues that can most likely be ignored.

Default Severity: Minor

OID: comcolDbADICWarn

Recovery:

No action required.

31130 - Network Health Warning

Alarm Type: NET

Description: Network health issue detected

Default Severity: Minor

OID: comcolNetworkHealthWarningNotify

Recovery:

1. Check configuration of all servers, and check for connectivity problems between server addresses.
2. If the problem persists, contact Tekelec [Customer Care Center](#).

31140 - DB Perl Fault

Alarm Type: SW

Description: Perl interface to DB is impaired by a s/w fault

Default Severity: Minor

OID: comcolDbPerlFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31145 - DB SQL Fault

Alarm Type: SW

Description: SQL interface to DB is impaired by a s/w fault

Default Severity: Minor

OID: comcolDbSQLFaultNotify

Recovery:

1. Export event history for the given server, and Imysqld task.
2. Contact Tekelec [Customer Care Center](#).

31146 - DB Mastership Fault

Alarm Type: SW

Description: DB replication is impaired due to no mastering process (inetsync/inetrep).

Default Severity: Major

OID: comcolDbMastershipFaultNotify

Recovery:

1. Export event history for the given server.

2. Contact Tekelec [Customer Care Center](#).

31147 - DB UpSyncLog Overrun

Alarm Type: SW

Description: UpSyncLog is not big enough for (WAN) replication.

Default Severity: Minor

OID: comcolDbUpSyncLogOverrunNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31148 - DB Lock Error Detected

Alarm Type: DB

Description: DB lock integrity error detected -- The DB service process (idbsvc) has detected an IDB lock-related error caused by another process. The alarm likely indicates a DB lock-related programming error, or it could be a side effect of a process crash.

Default Severity: Minor

OID: comcolDbLockErrorNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31200 - Process Management Fault

Alarm Type: SW

Description: The process manager (procmgr) is impaired by a s/w fault

Default Severity: Minor

OID: comcolProcMgmtFaultNotify

Recovery:

1. Export event history for the given server, all processes.

2. Contact Tekelec [Customer Care Center](#).

31201 - Process Not Running

Alarm Type: PROC

Description: A managed process cannot be started or has unexpectedly terminated

Default Severity: Major

OID: comcolProcNotRunningNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31202 - Unkillable Zombie Process**Alarm Type:** PROC

Description: A zombie process exists that cannot be killed by procmgr. procmgr will no longer manage this process. If the process does not exit, it may be necessary to reboot the server to eliminate the zombie process.

Default Severity: Major

OID: comcolProcZombieProcessNotify

Recovery:

1. If the process does not exit, it may be necessary to reboot the server to eliminate the zombie process.
2. Contact Tekelec [Customer Care Center](#).

31206 - Process Mgmt Monitoring Fault**Alarm Type:** SW

Description: The process manager monitor (pm.watchdog) is impaired by a s/w fault

Default Severity: Minor

OID: comcolProcMgmtMonFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31207 - Process Resource Monitoring Fault**Alarm Type:** SW

Description: The process resource monitor (ProcWatch) is impaired by a s/w fault

Default Severity: Minor

OID: comcolProcResourceMonFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31208 - IP Port Server Fault**Alarm Type:** SW

Description: The run environment port mapper (re.portmap) is impaired by a s/w fault

Default Severity: Minor

OID: comcolPortServerFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31209 - Hostname Lookup Failed

Alarm Type: SW

Description: Unable to resolve a hostname specified in the NodeInfo table.

Default Severity: Minor

OID: comcolHostLookupFailedNotify

Recovery:

1. This typically indicate a DNS Lookup failure. Verify all server hostnames are correct in the GUI configuration on the server generating the alarm.
2. If the problem persists, contact Tekelec [Customer Care Center](#).
3. When configuring/reconfiguration a system, the Primary Site/Secondary Site fields in Topology Settings are used to identify the site in which this cluster is located. If The default value "Unspecified" is kept unchanged while configuring Topology as Geo-redundant sites, the other servers in topology may raise this alarm. Resolution: Select the correct site for each cluster being configured in Topology Settings.

31213 - Process Scheduler Fault

Alarm Type: SW

Description: The process scheduler (ProcSched/runat) is impaired by a s/w fault

Default Severity: Minor

OID: comcolProcSchedulerFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31214 - Scheduled Process Fault

Alarm Type: PROC

Description: A scheduled process cannot be executed or abnormally terminated

Default Severity: Minor

OID: comcolScheduleProcessFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31215 - Process Resources Exceeded

Alarm Type: SW

Description: A process is consuming excessive system resources

Default Severity: Minor

OID: comcolProcResourcesExceededFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31216 - SysMetric Configuration Error

Alarm Type: SW

Description: A SysMetric Configuration table contains invalid data

Default Severity: Minor

OID: comcolSysMetricConfigErrorNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31220 - HA Config Monitor Fault

Alarm Type: SW

Description: The HA manager (cmha) is impaired by a s/w fault

Default Severity: Minor

OID: comcolHaCfgMonitorFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31221 - HA Alarm Monitor Fault

Alarm Type: SW

Description: The high availability alarm monitor is impaired by a s/w fault

Default Severity: Minor

OID: comcolHaAlarmMonitorFaultNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31222 - HA Not Configured

Alarm Type: HA

Description: High availability is disabled due to system configuration

Default Severity: Minor

OID: comcolHaNotConfiguredNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31223 - HA Heartbeat Transmit Failure

Alarm Type: HA

Description: The high availability monitor failed to send heartbeat

Default Severity: Major

OID: comcolHaHbTransmitFailureNotify

Recovery:

1. This alarm clears automatically when the server successfully registers for HA heartbeating.
2. If this alarm does not clear after a couple minutes, contact Tekelec [Customer Care Center](#).

31224 - HA Configuration Error

Alarm Type: HA

Description: High availability configuration error

Default Severity: Major

OID: comcolHaCfgErrorNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

31225 - HA Service Start Failure

Alarm Type: HA

Description: The high availability service failed to start

Default Severity: Major

OID: comcolHaSvcStartFailureNotify

Recovery:

1. This alarm clears automatically when the HA daemon is successfully started.
2. If this alarm does not clear after a couple minutes, contact Tekelec [Customer Care Center](#).

31226 - HA Availability Status Degraded

Alarm Type: HA

Description: The high availability status is degraded due to raised alarms

Default Severity: Major

OID: comcolHaAvailDegradedNotify

Recovery:

1. View alarms dashboard for other active alarms on this server.
2. Follow corrective actions for each individual alarm on the server to clear them.
3. If the problem persists, contact Tekelec [Customer Care Center](#).

31227 - HA Availability Status Failed

Alarm Type: HA

Description: The high availability status is failed due to raised alarms

Default Severity: Critical

OID: comcolHaAvailFailedNotify

Recovery:

1. View alarms dashboard for other active alarms on this server.
2. Follow corrective actions for each individual alarm on the server to clear them.
3. If the problem persists, contact Tekelec [Customer Care Center](#).

31228 - HA Standby Server Offline

Alarm Type: HA

Description: HA Standby Server Offline

Default Severity: Critical

OID: comcolHaStandbyOfflineNotify

Recovery:

1. If loss of communication between the active and standby servers is caused intentionally by maintenance activity, alarm can be ignored; it clears automatically when communication is restored between the two servers.
2. If communication fails at any other time, look for network connectivity issues and/or contact Tekelec [Customer Care Center](#).

31229 - HA Score Changed

Alarm Type: HA

Description: High availability health score changed

Default Severity: Info

OID: comcolHaScoreChangeNotify

Recovery:

Status message - no action required.

31230 - Recent Alarm Processing Fault

Alarm Type: SW

Description: The recent alarm event manager (raclerk) is impaired by a s/w fault

Default Severity: Minor

OID: comcolRecAlarmEvProcFaultNotify

Recovery:

1. Export event history for the given server and raclerk task.
2. Contact Tekelec [Customer Care Center](#).

31231 - Platform Alarm Agent Fault

Alarm Type: SW

Description: The platform alarm agent impaired by a s/w fault

Default Severity: Minor

OID: comcolPlatAlarmAgentNotify

Recovery:

Contact Tekelec [Customer Care Center](#).

31232 - HA Late Heartbeat Warning

Alarm Type: HA

Description: High availability server has not received a heartbeat within the configured interval

Default Severity: Minor

OID: comcolHaLateHeartbeatWarningNotify

Recovery:

No action required; this is a warning and can be due to transient conditions. If there continues to be no heartbeat from the server, alarm 31228 occurs.

31233 - HA Secondary Path Down

Alarm Type: HA

Description: High availability secondary path loss of connectivity

Default Severity: Major

OID: comcolHaSecPathDown

Recovery:

1. If loss of communication between the active and standby servers over the secondary path is caused intentionally by maintenance activity, the alarm can be ignored; it clears automatically when communication is restored between the two servers.
2. If communication fails at any other time, look for network connectivity issues on the secondary network and/or contact Tekelec *Customer Care Center*.

31234 - Untrusted Time Upon Initialization

Alarm Type: SW

Description: Upon system initialization, the system time is not trusted, probably because NTP is misconfigured or the NTP servers are unreachable. There are often accompanying Platform alarms to guide correction. Generally, applications are not started if time is not believed to be correct on start-up. Recovery will often require rebooting the server.

Default Severity: Critical

OID: comcolUtrustedTimeOnInit

Recovery:

1. Correct NTP configuration.
2. If required, contact Tekelec *Customer Care Center*.

31235 - Untrusted Time After Initialization

Alarm Type: SW

Description: After system initialization, the system time has become untrusted, probably because NTP has reconfigured improperly, time has been manually changed, the NTP servers are unreachable, etc. There are often accompanying Platform alarms to guide correction. Generally, applications remain running, but time-stamped data is likely incorrect, reports may be negatively affected, some behavior may be improper, etc.

Default Severity: Critical

OID: comcolUtrustedTimePostInit

Recovery:

1. Correct NTP configuration.
2. If required, contact Tekelec *Customer Care Center*.

31240 - Measurements Collection Fault

Alarm Type: SW

Description: The measurements collector (statclerk) is impaired by a s/w fault

Default Severity: Minor

OID: comcolMeasCollectorFaultNotify

Recovery:

1. Export event history for the given server and statclerk task.
2. Contact Tekelec [Customer Care Center](#).

31250 - RE Port Mapping Fault

Alarm Type: SW

Description: The IP service port mapper (re.portmap) is impaired by a s/w fault

Default Severity: Minor

OID: comcolRePortMappingFaultNotify

Recovery:

This typically indicate a DNS Lookup failure. Verify all server hostnames are correct in the GUI configuration on the server generating the alarm.

31260 - DB SNMP Agent

Alarm Type: SW

Description: The DB SNMP agent (snmpIdbAgent) is impaired by a s/w fault

Default Severity: Minor

OID: comcolDbSnmpAgentNotify

Recovery:

1. Export event history for the given server and all processes.
2. Contact Tekelec [Customer Care Center](#).

31270 - Logging Output

Alarm Type: SW

Description: Logging output set to Above Normal

Default Severity: Minor

OID: comcolLoggingOutputNotify

Recovery:

Extra diagnostic logs are being collected, potentially degrading system performance. Contact Tekelec [Customer Care Center](#).

31280 - HA Active to Standby Transition

Alarm Type: HA

Description: HA active to standby activity transition

Default Severity: Info

OID: comcolActiveToStandbyTransNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31281 - HA Standby to Active Transition

Alarm Type: HA

Description: HA standby to active activity transition

Default Severity: Info

OID: comcolStandbyToActiveTransNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31282 - HA Management Fault

Alarm Type: HA

Description: The HA manager (cmha) is impaired by a s/w fault.

Default Severity: Minor

OID: comcolHaMgmtFaultNotify

Recovery:

Export event history for the given server and cmha task, then contact Tekelec [Customer Care Center](#).

31283 - HA Server Offline

Alarm Type: HA

Description: High availability server is offline

Default Severity: Critical

OID: comcolHAServerOfflineNotify

Recovery

1. If loss of communication between the active and standby servers is caused intentionally by maintenance activity, alarm can be ignored; it clears automatically when communication is restored between the two servers.
2. If communication fails at any other time, look for network connectivity issues and/or contact Tekelec [Customer Care Center](#).

31284 - HA Remote Subscriber Heartbeat Warning

Alarm Type: HA

Description: High availability remote subscriber has not received a heartbeat within the configured interval

Default Severity: Minor

OID: comcolHARemoteHeartbeatWarningNotify

Recovery

1. No action required; this is a warning and can be due to transient conditions. The remote subscriber will move to another server in the cluster.
2. If there continues to be no heartbeat from the server, contact Tekelec [Customer Care Center](#).

31290 - HA Process Status

Alarm Type: HA

Description: HA manager (cmha) status

Default Severity: Info

OID: comcolHaProcessStatusNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31291 - HA Election Status

Alarm Type: HA

Description: HA DC Election status

Default Severity: Info

OID: comcolHAElectionStatusNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31292 - HA Policy Status

Alarm Type: HA

Description: HA Policy plan status

Default Severity: Info

OID: comcolHaPolicyStatusNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31293 - HA Resource Link Status

Alarm Type: HA

Description: HA Resource Agent Link status

Default Severity: Info

OID: comcolHaRaLinkStatusNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31294 - HA Resource Status

Alarm Type: HA

Description: HA Resource registration status

Default Severity: Info

OID: comcolHaResourceStatusNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31295 - HA Action Status

Alarm Type: HA

Description: HA Resource action status

Default Severity: Info

OID: comcolHaActionStatusNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31296 - HA Monitor Status

Alarm Type: HA

Description: HA Monitor action status

Default Severity: Info

OID: comcolHaMonitorStatusNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31297 - HA Resource Agent Info

Alarm Type: HA

Description: HA Resource Agent application information

Default Severity: Info

OID: comcolHaRaInfoNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31298 - HA Resource Agent Detail

Alarm Type: HA

Description: HA Resource Agent application detailed information

Default Severity: Info

OID: comcolHaRaDetailNotify

Recovery:

1. If this alarm occurs during routine maintenance activity, it may be ignored.
2. Otherwise, contact Tekelec [Customer Care Center](#).

31299 - HA Notification Status

Alarm Type: HA

Description: HA Notification Status

Default Severity: Info

OID: comcolHaNotification

Recovery:

No action required.

31300 - HA Control Status

Alarm Type: HA

Description: HA Control action status

Default Severity: Info

OID: comcolHaControl

Recovery:

No action required.

32113 - Uncorrectable ECC Memory Error

Alarm Type: PLAT

Description: Uncorrectable ECC Memory Error -- This alarm indicates that chipset has detected an uncorrectable (multiple-bit) memory error that the ECC (Error-Correcting Code) circuitry in the memory is unable to correct.

Default Severity: Critical

OID: tpdEccUncorrectableError

Recovery

Contact the Tekelec [Customer Care Center](#) to request hardware replacement.

32114 - SNMP Get Failure

Alarm Type: PLAT

Description: SNMP Get Failure -- The server failed to receive SNMP information from the switch.

Default Severity: Critical

OID: tpdSNMPGetFailure

Within this trap is one bind variable, the OID of which is 1.3.6.1.2.1.1.5 <sysname>, where <sysname> is the name of the switch where the failure occurred.

Recovery

1. Use the following command to verify the switch is active: ping switch1A/B (this requires command line access).
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

32115 - TPD NTP Daemon Not Synchronized Failure

Alarm Type: PLAT

Description: This alarm indicates that the server is not synchronized to an NTP source, has not been synchronized for an extended number of hours, and has reached the critical threshold.

Default Severity: Critical

OID: tpdNTPDaemonNotSynchronizedFailure

Recovery

1. Verify NTP settings and that NTP sources can be reached.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

32116 - TPD Server's Time Has Gone Backwards

Alarm Type: PLAT

Description: This alarm indicates that the server's current time precedes the timestamp of the last known time that the server's time was good.

Default Severity: Critical

OID: tpdNTPTimeGoneBackwards

Recovery

1. Verify NTP settings and that NTP sources are providing accurate time.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

32117 - TPD NTP Offset Check Failure

Alarm Type: PLAT

Description: This alarm indicates the NTP offset of the server that is currently being synced to is greater than the critical threshold.

Default Severity: Critical

OID: ntpOffsetCheckFailure descr

Recovery

1. Verify NTP settings, and that NTP sources are providing accurate time.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

32300 – Server Fan Failure

Alarm Type: PLAT

Description: Server Fan Failure -- This alarm indicates that a fan on the application server is either failing or has failed completely. In either case, there is a danger of component failure due to overheating.

Default Severity: Major

OID: tpdFanError

Recovery

Contact the Tekelec [Customer Care Center](#).

32301 - Server Internal Disk Error

Alarm Type: PLAT

Description: Server Internal Disk Error -- This alarm indicates the server is experiencing issues replicating data to one or more of its mirrored disk drives. This could indicate that one of the server's disks has either failed or is approaching failure.

Default Severity: Major

OID: tpdIntDiskError

Recovery

Contact the Tekelec [Customer Care Center](#).

32302 – Server RAID Disk Error

Alarm Type: PLAT

Description: Server RAID Disk Error -- This alarm indicates that the offboard storage server had a problem with its hardware disks.

Default Severity: Major

OID: tpdRaidDiskError

Recovery

Contact the Tekelec [Customer Care Center](#).

32303 - Server Platform Error

Alarm Type: PLAT

Description: Server Platform Error - This alarm indicates an error such as a corrupt system configuration or missing files.

Default Severity: Major

OID: tpdPlatformError

Recovery

Contact the Tekelec [Customer Care Center](#).

32304 - Server File System Error

Alarm Type: PLAT

Description: Server File System Error -- This alarm indicates unsuccessful writing to at least one of the server's file systems.

Default Severity: Major

OID: tpdFileSystemError

Recovery

Contact the Tekelec [Customer Care Center](#).

32305 - Server Platform Process Error

Alarm Type: PLAT

Description: Server Platform Process Error -- This alarm indicates that either the minimum number of instances for a required process are not currently running or too many instances of a required process are running.

Default Severity: Major

OID: tpdPlatProcessError

Recovery

Contact the Tekelec [Customer Care Center](#).

32307 - Server Swap Space Shortage Error

Alarm Type: PLAT

Description: Server Swap Space Shortage Error -- This alarm indicates that the server's swap space is in danger of being depleted. This is usually caused by a process that has allocated a very large amount of memory over time.

Default Severity: Major

OID: tpdSwapSpaceShortageError

Recovery

Contact the Tekelec [Customer Care Center](#).

32308 - Server Provisioning Network Error

Alarm Type: PLAT

Description: Server Provisioning Network Error -- This alarm indicates that the connection between the server's ethernet interface and the customer network is not functioning properly. The eth1 interface is at the upper right port on the rear of the server on the EAGLE backplane.

Default Severity: Major

OID: tpdProvNetworkError

Recovery

1. Verify that a customer-supplied cable labeled TO CUSTOMER NETWORK is securely connected to the appropriate server. Follow the cable to its connection point on the local network and verify this connection is also secure.
2. Test the customer-supplied cable labeled TO CUSTOMER NETWORK with an Ethernet Line Tester. If the cable does not test positive, replace it.
3. Have your network administrator verify that the network is functioning properly.
4. If no other nodes on the local network are experiencing problems and the fault has been isolated to the server or the network administrator is unable to determine the exact origin of the problem, contact the Tekelec *Customer Care Center*.

32312 - Server Disk Space Shortage Error

Alarm Type: PLAT

Description: Server Disk Space Shortage Error -- This alarm indicates that one of the following conditions has occurred:

- A filesystem has exceeded a failure threshold, which means that more than 90% of the available disk storage has been used on the filesystem.
- More than 90% of the total number of available files have been allocated on the filesystem.
- A filesystem has a different number of blocks than it had when installed.

Default Severity: Major

OID: tpdDiskSpaceShortageError

Recovery

Contact the Tekelec *Customer Care Center*.

32313 - Server Default Route Network Error

Alarm Type: PLAT

Description: Server Default Route Network Error -- This alarm indicates that the default network route of the server is experiencing a problem.



Caution: When changing the network routing configuration of the server, verify that the modifications will not impact the method of connectivity for the current login session. The route information must be entered correctly and set to the correct values. Incorrectly modifying the routing configuration of the server may result in total loss of remote network access.

Default Severity: Major

OID: tpdDefaultRouteNetworkError

Recovery

Contact the Tekelec *Customer Care Center*.

32314 - Server Temperature Error

Alarm Type: PLAT

Description: Server Temperature Error -- The internal temperature within the server is unacceptably high.

Default Severity: Major

OID: tpdTemperatureError

Recovery

1. Ensure that nothing is blocking the fan's intake. Remove any blockage.
2. Verify that the temperature in the room is normal. If it is too hot, lower the temperature in the room to an acceptable level.

Note: Be prepared to wait the appropriate period of time before continuing with the next step. Conditions need to be below alarm thresholds consistently for the alarm to clear. It may take about ten minutes after the room returns to an acceptable temperature before the alarm cleared.

3. If the problem has not been resolved, contact the Tekelec [Customer Care Center](#).

32315 – Server Mainboard Voltage Error

Alarm Type: PLAT

Description: Server Mainboard Voltage Error -- This alarm indicates that one or more of the monitored voltages on the server mainboard have been detected to be out of the normal expected operating range.

Default Severity: Major

OID: tpdServerMainboardVoltageError

Recovery

Contact the Tekelec [Customer Care Center](#).

32316 – Server Power Feed Error

Alarm Type: PLAT

Description: Server Power Feed Error -- This alarm indicates that one of the power feeds to the server has failed. If this alarm occurs in conjunction with any Breaker Panel alarm, there might be a problem with the breaker panel.

Default Severity: Major

OID: tpdPowerFeedError

Recovery

1. Verify that all the server power feed cables to the server that is reporting the error are securely connected.
2. Check to see if the alarm has cleared
 - If the alarm has been cleared, the problem is resolved.

- If the alarm has not been cleared, continue with the next step.
- 3. Follow the power feed to its connection on the power source. Ensure that the power source is ON and that the power feed is properly secured.
- 4. Check to see if the alarm has cleared
 - If the alarm has been cleared, the problem is resolved.
 - If the alarm has not been cleared, continue with the next step.
- 5. If the power source is functioning properly and the wires are all secure, have an electrician check the voltage on the power feed.
- 6. Check to see if the alarm has cleared
 - If the alarm has been cleared, the problem is resolved.
 - If the alarm has not been cleared, continue with the next step.
- 7. If the problem has not been resolved, contact the Tekelec [Customer Care Center](#).

32317 - Server Disk Health Test Error

Alarm Type: PLAT

Description: Server Disk Health Test Error -- Either the hard drive has failed or failure is imminent.

Default Severity: Major

OID: tpdDiskHealthError

Recovery

1. Perform the recovery procedures for the other alarms that accompany this alarm.
2. If the problem has not been resolved, contact the Tekelec [Customer Care Center](#).

32318 - Server Disk Unavailable Error

Alarm Type: PLAT

Description: Server Disk Unavailable Error -- The smartd service is not able to read the disk status because the disk has other problems that are reported by other alarms. This alarm appears only while a server is booting.

Default Severity: Major

OID: tpdDiskUnavailableError

Recovery

Contact the Tekelec [Customer Care Center](#).

32320 – Device Interface Error

Alarm Type: PLAT

Description: Device Interface Error -- This alarm indicates that the IP bond is either not configured or down.

Default Severity: Major

OID: tpdDeviceIfError

Recovery

Contact the Tekelec [Customer Care Center](#).

32321 – Correctable ECC memory error

Alarm Type: PLAT

Description: Correctable ECC Memory Error -- This alarm indicates that chipset has detected a correctable (single-bit) memory error that has been corrected by the ECC (Error-Correcting Code) circuitry in the memory.

Default Severity: Major

OID: tpdEccCorrectableError

Recovery

No recovery necessary. If the condition persists, contact the Tekelec [Customer Care Center](#) to request hardware replacement.

32322 – Power Supply A error

Alarm Type: PLAT

Description: Power Supply A Error -- This alarm indicates that power supply 1 (feed A) has failed.

Default Severity: Major

OID: tpdPowerSupply1Error

Recovery

1. Verify that nothing is obstructing the airflow to the fans of the power supply.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

32323 – Power Supply B Error

Alarm Type: PLAT

Description: Power Supply B Error -- This alarm indicates that power supply 2 (feed B) has failed.

Default Severity: Major

OID: tpdPowerSupply2Error

Recovery

1. Verify that nothing is obstructing the airflow to the fans of the power supply.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

32324 – Breaker panel Feed Error

Alarm Type: PLAT

Description: Breaker Panel Feed Error -- This alarm indicates that the server is not receiving information from the breaker panel relays.

Default Severity: Major

OID: tpdBrkPnlFeedError

Recovery

1. Verify that the same alarm is displayed by multiple servers:
 - If this alarm is displayed by only one server, the problem is most likely to be with the cable or the server itself. Look for other alarms that indicate a problem with the server and perform the recovery procedures for those alarms first.
 - If this alarm is displayed by multiple servers, go to the next step.
2. Verify that the cables that connect the servers to the breaker panel are not damaged and are securely fastened to both the Alarm Interface ports on the breaker panel and to the serial ports on both servers.
3. If the problem has not been resolved, call the Tekelec *Customer Care Center* to request that the breaker panel be replaced.

32325 – Breaker Panel Breaker Error

Alarm Type: PLAT

Description: Breaker Panel Breaker Error -- This alarm indicates that a power fault has been identified by the breaker panel.

Default Severity: Major

OID: tpdBrkPnlBreakerError

Recovery

1. Verify that the same alarm is displayed by multiple servers:
 - If this alarm is displayed by only one server, the problem is most likely to be with the cable or the server itself. Look for other alarms that indicate a problem with the server and perform the recovery procedures for those alarms first.
 - If this alarm is displayed by multiple servers, go to the next step.
2. Look at the breaker panel assignments and verify that the corresponding LED in the PWR BUS A group and the PWR BUS B group is illuminated Green.
3. Check the BRK FAIL LEDs for BUS A and for BUS B.
 - If one of the BRK FAIL LEDs is illuminated Red, then one or more of the respective Input Breakers has tripped. (A tripped breaker is indicated by the toggle located in the center position.) Perform the following steps to repair this issue:
 - a) For all tripped breakers, move the breaker down to the open (OFF) position and then back up to the closed (ON) position.

- b) After all the tripped breakers have been reset, check the BRK FAIL LEDs again. If one of the BRK FAIL LEDs is still illuminated Red, contact the Tekelec [Customer Care Center](#).
 - If all of the BRK FAIL LEDs and all the LEDs in the PWR BUS A group and the PWR BUS B group are illuminated Green, continue with the next step.
4. If the problem has not been resolved, contact the Tekelec [Customer Care Center](#).

32326 – Breaker Panel Monitoring Error

Alarm Type: PLAT

Description: Breaker Panel Monitoring Error -- This alarm indicates a failure in the hardware and/or software that monitors the breaker panel. This could mean there is a problem with the file I/O libraries, the serial device drivers, or the serial hardware itself.

Note: When this alarm occurs, the system is unable to monitor the breaker panel for faults. Thus, if this alarm is detected, it is imperative that the breaker panel be carefully examined for the existence of faults. The LEDs on the breaker panel will be the only indication of the occurrence of either alarm

- 32324-Breaker Panel Feed Error or
- 32325-Breaker Panel Breaker Error

until the Breaker Panel Monitoring Error has been corrected.

Default Severity: Major

OID: tpdBrkPnlMntError

Recovery

1. Verify that the same alarm is displayed by multiple servers:
 - If this alarm is displayed by only one server, the problem is most likely to be with the cable or the server itself. Look for other alarms that indicate a problem with the server and perform the recovery procedures for those alarms first.
 - If this alarm is displayed by multiple servers, go to the next step.
2. Verify that both ends of the labeled serial cables are secured properly (for locations of serial cables, see the appropriate hardware manual).
3. If the alarm has not been cleared, contact the Tekelec [Customer Care Center](#).

32327 – Server HA Keepalive Error

Alarm Type: PLAT

Description: Server HA Keepalive Error -- This alarm indicates that heartbeat process has detected that it has failed to receive a heartbeat packet within the timeout period.

Default Severity: Major

OID: tpdHaKeepaliveError

Recovery

1. Determine if the mate server is currently down and bring it up if possible.
2. Determine if the keepalive interface is down.

3. Determine if heartbeat is running (service TKLCha status).

Note: This step may require command line ability.

4. Contact the Tekelec [Customer Care Center](#).

32331 – HP disk problem

Alarm Type: TPD

Description: HP disk problem -- This major alarm indicates that there is an issue with either a physical or logical disk in the HP disk subsystem. The message will include the drive type, location, slot and status of the drive that has the error.

Default Severity: Major

OID: tpdHpDiskProblemNotify

Recovery

Contact the Tekelec [Customer Care Center](#).

32332 – HP Smart Array controller problem

Alarm Type: PLAT

Description: HP Smart Array controller problem -- This major alarm indicates that there is an issue with an HP disk controller. The message will include the slot location, the component on the controller that has failed, and status of the controller that has the error.

Default Severity: Major

OID: tpdHpDiskCtrlrProblemNotify

Recovery

Contact the Tekelec [Customer Care Center](#).

32333 – HP hpacucliStatus utility problem

Alarm Type: PLAT

Description: HP hpacucliStatus utility problem -- This major alarm indicates that there is an issue with the process that caches the HP disk subsystem status. This usually means that the hpacucliStatus daemon is either not running, or hung.

Default Severity: Major

OID: tpdHPACUCLIProblem

Recovery

Contact the Tekelec [Customer Care Center](#).

32335 - Switch Link Down Error

Alarm Type: PLAT

Description: Swith Link Down Error -- The link is down.

Default Severity: Major

OID: tpdSwitchLinkDownError

Within this trap are two bind variables, the OIDs of which are:

- 1.3.6.1.2.1.1.5 <sysname>, where <sysname> is the name of the switch where the failure occurred.
- 1.3.6.1.2.1.2.2.1.1 <link index>, where <link index> is the index of the failed link.

Recovery

1. Verify the cabling between the port and the remote side.
2. Verify networking on the remote end.
3. If the problem persists, contact the Tekelec [Customer Care Center](#), who should verify port settings on both the server and the switch.

32336 – Half open socket limit

Alarm Type: PLAT

Description: Half open socket limit -- This alarm indicates that the number of half open TCP sockets has reached the major threshold. This problem is caused by a remote system failing to complete the TCP 3-way handshake.

Default Severity: Major

OID: tpdHalfOpenSockLimit

Recovery

Contact the Tekelec [Customer Care Center](#).

32339 - TPD Max Number Of Running Processes Error

Alarm Type: PLAT

Description: This alarm indicates that the maximum number of running processes has reached the major threshold.

Default Severity: Major

OID: tpdMaxPidLimit

Recovery

1. Run syscheck in verbose mode.
2. Contact the Tekelec [Customer Care Center](#).

32340 - TPD NTP Daemon Not Synchronized Error

Alarm Type: PLAT

Description: This alarm indicates that the server is not synchronized to an NTP source, has not been synchronized for an extended number of hours, and has reached the major threshold.

Default Severity: Major

OID: tpdNTPDaemonNotSynchronizedError

Recovery

1. Verify NTP settings and that NTP sources can be reached.
2. Contact the Tekelec [Customer Care Center](#).

32341 - TPD NTP Daemon Never Synchronized Error

Alarm Type: PLAT

Description: This alarm indicates that the server is not synchronized to an NTP source and has never been synchronized since the last configuration change.

Default Severity: Major

OID: tpdNTPDaemonNeverSynchronized

Recovery

1. Verify NTP settings and that NTP sources can be reached.
2. Contact the Tekelec [Customer Care Center](#).

32342 - TPD NTP Offset Check Error

Alarm Type: PLAT

Description: This alarm indicates the NTP offset of the server that is currently being synced to is greater than the major threshold.

Default Severity: Major

OID: ntpOffsetCheckError

Recovery

1. Verify NTP settings and that NTP sources are providing accurate time.
2. Contact the Tekelec [Customer Care Center](#).

32343 - TPD RAID disk problem

Alarm Type: PLAT

Description: This alarm indicates that physical disk or logical volume on RAID controller is not in optimal state as reported by syscheck.

Default Severity: Major

OID: tpdDiskProblem

Recovery

1. Run syscheck in verbose mode.
2. Contact the Tekelec [Customer Care Center](#).

32344 - RAID controller problem

Alarm Type: PLAT

Description: This alarm indicates that RAID controller needs intervention. State reported by syscheck is not "Normal" and/or BBU (backup battery unit) state is not "Operational."

Default Severity: Major

OID: tpdDiskCtrlrProblem

Recovery

1. Run syscheck in verbose mode.
2. Contact the Tekelec [Customer Care Center](#).

32345 - Server Upgrade snapshot(s) invalid

Alarm Type: PLAT

Description: This alarms indicates that upgrade snapshot(s) are invalid and backout is no longer possible.

Default Severity: Major

OID: tpdUpgradeSnapshotInvalid

Recovery

1. Run syscheck in verbose mode.
2. Contact Customer Care Center [Customer Care Center](#).

32346 - OEM hardware management service reports an error

Alarm Type: PLAT

Description: This alarms indicates that OEM hardware management service reports an error.

Default Severity: Major

OID: tpdOEMHardwareProblem

Recovery

1. Run syscheck in verbose mode.
2. Contact Customer Care Center [Customer Care Center](#).

32347 - The hwmgmtcliStatus daemon needs intervention

Alarm Type: PLAT

Description: This alarm indicates the hwmgmtcliStatus daemon is not running or is not responding.

Default Severity: Major

OID: tpdHWMGMTCLIPProblem

Recovery

1. Run syscheck in verbose mode.
2. Contact Customer Care Center [Customer Care Center](#).

32500 – Server Disk Space Shortage Warning

Alarm Type: PLAT

Description: Server Disk Space Shortage Warning -- This alarm indicates that one of the following conditions has occurred:

- A file system has exceeded a warning threshold, which means that more than 80% (but less than 90%) of the available disk storage has been used on the file system.
- More than 80% (but less than 90%) of the total number of available files have been allocated on the file system.

Default Severity: Minor

OID: tpdDiskSpaceShortageWarning

Recovery

Contact the Tekelec [Customer Care Center](#).

32501 – Server Application Process Error

Alarm Type: PLAT

Description: Server Application Process Error -- This alarm indicates that either the minimum number of instances for a required process are not currently running or too many instances of a required process are running.

Default Severity: Minor

OID: tpdApplicationProcessError

Recovery

Contact the Tekelec [Customer Care Center](#).

32502 – Server Hardware Configuration Error

Alarm Type: PLAT

Description: Server Hardware Configuration Error -- This alarm indicates that one or more of the server's hardware components are not in compliance with Tekelec specifications (refer to the appropriate hardware manual).

Default Severity: Minor

OID: tpdHardwareConfigError

Recovery

Contact the Tekelec [Customer Care Center](#).

32505 – Server Swap Space Shortage Warning

Alarm Type: PLAT

Description: Server Swap Space Shortage Warning -- This alarm indicates that the swap space available on the server is less than expected. This is usually caused by a process that has allocated a very large amount of memory over time.

Note: For this alarm to clear, the underlying failure condition must be consistently undetected for a number of polling intervals. Therefore, the alarm may continue to be reported for several minutes after corrective actions are completed.

Default Severity: Minor

OID: tpdSwapSpaceShortageWarning

Recovery

Contact the Tekelec [Customer Care Center](#).

32506 – Server Default Router not Defined

Alarm Type: PLAT

Description: Server Default Router not Defined -- This alarm indicates that the default network route is either not configured or the current configuration contains an invalid IP address or hostname.

Default Severity: Minor

OID: tpdDefaultRouteNotDefined

Recovery

Contact the Tekelec [Customer Care Center](#).

32507 – Server Temperature Warning

Alarm Type: PLAT

Description: Server Temperature Warning -- This alarm indicates that the internal temperature within the server is outside of the normal operating range. A server Fan Failure may also exist along with the Server Temperature Warning.

Default Severity: Minor

OID: tpdTemperatureWarning

Recovery

1. Ensure that nothing is blocking the fan's intake. Remove any blockage.
2. Verify that the temperature in the room is normal. If it is too hot, lower the temperature in the room to an acceptable level.

Note: Be prepared to wait the appropriate period of time before continuing with the next step. Conditions need to be below alarm thresholds consistently for the alarm to clear. It may take about ten minutes after the room returns to an acceptable temperature before the alarm cleared.

3. Replace the filter (refer to the appropriate hardware manual).

Note: Be prepared to wait the appropriate period of time before continuing with the next step. Conditions need to be below alarm thresholds consistently for the alarm to clear. It may take about ten minutes after the filter is replaced before the alarm cleared.

4. If the problem has not been resolved, contact the Tekelec [Customer Care Center](#).

32508 – Server Core File Detected**Alarm Type:** PLAT

Description: Server Core File Detected -- This alarm indicates that an application process has failed and debug information is available.

Default Severity: Minor**OID:** tpdCoreFileDetected**Recovery**

Contact the Tekelec [Customer Care Center](#).

32509 – Server NTP Daemon Not Synchronized**Alarm Type:** PLAT

Description: Server NTP Daemon Not Synchronized -- This alarm indicates that the NTP daemon (background process) has been unable to locate a server to provide an acceptable time reference for synchronization.

Default Severity: Minor**OID:** tpdNTPDeamonNotSynchronized**Recovery**

Contact the Tekelec [Customer Care Center](#).

32510 – CMOS Battery Voltage Low**Alarm Type:** PLAT

Description: CMOS Battery Voltage Low -- The presence of this alarm indicates that the CMOS battery voltage has been detected to be below the expected value. This alarm is an early warning indicator of CMOS battery end-of-life failure which will cause problems in the event the server is powered off.

Default Severity: Minor

OID: tpdCMOSBatteryVoltageLow

Recovery

Contact the Tekelec [Customer Care Center](#).

32511 – Server Disk Self Test Warning

Alarm Type: PLAT

Description: Server Disk Self Test Warning -- A non-fatal disk issue (such as a sector cannot be read) exists.

Default Severity: Minor

OID: tpdSmartTestWarn

Recovery

Contact the Tekelec [Customer Care Center](#).

32512 – Device Warning

Alarm Type: PLAT

Description: Device Warning -- This alarm indicates that either we are unable to perform an snmpget command on the configured SNMP OID or the value returned failed the specified comparison operation.

Default Severity: Minor

OID: tpdDeviceWarn

Recovery

Contact the Tekelec [Customer Care Center](#).

32513 – Device Interface Warning

Alarm Type: PLAT

Description: Device Interface Warning -- This alarm can be generated by either an SNMP trap or an IP bond error.

Default Severity: Minor

OID: tpdDeviceIfWarn

Recovery

Contact the Tekelec [Customer Care Center](#).

32514 – Server Reboot Watchdog Initiated

Alarm Type: PLAT

Description: Server Reboot Watchdog Initiated -- This alarm indicates that the hardware watchdog was not strobed by the software and so the server rebooted the server. This applies to only the last reboot and is only supported on a T1100 application server.

Default Severity: Minor

OID: tpdWatchdogReboot

Recovery

Contact the Tekelec [Customer Care Center](#).

32515 – Server HA Failover Inhibited

Alarm Type: PLAT

Description: Server HA Failover Inhibited -- This alarm indicates that the server has been inhibited and therefore HA failover is prevented from occurring.

Default Severity: Minor

OID: tpdHaInhibited

Recovery

Contact the Tekelec [Customer Care Center](#).

32516 – Server HA Active To Standby Transition

Alarm Type: PLAT

Description: Server HA Active To Standby Transition -- This alarm indicates that the server is in the process of transitioning HA state from Active to Standby.

Default Severity: Minor

OID: tpdHaActiveToStandbyTrans

Recovery

Contact the Tekelec [Customer Care Center](#).

32517 – Server HA Standby To Active Transition

Alarm Type: PLAT

Description: Server HA Standby To Active Transition -- This alarm indicates that the server is in the process of transitioning HA state from Standby to Active.

Default Severity: Minor

OID: tpdHaStandbyToActiveTrans

Recovery

Contact the Tekelec [Customer Care Center](#).

32518 – Platform Health Check Failure

Alarm Type: PLAT

Description: Platform Health Check Failure -- This alarm is used to indicate a configuration error.

Default Severity: Minor

OID: tpdHealthCheckFailed

Recovery

Contact the Tekelec [Customer Care Center](#).

32519 – NTP Offset Check Failure

Alarm Type: PLAT

Description: NTP Offset Check Failure -- This minor alarm indicates that time on the server is outside the acceptable range (or offset) from the NTP server. The Alarm message will provide the offset value of the server from the NTP server and the offset limit that the application has set for the system.

Default Severity: Minor

OID: ntpOffsetCheckFailed

Recovery

Contact the Tekelec [Customer Care Center](#).

32520 – NTP Stratum Check Failure

Alarm Type: PLAT

Description: NTP Stratum Check Failure -- This alarm indicates that NTP is syncing to a server, but the stratum level of the NTP server is outside of the acceptable limit. The Alarm message will provide the stratum value of the NTP server and the stratum limit that the application has set for the system.

Default Severity: Minor

OID: ntpStratumCheckFailed

Recovery

Contact the Tekelec [Customer Care Center](#).

32521 – SAS Presence Sensor Missing

Alarm Type: PLAT

Description: SAS Presence Sensor Missing -- This alarm indicates that the T1200 server drive sensor is not working.

Default Severity: Minor

OID: sasPresenceSensorMissing

Recovery

Contact the Tekelec [Customer Care Center](#) to get a replacement server.

32522 – SAS Drive Missing

Alarm Type: PLAT

Description: SAS Drive Missing -- This alarm indicates that the number of drives configured for this server is not being detected.

Default Severity: Minor

OID: sasDriveMissing

Recovery

Contact the Tekelec [Customer Care Center](#) to determine whether the issue is with a failed drive or failed configuration.

32524 – HP disk resync

Alarm Type: PLAT

Description: HP disk resync -- This minor alarm indicates that the HP disk subsystem is currently resynchronizing after a failed or replaced drive, or some other change in the configuration of the HP disk subsystem. The output of the message will include the disk that is resynchronizing and the percentage complete. This alarm should eventually clear once the resync of the disk is completed. The time it takes for this is dependant on the size of the disk and the amount of activity on the system.

Default Severity: Minor

OID: tpdHpDiskResync

Recovery

Contact the Tekelec [Customer Care Center](#).

32525 – Telco Fan Warning

Alarm Type: PLAT

Description: Telco Fan Warning -- This alarm indicates that the Telco switch has detected an issue with an internal fan.

Default Severity: Minor

OID: tpdTelcoFanWarning

Recovery

1. Contact the Tekelec [Customer Care Center](#) to get a replacement switch. Verify the ambient air temperature around the switch is as low as possible until the switch is replaced.
2. Tekelec [Customer Care Center](#) personnel can perform an snmpget command or log into the switch to get detailed fan status information.

32526 – Telco Temperature Warning

Alarm Type: PLAT

Description: Telco Temperature Warning -- This alarm indicates that the Telco switch has detected the internal temperature has exceeded the threshold.

Default Severity: Minor

OID: tpdTelcoTemperatureWarning

Recovery

1. Lower the ambient air temperature around the switch as low as possible.
2. If problem persists, contact the Tekelec [Customer Care Center](#).

32527 – Telco Power Supply Warning

Alarm Type: PLAT

Description: Telco Power Supply Warning -- This alarm indicates that the Telco switch has detected that one of the duplicate power supplies has failed.

Default Severity: Minor

OID: tpdTelcoPowerSupplyWarning

Recovery

1. Verify breaker wasn't tripped.
2. If breaker is still good and problem persists, contact the Tekelec [Customer Care Center](#) who can perform a `snmpget` command or log into the switch to determine which power supply is failing. If the power supply is bad, the switch must be replaced.

32528 – Invalid BIOS value

Alarm Type: PLAT

Description: Invalid BIOS value -- This alarm indicates that the HP server has detected that one of the setting for either the embedded serial port or the virtual serial port is incorrect.

Default Severity: Minor

OID: tpdInvalidBiosValue

Recovery

Contact the Tekelec [Customer Care Center](#).

32529 – Server Kernel Dump File Detected

Alarm Type: PLAT

Description: Server Kernel Dump File Detected -- This alarm indicates that the kernel has crashed and debug information is available.

Default Severity: Minor

OID: tpdServerKernelDumpFileDetected

Recovery

Contact the Tekelec [Customer Care Center](#).

32530 – TPD Upgrade Fail Detected

Alarm Type: PLAT

Description: Server Upgrade Fail Detected -- This alarm indicates that a TPD upgrade has failed.

Default Severity: Minor

OID: tpdUpgradeFailed

Recovery

Contact the Tekelec [Customer Care Center](#).

32531 – Half Open Socket Warning

Alarm Type: PLAT

Description: Half Open Socket Warning -- This alarm indicates that the number of half open TCP sockets has reached the major threshold. This problem is caused by a remote system failing to complete the TCP 3-way handshake.

Default Severity: Minor

OID: tpdHalfOpenSocketWarning

Recovery

Contact the Tekelec [Customer Care Center](#).

32532 – Server Upgrade Pending Accept/Reject

Alarm Type: PLAT

Description: Server Upgrade Pending Accept/Reject -- This alarm indicates that an upgrade occurred but has not been accepted or rejected yet.

Default Severity: Minor

OID: tpdServerUpgradePendingAccept

Recovery

Follow the steps in the application's upgrade procedure for accepting or rejecting the upgrade.

32533 -TPD Max Number Of Running Processes Warning

Alarm Type: PLAT

Description: This alarm indicates that the maximum number of running processes has reached the minor threshold.

Default Severity: Minor

OID: tpdMaxPidWarning

Recovery

1. Run syscheck in verbose mode.
2. Contact the Tekelec [Customer Care Center](#).

32534 -TPD NTP Source Is Bad Warning

Alarm Type: PLAT

Description: This alarm indicates that an NTP source has been rejected by the NTP daemon and is not being considered as a time source.

Default Severity: Minor

OID: tpdNTPSourceIsBad

Recovery

1. Verify NTP settings and that NTP sources are providing accurate time.
2. Contact the Tekelec [Customer Care Center](#).

32535 -TPD RAID disk resync

Alarm Type: PLAT

Description: This alarm indicates that the RAID logical volume is currently resyncing after a failed/replaced drive or another change in the configuration. The output of the message includes the disk that is resyncing. This alarm eventually clears once the resync of the disk is completed. The time it takes for this is dependant on the size of the disk and the amount of activity on the system (rebuild of 600G disks without any load takes about 75min).

Default Severity: Minor

OID: tpdNTPSourceIsBad

Recovery

1. Run syscheck in verbose mode.
2. If this alarm persist for several hours (Server rebuild of the array may take multiple hours to finish, depending on the load of the server), contact the Tekelec [Customer Care Center](#).

32536 - Server Upgrade Snapshot(s) warning

Alarm Type: PLAT

Description: This alarm indicates that upgrade snapshot(s) are above configured threshold and either accept or reject of LVM upgrade has to be run soon otherwise snapshots will become 100% full and invalid.

Default Severity: Minor

OID: tpdUpgradeSnapshotWarning

Recovery

1. Run syscheck in verbose mode.
2. If this alarm persists for several hours (Server rebuild of the array may take multiple hours to finish, depending on the load of the server), contact the Tekelec [Customer Care Center](#).

QBus Platform (70000-70999)

The QBus Platform (QP) software provides an execution environment for Java-based applications, which are the Multiprotocol Routing Agent (MRA), Multimedia Policy Engine (MPE), or the Configuration Management Platform (CMP). QP provides common interfaces into databases, event logging, SNMP, and cluster state. Two blades in the cluster provide 1+1 High-Availability (HA) protection. The application executes on one blade. The other blade acts as a hot standby in case the first blade fails to provide service.

70001 - QP_procmgr failed

Alarm Type: QP

Description: The QP-procmgr process has failed. This process manages all pcrf software.

Default Severity: Critical

Instance: N/A

HA Score: Failed

Clearing Action: This alarm is cleared by qp-procmgr after qp-procmgr is restarted.

OID: pcrfMIBNotificationsQPProcmgrFailedNotify

Recovery:

If the alarm does not clear automatically within a few seconds, or if the alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

70002 - QP Critical process failed

Alarm Type: QP

Description: The QP-procmgr has detected that one of the critical processes it monitors has failed.

Default Severity: Critical

Instance: N/A

HA Score: Normal

Clearing Action: This alarm is cleared automatically.

OID: pcrfMIBNotificationsQPCriticalProcFailedNotify

Recovery:

This alarm automatically clears as Policy processes are restarted. If the alarm does not clear automatically within a few seconds, or if the alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

70003 - QP Non-critical process failed

Alarm Type: QP

Description: The QP-procmgr has detected that one of the non-critical processes it monitors has failed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 60 seconds.

OID: pcrfMIBNotificationsQPNonCriticalProcFailedNotify

Recovery:

If the alarm occurs infrequently, monitor the health of the system. If the alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

70004 - QP Processes down for maintenance

Alarm Type: QP

Description: The QP processes have been brought down for maintenance.

Default Severity: Major

Instance: N/A

HA Score: Failed

Clearing Action: This alarm clears when the QP processes are restarted and exit maintenance.

OID: pcrfMIBNotificationsQPMaintShutdownNotify

Recovery:

If the alarm is occurring, confirm that the server is down for maintenance.

Error Code Details for Alarms 70010 and 70011

Table 2: Error Code and Meaning - Alarms 70010/70011

Error Code	Meaning
1	Syntax or usage error
2	Protocol incompatibility
3	Errors selecting input/output files, dirs

Error Code	Meaning
4	Requested action not supported: an attempt was made to manipulate 64-bit files on a platform that cannot support them; or an option was specified that is supported by the client and not by the server
5	Error starting client-server protocol
6	Daemon unable to append to log-file
10	Error in socket I/O
11	Error in file I/O
12	Error in rsync protocol data stream
13	Errors with program diagnostics
14	Error in IPC code
20	Received SIGUSR1 or SIGINT
21	Some error returned by waitpid()
22	Error allocating core memory buffers
23	Partial transfer due to error
24	Partial transfer due to vanished source files
25	The --max-delete limit stopped deletions 30 Timeout in data send/receive
101	No mate found. Blade may be in degraded state
102	Called from master with '--fromMaster' option
103	Incorrect usage
104	Failed in key exchange with remote host

70010 - QP Failed Server-backup Remote Archive Rsync

Alarm Type: QP

Description: A scheduled backup failed to synchronize the local server-backup archive with the remote server-backup archive.

- Hostname=<hostname | IPAddr>
- path=<path>
- errorcode=<rsync error>

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 600 seconds (10 minutes).

OID: pcrfMIBNotificationsQPServerBackupRsyncFailedNotify

Recovery:

Check that the parameters are correct. Take corrective action based on the returned [Error Code Details for Alarms 70010 and 70011](#).

70011 - QP Failed System-backup Remote Archive Rsync

Alarm Type: QP

Description: A scheduled backup failed to synchronize the local system-backup archive with the remote system-backup archive.

Hostname=<hostname | IPAddr>, user=<user>, path=<path>,errorcode=<rsync error>

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 600 seconds.

OID: pcrfMIBNotificationsQPSystemBackupRsyncFailedNotify

Recovery:

Check that the parameters are correct. Take corrective action based on the returned [Error Code Details for Alarms 70010 and 70011](#).

70012 - QP Failed To Create Server Backup

Alarm Type: QP

Description: A scheduled backup failed to create the local server-backup file.

Failure-reason=<errorcode>

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 600 seconds.

OID: pcrfMIBNotificationsQPServerBackupFailedNotify

Recovery:

Take corrective action based on the returned error message.

70013 - QP Failed To Create System Backup

Alarm Type: QP

Description: A scheduled backup failed to create the local system-backup file.

Failure-reason=<errorcode>

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 600 seconds.

OID: pcrfMIBNotificationsQPSystemBackupFailedNotify

Recovery:

Take corrective action based on the returned error message.

70015 - VIP Route Add Failed

Alarm Type: QP

Description: VIP Route Add Failed -- VIP route add failed to re-apply during VIP event.

The alarm displays the following information:

- IP-Type
- Route-Type
- Network
- Destination
- Gateway-Address
- Error Message

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 3600 seconds.

OID: pcrfMIBNotificationsQpAddRouteFailedNotify

Recovery:

Use server UI (Platcfg Routing Menu) to repair the route manually.

70020 - QP Master database is outdated

Alarm Type: QP

Description: The current MYSQL master server has an outdated database.

Default Severity: Critical

Instance: N/A

HA Score: Degraded

Clearing Action: This alarm clears when the master server either is made a slave server or if a database restore action clears the condition.

OID: pcrfMIBNotificationsQPMySQLMasterOutdatedNotify

Recovery:

1. Once the condition has occurred, the 80003 event will be sent once a minute. Wait until all of the expected servers are being reported. It is important to wait because the best slave might be undergoing a reboot and its DB Level will not be known until after the reboot completes.
2. Use the information in 80003 to select the new master candidate.
3. Except for the current master and the master candidate, put all of the other servers into forcedStandby.
4. If the best slave is in the same cluster (the most common case), simply perform a failover by restarting the current active blade. If the best slave is in a separate cluster, then a site promotion is necessary.
5. Remove the forced standby settings on the other slaves.
6. If none of the slaves are good candidates, perform a database restore.
 - a) Put all of the slave servers into forced standby state
 - b) Perform a restore on the active server.
The restore will clear the condition.
 - c) Take the slave servers out of the standby state.

70021 - QP slave database is unconnected to the master

Alarm Type: QP

Description: The MySQL slave is not connected to the master.

Default Severity: Major

Instance: N/A

HA Score: Failed

Clearing Action: This alarm clears automatically when the slave server connects to the master server.

OID:pcrfMIBNotificationsQPMYSQLSlaveUnconnectedNotify

Recovery:

1. No action required unless the alarm does not clear within a few hours.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

70022 - QP Slave database failed to synchronize

Alarm Type: QP

Description: The MySQL slave failed to synchronize with the master.

Default Severity: Major

Instance: N/A

HA Score: Failed

Clearing Action: This alarm clears when the slave server synchronizes with the master server.

OID:pcrfMIBNotificationsQPMYSQLSlaveSyncFailureNotify

Recovery:

1. No action required unless the alarm does not clear within a few hours.

2. If the problem persists, contact the Tekelec [Customer Care Center](#).

70023 - QP Slave database lagging the master

Alarm Type: QP

Description: The MySQL slave is lagging the master -- The MySQL slave server is connected to the master server but its database has fallen behind the master database.

Default Severity: Minor

Instance: N/A

HA Score: Degraded

Clearing Action: This alarm clears automatically when the slave database is synchronized with the master database.

OID: pcrfMIBNotificationsQPMYSQLSlaveLaggingNotify

Recovery:

1. No action required unless the alarm does not clear within a few hours or the condition is repeatedly set and unset.
2. If either of the problems persists, contact the Tekelec [Customer Care Center](#).

70024 - QP Slave database is prevented from synchronizing with the master

Alarm Type: QP

Description: The MySQL slave has been prevented from synchronizing with the master -- The MySQL slave database has been prevented from synchronization with the master database because the master database is outdated.

Default Severity: Critical

Instance: N/A

HA Score: Degraded

Clearing Action: This alarm clears when the slave database is synchronized with the master database. This alarm is set on the slave server and will only occur when the active server on the primary site has set alarm 70020. This alarm clears automatically when the slave database is synchronized with the master database.

OID: pcrfMIBNotificationsQPMYSQLSlaveSyncPreventedNotify

Recovery:

1. Diagnose the CMP master server to clear its 70020 alarm.
2. Once alarm 70020 is cleared, the slave server will clear alarm 70024.

70025 - QP Slave database is a different version than the master

Alarm Type: QP

Description: The MySQL slave has a different schema version than the master.

Default Severity: Critical

Instance: N/A

HA Score: DegradedNormal

Clearing Action: The slave server clears the alarm when the master DB version is equal to the slave DB version.

OID: pcrfMIBNotificationsQPMYSQLSchemaVersionMismatchNotify

Recovery:

This alarm is set by the CMP Slave Server during a CMP Server Upgrade or Backout, when the CMP Master Server DB is a different version than the CMP Slave Server DB. The Slave Server clears the alarm when the Master Server and the Slave Server again have the same version.

70026 - QP Server Symantec NetBackup Operation in Progress

Alarm Type: QP

Description: Server is performing a Symantec NetBackup Operation.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Alarm clears when the NetBackup client operation has completed.

OID: pcrfMIBNotificationsQPNetBackupInProgressNotify

Recovery:

1. When operation is complete, alarm should clear.
2. If the alarm does not clear within a few hours, then check the NetBackup Server logs.
3. If the NetBackup Server logs have no errors, or if the alarm is occurring over and over, contact Tekelec [Customer Care Center](#).

70028 - QP Signaling Bonded Interface is Down

Alarm Type: QP

Description: Indicates both bond interfaces SIGA and SIGB are disconnected, and a failover has occurred. The cluster status changes to Degraded.

Default Severity: Critical

Instance: N/A

HA Score: Degraded

Clearing Action: N/A

OID: pcrfMIBNotificationsQPSignalBondedInterfaceDownNotify

Recovery:

1. If the alarm does not clear within a few seconds automatically or if the alarm is occurring over and over, contact Tekelec [Customer Care Center](#).

70029 - QP Peer Node Bonded Interface is Down

Alarm Type: QP

Description: Indicates QP peer node bonded interface is down.

Default Severity: Critical

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsQPPeerBondedInterfaceDown

Recovery:

1. If the alarm does not clear within a few seconds automatically or if the alarm is occurring over and over, contact Tekelec [Customer Care Center](#).

70030 - QP Backplane Bonded Interface is Down

Alarm Type: QP

Description: Indicates Backplane bonded interface bond3 is down.

Default Severity: Critical

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsQPBackplaneBondedInterfaceDown

Recovery:

1. If the alarm does not clear within a few seconds automatically or if the alarm is occurring over and over, contact Tekelec [Customer Care Center](#).

Policy Server (71000-89999)

This section provides a list of Policy Server alarms (71000-79999) and events (80000-89999) which are generated by servers such as MPEs and MRAs.

71004 - AM CONN LOST

Alarm Type: PCRF

Description: AM socket closed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: AM connection restored to remote peer.

OID: pcrfMIBNotificationsAMConnLostNotify

Recovery:

1. Check the availability of the AM.
2. Check the AM log for a recent failover or other operations that can interrupt communications.
3. If the AM has not failed, make sure that the path from the AM to the MPE device (port 3918) is operational.
4. If the problem persists, contact the Tekelec [Customer Care Center](#).

71101 - DQOS DOWNSTREAM CONNECTION CLOSED

Alarm Type: PCRF

Description: DQoS Downstream connection is closed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: DQOS connection restored to a remote peer.

OID: pcrfMIBNotificationsDqosDownstreamConnectionClosedNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

71102 - MSC CONN LOST

Alarm Type: PCRF

Description: MSC Conn Lost -- The connection was lost to the specified CMTS or downstream policy server.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to a remote peer is restored.

OID: pcrfMIBNotificationsMSCConnLostNotify

Recovery:

1. Check configuration and availability of the network element.

2. Check the network element for a reboot or other service interruption.
3. If the element has not failed, make sure that the network path from the MPE device to the element (port 3918) is operational.
4. If the problem persists, contact the Tekelec [Customer Care Center](#).

71104 - DQOS AM CONNECTION CLOSED

Alarm Type: PCRF

Description: DQoS AM Connection Closed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to a remote peer is restored.

OID: pcrfMIBNotificationsDqosAmConnectionClosedNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

71204 - SPC CONN CLOSED

Alarm Type: PCRF

Description: SPC SPC connection closed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to a remote peer is restored.

OID: pcrfMIBNotificationsSPCConnClosedNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

71402 - TRANSPORT CLOSED

Alarm Type: PCRF

Description: Diameter Transport Closed -- A connection with a Diameter peer has been closed by a network element.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 7200 seconds.

OID: pcrfMIBNotificationsTransportClosedNotify

Recovery:

1. Check the configuration and availability of the network element.
2. Check the network element for a reboot or other service interruption.
3. If the network element has not failed, ensure the network path from the device to the network element is operational.
4. If the problem persists, contact the Tekelec [Customer Care Center](#).

71403 - TRANSPORT DISCONNECTED

Alarm Type: PCRF

Description: Diameter Transport Disconnected -- Diameter connection socket is closed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 7200 seconds.

OID: pcrfMIBNotificationsTransportDisconnectedNotify

Recovery:

1. Check the configuration and availability of the network element.
2. Check the network element for a reboot or other service interruption.
3. If the network element has not failed, ensure the network path from the device to the network element is operational.
4. If the problem persists, contact the Tekelec [Customer Care Center](#).

71408 - DIAMETER NEW CONN REJECTED

Alarm Type: PCRF

Description: Diameter new connection rejected as an already functioning one exists. A Diameter peer (identified by its Diameter Identity) attempted to establish a connection with the device although it already has a valid connection. The Diameter protocol allows only one connection from a particular peer.

Note: This situation only occurs when DIAMETER.AllowMultipleConnectionsPerPeer is set to false, or when the multiple connections setting is turned off on the advanced tab of the policy server tab in the CMP GUI.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 300 seconds.

OID: pcrfMIBNotificationsDIAMETERNewConnRejectedNotify

Recovery:

1. Check the peer configuration and ensure that the peer sees a valid connection with the device.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

71414 - SCTP PATH STATUS CHANGED

Alarm Type: PCRF

Description: SCTP Path Status Changed -- Occurs when an MPE or MRA is multihoming. The alarm occurs when one path fails, and clears when the path becomes available again. If the path that is currently transmitting diameter messages fails, the alarm is triggered when the SCTP association tries to send the next diameter message. If the path is not transmitting diameter messages (it is a backup) then it may take up to 30 seconds for the alarm to be triggered, since heartbeat chunks are sent every 30 seconds.

Default Severity: Minor

Instance: Peer address + Association ID

HA Score: Normal

Clearing Action: This alarm clears automatically after 7200 seconds.

OID: pcrfMIBNotificationsSctpPathStatusChangedNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

71605 - LDAP CONN FAILED

Alarm Type: PCRF

Description: Connection to LDAP server failed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to LDAP server is restored.

OID: pcrfMIBNotificationsLdapConnFailedNotify

Recovery:

Verify that there is no problem with the LDAP server or the network path used to reach the server. If the problem persists, contact the Tekelec [Customer Care Center](#).

71630 - DHCP UNEXPECTED EVENT ID

Alarm Type: PCRF

Description: DHCP Communication exception.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Next successful DHCP operation will clear this alarm.

OID: pcrfMIBNotificationsDHCPUnexpectedEventIdNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

71631 - DHCP UNABLE TO BIND EVENT ID

Alarm Type: PCRF

Description: DHCP unable to bind event ID.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Next successful DHCP bind operation will clear this alarm.

OID: pcrfMIBNotificationsDHCPUnableToBindEventIdNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

71632 - DHCP RESPONSE TIMEOUT EVENT ID

Alarm Type: PCRF

Description: DHCP Response Timeout Event Id.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 60 seconds.

OID: pcrfMIBNotificationsDHCPResponseTimeoutEventIdNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

71633 - BAD RELAY ADDRESS EVENT ID

Alarm Type: PCRF

Description: DHCP bad relay address event id.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 30 seconds.

OID: pcrfMIBNotificationsDHCPBadRelayAddressEventIdNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

71634 - DHCP BAD PRIMARY ADDRESS EVENT ID

Alarm Type: PCRF

Description: DHCP no primary address specified.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 30 seconds.

OID: pcrfMIBNotificationsDHCPBadPrimaryAddressEventIdNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

71635 - DHCP BAD SECONDARY ADDRESS_EVENT ID

Alarm Type: PCRF

Description: DHCP no secondary address specified.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 30 seconds.

OID: pcrfMIBNotificationsDHCPBadSecondaryAddressEventIdNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

71684 - SPR CONNECTION CLOSED

Alarm Type: PCRF

Description: SPR Closing a secondary connection to revert to primary connection.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to SPR is restored.

OID: pcrfMIBNotificationsSPRConnectionClosedNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

71685 - MSR DB NOT REACHABLE

Alarm Type: PCRF

Description: Unable to connect to MSR after several attempts.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to MSR is restored.

OID: pcrfMIBNotificationsMSRDBNotReachableNotify

Recovery:

Verify that there is no problem with the MSR server or the network path used to reach the server.
If the problem persists, contact the Tekelec [Customer Care Center](#).

71702 - BRAS CONNECTION CLOSED

Alarm Type: PCRF

Description: Bras Connection Closed -- The MPE lost a connection to the B-RAS element of the gateway.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to BRAS is restored.

OID: pcrfMIBNotificationsBrasConnectionClosedNotify

Recovery:

1. Check availability of the gateway.

2. If the gateway has not failed, make sure that the path from the gateway to the MPE is operational.
3. If the problem persists, contact the Tekelec [Customer Care Center](#).

71703 - COPS UNKNOWN GATEWAY

Alarm Type: PCRF

Description: COPS Unknown Gateway -- An unknown gateway is trying to establish a COPS-PR connection to the MPE.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: COPS network element is associated with MPE.

OID: pcrfMIBNotificationsCOPSPUnknownGatewayNotify

Recovery:

1. Check the configuration of the network elements in the CMP. There should be a B-RAS network element for this gateway and that B-RAS must be associated with this MPE.
Make sure that the configuration of the B-RAS network element is consistent with the provisioned information on the gateway. The network element name in the CMP must match the provisioned router name on the gateway.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

71801 - PCMM NO PCEF

Alarm Type: PCRF

Description: PCMM no PCEF.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 60 seconds.

OID: pcrfMIBNotificationsPCMMNoPCEFNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

71805 - PCMM NO CONNECTION PCEF

Alarm Type: PCRF

Description: PCMM Non Connection to PCEF.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 60 seconds.

OID: pcrfMIBNotificationsPCMMNonConnectionPCEFNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

72198 - SMSR SMSC SWITCHED TO PRIMARY

Alarm Type: SMS

Description: Switched to primary SMSC -- Switched from Secondary to Primary SMSC.

Default Severity: Minor

Instance: SMSC address

HA Score: Normal

Clearing Action: Auto clear after 60 minutes

OID: pcrfMIBNotificationsSMSRSMTPConnectionClosedNotify

Recovery:

No action necessary.

72199 - SMSR SMSC SWITCHED TO SECONDARY

Alarm Type: SMPP

Description: Switched to Secondary SMSC -- Switched from Primary to Secondary SMSC.

Default Severity: Minor

Instance: SMSC Address

HA Score: Normal

Clearing Action: Auto clear after 60 minutes

OID: pcrfMIBNotificationsSMSRSMTPConnectionClosedNotify

Recovery:

No action necessary.

72210 - PCMM REACHED MAX GATES EVENT ID

Alarm Type: PCRF

Description: PCMM Reached Maximum Gates -- A subscriber at IP address ip-addr has reached the configured maximum number of upstream gates.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 60 seconds.

OID: pcrfMIBNotificationsPCMMReachedMaxGatesEventIdNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

72211 - PCMM REACHED MAX GPI EVENT ID

Alarm Type: PCRF

Description: PCMM Reached Maximum GPI -- PCMM reached maximum GPI. A subscriber at IP address ip-addr has reached the configured maximum grants per interval on all upstream gates.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears automatically after 60 seconds.

OID: pcrfMIBNotificationsPCMMReachedMaxGPIEventIdNotify

Recovery:

1. This subscriber address is exceeding the capacity; attention is required.
2. Contact the Tekelec [Customer Care Center](#).

72501 - SCE CONNECTION LOST

Alarm Type: PCRF

Description: SCE Connection is lost.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Connection to SCE is restored.

OID: pcrfMIBNotificationsSCEConnectionLostNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

72549 - SMSR QUEUE FULL

Alarm Type: PCRF

Description: SMSR queue full -- SMSR internal queue has reached capacity. This will result in messages being dropped until the queue is free to accept new messages.

Default Severity: Minor

Instance: SMSR queue

HA Score: Normal

Clearing Action: Auto clear after 60 minutes

OID: pcrfMIBNotificationsSMSRSMTPConnectionClosedNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

72559 - SMSR SMSC CONN CLOSED

Alarm Type: PCRF

Description: SMSC connection closed.

Default Severity: Minor

Instance: SMSC address

HA Score: Normal

Clearing Action: Auto clear after 60 minutes

OID: pcrfMIBNotificationsSMSRSMTPConnectionClosed

Recovery:

No action necessary.

72565 - SMSR SMTP CONN CLOSED

Alarm Type: PCRF

Description: SMTP connection closed -- SMTP connection has been closed to MTA {IP Address}.

Default Severity: Minor

Instance: {hostname of MTA}

HA Score: Normal

Clearing Action: Auto clear after 60 minutes

OID: pcrfMIBNotificationsSMSRSMTPConnectionClosedNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

72703 - RADIUS SERVER START FAILED

Alarm Type: PCRF

Description: RADIUS server start failed.

Default Severity: Minor

Instance: N/A

HA Score: N/A

Clearing Action: TBD

OID: pcrfMIBNotificationsRADIUSServerFailedNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

72904 - DIAMETER TOO BUSY

Alarm Type: PCRF

Description: Diameter load shedding set a busy state.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: The Diameter load drops below admission criteria thresholds or this alarm clears automatically after 30 seconds.

OID: pcrfMIBNotificationsDiameterTooBusyNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

72905 - RADIUS TOO BUSY

Alarm Type: PCRF

Description: RADIUS load shedding set a busy state.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: The RADIUS load drops below admission criteria thresholds or this alarm clears automatically after 30 seconds.

OID: pcrfMIBNotificationsRadiusTooBusyNotify

Recovery:

If this alarm occurs infrequently, then monitor the health of the system. If this alarm occurs frequently, contact the Tekelec [Customer Care Center](#).

74000 - POLICY CRITICAL ALARM

Alarm Type: PCRF

Description: Critical Policy alarm.

Default Severity: Critical

Instance: N/A

HA Score: Normal

Clearing Action: This alarm can be cleared by a policy or clears automatically after 3600 seconds (one hour).

OID: pcrfMIBNotificationsPolicyServerCriticalAlarmNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

74001 - POLICY MAJOR ALARM

Alarm Type: PCRF

Description: Major Policy alarm.

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm can be cleared by a policy or clears automatically after 3600 seconds (one hour).

OID: pcrfMIBNotificationsPolicyServerMajorAlarmNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

74002 - POLICY MINOR ALARM

Alarm Type: PCRF

Description: Minor Policy alarm.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: This alarm can be cleared by a policy or clears automatically after 3600 seconds (one hour).

OID: pcrfMIBNotificationsPolicyServerMajorAlarmNotify

Recovery:

Contact the Tekelec [Customer Care Center](#).

74020 - DELETE EXPIRE FILES

Alarm Type: PCRF

Description: Delete expire files -- Stats Files Generator Task has removed some files which weren't synced to remote servers (<external system IP>,<external system IP>, etc).

Default Severity: Major

Instance: Stats files generator

HA Score: Normal

Clearing Action: Auto clear 300 seconds

OID: pcrfMIBNotificationsFilesGeneratorDeleteExpireFilesNotify

Recovery:

Check all enabled Stats Files Synchronization tasks status in the DC (Data Collection) tasks of CMP, and ensure they are configured successfully.

74021 - FILE SYNCHRONIZATION FAILURE

Alarm Type: PCRF

Description: Files synchronization failure -- Stats Files Synchronization #<X> task failed to sync local to remote server (<external system Host Name/IP>) after retry <N> times, where:

- X: task #
- N: 1-5 retry times
- External system Host Name/IP: user-defined remote server's address to which files are synced

Default Severity: Minor

Instance: Stats files synchronization

HA Score: Normal

Clearing Action: Auto clear 300 seconds

OID: pcrfMIBNotificationsFilesSynchronizationFailureNotify

Recovery:

Check the network status of the remote server which you configured in the Stats Files Synchronization task; ensure remote server supports SSH protocol and you configured the user name and password correctly.

74022 - FILES UPLOADING FAILURE

Alarm Type: PCRF

Description: PM Statistics Files Uploading Task failed to upload local stat files to FTP server *FTP server Host Name/IP* after retry *number* times.

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: Auto clear 300 seconds

OID: FilesUploadingFailureNotify

Recovery:

1. Fix network problems or verify FTP configuration info, which is defined in the scheduler task of CMP.
2. If issue does not resolve, contact the Tekelec [Customer Care Center](#).

74602 - QP Multiple Active In Cluster Failure

Alarm Type: QP

Description: Multiple Active servers have been detected in the same cluster; the cluster is in Split Brain state.

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears when HA recovers or can clear automatically after 30 minutes. When HA recovers there will be only one Active server in a cluster.

OID: pcrfMIBNotificationsQPMultipleActiveInClusterFailureNotify

Recovery:

1. Fix network problems and restore connectivity.
2. Place one of the Active servers in the cluster into Forced Standby mode.
3. Contact the Tekelec [Customer Care Center](#).

74603 - QP Max Primary Cluster Failure Threshold

Alarm Type: QP

Description: The number of failed MPE pairs reaches the threshold of *the configured threshold value at the site name*.

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears when the number of failed MPE pairs remain at a lower value than the threshold of {Max Primary Site Failure Threshold} at {Site}, or clears automatically after 30 minutes.

OID: pcrfMIBNotificationsQPMPEPrimaryClusterFailureNotify

Recovery:

1. When the failure count drops below the threshold value and stays below the threshold for 30 seconds, the alarm is cleared. (The 30 seconds delay prevents the alarm from being cleared too soon.)
2. If alarm doesn't clear automatically, contact the Tekelec [Customer Care Center](#).

74604 - QP Policy Cluster Offline Failure

Alarm Type: QP

Description: Policy Cluster is offline.

Default Severity: Critical

Instance: N/A

HA Score: Normal

Clearing Action: This alarm clears when a server in the MPE cluster comes online. The alarm clears automatically after 30 minutes.

OID: pcrfMIBNotificationsQPMPEClusterOfflineFailureNotify

Recovery:

1. When a server comes online (in Active, Standby, or Spare state), the alarm is cleared. Please check whether all servers are powered down or rebooted at that time.
2. If alarm doesn't clear automatically, contact the Tekelec [Customer Care Center](#).

75000 - POLICY LIBRARY LOADING FAILED

Alarm Type: PCRF

Description: Policy library loading failed -- PCRF was unable to load the latest policy library. If this alarm occurred at startup time or at failover, this indicates the PCRF does not have any policies deployed. If this alarm occurred on a new policy push when PCRF was running with some existing policies, this alarm indicates that the PCRF will continue to run with those existing policies.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Performing a reapply config may fix the problem.

OID: pcrfMIBNotificationsPolicyLoadingLibraryFailedNotify

Recovery:

1. Perform a reapply config from the CMP to reload the library.
2. If the problem persists, contact the Tekelec [Customer Care Center](#).

75105 - Mediation SOAP load shedding set a busy state**Alarm Type:** Mediation**Description:** The Mediation Server SOAP provisioning interface has become busy, and has begun load shedding.**Default Severity:** Minor**Instance:** N/A**HA Score:** Normal**Clearing Action:** N/A**OID:** MediationSOAPTooBusyNotify**Recovery:**

No action required.

75106 - SPR: Create connection to SPR *ip-address* failed**Alarm Type:** Mediation**Description:** Create connection to SPR *ip-address* failed.**Default Severity:** Minor**Instance:** N/A**HA Score:** Normal**Clearing Action:** N/A**OID:** SPRConnectionFailedNotify**Recovery:**

No action required.

75107 - Sync: Backup folder disk quota exceeded. Disk quota: *percentage, total usage: space used***Alarm Type:** Mediation**Description:** Mediation sync directory disk quota has been exceeded.**Default Severity:** Minor**Instance:** N/A**HA Score:** Normal**Clearing Action:** N/A**OID:** MSDiskQuotaExceedNotify**Recovery:**

No action required.

75108 - No space left on device

Alarm Type: Mediation

Description: No space left on device.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: MSDiskNoSpaceNotify

Recovery:

No action required.

75109 - The Mediation Server has achieved 80% of the maximum number of users in SPR.

Alarm Type: Mediation

Description: Achieve 80% maximum number of users in SPR.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: SPRLicenseslimitNotify

Recovery:

No action required.

77904 - BOD PCMM TOO BUSY

Alarm Type: PCRF

Description: BOD PCMM TOO BUSY

Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsBODPCMMTooBusyNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

77905 - BOD DIAMETER TOO BUSY

Alarm Type: PCRF

Description: BOD DIAMETER TOO BUSY

Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsBODDiameterTooBusyNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

78000 - ADS CONNECTION LOST

Alarm Type: PCRF

Description: ADS Connection Lost -- The Analytics Data Stream (ADS) connection was lost to the specified client.

Default Severity: Minor

Instance: Analytics Client ID

HA Score: Normal

Clearing Action: Connection to a remote peer is restored by the same client (ID), or in one hour by auto clear.

OID: pcrfMIBNotificationsADSConnectionLostNotify

Recovery:

1. Check configuration and availability of the analytics client.
2. Check the client for reboot or other service interruption.
3. If the element has not failed, make sure that the network path from the MPE device to the element (port 222) is operational.
4. If the problem persists, contact the Tekelec [Customer Care Center](#).

78001 - RSYNC FAILED

Alarm Type: PCRF

Description: Transfer of Policy jar files failed -- PCRF was unable to transfer the latest policy library from the active to the standby server. The alarm can be raised by the active when a policy change is made or a Reapply Configuration is performed. It can be raised by the standby during startup if it was unable to get the policy jar file from the active during startup.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Since the alarm can be raised by both the active and standby servers, the alarm will not clear once the problem is fixed; it will auto-clear in an hour.

OID: pcrfMIBNotificationsRsyncFailedNotify

Recovery:

1. This alarm can be ignored during a mixed version upgrade (eg. 7.5/7.6 -> 9.1) and when rebooting both servers on the MPE.
2. If the alarm is seen on the MRA, it indicates the logback config files are not transferring, which is harmless to the operation.
3. The most likely cause is that the ssh keys have not been exchanged; ensure they are exchanged correctly.
4. Perform a Reapply Configuration.
5. If performing a Reapply Configuration does not fix the problem, another alarm will be raised by the active server for that particular operation. If the problem persists, contact the Tekelec [Customer Care Center](#).
6. The original alarm will auto-clear in an hour.

79002 - SESS_SIZE_REACHED_THRESHOLD

Alarm Type: PCRF

Description: Total session database size reached maximum threshold percentage of planned session database size.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Total session database size goes below minimum threshold percentage of planned session database size.

OID: pcrfMIBNotificationsSessDBSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79003 - AVERAGE_SESS_SIZE_EXCEED

Alarm Type: PCRF

Description: Average session size exceeded the projected size.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsAvgSessSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79004 - BIND_SIZE_REACHED_THRESHOLD

Alarm Type: PCRF

Description: Total binding database size reached maximum threshold percentage of planned binding database size.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: Total binding database size goes below minimum threshold percentage of planned binding database size.

OID: pcrfMIBNotificationsBindDBSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79005 - AVERAGE_BIND_SIZE_EXCEED

Alarm Type: PCRF

Description: Average binding size exceeded the projected size.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsAvgBindSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79105 - MEDIATION_SOAP_TOO_BUSY

Alarm Type: PCRF

Description: Mediation Server SOAP provisioning interface reaches busy state; load shedding begins.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsAvgBindSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79106 - SPR_CONNECTION_FAILED

Alarm Type: PCRF

Description: Created connection to SPR failed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsAvgBindSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79107 - MEDIATION_DISK_QUOTA_EXCEED

Alarm Type: PCRF

Description: Created connection to SPR failed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsAvgBindSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79108 - MEDIATION_DISK_NO_SPACE

Alarm Type: PCRF

Description: Created connection to SPR failed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsAvgBindSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

79109 - SPR_LICENSE_LIMIT

Alarm Type: PCRF

Description: Created connection to SPR failed.

Default Severity: Minor

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsAvgBindSizeReachedThresholdNotify

Recovery:

If the problem persists, contact the Tekelec [Customer Care Center](#).

80001 - QP DB State Transition

Alarm Type: QP

Description: The DB status of the blade is not fully ready -- The MySQL database manager generates a "MySQL state transition" event every time it makes a state-machine transition. The event text describes the transition.

Default Severity: Info

Instance: MySQL

HA Score: Normal

Clearing Action: This alarm is cleared by qp-procmgr as qp-procmgr shuts down.

OID: pcrfMIBNotificationsQPDBStateChangeNotify

Recovery:

No action required.

80002 - QP MySQL Relay Log Dropped

Alarm Type: QP

Description: A portion of the MySQL relay log was dropped as the slave was shutting down -- This event is raised when a slave server times out while trying to apply its relay log during a slave stop. The server may not be hurt, but there may be aftereffects. This event is raised to trigger a debug for possible aftereffects.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsQPMYSQLRelayLogDroppedNotify

Recovery:

Debug the system for possible aftereffects caused by the timeout.

80003 - QP MySQL Database Level Advertisement

Alarm Type: QP

Description: The ranking of slaves when the master is outdated -- If the master database is outdated, the server raises this event once per minute. The server will rank the slaves, from best to worst, based on their database level .

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsQPMYSQLDBLevelNotify

Recovery:

Use the information of this event to help resolve an outdated master database raised by alarm 70020.

82704 - BINDING RELEASE TASK

Alarm Type: PCRF

Description: Binding Release Task -- The binding release task has started, completed, or aborted.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsBindingReleaseTaskNotify

Recovery:

No action required.

84004 - POLICY INFO EVENT

Alarm Type: PCRF

Description: Policy Info Event -- Application is ready.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsPolicyInfoEventNotify

Recovery:

No action required.

86001 - APPLICATION IS READY

Alarm Type: PCRF

Description: Application is ready for service.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsApplicationIsReadyNotify

Recovery:

No action required.

86100 - CMP USER LOGIN

Alarm Type: PCRF

Description: CMP User login was succesful.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsCMPUserLoginNotify

Recovery:

No action required.

86101 - CMP USER LOGIN FAILED

Alarm Type: PCRF

Description: CMP User login failed.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsCMPUserLoginFailedNotify

Recovery:

No action required.

86102 - CMP USER LOGOUT

Alarm Type: PCRF

Description: CMP User performed logout.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsCMPUserLogoutNotify

Recovery:

No action required.

86200 - CMP USER PROMOTED SERVER

Alarm Type: PCRF

Description: CMP User promoted server -- Application is ready.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsCMPUserPromotedServerNotify

Recovery:

No action required.

86201 - CMP USER DEMOTED SERVER

Alarm Type: PCRF

Description: CMP User demoted either CMP 1 or CMP 2.

Default Severity: Info

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsCMPUserDemotedServerNotify

Recovery:

No action required.

86300 - SH ENABLE FAILED

Alarm Type: PCRF

Description: Enable Sh Connection failed -- The CMP performed a global operation to enable Sh on all MPE's and it failed on the specified MPE.

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsCMPShConEnableFailedNotify

Recovery:

The operation can be retried. If repeated attempts fail then there may be other management issues with the associated MPEs and connectivity to those devices should be verified.

86301 - SH DISABLE FAILED

Alarm Type: PCRF

Description: Disable Sh Connection failed -- The CMP performed a global operation to disable Sh on all MPE's and it failed on the specified MPE.

Default Severity: Major

Instance: N/A

HA Score: Normal

Clearing Action: N/A

OID: pcrfMIBNotificationsCMPShConDisableFailedNotify

Recovery:

The operation can be retried. If repeated attempts fail then there may be other management issues with the associated MPEs and connectivity to those devices should be verified.

Appendix A

Possible Result Codes during Rx-to-PCMM operation

Topics:

- *Error Codes and Conditions377*

The Rx-to-PCMM function of the Multimedia Policy Engine allows the MPE to fulfill the PacketCable Application Manager (PAM) function defined by CableLabs, in addition to the Policy Server (PS) role. Diameter Rx messages are accepted, triggering policy decisions as well as PacketCable MultiMedia/2.0 (PCMM) messages to CMTS devices. In some cases, events at the CMTS or in the network cause a PCMM error code to be returned. In other cases, events or policy logic within the MPE may trigger a non-successful result code on the Rx interface.

Error Codes and Conditions

The [Table 3: PCMM Error codes to Diameter Result-Codes mapping](#) table summarizes the mapping between received PCMM error codes and the Rx status code that are communicated as a result:

Table 3: PCMM Error codes to Diameter Result-Codes mapping

PCMM Error Code	Diameter Result-Codes
1 Insufficient Resources	5006 DIAMETER_RESOURCES_EXCEEDED
2 Unknown GateID	5012 DIAMETER_UNABLE_TO_COMPLY
6 Missing Required Object	5012 DIAMETER_UNABLE_TO_COMPLY
7 Invalid Object	5012 DIAMETER_UNABLE_TO_COMPLY
8 Volume Based Usage Limit Exceeded	5006 DIAMETER_RESOURCES_EXCEEDED
9 Time Based Usage Limit Exceeded	5006 DIAMETER_RESOURCES_EXCEEDED
10 Session Class Limit Exceeded	5006 DIAMETER_RESOURCES_EXCEEDED
11 Undefined Service Class Name	5003 DIAMETER_AUTHORIZATION_REJECTED
12 Incompatible Envelope	5012 DIAMETER_UNABLE_TO_COMPLY
13 Invalid SubscriberID	5030 DIAMETER_USER_UNKNOWN (defined in RFC 4006)
14 Unauthorized AMID	5003 DIAMETER_AUTHORIZATION_REJECTED
15 Number of Classifiers Not Supported	5012 DIAMETER_UNABLE_TO_COMPLY
16 Policy Exception	5003 DIAMETER_AUTHORIZATION_REJECTED
17 Invalid Field Value in Object	5012 DIAMETER_UNABLE_TO_COMPLY
18 Transport Error	5012 DIAMETER_UNABLE_TO_COMPLY
19 Unknown Gate Command	5012 DIAMETER_UNABLE_TO_COMPLY
20 DOCSIS 1.0 CM	5012 DIAMETER_UNABLE_TO_COMPLY
21 Number of SIDs exceeded in CM	5006 DIAMETER_RESOURCES_EXCEEDED
22 Number of SIDs exceeded in CMTS	5006 DIAMETER_RESOURCES_EXCEEDED
23 Unauthorized PSID	5003 DIAMETER_AUTHORIZATION_REJECTED
127 Other/Unspecified Error	5012 DIAMETER_UNABLE_TO_COMPLY

The [Table 4: Non-PCMM Error Conditions to Diameter Result-Codes Mapping](#) table summarizes Rx status codes that are generated by the MPE based on a non-PCMM-related condition.

Table 4: Non-PCMM Error Conditions to Diameter Result-Codes Mapping

Error Condition	Diameter Result-Code
ERRCODE_RESOURCES_EXCEEDED	5006 DIAMETER_RESOURCES_EXCEEDED
ERRCODE_USER_UNKNOWN	5030 DIAMETER_USER_UNKNOWN
ERRCODE_ENFORCEMENT_SESSION_NOT_FOUND	5030 DIAMETER_USER_UNKNOWN
ERRCODE_AUTHORIZATION_REFECTED	5003 DIAMETER_AUTHORIZATION_REJECTED
ERRCODE_POLICY_REJECTED	5003 DIAMETER_AUTHORIZATION_REJECTED
Other	5012 DIAMETER_UNABLE_TO_COMPLY

Glossary

A

AM	application manager A server within a network that is responsible for establishing and managing subscriber sessions associated with a specific application.
----	--

AMID	Application Manager ID
------	------------------------

B

B-RAS	broadband remote access server
-------	--------------------------------

C

CMP	Configuration Management Platform A centralized management interface to create policies, maintain policy libraries, configure, provision, and manage multiple distributed MPE policy server devices, and deploy policy rules to MPE devices. The CMP has a web-based interface.
-----	--

CMTS	Cable Modem Termination System: Equipment used by cable companies to provide high speed data services to cable subscribers.
------	---

D

DC	Data Collection
----	-----------------

DNS	Domain Name System
-----	--------------------

D

A system for converting Internet host and domain names into IP addresses.

DQoS

Dynamic Quality of Service

A COPS-based protocol that is part of the Packet Cable standards used to communicate between a CMS and a CMTS for setting up voice calls. An MPE device can be inserted between these two entities to apply additional policy rules as sessions are established.

G

GUI

Graphical User Interface

The term given to that set of items and facilities which provide the user with a graphic means for manipulating screen data rather than being limited to character based commands.

H

HA

High Availability

High Availability refers to a system or component that operates on a continuous basis by utilizing redundant connectivity, thereby circumventing unplanned outages.

HP

Hewlett-Packard

HSS

Home Subscriber Server

A central database for subscriber information.

L

L

LDAP	Lightweight Directory Access Protocol A protocol for providing and receiving directory information in a TCP/IP network.
------	--

M

MGPI	Multiple Grants Per Interval The ability to map multiple application flows using identical UGS (Unsolicited Grant Service) traffic profiles destined for the same subscriber into a single flow at the DOCSIS (service flow) level. Supports applications interacting with an MPE device over a Diameter-based Rx interface. See also Diameter, DOCSIS
------	---

MPE	Multimedia Policy Engine A high-performance, high-availability platform for operators to deliver and manage differentiated services over high-speed data networks. The MPE includes a protocol-independent policy rules engine that provides authorization for services based on policy conditions such as subscriber information, application information, time of day, and edge resource utilization.
-----	--

MRA	Multi-Protocol Routing Agent Scales the Policy Management infrastructure by distributing the PCRF load across multiple Policy Server devices.
-----	--

MSR	Multimedia Subscriber Repository
-----	----------------------------------

M

MTA	Major Trading Area
-----	--------------------

Multimedia Policy Engine	See MPE.
--------------------------	----------

Multiprotocol Routing Agent	See MRA.
-----------------------------	----------

N

NTP	Network Time Protocol
-----	-----------------------

NTP daemon	Network Time Protocol daemon – NTP process that runs in the background.
------------	---

O

OID	Object Identifier An identifier for a managed object in a Management Information Base (MIB) hierarchy. This can be depicted as a tree, the levels of which are assigned by different organizations. Top level MIB OIDs belong to different standard organizations. Vendors define private branches that include managed objects for their own products.
-----	--

OSS	Operations Support System Computer systems used by telecommunications service providers, supporting processes such as maintaining network inventory, provisioning services, configuring network components, and managing faults.
-----	---

OSSI	Operation Support System Interface
------	------------------------------------

O

An interface to a “back-end” (office) system. The Configuration Management Platform includes an OSSI XML interface.

P**PCEF**

Policy and Charging Enforcement Function

Maintains rules regarding a subscriber’s use of network resources. Responds to CCR and AAR messages. Periodically sends RAR messages. All policy sessions for a given subscriber, originating anywhere in the network, must be processed by the same PCRF.

PCMM

PacketCable MultiMedia

PCRF

Policy and Charging Rules Function. The ability to dynamically control access, services, network capacity, and charges in a network.

Maintains rules regarding a subscriber’s use of network resources. Responds to CCR and AAR messages. Periodically sends RAR messages. All policy sessions for a given subscriber, originating anywhere in the network, must be processed by the same PCRF.

Q**QBus Platform**

See QP.

QP

QBus Platform

Software that provides an execution environment for Java-based applications, providing common interfaces into databases,

Q

event logging, SNMP, and cluster state.

R

RKS Record Keeping Server

S

SCTP Stream Control Transmission Protocol

An IETF transport layer protocol, similar to TCP that sends a message in one operation.

The transport layer for all standard IETF-SIGTRAN protocols.

SCTP is a reliable transport protocol that operates on top of a connectionless packet network such as IP and is functionally equivalent to TCP. It establishes a connection between two endpoints (called an association; in TCP, these are sockets) for transmission of user messages.

SMPP Short Message Peer-to-Peer Protocol

An open, industry standard protocol that provides a flexible data communications interface for transfer of short message data.

SMSR SMS Relay Application

An interface between the MPE and SMSC or other specific SMS web service(s).

Simple Mail Transfer Protocol

S

SNMP	Simple Network Management Protocol.
	An industry-wide standard protocol used for network management. The SNMP agent maintains data variables that represent aspects of the network. These variables are called managed objects and are stored in a management information base (MIB). The SNMP protocol arranges managed objects into groups.
SOAP	Simple Object Access Protocol
SPC	Service Provisioning over COPS (Common Open Policy Service protocol)