

Diameter Signal Routing User Data Repository Cloud Installation and Configuration Guide for Release 14.0.2.0.0

F95762-01

April 2024



My Oracle Support (<https://support.oracle.com>) is your initial point of contact for all product support and training needs. A representative at Customer Access Support (CAS) can assist you with My Oracle Support registration.

Call the CAS main number at 1-800-223-1711 (toll-free in the US), or call the Oracle Support hotline for your local country from the list at

<http://www.oracle.com/us/support/contact/index.html>.

See more information on My Oracle Support, see Appendix K.

Copyright © 2016, 2019, 2020, 2021, 2022, 2023, 2024 Oracle and/or its affiliates. All rights reserved.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, delivered to U.S. Government end users are “commercial computer software” pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, use, duplication, disclosure, modification, and adaptation of the programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, shall be subject to license terms and license restrictions applicable to the programs. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Xeon are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Opteron, the AMD logo, and the AMD Opteron logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

TABLE OF CONTENTS

CHAPTER 1. INTRODUCTION.....	9
1.1 Purpose and Scope	9
1.2 References.....	9
1.3 Acronyms	9
1.4 Terminology.....	10
1.5 Assumptions.....	10
1.6 XML Files (for installing NE)	10
1.7 How to use this Document.....	11
CHAPTER 2. GENERAL DESCRIPTION	12
2.1 Required Materials	12
2.2 Installation Overview	12
2.3 Installation List of Procedures.....	13
CHAPTER 3. PRE-INSTALLATION PROCEDURE	14
3.1 Verify Deployment Options and Cloud Resources	14
CHAPTER 4. CLOUD CREATION.....	15
4.1 Deploy Oracle Communications User Data Repository Virtual Machines on VMware....	15
4.2 Deploy Oracle User Data Repository Virtual Machines on OpenStack.....	16
4.3 Deploy Oracle User Data Repository Virtual Machines on Oracle Linux/KVM.....	17
CHAPTER 5. ORACLE COMMUNICATIONS USER DATA REPOSITORY SERVER CONFIGURATION.....	18
5.1 Configure UDR-A Server (1 st NOAMP only).....	18
5.2 Create Configuration for Remaining Servers	29
5.3 Apply Configuration To Remaining Servers	35
5.4 Configure XSI Networks	39
CHAPTER 6. OAM PAIRING.....	41
6.1 OAM Pairing for Primary UDR Servers (1 st NOAMP site only)	41
6.2 OAM Pairing for DR Sites	52
CHAPTER 7. APPLICATION CONFIGURATION	62
7.1 Configure UDR Signaling Routes (All NOAM Sites).....	62
7.2 Configure Services on Signaling Network.....	65
7.3 Accept Installation	68

CONFIGURATION OF UDR FOR MNP, EIR, FABR AND SFAPP FEATURES	72
APPENDIX A. VMWARE VSPHERE ENVIRONMENT SETUP	72
A.1 Host Datastore configuration using vsphere	73
A.2 Host networking configuration using vsphere.....	74
APPENDIX B. VMWARE VSPHERE ORACLE COMMUNICATIONS USER DATA REPOSITORY DEPLOYMENT	78
B.1 Create Guests from OVA.....	78
B.2 Configure Guest Resources	81
B.3 Configure Guest Network	87
APPENDIX C. VMWARE VCLOUD DIRECTOR ORACLE COMMUNICATIONS USER DATA REPOSITORY DEPLOYMENT	90
C.1 vCloud Director Oracle Communications User Data Repository Media Upload.....	90
C.2 Create vApp	92
C.3 Create Guests from OVA.....	95
C.4 Configure Guest Resources	96
C.5 Create Guests from ISO	98
C.6 Install Guests from ISO	103
C.7 Configure Guests Network.....	111
APPENDIX D. OPENSTACK CLOUD ORACLE COMMUNICATIONS USER DATA REPOSITORY	114
D.1 OpenStack Image Creation from OVA.....	114
D.2 Create Resource Profiles (Flavors).....	116
D.3 Create Key Pair	117
D.4 Update UDR Stack Yaml File	118
D.5 Create VM Instances Using Yaml File	120
D.6 Extend VM Instance Volume Size.....	123
D.7 VM Instance Network Configuration	125
D.8 Virtual IP Address Assignment	127
D.9 Generate Private Key for SSH Access.....	131
D.10 Accessing VM Instance using SSH	134
D.11 Clobber the database on VM Instance	136
D.12 Associating Floating IPs.....	138

APPENDIX E. SAME NETWORK ELEMENT AND HARDWARE PROFILES.....	140
APPENDIX F. HIGH AVAILABILITY CONFIGURATIONS	142
APPENDIX G. RESOURCE PROFILE	143
APPENDIX H. NETWORK DEVICE ASSIGNMENTS.....	145
APPENDIX I. NETWORK AND PORT INFORMATION	146
APPENDIX J. INSTALL UDR ON ORACLE LINUX OS VIA KVM.....	148
APPENDIX K. MY ORACLE SUPPORT.....	166
APPENDIX L. LOCATE PRODUCT DOCUMENTATION ON THE ORACLE HELP CENTER SITE	167
APPENDIX M. CREATE AND INSTALL UDR VM VIA KVM GUI.....	168
APPENDIX N. ORCHESTRATING UDR VIA OSM.....	174
N.1 Configure Openstack VIM to run with OSM	174
N.2 Configure Config Agent Account (Juju Server)	175
N.3 Build and Deploy UDR NSD/VNFD Package	176
N.4 Perform Orchestration operations via OSM	183
N.5 Instantiate UDR	184
N.6 Terminate UDR	185
APPENDIX O. ORCHESTRATING UDR VIA TACKER.....	186
O.1 Tacker Configuration	186
O.2 Install UDR Tacker Support Scripts	187
O.3 Perform Orchestration Operations via Tacker.....	188
O.4 CREATE UDR VNF (Instantiation).....	189
O.5 DELETE UDR VNF (Termination).....	189

List of Figures

Figure 1. Example of an instruction that indicates the server to which it applies..... 10

Figure 2. Example of Initial Application Installation Path 12

Figure 3. Example port-show output. 130

Figure 4. Example Server Hardware Profile XML—Virtual Guest 141

Figure 5. Example of udrvnf-param.yaml 189

List of Tables

Table 1. Acronyms..... 9

Table 2. Installation Overview 13

List of Procedures

Procedure 1: Verify Deployment Options and Cloud Resources	14
Procedure 2: Deploy Oracle Communications User Data Repository Virtual Machines on VMware.....	15
Procedure 3: Deploy User Data Repository Virtual Machines on OpenStack	16
Procedure 4: Deploy User Data Repository Virtual Machines on Oracle Linux/KVM.....	17
Procedure 5: Configure UDR-A Server (1st NOAMP only)	18
Procedure 6: Create Configuration for Remaining Servers.....	29
Procedure 7: Apply Configuration to Remaining Servers	35
Procedure 8: Configure XSI Networks.....	39
Procedure 9: OAM Pairing for Primary UDR Servers (1st NOAMP site only).....	41
Procedure 10: OAM Pairing for DR Sites.....	53
Procedure 11: SSH Logon to Juju Server and fetch build and deploy source scripts.....	176

Chapter 1. Introduction

1.1 Purpose and Scope

This document describes the application-related installation procedures for an VMware User Data Repository system for Diameter Signal Router 9.0.2.

This document assumes that platform-related configuration has been completed.

The audience for this document includes Oracle customers as well as these groups: Software System, Product Verification, Documentation, and Customer Service including Software Operations and First Office Application.

1.2 References

- [1] Oracle Communications User Data Repository Cloud Resource Profile, E67495, latest revision
- [2] Oracle Communications User Data Repository Installation and Configuration Guide, E72453, latest revision
- [3] Oracle Communications User Data Repository Cloud Disaster Recovery Guide, F88180-01, latest revision

1.3 Acronyms

An alphabetized list of acronyms used in this document.

Table 1. Acronyms


Acronym	Definition
BIOS	Basic Input Output System
CD	Compact Disk
UDR	User Data Repository
ESXi	Elastic Sky X Integrated
FABR	Full Address Based Resolution
iDIH	Integrated Diameter Intelligence Hub
IPFE	IP Front End
IPM	Initial Product Manufacture—the process of installing TPD
IWF	Inter Working Function
NAPD	Network Architecture Planning Diagram
OS	Operating System (for example, TPD)
OVA	Open Virtualization Appliance
PDRA	Policy Diameter Routing Agent
PCA	Policy and Charging Application
RBAR	Range Based Address Resolution
SAN	Storage Area Network
SFTP	Secure File Transfer Protocol
SNMP	Simple Network Management Protocol

Acronym	Definition
TPD	Tekelec Platform Distribution
VM	Virtual Machine

1.4 Terminology

Multiple server types may be involved with the procedures in this manual. Therefore, most steps in the written procedures begin with the name or type of server to which the step applies.

Each step has a checkbox for every command within the step that the technician should check to keep track of the progress of the procedure.



1.	<input type="checkbox"/>	ServerX: Connect to the console of the server	Establish a connection to the server using cu on the terminal server/console. <pre>\$ cu -l /dev/ttyS7</pre>
----	--------------------------	---	---

Figure 1. Example of an instruction that indicates the server to which it applies

1.5 Assumptions

This procedure assumes that:

- You have the assigned values from the network and used the values to compile XML files (see Appendix C) for each NOAMP NE site before performing this procedure.
- You have at least an intermediate skill set with command prompt activities on an Open Systems computing environment such as Linux or TPD.

1.6 XML Files (for installing NE)

The XML files compiled for the installation of each NOAMP NE site must be maintained and accessible for use in Disaster Recovery procedures. The Professional Services Engineer (PSE) gives a copy of the XML files used for installation to the designated Customer Operations POC. You are ultimately responsible for maintaining and providing the XML files to My Oracle Support if needed for use in Disaster Recovery operations. For more details on Disaster Recovery refer to Oracle Communications User Data Repository Cloud Disaster Recovery Guide.

1.7 How to use this Document

Although this document is primarily to be used as an initial installation guide, its secondary purpose is to be used as a reference for Disaster Recovery procedures Oracle Communications User Data Repository Cloud Disaster Recovery Guide. When using this document for either purpose, there are a few points which help to ensure that you understand the intent of the author. These points are as follows;

1. Before beginning a procedure, completely read the instructional text (immediately after the Section heading for each procedure) and all associated procedural warnings or notes.
2. Before performing a step in a procedure, completely read the left and right columns including any step specific warnings or notes.

If a procedural step fails to complete successfully, stop and contact My Oracle Support for assistance before attempting to continue.

Chapter 2. General Description

This document defines the steps to perform the initial installation of the Oracle Communications User Data Repository application on a VMware hypervisor.

Figure 2 show the Oracle Communications User Data Repository installation paths. The general timeline for all processes to perform a software installation/configuration and upgrade is also included below.




Figure 2. Example of Initial Application Installation Path

2.1 Required Materials

The following materials are required to complete Oracle Communications User Data Repository installation:

1. Target release Oracle Communications User Data Repository OVA Media
2. Target release Oracle Communications User Data Repository ISO Media only for ISO installs
3. Target release TPD Media only for ISO installs

The software media referenced here may be acquired online from the Oracle e-Delivery service at edelivery.oracle.com.

This document and others referenced here can be acquired online from the Oracle Document Repository at the <http://docs.oracle.com/en/industries/communications/user-data-repository/index.html>

2.2 Installation Overview

This section describes the overall strategy to be used for a single or multi-site installation. It also lists the procedures required for installation with estimated times. Section 3.2.3 lists the steps required to install a Oracle Communications User Data Repository system. These sections expand on the information from the matrix and give a general timeline for the installation.

2.3 Installation List of Procedures

The following table illustrates the progression of the installation process by procedure with estimated times. The estimated times and the phases that must be completed may vary due to differences in typing ability and system configuration. The phases outlined are to be performed in the order listed.

Table 2. Installation Overview

Procedure	Phase	Elapsed Time (Minutes)	
		This Step	Cum.
Procedure 1	Verify Deployment Options and Cloud Resources	5	5
Procedure 2	Deploy Oracle Communications User Data Repository Virtual Machines on VMware	20	25
Procedure 3	Deploy Oracle User Data Repository Virtual Machines on OpenStack (Only for OpenStack deployments)	20	25
Procedure 4	Deploy Oracle User Data Repository Virtual Machines on Oracle Linux/KVM	20	25
Procedure 5	Configure UDR-A Server (1st NOAMP only)	25	50
Procedure 6	Create Configuration for Remaining Servers	15	65
Procedure 7	Apply Configuration To Remaining Servers	15	80
Procedure 8	Configure XSI Networks	10	90
Procedure 9	OAM Pairing for Primary UDR Servers (1st NOAMP site only)	10	100
Procedure 10	OAM Pairing for DR Sites	15	115
Procedure 11	Configure UDR Signaling Routes (All NOAM Sites)	10	145
Procedure 12	Configure Services on Signaling Network	5	150
Procedure 13	Accept Installation	5	155

Chapter 3. Pre-Installation Procedure

3.1 Verify Deployment Options and Cloud Resources

This procedure determines appropriate HA Configurations and VM profiles for the deployment, as well as verifies the environment.

Procedure 1: Verify Deployment Options and Cloud Resources

Step	Procedure	Result
1. <input type="checkbox"/>	Decide which profile to deploy	<p>The first step in deploying Oracle Communications User Data Repository for cloud is to review the resource profiles stated in Oracle Communications User Data Repository Cloud resource profile. A choice of HA configuration and resource profile must be driven by the available resources and expected use of the Oracle Communications User Data Repository deployment.</p> <ul style="list-style-type: none"> • For demo purposes a OVA lab profile is the best option. • For support of larger datasets, ISO installation may be required.
2. <input type="checkbox"/>	Ensure availability of cloud resources	<p>If you are using vCloud Director or vSphere as a non-privileged user, contact your cloud administrator to ensure the availability of sufficient process, memory, storage and network resources to meet the requirements of your chosen configuration and profile in Step 1</p> <p>NOTE: If you are a privileged user with VMWare vSphere, you can leverage procedures in 0 to configure storage and host networking for hosting Oracle Communications User Data Repository.</p>
THIS PROCEDURE HAS BEEN COMPLETED		

Chapter 4. Cloud Creation

4.1 Deploy Oracle Communications User Data Repository Virtual Machines on VMware

This procedure creates Oracle Communications User Data Repository virtual machines (guests) on VMware infrastructure.

Requirements:

- 3.1 Verify Deployment Options and Cloud Resources has been completed.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 2: Deploy Oracle Communications User Data Repository Virtual Machines on VMware

Step	Procedure	Result
1. <input type="checkbox"/>	Ready Installation media	<ul style="list-style-type: none"> If using vSphere client, place installation media (OVA, or ISO) onto your local machine. If using vCloud Director, upload installation media using Appendix C.1: vCloud Director Oracle Communications User Data Repository Media Upload
2. <input type="checkbox"/>	Create vApp	<ul style="list-style-type: none"> If using vCloud Director, follow: Appendix C.2: Create vApp If using vSphere client proceed to the next step.
3. <input type="checkbox"/>	Create Oracle Communications User Data Repository guests	<ul style="list-style-type: none"> If using vSphere client, follow: Appendix Appendix B: Create Guests from OVA If using vCloud Director, follow: Appendix C.5: Create Guests from ISO or Appendix C.3: Create Guests from OVA <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
4. <input type="checkbox"/>	Configure guest resources Only OVA installs	<ul style="list-style-type: none"> If using vSphere client to install by OVA, follow: Appendix B.2: Configure Guest Resources If using vCloud Director to install by OVA, follow: Appendix C.4: Configure Guest Resources If installing by ISO proceed to the next step. <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
5. <input type="checkbox"/>	Install guest OS Only ISO installs	<p>Only for ISO installs using vCloud Director, follow Appendix C.6: Install Guests from ISO</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>

Step	Procedure	Result
6. <input type="checkbox"/>	Configure guest OAM network	<p>If using vSphere client, follow:</p> <ul style="list-style-type: none"> Appendix B.3: Configure Guest Network <p>If using vCloud Director, follow:</p> <ul style="list-style-type: none"> Appendix C.7: Configure Guests Network <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
THIS PROCEDURE HAS BEEN COMPLETED		

4.2 Deploy Oracle User Data Repository Virtual Machines on OpenStack

This procedure creates User Data Repository virtual machines (guests) on OpenStack.

Requirements:

- Section 3.1 has been completed

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 3: Deploy User Data Repository Virtual Machines on OpenStack

Step	Procedure	Result
1. <input type="checkbox"/>	Ready Installation media	Create and import OVA image file to OpenStack using Appendix D.1: OpenStack Image Creation from OVA
2. <input type="checkbox"/>	Create Resource Profile	Create Resource Profile (Flavor) on OpenStack following: Appendix D.2: Create Resource Profiles (Flavors)
3. <input type="checkbox"/>	Create Key Pair	Create Key Pair on OpenStack following: Appendix D.3: Create Key Pair
4. <input type="checkbox"/>	Update the Yaml File	Update the UDR Stack Yaml file following: Appendix D.4: Update UDR Stack Yaml File
5. <input type="checkbox"/>	Create VM Instances	On OpenStack, follow this to create VM instances: Appendix D.5: Create VM Instances Using Yaml File
6. <input type="checkbox"/>	Configure guest OAM network	<p>Follow this step to configure OAM network for VM instances: Appendix D.7: VM Instance Network Configuration</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
7. <input type="checkbox"/>	Associate Floating IP	<p>Associate Floating IPs to the VM Instances if Floating IPs are available in cloud following: Appendix D.12: Associating Floating IPs</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p> <p>NOTE: This step is only needed if none of the networks assigned to VM Instances is a Public Network.</p>

Step	Procedure	Result
8. <input type="checkbox"/>	Create Virtual IPs	Assigning floating IP address to VIP, see Appendix D.8 Virtual IP Address Assignment NOTE: This step is only needed if none of the networks assigned to VM Instances is a Public Network.
THIS PROCEDURE HAS BEEN COMPLETED		

4.3 Deploy Oracle User Data Repository Virtual Machines on Oracle Linux/KVM

This procedure creates User Data Repository virtual machines (guests) on Oracle Linux/KVM.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 4: Deploy User Data Repository Virtual Machines on Oracle Linux/KVM

Step	Procedure	Result
9. <input type="checkbox"/>	Install Oracle Linux/KVM and create VMs	Install Oracle Linux/KVM on the host and create VMs using Virtual Machine Manager by following the below procedure: Appendix J Install UDR on Oracle Linux OS via KVM
THIS PROCEDURE HAS BEEN COMPLETED		

Chapter 5. Oracle Communications User Data Repository Server Configuration

5.1 Configure UDR-A Server (1st NOAMP only)

This procedure does all steps that are necessary for configuring the first UDR server. This includes creating the NOAMP Network Element, configuring Services and creating/configuring the first UDR-A server.

Requirements:



- Chapter 4 Cloud Creation has been completed

Assumptions:






- This procedure assumes that the Oracle Communications User Data Repository Network Element XML file for the Primary Provisioning NOAMP site has previously been created, as described in Appendix E.
- This procedure assumes that the Network Element XML files are either on a USB flash drive or the hard drive of the laptop. The steps are written as if the XML files are on a USB flash drive, but the files can exist on any accessible drive.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.




Procedure 5: Configure UDR-A Server (1st NOAMP only)

Step	Procedure	Result
1. <input type="checkbox"/>	UDR Server A: Launch an approved web browser and connect to the UDR Server A IP address NOTE: Click Continue to this website (not recommended) if the security certificate warning displays.	
2. <input type="checkbox"/>	UDR Server A: The login screen opens. Login to the GUI using the default user and password.	

Step	Procedure	Result
3. <input type="checkbox"/>	UDR Server A: The Oracle Communications User Data Repository Main Menu displays.	
4. <input type="checkbox"/>	UDR Server A: Configuring Network Element Navigate to Main Menu → Configuration → Networking → Networks	
5. <input type="checkbox"/>	UDR Server A: Go to the Configuration → Networking → Networks screen. Click Browse .	
6. <input type="checkbox"/>	UDR Server A: NOTE: This step assumes that the XML files were previously prepared, as described in Appendix C. 1. Select the location containing the site XML file. 2. Select the XML file and click the Open .	





Step	Procedure	Result
7. <input type="checkbox"/>	UDR Server A: Click Upload File (bottom left corner of screen).	
8. <input type="checkbox"/>	UDR Server A: If the values in the XML file pass validation rules, a banner message displays showing that the data has been successfully committed to the DB. NOTE You may have to left mouse click the Info banner option to see the message.	 
9. <input type="checkbox"/>	Navigate to Main Menu → Configuration → Networking → Services	
10. <input type="checkbox"/>	UDR Server A: Click Edit (located at the bottom left corner of the page).	

Step	Procedure	Result																								
11. <input type="checkbox"/>	UDR Server A: 1. Set the services values (see Note section). 2. Click Apply . 3. Click OK .	<div data-bbox="695 176 1398 1465"> <h3>Services</h3> <table> <thead> <tr> <th>Name</th><th>Intra-NE Network</th><th>Inter-NE Network</th></tr> </thead> <tbody> <tr> <td>OAM</td><td>IMI <input type="button" value="v"/></td><td>XMI <input type="button" value="v"/></td></tr> <tr> <td>Replication</td><td>IMI <input type="button" value="v"/></td><td>XMI <input type="button" value="v"/></td></tr> <tr> <td>Signaling</td><td>Unspecified <input type="button" value="v"/></td><td>Unspecified <input type="button" value="v"/></td></tr> <tr> <td>HA_Secondary</td><td>IMI <input type="button" value="v"/></td><td>XMI <input type="button" value="v"/></td></tr> <tr> <td>HA_MP_Secondary</td><td>IMI <input type="button" value="v"/></td><td>XMI <input type="button" value="v"/></td></tr> <tr> <td>Replication_MP</td><td>IMI <input type="button" value="v"/></td><td>XMI <input type="button" value="v"/></td></tr> <tr> <td>ComAgent</td><td>IMI <input type="button" value="v"/></td><td>XMI <input type="button" value="v"/></td></tr> </tbody> </table> <div> <input type="button" value="Ok"/> <input type="button" value="Apply"/> <input type="button" value="Cancel"/> </div> </div> <p>NOTE: Servers do not need to be restarted if this is a fresh installation.</p>	Name	Intra-NE Network	Inter-NE Network	OAM	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>	Replication	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>	Signaling	Unspecified <input type="button" value="v"/>	Unspecified <input type="button" value="v"/>	HA_Secondary	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>	HA_MP_Secondary	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>	Replication_MP	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>	ComAgent	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>
Name	Intra-NE Network	Inter-NE Network																								
OAM	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>																								
Replication	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>																								
Signaling	Unspecified <input type="button" value="v"/>	Unspecified <input type="button" value="v"/>																								
HA_Secondary	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>																								
HA_MP_Secondary	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>																								
Replication_MP	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>																								
ComAgent	IMI <input type="button" value="v"/>	XMI <input type="button" value="v"/>																								

Step	Procedure	Result																								
12. <input type="checkbox"/>	UDR Server A: The Services configuration screen opens.	<table border="1"> <thead> <tr> <th>Name</th><th>Intra-NE Network</th><th>Inter-NE Network</th></tr> </thead> <tbody> <tr> <td>OAM</td><td>IMI</td><td>XMI</td></tr> <tr> <td>Replication</td><td>IMI</td><td>XMI</td></tr> <tr> <td>Signaling</td><td>Unspecified</td><td>Unspecified</td></tr> <tr> <td>HA_Secondary</td><td>IMI</td><td>XMI</td></tr> <tr> <td>HA_MP_Secondary</td><td>IMI</td><td>XMI</td></tr> <tr> <td>Replication_MP</td><td>IMI</td><td>XMI</td></tr> <tr> <td>ComAgent</td><td>IMI</td><td>XMI</td></tr> </tbody> </table>	Name	Intra-NE Network	Inter-NE Network	OAM	IMI	XMI	Replication	IMI	XMI	Signaling	Unspecified	Unspecified	HA_Secondary	IMI	XMI	HA_MP_Secondary	IMI	XMI	Replication_MP	IMI	XMI	ComAgent	IMI	XMI
Name	Intra-NE Network	Inter-NE Network																								
OAM	IMI	XMI																								
Replication	IMI	XMI																								
Signaling	Unspecified	Unspecified																								
HA_Secondary	IMI	XMI																								
HA_MP_Secondary	IMI	XMI																								
Replication_MP	IMI	XMI																								
ComAgent	IMI	XMI																								
13. <input type="checkbox"/>	UDR Server A: Configuring Oracle Communications User Data Repository Server Navigate to Main Menu → Configuration → Servers																									
14. <input type="checkbox"/>	UDR Server A: Click Insert at the bottom left.																									
15. <input type="checkbox"/>	UDR Server A: The Adding a new server configuration screen opens.																									


Step	Procedure	Result									
16. <input type="checkbox"/>	UDR Server A: Enter the assigned hostname for the UDR-A Server.	<table border="1"> <thead> <tr> <th>Attribute</th><th>Value</th><th>Description</th></tr> </thead> <tbody> <tr> <td>Hostname *</td><td>OCUDR-A</td><td>Unique name for the server. string. Valid characters are an alphanumeric and end with</td></tr> </tbody> </table>	Attribute	Value	Description	Hostname *	OCUDR-A	Unique name for the server. string. Valid characters are an alphanumeric and end with			
Attribute	Value	Description									
Hostname *	OCUDR-A	Unique name for the server. string. Valid characters are an alphanumeric and end with									
17. <input type="checkbox"/>	UDR Server A: Select NETWORK OAM&P for the server Role from the menu.	<table border="1"> <tbody> <tr> <td>Role *</td><td> <div> <div>NETWORK OAM&P</div> <div>- Select Role -</div> <div>NETWORK OAM&P</div> <div>SYSTEM OAM</div> <div>MP</div> <div>QUERY SERVER</div> </div> </td><td></td></tr> <tr> <td>System ID</td><td></td><td></td></tr> <tr> <td>Hardware Profile</td><td>Cloud UDR NOAMP</td><td></td></tr> </tbody> </table>	Role *	<div> <div>NETWORK OAM&P</div> <div>- Select Role -</div> <div>NETWORK OAM&P</div> <div>SYSTEM OAM</div> <div>MP</div> <div>QUERY SERVER</div> </div>		System ID			Hardware Profile	Cloud UDR NOAMP	
Role *	<div> <div>NETWORK OAM&P</div> <div>- Select Role -</div> <div>NETWORK OAM&P</div> <div>SYSTEM OAM</div> <div>MP</div> <div>QUERY SERVER</div> </div>										
System ID											
Hardware Profile	Cloud UDR NOAMP										
18. <input type="checkbox"/>	UDR Server A: Enter the System ID for the NOAMP Server.	<table border="1"> <tbody> <tr> <td>System ID</td><td>NOAMP</td><td>System ID for the NOAMP or SOAM server. [Default = n/a. Range = A 64-character string. Valid value is any text string.]</td></tr> </tbody> </table>	System ID	NOAMP	System ID for the NOAMP or SOAM server. [Default = n/a. Range = A 64-character string. Valid value is any text string.]						
System ID	NOAMP	System ID for the NOAMP or SOAM server. [Default = n/a. Range = A 64-character string. Valid value is any text string.]									
19. <input type="checkbox"/>	UDR Server A: Select the hardware profile from the menu.	Select the hardware profile: Cloud UDR NOAMP <table border="1"> <tbody> <tr> <td>Hardware Profile</td><td>Cloud UDR NOAMP</td><td>Hardware profile of the server</td></tr> </tbody> </table>	Hardware Profile	Cloud UDR NOAMP	Hardware profile of the server						
Hardware Profile	Cloud UDR NOAMP	Hardware profile of the server									
20. <input type="checkbox"/>	UDR Server A: Select the Network Element Name from the menu. NOTE: After the Network Element Name is selected, the Interfaces fields are displayed.	<table border="1"> <tbody> <tr> <td>Network Element Name *</td><td>Site1_NE_NO</td><td>Select the network element [A value is required.]</td></tr> </tbody> </table>	Network Element Name *	Site1_NE_NO	Select the network element [A value is required.]						
Network Element Name *	Site1_NE_NO	Select the network element [A value is required.]									
21. <input type="checkbox"/>	UDR Server A: Enter the site location. NOTE: Location is an optional field.	<table border="1"> <tbody> <tr> <td>Location</td><td>Morrisville_NC</td><td>Location description [Default = ""]. Range = A 15-character string. Valid value is any text string.]</td></tr> </tbody> </table>	Location	Morrisville_NC	Location description [Default = ""]. Range = A 15-character string. Valid value is any text string.]						
Location	Morrisville_NC	Location description [Default = ""]. Range = A 15-character string. Valid value is any text string.]									

Step	Procedure	Result																			
22. <input type="checkbox"/>	UDR Server A: 1. Enter the IP Addresses for the Server. 2. Set the Interface parameters according to to deployment type.	<div>OAM Interfaces [At least one interface is required.]:</div> <table><thead><tr><th>Network</th><th>IP Address</th><th>Interface</th></tr></thead><tbody><tr><td>xmi (10.10.1.0/24)</td><td><input type="text" value="10.10.1.57"/></td><td>eth0 <input type="button" value="VLAN (3)"/></td></tr><tr><td>imi (10.10.2.0/24)</td><td><input type="text" value="10.10.2.156"/></td><td>eth1 <input type="button" value="VLAN (2)"/></td></tr></tbody></table> <p>1. Enter the IP Addresses for XMI and IMI networks. 2. Set the Interface device for XMI and IMI networks according to the network adapter assignment for the VM guest as viewable in B.3 Step 3 or C.7 Step 5. 3. Leave the VLANs unselected</p>	Network	IP Address	Interface	xmi (10.10.1.0/24)	<input type="text" value="10.10.1.57"/>	eth0 <input type="button" value="VLAN (3)"/>	imi (10.10.2.0/24)	<input type="text" value="10.10.2.156"/>	eth1 <input type="button" value="VLAN (2)"/>										
Network	IP Address	Interface																			
xmi (10.10.1.0/24)	<input type="text" value="10.10.1.57"/>	eth0 <input type="button" value="VLAN (3)"/>																			
imi (10.10.2.0/24)	<input type="text" value="10.10.2.156"/>	eth1 <input type="button" value="VLAN (2)"/>																			
23. <input type="checkbox"/>	UDR Server A: Click Add under NTP Servers and enter the address of the supplied NTP server.	<div><table><thead><tr><th>NTP Server IP Address</th><th>Prefer</th><th></th></tr></thead><tbody><tr><td><input type="text" value="10.240.15.7"/></td><td><input type="checkbox"/></td><td><input type="button" value="Add"/> <input type="button" value="Remove"/></td></tr><tr><td><input type="text" value="10.240.15.8"/></td><td><input type="checkbox"/></td><td><input type="button" value="Remove"/></td></tr><tr><td><input type="text" value="10.240.15.9"/></td><td><input type="checkbox"/></td><td><input type="button" value="Remove"/></td></tr><tr><td><input type="text" value="10.240.15.11"/></td><td><input type="checkbox"/></td><td><input type="button" value="Remove"/></td></tr></tbody></table><p>Set one ore more NTP Server IP Addresses to the supplied NTP servers. It is recommended to have minimum of 3 and up to 4 external NTP servers for reliable functioning of NTP service.</p><div>NTP Servers:<table><thead><tr><th>NTP Server IP Address</th><th>Prefer</th></tr></thead><tbody><tr><td><input type="text"/></td><td><input type="checkbox"/> <input type="button" value="Remove"/></td></tr></tbody></table></div></div>	NTP Server IP Address	Prefer		<input type="text" value="10.240.15.7"/>	<input type="checkbox"/>	<input type="button" value="Add"/> <input type="button" value="Remove"/>	<input type="text" value="10.240.15.8"/>	<input type="checkbox"/>	<input type="button" value="Remove"/>	<input type="text" value="10.240.15.9"/>	<input type="checkbox"/>	<input type="button" value="Remove"/>	<input type="text" value="10.240.15.11"/>	<input type="checkbox"/>	<input type="button" value="Remove"/>	NTP Server IP Address	Prefer	<input type="text"/>	<input type="checkbox"/> <input type="button" value="Remove"/>
NTP Server IP Address	Prefer																				
<input type="text" value="10.240.15.7"/>	<input type="checkbox"/>	<input type="button" value="Add"/> <input type="button" value="Remove"/>																			
<input type="text" value="10.240.15.8"/>	<input type="checkbox"/>	<input type="button" value="Remove"/>																			
<input type="text" value="10.240.15.9"/>	<input type="checkbox"/>	<input type="button" value="Remove"/>																			
<input type="text" value="10.240.15.11"/>	<input type="checkbox"/>	<input type="button" value="Remove"/>																			
NTP Server IP Address	Prefer																				
<input type="text"/>	<input type="checkbox"/> <input type="button" value="Remove"/>																				

Step	Procedure	Result																
24. <input type="checkbox"/>	UDR Server A: Click Info to see a banner message stating Pre-Validation passed. Click Apply .																	
25. <input type="checkbox"/>	UDR Server A: If the values match the network ranges assigned to the NOAMP NE,the banner message shows that the data has been validated and committed to the DB.																	
26. <input type="checkbox"/>	UDR Server A: Applying the Server Configuration File Navigate to Main Menu → Configuration → Servers	 <table><thead><tr><th>Hostname</th><th>Role</th><th>System ID</th><th>Server Group</th><th>Network Element</th></tr></thead><tbody><tr><td>OCUDR-A</td><td>Network OAM&P</td><td>NOAMP</td><td></td><td>Site1_NE_NO</td></tr></tbody></table>	Hostname	Role	System ID	Server Group	Network Element	OCUDR-A	Network OAM&P	NOAMP		Site1_NE_NO						
Hostname	Role	System ID	Server Group	Network Element														
OCUDR-A	Network OAM&P	NOAMP		Site1_NE_NO														
27. <input type="checkbox"/>	UDR Server A: The Configuration → Servers screen lists the added Server.	 <table><thead><tr><th>Hostname</th><th>Role</th><th>System ID</th><th>Server Group</th><th>Network Element</th><th>Location</th><th>Place</th><th>Details</th></tr></thead><tbody><tr><td>OCUDR-A</td><td>Network OAM&P</td><td>NOAMP</td><td></td><td>Site1_NE_NO</td><td>Morrisville_NC</td><td></td><td>xmi: 10.10.1.57 imi: 10.10.2.156</td></tr></tbody></table>	Hostname	Role	System ID	Server Group	Network Element	Location	Place	Details	OCUDR-A	Network OAM&P	NOAMP		Site1_NE_NO	Morrisville_NC		xmi: 10.10.1.57 imi: 10.10.2.156
Hostname	Role	System ID	Server Group	Network Element	Location	Place	Details											
OCUDR-A	Network OAM&P	NOAMP		Site1_NE_NO	Morrisville_NC		xmi: 10.10.1.57 imi: 10.10.2.156											

Step	Procedure	Result																
28. <input type="checkbox"/>	UDR Server A: 1. Use the cursor to select the added Server. 2. The row containing the Server is highlighted in SKY BLUE. 3. Click Export .	<div><div>Main Menu: Configuration -> Servers</div><div><div>Filter*</div><div>Fri Apr 06 01:55:15 2018 EDT</div></div><table><thead><tr><th>Hostname</th><th>Role</th><th>System ID</th><th>Server Group</th><th>Network Element</th><th>Location</th><th>Place</th><th>Details</th></tr></thead><tbody><tr><td>OCUDR-A</td><td>Network OAM&P</td><td>NOAMP</td><td></td><td>Site1_NE_NO</td><td>Morrisville_NC</td><td></td><td>xml: 10.10.1.57 imi: 10.10.2.156</td></tr></tbody></table><div><div>Insert</div><div>Edit</div><div>Delete</div><div>Export</div><div>Report</div></div></div>	Hostname	Role	System ID	Server Group	Network Element	Location	Place	Details	OCUDR-A	Network OAM&P	NOAMP		Site1_NE_NO	Morrisville_NC		xml: 10.10.1.57 imi: 10.10.2.156
Hostname	Role	System ID	Server Group	Network Element	Location	Place	Details											
OCUDR-A	Network OAM&P	NOAMP		Site1_NE_NO	Morrisville_NC		xml: 10.10.1.57 imi: 10.10.2.156											
29. <input type="checkbox"/>	UDR Server A: A banner information message showing a download link for the Server configuration data.	<div><div>Main Menu: Configuration -> Servers</div><div><div>Filter* Info</div><div>Fri Apr 06 01:57:56 2018 EDT</div></div><div><div>Info</div><div>• Exported server data in TKLCConfigData.OCUDR-A.sh may be downloaded</div></div><table><thead><tr><th>Hostname</th><th>Role</th><th>System ID</th><th>Server Group</th><th>Network Element</th><th>Location</th><th>Place</th><th>Details</th></tr></thead><tbody><tr><td>OCUDR-A</td><td>OAM&P</td><td>NOAMP</td><td></td><td>Site1_NE_NO</td><td>Morrisville_NC</td><td></td><td>xml: 10.10.1.57 imi: 10.10.2.156</td></tr></tbody></table></div> <div>The configuration file was created and stored in the /var/TKLC/db/filemgmt directory. The configuration file has a file name similar to TKLCConfigData.<hostname>.sh.</div>	Hostname	Role	System ID	Server Group	Network Element	Location	Place	Details	OCUDR-A	OAM&P	NOAMP		Site1_NE_NO	Morrisville_NC		xml: 10.10.1.57 imi: 10.10.2.156
Hostname	Role	System ID	Server Group	Network Element	Location	Place	Details											
OCUDR-A	OAM&P	NOAMP		Site1_NE_NO	Morrisville_NC		xml: 10.10.1.57 imi: 10.10.2.156											
30. <input type="checkbox"/>	UDR Server A: 1. Access the command prompt. 2. Log into the UDR-A server as the admusr user.	<pre>login as: admusr admusr@10.250.xx.yy's password: <admusr_password> Last login: Wed Mar 28 05:03:47 2018 from 10.178.25.81 [root@NO-A ~]#</pre>																
31. <input type="checkbox"/>	UDR Server A: Switch to root user.	<pre>[admusr@ UDR-A ~]\$ su - password: <root_password></pre>																
32. <input type="checkbox"/>	UDR Server A: Copy the server configuration file to the /var/tmp directory on the server, making sure to rename the file by omitting the server hostname from the file name.	<div><div>Example:</div><div>TKLCConfigData<.server_hostname>.sh translates to TKLCConfigData.sh</div><div><pre># cp -p /var/TKLC/db/filemgmt/TKLCConfigData.UDR-A.sh /var/tmp/TKLCConfigData.sh</pre></div><div>NOTE: The server polls the /var/tmp directory for the presence of the configuration file and automatically runs the file when it is found.</div></div>																

Step	Procedure	Result
33. <input type="checkbox"/>	<p>UDR Server A:</p> <p>After the script completes, a broadcast message is sent to the terminal.</p> <p>Ignore the output and press ENTER to return to the command prompt.</p> <p>NOTE: The time to complete this step varies by server and may take from 3 to 20 minutes to complete.</p>	<p>*** NO OUTPUT FOR approximately 3 to 20 MINUTES ***</p> <pre>Broadcast message from root (Fri Mar 30 01:47:58 2018): Server configuration completed successfully! See /var/TKLC/appw/logs/Process/install.log for details. Please remove the USB flash drive if connected and reboot the server. <ENTER></pre>
34. <input type="checkbox"/>	<p>UDR Server A:</p> <p>Configure the time zone.</p>	<pre># set_ini_tz.pl <time zone></pre> <p>NOTE: The following command example uses America/New_York time zone. Replace, as appropriate, with the time zone you have selected for this installation. For UTC, use Etc/UTC.</p> <pre># set_ini_tz.pl "America/New_York"</pre>
35. <input type="checkbox"/>	<p>UDR Server A:</p> <p>Initiate a reboot of the UDR Server.</p>	<pre># reboot</pre>
36. <input type="checkbox"/>	<p>UDR Server A:</p> <p>Wait until server reboot is complete. Then, SSH into the UDR-A server.</p>	<p>Wait approximately 9 minutes until the server reboot is complete.</p> <p>Using an SSH client such as putty, ssh to the UDR-A server.</p> <pre>login as: admusr admusr@10.250.xx.yy's password: <admusr_password> Last login: Wed Mar 28 05:03:47 2018 from 10.178.25.81</pre> <p>NOTE: If the server is not up, wait a few minutes and re-enter the ssh command. You can also try running the ping command to see if the server is up.</p>
37. <input type="checkbox"/>	<p>UDR Server A:</p> <p>Verify that the XMI and IMI IP addresses entered in Step 22 have been applied</p>	<pre>\$ ifconfig grep in grep -v inet6</pre> <p>Example:</p> <pre>eth0 Link encap:Ethernet HWaddr FA:16:3E:3C:8D:DE inet addr:10.10.1.57 Bcast:10.10.1.255 Mask:255.255.255.0 eth1 Link encap:Ethernet HWaddr FA:16:3E:EF:4D:EF inet addr:10.10.2.156 Bcast:10.10.2.255 Mask:255.255.255.0</pre> <p>NOTE: The XMI and IMI addresses for the server are verified by reviewing the server configuration using the Oracle Communications User Data Repository GUI.</p> <ol style="list-style-type: none"> 1. Navigate to Main Menu → Configuration → Servers 2. Scroll to line entry containing the hostname for the servers.

Step	Procedure	Result																														
38. <input type="checkbox"/>	UDR Server A: Use the ntpq command to verify that the server has connectivity to the assigned Primary (and Secondary if one was provided) NTP servers.	<pre>\$ ntpq -np</pre> <table><thead><tr><th>remote</th><th>refid</th><th>st</th><th>t</th><th>when</th><th>poll</th><th>reach</th><th>delay</th><th>offset</th><th>jitter</th></tr></thead><tbody><tr><td colspan="10">=====</td></tr><tr><td>*192.168.56.180</td><td>192.168.56.247</td><td>4</td><td>u</td><td>37</td><td>64</td><td>177</td><td>0.574</td><td>1.165</td><td>21.346</td></tr></tbody></table>	remote	refid	st	t	when	poll	reach	delay	offset	jitter	=====										*192.168.56.180	192.168.56.247	4	u	37	64	177	0.574	1.165	21.346
remote	refid	st	t	when	poll	reach	delay	offset	jitter																							
=====																																
*192.168.56.180	192.168.56.247	4	u	37	64	177	0.574	1.165	21.346																							
	IF CONNECTIVITY TO THE NTP SERVERS CANNOT BE ESTABLISHED, STOP AND PERFORM THE FOLLOWING STEPS:																															
Have the IT group provide a network path from the OAM server IP to the assigned NTP IP addresses. AFTER NETWORK CONNECTIVITY IS ESTABLISHED TO THE ASSIGNED NTP IP ADDRESSES, THEN RESTART THIS PROCEDURE BEGINNING WITH STEP 35.																																
39. <input type="checkbox"/>	UDR Server A: Run the alarmMgr to verify the health of the server	<pre>\$ alarmMgr --alarmStatus</pre> <p>NOTE: This command should not return output on a healthy system.</p>																														
40. <input type="checkbox"/>	UDR Server A: Exit the SSH session for the UDR-A server	<pre>\$ exit</pre>																														
THIS PROCEDURE HAS BEEN COMPLETED																																

5.2 Create Configuration for Remaining Servers




This procedure is used to create and configure all Oracle Communications User Data Repository Servers (Primary and DR Servers) except the first UDR-A server.





Requirements:





- Section 5.1 Configure UDR-A Server (1st NOAMP only) has been completed

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.



Procedure 6: Create Configuration for Remaining Servers





Step	Procedure	Result
1. <input type="checkbox"/>	UDR Server A: Launch an approved web browser and connect to the UDR Server A IP address NOTE: Click Continue to this website (not recommended) if the security certificate warning displays. Login to the GUI using the default user and password.	
For steps 4 through 8 add the remaining Network Elements one at a time. This includes the NO network Element for the DR elements (NO) if present. (DR elements can be uploaded during DR install)		
2. <input type="checkbox"/>	UDR Server A: Configuring Network Element Navigate to Main Menu → Configuration → Network Elements	
3. <input type="checkbox"/>	UDR Server A: On the Configuration → Network Elements screen, click Browse .	

Step	Procedure	Result																								
4. <input type="checkbox"/>	UDR Server A: NOTE: This step assumes that the xml files were previously prepared, as described inAppendix C. 1. Select the location containing the site .xml file. 2. Select the .xml file and click the Open .																									
5. <input type="checkbox"/>	UDR Server A: Click Upload File (bottom left corner of screen).																									
6. <input type="checkbox"/>	UDR Server A: If the values in the XML file pass validation rules, a banner message displays showing that the data has been successfully committed to the DB. NOTE: You may have to left mouse click the Info banner option to see the banner message.	 <table><tr><th>Network Name</th><th>Network Type</th><th>Default</th><th>Locked</th><th>Routed</th><th>VLAN</th><th>Configur Interface</th><th>Network</th></tr><tr><td>xmi</td><td>OAM</td><td>Yes</td><td>Yes</td><td>Yes</td><td>3</td><td>2</td><td>10.10.1.0/24</td></tr><tr><td>imi</td><td>OAM</td><td>No</td><td>Yes</td><td>Yes</td><td>2</td><td>2</td><td>10.10.2.0/24</td></tr></table>	Network Name	Network Type	Default	Locked	Routed	VLAN	Configur Interface	Network	xmi	OAM	Yes	Yes	Yes	3	2	10.10.1.0/24	imi	OAM	No	Yes	Yes	2	2	10.10.2.0/24
Network Name	Network Type	Default	Locked	Routed	VLAN	Configur Interface	Network																			
xmi	OAM	Yes	Yes	Yes	3	2	10.10.1.0/24																			
imi	OAM	No	Yes	Yes	2	2	10.10.2.0/24																			
NOTE: The following must be run for all servers except the first UDR-A server. These steps include a check box for UDR-A server. That check box refers to UDR-A servers that are not at the primary provisioning site, such as the UDR-A server at the disaster recovery (DR) site.																										
7. <input type="checkbox"/>	UDR Server A: Navigate to Main Menu → Configuration → Servers	 <p>Mark the check box as addition is completed for each server.</p> <div><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</div>																								

Step	Procedure	Result
8. <input type="checkbox"/>	UDR Server A: Click Insert at the bottom left.	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
9. <input type="checkbox"/>	UDR Server A: The Adding a new server configuration screen opens.	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
10. <input type="checkbox"/>	UDR Server A: Enter the assigned Hostname for the server.	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
11. <input type="checkbox"/>	UDR Server A: Select the appropriate server Role from the menu.	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B

Step	Procedure	Result									
12. <input type="checkbox"/>	UDR Server A: Enter the System ID for the server. NOTE: System ID is not required for MP.	<div> <div>System ID</div> <div>NOAMP</div> <div>System ID for the NOAMP or SOAM server. [Default = n/a. Range = A 64-character string. Valid value is any text string.]</div> </div> <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B									
13. <input type="checkbox"/>	UDR Server A: Select the hardware profile from the list.	NOAM select hardware profile: Cloud UDR NOAM <div> <div>Hardware Profile</div> <div>Cloud UDR NOAMP</div> <div>Hardware profile of the server</div> </div> <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B									
14. <input type="checkbox"/>	UDR Server A: Select the Network Element Name from the menu. NOTE: After the Network Element Name is selected, the Interfaces fields are displayed.	<div> <div>Network Element Name *</div> <div>Site1_NE_NO</div> <div>Select the network element [A value is required.]</div> </div> <p>NOTE: NO and DR pairs have their own Network element.</p> <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B									
15. <input type="checkbox"/>	UDR Server A: Enter the site location. NOTE: Location is an optional field.	<div> <div>Location</div> <div>Morrisville_NC</div> <div>Location description [Default = ""]. Range = A 15-character string. Valid value is any text string.]</div> </div> <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B									
16. <input type="checkbox"/>	UDR Server A: 1. Enter the IP Addresses for the Server. 2. Set the Interface parameters according to deployment type.	<div> <div>OAM Interfaces [At least one interface is required.]:</div> <table> <thead> <tr> <th>Network</th><th>IP Address</th><th>Interface</th></tr> </thead> <tbody> <tr> <td>xmi (10.10.1.0/24)</td><td>10.10.1.69</td><td>eth0 <input type="checkbox"/> VLAN (3)</td></tr> <tr> <td>imi (10.10.2.0/24)</td><td>10.10.2.155</td><td>eth1 <input type="checkbox"/> VLAN (2)</td></tr> </tbody> </table> </div> <p>1. Enter the IP Addresses for XMI and IMI networks. 2. Set the Interface device for XMI and IMI networks according to network adapter assignment for the VM guest as viewable in B.3 Step 3 or C.7 Step 5. 3. Leave the VLANs unselected.</p> <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B	Network	IP Address	Interface	xmi (10.10.1.0/24)	10.10.1.69	eth0 <input type="checkbox"/> VLAN (3)	imi (10.10.2.0/24)	10.10.2.155	eth1 <input type="checkbox"/> VLAN (2)
Network	IP Address	Interface									
xmi (10.10.1.0/24)	10.10.1.69	eth0 <input type="checkbox"/> VLAN (3)									
imi (10.10.2.0/24)	10.10.2.155	eth1 <input type="checkbox"/> VLAN (2)									

Step	Procedure	Result
17. <input type="checkbox"/>	UDR Server A: Click Add under NTP Servers and enter the addresses of the NTP servers.	 <p>Set one or more NTP Server IP Addresses to the supplied NTP servers. It is recommended to have minimum of 3 and up to 4 external NTP servers for reliable functioning of NTP service.</p> <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
18. <input type="checkbox"/>	UDR Server A: Click Info to see a banner with a message stating Pre-Validation passed. Click Apply .	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B

Step	Procedure	Result
19. <input type="checkbox"/>	UDR Server A: If the values match the network ranges assigned to the NE, click Info to see a banner message stating that the data has been validated and committed to the DB.	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
20. <input type="checkbox"/>	UDR Server A: Applying the Server Configuration File Select Main Menu → Configuration → Servers	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
21. <input type="checkbox"/>	UDR Server A: The Configuration → Servers screen shows the added Server in the list.	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
22. <input type="checkbox"/>	UDR Server A: 1. Use the cursor to select the added Server. 2. The row containing the Server is be highlighted in SKY BLUE. 3. Click Export .	 <p>Mark the check box as addition is completed for each server.</p> <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
23. <input type="checkbox"/>	VMware client: Repeat this procedure to create configuration	Repeat this procedure to create configuration for each remaining server: <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
THIS PROCEDURE HAS BEEN COMPLETED		

5.3 Apply Configuration To Remaining Servers

This procedure is used to apply configuration to all Oracle Communications User Data Repository Servers (Primary and DR Servers) except the first UDR-A server.

Requirements:

- Section 5.2 Create Configuration for Remaining Servers has been completed


Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 7: Apply Configuration to Remaining Servers

Step	Procedure	Result
1. <input type="checkbox"/>	UDR Server A: Connect to the UDR-A Server terminal at the Primary UDR site	SSH to the Primary UDR-A XMI IP_address. Mark the check box as addition is completed for each server. <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
2. <input type="checkbox"/>	UDR Server A: 1. Access the command prompt. 2. Log into the Primary UDR-A server as the admusr user.	<pre>login as: admusr admusr@10.250.xx.yy's password: <admusr_password> Last login: Mon Jul 30 10:33:19 2012 from 10.25.80.199 \$</pre> Mark the check box as addition is completed for each server. <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
3. <input type="checkbox"/>	UDR Server A: Change directory into the file management space	<pre>[admusr@pc9040833-no-a ~]\$ cd /var/TKLC/db/filemgmt</pre> Mark the check box as addition is completed for each server. <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
4. <input type="checkbox"/>	UDR Server A: Get a directory listing and find the configuration files for the servers.	<pre>[admusr@pc9040833-no-a ~]\$ ls -ltr TKLCCConfigData*.sh *** TRUNCATED OUTPUT *** -rw-rw-rw- 1 root root 1257 Aug 17 14:01 TKLCCConfigData.UDR-A .sh -rw-rw-rw- 1 root root 1311 Aug 17 14:30 TKLCCConfigData.NO-B.sh</pre> Mark the check box as addition is completed for each server. <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B
5. <input type="checkbox"/>	UDR Server A: Copy the configuration files found in the previous step to the target server based on the server name of the configuration file.	<pre>[admusr@pc9040833-no-a ~]\$ scp -p <configuration_file-a> <Associated_Server_XMI_IP>:/tmp admusr@10.240.39.4's password: <admusr_password> TKLCCConfigData.so-carync-a.sh 100% 1741 1.7KB/s 00:00 [root@no-mrsvnc-a filemgmt]\$</pre> Mark the check box as addition is completed for each server. <input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B

Step	Procedure	Result
6. <input type="checkbox"/>	UDR Server A: Connect to the target server which has received a configuration file copy in the previous step	<pre>[admusr@pc9040833-no-a ~]\$ ssh <Associated_Server_XMI_IP > admusr@192.168.1.10's password: <admusr_password></pre> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
7. <input type="checkbox"/>	Target Server: Copy the configuration file to the tmp directory.	<p>Copy the server configuration file to the /var/tmp directory on the server, making sure to rename the file by omitting the server hostname from the file name.</p> <p>Example:</p> <pre>TKLCConfigData<.server_hostname>.sh translates to TKLCConfigData.sh</pre> <pre>[admusr@hostname1326744539 ~]\$ sudo cp -p /tmp/TKLCConfigData.NO-B.sh /var/tmp/TKLCConfigData.sh [admusr@hostname1326744539 ~]\$</pre> <p>NOTE: The server polls the /var/tmp directory for the presence of the configuration file and automatically runs the file when it is found.</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
8. <input type="checkbox"/>	Target Server: After the script completes, a broadcast message is sent to the terminal. Ignore the output and press ENTER to return to the command prompt. NOTE: The time to complete this step varies by server and may take from approximately 3 to 20 minutes to complete.	<p>*** THERE IS NO OUTPUT FOR APPROXIMATELY 20 MINUTES ***</p> <pre>Broadcast message from root (Thu Dec 1 09:41:24 2011): Server configuration completed successfully! See /var/TKLC/appw/logs/Process/install.log for details. Please remove the USB flash drive if connected and reboot the server. <ENTER></pre> <pre>[admusr@hostname1326744539 ~]\$</pre> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
9. <input type="checkbox"/>	Target Server: Initiate a reboot of the Server.	<pre>[admusr@hostname1326744539 ~]\$ sudo reboot</pre> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>

Step	Procedure	Result
10. <input type="checkbox"/>	UDR Server A: The SSH session for the target server was terminated by previous step.	<p>The previous step causes the ssh session for the server to close and you are returned to the UDR server console prompt.</p> <pre>Connection to 192.168.1.16 closed by remote host. Connection to 192.168.1.16 closed. \$</pre> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
11. <input type="checkbox"/>	UDR Server A: Wait until server reboot is complete. Then, SSH into the target server using its XMI address.	<p>Wait approximately 10 minutes until the server reboot is complete.</p> <p>Using an SSH client such as putty, ssh to the target server using admusr credentials and the <XMI IP Address>.</p> <pre>[admusr@pc9040833-no-a ~]\$ ssh 192.168.1.xx admusr@192.168.1.20's password: <admusr_password></pre> <p>NOTE: If the server is not up, wait a few minutes and re-enter the ssh command. You can also run the ping command to see if the server is up.</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
12. <input type="checkbox"/>	Target Server: Verify that the XMI and IMI IP addresses entered in Section 5.2 Step 16 have been applied	<pre>\$ ifconfig grep in grep -v inet6 eth0 Link encap:Ethernet HWaddr FA:16:3E:BB:3D:AC inet addr:10.10.1.57 Bcast:10.10.1.255 Mask:255.255.255.0 eth1 Link encap:Ethernet HWaddr FA:16:3E:56:C1:F9 inet addr:10.10.2.156 Bcast:10.10.2.255 Mask:255.255.255.0 eth2 Link encap:Ethernet HWaddr FA:16:3E:B4:BD:0A lo Link encap:Local Loopback inet addr:127.0.0.1 Mask:255.0.0.0</pre> <p>NOTE: The XMI and IMI addresses for the server can be verified by reviewing the server configuration through the Oracle Communications User Data Repository GUI.</p> <p>Navigate to Main Menu → Configuration → Servers.</p> <p>Scroll to line containing the hostname for the server.</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>

Step	Procedure	Result																														
13. <input type="checkbox"/>	Target Server: Use the ntpq command to verify that the server has connectivity to the assigned Primary and Secondary NTP servers.	<pre>\$ ntpq -np</pre> <table><thead><tr><th>remote</th><th>refid</th><th>st</th><th>t</th><th>when</th><th>poll</th><th>reach</th><th>delay</th><th>offset</th><th>jitter</th></tr></thead><tbody><tr><td colspan="10">=====</td></tr><tr><td>*192.168.56.180</td><td>192.168.56.247</td><td>4</td><td>u</td><td>62</td><td>64</td><td>377</td><td>0.641</td><td>37.694</td><td>18.375</td></tr></tbody></table> <pre>[root@pc9040725-no-a ~]\$</pre> <p>If offset value is in excess of five seconds, run the commands below to sync time manually:</p> <pre>\$ sudo service ntpd stop</pre> <pre>Shutting down ntpd: [OK]</pre> <pre>\$ sudo ntpdate <Remote_NTP_Server_IP></pre> <pre>\$ sudo service ntpd start</pre> <pre>Starting ntpd: [OK]</pre> <p>Mark the check box as addition is completed for each server.</p> <div><input type="checkbox"/> UDR-A</div> <div><input type="checkbox"/> UDR-B</div>	remote	refid	st	t	when	poll	reach	delay	offset	jitter	=====										*192.168.56.180	192.168.56.247	4	u	62	64	377	0.641	37.694	18.375
remote	refid	st	t	when	poll	reach	delay	offset	jitter																							
=====																																
*192.168.56.180	192.168.56.247	4	u	62	64	377	0.641	37.694	18.375																							
		IF CONNECTIVITY TO THE NTP SERVERS CANNOT BE ESTABLISHED, STOP AND PERFORM THE FOLLOWING STEPS:																														
14. <input type="checkbox"/>	Target Server: Run the alarmMgr command to verify the health of the server	<pre>\$ alarmMgr --alarmStatus</pre> <p>NOTE: This command should not return output on a healthy system</p> <p>Mark the check box as addition is completed for each server.</p> <div><input type="checkbox"/> UDR-A</div> <div><input type="checkbox"/> UDR-B</div>																														
15. <input type="checkbox"/>	Target Server: Exit the SSH session for the target server	<pre>\$ exit</pre> <pre>logout</pre> <pre>Connection to 192.168.1.16 closed.</pre> <pre>#</pre> <p>Mark the check box as addition is completed for each server.</p> <div><input type="checkbox"/> UDR-A</div> <div><input type="checkbox"/> UDR-B</div>																														
16. <input type="checkbox"/>	UDR Server A: Exit terminal session	<pre># exit</pre> <pre>logout</pre> <pre>Connection to 192.168.1.4 closed.</pre> <pre>#</pre>																														
THIS PROCEDURE HAS BEEN COMPLETED																																

5.4 Configure XSI Networks



This procedure configures the XSI networks used on UDR to support signaling traffic.

Requirements:

- Section 5.3 Apply Configuration To Remaining Servers has been completed
- Section 5.1 Configure UDR-A Server (1st NOAMP only) has been completed

NOTE: If deploying two sites use the same name for both XSI networks.

Procedure 8: Configure XSI Networks

Step	Procedure	Result
1. <input type="checkbox"/>	UDR Server A: Launch an approved web browser and connect to the UDR Server A IP address NOTE: Click Continue to this website (not recommended) if the security certificate warning displays. Login to the GUI using the default user and password.	
2. <input type="checkbox"/>	UDR Server A Navigate to Main Menu → Configuration → Networking → Networks	

Step	Procedure	Result																											
3. <input type="checkbox"/>	UDR Server A Add the XSI1 network	<div><div>Insert</div><p>Click Insert.</p><div><div>Main Menu: Configuration -> Networking -> Networks [Insert]</div><div><div>Info*</div><div><div>Insert Network</div><table><thead><tr><th>Field</th><th>Value</th><th>Description</th></tr></thead><tbody><tr><td>Network Name *</td><td>XSI1</td><td>The name of this network. [Default = N/A. Range = Alphanumeric string up to 31 c</td></tr><tr><td>Network Type</td><td>Signaling</td><td>The type of this network.</td></tr><tr><td>VLAN ID</td><td>4</td><td>The VLAN ID to use for this network. If not set or set to 0, no VLAN ID is associate</td></tr><tr><td>Network Address *</td><td>10.10.3.0</td><td>The network address of this network. [Default = N/A. Range = Valid Network Addre</td></tr><tr><td>Netmask *</td><td>255.255.255.0</td><td>Subnetting to apply to servers within this network. [Default = N/A. Range = Valid N</td></tr><tr><td>Router IP</td><td></td><td>The IP address of a router on this network. If this is a default network, this will be router monitoring is enabled, this address will be the one monitored.</td></tr><tr><td>Default Network</td><td><div><div><input type="radio"/> Yes</div><div><input checked="" type="radio"/> No</div></div></td><td>A selection indicating whether this is the network with a default gateway.</td></tr><tr><td>Routed</td><td><div><div><input checked="" type="radio"/> Yes</div><div><input type="radio"/> No</div></div></td><td>Whether or not this network is routed outside its network element. If it is not assign</td></tr></tbody></table><div><div>Ok</div><div>Apply</div><div>Cancel</div></div></div></div></div><p>Enter all of the fields for the XSI1 network according to the network parameters. Retain the default values for Network Element (Signalling), Default Network (No) and Routable (Yes).</p><p>ComAgent Service may be configured to run on XSI1. In this case, the XSI1 network is used for MP to NOAMP ComAgent Traffic.</p><p>NOTE: Network names can be overloaded to support multiple subnets. When defining network for ComAgent Service, use same network name for Primary and DR Site.</p><p>NOTE: VLANs are not used in the context of this document, though VLAN ID is a required field on this screen. Enter any number in the valid range.</p></div>	Field	Value	Description	Network Name *	XSI1	The name of this network. [Default = N/A. Range = Alphanumeric string up to 31 c	Network Type	Signaling	The type of this network.	VLAN ID	4	The VLAN ID to use for this network. If not set or set to 0, no VLAN ID is associate	Network Address *	10.10.3.0	The network address of this network. [Default = N/A. Range = Valid Network Addre	Netmask *	255.255.255.0	Subnetting to apply to servers within this network. [Default = N/A. Range = Valid N	Router IP		The IP address of a router on this network. If this is a default network, this will be router monitoring is enabled, this address will be the one monitored.	Default Network	<div><div><input type="radio"/> Yes</div><div><input checked="" type="radio"/> No</div></div>	A selection indicating whether this is the network with a default gateway.	Routed	<div><div><input checked="" type="radio"/> Yes</div><div><input type="radio"/> No</div></div>	Whether or not this network is routed outside its network element. If it is not assign
Field	Value	Description																											
Network Name *	XSI1	The name of this network. [Default = N/A. Range = Alphanumeric string up to 31 c																											
Network Type	Signaling	The type of this network.																											
VLAN ID	4	The VLAN ID to use for this network. If not set or set to 0, no VLAN ID is associate																											
Network Address *	10.10.3.0	The network address of this network. [Default = N/A. Range = Valid Network Addre																											
Netmask *	255.255.255.0	Subnetting to apply to servers within this network. [Default = N/A. Range = Valid N																											
Router IP		The IP address of a router on this network. If this is a default network, this will be router monitoring is enabled, this address will be the one monitored.																											
Default Network	<div><div><input type="radio"/> Yes</div><div><input checked="" type="radio"/> No</div></div>	A selection indicating whether this is the network with a default gateway.																											
Routed	<div><div><input checked="" type="radio"/> Yes</div><div><input type="radio"/> No</div></div>	Whether or not this network is routed outside its network element. If it is not assign																											
4. <input type="checkbox"/>	UDR Server A Repeat as required	Repeat Step 3 of this procedure to Insertadditional signaling networks(XSI2, etc) if applicable.																											
5. <input type="checkbox"/>	UDR Server A XSI network is displayed along with a success message.	<div><div>Main Menu: Configuration -> Networking -> Networks</div><div><div>Info</div><div><div>Info</div><div><div>• Network 'XSI1' was successfully inserted.</div></div></div><table><thead><tr><th>Network Name</th><th>Network Type</th><th>Default</th><th>Locked</th><th>Routed</th><th>VLAN</th><th>Configured Interfaces</th><th>Network</th></tr></thead><tbody><tr><td>XSI1</td><td>Signaling</td><td>No</td><td>No</td><td>Yes</td><td>4</td><td>0</td><td>10.10.3.0/24</td></tr></tbody></table></div></div>	Network Name	Network Type	Default	Locked	Routed	VLAN	Configured Interfaces	Network	XSI1	Signaling	No	No	Yes	4	0	10.10.3.0/24											
Network Name	Network Type	Default	Locked	Routed	VLAN	Configured Interfaces	Network																						
XSI1	Signaling	No	No	Yes	4	0	10.10.3.0/24																						
THIS PROCEDURE HAS BEEN COMPLETED																													

Chapter 6. OAM Pairing

6.1 OAM Pairing for Primary UDR Servers (1st NOAMP site only)

During the OAM Pairing procedure, various errors may be seen at different stages of the procedure. While performing a step, ignore errors related to values other than the ones referenced by that step.




This procedure creates an active, standby pair for the UDR servers at the Primary Provisioning Site.

Requirements:




- Section 5.3 Apply Configuration To Remaining Servers has been completed

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 9: OAM Pairing for Primary UDR Servers (1st NOAMP site only)

Step	Procedure	Result
1. <input type="checkbox"/>	UDR Server A: Launch an approved web browser and connect to the UDR Server A IP address	NOTE: Click Continue to this website (not recommended) if the security certificate warning displays. Login to the GUI using the default user and password. 
2. <input type="checkbox"/>	UDR Server A: Configuring Server Group	Navigate to Main Menu → Configuration → Server Groups 
3. <input type="checkbox"/>	UDR Server A: Click Insert located at the bottom left corner of the page. NOTE: Use the vertical scroll-bar to see the Insert button.	




Step	Procedure	Result																		
4. <input type="checkbox"/>	UDR Server A: The Server Groups [Insert] screen opens.	<p>Adding new server group</p> <table border="1"> <thead> <tr> <th>Field</th><th>Value</th><th>Description</th></tr> </thead> <tbody> <tr> <td>Server Group Name *</td><td><input type="text"/></td><td>Unique identifier used to label a Server Group. [Default = n/a. Range = A 1-32-character string, at least one alpha and must not start with a digit.] [A value is required.]</td></tr> <tr> <td>Level *</td><td>- Select Level -</td><td>Select one of the Levels supported by the system. Level C groups contain MP servers. [A value is required.]</td></tr> <tr> <td>Parent *</td><td>- Select Parent -</td><td>Select an existing Server Group or NONE [A value is required.]</td></tr> <tr> <td>Function *</td><td>- Select Function -</td><td>Select one of the Functions supported by the system [A value is required.]</td></tr> <tr> <td>WAN Replication Connection Count</td><td><input type="text" value="1"/></td><td>Specify the number of TCP connections that will be used for WAN replication. [A value is required. Integer between 1 and 8.]</td></tr> </tbody> </table> <p>Ok Apply Cancel</p>	Field	Value	Description	Server Group Name *	<input type="text"/>	Unique identifier used to label a Server Group. [Default = n/a. Range = A 1-32-character string, at least one alpha and must not start with a digit.] [A value is required.]	Level *	- Select Level -	Select one of the Levels supported by the system. Level C groups contain MP servers. [A value is required.]	Parent *	- Select Parent -	Select an existing Server Group or NONE [A value is required.]	Function *	- Select Function -	Select one of the Functions supported by the system [A value is required.]	WAN Replication Connection Count	<input type="text" value="1"/>	Specify the number of TCP connections that will be used for WAN replication. [A value is required. Integer between 1 and 8.]
Field	Value	Description																		
Server Group Name *	<input type="text"/>	Unique identifier used to label a Server Group. [Default = n/a. Range = A 1-32-character string, at least one alpha and must not start with a digit.] [A value is required.]																		
Level *	- Select Level -	Select one of the Levels supported by the system. Level C groups contain MP servers. [A value is required.]																		
Parent *	- Select Parent -	Select an existing Server Group or NONE [A value is required.]																		
Function *	- Select Function -	Select one of the Functions supported by the system [A value is required.]																		
WAN Replication Connection Count	<input type="text" value="1"/>	Specify the number of TCP connections that will be used for WAN replication. [A value is required. Integer between 1 and 8.]																		
5. <input type="checkbox"/>	UDR Server A: Enter the Server Group Name.	<table border="1"> <thead> <tr> <th>Field</th><th>Value</th><th>Description</th></tr> </thead> <tbody> <tr> <td>Server Group Name *</td><td><input type="text" value="NO_SG"/></td><td>Unique identifier used to label a Server Group. [Default = n/a. Range = A 1-32-character string, at least one alpha and must not start with a digit.] [A value is required.]</td></tr> </tbody> </table>	Field	Value	Description	Server Group Name *	<input type="text" value="NO_SG"/>	Unique identifier used to label a Server Group. [Default = n/a. Range = A 1-32-character string, at least one alpha and must not start with a digit.] [A value is required.]												
Field	Value	Description																		
Server Group Name *	<input type="text" value="NO_SG"/>	Unique identifier used to label a Server Group. [Default = n/a. Range = A 1-32-character string, at least one alpha and must not start with a digit.] [A value is required.]																		
6. <input type="checkbox"/>	UDR Server A: Select A on the Level menu.	<table border="1"> <tbody> <tr> <td>Level *</td> <td> <div>- Select Level -</div> <div>- Select Level -</div> <div>A</div> </td> <td>Select one of the Levels supported by the system. B groups are optional and contain SOAM servers.</td> </tr> </tbody> </table>	Level *	<div>- Select Level -</div> <div>- Select Level -</div> <div>A</div>	Select one of the Levels supported by the system. B groups are optional and contain SOAM servers.															
Level *	<div>- Select Level -</div> <div>- Select Level -</div> <div>A</div>	Select one of the Levels supported by the system. B groups are optional and contain SOAM servers.																		
7. <input type="checkbox"/>	UDR Server A: Select None on the Parent menu.	<table border="1"> <tbody> <tr> <td>Parent *</td> <td> <div>- Select Parent-</div> <div>- Select Parent-</div> <div>NONE</div> </td> <td>Select an existing Server Group or NONE [A value is required.]</td> </tr> <tr> <td>Function *</td> <td>- Select Function -</td> <td>Select one of the Functions supported by the system [A value is required.]</td> </tr> </tbody> </table>	Parent *	<div>- Select Parent-</div> <div>- Select Parent-</div> <div>NONE</div>	Select an existing Server Group or NONE [A value is required.]	Function *	- Select Function -	Select one of the Functions supported by the system [A value is required.]												
Parent *	<div>- Select Parent-</div> <div>- Select Parent-</div> <div>NONE</div>	Select an existing Server Group or NONE [A value is required.]																		
Function *	- Select Function -	Select one of the Functions supported by the system [A value is required.]																		
8. <input type="checkbox"/>	UDR Server A: Select UDR-NO on the Function menu.	<table border="1"> <tbody> <tr> <td>Function *</td> <td> <div>UDR-NO</div> </td> <td></td> </tr> </tbody> </table>	Function *	<div>UDR-NO</div>																
Function *	<div>UDR-NO</div>																			
9. <input type="checkbox"/>	UDR Server A: Enter 8 for WAN Replication Connection Count.	<table border="1"> <tbody> <tr> <td>WAN Replication Connection Count</td> <td><input type="text" value="8"/></td> <td>Specify the number of TCP connections that will be used for WAN replication. [A value is required. Integer between 1 and 8.]</td> </tr> </tbody> </table>	WAN Replication Connection Count	<input type="text" value="8"/>	Specify the number of TCP connections that will be used for WAN replication. [A value is required. Integer between 1 and 8.]															
WAN Replication Connection Count	<input type="text" value="8"/>	Specify the number of TCP connections that will be used for WAN replication. [A value is required. Integer between 1 and 8.]																		




Step	Procedure	Result										
10. <input type="checkbox"/>	UDR Server A: Click Info to see a banner message stating Pre-Validation passed. Click Apply .											
11. <input type="checkbox"/>	UDR Server A: Click Info to see a banner message stating Data committed.											
12. <input type="checkbox"/>	UDR Server A: Navigate to Main Menu → Configuration → Server Groups	 <table><tr><th>Server Group Name</th><th>Level</th><th>Parent</th><th>Function</th><th>Connection Count</th></tr><tr><td>NO_SG</td><td>A</td><td>NONE</td><td>UDR-NO</td><td>8</td></tr></table>	Server Group Name	Level	Parent	Function	Connection Count	NO_SG	A	NONE	UDR-NO	8
Server Group Name	Level	Parent	Function	Connection Count								
NO_SG	A	NONE	UDR-NO	8								






Step	Procedure	Result										
13. <input type="checkbox"/>	<p>UDR Server A:</p> <ol style="list-style-type: none">1. Select the Server Group entry just added. The line entry is highlighted in sky blue.2. Click Edit (located at the bottom left corner of the page). <p>NOTE: You may need to use the vertical scroll-bar to see the Edit.</p>	<div><p>Main Menu: Configuration -> Server Groups</p><div><div>Filter* ▼</div><table><tr><th>Server Group Name</th><th>Level</th><th>Parent</th><th>Function</th><th>Connection Count</th></tr><tr><td>NO_SG</td><td>A</td><td>NONE</td><td>UDR-NO</td><td>8</td></tr></table></div><div><div>Insert</div><div>Edit</div><div>Delete</div><div>Report</div></div></div>	Server Group Name	Level	Parent	Function	Connection Count	NO_SG	A	NONE	UDR-NO	8
Server Group Name	Level	Parent	Function	Connection Count								
NO_SG	A	NONE	UDR-NO	8								



Step	Procedure	Result																																				
14. <input type="checkbox"/>	UDR Server A: The Server Groups [Edit] screen opens.	<div><div>Main Menu: Configuration -> Server Groups [Edit]</div><div><div>Modifying attributes of server group : NO_SG</div><table><thead><tr><th>Field</th><th>Value</th><th>Description</th></tr></thead><tbody><tr><td>Server Group Name *</td><td><input type="text" value="NO_SG"/></td><td>Unique identifier used to label a Server Group. [Default = n/a.]</td></tr><tr><td>Level *</td><td><input type="text" value="A"/></td><td>Select one of the Levels supported by the system [A value is required.]</td></tr><tr><td>Parent *</td><td><input type="text" value="NONE"/></td><td>Select an existing Server Group [A value is required.]</td></tr><tr><td>Function *</td><td><input type="text" value="UDR-NO"/></td><td>Select one of the Functions supported by the system [A value is required.]</td></tr><tr><td>WAN Replication Connection Count</td><td><input type="text" value="8"/></td><td>Specify the number of TCP connections that will be used by the system.</td></tr></tbody></table><div><div>Site1_NE_NO</div><div><input type="checkbox"/> Prefer Network Element as spare</div></div><table><thead><tr><th>Server</th><th>SG Inclusion</th><th>Preferred HA Role</th></tr></thead><tbody><tr><td>OCUDR-A</td><td><input type="checkbox"/> Include in SG</td><td><input type="checkbox"/> Prefer server as spare</td></tr><tr><td>OCUDR-B</td><td><input type="checkbox"/> Include in SG</td><td><input type="checkbox"/> Prefer server as spare</td></tr></tbody></table><div><div>Site2_NE_DR_NO</div><div><input type="checkbox"/> Prefer Network Element as spare</div></div><table><thead><tr><th>Server</th><th>SG Inclusion</th><th>Preferred HA Role</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td><input type="checkbox"/> Include in SG</td><td><input type="checkbox"/> Prefer server as spare</td></tr><tr><td>DR-OCUDR-B</td><td><input type="checkbox"/> Include in SG</td><td><input type="checkbox"/> Prefer server as spare</td></tr></tbody></table><div>VIP Assignment</div><div><div>VIP Address</div><div>Add</div></div><div><div>Ok</div><div>Apply</div><div>Cancel</div></div></div></div>	Field	Value	Description	Server Group Name *	<input type="text" value="NO_SG"/>	Unique identifier used to label a Server Group. [Default = n/a.]	Level *	<input type="text" value="A"/>	Select one of the Levels supported by the system [A value is required.]	Parent *	<input type="text" value="NONE"/>	Select an existing Server Group [A value is required.]	Function *	<input type="text" value="UDR-NO"/>	Select one of the Functions supported by the system [A value is required.]	WAN Replication Connection Count	<input type="text" value="8"/>	Specify the number of TCP connections that will be used by the system.	Server	SG Inclusion	Preferred HA Role	OCUDR-A	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare	OCUDR-B	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare	Server	SG Inclusion	Preferred HA Role	DR-OCUDR-A	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare	DR-OCUDR-B	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare
Field	Value	Description																																				
Server Group Name *	<input type="text" value="NO_SG"/>	Unique identifier used to label a Server Group. [Default = n/a.]																																				
Level *	<input type="text" value="A"/>	Select one of the Levels supported by the system [A value is required.]																																				
Parent *	<input type="text" value="NONE"/>	Select an existing Server Group [A value is required.]																																				
Function *	<input type="text" value="UDR-NO"/>	Select one of the Functions supported by the system [A value is required.]																																				
WAN Replication Connection Count	<input type="text" value="8"/>	Specify the number of TCP connections that will be used by the system.																																				
Server	SG Inclusion	Preferred HA Role																																				
OCUDR-A	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare																																				
OCUDR-B	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare																																				
Server	SG Inclusion	Preferred HA Role																																				
DR-OCUDR-A	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare																																				
DR-OCUDR-B	<input type="checkbox"/> Include in SG	<input type="checkbox"/> Prefer server as spare																																				


Step	Procedure	Result
15. <input type="checkbox"/>	<p>UDR Server A:</p> <p>Select the options to include the A server and the B server in the UDR server group.</p> <p>NOTE: For single server installation, only NO-A is displayed; therefore only one option is selected.</p> <p>If this is a primary site (single site), then the DR site is not listed.</p>	
16. <input type="checkbox"/>	<p>UDR Server A:</p> <p>Click Info to see a banner message stating Pre-Validation passed.</p> <p>Click Apply.</p>	







Step	Procedure	Result
17. <input type="checkbox"/>	UDR Server A: Click Info to see a banner message stating Data committed.	
18. <input type="checkbox"/>	UDR Server A: Click Add for the VIP Address. NOTE: VIP Address optional for Single Server Configuration.	
19. <input type="checkbox"/>	UDR Server A: Enter the VIP Address	

Step	Procedure	Result
20. <input type="checkbox"/>	UDR Server A: Click Info to see a banner message stating Pre-Validation passed. Click Apply .	
21. <input type="checkbox"/>	UDR Server A: Click Info to see a banner message stating Data committed.	
22. <input type="checkbox"/>	UDR Server A: Click Logout on the OAM A server GUI.	
23. <input type="checkbox"/>	IMPORTANT: <i>Wait at least 5 minutes before proceeding on to the next step.</i>	<p>Now that the servers have been paired in a Server Group they must establish a master/slave relationship for High Availability (HA). It may take several minutes for this process to be completed.</p> <p>NOTE: Single server configuration is not needed to establish the master/slave relationship for High Availability (HA).</p> <p>Allow a minimum of 5 minutes before continuing to the next Step.</p>

Step	Procedure	Result
24. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Launch an approved web browser and connect to the UDR Server A IP address</p> <p>NOTE: Click Continue to this website (not recommended) if the security certificate warning displays.</p> <p>Login to the GUI using the default user and password.</p>	
25. <input type="checkbox"/>	<p>UDR VIP:</p> <p>Restarting the UDR Server Application</p> <p>Navigate to Main Menu → Status & Manage → Server</p>	<p>Normal or Low Capacity Configuration:</p>  <p>Single Server Configuration:</p> 
26. <input type="checkbox"/>	<p>UDR VIP:</p> <p>1. The A and B servers are listed in the right panel.</p> <p>NOTE: For single server, only the A server is listed.</p> <p>2. Verify that the DB status shows Norm and the Proc status shows Man for one or both servers before proceeding to the next Step.</p>	<p>Normal or Low Capacity Configuration:</p>  <p>Single Server Configuration:</p> 

Step	Procedure	Result																																																								
27. <input type="checkbox"/>	<p>UDR VIP:</p> <ol style="list-style-type: none">Using the mouse, select UDR Server A. The line entry is highlighted in sky blue.Click Restart (located at the bottom of the page).Click OK. <p>A confirmation message (in the banner area) for UDR Server A displays stating: Successfully restarted application.</p> <p>NOTE: Use the vertical scroll-bar to see the Restart button.</p>	<p>Normal Configuration:</p> <table><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr></table> <p>Single Server Configuration:</p> <table><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr></table> <div><div> Help  Logout</div><div><div>Stop</div><div>Restart</div><div>Reboot</div></div></div> <div><p>Are you sure you wish to restart application software on the following server(s)? OCUDR-A</p><div><div>OK</div><div>Cancel</div></div></div> <p>Main Menu: Status & Manage -> Server</p> <div><div>Filter* Info</div><div><div>Info</div><div>• OCUDR-A: Successfully restarted application.</div></div><table><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr></table></div> <p>Fri Apr 06 03:38:51 2018 EDT</p>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	OCUDR-A	Site1_NE_NO	Disabled	Err	Norm	Norm	Man	OCUDR-B	Site1_NE_NO	Disabled	Err	Norm	Norm	Man	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	OCUDR-A	Site1_NE_NO	Disabled	Err	Norm	Norm	Man	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Disabled	Err	Norm	Norm	Man
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																																																				
OCUDR-A	Site1_NE_NO	Disabled	Err	Norm	Norm	Man																																																				
OCUDR-B	Site1_NE_NO	Disabled	Err	Norm	Norm	Man																																																				
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																																																				
OCUDR-A	Site1_NE_NO	Disabled	Err	Norm	Norm	Man																																																				
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																																																				
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																																																				
OCUDR-B	Site1_NE_NO	Disabled	Err	Norm	Norm	Man																																																				
28. <input type="checkbox"/>	<p>UDR VIP:</p> <p>Verify that the Appl State shows Enabled and that the DB, Reporting Status and Proc status columns all show Norm for UDR Server A before proceeding to the next Step.</p>	<table><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr></table> <p>NOTE: If you want to refresh the Server status screen before the default setting (15 to 30 seconds), this can be done by reselecting the Status & Manage → Server option from the Main menu.</p>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Disabled	Err	Norm	Norm	Man																																			
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																																																				
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																																																				
OCUDR-B	Site1_NE_NO	Disabled	Err	Norm	Norm	Man																																																				
29. <input type="checkbox"/>	<p>UDR VIP:</p> <p>Restart UDR Server B.</p>	<p>NOTE: Do not perform this step for single server installations.</p> <p>Repeat steps 27 and 28 to restart UDR Server B.</p>																																																								

Step	Procedure	Result																																																																																																																																																																																				
30. <input type="checkbox"/>	UDR VIP: Verifying the UDR server alarm status	Navigate to Main Menu → Alarms & Events → View Active 																																																																																																																																																																																				
31. <input type="checkbox"/>	UDR VIP: Verify that the Event IDs are the only alarms present on the system.	<table><tr><th>Seq #</th><th>Event ID</th><th>Timestamp</th><th>Severity</th><th>Product</th><th>Process</th><th>NE</th><th>Server</th><th>Type</th><th>Instance</th></tr><tr><td></td><td colspan="2">Alarm Text</td><td colspan="7">Additional Info</td></tr><tr><td>129</td><td>19820</td><td>2015-09-21 15:42:00.187 EDT</td><td>MAJOR</td><td>CAF</td><td>udrbe</td><td>NO_UDR_NE</td><td>no-b</td><td>CAF</td><td>UDR-RS-Sh-App</td></tr><tr><td></td><td colspan="9">Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [26801:ComAgentStack.C:2826]</td></tr><tr><td>309</td><td>19820</td><td>2015-09-21 15:14:54.295 EDT</td><td>MAJOR</td><td>CAF</td><td>udrbe</td><td>NO_UDR_NE</td><td>no-a</td><td>CAF</td><td>UDR-RS-Sh-App</td></tr><tr><td></td><td colspan="9">Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [16353:ComAgentStack.C:2826]</td></tr><tr><td>266</td><td>13001</td><td>2015-09-21 15:14:48.842 EDT</td><td>MAJOR</td><td>Provisioning</td><td>udrprov</td><td>NO_UDR_NE</td><td>no-a</td><td>PROV</td><td>REST</td></tr><tr><td></td><td colspan="9">No Remote RAS Client Connections GN_NOTENAB/WRN No remote provisioning RAS clients are connected. ^^ [16365... More...</td></tr><tr><td>265</td><td>13027</td><td>2015-09-21 15:14:47.841 EDT</td><td>MAJOR</td><td>Provisioning</td><td>udrprov</td><td>NO_UDR_NE</td><td>no-a</td><td>PROV</td><td>SOAP</td></tr><tr><td></td><td colspan="9">No Remote XSAS Client Connections GN_NOTENAB/WRN No remote provisioning XSAS clients are connected. ^^ [1636... More...</td></tr></table> <table><tr><th>Seq #</th><th>Event ID</th><th>Timestamp</th><th>Severity</th><th>Product</th><th>Process</th><th>NE</th><th>Server</th><th>Type</th><th>Instance</th></tr><tr><td></td><td colspan="2">Alarm Text</td><td colspan="7">Additional Info</td></tr><tr><td>45</td><td>19820</td><td>2018-04-06 03:22:08.022 EDT</td><td>MAJOR</td><td>CAF</td><td>udrbe</td><td>Site1_NE_NO</td><td>OCUDR-B</td><td>CAF</td><td>UDR-RS-Sh-App</td></tr><tr><td></td><td colspan="9">Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [31511:ComAgentStack.C:3025]</td></tr><tr><td>79</td><td>13075</td><td>2018-04-06 03:20:18.023 EDT</td><td>CRITICAL</td><td>Provisioning</td><td>udrprov</td><td>Site1_NE_NO</td><td>OCUDR-A</td><td>PROV</td><td></td></tr><tr><td></td><td colspan="9">Provisioning Interfaces Disabled GN_NOTENAB/WRN SOAP and REST interfaces are disabled ^^ [945:ProvControlle... More...</td></tr><tr><td>69</td><td>19820</td><td>2018-04-06 03:20:13.117 EDT</td><td>MAJOR</td><td>CAF</td><td>udrbe</td><td>Site1_NE_NO</td><td>OCUDR-A</td><td>CAF</td><td>UDR-RS-Sh-App</td></tr><tr><td></td><td colspan="9">Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [577:ComAgentStack.C:3025]</td></tr></table> Verify that only the following Event IDs are the only alarms present: 13075 Provisioning Interfaces Disabled 19820 Communicaton Agent Routed Service Unavailable NOTE: It may take a few minutes for residual process alarms to clear.	Seq #	Event ID	Timestamp	Severity	Product	Process	NE	Server	Type	Instance		Alarm Text		Additional Info							129	19820	2015-09-21 15:42:00.187 EDT	MAJOR	CAF	udrbe	NO_UDR_NE	no-b	CAF	UDR-RS-Sh-App		Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [26801:ComAgentStack.C:2826]									309	19820	2015-09-21 15:14:54.295 EDT	MAJOR	CAF	udrbe	NO_UDR_NE	no-a	CAF	UDR-RS-Sh-App		Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [16353:ComAgentStack.C:2826]									266	13001	2015-09-21 15:14:48.842 EDT	MAJOR	Provisioning	udrprov	NO_UDR_NE	no-a	PROV	REST		No Remote RAS Client Connections GN_NOTENAB/WRN No remote provisioning RAS clients are connected. ^^ [16365... More...									265	13027	2015-09-21 15:14:47.841 EDT	MAJOR	Provisioning	udrprov	NO_UDR_NE	no-a	PROV	SOAP		No Remote XSAS Client Connections GN_NOTENAB/WRN No remote provisioning XSAS clients are connected. ^^ [1636... More...									Seq #	Event ID	Timestamp	Severity	Product	Process	NE	Server	Type	Instance		Alarm Text		Additional Info							45	19820	2018-04-06 03:22:08.022 EDT	MAJOR	CAF	udrbe	Site1_NE_NO	OCUDR-B	CAF	UDR-RS-Sh-App		Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [31511:ComAgentStack.C:3025]									79	13075	2018-04-06 03:20:18.023 EDT	CRITICAL	Provisioning	udrprov	Site1_NE_NO	OCUDR-A	PROV			Provisioning Interfaces Disabled GN_NOTENAB/WRN SOAP and REST interfaces are disabled ^^ [945:ProvControlle... More...									69	19820	2018-04-06 03:20:13.117 EDT	MAJOR	CAF	udrbe	Site1_NE_NO	OCUDR-A	CAF	UDR-RS-Sh-App		Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [577:ComAgentStack.C:3025]								
Seq #	Event ID	Timestamp	Severity	Product	Process	NE	Server	Type	Instance																																																																																																																																																																													
	Alarm Text		Additional Info																																																																																																																																																																																			
129	19820	2015-09-21 15:42:00.187 EDT	MAJOR	CAF	udrbe	NO_UDR_NE	no-b	CAF	UDR-RS-Sh-App																																																																																																																																																																													
	Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [26801:ComAgentStack.C:2826]																																																																																																																																																																																					
309	19820	2015-09-21 15:14:54.295 EDT	MAJOR	CAF	udrbe	NO_UDR_NE	no-a	CAF	UDR-RS-Sh-App																																																																																																																																																																													
	Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [16353:ComAgentStack.C:2826]																																																																																																																																																																																					
266	13001	2015-09-21 15:14:48.842 EDT	MAJOR	Provisioning	udrprov	NO_UDR_NE	no-a	PROV	REST																																																																																																																																																																													
	No Remote RAS Client Connections GN_NOTENAB/WRN No remote provisioning RAS clients are connected. ^^ [16365... More...																																																																																																																																																																																					
265	13027	2015-09-21 15:14:47.841 EDT	MAJOR	Provisioning	udrprov	NO_UDR_NE	no-a	PROV	SOAP																																																																																																																																																																													
	No Remote XSAS Client Connections GN_NOTENAB/WRN No remote provisioning XSAS clients are connected. ^^ [1636... More...																																																																																																																																																																																					
Seq #	Event ID	Timestamp	Severity	Product	Process	NE	Server	Type	Instance																																																																																																																																																																													
	Alarm Text		Additional Info																																																																																																																																																																																			
45	19820	2018-04-06 03:22:08.022 EDT	MAJOR	CAF	udrbe	Site1_NE_NO	OCUDR-B	CAF	UDR-RS-Sh-App																																																																																																																																																																													
	Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [31511:ComAgentStack.C:3025]																																																																																																																																																																																					
79	13075	2018-04-06 03:20:18.023 EDT	CRITICAL	Provisioning	udrprov	Site1_NE_NO	OCUDR-A	PROV																																																																																																																																																																														
	Provisioning Interfaces Disabled GN_NOTENAB/WRN SOAP and REST interfaces are disabled ^^ [945:ProvControlle... More...																																																																																																																																																																																					
69	19820	2018-04-06 03:20:13.117 EDT	MAJOR	CAF	udrbe	Site1_NE_NO	OCUDR-A	CAF	UDR-RS-Sh-App																																																																																																																																																																													
	Communication Agent Routed Service Unavailable GN_INFO/WRN ^^ [577:ComAgentStack.C:3025]																																																																																																																																																																																					

Step	Procedure	Result
32. <input type="checkbox"/>	UDR VIP: Configuring SNMP for Traps from Individual Servers	Navigate to Main Menu → Administration → Remote Servers → SNMP Trapping  
33. <input type="checkbox"/>	UDR VIP: 1. Select Traps from Individual Servers . 2. Click OK located at the bottom in the center of the screen. 3. Verify that a banner message stating Data committed is received.	  
34. <input type="checkbox"/>	UDR VIP: Click Logout on the server GUI.	
THIS PROCEDURE HAS BEEN COMPLETED		

6.2 OAM Pairing for DR Sites

During the OAM Pairing procedure, various errors may be seen at different stages of the procedure. While performing a step, ignore errors related to values other than the ones referenced by that step.

The steps in this procedure are for all the DR UDR servers.




This procedure creates an active, standby pair for the DR UDR Servers.







Requirements:

- Chapter 5 Oracle Communications User Data Repository Server Configuration has been completed
- Section 6.1 OAM Pairing for Primary UDR Servers (1st NOAMP site only) has been completed





Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.





Procedure 10: OAM Pairing for DR Sites

Step	Procedure	Result
1. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Launch an approved web browser and connect to the UDR Server A IP address</p> <p>NOTE: Click Continue to this website (not recommended) if the security certificate warning displays.</p> <p>Login to the GUI using the default user and password.</p>	
2. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>For primary UDR standby server only:</p> <p>Change the HA role to forced standby for the server.</p> <ol style="list-style-type: none">1. Navigate to Main Menu → Status & Manage → HA2. Click Edit on bottom left3. Find the row for the primary UDR standby server and change Max Allowed HA Role to Standby.	<p>NOTE: Do not perform this step for single server installations.</p> 
3. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Navigate to Main Menu → Configuration → Server Groups</p>	

Step	Procedure	Result
4. <input type="checkbox"/>	Active UDR VIP: Click Insert located at the bottom left corner of the page. NOTE: Use the vertical scroll-bar to see the Insert button.	
5. <input type="checkbox"/>	Active UDR VIP: Configuring the DR UDR Server Group The Server Groups [Insert] page opens.	
6. <input type="checkbox"/>	Active UDR VIP: Enter the Server Group Name.	
7. <input type="checkbox"/>	Active UDR VIP: Assign the group Level.	 <p>Use this setting for group level:</p> <ul style="list-style-type: none"> For DR UDR server group: select A on the Level menu.
8. <input type="checkbox"/>	Active UDR VIP: Assign the Parent.	 <p>Use this setting for parent:</p> <p>For DR UDR server group: select NONE on the Parent menu.</p>
9. <input type="checkbox"/>	Active UDR VIP: Assign the Function.	 <p>Use this setting for function:</p> <p>For DR UDR server group: select UDR-NO on the Function menu.</p>

Step	Procedure	Result
10. <input type="checkbox"/>	Active UDR VIP: For DR UDR only: Enter 8 for the WAN Replication Connection Count.	<div><div>WAN Replication Connection Count</div><div>8</div><div>Specify the number of TCP connections that will be used by Group. [Default = 1. Range = An integer between 1 and 8.]</div></div>
11. <input type="checkbox"/>	Active UDR VIP: Click Info to see a banner with a message stating that Pre-Validation passed. Click Apply	<div><div><div>Main Menu: Configuration -> Server Groups [Insert]</div><div><div>Info</div><div><div>Info</div><div><div><div>• Pre-Validation passed - Data NOT committed ...</div></div></div></div></div><div><div>Ok</div><div>Apply</div><div>Cancel</div></div></div></div>
12. <input type="checkbox"/>	Active UDR VIP: You see a banner with a message stating Data committed.	<div><div><div>Main Menu: Configuration -> Server Groups [Insert]</div><div><div>Info*</div><div><div>Info</div><div><div><div>• Data committed!</div></div></div></div></div><div><div>Field</div><div>Value</div><div>Description</div></div></div></div>
13. <input type="checkbox"/>	Active UDR VIP: Navigate to Main Menu → Configuration → Server Groups NOTE: Server group entry is listed on the Server Groups configuration screen.	<div><div><div>Main Menu: Configuration -> Server Groups</div><div><div>Filter*</div><div><div><div>Server Group Name</div><div>Level</div><div>Parent</div><div>Function</div><div>Connection Count</div><div>Servers</div></div><div><div>DR_NO_SG</div><div>A</div><div>NONE</div><div>UDR-NO</div><div>8</div><div><div>Network Element: Site1_NE_NO</div><div>NE HA Pref: DEFAULT</div><div><div>Server</div><div>Node HA Pref</div><div>VIPs</div></div><div><div>OCUDR-A</div><div></div><div>10.10.1.121</div></div><div><div>OCUDR-B</div><div></div><div>10.10.1.121</div></div></div></div></div><div><div>NO_SG</div><div>A</div><div>NONE</div><div>UDR-NO</div><div>8</div><div></div></div></div></div></div>
14. <input type="checkbox"/>	Active UDR VIP: 1. Select the Server Group entry applied in Step 7. The line entry is highlighted in sky blue. 2. Click Edit (located at the bottom left corner of the page). NOTE: Use the vertical scroll-bar to see the Edit button.	<div><div><div><div>Server Group Name</div><div>Level</div><div>Parent</div><div>Function</div><div>Connection Count</div><div>Servers</div></div><div><div>DR_NO_SG</div><div>A</div><div>NONE</div><div>UDR-NO</div><div>8</div><div><div>Network Element: Site1_NE_NO</div><div>NE HA Pref: DEFAULT</div><div><div>Server</div><div>Node HA Pref</div><div>VIPs</div></div><div><div>OCUDR-A</div><div></div><div>10.10.1.121</div></div><div><div>OCUDR-B</div><div></div><div>10.10.1.121</div></div></div></div></div><div><div><div>Insert</div><div>Edit</div><div>Delete</div><div>Report</div></div></div></div>

Step	Procedure	Result									
15. <input type="checkbox"/>	Active UDR VIP: Select the A server and the B server from the list of servers.	Normal or Low Capacity Configuration:  <table border="1"> <thead> <tr> <th>Server</th><th>SG Inclusion</th><th>Preferred HA Role</th></tr> </thead> <tbody> <tr> <td>DR-OCUDR-A</td><td><input checked="" type="checkbox"/> Include in SG</td><td><input checked="" type="checkbox"/> Prefer server as spare</td></tr> <tr> <td>DR-OCUDR-B</td><td><input checked="" type="checkbox"/> Include in SG</td><td><input checked="" type="checkbox"/> Prefer server as spare</td></tr> </tbody> </table>	Server	SG Inclusion	Preferred HA Role	DR-OCUDR-A	<input checked="" type="checkbox"/> Include in SG	<input checked="" type="checkbox"/> Prefer server as spare	DR-OCUDR-B	<input checked="" type="checkbox"/> Include in SG	<input checked="" type="checkbox"/> Prefer server as spare
Server	SG Inclusion	Preferred HA Role									
DR-OCUDR-A	<input checked="" type="checkbox"/> Include in SG	<input checked="" type="checkbox"/> Prefer server as spare									
DR-OCUDR-B	<input checked="" type="checkbox"/> Include in SG	<input checked="" type="checkbox"/> Prefer server as spare									
16. <input type="checkbox"/>	Active UDR VIP: For DR UDR servers only Select the preferred spare options.	 <p>NOTE: DR UDR is not accessible via their VIP unless they become the active UDR. Individual servers in the DR UDR server group are always accessible by their XMI addresses.</p>									
17. <input type="checkbox"/>	Active UDR VIP: Click Info to see a banner message stating Pre-Validation passed. Click Apply.	 <p>Ok Apply Cancel</p>									
18. <input type="checkbox"/>	Active UDR VIP: Click Info to see a banner message stating Data committed.	 <p>Server group : DR_NO_SG</p> <table border="1"> <thead> <tr> <th>Field</th><th>Value</th><th>Description</th></tr> </thead> <tbody> <tr> <td>Server Group Name *</td><td>DR_NO_SG</td><td>Unique identifier least one alpha</td></tr> </tbody> </table>	Field	Value	Description	Server Group Name *	DR_NO_SG	Unique identifier least one alpha			
Field	Value	Description									
Server Group Name *	DR_NO_SG	Unique identifier least one alpha									

Step	Procedure	Result
19. <input type="checkbox"/>	Active UDR VIP: Click Add for the VIP Address.	
20. <input type="checkbox"/>	Active UDR VIP: Enter the VIP Address	
21. <input type="checkbox"/>	Active UDR VIP: Click Info to see a banner message stating Pre-Validation passed. Click Apply .	
22. <input type="checkbox"/>	Active UDR VIP: Click Info to see a banner message stating Data committed.	

Step	Procedure	Result																																								
23. <input type="checkbox"/>	IMPORTANT: Wait at least 5 minutes before proceeding on to the next Step.	<p>Now that the servers are paired in a Server Group, they must establish a master/slave relationship for High Availability (HA). It may take several minutes for this process to be completed.</p> <p>NOTE: Single Server Configurations do not establish master/slave relationship for High Availability (HA).</p> <p>Allow a minimum of 5 minutes before continuing to the next Step.</p>																																								
24. <input type="checkbox"/>	Active UDR VIP: Navigate to Main Menu → Status & Manage → HA	<div><div>Main Menu: Status & Manage -> HA</div><div><div>Filter*</div><table><thead><tr><th>Hostname</th><th>OAM HA Role</th><th>Application HA Role</th><th>Max Allowed HA Role</th><th>Mate Hostname List</th><th>Network Element</th><th>Server Role</th><th>Active VIPs</th></tr></thead><tbody><tr><td>OCUDR-A</td><td>Active</td><td>N/A</td><td>Active</td><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Network OAM&P</td><td>10.10.1.121</td></tr><tr><td>OCUDR-B</td><td>Standby</td><td>N/A</td><td>Standby</td><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Network OAM&P</td><td></td></tr><tr><td>DR-OCUDR-A</td><td>Spare</td><td>N/A</td><td>Active</td><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Network OAM&P</td><td>10.10.1.28</td></tr><tr><td>DR-OCUDR-B</td><td>Spare</td><td>N/A</td><td>Standby</td><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Network OAM&P</td><td></td></tr></tbody></table></div></div>	Hostname	OAM HA Role	Application HA Role	Max Allowed HA Role	Mate Hostname List	Network Element	Server Role	Active VIPs	OCUDR-A	Active	N/A	Active	OCUDR-B	Site1_NE_NO	Network OAM&P	10.10.1.121	OCUDR-B	Standby	N/A	Standby	OCUDR-A	Site1_NE_NO	Network OAM&P		DR-OCUDR-A	Spare	N/A	Active	DR-OCUDR-B	Site2_NE_DR_NO	Network OAM&P	10.10.1.28	DR-OCUDR-B	Spare	N/A	Standby	DR-OCUDR-A	Site2_NE_DR_NO	Network OAM&P	
Hostname	OAM HA Role	Application HA Role	Max Allowed HA Role	Mate Hostname List	Network Element	Server Role	Active VIPs																																			
OCUDR-A	Active	N/A	Active	OCUDR-B	Site1_NE_NO	Network OAM&P	10.10.1.121																																			
OCUDR-B	Standby	N/A	Standby	OCUDR-A	Site1_NE_NO	Network OAM&P																																				
DR-OCUDR-A	Spare	N/A	Active	DR-OCUDR-B	Site2_NE_DR_NO	Network OAM&P	10.10.1.28																																			
DR-OCUDR-B	Spare	N/A	Standby	DR-OCUDR-A	Site2_NE_DR_NO	Network OAM&P																																				
25. <input type="checkbox"/>	Active UDR VIP: NOTE: DR UDR servers have an OAM MAX HA Role of Spare and no active VIPs	<p>Normal or Low Capacity Configuration:</p> <div><div>Main Menu: Status & Manage -> HA</div><div><div>Filter*</div><table><thead><tr><th>Hostname</th><th>OAM HA Role</th><th>Application HA Role</th><th>Max Allowed HA Role</th><th>Mate Hostname List</th><th>Network Element</th><th>Server Role</th><th>Active VIPs</th></tr></thead><tbody><tr><td>OCUDR-A</td><td>Active</td><td>N/A</td><td>Active</td><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Network OAM&P</td><td>10.10.1.121</td></tr><tr><td>OCUDR-B</td><td>Standby</td><td>N/A</td><td>Standby</td><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Network OAM&P</td><td></td></tr><tr><td>DR-OCUDR-A</td><td>Spare</td><td>N/A</td><td>Active</td><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Network OAM&P</td><td>10.10.1.28</td></tr><tr><td>DR-OCUDR-B</td><td>Spare</td><td>N/A</td><td>Standby</td><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Network OAM&P</td><td></td></tr></tbody></table></div></div>	Hostname	OAM HA Role	Application HA Role	Max Allowed HA Role	Mate Hostname List	Network Element	Server Role	Active VIPs	OCUDR-A	Active	N/A	Active	OCUDR-B	Site1_NE_NO	Network OAM&P	10.10.1.121	OCUDR-B	Standby	N/A	Standby	OCUDR-A	Site1_NE_NO	Network OAM&P		DR-OCUDR-A	Spare	N/A	Active	DR-OCUDR-B	Site2_NE_DR_NO	Network OAM&P	10.10.1.28	DR-OCUDR-B	Spare	N/A	Standby	DR-OCUDR-A	Site2_NE_DR_NO	Network OAM&P	
Hostname	OAM HA Role	Application HA Role	Max Allowed HA Role	Mate Hostname List	Network Element	Server Role	Active VIPs																																			
OCUDR-A	Active	N/A	Active	OCUDR-B	Site1_NE_NO	Network OAM&P	10.10.1.121																																			
OCUDR-B	Standby	N/A	Standby	OCUDR-A	Site1_NE_NO	Network OAM&P																																				
DR-OCUDR-A	Spare	N/A	Active	DR-OCUDR-B	Site2_NE_DR_NO	Network OAM&P	10.10.1.28																																			
DR-OCUDR-B	Spare	N/A	Standby	DR-OCUDR-A	Site2_NE_DR_NO	Network OAM&P																																				
26. <input type="checkbox"/>	Active UDR VIP: Restarting the OAM Server Application Navigate to Main Menu → Status & Manage → Server	<div><div>Main Menu: Status & Manage -> Server</div><div><div>Filter*</div><table><thead><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></tbody></table></div></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man	DR-OCUDR-B	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm					
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																																				
DR-OCUDR-A	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man																																				
DR-OCUDR-B	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man																																				
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																																				
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																																				
27. <input type="checkbox"/>	Active UDR VIP: 1. The A and B servers are listed in the right panel. (Only A for single server installs) 2. Verify that the DB status shows Norm and the Proc status shows Man for both servers before proceeding to the next Step. (Only A server for single server configuration)	<p>Normal or Low Capacity Configuration:</p> <div><div><table><thead><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr></tbody></table></div><p>Single Server Configuration:</p></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man	DR-OCUDR-B	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man																			
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																																				
DR-OCUDR-A	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man																																				
DR-OCUDR-B	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man																																				

Step	Procedure	Result																																			
28. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>3. UsinXSg the mouse, select Server A. The line entry is highlighted in sky blue.</p> <p>4. Click Restart (located at the bottom of the page).</p> <p>5. Click OK.</p> <p>A confirmation message (in the banner area) for Server A stating: Successfully restarted application.</p> <p>NOTE: Use the vertical scroll-bar to see the Restart button.</p>	<p>Normal or Low Capacity Configuration:</p> <table><thead><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Disabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Man</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></tbody></table> <div><div> Help Legal Notices Logout</div><div><div>Stop</div><div>Restart</div><div>Reboot</div><div>NTP Sync</div><div>Report</div></div></div> <div><div>Are you sure you wish to restart application software on the following server(s)? DR-OCUDR-A</div><div><div>OK</div><div>Cancel</div></div></div> <div><div>Filter* Info</div><div><div>Server Host</div><div>DR-OCUDR</div></div><div><div>Info</div><div>• DR-OCUDR-A: Successfully restarted application.</div></div></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man	DR-OCUDR-B	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man																															
DR-OCUDR-B	Site2_NE_DR_NO	Disabled	Err	Norm	Norm	Man																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															
29. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Navigate to Main Menu → Status & Manage → Server</p>	<div><div>Main Menu: Status & Manage → Server</div><div>Fri Apr 06 04:58:03 2018 EDT</div><div><div>Filter* Info</div><table><thead><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></tbody></table></div></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															
30. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Verify that the Appl State shows Enabled and that the Alm, DB, Reporting Status and Proc columns all show Norm for OAM Server A before proceeding to the next Step.</p>	<div><div>Main Menu: Status & Manage → Server</div><div>Fri Apr 06 04:58:03 2018 EDT</div><div><div>Filter* Info</div><table><thead><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></tbody></table></div></div> <p>NOTE: To refresh the server status screen before the default setting (15 to 30 seconds). Select the Status & Manage → Server option from the Main menu on the left.</p>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															
31. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Navigate to Main Menu → Status & Manage → Server</p>	<div><div>Main Menu: Status & Manage → Server</div><div>Fri Apr 06 04:58:03 2018 EDT</div><div><div>Filter* Info</div><table><thead><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></tbody></table></div></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															

Step	Procedure	Result																																			
Perform steps 32 to 35 for multiple server configurations only (not single server).																																					
32. <input type="checkbox"/>	<p>Active UDR VIP:</p> <ol style="list-style-type: none">Using the mouse, select Server B. The line entry is highlighted in sky blue.Click Restart (located at the bottom of the page).Click OK. <p>A confirmation message displays in the banner area for server B stating: Successfully restarted application.</p> <p>NOTE: Use the vertical scroll-bar to see the Restart button.</p>	<div><table><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></table><div><div> Help Legal Notices Logout</div><div><div>Stop</div><div>Restart</div><div>Reboot</div><div>NTP Sync</div><div>Report</div></div></div><div><p>Are you sure you wish to restart application software on the following server(s)? DR-OCUDR-B</p><div><div>OK</div><div>Cancel</div></div></div><div><div>Info</div><div> • DR-OCUDR-B: Successfully restarted application.</div></div></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															
33. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Navigate to Main Menu → Status & Manage → Server</p>	<div><p>Main Menu: Status & Manage -> Server</p><div>Filter* ▾</div><table><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></table></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															
34. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Verify that the Appl State shows Enabled and that the Alm, DB, Reporting Status and Proc columns all show Norm for Server B before proceeding to the next Step.</p>	<div><p>Main Menu: Status & Manage -> Server</p><div>Filter* ▾</div><table><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></table><p>NOTE: If you want to refresh the server status screen before the default setting (15 to 30 seconds). Select the Status & Manage → Server option from the Main menu on the left.</p></div>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															
Repeat all steps for each DR UDR site being installed.																																					

Step	Procedure	Result															
35. <input type="checkbox"/>	<p>Active UDR VIP: <i>For primary UDR standby server only:</i></p> <p>Move the server back to Active</p> <p>Navigate to Main Menu → Status & Manage → HA[Edit]</p> <p>Find the row for the primary UDR standby server and change Max Allowed HA Role back to Active.</p>	<p>Modifying HA attributes</p> <table> <tr> <th>Hostname</th><th>Max Allowed HA Role</th><th>Description</th></tr> <tr> <td>OCUDR-A</td><td>Active ▼</td><td>The maximum desired HA Role for OCUDR-A</td></tr> <tr> <td>OCUDR-B</td><td>Active ▼</td><td>The maximum desired HA Role for OCUDR-B</td></tr> <tr> <td>DR-OCUDR-A</td><td>Active ▼</td><td>The maximum desired HA Role for DR-OCUDR-A</td></tr> <tr> <td>DR-OCUDR-B</td><td>Active ▼</td><td>The maximum desired HA Role for DR-OCUDR-B</td></tr> </table> <p>Ok Cancel</p>	Hostname	Max Allowed HA Role	Description	OCUDR-A	Active ▼	The maximum desired HA Role for OCUDR-A	OCUDR-B	Active ▼	The maximum desired HA Role for OCUDR-B	DR-OCUDR-A	Active ▼	The maximum desired HA Role for DR-OCUDR-A	DR-OCUDR-B	Active ▼	The maximum desired HA Role for DR-OCUDR-B
Hostname	Max Allowed HA Role	Description															
OCUDR-A	Active ▼	The maximum desired HA Role for OCUDR-A															
OCUDR-B	Active ▼	The maximum desired HA Role for OCUDR-B															
DR-OCUDR-A	Active ▼	The maximum desired HA Role for DR-OCUDR-A															
DR-OCUDR-B	Active ▼	The maximum desired HA Role for DR-OCUDR-B															
36. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Click Logout on the server GUI.</p>	<p>Help Logged in Account guiadmin ▼ Log Out</p> <p>Thu Mar 29 06:02:07 2018 EDT</p>															
THIS PROCEDURE HAS BEEN COMPLETED																	



Chapter 7. Application Configuration

7.1 Configure UDR Signaling Routes (All NOAM Sites)




This procedure configures the XSI signaling route for the UDR and DR UDR Server Groups.


Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 11: Configure UDR Signaling Routes

Step	Procedure	Result
1. <input type="checkbox"/>	<p>Active UDR VIP: Launch an approved web browser and connect to the UDR Server A IP address</p> <p>NOTE: Click Continue to this website (not recommended) if the security certificate warning displays.</p> <p>Login to the GUI using the default user and password.</p>	
2. <input type="checkbox"/>	<p>Active UDR VIP</p> <p>Navigate to Main Menu → Configuration → Networking → Devices</p>	 <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A (XSI-1) <input type="checkbox"/> UDR-B (XSI-1)</p>

Step	Procedure	Result																														
3. <input type="checkbox"/>	Active UDR VIP: Select the xsi device for the UDR	Select the UDR tab. Select the XSI-1 device (recorded in B.3 Step 3 or C.7 Step 5). <table border="1"><thead><tr><th colspan="6">OCUDR-A OCUDR-B DR-OCUDR-A DR-OCUDR-B</th></tr><tr><th>Device Name</th><th>Device Type</th><th>Device Options</th><th>IP Interface (Network)</th><th>Configuration Status</th><th>Is Locked?</th></tr></thead><tbody><tr><td>eth2</td><td>Ethernet</td><td>MTU = 1500 bootProto = none onboot = yes</td><td>fe80::f816:3eff:feb4:bd0a (/64)</td><td>Discovered</td><td>Locked</td></tr><tr><td>eth0</td><td>Ethernet</td><td>MTU = 1500 bootProto = none onboot = yes</td><td>10.10.1.57 (xmi) 10.10.1.121 (/24) fe80::f816:3eff:febb:3dac (/64)</td><td>Deployed</td><td>Locked</td></tr><tr><td>eth1</td><td>Ethernet</td><td>MTU = 1500 bootProto = none onboot = yes</td><td>10.10.2.156 (imi) fe80::f816:3eff:fe56:c1f9 (/64)</td><td>Deployed</td><td>Locked</td></tr></tbody></table> Mark the check box as addition is completed for each server. <input type="checkbox"/> UDR-A (XSI-1) <input type="checkbox"/> UDR-B (XSI-1)	OCUDR-A OCUDR-B DR-OCUDR-A DR-OCUDR-B						Device Name	Device Type	Device Options	IP Interface (Network)	Configuration Status	Is Locked?	eth2	Ethernet	MTU = 1500 bootProto = none onboot = yes	fe80::f816:3eff:feb4:bd0a (/64)	Discovered	Locked	eth0	Ethernet	MTU = 1500 bootProto = none onboot = yes	10.10.1.57 (xmi) 10.10.1.121 (/24) fe80::f816:3eff:febb:3dac (/64)	Deployed	Locked	eth1	Ethernet	MTU = 1500 bootProto = none onboot = yes	10.10.2.156 (imi) fe80::f816:3eff:fe56:c1f9 (/64)	Deployed	Locked
OCUDR-A OCUDR-B DR-OCUDR-A DR-OCUDR-B																																
Device Name	Device Type	Device Options	IP Interface (Network)	Configuration Status	Is Locked?																											
eth2	Ethernet	MTU = 1500 bootProto = none onboot = yes	fe80::f816:3eff:feb4:bd0a (/64)	Discovered	Locked																											
eth0	Ethernet	MTU = 1500 bootProto = none onboot = yes	10.10.1.57 (xmi) 10.10.1.121 (/24) fe80::f816:3eff:febb:3dac (/64)	Deployed	Locked																											
eth1	Ethernet	MTU = 1500 bootProto = none onboot = yes	10.10.2.156 (imi) fe80::f816:3eff:fe56:c1f9 (/64)	Deployed	Locked																											
4. <input type="checkbox"/>	Active UDR VIP Edit the xsi device for the UDR	Click Take Ownership . <div>Take Ownership</div> Mark the check box as addition is completed for each server. <input type="checkbox"/> UDR-A (XSI-1) <input type="checkbox"/> UDR-B (XSI-1)																														
5. <input type="checkbox"/>	Active UDR VIP 1. Add the xsi device for the UDR 2. For Start On Boot, select Enable 3. Click OK to apply changes.																															
6. <input type="checkbox"/>	Active UDR VIP: Repeat as required.	Repeat Steps 3 throughg 5 for each UDR and its Signaling networks. NOTE: Steps 7 throughg 9 are only needed for geo-redundant systems.																														
7. <input type="checkbox"/>	Active UDR VIP: Navigate to Main Menu → Configuration → Networking → Routes	<div><div>Main Menu<ul style="list-style-type: none">AdministrationConfiguration<ul style="list-style-type: none">Networking<ul style="list-style-type: none">NetworksDevicesRoutes</div><div>Main Menu: Configuration -> Networking -> Routes Entire Network DR_NO_SG NO_SG OCUDR-A OCUDR-B DR-OCUDR-A DR-OCUDR-B</div></div>																														

Step	Procedure	Result
8. <input type="checkbox"/>	Active UDR VIP: Insert a route for the UDR or DR UDR Server group.	<ol style="list-style-type: none"> 1. Select the Server Group tab on the top line. 2. Click Entire Server Group on the line below Server Group line.  <ol style="list-style-type: none"> 3. Click Insert 
9. <input type="checkbox"/>	Active UDR VIP: Add signaling route	 <ol style="list-style-type: none"> 1. Set Route Type to Net 2. Set Device to XSI-1 device (recorded in B.3 Step 3 or C.7 Step 5). 3. Enter Destination: This is the network address of the remote MP server group that connects to Oracle Communications User Data Repository UDR for ComAgent service. 4. Enter Netmask for the remote network. 5. Enter Gateway IP: This is the signaling network gateway for Oracle Communications User Data Repository. 6. Click Apply.

Step	Procedure	Result
10. <input type="checkbox"/>	NOTES: Destination would be DR Site XSI1 Address if configuring Primary Site and vice-versa. Netmask would be DR Site XSI1 Address if configuring Primary Site and vice-versa. Gateway IP would be Primary Site XSI1 Gateway if configuring Primary Site and vice-versa.	
11. <input type="checkbox"/>	Active UDR VIP: Click Logout on the server GUI.	
THIS PROCEDURE HAS BEEN COMPLETED		

7.2 Configure Services on Signaling Network

This procedure configures ComAgent communication between NOAMP and MP to use Signaling Network. This procedure also configures dual path HA heartbeat to use the XSI network.


Requirements:

- Section 7.1 Configure UDR Signaling Routes (All NOAM Sites) has been completed

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 12: Configure Services on Signaling Network

Step	Procedure	Result
1. <input type="checkbox"/>	Active UDR VIP: Launch an approved web browser and connect to the UDR Server A IP address NOTE: Click Continue to this website (not recommended) if the security certificate warning displays. Login to the GUI using the default user and password.	

Step	Procedure	Result																								
2. <input type="checkbox"/>	Active UDR VIP: Navigate to Main Menu → Configuration → Services	 <p>Main Menu: Configuration -> Networking -> Services</p> <table> <thead> <tr> <th>Name</th><th>Intra-NE Network</th><th>Inter-NE Network</th></tr> </thead> <tbody> <tr> <td>OAM</td><td>imi</td><td>xmi</td></tr> <tr> <td>Replication</td><td>imi</td><td>xmi</td></tr> <tr> <td>Signaling</td><td>Unspecified</td><td>Unspecified</td></tr> <tr> <td>HA_Secondary</td><td>imi</td><td>xmi</td></tr> <tr> <td>HA_MP_Secondary</td><td>imi</td><td>xmi</td></tr> <tr> <td>Replication_MP</td><td>imi</td><td>xmi</td></tr> <tr> <td>ComAgent</td><td>imi</td><td>xmi</td></tr> </tbody> </table>	Name	Intra-NE Network	Inter-NE Network	OAM	imi	xmi	Replication	imi	xmi	Signaling	Unspecified	Unspecified	HA_Secondary	imi	xmi	HA_MP_Secondary	imi	xmi	Replication_MP	imi	xmi	ComAgent	imi	xmi
Name	Intra-NE Network	Inter-NE Network																								
OAM	imi	xmi																								
Replication	imi	xmi																								
Signaling	Unspecified	Unspecified																								
HA_Secondary	imi	xmi																								
HA_MP_Secondary	imi	xmi																								
Replication_MP	imi	xmi																								
ComAgent	imi	xmi																								

Step	Procedure	Result																								
3. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>1. Set two services values:</p> <p style="padding-left: 40px;">Inter-NE HA_Secondary → XSI1</p> <p style="padding-left: 40px;">Inter-NE ComAgent → XSI1</p> <p>2. Click Apply.</p> <p>3. Click OK.</p>	<table border="1"> <thead> <tr> <th>Name</th><th>Intra-NE Network</th><th>Inter-NE Network</th></tr> </thead> <tbody> <tr> <td>OAM</td><td>imi</td><td>xmi</td></tr> <tr> <td>Replication</td><td>imi</td><td>xmi</td></tr> <tr> <td>Signaling</td><td>Unspecified</td><td>Unspecified</td></tr> <tr> <td>HA_Secondary</td><td>imi</td><td>XSI1</td></tr> <tr> <td>HA_MP_Secondary</td><td>imi</td><td>xmi</td></tr> <tr> <td>Replication_MP</td><td>imi</td><td>xmi</td></tr> <tr> <td>ComAgent</td><td>imi</td><td>xmi</td></tr> </tbody> </table> <div style="border: 1px solid gray; padding: 10px; margin-top: 10px; text-align: center;"> <p>You must restart all Servers to apply any services changes, ComAgent</p> <p>OK Cancel</p> </div> <p>UDR Servers must be restarted.</p>	Name	Intra-NE Network	Inter-NE Network	OAM	imi	xmi	Replication	imi	xmi	Signaling	Unspecified	Unspecified	HA_Secondary	imi	XSI1	HA_MP_Secondary	imi	xmi	Replication_MP	imi	xmi	ComAgent	imi	xmi
Name	Intra-NE Network	Inter-NE Network																								
OAM	imi	xmi																								
Replication	imi	xmi																								
Signaling	Unspecified	Unspecified																								
HA_Secondary	imi	XSI1																								
HA_MP_Secondary	imi	xmi																								
Replication_MP	imi	xmi																								
ComAgent	imi	xmi																								

Step	Procedure	Result																																			
4. <input type="checkbox"/>	Active UDR VIP: The Services configuration screen opens.	<table><thead><tr><th>Name</th><th>Intra-NE Network</th><th>Inter-NE Network</th></tr></thead><tbody><tr><td>OAM</td><td>imi</td><td>xmi</td></tr><tr><td>Replication</td><td>imi</td><td>xmi</td></tr><tr><td>Signaling</td><td>Unspecified</td><td>Unspecified</td></tr><tr><td>HA_Secondary</td><td>imi</td><td>XSI1</td></tr><tr><td>HA_MP_Secondary</td><td>imi</td><td>xmi</td></tr><tr><td>Replication_MP</td><td>imi</td><td>xmi</td></tr><tr><td>ComAgent</td><td>imi</td><td>xmi</td></tr></tbody></table>	Name	Intra-NE Network	Inter-NE Network	OAM	imi	xmi	Replication	imi	xmi	Signaling	Unspecified	Unspecified	HA_Secondary	imi	XSI1	HA_MP_Secondary	imi	xmi	Replication_MP	imi	xmi	ComAgent	imi	xmi											
Name	Intra-NE Network	Inter-NE Network																																			
OAM	imi	xmi																																			
Replication	imi	xmi																																			
Signaling	Unspecified	Unspecified																																			
HA_Secondary	imi	XSI1																																			
HA_MP_Secondary	imi	xmi																																			
Replication_MP	imi	xmi																																			
ComAgent	imi	xmi																																			
5. <input type="checkbox"/>	Reboot all UDR Servers	<p>Reboot all UDR servers either by</p> <ul style="list-style-type: none">On the GUI for the active UDR, go to Status & Manage → Server screen and click Reboot. <div><p>Main Menu: Status & Manage -> Server</p><div><div>Filter* ▼</div><table><thead><tr><th>Server Hostname</th><th>Network Element</th><th>Appl State</th><th>Alm</th><th>DB</th><th>Reporting Status</th><th>Proc</th></tr></thead><tbody><tr><td>DR-OCUDR-A</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>DR-OCUDR-B</td><td>Site2_NE_DR_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-A</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Norm</td><td>Norm</td></tr><tr><td>OCUDR-B</td><td>Site1_NE_NO</td><td>Enabled</td><td>Err</td><td>Norm</td><td>Man</td><td>Norm</td></tr></tbody></table><div><div>Stop</div><div>Restart</div><div>Reboot</div><div>NTP Sync</div><div>Report</div></div></div></div> <ul style="list-style-type: none">On the terminal of each server with the reboot command:<div>\$ sudo reboot</div> <p>NOTE: Perform this on all UDRs.</p>	Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc	DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm	OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm
Server Hostname	Network Element	Appl State	Alm	DB	Reporting Status	Proc																															
DR-OCUDR-A	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
DR-OCUDR-B	Site2_NE_DR_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-A	Site1_NE_NO	Enabled	Err	Norm	Norm	Norm																															
OCUDR-B	Site1_NE_NO	Enabled	Err	Norm	Man	Norm																															
THIS PROCEDURE HAS BEEN COMPLETED																																					

7.3 Accept Installation



This procedure accepts the installation/upgrade on any servers that have not been accepted. Depending on the manner of installation, there may not be any servers that require acceptance at this point in installation.

The upgrade needs either to be accepted or rejected before any subsequent upgrades are performed.

Alarm 32532 (Server Upgrade Pending Accept/Reject) displays for each server until one of these two actions (accept or reject) is performed.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure 13: Accept Installation

Step	Procedure	Result
1. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Launch an approved web browser and connect to the UDR Server A IP address</p> <p>NOTE: Click Continue to this website (not recommended) if the security certificate warning displays.</p> <p>Login to the GUI using the default user and password.</p>	 <p>The screenshot shows the Oracle System Login page. At the top is the Oracle logo. Below it is the title 'Oracle System Login' and a timestamp 'Wed Sep 23 15:26:39 2015 EDT'. In the center is a 'Log In' box with the text 'Enter your username and password to log in'. Below this, it says 'Session was logged out at 3:26:39 pm.' There are input fields for 'Username' (containing 'guiadmin') and 'Password' (masked with dots). A 'Change password' checkbox is present. A 'Log In' button is at the bottom of the box. At the very bottom of the page, it says 'Welcome to the Oracle System Login.'</p>
2. <input type="checkbox"/>	<p>Active UDR VIP:</p> <p>Navigate to Main Menu → Administration → Software Management → Upgrade</p>	 <p>The screenshot shows the 'Main Menu: Administration -> Software Management -> Upgrade' page. On the left is a tree view of the Main Menu with categories like Administration, Access Control, Software Management, Remote Servers, Configuration, Alarms & Events, Security Log, Status & Manage, Network Elements, and Server. The 'Upgrade' option under 'Software Management' is selected. The main area shows a table with columns: Hostname, Upgrade State, OAM HA Role, Server Role, and Function. The table has two rows: OCUDR-A and OCUDR-B. OCUDR-A has 'Backup Needed' (orange), 'Active' (green), 'Network OAM&P', and 'OAM&P'. OCUDR-B has 'Backup Needed' (orange), 'Standby' (yellow), 'Network OAM&P', and 'OAM&P'. There are also 'Err' (red) labels in the 'Server Status' column for both hosts.</p>

Step	Procedure	Result																						
3. <input type="checkbox"/>	Active UDR VIP (GUI): Accept upgrade for selected servers.	<p>Accept upgrade of selected servers:</p> <ol style="list-style-type: none">1. Select the server where the upgrade has not been accepted.2. Click Accept. <div><p>Main Menu: Administration -> Software Management -> Upgrade</p><div><div>Filter* ▾</div><div>Tasks ▾</div></div><div><div>DR_NO_SG</div><div>NO_SG</div></div><table><thead><tr><th>Hostname</th><th>Upgrade State</th><th>OAM HA Role</th><th>Server Role</th></tr><tr><th></th><th>Server Status</th><th>Appl HA Role</th><th>Network Element</th></tr></thead><tbody><tr><td rowspan="2">OCUDR-A</td><td>Backup Needed</td><td>Active</td><td>Network OAM&P</td></tr><tr><td>Err</td><td>N/A</td><td>Site1_NE_NO</td></tr><tr><td rowspan="2">OCUDR-B</td><td>Backup Needed</td><td>Standby</td><td>Network OAM&P</td></tr><tr><td>Err</td><td>N/A</td><td>Site1_NE_NO</td></tr></tbody></table><div><div>Backup</div><div>Upgrade Server</div><div>Accept</div><div>Report</div><div>Report All</div></div></div> <p>A confirmation dialog warns that after the upgrade is accepted, the servers are not able to revert back to their previous image states.</p> <div><div>The page at https://10.240.42.20 says: ×</div><div>WARNING: Selecting OK will result in the selected server being set to ACCEPT for its upgrade mode. Once accepted, the server will NOT be able to revert back to its previous image state.</div><div>Accept the upgrade for the following server?</div><div>BL908070109-NO-A (10.240.56.108)</div><div><div>OK</div><div>Cancel</div></div></div> <p>3. Click OK</p> <p>The Upgrade Administration screen re-displays.</p> <p>An Informational message indicates the servers where the upgrade was accepted.</p>	Hostname	Upgrade State	OAM HA Role	Server Role		Server Status	Appl HA Role	Network Element	OCUDR-A	Backup Needed	Active	Network OAM&P	Err	N/A	Site1_NE_NO	OCUDR-B	Backup Needed	Standby	Network OAM&P	Err	N/A	Site1_NE_NO
Hostname	Upgrade State	OAM HA Role	Server Role																					
	Server Status	Appl HA Role	Network Element																					
OCUDR-A	Backup Needed	Active	Network OAM&P																					
	Err	N/A	Site1_NE_NO																					
OCUDR-B	Backup Needed	Standby	Network OAM&P																					
	Err	N/A	Site1_NE_NO																					
4. <input type="checkbox"/>	Active UDR VIP: Accept upgrade of the rest of the system	<ol style="list-style-type: none">1. Accept upgrade on all remaining servers in the system:2. Repeat all sub-steps of step 3 of this procedure on remaining servers until the upgrade of all servers in the User Data Repository system has been accepted. <p>Note: As the upgrade is accepted on each server the corresponding Alarm ID 32532 (Server Upgrade Pending Accept/Reject) is removed.</p>																						

Step	Procedure	Result																
5. <input type="checkbox"/>	Active UDR VIP: Verify accept	<p>Check that alarms are removed:</p> <p>1. Navigate to Alarms & Events > View Active</p> <div><div>Main Menu: Alarms & Events -> View Active</div><div><div>Filter ▾</div><div>Tasks ▾</div></div><table><thead><tr><th>Seq #</th><th>Event ID</th><th>Timestamp</th><th>Severity</th><th>Product</th><th>Process</th><th>NE</th><th>Server</th></tr></thead><tbody><tr><td></td><td colspan="2">Alarm Text</td><td colspan="5">Additional Info</td></tr></tbody></table></div> <p>2. Verify that Alarm ID 32532 (Server Upgrade Pending Accept/Reject) is not displayed under active alarms on User Data Repository system</p>	Seq #	Event ID	Timestamp	Severity	Product	Process	NE	Server		Alarm Text		Additional Info				
Seq #	Event ID	Timestamp	Severity	Product	Process	NE	Server											
	Alarm Text		Additional Info															
THIS PROCEDURE HAS BEEN COMPLETED																		

Configuration of UDR for EIR, FABR, MNP and SFAPP features

After finishing installation and configuration of UDR, we need to configure the UDR for below features by executing the loader at Active NOAMP server.

These loaders are present under “/usr/TKLC/udr/prod/maint/loaders/upgrade” path .

Feature	Loader name	Description
MNP	enablevMNPsec	This loader will enable MNP feature
Split feature	enableSplitFeature	This loader will enable Split feature
MNP with Split	enableMNPwithSplit	This loader will configure SEC for MNP with Split. To enable MNP feature with feature ,execute this loader along with “enableSplitFeature” loader
Enum	enableMNPwithENUM	Configure and enable Enum as per old Schema
Enum	enableENUMSec	Configure and enable Enum as per New Schema
FABR	enableFabrSec	Configure and enable FABR use case
EIR	enableEIRSec	Configure and enable EIR use case
MNP with Split , ENUM and SFAPP/DSA	enableMNPwithSplit_Enum_SFAPP	This is common loader which will enable all the features MNP/SPLIT/ENUM/SFAPP/DSA
SFAPP/DSA	enableSecurityApp	This loader will enable SFAPP/DSA feature
Shared Memory Handling	enableCriticalShMemThManagement	This feature will enable Shared memory management which is used for SFAPP/DSA feature . This will act as safe guard when memory is going beyond Critical threshold memory
Set Shared memory threshold values	enableShMemThresholdsValues	This loader will set the threshold values for Minor and Major threshold
Disable Shared Memory Handling	disableCriticalShMemThManagement	This will disable the Shared memory management which is used for SFAPP/DSA feature
Split feature	disableSplitFeature	This loader will disable Split feature

Appendix A. VMWare vSphere Environment setup





A.1 HOST DATASTORE CONFIGURATION USING VSPHERE



This procedure is performed to configure a datastore on the Host so that the appropriate storage is available for Oracle Communications User Data Repository component VMs. Steps and screenshots are taken from vSphere Client.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

If this procedure fails, contact My Oracle Support, and ask for assistance.

Procedure14: Host Datastore Configuration with vSphere

Step	Procedure	Details
1. <input type="checkbox"/>	Log into the VMware client	
2. <input type="checkbox"/>	VMware client: 1. Select the Host on the left tree menu 2. Click the Configuration tab on right 3. Click Storage under Hardware menu	
3. <input type="checkbox"/>	VMware client: Click Add Storage	
4. <input type="checkbox"/>	VMware client: 1. Select Network File System storage type 2. Click Next	

Step	Procedure	Details
5. <input type="checkbox"/>	VMware client: 1. Enter a Server IP, Folder, and Datastore Name in the fields according to the resource availability in your VMware host environment 2. Click Next	
6. <input type="checkbox"/>	VMware client: 1. Review the Datastore summary 2. Click Finish	
THIS PROCEDURE HAS BEEN COMPLETED		

A.2 HOST NETWORKING CONFIGURATION USING VSPHERE

The following procedure is performed to configure the recommended Networking on the Host so that the appropriate vNICs are available for Oracle Communications User Data Repository component VMs. Steps and screenshots are taken from vSphere Client.

To view the available Networks on the Host, select the **Summary** tab. In the example below several OAM and Signaling Networks have been configured. Each of these is associated with vSwitch on the Host and physical ethernet.




Oracle Communications User Data Repository VMs can be associated with up to 5 vLAN Networks. All 5 vNICs must be created and configured in order to be available for the Guest. The expected vNICs correspond to the following dedicated interfaces of the Oracle Communications User Data Repository and so the recommendation is the label them similarly:



- XMI
OAM Management Interface for the application
- XSI1
Signaling Interface
- XSI2
Signaling Interface
- IMI
Replication Interface
- Guest Management
Reserved for Guest management activities.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.


If this procedure fails, contact My Oracle Support, and ask for assistance.

Procedure15: Host Networking Configuration with vSphere

Step	Procedure	Details
7. <input type="checkbox"/>	Log into the VMware client	
8. <input type="checkbox"/>	VMware client: 1. Select the Host on the left tree menu 2. Click Configuration tab on right 3. Click Networking under Hardware menu	
9. <input type="checkbox"/>	VMware client: 1. Select Add Networking from top 2. Select connection type Virtual Machine and click Next	

Step	Procedure	Details																		
10. <input type="checkbox"/>	VMware client: Select appropriate vSwitch type based on the Host hardware and click Next	 <p>Add Network Wizard Virtual Machines - Network Access Virtual machines reach networks through uplink adapters attached to vSphere standard switches.</p> <p>Connection Type: Network Access Connection Settings: Connection Settings Summary: Summary</p> <p>Select which vSphere standard switch will handle the network traffic for this connection. You may also create a new vSphere standard switch using the undrained network adapters listed below.</p> <table border="1"> <thead> <tr> <th>vmnic</th> <th>Speed</th> <th>Networks</th> </tr> </thead> <tbody> <tr> <td><input type="checkbox"/> vmnic1</td> <td>10000 Full</td> <td>None</td> </tr> <tr> <td><input checked="" type="radio"/> Use vSwitch2</td> <td>Intel Corporation Ethernet Controller 10 Gigabit X540-AT2</td> <td></td> </tr> <tr> <td><input checked="" type="checkbox"/> vmnic2</td> <td>10000 Full</td> <td>None</td> </tr> <tr> <td><input type="radio"/> Use vSwitch3</td> <td>Intel Corporation Ethernet Controller 10 Gigabit X540-AT2</td> <td></td> </tr> <tr> <td><input type="checkbox"/> vmnic3</td> <td>10000 Full</td> <td>None</td> </tr> </tbody> </table> <p>Preview:</p> <ul style="list-style-type: none"> - Virtual Machine Port Group: VM Network 2 - Virtual Machine Port Group: SigB-1 - Virtual Machine Port Group: SigA-1 - Physical Adapters: vnic2 <p>Buttons: Help, < Back, Next >, Cancel</p>	vmnic	Speed	Networks	<input type="checkbox"/> vmnic1	10000 Full	None	<input checked="" type="radio"/> Use vSwitch2	Intel Corporation Ethernet Controller 10 Gigabit X540-AT2		<input checked="" type="checkbox"/> vmnic2	10000 Full	None	<input type="radio"/> Use vSwitch3	Intel Corporation Ethernet Controller 10 Gigabit X540-AT2		<input type="checkbox"/> vmnic3	10000 Full	None
vmnic	Speed	Networks																		
<input type="checkbox"/> vmnic1	10000 Full	None																		
<input checked="" type="radio"/> Use vSwitch2	Intel Corporation Ethernet Controller 10 Gigabit X540-AT2																			
<input checked="" type="checkbox"/> vmnic2	10000 Full	None																		
<input type="radio"/> Use vSwitch3	Intel Corporation Ethernet Controller 10 Gigabit X540-AT2																			
<input type="checkbox"/> vmnic3	10000 Full	None																		
11. <input type="checkbox"/>	VMware client: Label the Network, enter its VLAN ID, click Next	 <p>Add Network Wizard Virtual Machines - Connection Settings Use network labels to identify migration compatible connections common to two or more hosts.</p> <p>Connection Type: Network Access Connection Settings: Connection Settings Summary: Summary</p> <p>Port Group Properties</p> <p>Network Label: XMI VLAN ID (Optional): 332</p> <p>Preview:</p> <ul style="list-style-type: none"> - Virtual Machine Port Group: XMI - Virtual Machine Port Group: VM Network - VMkernel Port: Management Network - Physical Adapters: vnic0 <p>Buttons: Help, < Back, Next >, Cancel</p>																		

NOTE: It is recommended that the name reflect how the Network is used or referenced from in the Guest, ie XMI, IMI, XSI1, and so on.

Step	Procedure	Details
12. <input type="checkbox"/>	VMware client: Review values and click Finish	
13. <input type="checkbox"/>	Repeat this procedure for each network	Repeat this procedure for each network type that is supported by this VMWare host: <input type="checkbox"/> XMI <input type="checkbox"/> IMI <input type="checkbox"/> XSI-1 <input type="checkbox"/> XSI-2 (optional)
THIS PROCEDURE HAS BEEN COMPLETED		

Appendix B. VMware vSphere Oracle Communications User Data Repository Deployment

B.1 CREATE GUESTS FROM OVA




This procedure creates Oracle Communications User Data Repository virtual machines (guests) from OVA.




Needed material:




- Oracle Communications User Data Repository OVA



Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure16: Deploy Oracle Communications User Data Repository OVA

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware client	
2. <input type="checkbox"/>	VMware client: Navigate to File → Deploy OVF Template	
3. <input type="checkbox"/>	VMware client: 1. Click Browse and select the OVA file 2. Click Next .	

Step	Procedure	Result
4. <input type="checkbox"/>	VMware client: Details screen displays, click Next	
5. <input type="checkbox"/>	VMware client: Accept End User License Agreement by clicking Accept then Next	
6. <input type="checkbox"/>	VMware client: Name the virtual machine and click Next	

Step	Procedure	Result																								
7. <input type="checkbox"/>	VMware client: Select destination storage for the virtual machine from the list of available data stores then click Next .	 <p>Storage Where do you want to store the virtual machine files?</p> <p>Select a destination storage for the virtual machine files:</p> <table><thead><tr><th>Name</th><th>Drive Type</th><th>Capacity</th><th>Provisioned</th><th>Free</th><th>Type</th><th>Thin Provisioning</th><th>Access</th></tr></thead><tbody><tr><td>datastore1</td><td>Non-SSD</td><td>550.25 GB</td><td>59.69 GB</td><td>490.56 GB</td><td>VMFSS</td><td>Supported</td><td>Single host</td></tr><tr><td>ESXi_5.5_255....</td><td>Non-SSD</td><td>1.17 TB</td><td>323.82 GB</td><td>875.93 GB</td><td>VMFSS</td><td>Supported</td><td>Single host</td></tr></tbody></table> <p>Help < Back Next > Cancel</p> <p>NOTE: For an upgradeable deployment, ensure the data store has enough free capacity to support the type of VM according to the profile selected from Oracle Communications User Data Repository Installation and Configuration Guide, E72453, latest revision.</p>	Name	Drive Type	Capacity	Provisioned	Free	Type	Thin Provisioning	Access	datastore1	Non-SSD	550.25 GB	59.69 GB	490.56 GB	VMFSS	Supported	Single host	ESXi_5.5_255....	Non-SSD	1.17 TB	323.82 GB	875.93 GB	VMFSS	Supported	Single host
Name	Drive Type	Capacity	Provisioned	Free	Type	Thin Provisioning	Access																			
datastore1	Non-SSD	550.25 GB	59.69 GB	490.56 GB	VMFSS	Supported	Single host																			
ESXi_5.5_255....	Non-SSD	1.17 TB	323.82 GB	875.93 GB	VMFSS	Supported	Single host																			
8. <input type="checkbox"/>	VMware client: Select Thick Provision Lazy Zeroed and click Next	 <p>Disk Format In which format do you want to store the virtual disks?</p> <p>Source OVF Template Details End User License Agreement Name and Location Storage Disk Format Network Mapping Ready to Complete</p> <p>Datastore: ESXi_5.5_255.168 Available space (GB): 875.9</p> <p><input checked="" type="radio"/> Thick Provision Lazy Zeroed <input type="radio"/> Thick Provision Eager Zeroed <input type="radio"/> Thin Provision</p> <p>Help < Back Next > Cancel</p>																								
9. <input type="checkbox"/>	VMware client: Click Next	 <p>Network Mapping What networks should the deployed template use?</p> <p>Source OVF Template Details End User License Agreement Name and Location Storage Disk Format Network Mapping Ready to Complete</p> <p>Map the networks used in this OVF template to networks in your inventory</p> <table><thead><tr><th>Source Networks</th><th>Destination Networks</th></tr></thead><tbody><tr><td>control</td><td>VM Network</td></tr></tbody></table> <p>Help < Back Next > Cancel</p>	Source Networks	Destination Networks	control	VM Network																				
Source Networks	Destination Networks																									
control	VM Network																									


Step	Procedure	Result
10. <input type="checkbox"/>	VMware client: Review deployment settings and click Finish	
11. <input type="checkbox"/>	VMware client: After a wait a deployment status message is displayed. Click Close .	
THIS PROCEDURE HAS BEEN COMPLETED		




B.2 CONFIGURE GUEST RESOURCES




This procedure configures the required resource allocations and associations for Oracle Communications User Data Repository virtual machines (guests) and power them on.



Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.



Procedure17: Configure Guest Resources



Step	Procedure	Result
1. <input type="checkbox"/>	VMware client: Log into the Vmware client	

Step	Procedure	Result
2. <input type="checkbox"/>	VMware client: <ol style="list-style-type: none"> 1. Select the Oracle Communications User Data Repository virtual machine from the left tree menu 2. Click Summary tab 3. Click Edit Settings under Commands 	
3. <input type="checkbox"/>	VMware client: <p>Select Memory from the Hardware menu and adjust Memory Size for the role of the server.</p> <p>UDR: 48 GB</p>	
4. <input type="checkbox"/>	VMware client: <p>Select CPUs from the Hardware menu and adjust the Number of virtual sockets according to [1].</p>	

Step	Procedure	Result				
5. <input type="checkbox"/>	VMware client: Select Hard disk 1 from the Hardware menu and adjust the Provisioned Size according to [1].					
6. <input type="checkbox"/>	VMware client: 1. Select any Network adapter that may exist by default 2. Click Remove tab					
7. <input type="checkbox"/>	VMware client: The network adapter is crossed out and a removal message displayed					
8. <input type="checkbox"/>	VMware client: Take note of the order in which networks are added.	<p>NOTE: The order in which networks are added by the following steps affects their device order in the virtual machine. Add them in the order they appear for each server:</p> <table><thead><tr><th>UDR</th></tr></thead><tbody><tr><td>1. <input type="checkbox"/> XMI</td></tr><tr><td>2. <input type="checkbox"/> IMI</td></tr><tr><td>3. <input type="checkbox"/> XSI-1 (optional)</td></tr></tbody></table>	UDR	1. <input type="checkbox"/> XMI	2. <input type="checkbox"/> IMI	3. <input type="checkbox"/> XSI-1 (optional)
UDR						
1. <input type="checkbox"/> XMI						
2. <input type="checkbox"/> IMI						
3. <input type="checkbox"/> XSI-1 (optional)						

Step	Procedure	Result
9. <input type="checkbox"/>	VMware client: Click Add on the Hardware tab.	
10. <input type="checkbox"/>	VMware client: Select Ethernet Adapter from the list of devices and click Next	

Step	Procedure	Result
11. <input type="checkbox"/>	VMware client: <ol style="list-style-type: none"> 1. Select Adapter Type to conform to your virtual host 2. Select the Network Label to match the network type 3. Click Next 	
12. <input type="checkbox"/>	VMware client: <p>Confirm Option settings and click Finish</p>	
13. <input type="checkbox"/>	VMware client: <p>Repeat as required</p>	Repeat Steps 9 through 12 to add every network required for the role of the server.



Step	Procedure	Result
14. <input type="checkbox"/>	VMware client: After all networks are added, confirm their entry in the Hardware menu then click OK .	
15. <input type="checkbox"/>	VMware client: New devices and networks are listed on the Summary tab and Reconfigure task shows status Completed under Recent Tasks. Click Power On under Commands.	
THIS PROCEDURE HAS BEEN COMPLETED		



B.3 CONFIGURE GUEST NETWORK

This procedure configures the OAM network on Oracle Communications User Data Repository virtual machines (guests).

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure18: Configure Guest OAM Network

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the Vmware client	
2. <input type="checkbox"/>	VMware client: 1. Select the Oracle Communications User Data Repository virtual machine from the left tree menu 2. Click the Summary tab 3. Click Edit Settings under Commands	

Step	Procedure	Result
3. <input type="checkbox"/>	VMware client: <ol style="list-style-type: none"> Take note of the Network adapter assignment under Hardware tab for each application network. Click Cancel 	 <p>Network adapters are enumerated under the Hardware tab. Their adapter number in the Hardware column corresponds to their zero-based device name assignment in a running guest.</p> <p>For instance, in the example capture above:</p> <ul style="list-style-type: none"> OAM (XMI) is on eth0 device OAM-1 (IMI) is on eth1 device Sig-A (XSI-1) is on eth2 device <p>Record the NIC device number assignment of these networks:</p> <p>XMI: _____</p> <p>IMI: _____</p> <p>XSI-1: _____</p> <p>XSI-2: _____ (optional)</p>
4. <input type="checkbox"/>	VMware client: <ol style="list-style-type: none"> Click the Console tab Click inside the console window to bring focus there <p>NOTE: Press Ctrl-Alt to escape from console.</p>	
5. <input type="checkbox"/>	VM Console: Login to console as admusr	<pre>login as: admusr Password:</pre>

Step	Procedure	Result
6. <input type="checkbox"/>	VM Console: Configure XMI network	<p>1. Set the XMI device for routable OAM access:</p> <p>NOTE: Where ethX is the interface associated with the XMI network</p> <pre>\$ sudo netAdm add --device=eth0 --address=<Guest_XMI_IP_Address> --netmask=<XMI_Netmask> --onboot=yes --bootproto=none</pre> <p>2. Add the default route for XMI:</p> <pre>\$ sudo netAdm add --route=default --gateway=<Gateway_XMI_IP_Address> --device=eth0</pre> <p>NOTE: The network device may be different than shown here (eth0) if the order of network adapter insertion was other than shown. Refer to Step 3 for this assignment.</p>
7. <input type="checkbox"/>	VM Console: Configure XSI network	<p>Set the XSI device for routable signaling network access (Only for NO and MP Servers):</p> <p>NOTE: Where ethX is the interface associated with the XSI network</p> <pre>\$ sudo netAdm add --device=eth2 --address=<Guest_XSI_IP_Address> --netmask=<XSI_Netmask> --onboot=yes --bootproto=none</pre> <p>NOTE: The network device may be different than shown here (eth2) if the order of network adapter insertion was other than shown. Refer to Step 3 for this assignment.</p>
8. <input type="checkbox"/>	VM Console: Repeat as required	Repeat Step 7 to add XS1-2 (eth3) if a second signaling network. Adjust parameter values as required.
9. <input type="checkbox"/>	VM Console: Exit console	<pre>\$ exit</pre> <p>NOTE: Press Ctrl-Alt to escape from console.</p>
THIS PROCEDURE HAS BEEN COMPLETED		

Appendix C. VMWare vCloud Director Oracle Communications User Data Repository Deployment

C.1 VCLOUD DIRECTOR ORACLE COMMUNICATIONS USER DATA REPOSITORY MEDIA UPLOAD

This procedure uploads Oracle Communications User Data Repository media (ISO or OVA) into vCloud Director Catalogs.

Needed material:




- Oracle Communications User Data Repository OVA





Optional material (required for ISO install only):


- Oracle Communications User Data Repository ISO
- TPD Platform ISO

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure19: vCloud Director Oracle Communications User Data Repository Media Upload

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware vCloud Director	
2. <input type="checkbox"/>	vCloud Director: Enter Oracle Communications User Data Repository catalog name in the search field and hit Enter.	
3. <input type="checkbox"/>	vCloud Director: Click the name for the appropriate catalog and proceed to Step 6	 <p>NOTE: If a catalog for Oracle Communications User Data Repository does not exist, create one using steps 4 and 5.</p>

Step	Procedure	Result
4. <input type="checkbox"/>	vCloud Director: Click Catalogs tab. Click the green plus sign.	
5. <input type="checkbox"/>	vCloud Director: 1. Enter the catalog name and description. 2. Unless this catalog requires special storage or sharing, click Finish .	 <p>NOTE: After clicking Finish, return to Step 2 of this procedure to access the catalog.</p>
6. <input type="checkbox"/>	vCloud Director: <ul style="list-style-type: none"> Select vApp Templates for OVA upload Select Media & Other for ISO upload 	
7. <input type="checkbox"/>	vCloud Director: Click the Blue Gear Symbol and then select Upload	



Step	Procedure	Result
8. <input type="checkbox"/>	vCloud Director: Select Source as either URL or local file then enter a Name. Click Upload .	
THIS PROCEDURE HAS BEEN COMPLETED		




C.2 CREATE VAPP





This procedure creates and configure a vApp virtual appliance.


Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure20: Create vApp

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware vCloud Director	
2. <input type="checkbox"/>	vCloud Director: Select Home tab, then click Build New vApp	

Step	Procedure	Result
3. <input type="checkbox"/>	vCloud Director: 1.. Enter the name for the vApp and other parameters as required. 2. Click Finish .	
4. <input type="checkbox"/>	vCloud Director: Navigate to My Cloud → <vApp Name> → Networking Then click the green plus icon to add a network.	
5. <input type="checkbox"/>	vCloud Director: Select vApp network . Click Next .	

Step	Procedure	Result
6. <input type="checkbox"/>	vCloud Director: Enter parameters for your internal network. Be sure to have sufficient address space for the number of servers you expect to deploy. Click Next .	
7. <input type="checkbox"/>	vCloud Director: Enter a Name for your network using [1] as a guide. Click Next .	
8. <input type="checkbox"/>	vCloud Director: Review the network data Click Finish .	
9. <input type="checkbox"/>	vCloud Director: Back on the Networking tab.	 <p>If the network is addressable outside the Cloud (such as XMI for administration), select an external network from the Connection list.</p> <p>Otherwise, leave Connection setting as None.</p>




Step	Procedure	Result
10. <input type="checkbox"/>	vCloud Director: Click Apply .	
THIS PROCEDURE HAS BEEN COMPLETED		




C.3 CREATE GUESTS FROM OVA

This procedure creates Oracle Communications User Data Repository virtual machines (guests) from OVA.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure21: Create Guests from OVA with vCloud Director

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware vCloud Director	
2. <input type="checkbox"/>	vCloud Director: Click Open for the Oracle Communications User Data Repository vApp	 <p>NOTE: Current vApps are listed on the Home Page. If a new vApp is required continue with the next step.</p>
3. <input type="checkbox"/>	vCloud Director: Select icon on left to Add VM	


Step	Procedure	Result
4. <input type="checkbox"/>	vCloud Director: <ol style="list-style-type: none"> Enter name in the search field and press Enter Select Oracle Communications User Data Repository media name Click Add. Click Next. 	
5. <input type="checkbox"/>	vCloud Director: <ol style="list-style-type: none"> Select the license agreement Click Next 	
6. <input type="checkbox"/>	vCloud Director: <ol style="list-style-type: none"> Rename virtual machines to reflect its location and role Click Finish. 	
THIS PROCEDURE HAS BEEN COMPLETED		




C.4 CONFIGURE GUEST RESOURCES

This procedure configures Oracle Communications User Data Repository virtual machines (guests) which have been created from OVA.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure22: Configure Guests from OVA with vCloud Director

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware vCloud Director	

Step	Procedure	Result
2. <input type="checkbox"/>	vCloud Director: Navigate to My Cloud → Virtual Machines	
3. <input type="checkbox"/>	vCloud Director: 1. Select the VM. 2. Click the Blue Gear icon. 3. Select Properties .	
4. <input type="checkbox"/>	vCloud Director: Under the General tab, adjust Virtual Machine and Computer names.	


Step	Procedure	Result																																
5. <input type="checkbox"/>	<p>vCloud Director:</p> <ol style="list-style-type: none">Go to the Hardware tab.Adjust the number of Virtual CPUs and Total Memory to match the role of the servers in [1].Select Expose hardware-assisted CPU virtualization to guest OS.Adjust NICs to match the role of the server role in [1].Click OK.	<div><div><div>GeneralHardwareGuest OS CustomizationGuest PropertiesResource Allocation</div><div><div>CPU</div><div>Number of virtual CPUs: 4</div><div>Cores per socket: 1</div><div>Number of sockets: 4</div><div><input checked="" type="checkbox"/> Expose hardware-assisted CPU virtualization to guest OS Select this option to support virtualization servers or 64-bit VMs running on this virtual machine.</div><div>Memory</div><div>Total memory: 6 GB</div></div></div></div> <div><div>NICs</div><div><div><div><div><div>Guest customization is required to run for the NIC changes to take effect.</div><div><input type="checkbox"/> Show network adapter type Adapter choice can affect both networking performance and migration compatibility. Consult the VMware KnowledgeBase for more information on choosing among the network adapter support for various guest operating systems and hosts.</div></div></div><table><tr><th>NIC#</th><th>Connected</th><th>Network</th><th>Primary NIC</th><th>IP Mode</th><th>IP Address</th><th>MAC Address</th><th></th></tr><tr><td>0</td><td><input checked="" type="checkbox"/></td><td>XMI</td><td><input checked="" type="radio"/></td><td>Static - IP Pool</td><td>10.240.23.9</td><td>00:50:56:01:06:84</td><td>Delete</td></tr><tr><td>1</td><td><input checked="" type="checkbox"/></td><td>IMI</td><td><input type="radio"/></td><td>Static - IP Pool</td><td></td><td>Will be generated</td><td>Delete</td></tr><tr><td>2</td><td><input checked="" type="checkbox"/></td><td>XSH</td><td><input type="radio"/></td><td>Static - IP Pool</td><td></td><td>Will be generated</td><td>Delete</td></tr></table><div><div>+</div>Add</div></div></div><div><div>OKCancel</div></div></div>	NIC#	Connected	Network	Primary NIC	IP Mode	IP Address	MAC Address		0	<input checked="" type="checkbox"/>	XMI	<input checked="" type="radio"/>	Static - IP Pool	10.240.23.9	00:50:56:01:06:84	Delete	1	<input checked="" type="checkbox"/>	IMI	<input type="radio"/>	Static - IP Pool		Will be generated	Delete	2	<input checked="" type="checkbox"/>	XSH	<input type="radio"/>	Static - IP Pool		Will be generated	Delete
NIC#	Connected	Network	Primary NIC	IP Mode	IP Address	MAC Address																												
0	<input checked="" type="checkbox"/>	XMI	<input checked="" type="radio"/>	Static - IP Pool	10.240.23.9	00:50:56:01:06:84	Delete																											
1	<input checked="" type="checkbox"/>	IMI	<input type="radio"/>	Static - IP Pool		Will be generated	Delete																											
2	<input checked="" type="checkbox"/>	XSH	<input type="radio"/>	Static - IP Pool		Will be generated	Delete																											
THIS PROCEDURE HAS BEEN COMPLETED																																		



C.5 CREATE GUESTS FROM ISO



This procedure creates Oracle Communications User Data Repository virtual machines (guests) from ISO.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.




Procedure23: Create Guests from ISO with vCloud Director


Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware vCloud Director	

Step	Procedure	Result
2. <input type="checkbox"/>	vCloud Director: Click Open for the Oracle Communications User Data Repository vApp	 <p>NOTE: Current vApps are listed on the Home Page. If a new vApp is required continue with the next step.</p>
3. <input type="checkbox"/>	vCloud Director: Select icon on left to Add VM	
4. <input type="checkbox"/>	vCloud Director: Click New Virtual Machine .	

Step	Procedure	Result
5. <input type="checkbox"/>	vCloud Director: <ol style="list-style-type: none"> 1. Enter Name and Computer Name for VM. 2. Set Operating System Family to Linux. 3. Select Expose hardware-assisted CPU.... 4. Enter all resource parameters according to the role given in resource profile[1]. 5. Click OK. 	
6. <input type="checkbox"/>	vCloud Director: Click Next .	

Step	Procedure	Result
7. <input type="checkbox"/>	vCloud Director: Click Next .	
8. <input type="checkbox"/>	vCloud Director: 1. Select Networks and IP Assignments for VM according to the role given in resource profile [1]. 2. Click Next .	
9. <input type="checkbox"/>	vCloud Director: 1. For each external network (XMI, XSI): Set Connection to the network a cloud administer has granted for external communication. 2. For each external network (XMI, XSI): Check NAT and Uncheck Firewall. 3. Click Next .	

Step	Procedure	Result												
10. <input type="checkbox"/>	vCloud Director: 1. Review the settings. 2. Click Finish .	 <table><tr><th>Virtual Machine</th><th>Guest OS</th><th>Storage Policy</th></tr><tr><td>NO-A</td><td>Red Hat Enterprise Linux 7 (64-bit)</td><td>* (Any)</td></tr><tr><td>NO-B</td><td>Red Hat Enterprise Linux 7 (64-bit)</td><td>* (Any)</td></tr></table>	Virtual Machine	Guest OS	Storage Policy	NO-A	Red Hat Enterprise Linux 7 (64-bit)	* (Any)	NO-B	Red Hat Enterprise Linux 7 (64-bit)	* (Any)			
Virtual Machine	Guest OS	Storage Policy												
NO-A	Red Hat Enterprise Linux 7 (64-bit)	* (Any)												
NO-B	Red Hat Enterprise Linux 7 (64-bit)	* (Any)												
11. <input type="checkbox"/>	vCloud Director: 1. Select the VM. 2. Click the Blue Gear icon. 3. Select Properties .													
12. <input type="checkbox"/>	vCloud Director: 1. Select the Hardware tab. 2. Adjust the size of Disk 0 to match VM profile [1]	 <table><tr><th>Name</th><th>Size</th><th>Bus Type</th><th>Bus Number</th><th>Unit Number</th><th>Delete</th></tr><tr><td>Disk 0</td><td>60 GB</td><td>Paravirtual (SCSI)</td><td>0</td><td>0</td><td>Delete</td></tr></table>	Name	Size	Bus Type	Bus Number	Unit Number	Delete	Disk 0	60 GB	Paravirtual (SCSI)	0	0	Delete
Name	Size	Bus Type	Bus Number	Unit Number	Delete									
Disk 0	60 GB	Paravirtual (SCSI)	0	0	Delete									




Step	Procedure	Result
13. <input type="checkbox"/>	vCloud Director: Only If the VM uses a second disk by [1]: 1. Click Add 2. Adjust size of Disk 1 to match VM profile [1]. 3. Click OK	
THIS PROCEDURE HAS BEEN COMPLETED		




C.6 INSTALL GUESTS FROM ISO



This procedure creates Oracle Communications User Data Repository virtual machines (guests) from ISO.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.




Procedure24: Install Guests from ISO with vCloud Director

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware vCloud Director	
2. <input type="checkbox"/>	vCloud Director: Click Open for the Oracle Communications User Data Repository vApp then proceed to Step 5.	 <p>NOTE: Current vApps are listed on the Home Page. If a new vApp is required continue with the next step.</p>
3. <input type="checkbox"/>	vCloud Director: Navigate to → My Cloud → Virtual Machines	





Step	Procedure	Result																				
4. <input type="checkbox"/>	vCloud Director: 1.Select the VM. 2.Click the Blue Gear icon. 3.Select Insert CD/DVD from Catalog .	 <p>The screenshot shows the vCloud Director interface with the 'Virtual Machines' tab selected. A list of VMs is shown: 'morrisville-udr-noA', 'morrisville-udr-noB', 'NO-A', and 'Seagull'. The 'NO-A' VM is selected. A context menu (vApp VM Menu) is open, showing options like 'Power On', 'Suspend', 'Shut Down Guest OS', 'Power Off', 'Reset', 'Power On and Force Recustomization', 'Discard Suspended State', 'Insert CD/DVD from Catalog...', 'Eject CD/DVD', 'Install VMware Tools', 'Upgrade Virtual Hardware Version', 'Download Windows Remote Desktop Shortcut File...', and 'Copy to...'. The 'Insert CD/DVD from Catalog...' option is highlighted.</p>																				
5. <input type="checkbox"/>	vCloud Director: 1.Select TPD ISO. 2.Click Insert	 <p>The screenshot shows the 'Insert CD' dialog box. It prompts the user to 'Select the media file to insert in the VM.' and lists 'Media available now:'. A table shows the available media files:</p> <table><thead><tr><th>Name</th><th>Catalog</th><th>Owner</th><th>Created On</th><th>Storage Used</th></tr></thead><tbody><tr><td>TPD.install-7.0.2.0.0_86</td><td>UDR</td><td>jpaley3</td><td>11/05/2015 2:44 PM</td><td>715.24 MB</td></tr><tr><td>UDR-12.1.0.0.0_13.3.0-</td><td>UDR</td><td>jpaley3</td><td>11/17/2015 2:43 PM</td><td>871.99 MB</td></tr><tr><td>UDR-12.1.0.0.0_13.7.0-</td><td>UDR</td><td>jpaley3</td><td>01/08/2016 3:25 PM</td><td>873.17 MB</td></tr></tbody></table> <p>The 'Insert' button is highlighted at the bottom right of the dialog.</p>	Name	Catalog	Owner	Created On	Storage Used	TPD.install-7.0.2.0.0_86	UDR	jpaley3	11/05/2015 2:44 PM	715.24 MB	UDR-12.1.0.0.0_13.3.0-	UDR	jpaley3	11/17/2015 2:43 PM	871.99 MB	UDR-12.1.0.0.0_13.7.0-	UDR	jpaley3	01/08/2016 3:25 PM	873.17 MB
Name	Catalog	Owner	Created On	Storage Used																		
TPD.install-7.0.2.0.0_86	UDR	jpaley3	11/05/2015 2:44 PM	715.24 MB																		
UDR-12.1.0.0.0_13.3.0-	UDR	jpaley3	11/17/2015 2:43 PM	871.99 MB																		
UDR-12.1.0.0.0_13.7.0-	UDR	jpaley3	01/08/2016 3:25 PM	873.17 MB																		
6. <input type="checkbox"/>	vCloud Director: 1.Click the sky blue Play icon to start the VM 2.Click the Console to open the console window	 <p>The screenshot shows the vCloud Director interface with the 'Virtual Machines' tab selected. A table lists the VMs and their status:</p> <table><thead><tr><th>Name</th><th>Status</th><th>OS</th><th>Netw...</th></tr></thead><tbody><tr><td>morrisville-udr-noB</td><td>Powered Off</td><td>Oracle L</td><td>NIC 0*: NIC 1 : NIC 2 :</td></tr><tr><td>NO-A</td><td>Powered Off</td><td>Red Ha</td><td>NIC 0*: NIC 1 : NIC 2 :</td></tr><tr><td>Seagull</td><td>Powered On</td><td>Other Li</td><td>NIC 0*: NIC 1 : NIC 2 :</td></tr></tbody></table>	Name	Status	OS	Netw...	morrisville-udr-noB	Powered Off	Oracle L	NIC 0*: NIC 1 : NIC 2 :	NO-A	Powered Off	Red Ha	NIC 0*: NIC 1 : NIC 2 :	Seagull	Powered On	Other Li	NIC 0*: NIC 1 : NIC 2 :				
Name	Status	OS	Netw...																			
morrisville-udr-noB	Powered Off	Oracle L	NIC 0*: NIC 1 : NIC 2 :																			
NO-A	Powered Off	Red Ha	NIC 0*: NIC 1 : NIC 2 :																			
Seagull	Powered On	Other Li	NIC 0*: NIC 1 : NIC 2 :																			

Step	Procedure	Result
7. <input type="checkbox"/>	vCloud Director: Initiate operating system install by entering the given text into console boot prompt	 <pre> boot: TPDnoraidd console=tty0 </pre>
8. <input type="checkbox"/>	When installation completes, press Enter to reboot	 <p>NOTE: Escape the console session by pressing Ctrl-Alt</p>
9. <input type="checkbox"/>	After reboot, log into console	<pre> Hostname:b6092a316785 login: root password: </pre>
10. <input type="checkbox"/>	Verify that the TPD release is 7.6.1.x	<pre> # getPlatRev 7.6.1.0.0-88.55.0 </pre>
11. <input type="checkbox"/>	Run the <code>alarmMgr</code> command to verify health of the server before Application install.	<pre> # alarmMgr --alarmStatus </pre> <p>NOTE: This command should not return output on a healthy system.</p>
12. <input type="checkbox"/>	Run the <code>verifyIPM</code> as a secondary way to verify health of the server before Application install.	<pre> # verifyIPM </pre> <p>NOTE: This command should not return output on a healthy system.</p>
13. <input type="checkbox"/>	Create physical volume <code>sdb</code>	<pre> # pvcreate /dev/sdb Physical volume "/dev/sdb" successfully created </pre>

Step	Procedure	Result
14. <input type="checkbox"/>	Create volume group stripe_vg	<pre># vgcreate stripe_vg /dev/sdb</pre> <p>Volume group "stripe_vg" successfully created</p>
15. <input type="checkbox"/>	Create logical volume rundb	<pre># lvcreate -L <SIZE>G --alloc anywhere --name rundb stripe_vg</pre> <p>Replace <SIZE> size tag with a number in gigabytes half the size of the second disk according to [1].</p> <pre>ISO lab second disk is 120: <SIZE> = 60 ISO production second disk is 720: <SIZE> = 360</pre>
16. <input type="checkbox"/>	Make filesystem on rundb	<pre># mkfs -t ext4 /dev/stripe_vg/rundb</pre> <pre>mke2fs 1.43-WIP (20-Jun-2013) Filesystem label= OS type: Linux Block size=4096 (log=2) Fragment size=4096 (log=2) Stride=0 blocks, Stripe width=0 blocks 25231360 inodes, 100925440 blocks 5046272 blocks (5.00%) reserved for the super user First data block=0 Maximum filesystem blocks=4294967296 3080 block groups 32768 blocks per group, 32768 fragments per group 8192 inodes per group Superblock backups stored on blocks: 32768, 98304, 163840, 229376, 294912, 819200, 884736, 1605632, 2654208, 4096000, 7962624, 11239424, 20480000, 23887872, 71663616, 78675968 Allocating group tables: done Writing inode tables: done Creating journal (32768 blocks): done Writing superblocks and filesystem accounting information: done This filesystem will be automatically checked every 22 mounts or 180 days, whichever comes first. Use tune2fs -c or -i to override.</pre>
17. <input type="checkbox"/>	Run the syscheck/restart steps in order	<pre># syscheck --reconfig disk</pre>
18. <input type="checkbox"/>	Escape console	Escape the console session by pressing Ctrl-Alt

Step	Procedure	Result
19. <input type="checkbox"/>	vCloud Director: 1. Select the VM . 2. Click the Blue Gear icon. 3. Select Insert CD/DVD from Catalog .	
20. <input type="checkbox"/>	vCloud Director: 1. Select Oracle Communications User Data Repository ISO. 2. Click Insert	
21. <input type="checkbox"/>	VM Console: 1. Re-enter the console window 2. Login to the platcfg utility.	

Step	Procedure	Result
22. <input type="checkbox"/>	VM Console: From the platcfg Main Menu, select each option, pressing Enter after each selection.	 <p>The first screenshot shows the Main Menu with options: Maintenance, Diagnostics, Server Configuration, Remote Consoles, Network Configuration, and Exit. The second screenshot shows the Maintenance Menu with options: Upgrade, Halt Server, Backup and Restore, View Mail Queues, Restart Server, Eject CDROM, Save Platform Debug Logs, and Exit. The third screenshot shows the Upgrade Menu with options: Validate Media, Early Upgrade Checks, Initiate Upgrade, Non Tekelec RPM Management, and Exit.</p>
23. <input type="checkbox"/>	VM Console: 1. From the platcfg Main Menu, verify that the CDROM is Valid. 2. Press any key to return to platcfg menu.	 <p>The screenshot shows the terminal output of the UMVT Validate Utility. It displays the path to the ISO file, the date and time, the volume ID, part number, version, disc label, and disc description. The result of the validation is PASS, and the CDROM is confirmed as valid. The prompt at the bottom asks the user to press any key to return to the platcfg menu.</p>

Step	Procedure	Result
24. <input type="checkbox"/>	VM Console: From the platcfg Main Menu, select each option, pressing the Enter after each selection.	 
25. <input type="checkbox"/>	VM Console: Verify that the Application release level matches the target release. Press Enter .	 
26. <input type="checkbox"/>	VM Console: Output similar to that shown on the right may be observed as the Application install progresses.	<pre> Determining if we should upgrade... Install product is TPD Install product record exists in /etc/tekelec.cfg Install products match Stopping cron service... Checking for stale RPM DB locks... Installing public key /mnt/upgrade/upgrade/pub_keys/MySQL_public_key.asc... Installing public key /mnt/upgrade/upgrade/pub_keys/RPM-GPG-KEY-redhat-beta... Installing public key /mnt/upgrade/upgrade/pub_keys/RPM-GPG-KEY-redhat-release... . Checking for any missing packages or files Checking for missing files... No missing files found. Checking if upgrade is supported Current platform version: 5.0.0-72.28.0 Target platform version: 5.0.0-72.28.0 Minimum supported version: 4.2.0-70.60.0 Upgrade from same release as current is supported Evaluate if there are any packages to upgrade Evaluating if there are packages to upgrade... </pre>

Step	Procedure	Result
27. <input type="checkbox"/>	VM Console: Output similar to that shown on the right may be observed as the server initiates a post-install reboot.	<pre>scsi7 : SCSI emulation for USB Mass Storage devices scsi8 : SCSI emulation for USB Mass Storage devices input: Intel(R) Multidevice as /class/input/input3 input: USB HID v1.01 Mouse [Intel(R) Multidevice] on usb-0000:00:1d.3-1 input: Intel(R) Multidevice as /class/input/input4 input: USB HID v1.01 Keyboard [Intel(R) Multidevice] on usb-0000:00:1d.3-1 Restarting system. . machine restart</pre>
28. <input type="checkbox"/>	VM Console: After the server has completed reboot, log into the server as admusr.	<pre>CentOS release 5.6 (Final) Kernel 2.6.18-238.19.1.el5prere15.0.0_72.22.0 on an x86_64 hostname1260476221 login:admusr Password: <admusr_password></pre>
29. <input type="checkbox"/>	VM Console: Output similar to that shown on the right appears as the server returns to a command prompt.	<pre>*** TRUNCATED OUTPUT *** ===== This system has been upgraded but the upgrade has not yet been accepted or rejected. Please accept or reject the upgrade soon. ===== VPATH=/opt/TKLCcomcol/runcm5.16:/opt/TKLCcomcol/cm5.16 PRODPATH= RELEASE=5.16 RUNID=00 VPATH=/var/TKLC/rundb:/usr/TKLC/appworks:/usr/TKLC/awpcommon:/usr/TKLC /comagent-gui:/usr/TKLC/comagent:/usr/TKLC/udr PRODPATH=/opt/comcol/prod RUNID=00 [admusr@hostname1260476221 ~]\$</pre>
30. <input type="checkbox"/>	VM Console: Verify successful upgrade.	<pre>\$ verifyUpgrade</pre> <p>NOTE: This command should not return output on a healthy system.</p>
31. <input type="checkbox"/>	VM Console: Verify that the Application release level matches the target release.	<pre>[admusr@ pc9000724-no-a ~]\$ appRev Install Time: Fri Feb 9 04:48:18 2019 Product Name: UDR Product Release: 12.5.1.0.0_17.7.0 Base Distro Product: TPD Base Distro Release: 7.6.1.0.0-88.55.0 Base Distro ISO: TPD.install-7.6.1.0.0_88.55.0-OracleLinux6.9- x86_64.iso ISO name: UDR-12.5.1.0.0_17.7.0-x86_64.iso OS: OracleLinux 6.9</pre>
32. <input type="checkbox"/>	Change directory	<pre>\$ cd /var/TKLC/backout</pre>
33. <input type="checkbox"/>	Perform upgrade acceptance.	<pre>\$ sudo ./accept</pre>



Step	Procedure	Result
34. <input type="checkbox"/>	VM Console: Reboot the server	Reboot the server: <pre>\$ sudo reboot</pre> Wait until the reboot completes and re-login with admusr credentials.
35. <input type="checkbox"/>	VM Console: Verify server health	Verify server health: <pre>\$ alarmMgr --alarmStatus</pre> NOTE: This command should return only one alarm related to pending upgrade acceptance.
THIS PROCEDURE HAS BEEN COMPLETED		




C.7 CONFIGURE GUESTS NETWORK


This procedure creates Oracle Communications User Data Repository virtual machines (guests) from ISO.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure25: Configure Guest OAM Network

Step	Procedure	Result
1. <input type="checkbox"/>	Log into the VMware vCloud Director	 The image shows the VMware vCloud Director login interface. It has a blue background with the VMware logo at the top left. There are two input fields labeled 'User name:' and 'Password:'. Below them is a blue 'Login' button. The text 'VMware vCloud Director' is displayed on the right side.
2. <input type="checkbox"/>	vCloud Director: Select Open hyperlink for the Oracle Communications User Data Repository vApp then proceed to Step 5.	 The image shows the VMware vCloud Director Home page. At the top are tabs for 'Home', 'My Cloud', and 'Catalogs'. Below is a 'Quick Access' section with instructions: 'To start a vApp, click Start. To use a powered on vApp, click on its thumbnail.' There are two buttons: 'Add vApp from Catalog' and 'Build New vApp'. Below these are two vApp thumbnails. The first is titled 'UDR 12.1 DR Site' and shows three server icons. It has a status of 'Partially Running' and a green arrow icon. The second is titled 'UDR 12.1 Primary Site' and also shows three server icons. It has a status of 'Running' and a green arrow icon. Both thumbnails have a 'Lease expires: 10 days' message and an 'Open' button. At the bottom, there are three icons: a green play button, a yellow pause button, and a red stop button. NOTE: Current vApps are listed on the Home Page. If a new vApp is required continue with the next step.

Step	Procedure	Result
3. <input type="checkbox"/>	vCloud Director: Navigate to My Cloud → Virtual Machines	
4. <input type="checkbox"/>	vCloud Director: 1. Select the VM. 2. Click the Blue Gear icon. 3. Select Properties	
5. <input type="checkbox"/>	vCloud Director: 1. Select Hardware tab. 2. Record the NIC number assignment of application networks 3. Click Cancel	 <p>Record the NIC device number assignment for these networks:</p> <p>XMI: _____</p> <p>IMI: _____</p> <p>XSI-1: _____</p> <p>XSI-2: _____ (optional)</p> <p>OK Cancel</p>

Step	Procedure	Result
6. <input type="checkbox"/>	vCloud Director: Click the console to raise console window	
7. <input type="checkbox"/>	VM Console: Login to console as admusr	<pre>login as: admusr Password:</pre>
8. <input type="checkbox"/>	VM Console: Configure XMI network	<p>1. View a list of netAdm devices</p> <pre>\$ sudo netAdm show</pre> <p>2. Set the XMI device for routable OAM access:</p> <p>NOTE: Use add if the show command did not list device eth0. Use set otherwise.</p> <pre>\$ sudo netAdm add --device=eth0 --address=<Guest_XMI_IP_Address> --netmask=<XMI_Netmask> --onboot=yes --bootproto=none</pre> <p>3. Add the default route for XMI:</p> <pre>\$ sudo netAdm add --route=default --gateway=<Gateway_XMI_IP_Address> --device=eth0</pre> <p>NOTE: The network device may be different than shown here (eth0) if the order of network adapter insertion was other than shown. Refer to Step 5 for this assignment.</p>
9. <input type="checkbox"/>	VM Console: Configure XSI network	<p>Set the XSI device for routable signaling network access (Only for NO and MP Servers):</p> <p>NOTE: Where ethX is the interface associated with the signaling network</p> <pre>\$ sudo netAdm add --device=eth2 --address=<Guest_XSI_IP_Address> --netmask=<XSI_Netmask> --onboot=yes --bootproto=none</pre> <p>NOTE: The network device may be different than shown here (eth2) if the order of network adapter insertion was other than shown. Refer to Step 5 for this assignment.</p>
10. <input type="checkbox"/>	VM Console: Repeat as required	Repeat Step 7 to add XS1-2 (eth3) if a second signaling network is in use. Adjust parameter values as required
11. <input type="checkbox"/>	VM Console: Exit console	<pre>\$ exit</pre> <p>NOTE: Press Ctrl-Alt to escape from console.</p>
THIS PROCEDURE HAS BEEN COMPLETED		

Appendix D. OpenStack Cloud Oracle Communications User Data Repository

This appendix contains procedures for deploying Oracle Communications User Data Repository on the Openstack platform. The steps here contain references to third party interfaces, the accuracy of which cannot be guaranteed. Appearance and function may differ between versions of Openstack software and deployments of Openstack cloud computing.

IMPORTANT NOTE: The content of this appendix is for informational purposes only. Consult the latest documents from the vendor of your OpenStack distrobution.

D.1 OPENSTACK IMAGE CREATION FROM OVA

This procedure converts application media (OVA) to qcow2 format and upload it into OpenStack.

Needed material:

- Oracle Communications User Data Repository OVAs

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure26: OpenStack Image Creation from OVA

Step	Procedure	Result
1. <input type="checkbox"/>	1. Login to OpenStack Controller Node using root user 2. Create /home/ova dir	login as: root root@100.65.218.136's password: <root_password> Last login: Thu Feb 9 21:10:59 2016 from 10.182.167.73 [root@pc12107008 ~]# mkdir -p /home/ova [root@pc12107008 ~]# cd /home/ova
2. <input type="checkbox"/>	Transfer OVA file this dir using sftp tool	[root@pc12107008 ova]# ll -rw-r--r-- 1 root root 1519329280 Feb 2 03:40 UDR-12.5.1.0.0_17.7.0.ova
3. <input type="checkbox"/>	Untar this ova file	[root@pc12107008 ova]# tar xvf UDR-12.5.1.0.0_17.7.0.ova UDR-17_7_0.ovf UDR-17_7_0.mf UDR-17_7_0.vmdk
4. <input type="checkbox"/>	Convert this vmdk file to qcow2 file	[root@pc12107008 ova]# qemu-img convert -O qcow2 UDR-17_17_0.vmdk UDR-17_7_0.qcow2




Step	Procedure	Result																																										
5. <input type="checkbox"/>	Import converted qcow2 file into OpenStack	<pre>[root@pcl2107008 ova]# source /root/keystonerc_admin [root@pcl2107008 ova(keystone_admin)]# time glance image-create --name UDR-17_7_0 --disk-format=qcow2 --container-format=bare -- visibility=public-- file= UDR-17_7_0.qcow2</pre> <table><tr><th>Property</th><th>Value</th></tr><tr><td>checksum</td><td>81e7f682231b108e29053e9516ff91ac</td></tr><tr><td>container_format</td><td>bare</td></tr><tr><td>created_at</td><td>2019-02-9T06:56:51</td></tr><tr><td>deleted</td><td>False</td></tr><tr><td>deleted_at</td><td>None</td></tr><tr><td>disk_format</td><td>qcow2</td></tr><tr><td>id</td><td>ee0ffa59-356b-4b32-aea2-b0cdf9063653</td></tr><tr><td>is_public</td><td>True</td></tr><tr><td>min_disk</td><td>0</td></tr><tr><td>min_ram</td><td>0</td></tr><tr><td>name</td><td>UDR-17_7_0</td></tr><tr><td>owner</td><td>63efbafd70864562aa6440abfca60ca5</td></tr><tr><td>protected</td><td>False</td></tr><tr><td>size</td><td>3615227904</td></tr><tr><td>status</td><td>active</td></tr><tr><td>updated_at</td><td>2016-03-29T06:57:16</td></tr><tr><td>virtual_size</td><td>None</td></tr></table> <table><tr><td>real</td><td>0m26.267s</td></tr><tr><td>user</td><td>0m2.435s</td></tr><tr><td>sys</td><td>0m2.691s</td></tr></table>	Property	Value	checksum	81e7f682231b108e29053e9516ff91ac	container_format	bare	created_at	2019-02-9T06:56:51	deleted	False	deleted_at	None	disk_format	qcow2	id	ee0ffa59-356b-4b32-aea2-b0cdf9063653	is_public	True	min_disk	0	min_ram	0	name	UDR-17_7_0	owner	63efbafd70864562aa6440abfca60ca5	protected	False	size	3615227904	status	active	updated_at	2016-03-29T06:57:16	virtual_size	None	real	0m26.267s	user	0m2.435s	sys	0m2.691s
Property	Value																																											
checksum	81e7f682231b108e29053e9516ff91ac																																											
container_format	bare																																											
created_at	2019-02-9T06:56:51																																											
deleted	False																																											
deleted_at	None																																											
disk_format	qcow2																																											
id	ee0ffa59-356b-4b32-aea2-b0cdf9063653																																											
is_public	True																																											
min_disk	0																																											
min_ram	0																																											
name	UDR-17_7_0																																											
owner	63efbafd70864562aa6440abfca60ca5																																											
protected	False																																											
size	3615227904																																											
status	active																																											
updated_at	2016-03-29T06:57:16																																											
virtual_size	None																																											
real	0m26.267s																																											
user	0m2.435s																																											
sys	0m2.691s																																											
6. <input type="checkbox"/>	After image-create, this image could be seen from OpenStack GUI under Project → Images	<div><div><input type="text" value="Q"/></div><div><div><input type="checkbox"/></div><div>Owner</div></div><div><div><input type="checkbox"/></div><div>Name ^</div></div><div><div><input type="checkbox"/></div><div>Type</div></div><div><div><input type="checkbox"/></div><div>Status</div></div><div><div><input type="checkbox"/></div><div>Visibility</div></div><div><div><input type="checkbox"/></div><div>Protected</div></div><div><div><input type="checkbox"/></div><div>Disk Format</div></div><div><div><input type="checkbox"/></div><div>Size</div></div></div> <div><div><input type="checkbox"/></div><div>admin</div></div> <div><div><input type="checkbox"/></div><div>UDR-17_7</div></div> <div><div><input type="checkbox"/></div><div>Image</div></div> <div><div><input type="checkbox"/></div><div>Active</div></div> <div><div><input type="checkbox"/></div><div>Public</div></div> <div><div><input type="checkbox"/></div><div>No</div></div> <div><div><input type="checkbox"/></div><div>QCOW2</div></div> <div><div><input type="checkbox"/></div><div>4.06 GB</div></div> <div><div><input type="button" value="Create Image"/></div></div>																																										
THIS PROCEDURE HAS BEEN COMPLETED																																												


D.2 CREATE RESOURCE PROFILES (FLAVORS)

This procedure creates resource profiles called flavors to aid in VM creation.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure27: Create Resource Profiles (Flavors)

Step	Procedure	Result
1. <input type="checkbox"/>	Login to the OpenStack GUI NOTE: Flavor profile creation may require administrative privilege.	
2. <input type="checkbox"/>	Select Main Menu → Admin → System Panel → Flavors	
3. <input type="checkbox"/>	Click Create Flavor	


Step	Procedure	Result
4. <input type="checkbox"/>	<p>Enter Flavor Details using Appendix G as a guide *</p> <p>Name: udr-no</p> <p>ID: auto</p> <p>VCPUs: vCPUs*</p> <p>RAM: RAM*</p> <p>Root Disk: Storage*</p> <p>Ephemeral Disk: 0</p> <p>Swap Disk: 0</p> <p>NOTE: UDR does not require Ephemeral or Swap Disk.</p> <p>Then click Create Flavor.</p>	 <p>Create Flavor</p> <p>Flavor Info * Flavor Access</p> <p>Name: * From here you can create a new flavor to organize instance resources.</p> <p>ID: auto</p> <p>VCPUs: *</p> <p>RAM MB: *</p> <p>Root Disk GB: *</p> <p>Ephemeral Disk GB: *</p> <p>Swap Disk MB: *</p> <p>Cancel Create Flavor</p>
THIS PROCEDURE HAS BEEN COMPLETED		




D.3 CREATE KEY PAIR

This procedure creates Key Pair to be used in VM creation.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure28: Create Key Pair

Step	Procedure	Result
1. <input type="checkbox"/>	<p>Login to the OpenStack GUI</p> <p>NOTE: Flavor profile creation may require administrative privilege.</p>	 <p>openstack DASHBOARD</p> <p>Log In</p> <p>User Name: admin</p> <p>Password: *****</p> <p>Sign In</p>

Step	Procedure	Result
2. <input type="checkbox"/>	Select: Main Menu → Compute → Access & Security → Key Pairs	
3. <input type="checkbox"/>	Click Create Key Pair .	
4. <input type="checkbox"/>	Enter Key Pair Name Then click Create Key Pair .	
5. <input type="checkbox"/>	The Key pair automatically get downloaded to your computer.	The generated Key Pair gets downloaded automatically on creation. This is used for SSH Access to VM Instances.
THIS PROCEDURE HAS BEEN COMPLETED		

D.4 UPDATE UDR STACK YAML FILE

This procedure updates UDR Stack Yaml File to be used in VM creation.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure29: Create Key Pair

Step	Procedure	Result
1. <input type="checkbox"/>	Download the yaml file	Go to the Oracle Help Center and download the zip file containing the UDR Heat Templates .
2. <input type="checkbox"/>	Update Image name or ID with the name of the UDR Qcow2 to be used	Change the default value. <pre> label: Image name or ID description: UDR Image to be used for launching UDR VM default: UDR-12.5.1.0.0_17.7.0 </pre>




Step	Procedure	Result
3. <input type="checkbox"/>	Update the NTP Server IP	Change the default value. label: NTP server description: IP address of the NTP server used for UDR VM syncing time default: 192.168.56.180
4. <input type="checkbox"/>	Update the UDR flavor name if different	Change the default value. label: Flavor for UDR description: Type of instance (flavor) to be used for launching UDR VM default: UDR
5. <input type="checkbox"/>	Update the XMI Network name if different	Change the default value. label: UDR XMI network description: Network name or ID to attach UDR XMI network to. default: xmi
6. <input type="checkbox"/>	Update the IMI Network name if different	Change the default value. label: UDR IMI network description: Private network name or ID to attach UDR IMI network to. default: imi
7. <input type="checkbox"/>	Update the XSI1 Network name if different	Change the default value. label: UDR XSI1 network description: Network name or ID to attach UDR XSI1 network to. default: xsi1
8. <input type="checkbox"/>	Update the XSI2 Network name if different	Change the default value. label: UDR XSI2 network description: Network name or ID to attach UDR XSI2 network to. default: xsi2
9. <input type="checkbox"/>	Uncomment UDROB configuration from line 147 to 234 if configuring active, standby UDRs	Uncomment UDRB configuration from line 147 to 234 if configuring active, standby UDRs
THIS PROCEDURE HAS BEEN COMPLETED		


D.5 CREATE VM INSTANCES USING YAML FILE



This procedure creates and configure all VM instances needed for UDR configuration.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure30: Create VM Instances Using Yaml File

Step	Procedure	Result
1. <input type="checkbox"/>	Login to the OpenStack GUI	 <p>The screenshot shows the OpenStack Dashboard login page. The 'Log In' section has a 'User Name' field with 'admin' entered and a 'Password' field with masked characters. A 'Sign In' button is at the bottom right.</p>
2. <input type="checkbox"/>	1. Select project, (for example, UDR). 2. Navigate to Project → Orchestration → Stacks to show all Stacks created under this project.	 <p>The screenshot shows the OpenStack Project page for 'ocudr'. The left sidebar has 'Orchestration' selected, and the 'Stacks' sub-tab is active. The main area displays a list of stacks: Stack Name, komal, UDR-x52, Edward1, UDRPV04, UDRPV01, and UDRPV02.</p>
3. <input type="checkbox"/>	Click Launch Stack	 <p>The screenshot shows the bottom of the stacks list. A '+ Launch Stack' button is highlighted with a red box. Other buttons include 'Filter', 'Preview Stack', 'Updated', and 'Status'.</p>

Step	Procedure	Result
4. <input type="checkbox"/>	Select the Template File and Click Next	

Step	Procedure	Result
5. <input type="checkbox"/>	1. Enter the Stack Name 2. Enter the password for Openstack user 3. Click Launch to create UDR Stack	
6. <input type="checkbox"/>	Wait for stack creation to finish.	
THIS PROCEDURE HAS BEEN COMPLETED		

D.6 EXTEND VM INSTANCE VOLUME SIZE

This procedure extends the storage capacity of a VM instance using filesystem utilities.

Important: The steps in this procedure only apply to servers where storage demands exceed the default size of 60GB. The numbers here vary depending on the unique needs of each deployment and the specific hardware resource availability. This is to be taken as an example only. The suitability of these steps cannot be guaranteed across all deployment scenarios.

This procedure must be performed only under these conditions:

- UDR Instance with resource profile other than lab profile

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure31: Extend VM Instance Volume Size

Step	Procedure	Result
1. <input type="checkbox"/>	Login to the VM Instance as per D.10 Accessing VM Instance using SSH	<pre>hostnameea0c2d9aa8bce login: admusr</pre>
2. <input type="checkbox"/>	Switch to root user	<pre># su - root password: <root_password></pre>
3. <input type="checkbox"/>	Use fdisk to create a partition on /dev/vda NOTE: First cylinder of /dev/vda3 is calculated from end cylinder of /dev/vda2, say 124810 is the next of the end cylinder of /dev/vda2	<pre>[root@hostnameb267a6968148 ~]#fdisk /dev/vda Command (m for help): p Disk /dev/vda: 171.8 GB, 171798691840 bytes 16 heads, 63 sectors/track, 332881 cylinders Units = cylinders of 1008 * 512 = 516096 bytes Sector size (logical/physical): 512 bytes / 512 bytes I/O size (minimum/optimal): 512 bytes / 512 bytes Disk identifier: 0x0008a531 Device Boot Start End Blocks Id System /dev/vda1 * 3 523 262144 83 Linux Partition 1 does not end on cylinder boundary. /dev/vda2 523 124809 62640128 8e Linux LVM Partition 2 does not end on cylinder boundary. Command (m for help): n Command action e extended p primary partition (1-4) p Partition number (1-4): 3 First cylinder (1-332881, default 1): 124810 Last cylinder, +cylinders or +size{K,M,G} (124810-332881, default 332881): Using default value 332881 Command (m for help): w The partition table has been altered! Calling ioctl() to re-read partition table. WARNING: Re-reading the partition table failed with error 16: Device or resource busy. The kernel still uses the old table. The new table will be used at the next reboot or after you run partprobe(8) or kpartx(8) Syncing disks.</pre>
4. <input type="checkbox"/>	Reboot instance	<pre>[root@hostnameb267a6968148 ~]# init 6</pre>

Step	Procedure	Result
5. <input type="checkbox"/>	After reboot, Login to the VM with admusr user and switch to root user D.10 Accessing VM Instance using SSH	<pre>hostnameb267a6968148 login: admusr # su - root password: <root_password></pre>
6. <input type="checkbox"/>	Create pv /dev/vda3	<pre>[root@hostnameb267a6968148 ~]# pvcreate /dev/vda3 Physical volume "/dev/vda3" successfully created</pre>
7. <input type="checkbox"/>	Extend vg vgroot on /dev/vda3	<pre>[root@hostnameb267a6968148 ~]# vgextend vgroot /dev/vda3 Volume group "vgroot" successfully extended</pre>
8. <input type="checkbox"/>	Extend logical volumes for 2K profile	<pre># lvextend -L +52428800K /dev/vgroot/run_db # lvextend -L +52428800K /dev/vgroot/filemgmt # lvextend -L +6291456K /dev/vgroot/logs_process # resize2fs /dev/mapper/vgroot-filemgmt # resize2fs /dev/mapper/vgroot-run_db # resize2fs /dev/mapper/vgroot-logs_process # lvsdf -ha LV VG Attr LSize Pool Origin Data% Meta% Move Log Cpy%Sync Convert apw_tmp vgroot -wi-ao---- 9.09g filemgmt vgroot -wi-ao---- 68.19g logs_process vgroot -wi-ao---- 9.66g logs_security vgroot -wi-ao---- 3.66g netbackup_lv vgroot -wi-ao---- 2.00g plat_root vgroot -wi-ao---- 1.00g plat_tmp vgroot -wi-ao---- 1.00g plat_usr vgroot -wi-ao---- 4.00g plat_var vgroot -wi-ao---- 1.00g plat_var_tklc vgroot -wi-ao---- 4.00g run_db vgroot -wi-ao---- 59.09g # vgs VG #PV #LV #SN Attr VSize VFree vgroot 2 11 0 wz--n- 219.72g 57.03g</pre>


Step	Procedure	Result
9. <input type="checkbox"/>	Extend logical volumes for 7K or 12.5K profile	<pre># lvextend -L +115343360K /dev/vgroot/run_db # lvextend -L +104857600K /dev/vgroot/filemgmt # lvextend -L +6291456K /dev/vgroot/logs_process # lvextend -L +10485760K /dev/vgroot/apw_tmp # resize2fs /dev/mapper/vgroot-filemgmt # resize2fs /dev/mapper/vgroot-run_db # resize2fs /dev/mapper/vgroot-logs_process # resize2fs /dev/mapper/vgroot-apw_tmp# lvs LV VG Attr LSize Pool Origin Data% Meta% Move Log Cpy%Sync Convert apw_tmp vgroot -wi-ao---- 29.09g filemgmt vgroot -wi-ao---- 118.19g logs_process vgroot -wi-ao---- 9.66g logs_security vgroot -wi-ao---- 3.66g netbackup_lv vgroot -wi-ao---- 2.00g plat_root vgroot -wi-ao---- 1.00g plat_tmp vgroot -wi-ao---- 1.00g plat_usr vgroot -wi-ao---- 4.00g plat_var vgroot -wi-ao---- 1.00g plat_var_tklc vgroot -wi-ao---- 4.00g run_db vgroot -wi-ao---- 109.09g # vgs VG #PV #LV #SN Attr VSize VFree vgroot 2 11 0 wz--n- 282.69g 117.31g</pre>
10. <input type="checkbox"/>	Reboot instance	<pre>[root@hostnameb267a6968148 ~]# init 6</pre>
THIS PROCEDURE HAS BEEN COMPLETED		


D.7 VM INSTANCE NETWORK CONFIGURATION

This procedure configures network interfaces for VM instance.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure32: VM Instance Network Configuration

Step	Procedure	Result
1. <input type="checkbox"/>	Login to the OpenStack GUI	



Step	Procedure	Result
2. <input type="checkbox"/>	Login VM instance from Project → Compute → Instances → More → Console	
3. <input type="checkbox"/>	Login to the VM with root user	<pre>hostnameea0c2d9aa8bce login: root password: <root_password></pre>
4. <input type="checkbox"/>	Use netAdm to add device and set ip address (ISO installs only)	<p>NOTE: This step is required only for ISO installs.</p> <pre>[root@ hostnameea0c2d9aa8bce ~]# netAdm add --device=eth0 Interface eth0 added</pre>
5. <input type="checkbox"/>	Set ip address for this interface	<pre>[root@ hostnameea0c2d9aa8bce ~]# netAdm set --device=eth0 --onboot=yes \ --netmask=<netmask> --address=<ip_address> Interface eth0 updated</pre>
6. <input type="checkbox"/>	Add default router	<pre>[root@ hostnameea0c2d9aa8bce ~]# netAdm add --route=default -- device=eth0 \ --gateway=10.240.174.1 Route to eth0 added</pre>
7. <input type="checkbox"/>	Add eth1 interface	<pre>[root@ hostnameea0c2d9aa8bce ~]# netAdm add --device=eth1 Interface eth1 added</pre>
8. <input type="checkbox"/>	Add eth2 interface	<pre>[root@hostnameeb6092a316785 ~]# netAdm add --device=eth2 Interface eth2 added</pre>
THIS PROCEDURE HAS BEEN COMPLETED		



D.8 VIRTUAL IP ADDRESS ASSIGNMENT

This procedure configures a VIP for a virtual machine. Administrative access to the OpenStack controller node is required.

Mark (Ö) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure33: Virtual IP Address Assignment

Step	Procedure	Result									
1. <input type="checkbox"/>	Login to the OpenStack GUI	 <p>The screenshot shows the OpenStack Dashboard login page. The 'Log In' section has a 'User Name' field with 'admin' entered and a 'Password' field with masked characters. A 'Sign In' button is at the bottom right.</p>									
2. <input type="checkbox"/>	1. Select project, (for example: UDR). 2. Select Project → Compute → Instances to show all Instances created under this project:	 <p>The screenshot shows the OpenStack 'Instances' page. The left sidebar has a menu with 'Project', 'Compute', 'Overview', 'Instances' (selected), 'Volumes', 'Images', 'Access & Security', 'Network', 'Orchestration', and 'Object Store'. The main content area shows a table of instances:</p> <table border="1"> <thead> <tr> <th>Instance Name</th> <th>Image Name</th> <th>IP Address</th> </tr> </thead> <tbody> <tr> <td><input type="checkbox"/> int-imi</td> <td></td> <td>• 10.10.2.63</td> </tr> <tr> <td><input type="checkbox"/> pv2kbncmk-qyls-noa</td> <td>UDR-12.4_16.14.0</td> <td>int-xsi1 • 10.10.3.21 EXT-XMI • 10.75.173.233</td> </tr> </tbody> </table>	Instance Name	Image Name	IP Address	<input type="checkbox"/> int-imi		• 10.10.2.63	<input type="checkbox"/> pv2kbncmk-qyls-noa	UDR-12.4_16.14.0	int-xsi1 • 10.10.3.21 EXT-XMI • 10.75.173.233
Instance Name	Image Name	IP Address									
<input type="checkbox"/> int-imi		• 10.10.2.63									
<input type="checkbox"/> pv2kbncmk-qyls-noa	UDR-12.4_16.14.0	int-xsi1 • 10.10.3.21 EXT-XMI • 10.75.173.233									
3. <input type="checkbox"/>	Find the UDR instances	Record the IP addresses of the UDR instances primary XMI network. UDR A: _____ UDR B: _____									

Step	Procedure	Result																																																																	
4. <input type="checkbox"/>	<div>1. Navigate to Project → Orchestration → Stacks</div> <div>2. Select the Stack Name to see more detail</div>																																																																		
5. <input type="checkbox"/>	Select the Resource tab, find the VIP PORT for UDR servers.	 <table><tr><th>Topology</th><th>Overview</th><th>Resources</th><th>Events</th><th>Template</th></tr><tr><th colspan="2">Stack Resource</th><th colspan="3">Resource</th></tr><tr><td colspan="2">OCUDRSITE1_OCUDRB_XMI_PORT</td><td colspan="3">3d3d71b9-dd54-4424-9025-352ee53d2ac4</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRA_XMI_PORT</td><td colspan="3">0afb48ed-b0a1-48f5-a603-00d24f360668</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRB_XMI_PORT</td><td colspan="3">be428e3e-6275-4629-beb3-e5b649ef0942</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRB_XSI2_PORT</td><td colspan="3">451b4d2d-9b48-4c64-8e5f-17804701a6bb</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRB</td><td colspan="3">6e439ff8-620d-4cf2-a9e4-e387c6fa6f2e</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRB_XSI1_PORT</td><td colspan="3">887a2614-432f-44a9-abb2-d1ffc516ad8</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRA_XSI1_PORT</td><td colspan="3">bf6affe8-e720-4f80-b514-16ad7e9df5a6</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRA_XSI2_PORT</td><td colspan="3">bed62056-3b8b-493c-bed7-128dd04acc8f</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRA_XMI_PORT</td><td colspan="3">3c0ce151-c72d-4a07-9df3-646497fa1b3c</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDR_VIP_PORT</td><td colspan="3">0786cf62-3203-46b5-a4f8-beb19cf5f5b7</td></tr><tr><td colspan="2">OCUDRSITE1_OCUDRA</td><td colspan="3">3c1f76d0-4142-4ff1-8d3e-22dba8132b40</td></tr></table>	Topology	Overview	Resources	Events	Template	Stack Resource		Resource			OCUDRSITE1_OCUDRB_XMI_PORT		3d3d71b9-dd54-4424-9025-352ee53d2ac4			OCUDRSITE1_OCUDRA_XMI_PORT		0afb48ed-b0a1-48f5-a603-00d24f360668			OCUDRSITE1_OCUDRB_XMI_PORT		be428e3e-6275-4629-beb3-e5b649ef0942			OCUDRSITE1_OCUDRB_XSI2_PORT		451b4d2d-9b48-4c64-8e5f-17804701a6bb			OCUDRSITE1_OCUDRB		6e439ff8-620d-4cf2-a9e4-e387c6fa6f2e			OCUDRSITE1_OCUDRB_XSI1_PORT		887a2614-432f-44a9-abb2-d1ffc516ad8			OCUDRSITE1_OCUDRA_XSI1_PORT		bf6affe8-e720-4f80-b514-16ad7e9df5a6			OCUDRSITE1_OCUDRA_XSI2_PORT		bed62056-3b8b-493c-bed7-128dd04acc8f			OCUDRSITE1_OCUDRA_XMI_PORT		3c0ce151-c72d-4a07-9df3-646497fa1b3c			OCUDRSITE1_OCUDR_VIP_PORT		0786cf62-3203-46b5-a4f8-beb19cf5f5b7			OCUDRSITE1_OCUDRA		3c1f76d0-4142-4ff1-8d3e-22dba8132b40		
Topology	Overview	Resources	Events	Template																																																															
Stack Resource		Resource																																																																	
OCUDRSITE1_OCUDRB_XMI_PORT		3d3d71b9-dd54-4424-9025-352ee53d2ac4																																																																	
OCUDRSITE1_OCUDRA_XMI_PORT		0afb48ed-b0a1-48f5-a603-00d24f360668																																																																	
OCUDRSITE1_OCUDRB_XMI_PORT		be428e3e-6275-4629-beb3-e5b649ef0942																																																																	
OCUDRSITE1_OCUDRB_XSI2_PORT		451b4d2d-9b48-4c64-8e5f-17804701a6bb																																																																	
OCUDRSITE1_OCUDRB		6e439ff8-620d-4cf2-a9e4-e387c6fa6f2e																																																																	
OCUDRSITE1_OCUDRB_XSI1_PORT		887a2614-432f-44a9-abb2-d1ffc516ad8																																																																	
OCUDRSITE1_OCUDRA_XSI1_PORT		bf6affe8-e720-4f80-b514-16ad7e9df5a6																																																																	
OCUDRSITE1_OCUDRA_XSI2_PORT		bed62056-3b8b-493c-bed7-128dd04acc8f																																																																	
OCUDRSITE1_OCUDRA_XMI_PORT		3c0ce151-c72d-4a07-9df3-646497fa1b3c																																																																	
OCUDRSITE1_OCUDR_VIP_PORT		0786cf62-3203-46b5-a4f8-beb19cf5f5b7																																																																	
OCUDRSITE1_OCUDRA		3c1f76d0-4142-4ff1-8d3e-22dba8132b40																																																																	

Step	Procedure	Result																								
6. <input type="checkbox"/>	Copy or record the Port ID for UDR	<div><div>TopologyOverviewResourcesEventsTemplate</div><table><thead><tr><th>Stack Resource</th><th>Resource</th></tr></thead><tbody><tr><td>OCUDRSITE1_OCUDRB_XMI_PORT</td><td>3d3d71b9-dd54-4424-9025-352ee53d2ac4</td></tr><tr><td>OCUDRSITE1_OCUDRA_XMI_PORT</td><td>0afb48ed-b0a1-48f5-a603-00d24f360668</td></tr><tr><td>OCUDRSITE1_OCUDRB_XMI_PORT</td><td>be428e3e-6275-4629-beb3-e5b649ef0942</td></tr><tr><td>OCUDRSITE1_OCUDRB_XSI2_PORT</td><td>451b4d2d-9b48-4c54-8e5f-17804701a6bb</td></tr><tr><td>OCUDRSITE1_OCUDRB</td><td>6e439f8b-620d-4cf2-a9e4-e387c6fa6f2e</td></tr><tr><td>OCUDRSITE1_OCUDRB_XSI1_PORT</td><td>887a2614-432f-44a9-abb2-d1ffc516ad8</td></tr><tr><td>OCUDRSITE1_OCUDRA_XSI1_PORT</td><td>bf6affe8-e720-4f80-b514-16ad7e9df5a6</td></tr><tr><td>OCUDRSITE1_OCUDRA_XSI2_PORT</td><td>bed62056-3b8b-493c-bed7-128dd04acc8f</td></tr><tr><td>OCUDRSITE1_OCUDRA_XMI_PORT</td><td>3c0ce151-c72d-4a07-9df3-646497fa1b3c</td></tr><tr><td>OCUDRSITE1_OCUDR_VIP_PORT</td><td>0786cf62-3203-46b5-a4f8-beb19df5f5b7</td></tr><tr><td>OCUDRSITE1_OCUDRA</td><td>3c1f76d0-4142-4ff1-8d3e-22d0a8132b40</td></tr></tbody></table></div>	Stack Resource	Resource	OCUDRSITE1_OCUDRB_XMI_PORT	3d3d71b9-dd54-4424-9025-352ee53d2ac4	OCUDRSITE1_OCUDRA_XMI_PORT	0afb48ed-b0a1-48f5-a603-00d24f360668	OCUDRSITE1_OCUDRB_XMI_PORT	be428e3e-6275-4629-beb3-e5b649ef0942	OCUDRSITE1_OCUDRB_XSI2_PORT	451b4d2d-9b48-4c54-8e5f-17804701a6bb	OCUDRSITE1_OCUDRB	6e439f8b-620d-4cf2-a9e4-e387c6fa6f2e	OCUDRSITE1_OCUDRB_XSI1_PORT	887a2614-432f-44a9-abb2-d1ffc516ad8	OCUDRSITE1_OCUDRA_XSI1_PORT	bf6affe8-e720-4f80-b514-16ad7e9df5a6	OCUDRSITE1_OCUDRA_XSI2_PORT	bed62056-3b8b-493c-bed7-128dd04acc8f	OCUDRSITE1_OCUDRA_XMI_PORT	3c0ce151-c72d-4a07-9df3-646497fa1b3c	OCUDRSITE1_OCUDR_VIP_PORT	0786cf62-3203-46b5-a4f8-beb19df5f5b7	OCUDRSITE1_OCUDRA	3c1f76d0-4142-4ff1-8d3e-22d0a8132b40
Stack Resource	Resource																									
OCUDRSITE1_OCUDRB_XMI_PORT	3d3d71b9-dd54-4424-9025-352ee53d2ac4																									
OCUDRSITE1_OCUDRA_XMI_PORT	0afb48ed-b0a1-48f5-a603-00d24f360668																									
OCUDRSITE1_OCUDRB_XMI_PORT	be428e3e-6275-4629-beb3-e5b649ef0942																									
OCUDRSITE1_OCUDRB_XSI2_PORT	451b4d2d-9b48-4c54-8e5f-17804701a6bb																									
OCUDRSITE1_OCUDRB	6e439f8b-620d-4cf2-a9e4-e387c6fa6f2e																									
OCUDRSITE1_OCUDRB_XSI1_PORT	887a2614-432f-44a9-abb2-d1ffc516ad8																									
OCUDRSITE1_OCUDRA_XSI1_PORT	bf6affe8-e720-4f80-b514-16ad7e9df5a6																									
OCUDRSITE1_OCUDRA_XSI2_PORT	bed62056-3b8b-493c-bed7-128dd04acc8f																									
OCUDRSITE1_OCUDRA_XMI_PORT	3c0ce151-c72d-4a07-9df3-646497fa1b3c																									
OCUDRSITE1_OCUDR_VIP_PORT	0786cf62-3203-46b5-a4f8-beb19df5f5b7																									
OCUDRSITE1_OCUDRA	3c1f76d0-4142-4ff1-8d3e-22d0a8132b40																									
7. <input type="checkbox"/>	Copy or record all required Port IDs for DR Site.	Repeat Step 5 and Step 6 to copy or record the Port ID of both servers: DR-UDR-A and DR-UDR-B. DR-UDR-A: _____ DR-UDR-B _____																								
8. <input type="checkbox"/>	OpenStack Controller node: 1. Access the command prompt. 2. Log into the controller node as a privileged user.	<pre>login as: <usr_name> root@10.250.xx.yy's password: <usr_password> Last login: Mon Jul 30 10:33:19 2012 from 10.25.80.199 [root@control01]#</pre>																								
9. <input type="checkbox"/>	OpenStack Controller node: Initialize environment variables	<pre>controller ~]# source keystone_rc_udrsw</pre>																								

Step	Procedure	Result
10. <input type="checkbox"/>	OpenStack Controller node: Assign VIP by Port IDs	Assign the VIP address to both A and B servers sharing the VIP: <pre>[root@control01 ~(keystone_udrsw)]# openstack floating ip create --port <UDR_VIP_Port_ID> EXT-XMI</pre> For example: <pre>openstack floating ip create --port fc7b8473-b39d-477f-8b2b-7e0a3b45ce5b EXT-XMI</pre>
11. <input type="checkbox"/>	OpenStack Controller node: Repeat if needed	Repeat Step 10 as required for any other server pairs requiring a VIP.
12. <input type="checkbox"/>	OpenStack Controller node: Confirm VIP association	VIP associations may be confirmed with the following command by Port ID: <pre>[root@control01 ~(keystone_udrsw)]# neutron port-show <port_id></pre> See Figure 3 for an example of the output.
THIS PROCEDURE HAS BEEN COMPLETED		

Figure 3 Example port-show output.


Field	Value
admin_state_up	True
allowed_address_pairs	{"ip_address": "10.240.221.36", "mac_address": "fa:16:3e:ce:18:2a"}
binding:host_id	compute05.labafrika
binding:profile	{}
binding:vif_details	{"port_filter": true, "ovs_hybrid_plug": true}
binding:vif_type	ovs
binding:vnictype	normal
device_id	947457b4-46e8-43e7-8f14-79c816388e3d
device_owner	compute:Odds
extra_dhcp_opts	
fixed_ips	{"subnet_id": "23f28095-bdb6-4fab-b13e-281d726ef3eb", "ip_address": "10.240.221.38"}
id	aa14b554-d0a6-413d-b77c-63e11a3c9895
mac_address	fa:16:3e:ce:18:2a
name	
network_id	62027e77-7556-42b2-8070-ffbd61933877
port_security_enabled	True
security_groups	1e4bd44c-9ac2-4cd0-a56b-c094a52830c2
status	ACTIVE
tenant_id	d2fda814485247f795c23b9af2bc2e1c


D.9 GENERATE PRIVATE KEY FOR SSH ACCESS



This procedure is used to generate Private Key to be used for accessing VM instance via SSH.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure34: Generate Private Key for SSH Access

Step	Procedure	Result
1. <input type="checkbox"/>	Launch PuTTYGen	

Step	Procedure	Result
2. <input type="checkbox"/>	<p>Load the key file i.e *.pem generated in D.3 Create Key Pair</p> <p>Click OK</p>	

Step	Procedure	Result
3. <input type="checkbox"/>	<p>Save the Private Key by clicking Save Private Key</p> <p>Click Yes</p> <p>Click Save</p>	 
THIS PROCEDURE HAS BEEN COMPLETED		


D.10 ACCESSING VM INSTANCE USING SSH


This procedure is used to access VM instance via SSH. This procedure assumes following:


- Network configuration on VM instance is complete or floating IPs have been associated with VM instance
- Private Key has been generated as per D.9 Generate Private Key for SSH Access

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure35: SSH Access to VM Instance

Step	Procedure	Result
1. <input type="checkbox"/>	Launch Putty Specify IP Address of the VM Instance	

Step	Procedure	Result
2. <input type="checkbox"/>	<p>Navigate to SSH → Auth</p> <p>Select the *.ppk file generated by D.9 Generate Private Key for SSH Access</p>	

Step	Procedure	Result
3. <input type="checkbox"/>	<p>From Session Category, click Open to launch the SSH connection</p> <p>Specify username admusr when prompted</p>	 <p>THIS PROCEDURE HAS BEEN COMPLETED</p>

D.11 CLOBBER THE DATABASE ON VM INSTANCE

This procedure clobbers the database on VM instance.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure36: Clobber Database on VM Instance

Step	Procedure	Result
1. <input type="checkbox"/>	Login to the VM with admusr via SSH as per D.10 Accessing VM Instance using SSH	<code>hostnameea0c2d9aa8bce login: admusr</code>
2. <input type="checkbox"/>	Switch to root user	<code># su - root password: <root_password></code>



Step	Procedure	Result
3. <input type="checkbox"/>	Run prod.clobber on the created instances	<pre> [root@hostname2c6772f9819e ~]# prod.clobber ...prod.clobber (RUNID=00)... ...getting current state... Current state: X (product under procmgr) WARNING: ABOUT TO DESTROY ALL PRODUCT DISK FILES !!!! Are you sure? [enter Y or N] y ...setting state 0... ...waiting for state 0... Current state is 0 ...taking down processes... processes down ...removing existing IPC resources... + md_ipcrm ... 852 resources ...clobbering runenv files... + rm -rf /var/TKLC/run/db/run </pre>
4. <input type="checkbox"/>	Run prod.start on instance After start, use pl to check process status, after first start, only a few processes start	<pre> [root@hostname2c6772f9819e ~]# prod.start_ + lgt -liddioXML -DataDictPart > /var/TKLC/run/db/DataDictPart/20160527.055813.5460.DataDictPart.tmp + edd.op --install --must-eq-current /var/TKLC/run/db/DataDictPart/20160527.055813.5460.DataDictPart.tmp created: 20160527.055813.5460.DataDictPart.xml ...starting procmgr ... [root@hostname2c6772f9819e ~]# pl \$ pid procTag \$1 stat spawnTime N cmd Z 29470 cnha Up 05/27 01:59:29 1 cnha Z 29471 cnsoapa Up 05/27 01:59:29 1 cnsoapa Z 29473 idbsvc Up 05/27 01:59:29 1 idbsvc -H10 -HE204 -D40 -DE820 -U1 -S2 -L1 Z 29475 inetmerge Up 05/27 01:59:29 1 inetmerge Z 29477 raclerk Up 05/27 01:59:29 1 raclerk -r 3000 Z 29478 re.portnap Up 05/27 01:59:29 1 re.portnap -c100 </pre>
5. <input type="checkbox"/>	Run prod.start -i again on instance, this time, all processes started	<pre> [root@hostname2c6772f9819e ~]# prod.start ...prod.start (RUNID=00)... ...getting current state... Current state: Z (product under procmgr) ...setting state X... ...waiting for state [X00]... Current state is X [root@hostname2c6772f9819e ~]# pl \$ pid procTag \$1 stat spawnTime N cmd X 29586 lmysqld Up 05/27 02:00:25 1 lmysqld.start -force X 29587 ProcWatch Up 05/27 02:00:25 1 ProcWatch -L X 29589 apuSoapServer Up 05/27 02:00:25 1 tCH00SIGCHK=1 apuSoapServer X 29470 cnha Up 05/27 01:59:29 1 cnha X 29591 cnplatalarm Up 05/27 02:00:25 1 cnplatalarm X 29593 cnsnmpsa Up 05/27 02:00:25 1 cnsnmpsa -R 1.3.6.1.4.1.323.5.3.32.1 X 29471 cnsoapa Up 05/27 01:59:29 1 cnsoapa X 29608 eclipseHelp Up 05/27 02:00:25 1 eclipseHelp X 29594 guiReqMapLoad Up 05/27 02:00:25 1 guiReqMapLoad X 29473 idbsvc Up 05/27 01:59:29 1 idbsvc -H10 -HE204 -D40 -DE820 -U1 -S2 -L1 X 29475 inetmerge Up 05/27 01:59:29 1 inetmerge X 29596 inetrep Up 05/27 02:00:25 1 inetrep X 29598 nkdbhooks Up 05/27 02:00:25 1 nkdbhooks X 29601 oanpAgent Up 05/27 02:00:25 1 oanpAgent X 29603 pn.watchdog Up 05/27 02:00:25 1 pn.watchdog X 29477 raclerk Up 05/27 01:59:29 1 raclerk -r 3000 X 29478 re.portnap Up 05/27 01:59:29 1 re.portnap -c100 X 29605 statclerk Up 05/27 02:00:25 1 statclerk -s -0 X 29607 vipmgr Up 05/27 02:00:25 1 vipmgr </pre>
THIS PROCEDURE HAS BEEN COMPLETED		


D.12 ASSOCIATING FLOATING IPS

This procedure associates Floating IP to VM instance.

Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.

Procedure37: Associate Floating IP

Step	Procedure	Result
1. <input type="checkbox"/>	Login to the OpenStack GUI	 <p>The screenshot shows the OpenStack Dashboard login page. The 'Log In' section has a 'User Name' field containing 'admin' and a 'Password' field with masked characters. A 'Sign In' button is at the bottom right.</p>
2. <input type="checkbox"/>	Login to the VM instance by navigating to Project → Instances → More → Associate Floating IP	 <p>The screenshot shows the 'Instances' table in the OpenStack dashboard. The 'Actions' column for a VM instance is expanded, showing a list of actions. The 'Associate Floating IP' option is highlighted with a red box. The 'Time since created' column shows '4 hours, 12 minutes' for the selected instance.</p>

Step	Procedure	Result
3. <input type="checkbox"/>	Select the IP Addresss and Port to be associated Click Associate	
THIS PROCEDURE HAS BEEN COMPLETED		

Appendix E. Same Network Element and Hardware Profiles

In order to enter all the network information for a network element into an Appworks-based system, a specially formatted XML file needs to be updated with the required network information. The network information is needed to configure both the NOAMP and any SOAM Network Elements.

It is expected that the maintainer/creator of this file has networking knowledge of this product and the site at which it is being installed. The following is an example of a Network Element XML file.

The SOAM Network Element XML file needs to have same network names for the networks as the NOAMP Network Element XML file has. It is easy to accidentally create different network names for NOAMP and SOAM Network Element, and then the mapping of services to networks is not possible.

Example Network Element XML file:

Example NOAMP Network Element XML	Example SOAM Network Element XML
<pre><?xml version="1.0"?> <networkelement> <name>NO_UDR_NE</name> <networks> <network> <name>XMI</name> <vlanId>3</vlanId> <ip>10.2.0.0</ip> <mask>255.255.255.0</mask> <gateway>10.2.0.1</gateway> <isDefault>true</isDefault> </network> <network> <name>IMI</name> <vlanId>4</vlanId> <ip>10.3.0.0</ip> <mask>255.255.255.0</mask> <nonRoutable>true</nonRoutable> </network> </networks> </networkelement></pre>	<pre><?xml version="1.0"?> <networkelement> <name>SO_UDR_NE</name> <networks> <network> <name>XMI</name> <vlanId>3</vlanId> <ip>10.2.0.0</ip> <mask>255.255.255.0</mask> <gateway>10.2.0.1</gateway> <isDefault>true</isDefault> </network> <network> <name>IMI</name> <vlanId>4</vlanId> <ip>10.3.0.0</ip> <mask>255.255.255.0</mask> <nonRoutable>true</nonRoutable> </network> </networks> </networkelement></pre>

NOTE: Do not include the XSI networks in a Network Element XML file.

The server hardware information is needed to configure the Ethernet interfaces on the servers. This server hardware profile data XML file is used for Appworks deployments. It is supplied to the NOAMP server so that the information can be pulled in by Appworks and presented in the GUI during server configuration. Figure 4 is an example of a server hardware profile XML file stored in the `/var/TKLC/appworks/profiles` directory.

Figure 4: Example Server Hardware Profile XML—Virtual Guest

```
<profile>
  <serverType>Cloud UDR</serverType>
  <available>
    <device>eth0</device>
    <device>eth1</device>
    <device>eth2</device>
    <device>eth3</device>
  </available>
  <devices>
    <device>
      <name>eth0</name>
      <type>ETHERNET</type>
    </device>
    <device>
      <name>eth1</name>
      <type>ETHERNET</type>
    </device>
    <device>
      <name>eth2</name>
      <type>ETHERNET</type>
    </device>
    <device>
      <name>eth3</name>
      <type>ETHERNET</type>
    </device>
  </devices>
</profile>
```

Appendix F. High Availability Configurations

VM Name	Non HA		HA			
	Min number of VMs	Max number of VMs	Min number of VMs	Max number of VMs	HA config	Affinity
UDR	1	2	2	2	Active-Standby	Anti-affinity. UDRs must be hosted on different servers

NOTES:

Non-HA configuration is for labs and demonstrations only.

The UDR VMs raise HA alarms when deployed as singletons. For this reason, standby VMs are often deployed even in non-HA labs.

The HA Max number of VMs was used for performance testing

For Geo-Diverse configurations, DR site VMs must be hosted at a geo-diverse location from the first site

Appendix G. Resource Profile

VM Name VM Purpose		vCPUs						RAM(GB)						Storage(GB)					
		Small	Medium	vEIR	vmNP	v300M_EIR	vFABR-Large	Small	Medium	vEIR	vmNP	v300M_EIR	vFABR-Large	Small	Medium	vEIR	vmNP	v300M_EIR	vFABR-Large
UDR	Network Operation, Administration, Maintenance, And Provisioning	6	12	18	32	32	56	16	32	70	128	140	256	270	450	450	850	850	850

NOTES:

-
-
- Lab numbers are for demonstration of functionality only and can only support 100/s SOAP provisioning with 2k/s traffic.
- 1:1vCPU to CPU ratio based on Intel(R) Xeon(R) CPU E5-2699 v3 @ 2.30GHz
- vmNP flavor must be used for Signaling Security Application(For vSTP and DSA).

Subscriber Capacity:

Deployment Type	Flavor Type	Max Subscriber(In Millions)
MNP	vmNP	250
EIR	vEIR	120
300M_EIR	v300M_EIR	300

Appendix H. Network Device Assignments

		Interface Assignment						
Product	Role	Control	Platform Management	OAMP (XMI)	Local (IMI)	Signaling A (XSI1)	Signaling B (XSI2)	NetBackup
Platform	TVOE							
	PMAC							
UDR	NOAMP			eth0	eth1	eth2		

Legend				
Mandatory	Not Applicable	Unsupported	Optional	Suggested

Appendix I. Network and Port Information

Network	Description	Also Known As	Optional/ Mandatory	Type	IPv6	VMs using	Services	Notes
OAMP	Routable operations, administration, maintenance and provisioning flows	External Management Interface (XMI)	Mandatory	External	No	All	AppWorks SOAP Server (TCP/18081) AppWorks GUI (TCP/443, TCP/80) AppWorks File Transfer (TCP/22) AppWorks Online Help (TCP/8081) DNS (TCP/53, UDP/53) NTP (UDP/123) SNMP gets (UDP/161) SSH (TCP/22) X11 Forwarding (TCP/6010) RPC Bind (TCP/111) Prov REST (TCP/8787) Prov SOAP (TCP/62001) Prov GUI (TCP/16530) Prov Import (TCP/16531) Prov OnDemand (TCP/16532) Prov Notifications (TCP/16535)	Local services may also run on OAM network when the target is outside the Network Element. ComAgent Services may run over OAMP Network between Network Elements unless configured to run on Signaling A.

Local	Application internal communications	Internal Management Interface (IMI)	Mandatory	Internal	No	All	COMCOL SOAP Server (TCP/15360) COMCOL Merging (TCP/16878) COMCOL Replication (TCP/17398,17399, TCP/17400) COMCOL HA (TCP/17401,17402,17406 UDP/17401) ComAgent EventTransfer (TCP/16529) ComAgent EventTransfer Alert (TCP/16541) Imysql (TCP 15616)	OAM services may be configured to run on the Local network when the destination is inside the Network Element.
Signaling A	Application external communications	External Signaling Interface 1 (XSI1)	Mandatory	External	Yes	MP, Optional:NOAMP	Diameter (TCP/3868, SCTP/3868)	Signal A network may also be configured to host ComAgent services when the target is outside the Network Element.
Signaling B	Application external communications	External Signaling Interface 2 (XSI2)	Optional	External	Yes	MP	Diameter (TCP/3868, SCTP/3868)	
Port values are configurable (default values a listed)								

Appendix J. Install UDR on Oracle Linux OS via KVM

Important: *The content of this appendix is for informational purposes only.*

This procedure installs UDR configuration on Oracle Linux OS with direct KVM as hypervisor.


NOTE:


- This installation procedure only applies when installing UDR on Oracle Linux OS via direct KVM
- For the Oracle Linux OS, Oracle Linux 7.2 GA release is used and verified OK.


Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.


Procedure38: Install UDR on Oracle Linux/KVM


Step	Procedure	Result
1. <input type="checkbox"/>	For each Oracle X5-2 RMS, mount virtual media contains Oracle Linux OS software	Follow steps defined in Appendix C.3 Mounting Virtual Media on Oracle RMS Server of Error! Reference source not found.. to mount the Oracle Linux OS software ISO.


Step	Procedure	Result
2. <input type="checkbox"/>	For each Oracle X5-2 RMS, reboot the host.	<p>1. Login to the X5-2 iLo GUI browser page and launch remote console</p> <p>2. In ILO GUI, navigate to Host Management → Power Control</p> <p>3. Select Reset</p> <p>4. Click Save to reboot host.</p> <p>In remote console window, you see that the host is rebooting. Wait for the reboot to complete.</p>  <p>The screenshot shows two parts of the process. The top part is the 'Power Control' page in the iLo GUI, which includes instructions on how to use the 'Actions' drop-down list for power management. The 'Settings' section shows 'Host is currently on.' and a 'Reset' button selected in the drop-down menu. The bottom part is a remote console window titled 'Oracle(R) Integrated Lights Out Manager Remote System Console Plus - 10.113.65.119'. It displays the BIOS boot screen with the text: 'ORACLE Copyright (C) 2014, Oracle and/or its affiliates. All rights reserved. BIOS Version : 30040200 System is Booting. Please Wait...'</p>


Step	Procedure	Result
3. <input type="checkbox"/>	For each Oracle X5-2 RMS, initiate Oracle Linux Platform installation	<p>After the reboot is complete, the host boots with Oracle Linux installation ISO and the Oracle Linux GUI with the installation option opens.</p> <p>Select Install Oracle Linux 7.x.</p> 


Step	Procedure	Result
4. <input type="checkbox"/>	For each Oracle X5-2 RMS, select Oracle Linux OS language	<div>1. When prompted, select English as Oracle Linux OS language:</div> <div></div> <div>2. Click Continue.</div>


Step	Procedure	Result
5. <input type="checkbox"/>	For each Oracle X5-2 RMS, setup time zone	<p>The next page prompts you for Oracle Linux OS installation required information to start installation.</p>  <ol style="list-style-type: none"> 1. Navigate to LOCALIZATION → DATE & TIME. 2. Set time zone as Americas/New York. 3. Click Done to save the changes and return to the main configuration page.


Step	Procedure	Result
6. <input type="checkbox"/>	<p>For each Oracle X5-2 RMS:</p> <p>Setup installation base environment</p>	<ol style="list-style-type: none"> 1. Navigate to SOFTWARE → SOFTWARE SELECTION menu. 2. Select Server with GUI, and verify that these add-ons are selected: <ul style="list-style-type: none"> - Virtualization Client - Virtualization Hypervisor - Virtualization Tools - Compatibility Libraries  <p>Click Done to save the changes and go back to the main configuration page.</p>


Step	Procedure	Result
7. <input type="checkbox"/>	For each Oracle X5-2 RMS, setup installation destination	<p>1. Navigate to SYSTEM → INSTALLATION DESTINATION menu.</p> <p>2. Select sda and sdb.</p> <p>3. Select Automatically configure partitioning.</p> <p>4. Click Done.</p> 

Step	Procedure	Result
8. <input type="checkbox"/>	For each Oracle X5-2 RMS, review configuration and start to install	<p>Review all information before clicking Begin Installation.</p> <p>(You do not need to configure the network at this time, network configuration is performed after the Oracle Linux OS is installed.)</p> 

Step	Procedure	Result
9. <input type="checkbox"/>	For each Oracle X5-2 RMS, create login credential	<p>At the same time Oracle Linux installation software is putting files onto the Oracle X5-2 local hard disk, you can configure the root credentials or any other login credentials required.</p> 

Step	Procedure	Result
10. <input type="checkbox"/>	For each Oracle X5-2 RMS, reboot host after installation completed	<p>Wait for the installation to complete.</p>  <p>Click Reboot.</p>

Step	Procedure	Result
11. <input type="checkbox"/>	For each Oracle X5-2 RMS, read and accept the license agreement	<p>After reboot is complete, the license agreement page opens.</p>  <p>1. Select I accept the license agreement.</p> <p>2. Click Finish Configuration.</p> <p>If you are prompted for ULN setting, skip that step.</p>

Step	Procedure	Result
12. <input type="checkbox"/>	For each Oracle X5-2 RMS, verify kernel version and KVM version	<p>Open SSH console window and check following:</p> 
13. <input type="checkbox"/>	For each Oracle X5-2 RMS, change network interface name pattern to ethx	<ol style="list-style-type: none"> Edit /etc/default/grub to append net.ifnames=0 to option GRUB_CMDLINE_LINUX: <pre>[root@udr-x5-2-62-ol7 admusr]# cat /etc/default/grub</pre> <pre>GRUB_TIMEOUT=5 GRUB_DISTRIBUTOR="\$(sed 's, release .*\$,g' /etc/system-release)" GRUB_DEFAULT=saved GRUB_DISABLE_SUBMENU=true GRUB_TERMINAL_OUTPUT="console" GRUB_CMDLINE_LINUX="crashkernel=auto rd.lvm.lv=ol00/root rd.lvm.lv=ol00/swap rhgb quiet net.ifnames=0" GRUB_DISABLE_RECOVERY="true"</pre> Recreate the grub2 config file with following command: <pre># grub2-mkconfig -o /boot/grub2/grub.cfg</pre> Restart host using shutdown -r command and verify that network interface have the ethx name pattern.

Step	Procedure	Result
14. <input type="checkbox"/>	For each Oracle X5-2 RMS, Create bond0 device	<p>1. Create device bond0 configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-bond0</pre> <pre>DEVICE=bond0 TYPE=Bonding BOND_INTERFACES=<nic1>,<nic2> ONBOOT=yes NM_CONTROLLED=no BOOTPROTO=none BONDING_OPTS="mode=active-backup primary=<nic1> miimon=100"</pre> <p>2. Save the file and exit.</p> <p>3. Create device eth0 configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-<nic1></pre> <pre>DEVICE=<nic1> TYPE=Ethernet ONBOOT=yes NM_CONTROLLED=no BOOTPROTO=none MASTER=bond0 SLAVE=yes</pre> <p>4. Save the file and exit.</p> <p>5. Create device eth1 configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-<nic2></pre> <pre>DEVICE=<nic2> TYPE=Ethernet ONBOOT=yes NM_CONTROLLED=no BOOTPROTO=none MASTER=bond0 SLAVE=yes</pre> <p>6. Save the file and exit.</p> <p>7. Bring the devices into service:</p> <pre># ifup <nic1> # ifup <nic2> # ifup bond0</pre>
15. <input type="checkbox"/>	For each Oracle X5-2 RMS, create IMI bridge	<p>1. Create bond0.<imi_vlan> configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-bond0.<imi_vlan></pre> <pre>DEVICE=bond0.<imi_vlan> TYPE=Ethernet BOOTPROTO=none ONBOOT=yes NM_CONTROLLED=no BRIDGE=imi VLAN=yes</pre> <p>2. Create imi device configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-imi</pre> <pre>DEVICE=imi TYPE=Bridge BOOTPROTO=none ONBOOT=yes NM_CONTROLLED=no BRIDGE_INTERFACES=bond0.<imi_vlan></pre> <p>3. Bring the devices into service:</p> <pre># ifup bond0.<imi_vlan> # ifup imi</pre>

Step	Procedure	Result
16. <input type="checkbox"/>	For each Oracle X5-2 RMS, create XMI bridge	<p>1. Create bond0.<xmi_vlan> configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-bond0.<xmi_vlan> DEVICE=bond0.<xmi_vlan> TYPE=Ethernet BOOTPROTO=none ONBOOT=yes NM_CONTROLLED=no BRIDGE=xmi VLAN=yes</pre> <p>2. Create xmi device configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-xmi: DEVICE=xmi TYPE=Bridge BOOTPROTO=none ONBOOT=yes NM_CONTROLLED=no IPADDR=<xmi_ip_addr> NETMASK=<xmi_netmask> NETWORK=<xmi_network> BRIDGE_INTERFACES=bond0.<xmi_vlan></pre> <p>3. Set default route for xmi network:</p> <pre># vim /etc/sysconfig/network-scripts/route-xmi default via <xmi_gateway> table main</pre> <p>4. Bring the devices into service:</p> <pre># ifup bond0.<xmi_vlan> # ifup xmi</pre>

Step	Procedure	Result
17. <input type="checkbox"/>	For each Oracle X5-2 RMS, Create bond1 device	<p>Create device bond1 configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-bond1</pre> <pre>DEVICE=bond1 TYPE=Bonding BOND_INTERFACES=<nic3>,<nic4> ONBOOT=yes NM_CONTROLLED=no BOOTPROTO=none BONDING_OPTS="mode=active-backup primary=<nic3> miimon=100"</pre> <p>Create device eth4 configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-<nic3></pre> <pre>DEVICE=<nic3> TYPE=Ethernet ONBOOT=yes NM_CONTROLLED=no BOOTPROTO=none MASTER=bond1 SLAVE=yes</pre> <p>Create device eth5 configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-<nic4></pre> <pre>DEVICE=<nic4> TYPE=Ethernet ONBOOT=yes NM_CONTROLLED=no BOOTPROTO=none MASTER=bond1 SLAVE=yes</pre> <p>Bring the devices into service:</p> <pre># ifup <nic3> # ifup <nic4> # ifup bond1</pre>

Step	Procedure	Result
18. <input type="checkbox"/>	For each Oracle X5-2 RMS, Create xsi1/xsi2 bridge	<p>Create device bond1.<xsi1_vlan> configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-bond1.<xsi1_vlan></pre> <pre>BOOTPROTO=none VLAN=yes ONBOOT=yes TYPE=Ethernet DEVICE=bond1.<xsi1_vlan> BRIDGE=xsi1 NM_CONTROLLED=no</pre> <p>Create device xsi1 configuration file:</p> <pre># vim /etc/sysconfig/network-scripts/ifcfg-xsi1</pre> <pre>DEVICE=xsi1 TYPE=Bridge BOOTPROTO=none ONBOOT=yes NM_CONTROLLED=no BRIDGE_INTERFACES=bond1.<xsi1_vlan></pre> <p>Bring the devices into service:</p> <pre># ifup xsi1 # ifup bond1.<xsi1_vlan></pre> <p>Perform similar operations to create network devices for xsi2.</p>
19. <input type="checkbox"/>	For each Oracle X5-2 RMS, set the host name	<p>Rename host by modifying /etc/hostname file:</p> <pre>[root@localhost network-scripts]# cat /etc/hostname</pre> <pre>udr-x5-2-62-017</pre> <p>Review host name change with following command:</p> <pre>[root@localhost network-scripts]# hostnamectl status</pre> <pre>Static hostname: udr-x5-2-62-017 Icon name: computer-server Chassis: server Machine ID: 17980a78ef7d440ca5a6900768903795 Boot ID: a2a5a649eea14d8ab7534aec962c6782 Operating System: Oracle Linux Server 7.2 CPE OS Name: cpe:/o:oracle:linux:7:2:server Kernel: Linux 3.8.13-98.7.1.el7uek.x86_64 Architecture: x86-64</pre>

Step	Procedure	Result
20. <input type="checkbox"/>	For each Oracle X5-2 RMS, set the NTP service	<p>Modify /etc/chrony.conf, comment out all server * entries and append your NTP server IP to the list with prepending server text:</p> <pre># Use public servers from the pool.ntp.org project. # Please consider joining the pool (http://www.pool.ntp.org/join.html). #server 0.rhel.pool.ntp.org iburst #server 1.rhel.pool.ntp.org iburst #server 2.rhel.pool.ntp.org iburst #server 3.rhel.pool.ntp.org iburst server 144.25.255.140</pre> <p>Force ntp to sync with the added server:</p> <pre># ntpdate 144.25.255.140 # timedatectl</pre> <p>Verify time synced:</p> <pre>[root@udr-x5-2-62 log]# chronyc tracking</pre> <pre>Reference ID : 144.25.255.140 (144.25.255.140) Stratum : 3 Ref time (UTC) : Mon Feb 29 06:06:44 2016 System time : 1.692247748 seconds slow of NTP time Last offset : -3.862722397 seconds RMS offset : 3.862722397 seconds Frequency : 0.000 ppm fast Residual freq : -93.109 ppm Skew : 1000000.000 ppm Root delay : 0.178002 seconds Root dispersion : 30.041723 seconds Update interval : 0.0 seconds Leap status : Normal</pre>
21. <input type="checkbox"/>	For each Oracle X5-2 RMS: Create /home/ova dir	<pre>[root@pc9112020 ~]# mkdir -p /home/ova [root@pc9112020 ~]# cd /home/ova</pre>
22. <input type="checkbox"/>	Transfer OVA file this dir using sftp tool	<pre>[root@pc12107008 ova]# ll total 12322888 -rw-r--r--. 1 root root 1047767040 May 2 00:51 UDR-12.5.1.0.0_17.7.0.ova</pre>
23. <input type="checkbox"/>	Untar this ova file	<pre>[root@pc9112020 ova]# tar xvf UDR-12.5.1.0.0_17.7.0.ova UDR-17_7_0.ovf UDR-17_7_0.mf UDR-17_7_0.vmdk</pre>
24. <input type="checkbox"/>	Convert this vmdk	<pre>[root@pc9112020 ova]# qemu-img convert -O qcow2 DR- UDR-12.5.1.0.0_17.7.0.ova.vmdk UDRNO-17_7_0.qcow2</pre>

Step	Procedure	Result
	file to qcow2 file	
25. <input type="checkbox"/>	Copy the qcow2 files for SO and MP	<pre>[root@pc9112020 ova]# cp UDRNO-17_7_0.qcow2 UDRSO-17_7_0.qcow2 [root@pc9112020 ova]# cp UDRNO-17_7_0.qcow2 UDRMP-17_7_0.qcow2</pre>
26. <input type="checkbox"/>	Configure storage for corresponding qcow2 files	<p>Configure storage qcow2 files as per corresponding VMs. Refer Appendix G to get the required storage.</p> <p>Run the following command for each VM to set the storage:</p> <pre>qemu-img resize <NO_qcow2_filename>.qcow2 <storage_in_gigabytes>G</pre> <p>Run the command for a VM if storage required is greater than 60G. You do not have to run this command if the storage required is 60G or less.</p> <p>For example, if resource profile is EIR and VM is UDR, the storage required is 400G. The command in that case is:</p> <pre>qemu-img resize UDRNO-17_7_0.qcow2 400G</pre>
27. <input type="checkbox"/>	Create UDR VMs. Repeat this step for each VM.	<p>Create UDR VMs: NO, SO and MP using appendix below. Repeat the below procedure for each VM</p> <p>Appendix J Install UDR on Oracle Linux OS via KVM</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR</p>
28. <input type="checkbox"/>	For each UDR VMs: Add the network device	<p>Login to each VM created and add the network devices:</p> <p>UDR:</p> <pre># netAdm add -device=eth0 # netAdm add -device=eth1 # netAdm add -device=eth2</pre> <p>NOTE: eth0 is XMI, eth1 is IMI and eth2 is XSI1 and eth3 is XSI2 (create eth3 if XSI2 is required).</p>
29. <input type="checkbox"/>	For each UDR VMs: Configure XMI network address	<p>Set XMI network address for each UDR VM:</p> <pre># netAdm set --device=eth0 --onboot=yes --netmask=<XMI_netmask> --address=<XMI_network_address> # netAdm add --device=eth0 --route=default --gateway=<XMI_gateway></pre>
30. <input type="checkbox"/>	For each UDR VMs: Configure NTP service	<p>Use Step 5 to 6 of Appendix L.6 Configure TVOE Server (Hostname, Time Zone, SNMP, NTP, etc) in [2] to configure NTP service for each VM.</p>
31. <input type="checkbox"/>	Extend VM Instance volume	<p>Extend volumes for various VM Instances depending on flavor following:</p> <p>Appendix D.6 Extend VM Instance Volume Size</p> <p>Mark the check box as addition is completed for each server.</p> <p><input type="checkbox"/> UDR-A <input type="checkbox"/> UDR-B</p>
THIS PROCEDURE HAS BEEN COMPLETED		

Appendix K. My Oracle Support

My Oracle Support (<https://support.oracle.com>) is your initial point of contact for all product support and training needs. A representative at Customer Access Support (CAS) can assist you with My Oracle Support registration.

Call the CAS main number at 1-800-223-1711 (toll-free in the US), or call the Oracle Support hotline for your local country from the list at <http://www.oracle.com/us/support/contact/index.html>. When calling, make the selections in sequence on the Support telephone menu:

1. Select **2** for New Service Request.
2. Select **3** for Hardware, Networking and Solaris Operating System Support.
3. Select one of the following options:
 - o For Technical issues such as creating a Service Request (SR), Select **1**.
 - o For Non-technical issues such as registration or assistance with My Oracle Support, Select **2**.

You are connected to a live agent who can assist you with My Oracle Support registration and opening a support ticket.

My Oracle Support is available 24 hours a day, 7 days a week, 365 days a year.

Appendix L. Locate Product Documentation on the Oracle Help Center Site

Oracle Communications customer documentation is available on the web at the Oracle Help Center (OHC) site, <http://docs.oracle.com>. You do not have to register to access these documents. Viewing these files requires Adobe Acrobat Reader, which can be downloaded at <http://www.adobe.com>.

1. Access the Oracle Help Center site at <http://docs.oracle.com>
2. Click **Industries**.
3. Under the Oracle Communications subheading, click the **Oracle Communications documentation** link.
4. The Communications Documentation page displays. Most products covered by these documentation sets appear under the headings Network Session Delivery and Control Infrastructure or Platforms.
5. Click your Product and then the Release Number.
6. A list of the documentation set for the selected product and release displays.
7. To download a file to your location, right-click the **PDF** link, select **Save target as** (or similar command based on your browser), and save to a local folder.

Appendix M. Create and install UDR VM via KVM GUI

IMPORTANT: The content of this appendix is for informational purposes only.

This procedure installs UDR VMs NO, SO and MP using KVM GUI.


NOTE: This procedure needs to be done for each VM: NO, SO and MP


Requirements:



- [Appendix J Install UDR on Oracle Linux OS via KVM](#) Steps: 1 to 25 must be complete.


Mark (✓) each step as it is completed. Boxes have been provided for this purpose by each step number.


Procedure39: Create and Install UDR VMs via KVM GUI


Step	Procedure	Result
1. <input type="checkbox"/>	Login to the host machine and open the Virtual Machine Manager	<p>Login to the host machine which has Oracle Linux installed and open the Virtual Machine Manager via command-line using <code>virt-manager</code> command.</p> <p>NOTE: Verify that X11 forwarding is enabled before running the <code>virt-manager</code> command.</p> 

Step	Procedure	Result
2. <input type="checkbox"/>	Create a Virtual Machine using the Virtual Manager GUI	<p data-bbox="500 163 764 195">On Virtual Manager GUI,</p> <ol data-bbox="500 212 967 275" style="list-style-type: none">1. Navigate to File → New Virtual Machine.2. Select Import existing disk image. 

Step	Procedure	Result
3. <input type="checkbox"/>	Select the image file	<p>Select the qcow2 from the location: <code>/home/ova</code> (as done Steps 24 and 25 in Appendix J) by browsing the location and clicking Forward</p> 
4. <input type="checkbox"/>	Select RAM and vCPUs for VM	<p>For each VM, select the RAM and vCPUs as per the required resource profile. Refer to Appendix G. Click Forward.</p> 

Step	Procedure	Result
5. <input type="checkbox"/>	Verify and customize VM	<p>Update the VM name and select Customize configuration before install.</p> <p>In Network selection, select XMI bridge and click Finish:</p> 

Step	Procedure	Result
6. <input type="checkbox"/>	Customize the network configuration	<p>On the next screen, click Add Hardware. Under Network, select the IMI bridge.</p> <ul style="list-style-type: none"> • For NO and SO, select IMI bridge only. • For MP, add XSI1 along with IMI by repeating this step. <p>Click Finish.</p> 

Step	Procedure	Result
7. <input type="checkbox"/>	Verify and begin installation	<p>After adding all bridges, verify and begin the VM installation:</p>  <p>THIS PROCEDURE HAS BEEN COMPLETED</p>


Appendix N. Orchestrating UDR Via OSM

Pre-requisites:

- OSM Release Two must be successfully installed.
- A standalone Juju server must be successfully bootstrapped .


N.1 CONFIGURE OPENSTACK VIM TO RUN WITH OSM

On the OSM GUI, navigate to the Accounts tab and click **Add VIM Account**. Enter the OpenStack VIM details and add the VIM account.

Procedure	Result
Add the VIM details on the Account → VIM ACCOUNTS on OSM GUI.	 <p>The screenshot shows the OSM GUI 'ACCOUNTS' page. On the left, there are three sections: 'VIM ACCOUNTS' with an 'ADD VIM ACCOUNT' button, 'SDN ACCOUNTS' with an 'ADD SDN ACCOUNT' button, and 'CONFIG AGENT ACCOUNTS' with an 'ADD CONFIG AGENT ACCOUNT' button. The 'VIM ACCOUNTS' section lists 'MRV X5-2 CLOUD 2' with a green status indicator. The right pane displays the 'UPDATE ACCOUNT DETAILS' form for the selected 'MRV X5-2 Cloud 2' account, which is identified as an 'OpenStack' account. The form includes fields for KEY *, SECRET *, AUTHENTICATION URL *, TENANT *, MANAGEMENT NETWORK *, FLOATING IP POOL NETWORK NAME, USER DOMAIN, PROJECT DOMAIN, and REGION. The 'SUCCESS' message is visible under 'CONNECTION STATUS'. At the bottom of the form are buttons for 'REMOVE ACCOUNT', 'CANCEL', and 'UPDATE'.</p>

N.2 CONFIGURE CONFIG AGENT ACCOUNT (JUJU SERVER)

Add the details of standalone Juju server as a Config Agent account in order to enable OSM to communicate with Juju Server. On the OSM GUI, navigate to Accounts tab and **Add Config Agent Account**. A screen like the one below displays. Enter in the Juju Server details and add the account.


Procedure	Result
<p>Add the CONFIG AGENT (Juju) account details in the Account → CONFIG AGENT ACCOUNTS on OSM GUI.</p>	 <p>The screenshot shows the OSM GUI 'ACCOUNTS' page. The left sidebar has tabs for 'ACCOUNTS', 'CONFIG', 'LAUNCHPAD', and 'CATALOG'. The main content area is titled 'ACCOUNTS' and includes a 'CHECK ALL CONNECTIVITY STATUS' button. Under 'VIM ACCOUNTS', there is an entry for 'MRV X5-2 CLOUD 2' with an 'ADD VIM ACCOUNT' button. Under 'SDN ACCOUNTS', there is an 'ADD SDN ACCOUNT' button. Under 'CONFIG AGENT ACCOUNTS', there is an entry for 'OSMJUJU' with a green status dot and an 'ADD CONFIG AGENT ACCOUNT' button. The 'OSMJUJU' account is selected, and the 'UPDATE ACCOUNT DETAILS' form is displayed. The form fields are: IP ADDRESS * (10.75.173.185), PORT (17070), USERNAME (admin), and SECRET (admin). The 'CONNECTION STATUS' shows 'SUCCESS' with a 'REFRESH STATUS' button. At the bottom, there are buttons for 'REMOVE ACCOUNT', 'CANCEL', and 'UPDATE'.</p>



N.3 BUILD AND DEPLOY UDR NSD/VNFD PACKAGE


Build and deploy scripts must be run in order to upload UDR NSDs and VNFDs to OSM.


Procedure 11 SSH Logon to Juju Server and fetch build and deploy source scripts



Step	Procedure	Result
1. <input type="checkbox"/>	SSH Logon to Juju server and fetch the build and deploy source scripts	<p>1. Copy the qcow2 file made from the ova file of UDR image to the Juju server.</p> <p>2. Run the following commands:</p> <pre>\$ sudo guestmount -a UDR-12.5.1.0.0_17.7.0.qcow2 -m /dev/mapper/vgroot-plat_usr /mnt</pre> <pre>\$ sudo cp /mnt/TKLC/udr/cloud/OSM-support.tar.gz ./</pre> <pre>\$ sudo guestunmount /mnt</pre> <p>3. These commands extract osm-supprt.tar.gz file from qcow2 image</p> <p>4. Untar the file to osm-support directory</p> <p>Copied Image on Juju Server:</p> <pre>ubuntu@edward-juju-server:~\$ ls -l UDR-12.4.0.0.0_16.13.0.qcow2 -rw-r--r-- 1 ubuntu ubuntu 4345757696 Jan 23 09:57 UDR-12.4.0.0.0_16.13.0.qcow2 ubuntu@edward-juju-server:~\$</pre> <p>Extracted osm-support directory from qcow2 Image</p> <pre>ubuntu@edward-juju-server:~\$ cd osm-support/ ubuntu@edward-juju-server:~/osm-support\$ ls build build.sh charms deploy.sh doc nsd vnfd ubuntu@edward-juju-server:~/osm-support\$</pre>
2. <input type="checkbox"/>	<p>Navigate to OSM-Support directory and Run the build script</p> <pre>\$./build.sh</pre> <p>NOTE: Monitor the console output to verify that the build script completed successfully</p>	<pre>ubuntu@edward-juju-server:~/osm-support\$./build.sh ocudr_soa_2k_vnf/ ocudr_soa_2k_vnf/ocudr_soa_2k_vnfd.yaml ocudr_soa_2k_vnf/README ocudr_soa_2k_vnf/icons/ ocudr_soa_2k_vnf/icons/oracle-64.png ocudr_soa_2k_vnf/checksums.txt ocudr_soa_2k_vnf/cloud_init/ ocudr_soa_2k_vnf/cloud_init/ocudr_soa_2k_vnfd-VM.init ocudr_sob_2k_vnf/ ocudr_nob_12_5k_vnf/cloud_init/ocudr_nob_12_5k_vnfd-VM.in build: Composing into /home/ubuntu/osm-support/charms build: Destination charm directory: /home/ubuntu/osm-suppo nfaproxyd build: Processing layer: layer:basic build: Processing layer: layer:sshproxy build: Processing layer: layer:vnfproxy build: Processing layer: nfaproxyd (from charms/nfaproxyd proof: I: Includes template icon.svg file. proof: W: Includes template README.ex file proof: W: README.ex includes boilerplate: Step by step in g the charm: proof: W: README.ex includes boilerplate: You can then br address to configure the service. proof: W: README.ex includes boilerplate: - Upstream mail t information proof: W: README.ex includes boilerplate: - Feel free to useful for users proof: I: all charms should provide at least one thing</pre>


Step	Procedure	Result
		<pre> ocudr_12_5k_level1_ns/ ocudr_12_5k_level1_ns/README ocudr_12_5k_level1_ns/icons/ ocudr_12_5k_level1_ns/icons/oracle-64.png ocudr_12_5k_level1_ns/ocudr_12_5k_level1_nsd.yaml ocudr_12_5k_level1_ns/checksums.txt ocudr_12_5k_level2_ns/ ocudr_12_5k_level2_ns/README ocudr_12_5k_level2_ns/icons/ ocudr_12_5k_level2_ns/icons/oracle-64.png ocudr_12_5k_level2_ns/checksums.txt ocudr_12_5k_level2_ns/ocudr_12_5k_level2_nsd.yaml ubuntu@edward-juju-server:~/osm-support\$ </pre>
3. <input type="checkbox"/>	<p>After the build script completes, run the deploy script inside OSM-support directory</p> <p>Pre-requisite: OSM host IP is required to run <code>deploy.sh</code>. Open the deploy script with an editor and change the env variable of <code>OSM_HOSTNAME</code> to your OSM host IP before running <code>deploy.sh</code>.</p> <pre>\$. /deploy.sh</pre>	<pre> ubuntu@edward-juju-server:~/osm-support\$./deploy.sh failed to delete vnfd ocudr_noa_2k_vnfd failed to delete vnfd ocudr_nob_2k_vnfd failed to delete vnfd ocudr_soa_2k_vnfd failed to delete vnfd ocudr_sob_2k_vnfd failed to delete vnfd ocudr_mp1_2k_vnfd failed to delete vnfd ocudr_mp2_2k_vnfd </pre>
4. <input type="checkbox"/>	<p>Logon to OSM GUI, verify that UDR NSD/VNFD has been uploaded successfully:</p>	

Step	Procedure	Result
		
5. <input type="checkbox"/>	<p>Optional Step: Change UDR image name</p> <ol style="list-style-type: none"> 1. Open The OSM GUI and select CATALOG. <p>Follow the steps in the image to change UDR Image Name:</p> <ol style="list-style-type: none"> 2. Double click VNFD to open edit pane 3. Double click VDU to edit its properties 4. Change the image name 5. Click Update to save changes <p>NOTE: UDR image name must match the one you intend to use and an image with the same name is available on openstack</p>	

Step	Procedure	Result
6. <input type="checkbox"/>	<div>1. Open the OSM GUI.</div> <div>2. Click LAUNCHPAD</div> <div>3. Click Instantiate Service</div> <div>4. Select UDR_2k_nsd.</div> <div>5. Click Next.</div>	<div></div>

Step	Procedure	Result
7. <input type="checkbox"/>	Enter the required information and click Launch , enter the instance name.	<p>NOTE: Enter the VLD:*_network: VLD:IMI_NETWORK → int-imi, VLD:XSI1_NETWORK → int-xsi1, VLD:XSI2_NETWORK → int-xsi2</p>  <p>The screenshots show the 'LAUNCHPAD: INSTANTIATE' interface. The top screenshot displays the 'INPUT PARAMETERS' section with the following settings:</p> <ul style="list-style-type: none"> VLD: IMI_NETWORK: SPECIFY VLD PARAMETERS <ul style="list-style-type: none"> <input checked="" type="radio"/> VIM NETWORK NAME <input type="radio"/> NONE NETWORK NAME: int-imi VLD: XSI1_NETWORK: SPECIFY VLD PARAMETERS <ul style="list-style-type: none"> <input checked="" type="radio"/> VIM NETWORK NAME <input type="radio"/> NONE NETWORK NAME: int-xsi1 VLD: XSI2_NETWORK: SPECIFY VLD PARAMETERS <ul style="list-style-type: none"> <input checked="" type="radio"/> VIM NETWORK NAME <input type="radio"/> NONE NETWORK NAME: int-xsi2 <p>The bottom screenshot shows the same interface with the 'LAUNCH' button highlighted.</p>

Step	Procedure	Result
8. <input type="checkbox"/>	Wait for the instantiation operation to complete	<p>NOTE: In OSM Release 2, UDR NSR information may be incorrectly shown on GUI.</p> <p>To verify the status, logon to the Juju server and issue the command</p> <pre>\$watch juju status</pre> <p>The screen displays a message. Wait for the cleanup of the message. The cleanup of message indicates success. (Refer to the second figure in this step)</p>  

Step	Procedure	Result
9. <input type="checkbox"/>	<p>After instantiation is complete, query UDR NSR ID from OSM GUI and configure the parameter of udr-nsr-id in NO charm.</p> <p>Follow the steps in the image to Add UDR NSR ID in NO charm</p>	 <p>The screenshot shows the MANO LAUNCHPAD interface. On the left, under 'NETWORK SERVICES', there is a table with columns: NS NAME, NSD, STATUS, and UPTIME. The table contains one entry: 'edward' with NSD 'ocudr_2k_nsd', STATUS 'Configura...', and UPTIME '1h:17m'. On the right, under 'NETWORK SERVICE DETAILS', there is a green banner for 'edward' with a red circle around the name and a red text '1. click here'. Below this, it says 'NSD: ocudr_2k_nsd', 'MONITORING PARAMETERS NOT LOADED', 'NFVI-METRICS', 'NO NFVI METRICS CONFIGURED', 'EPA-PARAMS', and 'GUEST-EPA' with 'CPU-PINNING-POLICY ANY: 3 vms'. At the bottom, there is an 'EVENT CENTER' section.</p>

Step	Procedure	Result

N.4 PERFORM ORCHESTRATION OPERATIONS VIA OSM


After the UDR NSR ID is added in the NO charm, UDR Orchestration operations can be performed. OSM supports two operations:

1. Instantiation
2. Termination

N.5 INSTANTIATE UDR


After the steps in [Appendix N-3](#) are completed successfully, a UDR instance can be instantiated either to level1 or level 2.

1. Navigate to **Launchpad**
→ **Viewport** →
UDR_NO_VM
2. Click the **Service**
Primitive tab
3. Select **instantiate-udr**
action
4. Enter the levelId to
instantiate UDR
5. Click **instantiate-UDR**




N.6 TERMINATE UDR

1. Navigate to **Launchpad** → **Viewport** → **UDR_NO_VM**
2. Click the **Service Primitive** tab
3. Select **terminate-udr** action
4. Click **terminate-UDR**



Manually remove the UDR NSR to remove the deployed VNFDs from openstack

Navigate to **LAUNCHPAD** → **DASHBOARD** on OSM GUI and click the delete icon for the corresponding UDR-NSR



Appendix O. Orchestrating UDR via Tacker

Pre-requisites:

1. Openstack Pike with Tacker service must be installed
2. UDR is successfully instantiated and NFAgent service is up and running. Also a public IP is available to access the NFAgent service.

O.1 TACKER CONFIGURATION

Edit the tacker.conf file location, `/usr/local/etc/tacker/tacker.conf`, and add the following configuration options to it:

```
[udr]

#
# From tacker.vnfm.mgmt_drivers.udr.udr
#

# IP address on which host NFAgent service is deployed (string value)
nfagent_ip = 10.113.79.112

# user name to login NFAgent (string value)
#user = admusr

# password to login NFAgent (string value)
#password =

# time to wait for UDR VMs to be ready for application configuration (seconds)
#udr_init_wait_sec = 600
udr_init_wait_sec = 900
```

Configuration Options

- `nfagent_ip`: The public IP Address of the NFAgent service deployed as a pre-requisite before this step
- `user`: user name to login NFAgent (string value)
- `password`: password to login NFAgent (string value)
- `udr_init_wait_sec`: time to wait for UDR VMs to be ready for application configuration (seconds)

O.2 INSTALL UDR TACKER SUPPORT SCRIPTS

Step	Procedure	Result
1. <input type="checkbox"/>	<p>SSH Logon to Tacker server</p> <p>1. Copy the qcow2 file made from the ova file of UDR image to the tacker server (controller Node).</p> <p>2. Run the following commands:</p> <pre>\$ sudo guestmount -a UDR- 12.5.1.0.0_ 17.7.0.0.qcow 2 -m /dev/mapper /vgroot- plat_usr /mnt \$ sudo cp /mnt/TKLC/u dr/cloud/Ta cker- support.tar .gz ./ \$ sudo guestunmoun t /mnt</pre> <p>These commands extract Tacker-supprt.tar.gz file from qcow2 image</p> <p>3. Untar the file to tacker-support directory</p>	<p>Copied Image on Tacker server:</p> <pre>[root@nj-x52-61 image]# ls -l UDR-12.4.0.0.0 16.13.0.qcow2 -rwxrwxrwx 1 root root 4345757696 Jan 24 18:05 UDR-12.4.0.0.0 16.13.0.qcow2 [root@nj-x52-61 image]#</pre> <p>Extracted tacker-support directory from qcow2 image</p> <pre>[root@nj-x52-61 tacker-support]# ls bin mgmt_driver requirements.txt vnfd</pre>

Step	Procedure	Result
2. <input type="checkbox"/>	Browse to the directory where the tacker scripts are copied on the controller Node.	<p>Run the following commands:</p> <ol style="list-style-type: none"> 1. <code>sudo mkdir -p /usr/lib/python2.7/site-packages/tacker/vnfm/mgmt_drivers/udr</code> 2. edit <code>mgmt_driver/udr/udr.py</code> to navigate to line 102: 3. <code>level = str(self.cluster_info['options']['LEVEL'])</code> 4. <code>sudo cp mgmt_driver/udr/*.py /usr/lib/python2.7/site-packages/tacker/vnfm/mgmt_drivers/udr/</code> 5. <code>sudo service openstack-tacker-server restart</code> <p>NOTE: Substitute <code>/usr/lib/python2.7/site-packages/tacker</code> with the tacker script installation directory for your local tacker installation path.</p> <p>Inspect <code>tacker.log</code> to verify that UDR management driver installed successfully.</p> <pre>[root@nj-x52-61 tacker-support]# mkdir -p /usr/lib/python2.7/site-packages/tacker/vnfm/mgmt_drivers/udr/ [root@nj-x52-61 tacker-support]# /bin/cp -rf mgmt_driver/udr/*.py /usr/lib/python2.7/site-packages/tacker/vnfm/mgmt_drivers/udr/ [root@nj-x52-61 tacker-support]# service openstack-tacker-server restart Redirecting to /bin/systemctl restart openstack-tacker-server.service [root@nj-x52-61 tacker-support]#</pre>
3. <input type="checkbox"/>	Deploy VNFD for UDR 2k level 2 VNF	<ol style="list-style-type: none"> 1. Edit <code>vnfd/udr-2k-vnfd.yaml</code> and find occurrences of <code>init 6</code> (there are 6 occurrences in total), prepend line with: <pre>echo 'ifconfig eth0 mtu 1450' >> /etc/rc.d/rc.local</pre> before each occurrence of <code>'init 6'</code>, like following: <pre>echo 'ifconfig eth0 mtu 1450' >> /etc/rc.d/rc.local</pre> <code>init 6</code> 2. Source keystone rc file of openstack: <pre>source ~/keystonerc_admin</pre> 3. Deploy the updated VNFD file with following command: <pre>tacker vnfd-create --vnfd-file vnfd/udr-2k-vnfd.yaml udrvnfd</pre> 4. Verify that VNFD is deployed successfully. <pre>[root@nj-x52-61 tacker-support]# vim vnfd/udr-2k-vnfd.yaml [root@nj-x52-61 tacker-support]# tacker vnfd-create --vnfd-file vnfd/udr-2k-vnfd.yaml udr-2k-vnfd You must provide a username or user ID via --os-username, env[OS_USERNAME] or --os-user-id, env[OS_USER_ID] [root@nj-x52-61 tacker-support]# source ~/keystonerc_admin [root@nj-x52-61 tacker-support(keystone_admin)]# tacker vnfd-create --vnfd-file vnfd/udr-2k-vnfd.yaml udr-2k-vnfd Created a new vnfd: +-----+ Field Value +-----+ created_at 2018-02-05 03:47:24.167240 description Demo with udr cluster id 0874def4-0ac5-4352-bc7a-cff6139d6df4 name udr-2k-vnfd service_types vnfd template_source onboarded tenant_id 45a69279f4be47d89556b5299bdec769 updated_at +-----+ [root@nj-x52-61 tacker-support(keystone_admin)]#</pre>

0.3 PERFORM ORCHESTRATION OPERATIONS VIA TACKER

After the successful completion of [Appendix O-2](#), you can proceed with the orchestration of UDR. Tacker supports two orchestration operations:

1. Instantiation (CREATE UDR VNF)
2. Termination (DELETE UDR VNF)

O.4 CREATE UDR VNF (INSTANTIATION)

Issue the following command to create UDR VNF (assumes to have sourced the keystone rc file for openstack):

```
tacker vnf-create --vnfd-name udrvnfd <udr_vnf_name> --param-file udrvnf-param.yaml
```

Where:

- `udr_vnf_name` is replaced with the name you specify for udr vnf.
- `udrvnf-param.yaml` is the configuration file used for customizing parameters in UDR VNFD template. Change the file parameters to specify the configuration.

Figure 5 Example of udrvnf-param.yaml

```
xmi_network: int-xmi
imi_network: int-imi
xsi1_network: int-xsi1
xsi2_network: int-xsi2
image: UDR-12.5.1.0.0_17.7.0.0
```

```
[root@nj-x52-61 tacker-support]# source ~/keystonerc_admin
[root@nj-x52-61 tacker-support(keystone_admin)]# tacker vnf-create --vnfd-name udr-2k-vnfd udrpv1
Created a new vnf:
+-----+-----+
| Field          | Value                                     |
+-----+-----+
| created_at     | 2018-02-05 04:52:52.342068              |
| description    | Demo with udr cluster                   |
| error_reason   |                                          |
| id             | e60483c1-94a2-4af6-b415-1a740de59c64    |
| instance_id    | 204ad65b-8835-4052-ae57-79d3859a53d7    |
| mgmt_url       |                                          |
| name           | udrpv1                                  |
| placement_attr | {"vim_name": "tacker"}                  |
| status         | PENDING_CREATE                         |
| tenant_id      | 45a69279f4be47d89556b5299bdec769       |
| updated_at     |                                          |
| vim_id         | 7ae4f37b-056b-45de-a131-62463bdfce6d   |
| vnfd_id        | 0874def4-0ac5-4352-bc7a-cff6139d6df4    |
+-----+-----+
[root@nj-x52-61 tacker-support(keystone_admin)]#
```

To inspect the detailed log for creating UDR VNF, refer to tacker log use following command:

```
$ sudo tail -f /var/log/tacker/tacker.log
```

O.5 DELETE UDR VNF (TERMINATION)

Issue the following command to delete UDR VNF:

```
tacker vnf-delete <udr_vnf_name>
```

Where:

- `udr_vnf_name` is replaced with the name of udr vnf you want to terminate.

```
[root@nj-x52-61 tacker-support]# source ~/keystonerc_admin
[root@nj-x52-61 tacker-support(keystone_admin)]# tacker vnf-delete udrpv1
All specified vnf(s) delete initiated successfully
[root@nj-x52-61 tacker-support(keystone_admin)]#
```