

Oracle® Communications Network Charging and Control

SIGTRAN Technical Guide



Release 15.2

January 2026



Copyright

Copyright © 2026, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software" or "commercial computer software documentation" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

About This Document	v
Document Conventions	vi
Chapter 1	
System Overview	1
Overview	1
Introduction to SLEE TCAP Interfaces	1
SCCP Level TCAP Interfaces	2
M3UA Level TCAP Interfaces	4
Routing to Services	5
Chapter 2	
Configuration.....	9
Overview.....	9
Configuration Overview	9
Configuring tcapif.def.....	12
Configuring sigtran.config.....	21
Example Configuration Scenarios	48
Chapter 3	
Background Processes	53
Overview.....	53
sua_if	53
m3ua_if.....	54
Chapter 4	
Troubleshooting.....	55
Overview.....	55
Common Troubleshooting Procedures.....	55
Debug	55
Chapter 5	
Statistics and Reports	57
Overview.....	57
Statistics	57
Chapter 6	
About Installation and Removal	59
Overview.....	59
Installation and Removal Overview	59
Checking the Installation	59

About This Document

Scope

The scope of this document includes all the information required to install, configure and administer the SIGTRAN Interfaces application.

Audience

This guide was written primarily for system administrators and persons installing and administering the SIGTRAN Interfaces application. The documentation assumes that the person using this guide has a good technical knowledge of the system.

Prerequisites

Although there are no prerequisites for using this guide, familiarity with the target platform would be an advantage.

A solid understanding of Unix and a familiarity with IN concepts are an essential prerequisite for safely using the information contained in this technical guide. Attempting to install, remove, configure or otherwise alter the described system without the appropriate background skills, could cause damage to the system; including temporary or permanent incorrect operation, loss of service, and may render your system beyond recovery.

This manual describes system tasks that should only be carried out by suitably trained operators.

Related Documents

The following documents are related to this document:

- *Service Logic Execution Environment Technical Guide*
- *Service Management System Technical Guide*

Document Conventions

Typographical Conventions

The following terms and typographical conventions are used in the Oracle Communications Network Charging and Control (NCC) documentation.

Formatting Convention	Type of Information
Special Bold	Items you must select, such as names of tabs. Names of database tables and fields.
<i>Italics</i>	Name of a document, chapter, topic or other publication. Emphasis within text.
Button	The name of a button to click or a key to press. Example: To close the window, either click Close , or press Esc .
Key+Key	Key combinations for which the user must press and hold down one key and then press another. Example: Ctrl+P or Alt+F4 .
Monospace	Examples of code or standard output.
Monospace Bold	Text that you must enter.
<i>variable</i>	Used to indicate variables or text that should be replaced with an actual value.
menu option > menu option >	Used to indicate the cascading menu option to be selected. Example: Operator Functions > Report Functions
hypertext link	Used to indicate a hypertext link.

Specialized terms and acronyms are defined in the glossary at the end of this guide.

System Overview

Overview

Introduction

This chapter provides a high-level overview of the application. It explains the basic functionality of the system and lists the main components.

It is not intended to advise on any specific Oracle Communications Network Charging and Control (NCC) network or service implications of the product.

In this Chapter

This chapter contains the following topics.

Introduction to SLEE TCAP Interfaces	1
SCCP Level TCAP Interfaces	2
M3UA Level TCAP Interfaces	4
Routing to Services	5

Introduction to SLEE TCAP Interfaces

Introduction

The Oracle SIGTRAN TCAP Interface is a SLEE interface that enables the SLEE to inter-work with a TCAP Protocol stack.

The interface converts messages arriving from the TCAP Protocol stack and converts them into SLEE events. The SLEE events are then sent to the application which is configured to handle the call. The SIGTRAN TCAP Interface also converts SLEE events coming from a SLEE application back into a form the TCAP Protocol stack can understand.

For more information about SLEE events and applications, see *SLEE Technical Guide*.

Service routing and message correlation

The SIGTRAN TCAP Interface also has a role in routing calls to services on the platform.

It routes the message setting one of the following:

- The SLEE service key for the message
- A correlation ID which matches the message to one sent to the SLEE earlier (in this case, the second message will use the same service key as the first)

TCAP Protocol stack

A TCAP Protocol stack is a software implementation of a networking protocol suite. It involves a group of protocols working together to allow Oracle platform software and hardware to communicate with a telecommunications network.

The protocols are:

- TCAP
- underlying protocols such as SCCP/MTP or SUA/SCTP/IP

The hardware is Network Interface Cards on an applicable high-performance server-based platform.

The networks typically support Intelligent Network-type Signaling Control and other associated or similar functions.

TCAP Interface layers

The SIGTRAN TCAP Interface used in a specific installation will depend on the requirements of the network and the type of physical interface and network protocols used.

Generally, the SIGTRAN TCAP Interface which will be installed is built from underlying layers of smaller protocol stacks which sit below the TCAP layer. These layers may be comprised of TCP/IP or SIGTRAN protocols (SUA/SCCP/M3UA). They may be provided and supported by Oracle and/or third party vendors.

Available TCAP Interfaces

This table lists the available SIGTRAN TCAP Interfaces.

Stack name	Protocol	Interface name
SIGTRAN	SCCP	sua_if
	M3UA	m3ua_if


SCCP Level TCAP Interfaces

Introduction

The SIGTRAN TCAP Interface stack can be used to translate to a third party SCCP/SUA implementation.

SIGTRAN SCCP/SUA interface diagram

This diagram shows the SIGTRAN SCCP/SUA interface on a SLC.



SIGTRAN/SUA interface components

This table describes the main components in the SUA version of the SIGTRAN TCAP Interface.

Process	Role	Further information
sua_if	Interface between the SLEE and the network. Note: This process includes the SIGTRAN libraries which interface to the network.	<i>sua_if</i> (on page 53).
SLEE	Real-time interface between the interfaces and applications which have been configured to communicate through the SLEE.	<i>Service Logic Execution Environment Technical Guide</i> .
sua_if.sh	Shell Startup script used to set the command line parameters for configuring sua_if.	<i>Configuration Overview</i> (on page 9).
tcapif.def	Optional configuration file for sua_if. Can be used to set some command line parameters.	<i>Configuring tcapif.def</i> (on page 12).
sigtran.config	Main configuration file for sua_if.	<i>Configuring sigtran.config</i> (on page 21).
scpp_YYYYMMDD_hh_mm.log	The SCCP-level message log file.	<i>log</i> (on page 27).


M3UA Level TCAP Interfaces

Introduction

The SIGTRAN TCAP stack can be used to translate to a third party SCCP/M3UA implementation.

SIGTRAN m3ua interface diagram

This diagram shows the SIGTRAN M3UA interface on a SLC.



SIGTRAN m3ua interface components

This table describes the main components in the M3UA version of the SIGTRAN TCAP Interface.

Process	Role	Further information
m3ua_if	Interface between the SLEE and the network. Note: This process includes the SIGTRAN libraries which interface to the network.	<i>m3ua_if</i> (on page 54).
SLEE	Real-time interface between the interfaces and applications which have been configured to communicate through the SLEE.	<i>Service Logic Execution Environment Technical Guide</i> .
m3ua_if.sh	Shell Startup script used to set the command line parameters for configuring m3ua_if.	<i>Configuration Overview</i> (on page 9).
tcapif.def	Optional configuration file for m3ua_if. Can be used to set some command line parameters.	<i>Configuring tcapif.def</i> (on page 12).
sigtran.config	Main configuration file for m3ua_if.	<i>Configuring sigtran.config</i> (on page 21).

sccp_YYYYMMDD_hh mm.log	The SCCP-level message log file.	<i>log</i> (on page 27).
----------------------------	----------------------------------	--------------------------

Routing to Services

Introduction

When the SIGTRAN TCAP Interface receives a new TCAP message (TC-BEGIN), it determines what SLEE service key it should use when sending the message on. SLEE service keys are used by the SLEE to determine where to route the message to. For more information about how SLEE routes calls, see *SLEE Technical Guide*.

Note: If the message is an assistRequestInstructions, sua_if/m3ua_if will send the message to the SLEE with a correlation ID. The SLEE will then route based on only correlation ID. For more information about correlation IDs and how they are processed, see *Correlation IDs* (on page 7).

Routing process

This table describes how SIGTRAN TCAP Interface constructs the SLEE service key for an incoming message.

Stage	Description
1	TC-BEGIN arrives at sua_if/m3ua_if.
2	sua_if/m3ua_if determines which protocol the message is using by matching the SSN the message arrived from to the ssn details in its command line or tcapif.def configuration. For more information about setting which SSNs correspond to which protocols, see <i>tcapif parameters</i> (on page 13).
3	If the protocol is INAP, sua_if/m3ua_if will check whether the operation is assistRequestInstructions. If it is, it will set a correlation ID in the message and send it to the SLEE. No further action is taken.
4	If the protocol is not INAP, or it is INAP but the operation is an InitialDP, sua_if/m3ua_if will construct the SLEE service key.
5	sua_if/m3ua_if sends the message on to the SLEE, where it will be routed according to the rules defined for service keys in SLEE.cfg.

SLEE service key construction

The SLEE service key constructed by sua_if/m3ua_if is made up from the following elements:

Byte	MSB 8	7	6	5	4	3	2	LSB 1
Sourced from	Base service key value defined by <i>sleekey</i> (on page 19).			Dest SSN (SCCP)	Depends on the protocol of incoming message:			
					Protocol	Value		
					INAP IDP	IDP's ServiceKey value		
					INAP Initiate CallAttempt	ffffffffff		
					MAP	MAP Operation ID value		
					CAMEL GPRS	CAP_InitialDPGPRS Servicekey value, or DestinationReference for other operations		
					CAMEL SMS	CAP_InitialDPSMS Servicekey value		
					any other	ffffffffff		
Example 1	0x1		0xd0		00000009			
Example 2	0x123456		0x05		ffffffffff			

Note: The base service key (bytes 6-8) is not padded with leading zeros. Bytes 1 to 4, and byte 5 are padded with leading zeros.

Example SLEE service keys

Example 1:

If sua_if/m3ua_if is using the default base key of 0x1, and the TC-BEGIN has INAP SSN = 13 (that is, 0xd) and service key = 8: the SLEE service key will be 0x10d00000008.

The message can then be routed to INAPService1 on App1 by the following lines in **SLEE.cfg**:

```
SERVICEKEY=INTEGER 0x10d00000008 INAPService1
SERVICE=INAPService1 1 App1 INAPService1
```

Example 2:

If sua_if/m3ua_if is using a non-default base key of 0x1234, and the TC-BEGIN has INAP SSN = 112 (that is, 0x70) and service key = 10: the SLEE service key will be 0x12347000000010.

The message can then be routed to INAPService2 on App2 by the following lines in **SLEE.cfg**:

```
SERVICEKEY=INTEGER 0x12347000000010 INAPService2
SERVICE=INAPService2 1 App2 INAPService2
```

Example 3:

If sua_if/m3ua_if is using the default base key of 0x1, and the TC-BEGIN has MAP SSN = 5 and operation ID = 5: the SLEE service key will be 0x10500000005.

The message can then be routed to MAPService on App2 by the following lines in **SLEE.cfg**:

```
SERVICEKEY=INTEGER 0x105000000005 MAPService
SERVICE=MAPService 1 App2 MAPService
```


Correlation IDs

In some circumstances, a message arriving at sua_if/m3ua_if will need to be matched to an earlier message. For example, when a play announcement node has requested an Intelligent Peripheral to play a message to a caller, and the IP is reporting the result of the action.

In this case, the second message received by sua_if/m3ua_if (sent by the IP) will be an INAP AssistRequestInstructions (ARI) operation, and will contain a correlation ID. sua_if/m3ua_if will attempt to initiate a SLEE dialog using the correlation ID instead of a service key. The correlation ID will be a decimal conversion of the digits from the ARI's correlationID parameter.

SLEE Correlation ID diagram

This diagram shows how correlation IDs are linked across the system.



Matching SLEE correlation IDs

These are the steps involved in matching correlation IDs.

Stage	Description
1	On an SLC, an InitialDP is sent across the SLEE. (Usually sent by an interface such as sua_if/m3ua_if to a service application such as slee_acs). The SLEE assigns it a call ID.
2	The SLEE service application which received the InitialDP requests the SLEE to assign a correlation ID to the InitialDP.
	The SLEE allocates a correlation ID and returns it to the SLEE service application.
3	The SLEE service application sends an INAP ETC operation over the SLEE to an interface. The operation contains the Address of an external network entity and the correlation ID.
4	The interface sends the operation to the switch which forwards it to the remote entity specified in the Address (usually an Intelligent Peripheral).
5	The remote entity sends the interface on the SLC an INAP TC-BEGIN containing an AssistRequestInstructions (ARI) and the original correlation ID.

Stage	Description
6	<p>When sua_if/m3ua_if receives the ARI, it initiates a new SLEE dialog using the correlation ID. The correlation ID is matched to the call ID assigned in Stage 1, and the same service key routing rules are applied (this means the ARI will be delivered to the SLEE service application which sent the ETC).</p> <p>The correlation ID must be read from within the TCAP component which holds the conveyed protocol's first message.</p>
7	<p>The SLEE service application receives the message with the call ID assigned to the InitialDP and correlates the messages.</p>

For an example of how correlation IDs are used by ACS when playing announcements, see *Advanced Control Services Technical Guide*.

Chapter 2

Configuration

Overview

Introduction

This chapter explains how to configure the Oracle Communications Network Charging and Control (NCC) application.

In this chapter

This chapter contains the following topics.

Configuration Overview	9
Configuring tcapif.def	12
Configuring sigtran.config.....	21
Example Configuration Scenarios	48

Configuration Overview

Introduction

This topic provides a high level overview of how the SIGTRAN TCAP Interfaces are configured.

sua_if/m3ua_if are configured using the following options set in the:

- Startup shell script and/or **tcapif.def**
- **sigtran.config** file

Configuration components

TCAP Interface is configured by the following components:

Component	Locations	Description	Further Information
Environmental variables	any machine connected to a switch	Set in startup scripts.	<i>Environmental variables</i> (on page 10).
Command line variables	any machine connected to a switch	Set in startup scripts or tcapif.def.	<i>Configuring tcapif.def</i> (on page 12).
tcapif.def	any machine connected to a switch	Optional file that sets the configuration parameters which are shared with other types of TCAP Interface.	<i>Configuring tcapif.def</i> (on page 12).
sigtran.config	any machine connected to a switch	This file sets the configuration parameters which are specific to SIGTRAN TCAP Interface.	<i>Configuring sigtran.config</i> (on page 21).

Configuration process overview

This table describes the steps involved in configuring the SIGTRAN TCAP Interface for the first time.

Stage	Description
1	<p>The environment <code>sua_if/m3ua_if</code> will run in must be configured correctly. This includes:</p> <ul style="list-style-type: none"> Setting the location of the SLEE base directory (if this is different from default) Configuring the name of the main configuration file Configuring the location of the SCCP log file <p>For more information about configuring environmental variables, see Environmental variables.</p>
2	Changing the default startup variables in the SLEE.cfg file, especially service keys.
3	Any non-default command line parameters must be added to one of the following:
	<ul style="list-style-type: none"> The relevant <code>sua_if/m3ua_if</code> startup shell script(s): <code>sua_if.sh</code> or <code>m3ua_if.sh</code> (if supported) <code>tcapif.def</code>
4	Configuration data must be configured for <code>sua_if/m3ua_if</code> in <code>sigtran.config</code> .

Environmental variables

The following UNIX shell environment variables can be set.

SCCP_LOG_FILE

Syntax:	<code>SCCP_LOG_FILE=filename</code>
Description:	File name prefix, including path, of the optional SCCP log file. A timestamp and <code>.log</code> suffix is added.
Type:	String
Optionality:	Optional, default used if not set.
Allowed:	
Default:	<code>/tmp/sccp</code>
Notes:	Using the default value for example, the resulting file name in the output of log files have names in the format <code>/tmp/sccp_yyyymmdd_hhmm.log</code> . By default a new log file, with a different timestamp, is created every 10 minutes. Other intervals can be specified using the <code>SCCP_LOG_TIME</code> environment variable.
Example:	<code>SCCP_LOG_FILE=/var/tmp/sua_if_sccp</code>

SCCP_LOG_TIME

Syntax:	<code>SCCP_LOG_TIME = value</code>
Description:	The interval, in minutes, between starting an <code>SCCP_LOG_FILE</code> log file.
Type:	Integer
Optionality:	Optional (default used if not set).
Allowed:	
Default:	10 (minutes)

Notes: If SCCP_LOG_TIME is defined as 20 then, if logging is enabled, new log files will be created every 20 minutes on the hour, 20 past and 40 past the hour with names like:

/var/tmp/sccp_20091225_1500.log

Example: SCCP_LOG_TIME = 20

SLEE_etc_dir

Syntax: SLEE_etc_dir=*path*

Description: Full path name of the SLEE's etc directory.

Type: Integer

Optionality: Optional, default used if not set.

Allowed:

Default: ./etc

Notes: SLEE's etc directory is where **tcapif.def** resides.

Example: SLEE_etc_dir=.../.../SLEE/etc

TCAPIF_DEF

Syntax: TCAPIF_DEF=*filename*

Description: Defines the name of configuration file which contains TCAP Interface parameters common to all TCAP Interfaces.

Type: String

Optionality: Optional, default used if not set.

Allowed:

Default: tcapif.def

Notes:

Example: TCAPIF_DEF=sua_tcapif.def

ESERV_CONFIG_FILE

Syntax: ESERV_CONFIG_FILE=*filename*

Description: Name of configuration file which contains SIGTRAN TCAP Interface-specific parameters.

Type: String

Optionality: Optional, default used if not set.

Allowed: Any valid filename.

Default: sigtran.config

Notes:

Example: ESERV_CONFIG_FILE=sigtran.config

SIGTRAN_CONFIG_SECTION

Syntax: SIGTRAN_CONFIG_SECTION=*str*

Description: The name of the section in the ESERV_CONFIG_FILE configuration file which holds the Sigtran Tcap Interface-specific configuration.

Type: String

Optionality: Optional (default used if not set).

Allowed: ASCII text.

Default: For m3ua_if: M3UA.
For sua_if: SUA

Notes:

Example: SIGTRAN_CONFIG_SECTION=M3UA

Configuring tcapif.def

Setting parameters

Each parameter has a default that will be used if the parameter is not defined.

Parameters may be defined in two ways:

- 1 The command line
- 2 In the **tcapif.def** file

Note: If a parameter is set in both the command line and the **tcapif.def** file, the command line setting will be used.

Defining the parameters

For a parameter 'param val', the value may be set in the configuration file with a line such as:

```
PARAM VAL=value
```

Note: Spaces can be inserted into the parameter name in **tcapif.def** without effect.

Or the parameter may be defined on the command line, for example:

- sua_if -paramval value
- m3ua_if -paramval value

Note: Spaces can not be inserted into the parameter names on the command line, and command line parameter names are case sensitive.

Setting command line parameters

Since the executable is started by the SLEE, the only way to set the command line parameters is via an intermediate startup shell script. This shell script is pointed to in **SLEE.cfg**.

Example 1: Startup script:

```
#!/bin/sh
exec sua_if -ssns 123 -proto inap -tcap ccitt
```

Example 2: Startup script:

```
#!/bin/sh
exec sua_if -pc 160 -ssns 123 -proto inap -tcap \
ccitt
```

Note: To split over a line (as shown in Example 2), use "\" at the end of the line.

tcapif.def

The **tcapif.def** file can be used to define common configuration for all TCAP interfaces running on the same system.

Where different TCAP Interfaces require different configuration, the file-set configuration options can be overridden on the command line on a binary by binary basis. Command line options are set in the startup shell scripts. Every option in the **tcap.def** file can be overridden in this way.

Note: In the file, the options are all uppercase. On the command line, they are lowercase.

tcapif parameters

The generic configuration variables applicable to all TCAP interfaces are listed below:

Note: If any of the following parameters are set (all default to not set) then the TCAP Interface will use a default SCCP Origination Address in the first TC-CONTINUE that it sends out. By default the TCAP Interface will use the SCCP destination address of the first incoming message. This capability can be used to ensure any subsequent messages sent by the far end in the same dialog will be routed to this address. This can be useful when initial messages are sent to aliased addresses and round-robin routed by an STP to a series of SLCs.

alwayssendaddr

Syntax: `-alwaysendaddr true|false`
Description: Which messages to send the SCCP destination address in.
Type: Boolean
Optionality:
Allowed: `true` Send the SCCP destination address in all messages.
`false` Send the SCCP destination address in only the initial message received in a dialog.
Default: `false`
Notes: If this parameter and sendorigaddr are both set to true, the TCAP Interface will send the destination and origination addresses.
Example: `-alwaysendaddr true`

autoac

Syntax: `-autoac yes|no`
Description: Whether to use the Application context of a CCITT white book TCAP message received in the response to the message if the SLEE application does not supply one.
In addition, dialogs initiated by the interface will use the default application context defined by the `defoutac` variable below.
Type: Boolean
Optionality:
Allowed: `yes` Use the Application context from the TCAP message if none is supplied when a SLEE application responds to a message.
`no` Do not attempt to supply an Application context if none is provided.
Default: `yes`
Notes: Setting to yes, effectively acknowledges the white book application context used.
If `defoutac` is set, `sua_if/m3ua_if` will add the default application context if one is not set by the SLEE application or in the TCAP message.
Example: `-autoac no`

defoutac

Syntax:	<code>-defoutac value</code>	
Description:	The default application context to use if no application context is supplied by the SLEE application or set by autoac.	
Type:	String	
Optionality:		
Allowed:	none	Missing application contexts will not be set to a default.
	<i>oid1,oid2...</i>	The default CCITT white book TCAP application context to use for dialogs initiated by sua_if/m3ua_if.
Default:	none	
Notes:		
Example:	<code>-defoutac 1,2,3</code>	

displaymonitors

Syntax:	<code>-displaymonitors true false</code>	
Description:	Whether to log CAPS.	
Type:	Boolean	
Optionality:		
Allowed:	true	New call attempt rates (CAPS) will be logged to stdout at period defined by <code>-reportperiod</code> .
	false	
Default:	false	
Notes:		
Example:	<code>-displaymonitors true</code>	

dpause

Syntax:	<code>-dpause seconds</code>	
Description:	Number of seconds to sleep at startup.	
Type:	Integer	
Optionality:		
Allowed:		
Default:	0	
Notes:	Allows a global session to be attached to the process.	
Example:	<code>-dpause 7</code>	

fixedSleekey

Syntax:	<code>-fixedSleekey true false</code>	
Description:	When this parameter is set to true, use the following as sleekey for INAP operations:	
	InitialDP > sleekey = 1	
	AssistRequestInstructions > sleekey = 2	
	CAMEL GPRS operation > sleekey = 3	
	InitialDPSMS > sleekey = 4	
	InitiateCallAttempt > sleekey = 5	

Type:	Boolean
Optionality:	Optional, default will be used if not set.
Allowed:	true false
Default:	false
Notes:	When <code>fixedSleekey</code> is set to true, slee service key supplied with <code>sleekey</code> option will not be used for INAP operations, rather the fixed sleekeys will be used as described above. For more information about how <code>sleekey</code> is used to construct the base key in the SLEE service key, see Routing process (on page 5) .
Example:	<code>-fixedSleekey true</code>
 inapssns	
Syntax:	<code>-inapssns value1,value2,...</code>
Description:	A comma-separated list of the SCCP subsystem numbers (SSNs) that <code>sua_if/m3ua_if</code> will treat as INAP (regardless of the default protocol defined by <code>-proto</code>).
Type:	Integer
Optionality:	Mandatory
Allowed:	0-255
Default:	Empty set
Notes:	
Example:	<code>-inapssns 33,45,99</code>
 mapssns	
Syntax:	<code>-mapssns value1,value2,...</code>
Description:	A comma-separated list of the SCCP subsystem numbers (SSNs) that <code>sua_if/m3ua_if</code> will treat as MAP (regardless of the default protocol defined by <code>-proto</code>).
Type:	Integer
Optionality:	Mandatory
Allowed:	0-255
Default:	Empty set
Notes:	
Example:	<code>-mapssns 22,26</code>
 monitorperiod	
Syntax:	<code>-monitorperiod milliseconds</code>
Description:	Period call rate rejection monitoring occurs in.
Type:	Integer (number of milli-seconds)
Optionality:	
Allowed:	
Default:	1000
Notes:	Default of 1 sec allows <code>-rejectlevel</code> to represent CAPS.
Example:	<code>-monitorperiod 1000</code>

Chapter 2

polltime

Syntax: -polltime *microseconds*
Description: Interval between polling interface.
Type: Integer (micro seconds)
Optionality:
Allowed:
Default: 1000
Notes:
Example: -polltime 500

proto

Syntax: -proto = *protocol*
Description: Defines the default protocol to use when the interface (sua_if/m3ua_if) constructs a SLEE service key. This parameter is used only when an incoming TCAP message SCCP Subsystem Number (SSN) is not mapped to a protocol.
Type: String
Optionality: Optional (default used if not set)
Allowed:

- inap – INAP interface
- map – MAP interface
- is41d – IS41D interface
- any – Uses a value of eight Fs (ffffffff) in its SLEE service key construction. This allows service routing of the message with the unknown protocol to a SLEE service for further processing, if needed.

Default: inap
Notes: A combination of the incoming SSN, the interface's SSN/protocol mapping, and its -sleekey value (default 0x1) are used to route incoming calls to a SLEE service.
Example: -proto = map

rejectlevel

Syntax: -rejectlevel *max number of calls*
Description: If more than 0, this sets the maximum number of new call attempts that will be processed within a given interval (as determined by -monitorperiod).
Type: Integer
Optionality:
Allowed:
Default: 0
Notes: In conjunction with -monitorperiod it provides a call limiter for the interface.
Example: -rejectlevel 4000

reportperiod

Syntax: -reportperiod *reject logging period*
Description: How often:

- rejection indications are logged to the alarm system (if rejections are occurring), and
- call rates are logged (if -displaymonitors is set).

Type: Integer (seconds)

Optionality:**Allowed:****Default:** 30**Notes:****Example:** -reportperiod 25

retgt

Syntax: -retgt "str"**Description:** If set to something other than **none**, a default SCCP Origination Address will be used which will contain this Global Title.**Type:** String**Optionality:****Allowed:** none

"1,noa,address_digits"

"2,trans_type,address_digits"

"3,trans_type,num_plan,address_digits"

"4,trans_type,num_plan,noa,address_digits"

Default: none**Notes:** The variables used in the gt are:

<noa> Nature of Address

<address_digits> Destination/Called Party Number

<trans_type> Transmission Type

<num_plan> Number Plan

Example: -retgt "1,1,123456789"

rethandover

Syntax: -rethandover *true|false***Description:** Sets whether to use the default SCCP originating address in TCAP handover messages.**Type:** Boolean**Optionality:** Optional (default used if not set)**Allowed:** *true* Sends the default originating address (set with -retgt or default_gt) in TCAP handover messages. *false* Sends the originating address of the original message in TCAP handover messages.**Default:** *true***Notes:** If this is set to *true* and there is no default address, the behavior is as if this was set to *false*.**Example:** -rethandover *false*

retni

Syntax: -retni = 0|1**Description:** Sets the National Indicator in a return address (an ANSI SCCP address rather than an ITU one), created using the retssn/ retpc/ retgt config parameters.**Type:** Integer

Optionality:

Allowed: 0 Set the NI to 0 (ITU).
1 Set the NI to 1 (ANSI).

Default:

Notes: The National Indicator is the first bit of the return address (that is, the SCCP address).

Example: -retni = 1

retpc

Syntax: -retpc *point code value*

Description: If set to a non-zero value, a default SCCP Origination Address will be used which will contain this Point Code.

Type: Hex or decimal integer

Optionality:**Allowed:**

Default: 0

Notes:

Example: -retpc 55

retri

Syntax: -retri *Routing Indicator*

Description: Default SCCP Origination Address's routing indicator.

Type: Integer

Optionality:

Allowed: 0 route on GT
1 route on PC

Default: 0

Notes: Used in conjunction with retssn, retpc and retgt options.

Example: -retri 1

retssn

Syntax: -retssn *SSN*

Description: If set to a non-zero value, a default SCCP Origination Address will be used in the first outgoing TC-CONTINUE message which will contain this SSN.

If set to -1, then outgoing SCCP origin address SSN is populated dynamically, & it is set as the incoming destination address SSN. i.e outgoing CgPA SSN will be set to incoming CdPA SSN' when retssn is set as -1.

Type: Integer

Optionality:

Allowed: 0-255, -1
Default: 0

Notes:

Example: -retssn 20

sendorigaddr

Syntax:	<code>-sendorigaddr true false</code>				
Description:	Whether to send the SCCP origination address in addition to the destination address.				
Type:	Boolean				
Optionality:					
Allowed:	<table> <tr> <td><code>true</code></td><td>Send the SCCP origination address.</td></tr> <tr> <td><code>false</code></td><td>Do not send the SCCP origination address.</td></tr> </table>	<code>true</code>	Send the SCCP origination address.	<code>false</code>	Do not send the SCCP origination address.
<code>true</code>	Send the SCCP origination address.				
<code>false</code>	Do not send the SCCP origination address.				
Default:	<code>false</code>				
Notes:	If <code>statsif</code> is defined, <code>sendorigaddr</code> is set to true regardless of the configuration value set here.				
Example:	<code>-sendorigaddr true</code>				

sleekey

Syntax:	<code>-sleekey SLEE_Service_Key</code>
Description:	Base SLEE service key value to use in base key (bytes 6-8) part of the SLEE service key created by <code>sua_if/m3ua_if</code> to enable the SLEE to route the message to the correct service.
Type:	Integer
Optionality:	Optional, default will be used if not set.
Allowed:	A single value or a range of values (in hex or decimal integers)
Default:	<code>0x1</code>
Notes:	For more information about how <code>sleekey</code> is used to construct the base key in the SLEE service key, see <i>Routing process</i> (on page 5).
Examples:	<p><code>-sleekey 0x89abcd</code></p> <p>In this example, the base key in all SLEE service keys created by this <code>sua_if/m3ua_if</code> will be <code>0x89abcd</code>.</p>

`-sleekey 0x1-0x5`

In this example, the base key of SLEE service keys created by `sua_if/m3ua_if` will range between `0x1` and `0x5` picked in a round-robin.

ssns

Syntax:	<code>-ssns ssn1,ssn2,...</code>
Description:	A comma separated list of SCCP subsystem numbers (SSNs) that the TCAP Interface will register to.
Type:	Decimal integer
Optionality:	
Allowed:	0 to 255
Default:	<code>19</code>
Notes:	
Example:	<code>-ssns 12,33</code>

statsif

Syntax:	-statsif none slee_if_name	
Description:	SLEE interface to which all initial messages in a TCAP dialog are copied to allow statistics monitoring.	
Type:	String	
Optionality:		
Allowed:	none	don't copy initial messages
	SLEE interface name	SLEE interface to copy initial messages to. Must match interfaceName in SLEE.cfg.
Default:	none	
Notes:	Currently this is only used with the SLEE Callmapping solution. If statsif is not none, sendorigaddr's value is over-ridden and set to true. For more information about SLEE interfaces including the statistics interface, see <i>Service Logic Execution Environment Technical Guide</i> .	
Example:	-statsif none	

stderron

Syntax:	-stderron 0 1	
Description:	Whether syslog messages generated by the interface class should be printed to stderr as well as the system log file.	
Type:	Boolean	
Optionality:		
Allowed:	0	print to syslog only
	1	print to stderr and syslog
Default:	0	
Notes:		
Example:	-stderron 1	

stps

Syntax:	-stps pc1,pc2,...	
Description:	Comma-separated list of STP point codes to which sua_if/m3ua_if should round-robin route outward messages.	
Type:	Decimal integer	
Optionality:		
Allowed:	none	Packets will only be sent to addresses that have a direct route set up.
	comma-separated list of STP point codes (decimal integers)	List of STP point codes to send messages to in round robin.
Default:	none	
Notes:	Each PC will be substituted into the MTP destination addresses.	
Example:	-stps 2,5,7	

unknowncorridoverridesleekey

Syntax: `-unknowncorridoverridesleekey value`
Description: It redirects incoming ARI message to configured service key if correlationID is not found.
Type: Integer
Optionality: Optional
Allowed: Integer
Default: -1
Notes:
Example: `-unknowncorridoverridesleekey 108`

Configuring `sigtran.config`

Introduction

This topic explains the configuration options and parameters for `sua_if/m3ua_if` in the `sigtran.config` file.

Note: Unlike the parameters set in `tcapif.def`. These parameter cannot be set on the command line.

`sigtran.config` example

SIGTRAN TCAP Interface is installed with two `sigtran.config` files:

File	Description
<code>sigtran.config.example</code>	A full set of parameters showing example configuration with explanations.
<code>sigtran.config.simple</code>	Two very simple configurations. This file shows minimal configuration and does not include all available parameters.

You can use either of these files as a source to create the `sigtran.config` file which will actually be used by `sua_if/m3ua_if`.

Note: Some specific parameters (for example host names) will need to be amended in `sigtran.config` to run `sua_if/m3ua_if` correctly.

Using `eserv.config` instead of `sigtran.config`

You can put the `sigtran.config` configuration into the main `eserv.config` file for the machine you are running `sua_if/m3ua_if` on. If you do this, you will need to change the `ESERV_CONFIG_FILE` environmental variable in the Interface's startup script. For more information about the `ESERV_CONFIG_FILE` environmental variable, see *ESERV_CONFIG_FILE* (on page 11).

Editing the File

Open the configuration file on your system using a standard text editor. Do not use text editors, such as Microsoft Word, that attach control characters. These can be, for example, Microsoft DOS or Windows line termination characters (for example, `^M`), which are not visible to the user, at the end of each row. This causes file errors when the application tries to read the configuration file.

Always keep a backup of your file before making any changes to it. This ensures you have a working copy to which you can return.

Loading configuration changes

If you change the configuration, you must send a SIGHUP to sua_if/m3ua_if to enable the new options to take effect.

sigtran.config structure

This text shows the structure of the **sigtran.config** file.

```

SUA = {
    ansi = true|false
    maxSLS = int
    maxDids = int
    rejectTimeout = secs
    invokeTimers = true|false
    log = true|false
    xudtHopCount = int
    retAddrAll = true|false
    qos = int
    opc = dec int
    stpPCs = [ pc[, pc, ...] ]
    statisticsInterval = secs
    networkDebug = true|false

    connections = {
        name = {
            remote_host = [ "itp"[, "itp"] ]
            [remote_port = port]
            [local_host = [ "host"[, "host"] ]]
            [local_port = port]
            [remote_role = "sg|as|as_only|*"]

            routing_context = int
            traffic_mode_type = "mode"
            [message_priority = int]
            [importance = 0|1]
            [network_indicator = 0|1]
            [network_appearance = int]
            [asp_identifier = int]
            [application_server = "str"]
            [transport = "sctp|tcp"]
            [initiation = "str"]
            [rcvbuf = bytes]
            [sndbuf = bytes]
            [sctp_ostreams = int]
            [sctp_istreams = int]
            [sctp_hbinterval = millisecs]
            [sctp_init_timeout = secs]
            [default_gt = "gt"]
            [activate = "down|up|active"]
            [segment_size = bytes]
            [asp_identifier = int]
            [use = "name"]

            [gtt_pc = pc]
            [gtt_ssn = ssn]
            [gtt_remove = true|false]
            [gtt_route_pc = true|false]
            [gtt_np = int]
        }
        [...]
    }
}

routes = [

```

```

{
    [first = pc|gt last = pc|gt]
    [peer = pc]
    [priority = int]
    [label = "str"]
    [use = "str"]
    [connection parameters]
    [connection parameters]
}
[...]
]

classifiers = [
{
    [routing_indicator = int]
    [address_indicator = int]
    [subsystem_number = ssn]
    [point_code = pc]
    [gti = int]
    [trans_type = int]
    [num_plan = int]
    [nature_of_add = noa]

    [source_routing_indicator = int]
    [source_address_indicator = int]
    [source_subsystem_number = ssn]
    [source_point_code = pc]
    [source_gti = int]
    [source_trans_type = int]
    [source_num_plan = int]
    [source_nature_of_add = noa]

    label = "str"
}
[...]
]
}

M3UA = {
    sigtran.config parameters
    japanese_sccp = true|false
    connections = {
        {
            other connection parameters
            mtp3_dpc = pc
        }
        [...]
    }
    routes = [
        routes
    ]
    [classifiers = [class matches]]
}

```

sigtran.config parameters

The configuration variables available in **sigtran.config** for sua_if and m3ua_if are listed below.

ansi

Syntax: ansi = true|false

Description: Use ANSI or ITU addressing selection.

Type: Boolean
Optionality:
Allowed: true ANSI addressing
false ITU addressing
Default: false
Notes: This is only used when converting a SUA address in a received packet into an SCCP address. In all other cases, the national indicator field of the address is used for that purpose.
Example: `ansi = false`

asn1_validate

Syntax: `asn1_validate = value`
Description: How to validate incoming ASN.1 data.
Type: Integer
Optionality: Optional (default used if not set).
Allowed: 0 to 3
Default: 3
Notes: Options are:
0 = no validation.
1 = validate but silently discard broken packets.
2 = validate and short syslog message for broken packets.
3 = validate and syslog broken packet contents.
Example: `asn1_validate = 2`

classifiers

Syntax: `classifiers = [{class1}{class2}...]`
Description: Defines the classification match patterns.
Type: Array
Optionality: Optional (if not set, all matching done in Route section).
Allowed:
Default: None
Notes: For more information about the configuration available for classifiers, see *Classifier parameters* (on page 44).
Example: `classifier = [`
 `{`
 `trans_type = 9`
 `label = "message-class-1"`
 `}`
 `{`
 `trans_type = 9`
 `num_plan = 1`
 `label = "message-class-2"`
 `}`
`]`

connections

Syntax:

```
connections = {
    name = {parameters}
    [name = {parameters}]
    [...]
}
```

Description: This section defines how packets are passed from sua_if to the destination ITP/STP.

Type: Array

Optionality: Mandatory

Allowed:

Default: None

Notes: The same connection can be used for multiple routes. This removes the need to configure the same connection information each time the connection is used by a route.

Connections can inherit details from other connections using the 'use' parameter. If this is done, you can override inherited details by re-specifying a parameter within the inheriting connection.

Routes use connections by inheriting the connection details using the 'use' parameter. Like connections, you can override inherited details by specifying them within the route.

Only connections listed in the routes section are actually used.

For details of the parameters which can be used to define a connection, see *Connection parameters* (on page 32).

Example:

```
connections = {
    default = {
        remote_host = "supitp1"
        remote_port = 15000
        local_port = 14001
    }
    secondary = {
        use = "default"
        remote_host = "supitp2"
        asp_identifier = 1234
    }
}
```

default_retgt

Syntax: default_retgt = "str"

Description: Defines the default return Global Title which will be used when retgt_mapping is set and a match cannot be found for the return address.

Type: String

Optionality: Optional

Allowed: none

"1,noa,address_digits"

"2,trans_type,address_digits"

"3,trans_type,num_plan,address_digits"

"4,trans_type,num_plan,noa,address_digits"

Default: none

Notes:	The variables used in the gt are:
	<i>noa</i> Nature of Address
	<i>address_digit</i> Destination/Called Party Number
	<i>trans_type</i> Transmission Type
	<i>num_plan</i> Number Plan
Example:	default_retgt = "4,0,1,2,44321456"

retgt_mapping

Syntax:	retgt_mapping = [{ from="str", to = "str"}, { from="str", to = "str"},]
----------------	--

Description:	Used to map return addresses. The mapping will be applied to every outgoing message. If there is no match for the return address then the value defined for default_retgt will be used.
---------------------	---

Type:	Array
--------------	-------

Optionality:	Optional.
---------------------	-----------

Allowed:	"str" can be replaced with:
-----------------	-----------------------------

"1,noa,address_digits"
"2,trans_type,address_digits"
"3,trans_type,num_plan,address_digits"
"4,trans_type,num_plan,noa,address_digits"

Default:	Defaults to mapping set in default_retgt
-----------------	--

Notes:	Variables used are:
---------------	---------------------

<i>noa</i>	Nature of Address
<i>address_digits</i>	Destination/Called Party Number
<i>trans_type</i>	Transmission Type
<i>num_plan</i>	Number Plan

Example:	retgt_mapping = [{ from="4,0,1,4,123", to = "4,0,1,4,441482255436"}, { from="4,0,1,4,4414782255436", to = "4,0,1,4,441482255436"},]
-----------------	--

Note: In this example, the first entry maps the 123 address to the 441482255436 address. The second entry ensures this address is used in the future. Otherwise the setting from default_retgt will be used.

invokeTimers

Syntax:	invokeTimers = true false
----------------	---------------------------

Description:	Whether to run invoke timers or not.
---------------------	--------------------------------------

Type:	Boolean
--------------	---------

Optionality:	
---------------------	--

Allowed:	true	Run invoke timers.
	false	Do not run invoke timers.

Important: Turning off invoke timers will cause extremely non-standard TCAP behavior. It should only be done in highly specialized circumstances after careful consideration of the consequences. Do not set invokeTimers to false without detailed consultation with Oracle about possible effects.

Default:

true

Notes:

For more information about invoke timers, see Q.774 3.2.1.1.3.

Example:

invokeTimers = true

invokeTimerOverride

Syntax:

invokeTimerOverride = *seconds*

Description:

Override invoke timers with a default global value in seconds.

Type:

Integer

Optionality:

Optional (default used if not set).

Allowed:

Valid values are 0 - 3600. See Q.774 3.2.1.1.3.

Default:

0

Notes:

0 = Do not override invoke timers.

This configuration item is normally used for services that require interactions which last for >30 seconds (for example, some USSD services).

Example:

invokeTimerOverride = 0

Warning: This configuration item is normally used for services that require interactions which last for >30 seconds (for example some USSD services).

Changing invoke timers will cause extremely non-standard TCAP behavior, and this should only be done in highly specialized circumstances after careful consideration of the consequences. Do not change invokeTimerOverride without detailed consultation with Oracle as to the resultant behavior.

log

Syntax:

log = true|false

Description:

Controls SCCP logging.

Type:

Boolean

Optionality:

Allowed:

true All SCCP level traffic is logged to /tmp.

false SCCP logging is not done.

Default:

false

Notes:

This may be toggled at run-time by sending a SIGUSR1 to the TCAP Interface. SCCP logging is done at the SCCP level for both SUA and M3UA.

Example:

log = false

maxDids

Syntax:

maxDids = *int*

Description:

Maximum number of in-progress transactions.

Type:

Integer

Optionality: Optional
Allowed: Positive integer
Default: 100000
Notes: This parameter is not reloaded on SIGHUP.
Example: maxDids = 100000

maxSLS

Syntax: maxSLS = *int*
Description: Maximum Signalling Link Selection to use.
Type: Integer
Optionality: Optional
Allowed: Positive integer
Default: 255
Notes: The SLS determines the:

- Specific SS7 link that an ITP will send a packet over
- SCTP stream the TCAP Interface will use.

Example: maxSLS = 255

networkDebug

Syntax: networkDebug = *true|false*
Description: Whether or not to turn on the sigtran_network debug facility.
Type: Boolean
Optionality: Optional (if not specified, the sigtran_network setting from the DEBUG environment variable is used).
Allowed:

true	Use the sigtran_network debug.
false	Use the sigtran_network setting from the DEBUG environment variable.

Default: false
Notes: The debug produces is one line per packet of debug info and some per-connection stats approximately once per second.
Example: networkDebug = true

opc

Syntax: opc = *dec int*
Description: Local point code for outgoing messages.
Type: Decimal integer
Optionality: Mandatory
Allowed:

any valid point code	This point code will be set as the local point code in outgoing messages.
-1	Use other methods to set local point code. If you use this, you must be careful to make sure that all outgoing messages get a valid originating address.

Note: Only valid for SUA.

Default:
Notes: Parameter is given as an integer.

Example:	An ITU point code of 1-1-1 is configured as: opc = 2057
qos	
Syntax:	qos = <i>int</i>
Description:	SCCP/SUA protocol class.
Type:	Decimal integer
Optionality:	
Allowed:	0 unordered delivery, no error returns 1 ordered delivery, no error returns 128 unordered delivery, return on error 129 ordered delivery, return on error
Default:	1
Notes:	If you wish to have your packets randomly re-ordered, set to 0. Otherwise leave as the default 1.
Example:	qos = 1
rejectTimeout	
Syntax:	rejectTimeout = <i>secs</i>
Description:	Reject timeout as specified in Q.774 3.2.1.1.3.
Type:	Integer
Optionality:	
Allowed:	0 No timer. Important: Turning off reject timers will cause extremely non-standard TCAP behavior. It should only be done in highly specialized circumstances after careful consideration of the consequences. Do not set rejectTimeout to 0 without detailed consultation with Oracle about possible effects.
	Positive integer Reject timeout.
Default:	1
Notes:	
Example:	rejectTimeout = 10
retAddrAll	
Syntax:	retAddrAll = <i>true false</i>
Description:	Indicates how to change the return address on a received transaction.
Type:	Boolean
Optionality:	
Allowed:	false Apply strict Q.774 logic for changing the return address on a received transaction. true The return address may be changed at any stage of the transaction.

Default:	false
Notes:	
Example:	retAddrAll = true
routes	
Syntax:	<pre>routes = [{route1} [{route2}] [...]]</pre>
Description:	Matches details in outgoing packets and sets the packets destination details.
Type:	Array
Optionality:	Mandatory
Allowed:	
Default:	None
Notes:	<p>Each route matches details in outgoing traffic and routes it to a specific destination (usually specified by the connection set by the use parameter). Matching details include one of the following:</p> <ul style="list-style-type: none">• A range of point-codes (numeric)• A range of GT prefixes (strings) <p>If two (or more) routes have identical ranges, they are merged and all the endpoints used. If one range is strictly contained within another, the narrower range overrides the larger.</p> <p>Outgoing traffic may also match details in the classifiers section, which will then use the route with the same label to define the destination.</p> <p>For more information about the configuration available for routes, see <i>Route parameters</i> (on page 42).</p>
Example:	<pre>routes = [{ first = 0 last = 16777215 use = "default" } { first = 0 last = 16777215 use = "secondary" }]</pre>
scmg_ssn	
Syntax:	scmg_ssn = int
Description:	The sub-system number for SCMG processing by the M3UA interface.
Type:	Integer
Optionality:	Optional (default used if not set).
Allowed:	Integer value between -1 and 255
Default:	-1. No SCMG processing will take place.
Notes:	
Example:	scmg_ssn = 1

statisticsInterval

Syntax: statisticsInterval = *secs*
Description: How often in seconds to notify statistics to syslog.
Type: Decimal integer
Optionality:
Allowed: 0 turn off notification
positive integer notification period
Default: 0
Notes:
Example: statisticsInterval = 0

stpPCs

Syntax: stpPCs = [*stp1*[, *stp2*, ...]]
Description: Failover routing to the routes configured in the routes = [] section.
Type: Decimal integer
Optionality: Optional
Allowed:
Default:
Notes: The routing logic follows these steps:
1 Attempt to route a packet directly to its real destination address.
2 If that fails, choose an STP point code from the stpPCs list, and route using that point code.
This gives two separate mechanisms for spreading traffic over multiple destinations. The stpPCs list is more limited (because it applies to all destinations) but it is integrated with TCAP dialogs (it ensures multiple packets on the same TCAP dialog use the same STP PC).
The STP list can also be specified on the command line. The command line configuration will override any set here.
The whitespace used within the square brackets does not affect the parsing of the STP references.
For more information about TCAP dialogs, see *Service Logic Execution Environment Technical Guide*.
Example: stpPCs = [1234, 1235]

xudtHopCount

Syntax: xudtHopCount = *int*
Description: The hop count to send on protocols that support it.
Type: Decimal integer
Optionality:
Allowed: -1 Do not set a hop count
1-255 Hop count
Default: -1
Notes: For SCCP over M3UA, we send UDTs if the hop count is -1, and XUDTs otherwise.
Example: xudtHopCount = -1

Connection key configuration

These parameter values identify which connection a route uses.

- local_host
- local_port
- remote_host
- remote_port
- transport

Connection parameters

The connections subsection of the `sigtran.config` configuration supports these parameters.

```
connections = {
    name = {
        remote_host = [ "itp" [, "itp"] ]
        [remote_port = port]
        [local_host = [ "host" [, "host"] ]]
        [local_port = port]
        [remote_role = "sg|as|as_only|*"]

        routing_context = int
        traffic_mode_type = "mode"
        [message_priority = int]
        [importance = 0|1]
        [network_indicator = 0|1]
        [network_appearance = int]
        [asp_identifier = int]
        [application_server = "str"]
        [transport = "sctp|tcp"]
        [initiation = "str"]
        [rcvbuf = bytes]
        [sndbuf = bytes]
        [sctp_ostreams = int]
        [sctp_istreams = int]
        [sctp_hbinterval = millisecs]
        [sctp_init_timeout = secs]
        [default_gt = "gt"]
        [activate = "down|up|active"]
        [segment_size = bytes]
        [asp_identifier = int]
        [use = "name"]

        [gtt_pc = pc]
        [gtt_ssn = ssn]
        [gtt_remove = true|false]
        [gtt_route_pc = true|false]
        [gtt_np = int]
    }
    [...]
}
```

The parameters in this subsection are described in detail below.

activate

Syntax: `activate = "down|up|active"`
Description: Set the target state for a connection.
Type: String
Optionality: Optional

Allowed:	down	Connection is disabled.
	up	Connection will change to UP state (but not ACTIVE). Remote attempts to activate will get a management-blocking error.
	active	Connection will be allowed to change to ACTIVE state following the normal process.

Default: active

Notes:

Example: activate = "active"

application_server

Syntax: application_server = "str"

Description: The remote peers may be grouped into application servers for override handling. If the peers are override, then we try and maintain only one ASP active in each AS at any one time.

Type: String

Optionality: Optional

Allowed: Any name for the AS to which the ASPs belong.

Default: By default, the interface attempts to guess the ASP to AS groupings from the routing information.

Notes: Override default by specifying a name for the AS to which some ASPs belong.

Example: application_server = "appserver1"

asp_identifier

Syntax: asp_identifier = int

Description: The ASP Identifier sent to the SGP.

Type: Decimal integer

Optionality: Optional

Allowed:

Default:

Notes: This is an arbitrary number expected by the remote entity.

Example: asp_identifier = 5

default_gt

Syntax: default_gt = "gt"

Description: Override outgoing calling party address with route on PC/SSN to one of the following:

- Route on GT
- Using the specified GT

Type: Numeric string

Optionality: Optional

Allowed:

Default: The default is to not set this parameter (leave PC/SSN routing alone).

Notes: For most purposes, the *retgt* (on page 17) command line parameter will provide more predictable behaviour.

Example: default_gt = "12345678"

gtt_pc

Syntax: gtt_pc = *pc*

Description: Sets point code for Global Title Translation parameters used to set a PC on the destination address.

Type: Decimal integer

Optionality: Optional

Allowed:

Default:

Notes: Used for routing an outgoing packet on GT.

The PC & SSN supplied by GTT only effect the packet content - it does not change where we send it. The GTT will not override a PC and SSN already on the address.

The GTT parameters are ignored when routing on PC/SSN.

Example: gtt_pc = 1234

gtt_np

Syntax: gtt_np = *int*

Description: Sets NP for Global Title Translation parameters used to set a PC and SSN on the destination address.

Type: Integer

Optionality: Optional

Allowed:

Default:

Notes: gtt_np has no effect if gtt_remove is set, or if the GT type does not have an NP.

ITU GTI 3 and 4 have NP.

ITU GTI 1 and 2 do not have NP.

Example:

gtt_remove

Syntax: gtt_remove = *true|false*

Description: Defines GT details in outgoing message using GT routing.

Type: Boolean

Optionality: Optional

Allowed: true Remove GT and replace with PC.

false Leave existing GT.

Default: false

Notes:

Example: gtt_remove = true

gtt_route_pc

Syntax: gtt_route_pc = *true|false*

Description: Whether or not to override routing indicator.

Type: Boolean

Optionality: Optional

Allowed:	true	Route on PC.
	false	Do not change routing indicator.
Default:	false	
Notes:		
Example:	gtt_route_pc = true	
 gtt_ssn		
Syntax:	gtt_ssn = <i>ssn</i>	
Description:		Sets Subsystem Number for Global Title Translation parameters used to set an SSN on the destination address.
Type:	Hex integer	
Optionality:	Optional	
Allowed:		
Default:		
Notes:		Used for routing an outgoing packet on GT.
		The PC & SSN supplied by GTT only effect the packet content - it does not change where we send it. The GTT will not override a PC and SSN already on the address.
		The GTT parameters are ignored when routing on PC/SSN.
Example:	gtt_ssn = 11	
 importance		
Syntax:	importance = 0 1	
Description:		Sets the SCCP XUDT/LUDT and SUA importance field.
Type:	Boolean	
Optionality:	Optional	
Allowed:	0	Sets field to 0 (normal)
	1	Sets field to 1 (important)
Default:	0	
Notes:		
Example:	importance = 0	
 initiation		
Syntax:	initiation = "str"	
Description:		Overrides the default action for local and remote ports.
Type:	String	
Optionality:	Optional	
Allowed:	listen	Listen for incoming connections.
	connect	Attempt to connect to remote peer.
	none	Do not listen or attempt to connect.
	both	Listen for incoming connections and attempt to connect to remote peer.
Default:		By default, if the local_port is specified, TCAP Interface listens for incoming connections, and if the remote_port is given, TCAP Interface attempts to connect.
Notes:		In some circumstances the default behavior may be undesirable.

Examples:

- Where the remote end must use a fixed port number but we want the remote end to initiate the connection).
- When using SIGTRAN over TCP, listening on a port means that you can't later connect using that local port.

Example: initiation = "connect"

local_host

Syntax: Either:

- local_host = "localAddr"
- local_host = ["localAddr1", "localAddr2" [, ...]]

Description: IP address or hostname of local host.

Type: String

Optionality: Optional

Allowed: Any valid:

- hostname
- hostname and domain
- ip address

Default:

Notes: Using an array of remote hosts provides control over the SCTP multi-home functionality. The local_host list is used to bind the local socket.

If you leave the local_host unset, the SCTP will enable multi-homing over all addresses.

The connections are identified internally by only the first remote_host.

Examples:
local_host = "produas01.telcoexample.com"
local_host = ["localAddr1", "localAddr2"]

local_port

Syntax: local_port = *port*

Description: Local host port number.

Type: Decimal integer

Optionality: At least one of remote_port and local_port must be specified. If using SCTP, both may be specified.

Allowed:

Default: If not set, the Operating System will set a port for outgoing messages.

Notes:

Example: local_port = 14001

message_priority

Syntax: message_priority = *int*

Description: Sets the MTP3 message_priority field in outgoing M3UA packets.

Type: Decimal integer

Optionality: Optional

Allowed:

Default: 0

Notes: If not set, is set to zero in M3UA packets and omitted from SUA packets.

Example:	message_priority = 0
	network_appearance
Syntax:	network_appearance = <i>int</i>
Description:	M3UA network appearance value sent in M3UA packets sent to the network.
Type:	Integer
Optionality:	Optional
Allowed:	
Default:	0
Notes:	If not set, this field is omitted from M3UA packets sent to the network.
Example:	network_appearance = 10
	routing_context
Syntax:	routing_context = <i>int</i>
Description:	The SIGTRAN routing context.
Type:	Decimal integer
Optionality:	Generally mandatory for SUA. Generally optional for M3UA.
Allowed:	32-bit integers
Default:	
Notes:	The context is derived from the ACTIVE handshake if possible.
Example:	routing_context = 666
	network_indicator
Syntax:	network_indicator = 0 2
Description:	Sets the value of the MTP3 network indicator in outgoing messages. 0000 International 0010 National
Type:	A 4-bit binary field
Optionality:	Mandatory
Allowed:	0, 2
Default:	0
Notes:	As defined by ANSI / ITU-T
Example:	network_indicator = 0
	rcvbuf
Syntax:	rcvbuf = <i>bytes</i>
Description:	Receive buffer size.
Type:	Decimal integer
Optionality:	Optional
Allowed:	0 Use the OS default. positive integer Set the rcvbuf value in outgoing messages. Must not be less than 32768.
Default:	0

Notes: **Important:** This value needs to cover all outstanding unacknowledged SCTP data on the network. If you set these to a non-zero value, it is unlikely to work properly if set to less than 64000.

Do not change this parameter from the default value without calculating the new value based on network conditions. The defaults should work fine in all but the highest traffic conditions.

Example: `rcvbuf = 131072`

`remote_host`

Syntax: Either:

- `remote_host = "itpAddr"`
- `remote_host = ["itpAddr1", "itpAddr2", ...]`

Description: Location of the remote host(s).

Type: String or array of comma-separated strings.

Optionality: Mandatory

Allowed: Any valid:

- hostname
- hostname and domain
- ip address

Default:

Notes: Using an array of remote hosts provides control over the SCTP multi-home functionality. When connecting, `remote_host` gives the candidate peer addresses. When listening, and incoming connection matches if its primary IP address matches any of the `remote_hosts`.

The connections are identified internally by only the first `remote_host`.

Examples: `remote_host = "itp"`

`remote_host = ["itp1", "itp2"]`

`remote_port`

Syntax: `remote_port = port`

Description: Port to connect to on `remote_host`.

Type: Decimal integer

Optionality: At least one of `remote_port` and `local_port` must be specified. If using SCTP, both may be specified.

Allowed:

Default: If not set, the operating system will accept connections from any remote port.

Notes:

Example: `remote_port = 26600`

`remote_role`

Syntax: `remote_role = "sg|as|as_only|*"`

Description: How UPs and ACTIVEs are expected to flow between TCAP Interface and peer.

Type: String

Optionality: Optional, default is used if not set.

Allowed: sg Peer is expected to receive UPs and ACTIVEs but not send them to us.
 as UPs and ACTIVEs should go both ways.
 as_only Peer is expected to send UPs and ACTIVEs but we will not send them to the peer.
 * Both ways are attempted, but only one direction needs to be active for data to flow.

Default: `""`

Notes: `""` should work in most circumstances.

Example: `remote_role = "sg"`

`sctp_hbinterval`

Syntax: `sctp_hbinterval = millisecs`

Description: SCTP heartbeat interval in milliseconds.

Type: Decimal integer

Optionality: Optional (default used if not set).

Allowed: 0 Turn off heartbeat messages.
 positive integer Heartbeat interval.

Default: 1000

Notes: To speed up failover behavior, it may help to reduce some kernel-level parameters using the `ndd` command, including:

- `sctp_pp_max_retr`
- `sctp_rto_min`
- `sctp_rto_max`
- `sctp_rto_initial`.

Example: `sctp_hbinterval = 2500`

`sctp_init_timeout`

Syntax: `sctp_init_timeout = secs`

Description: Gives the maximum time the SIGTRAN stack will allow for an SCTP association to form. If the association fails to form within this time, the attempt is abandoned and a new attempt is begun.

Type: Decimal integer

Optionality: Optional (default used if not set).

Allowed: 0 No timeout will be applied and the operating system's values are all that will be used.
 positive integer Length of timeout, in seconds

Default: 5

Notes: Note that this interacts very heavily with the operating system's SCTP timeout values. Its purpose is to ensure that the SIGTRAN stack will attempt to form a connection at least every time the timeout fires. The default of five seconds means that no matter how the operating system is configured the SIGTRAN stack will attempt to connect every five seconds. This is very useful in case the operating system has not been configured or has been incorrectly configured. Setting `sctp_rto_max` to 1000 (the units are milliseconds) will ensure that the connection is retried every second thus giving us the fastest restart time.

Example: `sctp_init_timeout = 5`

sctp_istreams

Syntax: sctp_istreams = *int*
Description: Number of SCTP input streams per connection.
Type: Decimal integer
Optionality: Optional (default used if not set).
Allowed: 0 Use the OS default.
positive integer Maximum number of SCTP input streams per connection.
Default: 0
Notes:
Example: sctp_istreams = 10

sctp_ostreams

Syntax: sctp_ostreams = *int*
Description: Number of SCTP output streams per connection.
Type: Decimal integer
Optionality: Optional (default used if not set).
Allowed: 0 Use the OS default.
positive integer Maximum number of SCTP output streams per connection.
Default: 0
Notes:
Example: sctp_ostreams = 10

segment_size

Syntax: segment_size = *bytes*
Description: The maximum number of bytes allowed in a segment in an SCCP payload.
Type: Decimal integer
Optionality: Optional
Allowed:
Default: If not set, segmentation will not be performed.
Notes: Over SCCP/M3UA, only used if xudtHopCount is set (so that XUDT packets are sent). If sudtHopCount is not set, then UDT packets are sent, and segment_size is ignored.
If set, and network is SUA, segment_size is always applied.
Example: segment_size = 255

sndbuf

Syntax: sndbuf = *bytes*
Description: Send buffer size, in bytes.
Type: Decimal integer
Optionality: Optional
Allowed: 0 Use the OS default.
positive integer Specifies maximum size of buffer for outgoing messages. Must not be less than 32768.

Default:	0
Notes:	<p>Important: This value needs to cover all outstanding unacknowledged SCTP data on the network. If you set these to a non-zero value, it is unlikely to work properly if set to less than 64000.</p> <p>Do not change this parameter from the default value without calculating the new value based on network conditions. The defaults should work fine in all but the highest traffic conditions.</p>
Example: <code>sndbuf = 131072</code>	

`traffic_mode_type`

Syntax:	<code>traffic_mode_type = "mode"</code>								
Description:	Traffic mode type.								
Type:	String								
Optionality:	Optional. However, if not set, <code>sua_if/m3ua_if</code> will be using loadshare and peers may not be, which will result in ITPs failing.								
Allowed:	<table> <tr> <td><code>override</code></td> <td>SIGTRAN override, <code>sua_if/m3ua_if</code> will wait for a request before setting a connection to active.</td> </tr> <tr> <td><code>override_primary</code></td> <td>SIGTRAN override, <code>sua_if/m3ua_if</code> will set connections to active as soon as possible.</td> </tr> <tr> <td><code>loadshare</code></td> <td><code>sua_if/m3ua_if</code> will send messages on sequential connections in a round robin (one after the other) pattern.</td> </tr> <tr> <td><code>broadcast</code></td> <td><code>sua_if/m3ua_if</code> will send messages on all applicable connections.</td> </tr> </table>	<code>override</code>	SIGTRAN override, <code>sua_if/m3ua_if</code> will wait for a request before setting a connection to active.	<code>override_primary</code>	SIGTRAN override, <code>sua_if/m3ua_if</code> will set connections to active as soon as possible.	<code>loadshare</code>	<code>sua_if/m3ua_if</code> will send messages on sequential connections in a round robin (one after the other) pattern.	<code>broadcast</code>	<code>sua_if/m3ua_if</code> will send messages on all applicable connections.
<code>override</code>	SIGTRAN override, <code>sua_if/m3ua_if</code> will wait for a request before setting a connection to active.								
<code>override_primary</code>	SIGTRAN override, <code>sua_if/m3ua_if</code> will set connections to active as soon as possible.								
<code>loadshare</code>	<code>sua_if/m3ua_if</code> will send messages on sequential connections in a round robin (one after the other) pattern.								
<code>broadcast</code>	<code>sua_if/m3ua_if</code> will send messages on all applicable connections.								
Default:	If not specified or negotiated, <code>loadshare</code> is used.								
Notes:									
Example:	<code>traffic_mode_type = "loadshare"</code>								

`transport`

Syntax:	<code>transport = "sctp tcp"</code>				
Description:	The transport type for this connection.				
Type:	String				
Optionality:	Optional				
Allowed:	<table> <tr> <td><code>sctp</code></td> <td>SIGTRAN over SCTP</td> </tr> <tr> <td><code>tcp</code></td> <td>SIGTRAN over TCP</td> </tr> </table>	<code>sctp</code>	SIGTRAN over SCTP	<code>tcp</code>	SIGTRAN over TCP
<code>sctp</code>	SIGTRAN over SCTP				
<code>tcp</code>	SIGTRAN over TCP				
Default:	<code>sctp</code>				
Notes:	In normal networks, SCTP is always used.				
Example:	<code>transport = "sctp"</code>				

`use`

Syntax:	<code>use = "name"</code>
Description:	Base this connection configuration on the named connection.
Type:	String
Optionality:	Optional

Allowed:	Any already defined connection name.
Default:	
Notes:	This enables parameters to be redefined specifically for this connection without the need to repeat the unchanged ones.
Example:	<code>use = "PrimaryConnection"</code>

Route parameters

The routes subsection of the `sigtran.config` configuration supports these parameters.

Notes:

- All routes have the same parameters available as listed for *Connection parameters* (on page 32), plus those listed below for Route parameters.
- Routes can also use parameters from the *Classifier parameters* (on page 44) section, though this is only recommended for simple routing situations.

```
routes = [
{
    [first = pc|gt last = pc|gt]
    [peer = pc]
    [priority = int]
    [label = "str"]
    [use = "str"]
    [connection parameters]
    [connection parameters]
}
[...]
]
```

The parameters in this subsection are described in detail below.

first

Syntax:	Either:
	<ul style="list-style-type: none"> • <code>first = startPC</code> • <code>first = "startGT"</code>
Description:	The first number (Point Codes) or string (Global Title) in the range of destination addresses.
Type:	Decimal integer or Numeric string
Optionality:	Optional. Must be set if last is set. Must be set if peer is not set. Must not be set if peer is set.
Allowed:	
Default:	
Notes:	This number is inclusive.
Examples:	<pre>first = 0 first = "6441"</pre>

label

Syntax:	<code>label = "str"</code>
Description:	If a message has matched a classifier with the same label value as this parameter, the message can use this route.
Type:	String
Optionality:	Optional (not used if not set).

Allowed:

Default:	None (no label).
Notes:	If this route will be used by messages which have been matched in the <i>Classifier parameters</i> (on page 44) section, this string must match a label value exactly. If more than one route has the same label, qualifying messages will follow the usual routing match rules to determine which route to use.
Example:	<pre>label = "itp-special"</pre>
 last	
Syntax:	Either:
	<ul style="list-style-type: none"> • <code>last = endPC</code> • <code>last = "endGT"</code>
Description:	The last Point Code or Global Title prefix in the range of destination addresses.
Type:	Decimal integer or Numeric string
Optionality:	Optional. Must be set if first is set. Must be set if peer is not set. Must not be set if peer is set.
Allowed:	
Default:	
Notes:	This number is inclusive.
Examples:	<pre>last = 6441 last = "6441"</pre>
 peer	
Syntax:	<pre>peer = pc peer = "gt"</pre>
Description:	Point Code or Global Title prefix of the application server to connect to. Routes to a single point code instead of using the first and last parameters.
Type:	Point codes are decimal integer. Global Title prefixes are string.
Optionality:	Optional. Must be set if first or last are not set. Must not be set if first or last are set.
Allowed:	
Default:	None.
Notes:	<code>peer = "all_pc"</code> supplies a route covering all point codes. <code>peer = "**"</code> supplies a route covering all point codes and all global titles.
Examples:	<pre>peer = 131330 peer = "64321"</pre>
 priority	
Syntax:	<code>priority = priority</code>
Description:	The route's priority.
Type:	Decimal integer
Optionality:	
Allowed:	
Default:	0
Notes:	The usable routes with the highest priority will be used for a message.

If multiple routes with the same priority are given, they are round-robined (unless a remote ASP specifically requests override mode).

The priority is per route, not per-connection, so a priority 1 for a route is not shared with the other routes using the same connection (although an item in the 'connections' section above may be given a priority to be used unless overridden).

Example: priority = 1

use

Syntax: use = "route_name"

Description: Base this route configuration on the named route.

Type: String

Optionality: Optional

Allowed: Any already defined route name.

Default:

Notes: This enables parameters to be redefined specifically for this route without the need to repeat the unchanged ones.

Example: use = "PrimaryRoute"

Classifier parameters

The classifiers section is used to set up routing based on things other than the destination PC or global-tile digits. If one of the classifiers matches a message, then routes with the same 'label' as the classifier are used.

The classifiers are tested in order, and the first matching classifier is used. To match, a message must match all the conditions. If no classifiers match, then the routes with no label parameter are used.

This section is optional. The classifier-matches may be inserted directly into the 'routes' section. For more information about this, see *Route parameters* (on page 42).

```
classifiers = [
    {
        [routing_indicator = int]
        [address_indicator = int]
        [subsystem_number = ssn]
        [point_code = pc]
        [gti = int]
        [trans_type = int]
        [num_plan = int]
        [nature_of_add = noa]

        [source_routing_indicator = int]
        [source_address_indicator = int]
        [source_subsystem_number = ssn]
        [source_point_code = pc]
        [source_gti = int]
        [source_trans_type = int]
        [source_num_plan = int]
        [source_nature_of_add = noa]

        label = "str"
    }
    [...]
]
```

The parameters in this subsection are described in detail below.

address_indicator

Syntax: address_indicator = *int*
Description: For SUA, match against the address indicator field from the destination SUA address.
 For SCCP, match against the address indicator field from the destination SCCP address (the first byte of the SCCP address).
Type: Integer
Optionality: Optional, (if not set, no matching is done against address indicator).
Allowed:
Default: None.
Notes:
Example: address_indicator = 2

gti

Syntax: gti = *int*
Description: For SUA, match against the GTI field from the destination SUA address.
 For SCCP, match against the GTI field from the destination SCCP address (the middle 4 bits of the address indicator byte).
Type: Integer
Optionality: Optional, (if not set, no matching is done against GTI).
Allowed: For SCCP, only 0 through 4 are used.
Default: None.
Notes:
Example: gti = 2

label

Syntax: label = "str"
Description: Traffic which matches a classifier with this label, will be routed to the route which also specified this label.
Type: String
Optionality: Mandatory
Allowed:
Default: None.
Notes: Must be set for each classifier entry.
 If this value is not set, the traffic will route down the default route.
Example: label = "itp-special"

nature_of_add

Syntax: nature_of_add = *noa*
Description: Match against the NOA field from the destination SUA or SCCP address.
Type: Integer
Optionality: Optional, (if not set, no matching is done against NOA).
Allowed:

Default:	None.
Notes:	
Example:	<code>nature_of_add = 1</code>
num_plan	
Syntax:	<code>num_plan = int</code>
Description:	For SUA, match against the Number Plan field from the destination SUA address. For SCCP, match against the Numbering Plan in the destination SCCP address (the top four bits of the GT numbering plan / encoding scheme byte).
Type:	Integer
Optionality:	Optional, (if not set, no matching is done against number plan).
Allowed:	For SCCP, 0 - 15
Default:	None.
Notes:	
Example:	<code>num_plan = 2</code>
point_code	
Syntax:	<code>point_code = pc</code>
Description:	Match against the PC field from the destination SUA/SCCP address.
Type:	Integer
Optionality:	Optional, (if not set, no matching is done against point code).
Allowed:	
Default:	None.
Notes:	
Example:	<code>point_code = 1234</code>
routing_indicator	
Syntax:	<code>routing_indicator = int</code>
Description:	What details in the destination SUA/SCCP address to match against.
Type:	Integer
Optionality:	Optional, (if not set, no matching is done against routing indicator).
Allowed:	0 Route on GT 1 Route on PC and SSN.
Default:	None.
Notes:	
Example:	<code>routing_indicator = 1</code>
subsystem_number	
Syntax:	<code>subsystem_number = ssn</code>
Description:	Match against the SSN field from the destination SUA/SCCP address.
Type:	Integer
Optionality:	Optional, (if not set, no matching is done against SSN).
Allowed:	
Default:	None.
Notes:	

Example: subsystem_number = 8

trans_type

Syntax: trans_type = *int*

Description: Match against the translation type field from the destination SUA/SCCP address.

Type: Integer

Optionality: Optional (if not set, no matching is done against translation type).

Allowed: Any valid translation type.

Default: None.

Notes:

Example: trans_type = 9

M3UA route parameters

The M3UA configuration is almost identical to the SUA config. The only difference is the additional parameters listed here.

japanese_sccp

Syntax: japanese_sccp = true|false

Description: Japanese SCCP variant. Specifies whether SCCP addresses include a national-use (ANSI) bit.

Type: Boolean

Optionality: Optional

Allowed: True - SCCP addresses include an additional ANSI bit. The ANSI bit is ignored on incoming SCCP addresses and set on outgoing SCCP addresses.
False - SCCP addresses do not include an additional ANSI bit.

Default: False

Notes:

Example: japanese_sccp = true

The `connections` subsection of the `sigtran.config` configuration supports these parameters.

```
M3UA = {
    sigtran.config parameters
    japanese_sccp = true|false
    connections = {
        {
            other connection parameters
            mtp3_dpc = pc
        }
        [...]
    }
    routes = [
        routes
    ]
    [classifiers = [class matches]]
}
```

The parameters in this subsection are described in detail below.

mtp3_dpc

Syntax: mtp3_dpc = *pc*

Description: The destination point code required in MTP3 header.

Type: Decimal integer

Optionality:

Allowed:

Default:

Notes: There are three possible sources:

- The SCCP address
- The gtt_pc (when routing on GT)
- Explicitly configured

Example: mtp3_dpc = 3245

Example Configuration Scenarios

Example - route 2 PCs

This is a small and simple **eserv.config** for the SUA stack. This example routes to 2 PCs. However, because they are configured as STP PCs, traffic is re-directed to STPs. All end-points have two IP addresses, so SCTP multi-homing is used.

```

SUA = {
    # Local point code.
    opc = 2057
    # Failover list for failed traffic.
    stpPCs = [ 4101, 4102 ]

    connections = {
        itp1 = {
            # multi-home to both nics.
            remote_host = [ "itp1-nicA", "itp1-nicB" ]
            remote_port = 14001
            local_host = [ "local-nicA", "local-nicB" ]
            # specify routing context and loadshare for ITPs.
            routing_context = 666
            traffic_mode_type = "loadshare"
        }
        itp2 = {
            # multi-home to both nics.
            remote_host = [ "itp2-nicA", "itp2-nicB" ]
            remote_port = 14001
            local_host = [ "local-nicA", "local-nicB" ]
            # specify routing context and loadshare for ITPs.
            routing_context = 666
            traffic_mode_type = "loadshare"
        }
    }


    routes = [
        {
            peer = 4101          # Route all traffic to peer 4101 to
            use = "itp1"         # dest defined in connection 'itp1'.
        }
        {
            peer = 4102          # Route all traffic to peer 4102 to
            use = "itp2"         # dest defined in connection 'itp2'.
        }
    ]
}
```

```

        }
    ]
}
}
```

Diagram - route 2 PCs

Here is a diagram which shows some of the features of the example.



Example - route all to balanced ITPs

This example directly routes all PCs and all GTs to a pair of load-balanced ITPs (itp1 and itp2).


```

SUA = {
    opc = 2057
    connections = {
        multi-home = {
            # multi-home to both itps.
            remote_host = [ "itp1", "itp2" ]
            remote_port = 14001
            local_host = [ "localhost" ]
            routing_context = 666
            traffic_mode_type = "loadshare"
        }
    }
    routes = [
        {
            peer = "*"          # Route all traffic to
            use = "multi-home" # destns in connection 'multi-home'.
        }
    ]
}
```

Note: The STP mechanism is not used, so the TCAP transactions are not tracked (as there is only one destination, that doesn't matter).

Diagram - route all to balanced ITPs

Here is a diagram which shows some of the features of the example.



Example - route on transmission type

This example directly routes all PCs and all GTs to an ITP (itp1), except for traffic with transmission type 9 which goes to itp3.

```

SUA = {
    opc = 2057

    connections = {
        multi-home = {
            # multi-home to both itps.
            remote_host = [ "itp1", "itp2" ]
            remote_port = 14001
            local_host = [ "localhost" ]
            routing_context = 666
            traffic_mode_type = "loadshare"
        }
        itp3 = {
            remote_host = "itp3" # Send to itp3.
            use = "multi-home" # Use main config to set defaults.
        }
    }

    routes = [
        {
            peer = "*" # Route all traffic to
            use = "multi-home" # destns in connection 'multi-home'.
        }
        {
            label = "tt9" # Class 'tt9' will use
            use = "itp3" # dest defined in connection 'itp3'.
        }
    ]
}
  
```


```

classifiers = [
    {
        trans_type = 9      # Route all traffic with transmission type 9
        label = "tt9"      # to dest in route labelled 'tt9'
    }
]
}

```

Diagram - route on transmission type

Here is a diagram which shows some of the features of the example.



Chapter 3

Background Processes

Overview

Introduction

This chapter explains the processes that are started automatically by Service Logic Execution Environment (SLEE).

Note: This chapter also includes some plug-ins to background processes which do not run independently.

In this chapter

This chapter contains the following topics.

sua_if	53
m3ua_if.....	54

sua_if

Purpose

sua_if is the main binary in the SIGTRAN TCAP Interface, for a SUA installation.

Startup

sua_if is an SLEE Interface and is started during SLEE initialization. The line in the **SLEE.cfg** which starts the sua_if is:

```
INTERFACE=sua_if sua_if.sh /IN/service_packages/SLEE/bin EVENT
```

For instructions about starting and stopping sua_if, see *Service Logic Execution Environment Technical Guide*.

Configuration

sua_if is configured by the:

- File set by the **ESERV_CONFIG_FILE** environmental variable (usually this will be **sigtran.config**)
- Command line parameters that can also be set in **tcapif.def**

For more information about configuring this binary, see *Configuration Overview* (on page 9).

Output

The sua_if process writes error messages to the system messages file. It also writes additional output to the **/IN/service_packages/SLEE/tmp/sigtran.log** file.

m3ua_if

Purpose

m3ua_if is the main binary in the SIGTRAN TCAP Interface, for a M3UA installation.

Startup

m3ua_if is an SLEE Interface and is started during SLEE initialization. The line in the **SLEE.cfg** which starts the m3ua_if is:

```
INTERFACE=m3ua_if m3ua_if.sh /IN/service_packages/SLEE/bin EVENT
For instructions about starting and stopping m3ua_if, see Service Logic Execution Environment Technical Guide.
```

Configuration

m3ua_if is configured by the:

- File set by the **ESERV_CONFIG_FILE** environmental variable (usually this will be **sigtran.config**)
- Command line parameters that can also be set in **tcapif.def**.

For more information about configuring this binary, see *Configuration Overview* (on page 9).

Output

The sua_if process writes error messages to the system messages file. It also writes additional output to the **/IN/service_packages/SLEE/tmp/sigtran.log** file.

Troubleshooting

Overview

Introduction

This chapter explains the important processes on each of the server components in NCC, and describes a number of example troubleshooting methods that can help aid the troubleshooting process before you raise a support ticket.

In this chapter

This chapter contains the following topics.

Common Troubleshooting Procedures.....	55
Debug	55

Common Troubleshooting Procedures

Introduction

Refer to *System Administrator's Guide* for troubleshooting procedures common to all NCC components.

Debug

Introduction

sua_if/m3ua_if contains a logging capability that can be used to store messages received and sent by the stack.

Messages are recorded at SCCP-level for both SUA and M3UA.

Setup

To turn on the SCCP-level message logging, set the log parameter to true, and reload the configuration.

Note: You can reload the configuration by sending the interface a SIGHUP.

For more information about the log parameter, see *log* (on page 27).

Output

Once logging is switched on the interface will append to a binary log file in `/IN/service_packages/SLEE/tmp`.

Output is in the form of raw data which can be decoded with the tcread program.

Statistics and Reports

Overview

Introduction

This chapter explains the statistics produced by the application, and the reports you can run on the statistics.

In this chapter

This chapter contains the following topics.

Statistics	57
------------------	----

Statistics

Introduction

The SIGTRAN TCAP Interface logs an array of statistics counters for each socket. Statistics are kept for:

- Errors
- Packets sent and received (per packet type)

Statistics for all connections

This table describes the statistics which are kept for all connections:

Statistic	Description
RX_total	Total packets received.
TX_total	Total packets sent.
RX_error	Number of errors when attempting to read a packet from a connection.
TX_error	Number of errors when attempting to write a packet to a connection.
RX_corrupt	Number of packets received that contain incorrect data. This may be: <ul style="list-style-type: none"> • Incorrectly formatted packets • Correctly formatted packet that is not valid for the current state of the connection
TX_congest	Number of outbound packets dropped due to transmit buffers being full.
connection_failures	Number of times an error has resulted in the connection being disconnected.

SUA connections

For each packet type (for example, CLDT) two statistics are kept with the:

- RX_ prefix, for packets received (for example, RX_CLDT).
- TX_ prefix, for packets sent (for example, TX_CLDT).

M3UA connections

For each packet type (for example: DATA) two statistics are kept with the:

- RX_ prefix, for packets received (for example, RX_DATA).
- TX_ prefix, for packets sent (for example, TX_DATA).

SCCP over M3UA connections

In addition to the M3UA statistics, for each SCCP packet type (for example: UDT) two statistics are kept with the:

- RX_SCCP_ prefix, for packets received (for example, RX_SCCP_UDT).
- TX_SCCP_ prefix, for packets sent (for example, TX_SCCP_UDT).

Note: A SCCP UDT packet contained in a M3UA DATA packet will be counted in both the relevant SCCP and M3UA counters.

About Installation and Removal

Overview

Introduction

This chapter provides information about the installed components for the Oracle Communications Network Charging and Control (NCC) application described in this guide. It also lists the files installed by the application that you can check for, to ensure that the application installed successfully.

In this Chapter

This chapter contains the following topics.

Installation and Removal Overview	59
Checking the Installation	59

Installation and Removal Overview

Introduction

For information about the following requirements and tasks, see *Installation Guide*:

- NCC system requirements
- Pre-installation tasks
- Installing and removing NCC packages

SIGTRAN packages

An installation of SIGTRAN includes the following packages, on the:

- SMS:
 - sigtranSms
- SLC:
 - sigtranScp

Checking the Installation

Introduction

Refer to these checklists to ensure that SIGTRAN TCAP Interface has installed correctly.

Checklist - SMS

Follow the steps in this checklist to ensure SIGTRAN TCAP Interface has been installed on a SMS machine correctly.

Step	Action
1	Log into the system as acs_oper.
2	Enter <code>sqlplus /</code> Note: No password is required.
3	Ensure that the SMF_STATISTICS_DEFN table in the SMF database has been updated to include SIGTRAN TCAP Interface entries.

Checklist - non-SMS

Follow the steps in this checklist to ensure SIGTRAN TCAP Interface has been installed on a non-SMS machine correctly.

Step	Action
1	Log into the machine as the user which operates the SLEE running on this machine.
2	Check the <code>/IN/service_packages/SLEE</code> directory structure exists with subdirectories.
3	Check the <code>/IN/service_packages/SLEE/bin</code> directory contains the following files: <ul style="list-style-type: none">• <code>sua_if</code>• <code>sua_if.sh</code>• <code>m3ua_if</code>• <code>m3ua_if.sh</code>
4	Check the <code>/IN/service_packages/SLEE/etc</code> directory contains the following files: <ul style="list-style-type: none">• <code>sigtran.conf.example</code>• <code>sigtran.conf.sample</code>

Process list

If the application is running correctly, the following processes should be running on each non-SMS machine:

- Started during SLEE startup, one of the following:
 - `sua_if`
 - `m3ua_if`