Oracle® Database Appliance X8-2 and Earlier Service Manual





Oracle Database Appliance X8-2 and Earlier Service Manual,

G42892-01

Copyright © 2025, Oracle and/or its affiliates.

Primary Author: Ralph Woodley

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software, software documentation, data (as defined in the Federal Acquisition Regulation), or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software," "commercial computer software documentation," or "limited rights data" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle®, Java, MySQL, and NetSuite are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Preface

Audience Documentation Accessibility	
Related Documents	
Conventions	
Overview of System Status Indicators and LEDs	
Oracle Database Appliance X8-2S/X8-2M Status Indicators	
Oracle Database Appliance X8-2S/X8-2M Server Status Indicators	
Oracle Database Appliance X8-2S Front Panel Status Indicators	
Oracle Database Appliance X8-2M Front Panel Status Indicators	
Oracle Database Appliance X8-2S/X8-2M Back Panel Status Indicators	
Oracle Database Appliance X8-2-HA Status Indicators	
Oracle Database Appliance X8-2-HA Server Node Status Indicators	-
Server Node Front Panel Status Indicators	-
Server Node Back Panel Status Indicators	1
Oracle Database Appliance X8-2-HA Storage Shelf Indicators	-
Storage Shelf Front Panel Status Indicators	1
Storage Shelf Back Panel Status Indicators	1
Oracle Database Appliance X7-2S/X7-2M Status Indicators	1
Oracle Database Appliance X7-2S/X7-2M Server Status Indicators	-
Server Front Panel Status Indicators	1
Server Back Panel Status Indicators	2
Oracle Database Appliance X7-2-HA Status Indicators	2
Oracle Database Appliance X7-2-HA Server Node Status Indicators	2
Server Node Front Panel Status Indicators	2
Server Node Back Panel Status Indicators	2
Oracle Database Appliance X7-2-HA Storage Shelf Indicators	2
Storage Shelf Front Panel Status Indicators	2
Storage Shelf Back Panel Status Indicators	2
Oracle Database Appliance X6-2S/X6-2M/X6-2L Status Indicators	3
Oracle Database Appliance X6-2S/X6-2M Server Status Indicators	3
Server Front Panel Status Indicators	3

Server Back Panel Status Indicators	33
Oracle Database Appliance X6-2L Server Status Indicators	35
Server Front Panel Status Indicators	35
Server Back Panel Status Indicators	37
Oracle Database Appliance X6-2-HA Status Indicators	39
Oracle Database Appliance X6-2-HA Server Node Status Indicators	39
Server Node Front Panel Status Indicators	39
Server Node Back Panel Status Indicators	42
Oracle Database Appliance X6-2-HA Storage Shelf Indicators	44
Storage Shelf Front Panel Status Indicators	44
Storage Shelf Back Panel Status Indicators	46
Oracle Database Appliance X5-2 Status Indicators	47
Oracle Database Appliance X5-2 Server Node Status Indicators	48
Server Node Front Panel Status Indicators	48
Server Node Back Panel Status Indicators	50
Oracle Database Appliance X5-2 Storage Shelf Indicators	52
Storage Shelf Front Panel Status Indicators	52
Storage Shelf Back Panel Status Indicators	54
Oracle Database Appliance X3-2/X4-2 Status Indicators	55
Oracle Database Appliance X3-2/X4-2 Server Node Status Indicators	55
Server Node Front Panel Status Indicators	55
Server Node Back Panel Status Indicators	58
Oracle Database Appliance X3-2/X4-2 Storage Shelf Indicators	60
Storage Shelf Front Panel Status Indicators	61
Storage Shelf Back Panel Status Indicators	62
Oracle Database Appliance Version 1 Status Indicators	63
Server Node Front Status Indicators	64
Server Node Fan Status Indicators	67
Server Node Storage and Boot Drive Status Indicators	68
Server Node Power Supply Status Indicators	69
Server Node Rear Status Indicators	70
Server Node Internal LEDs	71
Server Node Ethernet Port Status Indicators	72
Preparing Oracle Database Appliance for Service	
Preparing Oracle Database Appliance X8-2 Series for Service	1
Preparing Oracle Database Appliance X7-2 Series for Service	2
Preparing Oracle Database Appliance X6-2 Series for Service	2
Preparing Oracle Database Appliance X3-2/X4-2/X5-2 for Service	3
Preparing Oracle Database Appliance Version 1 for Service	4

2

3 Servicing CRUs That Do Not Require System Power Off

Oracle Database Appliance X8-2 Series Server Node Hot-Pluggable Components	1
Servicing NVMe Storage Drives (CRU)	2
Replacing an NVMe Storage Drive	3
Adding NVMe Expansion Storage	4
Oracle Database Appliance X7-2 Series Server Node Hot-Pluggable Components	6
Servicing NVMe Storage Drives (CRU)	7
Replacing an NVMe Storage Drive	7
Adding NVMe Expansion Storage	g
Oracle Database Appliance X6-2 Series Server Node Hot-Pluggable Components	10
Servicing NVMe Storage Drives (CRU)	11
Replacing an NVMe Storage Drive	12
Adding NVMe Expansion Storage	13
Oracle Database Appliance X3-2/X4-2/X5-2 Series Server Node Hot-Pluggable Components	15
Oracle Database Appliance Storage Shelf Hot-Pluggable Components	16
Servicing Storage Shelf Components	17
Adding Optional Oracle Database Appliance X8-2-HA Storage Shelf Drives (CRU)	17
Adding Optional Oracle Database Appliance X7-2-HA Storage Shelf Drives (CRU)	21
Adding Optional Oracle Database Appliance X6-2-HA Storage Shelf Drives (CRU)	25
Replace a Storage Shelf HDD or SSD (CRU)	28
Replace a Storage Shelf Power Supply (CRU)	31
Replace a Storage Shelf I/O Module (CRU)	34
Oracle Database Appliance Version 1 Hot-Pluggable Components	37
Servicing CRUs That Require System Power Off	
Servicing Oracle Database Appliance X8-2 Series CRUs	2
Adding Optional Public Network PCIe Cards in Oracle Database Appliance X8-2	2
Servicing Oracle Database Appliance X7-2 Series CRUs	4
Servicing Oracle Database Appliance X6-2 Series CRUs	5
Servicing Oracle Database Appliance X3-2/X4-2/X5-2 CRUs	6
Servicing Oracle Database Appliance Version 1 CRUs	7
Servicing FRUs	
Servicing Oracle Database Appliance X8-2 Series FRUs	1
Servicing Oracle Database Appliance X7-2 Series FRUs	
Servicing Oracle Database Appliance X6-2 Series FRUs	2
Servicing the Internal SAS Host Bus Adapter (HBA) (FRU)	2 3 4
Servicing the Internal SAS Host Bus Adapter (HBA) (FRU) Replace the Internal SAS HBA Card	
	3

4

5

	Servicing Oracle Database Appliance X3-2/X4-2/X5-2 FRUs	10		
	Managing System Fault Management	11 11		
	Component Fault Management Sorvicing Oracle Database Appliance Version 1 FBUs	12		
	Servicing Oracle Database Appliance Version 1 FRUs	12		
6	Returning Oracle Database Appliance to Operation			
	Returning Oracle Database Appliance X8-2 Series to Operation	1		
	Returning Oracle Database Appliance X7-2 Series to Operation	2		
	Returning Oracle Database Appliance X6-2 Series to Operation	2		
	Returning Oracle Database Appliance X3-2/X4-2/X5-2 to Operation	3		
	Powering On an Oracle Database Appliance That Includes a Storage Shelf	4		
	Returning Oracle Database Appliance Version 1 to Operation	5		
7	Server Node Diagnostic Tools and Resetting the Service Proces	Server Node Diagnostic Tools and Resetting the Service Processor		
	Server Node Diagnostic Tools	1		
	Resetting the Service Processor	3		
8	Server Node Basic Input/Output System (BIOS)			
	Oracle Database Appliance X8-2 Series BIOS Utility	1		
	Setting Up BIOS Configuration Parameters	2		
	BIOS Setup Utility Menu Options	2		
	Oracle Database Appliance X7-2 Series BIOS Utility	3		
	Setting Up BIOS Configuration Parameters	3		
	BIOS Setup Utility Menu Options	4		
	Oracle Database Appliance X6-2 Series BIOS Utility	4		
	Setting Up BIOS Configuration Parameters	4		
	BIOS Setup Utility Menu Options	5		
	Oracle Database Appliance X3-2/X4-2/X5-2 BIOS Utility	5		
	Setting Up BIOS Configuration Parameters	6		
	BIOS Setup Utility Menu Options	6		
	Oracle Database Appliance Version 1 BIOS Utility	7		
А	Servicing the Oracle Database Appliance Version 1			
, .	Preparing Oracle Database Appliance Version 1 for Service	A-1		
	Component Replacement Policy (CRUs and FRUs)	A-2		
	Safety Information	A-2 A-3		
	Required Tools	A-3 A-4		
	Obtaining the Chassis Serial Number	A-4		

Shutting Down a Server Node and Powering Off the System	A-5
Shut Down a Server Node	A-6
Power Off the System	A-8
Performing Electrostatic Discharge and Antistatic Prevention Measures	A-8
Removing Server Nodes From the System Chassis	A-9
Remove a Server Node From the System Chassis	A-9
Removing the Server Node Top Cover	A-10
Remove the Server Node Top Cover	A-11
Removing the Middle Section of the System Top Cover	A-11
Remove the Middle Section of System Top Cover	A-12
Servicing Hot-Pluggable Components	A-13
Servicing Storage Drives and Boot Drives (CRU)	A-14
Storage and Boot Drive Locations	A-14
Remove a Storage Drive	A-16
Install a Storage Drive	A-17
Remove a Boot Drive	A-18
Install a Boot Drive	A-19
Servicing Fan Modules (CRU)	A-20
Detecting a Fan Module Failure	A-21
Remove a Fan Module	A-21
Install a Fan Module	A-22
Servicing Power Supplies (CRU)	A-23
Detecting a Power Supply Failure	A-24
Remove a Power Supply	A-24
Install a Power Supply	A-25
Servicing CRUs That Require Server Node Power Off	A-26
Server Node CRU Component Locations	A-27
Servicing Memory Modules (DIMMs) (CRU)	A-28
DIMM and CPU Physical Layout	A-28
Remove Faulty DIMMs	A-29
Install DIMMs	A-32
Error Correction and Parity Protection	A-34
Servicing PCIe Risers (CRU)	A-34
Remove PCIe Riser From Server Nodes	A-35
Install PCIe Riser in Server Nodes	A-36
Servicing PCIe Cards (CRU)	A-38
PCIe Card Configuration	A-39
Remove PCIe Card From PCIe Riser	A-39
Install PCIe Card in PCIe Riser	A-41
Remove Primary HBA PCIe Card From Motherboard	A-43
Install Primary HBA PCIe Card in Motherboard	A-44
Servicing the Server Node Battery (CRU)	A-45

Remove Battery	A-46
Install Battery	A-47
Servicing FRUs	A-48
Removing and Installing the Air Duct (FRU)	A-49
Remove Air Duct	A-49
Install Air Duct	A-50
Servicing Processors (CPUs) (FRU)	A-51
Remove Processor (CPU)	A-52
Install Processor (CPU)	A-54
Servicing the Boot Disk Backplane (FRU)	A-56
Remove Boot Disk Backplane	A-57
Install Boot Disk Backplane	A-58
Servicing the Power Distribution Board (FRU)	A-58
Remove Power Distribution Board	A-59
Install Power Distribution Board	A-61
Servicing the Disk Midplane Module (FRU)	A-62
Remove Disk Midplane Module	A-63
Install Disk Midplane Module	A-66
Servicing the Disk Midplane Module HDD Cable (FRU)	A-67
Remove Disk Midplane Module HDD Cable	A-68
Install Disk Midplane Module HDD Cable	A-69
Servicing the Front Indicator Panels (FRU)	A-69
Remove Front Indicator Panel	A-70
Install Front Indicator Panel	A-72
Servicing Server Node Cables	A-73
Servicing Fan Power Cables (FRU)	A-74
Servicing the HBA PCIe Card Cables (FRU)	A-75
Servicing the SAS Expander Cable (FRU)	A-80
Servicing the Boot Disk Backplane Cables (FRU)	A-82
Servicing the Motherboard Assembly (FRU)	A-84
Remove Replaceable Components From Motherboard Assembly	A-86
Install Replaceable Components in Motherboard Assembly	A-87
Returning the Appliance to Operation	A-88
Installing the Server Node Top Cover	A-89
Install Server Node Top Cover	A-90
Installing a Server Node Into the System Chassis	A-90
Install Server Node Into System Chassis	A-91
Powering On Oracle Database Appliance Version 1	A-92
Power On Oracle Database Appliance Version 1	A-92
Server Node Basic Input/Output System (BIOS)	A-94
BIOS Booting and Setup	A-95
Default BIOS Power-On Self-Test (POST) Events	A-96

BIOS POST F1 and F2 Errors	A-97
How BIOS POST Memory Testing Works	A-99
Clearing Server Node CMOS NVRAM	A-100
Reset BIOS Password and Clear CMOS NVRAM Using CLR CMOS Button	A-101
Ethernet Port Naming and Boot Order	A-102
Configuring Support for TPM	A-103
Configure TPM Support in BIOS	A-103
Configuring SP LAN Settings	A-107
Configure LAN Settings for SP	A-108
Configuring Option ROM Settings in BIOS	A-108
Enable or Disable Option ROM Settings	A-109
BIOS Setup Utility Hot Keys	A-110
Accessing the BIOS Setup Utility Menus	A-111
Access BIOS Setup Utility Menus	A-111
BIOS Setup Utility Screens	A-113
BIOS Setup Utility Screen Overview	A-114
BIOS Main Menu Screen	A-116
BIOS Advanced Menu Screen	A-117
BIOS PCI Menu Screen	A-118
BIOS Boot Menu Screen	A-119
BIOS Security Menu Screen	A-119
BIOS Chipset Menu Screen	A-120
BIOS Exit Menu Screen	A-121

Index



Preface

This guide provides instructions for servicing the Oracle Database Appliance.

- Audience
- Documentation Accessibility
- Related Documents
- Conventions

Audience

This document is intended for technicians, system administrators, and authorized service providers responsible for installing the Oracle Database Appliance.

Documentation Accessibility

For information about Oracle's commitment to accessibility, visit the Oracle Accessibility Program website at http://www.oracle.com/pls/topic/lookup?ctx=acc&id=docacc.

Access to Oracle Support

Oracle customers that have purchased support have access to electronic support through My Oracle Support. For information, visit http://www.oracle.com/pls/topic/lookup?ctx=acc&id=info or visit http://www.oracle.com/pls/topic/lookup?ctx=acc&id=trs if you are hearing impaired.

Related Documents

For more information about Oracle Database Appliance, go to http://www.oracle.com/goto/oda/docs and click the appropriate release. The following documents are published in the Oracle Database Appliance online documentation library:

- Oracle Database Appliance Release Notes
- Oracle Database Appliance Licensing Information User Manual
- Oracle Database Appliance Security Guide
- Oracle Database Appliance Accessibility Guide
- Oracle Database Appliance Deployment and User's Guide (model-specific)
- Oracle Database Appliance Owner's Guide
- Oracle Database Appliance Service Manual

Conventions

The following text conventions are used in this document:



Convention	Meaning
boldface	Boldface type indicates graphical user interface elements associated with an action or terms defined in the text.
italic	Italic type indicates book titles, emphasis, or placeholder variables for which you supply particular values.
monospace	Monospace type indicates commands within a paragraph, URLs, code in examples, text that appears on the screen, or text that you enter.
# prompt	The pound (#) prompt indicates a command that is run as the root user.

Overview of System Status Indicators and LEDs

Learn about various Oracle Database Appliance model indicators and LEDs.

(i) Note

For information about system features and racking, refer to the *Oracle Database Appliance Owner's Guide*. For information about cabling, Oracle ILOM initial setup, and appliance software setup, refer to the *Oracle Database Appliance Deployment and User's Guide* for your model.

- Oracle Database Appliance X8-2S/X8-2M Status Indicators
 Learn about Oracle Database Appliance X8-2S/X8-2M status indicators.
- Oracle Database Appliance X8-2-HA Status Indicators
 Learn about Oracle Database Appliance X8-2-HA status indicators.
- Oracle Database Appliance X7-2S/X7-2M Status Indicators
 Learn about Oracle Database Appliance X7-2S/X7-2M status indicators.
- Oracle Database Appliance X7-2-HA Status Indicators
 Learn about Oracle Database Appliance X7-2-HA status indicators.
- Oracle Database Appliance X6-2S/X6-2M/X6-2L Status Indicators
 Learn about Oracle Database Appliance X6-2S/X6-2M/X6-2L status indicators.
- Oracle Database Appliance X6-2-HA Status Indicators
 Learn about Oracle Database Appliance X6-2-HA status indicators.
- Oracle Database Appliance X5-2 Status Indicators
 Learn about Oracle Database Appliance X5-2 status indicators.
- Oracle Database Appliance X3-2/X4-2 Status Indicators
 Learn about Oracle Database Appliance X3-2/X4-2 status indicators.
- Oracle Database Appliance Version 1 Status Indicators
 Learn about Oracle Database Appliance Version 1 front and back status indicators.

Oracle Database Appliance X8-2S/X8-2M Status Indicators

Learn about Oracle Database Appliance X8-2S/X8-2M status indicators.

Oracle Database Appliance X8-2S/X8-2M Server Status Indicators
 See a description of the front and back status indicators for the Oracle Database Appliance X8-2S/X8-2M.



Oracle Database Appliance X8-2S/X8-2M Server Status Indicators


See a description of the front and back status indicators for the Oracle Database Appliance X8-2S/X8-2M.

- Oracle Database Appliance X8-2S Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2S.
- Oracle Database Appliance X8-2M Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2M.
- Oracle Database Appliance X8-2S/X8-2M Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X8-2S/X8-2M.

Oracle Database Appliance X8-2S Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2S.

The following figure shows the Oracle Database Appliance X8-2S server front panel indicators for the system and storage drives.



Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.



Callout	Indicator/LED: Color	State Meaning
2	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.
3	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
4	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
5	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.
6	Rear PS: amber	 Indicates that one (or more) of the power supplies has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply.




Callout	Indicator/LED: Color	State Meaning
7	Over temperature warning: amber	Off - Normal operation; no service is required. On - The system is experiencing an over temperature warning condition. This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.
9	DO NOT SERVICE: white	 Indicates that the system is not ready to service. Off - Normal operation. On - The system is not ready for service. The DO NOT SERVICE indicator is application specific. This indicator is only illuminated on demand by the Host application.
10	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be removed safely during a hot-plug operation.
11	Drive Service Required: amber	 Off - The storage drive is operating normally. On - The system has detected a fault with the storage drive.
12	Drive OK: green	 Off - Power is off or the installed drive is not recognized by the system. On - The drive is engaged and is receiving power. Random blink - There is disk activity. The indicator blinks on and off to indicate activity.

Oracle Database Appliance X8-2M Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2M.

The following figure shows the Oracle Database Appliance X8-2M server front panel indicators for the system and storage drives.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM.
		 Pressing this button toggles the fast blink on or off.
2	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node.
	The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.	



Callout	Indicator/LED: Color	State Meaning
3	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
4	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
5	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.
6	Rear PS: amber	 Indicates that one (or more) of the power supplies has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply.




Callout	Indicator/LED: Color	State Meaning
7	Over temperature warning: amber	Off - Normal operation; no service is required. On - The system is experiencing an over temperature warning condition. This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.
9	DO NOT SERVICE: white	 Indicates that the system is not ready to service. Off - Normal operation. On - The system is not ready for service. The DO NOT SERVICE indicator is application specific. This indicator is only illuminated on demand by the Host application.
10	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be removed safely during a hot-plug operation.
11	Drive Service Required: amber	 Off - The storage drive is operating normally. On - The system has detected a fault with the storage drive.
12	Drive OK: green	 Off - Power is off or the installed drive is not recognized by the system. On - The drive is engaged and is receiving power. Random blink - There is disk activity. The indicator blinks on and off to indicate activity.

Oracle Database Appliance X8-2S/X8-2M Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X8-2S/X8-2M.

The following figure shows the Oracle Database Appliance X8-2S/X8-2M server back panel and includes indicators for the system, power supplies and network ports.





Callout	Indicator/LED: Color	State Meaning
1	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.



Callout	Indicator/LED: Color	State Meaning
3	 3a. Oracle Dual Port 25 Gb Ethernet Adapter SFP28 ports: green/yellow 	Oracle Dual Port 25 Gb Ethernet Adapter. Each of the two ports has:
	or	 Left activity indicator:
	 3b. Oracle Quad Port 10GBase-T Adapter RJ-45 ports: green/yellow 	Off - No activity.Flashing - Packet activity.
		Right link indicator:
		Off - No function.
		Green On - 25GbE link.Yellow On - 10GbE link.
		Oracle Quad Port 10GBase-T Adapter. Each of the four ports has:
		 Top activity indicator:
		 Off - No activity.
		 Flashing - Packet activity.
		 Bottom link indicator:
		 Off - 100 Mb link.
		Green On - 10GbE link.Yellow On - 1GbE link.
4	NET MGT port: green	10/100/1000 BASE-T Ethernet management interface.
		Top left speed indicator:
		 Off - 10/100BASE-T link.
		 On - Green for 1000Base-T link.
		Top right activity indicator:
		 Off - No link or link down.
		• On - Link up.
_	NET 0	Blinking - Packet activity.
5	NET 0 port: green	10/100/1000 BASE-T Ethernet interface.
		Bottom left activity indicator:
		Off - No link or link down.
		On - Link up. Plinking - Regket activity
		 Blinking - Packet activity. Bottom right link indicator:
		Off - 10/100BASE-T link.
		• On - 1000Base-T link.
6	System locate, service required and OK: various	These operate in the same way as on the front panel.

Oracle Database Appliance X8-2-HA Status Indicators

Learn about Oracle Database Appliance X8-2-HA status indicators.

Oracle Database Appliance X8-2-HA Server Node Status Indicators
 See a description of the Oracle Database Appliance X8-2-HA server node front and back status indicators.



Oracle Database Appliance X8-2-HA Storage Shelf Indicators
 See a description of the front and back Oracle Database Appliance X8-2-HA storage shelf status indicators.

Oracle Database Appliance X8-2-HA Server Node Status Indicators


See a description of the Oracle Database Appliance X8-2-HA server node front and back status indicators.

- Server Node Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2-HA server node.
- Server Node Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X8-2-HA server node.

Server Node Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2-HA server node.

The following figure shows the Oracle Database Appliance X8-2-HA server node front panel and includes indicators for the system and storage drives.



Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.



Callout	Indicator/LED: Color	State Meaning
2	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.
3	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
4	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
5	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.
6	Rear PS: amber	 Indicates that one (or more) of the power supplies has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply.




Callout	Indicator/LED: Color	State Meaning
7	Over temperature warning: amber	Off - Normal operation; no service is required. On - The system is experiencing an over temperature warning condition. This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.
9	DO NOT SERVICE: white	 Indicates that the system is not ready to service. Off - Normal operation. On - The system is not ready for service. The DO NOT SERVICE indicator is application specific. This indicator is only illuminated on demand by the Host application.

Server Node Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X8-2-HA server node.

The following figure shows the Oracle Database Appliance X8-2-HA server node back panel and includes indicators for the system, power supplies and network ports.





Callout	Indicator/LED: Color	State Meaning
1	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.
3	PORT 1 and 2 private cluster interconnect 10/25 GbE SFP28 ports: green/yellow	10/25 GbE SFP28 interface. Left activity indicator: Off - No activity. Flashing - Packet activity. Right link indicator: Off - No link.
4	NET MGT port: green	 Green On - 25GbE link. Yellow On - 10GbE link. 10/100/1000 BASE-T Ethernet management interface. Top left speed indicator: Off - 10/100BASE-T link. On - Green for 1000Base-T link. Top right activity indicator:
5	NET 0 port: green	 Off - No link or link down. On - Link up. Blinking - Packet activity. 10/100/1000 BASE-T Ethernet interface. Top right speed indicator: Off - 10/100BASE-T link. On - Green for 1000Base-T link. Top left link indicator: Off - No link or link down. On - Link up.
6	System locate, service required and OK: various	 Blinking - Packet activity. These operate in the same way as on the front panel.



Callout	Indicator/LED: Color	State Meaning
7	 7a. Oracle Dual Port 25 Gb Ethernet Adapter SFP28 ports: green/yellow 	Oracle Dual Port 25 Gb Ethernet Adapter. Each of the two ports has:
	or	 Left activity indicator:
	 7b. Oracle Quad Port 10GBase-T Adapter RJ-45 ports: green/yellow 	 Off - No activity. Flashing - Packet activity. Right link indicator: Off - No function.
		Green On - 25GbE link.Yellow On - 10GbE link.
		Oracle Quad Port 10GBase-T Adapter. Each of the four ports has:
		 Top activity indicator:
		Off - No activity.Flashing - Packet activity.
		Bottom link indicator:
		 Off - 100 Mb link.
		Green On - 10GbE link.Yellow On - 1GbE link.

Oracle Database Appliance X8-2-HA Storage Shelf Indicators

See a description of the front and back Oracle Database Appliance X8-2-HA storage shelf status indicators.

- Storage Shelf Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2-HA storage shelf.
- Storage Shelf Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X8-2-HA storage shelf.

Storage Shelf Front Panel Status Indicators


See a listing of the various font panel status indicators for the Oracle Database Appliance X8-2-HA storage shelf.

The following figure shows the controls and indicators on the for the Oracle Database Appliance X8-2-HA storage shelf (DE3-24C) front panel and drives.



The 2 or 3 character LED enclosure ID display panel on the front of the storage shelf is not used with the Oracle Database Appliance product. Any numbers or letters displayed in this panel other than zeros could indicate a fault with either the panel, its cabling (neither of which are customer replaceable), or some other storage shelf component.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the storage shelf.
3	OK: green	 Off - The storage shelf is unplugged or turned off. On - The storage shelf is powered on and operating normally.
4	Power Supply fault indicator: amber	 Off - Normal operation. On - Indicates a fault with a power supply. View the LEDs at the back of the storage shelf to determine which power supply has the fault.
5	SAS I/O Module fault indicator: amber	 Off - Normal operation. On - Indicates a fault with a SAS I/O module. View the LEDs at the back of the storage shelf to determine which module has the fault.
6	Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be safely removed during a hot-plug operation.




Callout	Indicator/LED: Color	State Meaning
7	Drive Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the disk drive.
8	Power/Activity: green	 Off - The drive is powered off or the installed drive is not recognized by the system. On - The drive is installed and recognized by the system but there is no drive activity. Blink - The LED blinks randomly in response to data being written to or read from the drive.

Storage Shelf Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X8-2-HA storage shelf.

The following figure shows the controls and indicators on the Oracle Database Appliance X8-2-HA storage shelf (DE3-24C) back panel.



Callout	Indicator/LED: Color	State Meaning
1	AC power fault indicator: amber	 Off - Normal operation. On - Indicates an AC power fault.
2	Fan fail indicator: amber	Off - Normal operation.On - The fan is faulty.



Callout	Indicator/LED: Color	State Meaning
3	Power supply status indicator: green	 Off - The power supply is unplugged or turned off. On - The power supply is
4	DC power fail indicator: amber	 operating normally. Off - Normal operation. On - The power supply is
5	Reserved	faulty. This port is reserved for Oracle Service.
6	Network port (reserved)	This port is reserved for Oracle Service.
7	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
8	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the storage shelf.
9	OK: green	 Off - The storage shelf is unplugged or turned off. On - The storage shelf is powered on and operating normally.
10	SAS I/O Module Ready-to- Remove: blue	 Off - The I/O module has not been prepared for removal. On - The I/O module can be safely removed during a hotplug operation.
11	SAS I/O Module Service Required indicator: amber	 Off - Normal operation. Steady on - A fault is present in the SAS I/O module.
12	SAS I/O Module OK: green	 Off - The I/O module is unplugged or turned off. On - The I/O module is powered on and operating normally.
13	Host SAS port Service Required indicator: amber	 Off - Normal operation. Steady on - A fault is present with the port or connection.
14	Host SAS port activity indicator: green	 Off - No link activity. Random blinking - Indicates host SAS link activity.

Oracle Database Appliance X7-2S/X7-2M Status Indicators

Learn about Oracle Database Appliance X7-2S/X7-2M status indicators.



Oracle Database Appliance X7-2S/X7-2M Server Status Indicators
 See a description of the front and back status indicators for the Oracle Database Appliance X7-2S/X7-2M.

Oracle Database Appliance X7-2S/X7-2M Server Status Indicators


See a description of the front and back status indicators for the Oracle Database Appliance X7-2S/X7-2M.

- <u>Server Front Panel Status Indicators</u>
 See a listing of the various font panel status indicators for the Oracle Database Appliance X7-2S/X7-2M.
- <u>Server Back Panel Status Indicators</u>
 See a listing of the various back panel status indicators for the Oracle Database Appliance X7-2S/X7-2M.

Server Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X7-2S/X7-2M.

The following figure shows the Oracle Database Appliance X7-2S/X7-2M server front panel includes indicators for the system and storage drives.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.
3	Rear PS: amber	 Indicates that one (or more) of the power supplies has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply.
4	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.
5	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.




Callout	Indicator/LED: Color	State Meaning
6	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
7	DO NOT SERVICE: white	 Indicates that the system is not ready to service. Off - Normal operation. On - The system is not ready for service. The DO NOT SERVICE indicator is application specific. This indicator is only illuminated on demand by the Host application.
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.
9	Over temperature warning: amber	 Off - Normal operation; no service is required. On - The system is experiencing an over temperature warning condition. This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
10	Drive OK: green	 Off - Power is off or the installed drive is not recognized by the system. On - The drive is engaged and is receiving power. Random blink - There is disk activity. The indicator blinks on and off to indicate activity.
11	Drive Service Required: amber	 Off - The storage drive is operating normally. On - The system has detected a fault with the storage drive.
12	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be removed safely during a hot-plug operation.



Server Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X7-2S/X7-2M.

The following figure shows the Oracle Database Appliance X7-2S/X7-2M server back panel and includes indicators for the system, power supplies and network ports.



Callout	Indicator/LED: Color	State Meaning
1, 3	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2, 4	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.
5	System locate, service required and OK: various	These operate in the same way as on the front panel.
6	NET MGT port: green	 10/100/1000 BASE-T Ethernet management interface. Top left speed indicator: Off - 10/100BASE-T link. On - Green for 1000Base-T link. Top right activity indicator: Off - No link or link down. On - Link up. Blinking - Packet activity.



Callout	Indicator/LED: Color	State Meaning
7	NET 0 port: green	10/100/1000 BASE-T Ethernet interface.
		 Top right speed indicator: Off - 10/100BASE-T link (if link up). On - 1000Base-T link. Top left link indicator: Off - No link or link down. On - Link up. Blinking - Packet activity.
8	NET 1 and 2 10 GbE ports: green The 10/25 GbE SFP28 (NET 1 and NET 2) ports are the default network ports for the server. When using an SFP28 port, network connectivity is disabled on the 10GbE RJ-45 ports (NET 1 and NET 2).	10 GbE Ethernet interface. Top left activity indicator: Off - No activity. On - Link up. Flashing - Packet activity. Top right speed indicator: Off - 1000BASE-T link (if link up). Green On - 10000BASE-T link.
9	NET 1 and 2 10/25 GbE SFP28 ports: green/amber The 10/25 GbE SFP28 (NET 1 and NET 2) ports are the default network ports for the server. When using an SFP28 port, network connectivity is disabled on the 10GbE RJ-45 ports (NET 1 and NET 2).	 10/25 SFP28 Ethernet interface. Top activity indicator: Off - No activity. Flashing - Packet activity. Bottom speed indicator: Off - No activity. Amber On - 10GbE link. Green On - 25GbE link.

Oracle Database Appliance X7-2-HA Status Indicators

Learn about Oracle Database Appliance X7-2-HA status indicators.

- Oracle Database Appliance X7-2-HA Server Node Status Indicators
 See a description of the Oracle Database Appliance X7-2-HA server node front and back status indicators.
- Oracle Database Appliance X7-2-HA Storage Shelf Indicators
 See a description of the front and back Oracle Database Appliance X7-2-HA storage shelf status indicators.

Oracle Database Appliance X7-2-HA Server Node Status Indicators

See a description of the Oracle Database Appliance X7-2-HA server node front and back status indicators.

<u>Server Node Front Panel Status Indicators</u>
 See a listing of the various font panel status indicators for the Oracle Database Appliance X7-2-HA server node.




Server Node Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance
 X7-2-HA server node.

Server Node Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X7-2-HA server node.

The following figure shows the Oracle Database Appliance X7-2-HA server node front panel and includes indicators for the system and storage drives.



Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.



Callout	Indicator/LED: Color	State Meaning
3	Rear PS: amber	 Indicates that one (or more) of the power supplies has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply.
4	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.
5	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
6	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
7	DO NOT SERVICE: white	 Indicates that the system is not ready to service. Off - Normal operation. On - The system is not ready for service. The DO NOT SERVICE indicator is application specific. This indicator is only illuminated on demand by the Host application.




Callout	Indicator/LED: Color	State Meaning
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.
9	Over temperature warning: amber	 Off - Normal operation; no service is required. On - The system is experiencing an over temperature warning condition.
		This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.

Server Node Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X7-2-HA server node.

The following figure shows the Oracle Database Appliance X7-2-HA server node back panel and includes indicators for the system, power supplies and network ports



Callout	Indicator/LED: Color	State Meaning
1, 3	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2, 4	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.



Callout	Indicator/LED: Color	State Meaning
5	PORT 1 and 2 private cluster interconnect 10/25 GbE SFP28 ports: green/yellow	 10/25 GbE SFP28 interface. Top activity indicator: Off - No activity. Flashing - Packet activity. Bottom link indicator: Off - No link. Green On - 25GbE link. Yellow On - 10GbE link.
6	System locate, service required and OK: various	These operate in the same way as on the front panel.
7	NET MGT port: green	 10/100/1000 BASE-T Ethernet management interface. Top left speed indicator: Off - 10/100BASE-T link. On - Green for 1000Base-T link. Top right activity indicator: Off - No link or link down. On - Link up. Blinking - Packet activity
8	NET 0 port: green	 Blinking - Packet activity. 10/100/1000 BASE-T Ethernet interface. Top right speed indicator: Off - 10/100BASE-T link (if link up). On - Green for 1000Base-T link. Top left link indicator: Off - No link or link down. On - Link up. Blinking - Packet activity.
9	NET 1 and 2 10 GbE ports: green The 10/25 GbE SFP28 (NET 1 and NET 2) ports are the default network ports for the server. When using an SFP28 port, network connectivity is disabled on the 10GbE RJ-45 ports (NET 1 and NET 2).	*
10	NET 1 and 2 10/25 GbE SFP28 ports: green/amber The 10/25 GbE SFP28 (NET 1 and NET 2) ports are the default network ports for the server. When using an SFP28 port, network connectivity is disabled on the 10GbE RJ-45 ports (NET 1 and NET 2).	10/25 GbE SFP28 Ethernet interface. Top activity indicator: Off - No activity. Flashing - Packet activity. Bottom speed indicator: Off - No activity. Amber On - 10GbE link. Green On - 25GbE link.



Oracle Database Appliance X7-2-HA Storage Shelf Indicators

See a description of the front and back Oracle Database Appliance X7-2-HA storage shelf status indicators.

- Storage Shelf Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance
 X7-2-HA storage shelf.
- Storage Shelf Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X7-2-HA storage shelf.


Storage Shelf Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X7-2-HA storage shelf.

The following figure shows the controls and indicators on the for the Oracle Database Appliance X7-2-HA storage shelf (DE3-24C) front panel and drives.

(i) Note

The 2 or 3 character LED enclosure ID display panel on the front of the storage shelf is not used with the Oracle Database Appliance product. Any numbers or letters displayed in this panel other than zeros could indicate a fault with either the panel, its cabling (neither of which are customer replaceable), or some other storage shelf component.






Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the storage shelf.
3	OK: green	 Off - The storage shelf is unplugged or turned off. On - The storage shelf is powered on and operating normally.
4	Power Supply fault indicator: amber	 Off - Normal operation. On - Indicates a fault with a power supply. View the LEDs at the back of the storage shelf to determine which power supply has the fault.
5	SAS I/O Module fault indicator: amber	 Off - Normal operation. On - Indicates a fault with a SAS I/O module. View the LEDs at the back of the storage shelf to determine which module has the fault.
6	Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be safely removed during a hot-plug operation.
7	Drive Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the disk drive.
8	Power/Activity: green	 Off - The drive is powered off or the installed drive is not recognized by the system. On - The drive is installed and recognized by the system but there is no drive activity. Blink - The LED blinks randomly in response to data being written to or read from the drive.



Storage Shelf Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X7-2-HA storage shelf.

The following figure shows the controls and indicators on the Oracle Database Appliance X7-2-HA storage shelf (DE3-24C) back panel.



Callout	Indicator/LED: Color	State Meaning
1	AC power fault indicator: amber	 Off - Normal operation. On - Indicates an AC power fault.
2	Fan fail indicator: amber	Off - Normal operation.On - The fan is faulty.
3	Power supply status indicator: green	 Off - The power supply is unplugged or turned off. On - The power supply is operating normally.
4	DC power fail indicator: amber	 Off - Normal operation. On - The power supply is faulty.
5	Reserved	This port is reserved for Oracle Service.
6	Network port (reserved)	This port is reserved for Oracle Service.



Callout	Indicator/LED: Color	State Meaning
7	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
8	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the storage shelf.
9	OK: green	 Off - The storage shelf is unplugged or turned off. On - The storage shelf is powered on and operating normally.
10	SAS I/O Module Ready-to- Remove: blue	 Off - The I/O module has not been prepared for removal. On - The I/O module can be safely removed during a hotplug operation.
11	SAS I/O Module Service Required indicator: amber	 Off - Normal operation. Steady on - A fault is present in the SAS I/O module.
12	SAS I/O Module OK: green	 Off - The I/O module is unplugged or turned off. On - The I/O module is powered on and operating normally.
13	Host SAS port Service Required indicator: amber	 Off - Normal operation. Steady on - A fault is present with the port or connection.
14	Host SAS port activity indicator: green	 Off - No link activity. Random blinking - Indicates host SAS link activity.

Oracle Database Appliance X6-2S/X6-2M/X6-2L Status Indicators

Learn about Oracle Database Appliance X6-2S/X6-2M/X6-2L status indicators.

- Oracle Database Appliance X6-2S/X6-2M Server Status Indicators
 See a description of the front and back status indicators for the Oracle Database Appliance X6-2S/X6-2M.
- Oracle Database Appliance X6-2L Server Status Indicators
 See a description of the front and back status indicators for the Oracle Database Appliance X6-2L.



Oracle Database Appliance X6-2S/X6-2M Server Status Indicators


See a description of the front and back status indicators for the Oracle Database Appliance X6-2S/X6-2M.

- Server Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2S/X6-2M.
- Server Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2S/X6-2M.

Server Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2S/X6-2M.

The following figure shows the Oracle Database Appliance X6-2S/X6-2M server front panel and includes indicators for the system and storage drives.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.
3	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
4	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
5	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.




Callout	Indicator/LED: Color	State Meaning
6	Rear PS: amber	Indicates that one (or more) of the power supplies has failed.
		 Off - Indicates steady state; no service is required.
		 On - Indicates service required; service the failed power supply.
7	Over temperature warning: amber	 Off - Normal operation; no service is required.
		 On - The system is experiencing an over temperature warning condition.
		This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully
		operational.Slow blink - SP is booting.
9	Drive OK: green	Off - Power is off or the installed drive is not recognized by the system.
		On - The drive is engaged and is receiving power.
		 Random blink - There is disk activity. The indicator blinks on and off to indicate activity.
10	Drive Service Required: amber	 Off - The storage drive is operating normally.
		 On - The system has detected a fault with the storage drive.
11	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal.
		 On - The storage drive can be removed safely during a hot-plug operation.

Server Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2S/X6-2M.

The following figure shows the Oracle Database Appliance X6-2S/X6-2M server back panel and includes indicators for the system, power supplies and network ports.





Callout	Indicator/LED: Color	State Meaning
1, 3	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2, 4	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.
5	System locate, service required and OK: various	These operate in the same way as on the front panel.
6	NET MGT port: green	 10/100/1000 BASE-T Ethernet management interface. Top left link indicator: Off - 10/100BASE-T link. On - Green for 1000Base-T link. Top right activity indicator: Off - No link or link down. On - Link up. Blinking - Packet activity.
7	NET 0-3 ports: green/amber	100/1000/10000 BASE-T Ethernet interface. Top left activity indicator: Off - No activity. On - No function. Blinking - Packet activity. Top right link indicator: Off - 100BASE-T link. On - Amber for 1000Base-T link; green for 10GBBase-T link. Blinking - No function.



Callout	Indicator/LED: Color	State Meaning
8	Dual 10 GbE SFP+ PCIe 2.0 Low Profile Adapter ports: green/	1000/10000 BASE-T Ethernet interface.
	amber	GRN=10G:
		 Off - No function.
		 On - Green for 10GbE link; amber for 1GbE link.
		ACT/LINK (A or B):
		Off - No link.
		 On - Green for link up.
		 Blinking - Green for packet activity.

Oracle Database Appliance X6-2L Server Status Indicators


See a description of the front and back status indicators for the Oracle Database Appliance X6-2L.

- Server Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2L.
- Server Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2L.

Server Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2L.

The following figure shows the Oracle Database Appliance X6-2L server front panel and includes indicators for the system and storage drives.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.
3	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
4	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
5	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.




Callout	Indicator/LED: Color	State Meaning
6	Drive OK: green	 Off - Power is off or the installed drive is not recognized by the system. On - The drive is engaged and is receiving power. Random blink - There is disk activity. The indicator blinks on and off to indicate activity.
7	Drive Service Required: amber	 Off - The storage drive is operating normally. On - The system has detected a fault with the storage drive.
8	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be removed safely during a hot-plug operation.
9	Top fan: amber Rear PS: amber Over-temperature warning: amber	 Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module. Rear PS: Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply. Over-temperature warning: Off - Normal operation; no service is required. On - The system is experiencing an over-temperature warning condition. This is a warning indication, not a fatal over-temperature
		not a fatal over-temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.

Server Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2L.

The following figure shows the Oracle Database Appliance X6-2S/X6-2M server back panel and includes indicators for the system, power supplies and network ports.





Callout	Indicator/LED: Color	State Meaning
1, 2	Storage drive status: various	These operate in the same way as on the front panel.
3	Dual-port 10 GbE SFP+ PCle 2.0	GRN=10G:
	Low Profile Adapter ports: green/ amber	 Off - No function. On - Green for 10GbE link; amber for 1GbE link.
		ACT/LINK (A or B):
		 Off - No link.
		 On - Green for link up.
		 Blinking - Green for packet activity.
4	NET MGT port: green	10/100/1000 BASE-T Ethernet management interface.
		Top left link indicator:
		 Off - 10/100BASE-T link.
		• On - Green for 1000Base-T link.
		Top right activity indicator:
		 Off - No link or link down.
		On - Link up.
		 Blinking - Packet activity.
5, 6	PS Service Required: amber	PS Service Required:
	PS OK: green	 Off - Normal operation.
	ŭ	 On - The power supply (PS) has detected a PS fan failure, PS over-temperature, PS over current, or PS over or under voltage.
		PS OK:
		Off - No AC power is present
		 On - Normal operation. Input AC power and DC output voltage are within specification.
		 Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled



Callout	Indicator/LED: Color	State Meaning
7	System locate, service required and OK: various	These operate in the same way as on the front panel.
8	NET 0-3 ports: green/amber	100/1000/10000 BASE-T Ethernet interface.
		Top left activity indicator:
		 Off - No activity.
		On - No function.
		 Blinking - Packet activity.
		Top right link indicator:
		 Off - 100BASE-T link.
		 On - Amber for 1000Base-T link; green for 10GBBase-T link.
		 Blinking - No function.

Oracle Database Appliance X6-2-HA Status Indicators

Learn about Oracle Database Appliance X6-2-HA status indicators.

- Oracle Database Appliance X6-2-HA Server Node Status Indicators
 See a description of the Oracle Database Appliance X6-2-HA server node front and back status indicators.
- Oracle Database Appliance X6-2-HA Storage Shelf Indicators
 See a description of the front and back Oracle Database Appliance X6-2-HA storage shelf status indicators.

Oracle Database Appliance X6-2-HA Server Node Status Indicators

See a description of the Oracle Database Appliance X6-2-HA server node front and back status indicators.


- Server Node Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2-HA server node.
- <u>Server Node Back Panel Status Indicators</u>
 See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2-HA server node.

Server Node Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2-HA server node.

The following figure shows the Oracle Database Appliance X6-2-HA server node front panel and includes indicators for the system and storage drives.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	Off - Normal operation.
		 Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.



Callout	Indicator/LED: Color	State Meaning
3	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
4	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
5	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.
6	Rear PS: amber	 Indicates that one (or more) of the power supplies has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply.




Callout	Indicator/LED: Color	State Meaning
7	Over temperature warning: ambe	 Off - Normal operation; no service is required. On - The system is experiencing an over temperature warning condition. This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.
9	Drive OK: green	 Off - Power is off or the installed drive is not recognized by the system. On - The drive is receiving power and is recognized by the system. Random blink - There is disk activity. The indicator blinks on and off to indicate activity.
10	Drive Service Required: amber	 Off - The storage drive is operating normally. On - The system has detected a fault with the storage drive.
11	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be removed safely during a hot-plug operation.

Server Node Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2-HA server node.

The following figure shows the Oracle Database Appliance X6-2-HA server node back panel and includes indicators for the system, power supplies and network ports





Callout	Indicator/LED: Color	State Meaning
1, 3	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2, 4	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.
5	System locate, service required and OK: various	These operate in the same way as on the front panel.
6	NET MGT port: green	10/100/1000 BASE-T Ethernet management interface. Top left link indicator: Off - 10/100BASE-T link. On - Green for 1000Base-T link. Top right activity indicator: Off - No link or link down. On - Link up. Blinking - Packet activity.
7	Two InfiniBand QSFP+ Adapter ports (shown): green/yellowor Dual 10 GbE SFP+ PCle 2.0 Low Profile Adapter ports (not shown): green/amber	 InfiniBand QSFP+ interface. Green off - No link. Green on - InfiniBand physical link established. Yellow off - A physical and/or logical link has not been established. Yellow on - InfiniBand is discovered over the link, but no data is being passed . Yellow blinking - Data being passed. Yellow blinking - Data being passed. GRN=10G: Off - No function. On - Green for 10GbE link; amber for 1GbE link. ACT/LINK (A or B): Off - No link. On - Green for link up. Blinking - Green for packet activity.



Callout	Indicator/LED: Color	State Meaning
8	NET 0-3 ports: green/amber	100/1000/10000 BASE-T Ethernet interface.
		 Top left activity indicator: Off - No activity. On - No function. Blinking - Packet activity. Top right link indicator: Off - 100BASE-T link. On - Amber for 1000Base-T link; green for 10GBBase-T link.
		 Blinking - No function.

Oracle Database Appliance X6-2-HA Storage Shelf Indicators

See a description of the front and back Oracle Database Appliance X6-2-HA storage shelf status indicators.

- Storage Shelf Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2-HA storage shelf.
- Storage Shelf Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2-HA storage shelf.

Storage Shelf Front Panel Status Indicators


See a listing of the various font panel status indicators for the Oracle Database Appliance X6-2-HA storage shelf.

The following figure shows the controls and indicators on the for the Oracle Database Appliance X6-2-HA storage shelf (DE3-24C) front panel and drives.



The 2 or 3 character LED enclosure ID display panel on the front of the storage shelf is not used with the Oracle Database Appliance product. Any numbers or letters displayed in this panel other than zeros could indicate a fault with either the panel, its cabling (neither of which are customer replaceable), or some other storage shelf component.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service Required: amber	Off - Normal operation.Steady on - A fault is present in the storage shelf.
3	OK: green	 Off - The storage shelf is unplugged or turned off. On - The storage shelf is powered on and operating normally.
4	Power Supply fault indicator: amber	 Off - Normal operation. On - Indicates a fault with a power supply. View the LEDs at the back of the storage shelf to determine which power supply has the fault.
5	SAS I/O Module fault indicator: amber	 Off - Normal operation. On - Indicates a fault with a SAS I/O module. View the LEDs at the back of the storage shelf to determine which module has the fault.
6	Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be safely removed during a hot-plug operation.




Callout	Indicator/LED: Color	State Meaning
7	Drive Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the disk drive.
8	Power/Activity: green	 Off - The drive is powered off or the installed drive is not recognized by the system. On - The drive is installed and recognized by the system but there is no drive activity. Blink - The LED blinks randomly in response to data being written to or read from the drive.

Storage Shelf Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X6-2-HA storage shelf.

The following figure shows the controls and indicators on the Oracle Database Appliance X6-2-HA storage shelf (DE3-24C) back panel.



Callout	Indicator/LED: Color	State Meaning
1	AC power fault indicator: amber	 Off - Normal operation. On - Indicates an AC power fault.
2	Fan fail indicator: amber	Off - Normal operation.On - The fan is faulty.



Callout	Indicator/LED: Color	State Meaning
3	Power supply status indicator: green	 Off - The power supply is unplugged or turned off. On - The power supply is operating normally.
4	DC power fail indicator: amber	 Off - Normal operation. On - The power supply is faulty.
5	Reserved	This port is reserved for Oracle Service.
6	Network port (reserved)	This port is reserved for Oracle Service.
7	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
8	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the storage shelf.
9	OK: green	 Off - The storage shelf is unplugged or turned off. On - The storage shelf is powered on and operating normally.
10	SAS I/O Module Ready-to- Remove: blue	 Off - The I/O module has not been prepared for removal. On - The I/O module can be safely removed during a hotplug operation.
11	SAS I/O Module Service Required indicator: amber	 Off - Normal operation. Steady on - A fault is present in the SAS I/O module.
12	SAS I/O Module OK: green	 Off - The I/O module is unplugged or turned off. On - The I/O module is powered on and operating normally.
13	Host SAS port Service Required indicator: amber	 Off - Normal operation. Steady on - A fault is present with the port or connection.
14	Host SAS port activity indicator: green	 Off - No link activity. Random blinking - Indicates host SAS link activity.

Oracle Database Appliance X5-2 Status Indicators

Learn about Oracle Database Appliance X5-2 status indicators.



- Oracle Database Appliance X5-2 Server Node Status Indicators
 See a description of the Oracle Database Appliance X5-2 server node front and back status indicators.
- Oracle Database Appliance X5-2 Storage Shelf Indicators
 See a description of the front and back Oracle Database Appliance X5-2 storage shelf status indicators.

Oracle Database Appliance X5-2 Server Node Status Indicators


See a description of the Oracle Database Appliance X5-2 server node front and back status indicators.

- <u>Server Node Front Panel Status Indicators</u>
 See a listing of the various font panel status indicators for the Oracle Database Appliance X5-2 server node.
- Server Node Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance
 X5-2 server node.

Server Node Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X5-2 server node.

The following figure shows the Oracle Database Appliance X5-2 server node front panel and includes indicators for the system and storage drives.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.
3	OK: green	 Indicates the operational state of the server node: Off - AC power is either not present or the Oracle ILOM service processor (SP) boot process is not complete. Steady blink - Standby power is on and the Oracle ILOM SP is running, but the server host power is off. Slow blink - Startup/ shutdown sequence has been initiated on the server host. During startup, the power-on self tests are running on the system. During shutdown, the server host is shutting down and transitioning from full power to standby power. On - The server host is powered on and is in the process of booting or is running the operating system.
4	Power button	Press to apply full power and start the server host. Press again to transition from full power to standby power where only the Oracle ILOM SP is running.
5	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.




Callout	Indicator/LED: Color	State Meaning
6	Rear PS: amber	Indicates that one (or more) of the power supplies has failed.
		 Off - Indicates steady state; no service is required.
		 On - Indicates service required; service the failed power supply.
7	Over temperature warning: amber	 Off - Normal operation; no service is required.
		 On - The system is experiencing an over temperature warning condition.
		This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
8	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully
		operational.Slow blink - SP is booting.
9	Drive OK: green	Off - Power is off or the installed drive is not recognized by the system.
		On - The drive is engaged and is receiving power.
		 Random blink - There is disk activity. The indicator blinks on and off to indicate activity.
10	Drive Service Required: amber	 Off - The storage drive is operating normally.
		 On - The system has detected a fault with the storage drive.
11	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal.
		 On - The storage drive can be removed safely during a hot-plug operation.

Server Node Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X5-2 server node.

The following figure shows the Oracle Database Appliance X5-2 server node back panel and includes indicators for the system, power supplies and network ports





Callout	Indicator/LED: Color	State Meaning
1, 3	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2, 4	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.
5	System locate, service required and OK: various	These operate in the same way as on the front panel.
6	NET MGT port: green	 10/100/1000 BASE-T Ethernet management interface. Top left link indicator: On - Green for 1000Base-T link. Off - 10/100BASE-T link. Top right activity indicator: On - Link up. Off - No link or link down. Blinking - Packet activity.
7	Two InfiniBand QSFP+ Adapter ports (shown): green/yellow	 InfiniBand QSFP+ interface. Green on - InfiniBand physical link established. Green off - No link. Yellow on - InfiniBand is discovered over the link, but no data is being passed . Yellow off - A physical and/or logical link has not been established. Yellow blinking - Data being passed.



Callout	Indicator/LED: Color	State Meaning
8	NET 0-3 ports: green/amber	100/1000 BASE-T Ethernet interface.
		Top left activity indicator: On - No function. Off - No activity. Blinking - Packet activity.
		Top right link indicator: On - Amber for 100 base-T link; green for 1000 base-T link.
		Off - No link.Blinking - No function.

Oracle Database Appliance X5-2 Storage Shelf Indicators

See a description of the front and back Oracle Database Appliance X5-2 storage shelf status indicators.

- Storage Shelf Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X5-2 storage shelf.
- Storage Shelf Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X5-2 storage shelf.

Storage Shelf Front Panel Status Indicators


See a listing of the various font panel status indicators for the Oracle Database Appliance X5-2 storage shelf.

The following figure shows the controls and indicators on the Oracle Database Appliance X5-2 storage shelf (DE2-24C) front panel and drives.



The 2 or 3 character LED enclosure ID display panel on the front of the storage shelf is not used with the Oracle Database Appliance product. Any numbers or letters displayed in this panel other than zeros could indicate a fault with either the panel, its cabling (neither of which are customer replaceable), or some other storage shelf component.






Callout	Indicator/LED: Color	State Meaning
1	OK: green	 On - The storage shelf is powered on and operating normally.
		 Off - The storage shelf is unplugged or turned off.
2	Service Required: amber	 Off - Normal operation.
		• Steady on - A fault is present in the storage shelf.
3	Locate: white	 Off - Normal operation.
		 Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM.
		 Pressing this button toggles the fast blink on or off.
4	Power/Activity: green	 On - The drive is installed and recognized by the system but there is no drive activity.
		 Blink - The LED blinks randomly in response to data being written to or read from the drive.
		 Off - The drive is powered off or the installed drive is not recognized by the system.
5	Drive Service Required: amber	 Off - Normal operation.
		Steady on - A fault is present in the disk drive.



Storage Shelf Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X5-2 storage shelf.

The following figure shows the controls and indicators on the Oracle Database Appliance X5-2 storage shelf (DE2-24C) back panel.



Callout	Indicator/LED: Color	State Meaning
1	AC power fault indicator: amber	On - Indicates an AC power fault.Off - Normal operation.
2	Power supply status indicator: green	 On - The power supply is operating normally. Off - The power supply is unplugged or turned off.
3	Fan fail indicator: amber	On - The fan is faulty.Off - Normal operation.
4	DC power fail indicator: amber	On - The power supply is faulty.Off - Normal operation.
5	SAS I/O Module status indicators: green or amber	·
6	Reserved	This port is reserved for Oracle Service.
7	Network port (reserved)	This port is reserved for Oracle Service.



Callout	Indicator/LED: Color	St	ate Meaning
8	Host SAS port activity indicators (x4 per port): green	•	Random blinking - Indicates host SAS link activity.
		•	Off - No link activity.

Oracle Database Appliance X3-2/X4-2 Status Indicators

Learn about Oracle Database Appliance X3-2/X4-2 status indicators.

- Oracle Database Appliance X3-2/X4-2 Server Node Status Indicators
 See a description of the Oracle Database Appliance X3-2/X4-2 server node front and back status indicators.
- Oracle Database Appliance X3-2/X4-2 Storage Shelf Indicators
 See a description of the front and back Oracle Database Appliance X3-2/X4-2 storage shelf status indicators.

Oracle Database Appliance X3-2/X4-2 Server Node Status Indicators

See a description of the Oracle Database Appliance X3-2/X4-2 server node front and back status indicators.


- Server Node Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X3-2/X4-2 server node.
- <u>Server Node Back Panel Status Indicators</u>
 See a listing of the various back panel status indicators for the Oracle Database Appliance X3-2/X4-2 server node.

Server Node Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X3-2/X4-2 server node.

The following figure shows the Oracle Database Appliance X3-2/X4-2 server node front panel and includes indicators for the system and storage drives.





Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.
2	Service processor (SP): green	 Off - The service processor (SP) is not running. On - The SP is fully operational. Slow blink - SP is booting.
3	Service Required: amber	 Off - Normal operation. On - A fault is present in the server node. The lighting of this indicator is always accompanied by a system console message that includes a recommended service action.



Callout	Indicator/LED: Color	State Meaning
4	OK: green	Indicates the operational state of the server node:
		 On - The server is powered on, and all host POST code checkpoint tests are complete. The server is in one of the following states: 1) the server host is booting the operating system (OS), 2) the server host is running the OS.
		 Off - AC power is not present or the Oracle ILOM boot is not complete.
		 Steady blink - Standby power is on, but the chassis power is off and the Oracle ILOM
5	Power button	SP is running. Slow blink - Startup sequence has been initiated on the host. This pattern should begin soon after you power on the server. This status indicates either: (1) POST code checkpoint tests are running on the server host system, or (2) the host is transitioning from the powered-on state to the standby state on shutdown.
		again to turn main power off, but leave standby power on the Oracle ILOM.
6	Top fan: amber	 Indicates that one (or more) of the internal fan modules has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed fan module.
7	Rear PS: amber	 Indicates that one (or more) of the power supplies has failed. Off - Indicates steady state; no service is required. On - Indicates service required; service the failed power supply.




Callout	Indicator/LED: Color	State Meaning
8	Over temperature warning: ambe	 Off - Normal operation; no service is required. On - The system is experiencing an over temperature warning condition.
		This is a warning indication, not a fatal over temperature. Failure to correct this condition might result in the system overheating and shutting down unexpectedly.
9	Drive OK: green	 Off - Power is off or the installed drive is not recognized by the system. On - The drive is engaged and is receiving power. Random blink - There is disk activity. The indicator blinks on and off to indicate activity.
10	Drive Service Required: amber	 Off - The storage drive is operating normally. On - The system has detected a fault with the storage drive.
11	Drive Ready-to-Remove: blue	 Off - The storage drive has not been prepared for removal. On - The storage drive can be removed safely during a hot-plug operation.

Server Node Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X3-2/X4-2 server node.

The following figure shows the Oracle Database Appliance X3-2/X4-2 server node back panel and includes indicators for the system, power supplies and network ports.





Callout	Indicator/LED: Color	State Meaning
1, 3	PS Service Required: amber	 Off - Normal operation. On - The power supply (PS) has detected a PS fan failure, PS overtemperature, PS over current, or PS over or under voltage.
2, 4	PS OK: green	 Off - No AC power is present. On - Normal operation. Input AC power and DC output voltage are within specification. Slow blink - Normal operation. Input power is within specification. DC output voltage is not enabled.
5	System locate, service required and OK: various	These operate in the same way as on the front panel.
6	NET MGT port: green/amber	 10/100 BASE-T Ethernet management interface. Top left link indicator: On - Amber for 10Base-T link; green for 100Base-T link. Off - No link or link down. Top right activity indicator: On - No function. Off - No activity. Blinking - Packet activity.



Callout	Indicator/LED: Color	State Meaning
7	Oracle Database Appliance X4-2: Dual 10 GbE SFP+ PCIe 2.0 Low Profile Adapter ports (shown): green/amber or	Oracle Database Appliance X4-2 with 1000/10000 BASE-T SFP+ Ethernet interface. GRN=10G: On - Green for 10GbE
	Oracle Database Appliance X3-2: Sun Dual Port 10GBase-T Adapter ports (not shown): green/ yellow	link; amber for 1GbE link. Off - No function. ACT/LINK (A or B):
		 On - Green for link up. Off - No link. Blinking - Green for packet activity.
		Oracle Database Appliance X3-2 with 1000/10000 BASE-T Ethernet interface.
		 1G/100M=YLW: On - Green for 1GbE link; yellow for 10GbE link. Off - No link.
		 ACT/LINK: On - Green for link up. Off - No link. Blinking - Green for packet activity.
8	NET 0-3 ports: green/amber	100/1000 BASE-T Ethernet interface.
		 Top left activity indicator: On - No function. Off - No activity. Blinking - Packet activity. Top right link indicator: On - Amber for 100Base-T link; green for 1000/10GBBase-T link. Off - No link. Blinking - No function.

Oracle Database Appliance X3-2/X4-2 Storage Shelf Indicators

See a description of the front and back Oracle Database Appliance X3-2/X4-2 storage shelf status indicators.

- Storage Shelf Front Panel Status Indicators
 See a listing of the various font panel status indicators for the Oracle Database Appliance X3-2/X4-2 storage shelf.
- Storage Shelf Back Panel Status Indicators
 See a listing of the various back panel status indicators for the Oracle Database Appliance X3-2/X4-2 storage shelf.




Storage Shelf Front Panel Status Indicators

See a listing of the various font panel status indicators for the Oracle Database Appliance X3-2/X4-2 storage shelf.

The following figure shows the controls and indicators on the Oracle Database Appliance X3-2/ X4-2 storage shelf (DE2-24P) front panel and drives.

(i) Note

The 2 or 3 character LED enclosure ID display panel on the front of the storage shelf is not used with the Oracle Database Appliance product. Any numbers or letters displayed in this panel other than zeros could indicate a fault with either the panel, its cabling (neither of which are customer replaceable), or some other storage shelf component.



Callout	Indicator/LED: Color	State Meaning
1	OK: green	 On - The storage shelf is powered on and operating normally. Off - The storage shelf is unplugged or turned off.
2	Service Required: amber	Off - Normal operation.Steady on - A fault is present in the storage shelf.
3	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off.




Callout	Indicator/LED: Color	State Meaning
4	Drive Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the disk drive.
5	Power/Activity: green	 On - The drive is installed and recognized by the system but there is no drive activity. Blink - The LED blinks randomly in response to data being written to or read from the drive. Off - The drive is powered off or the installed drive is not recognized by the system.

Storage Shelf Back Panel Status Indicators

See a listing of the various back panel status indicators for the Oracle Database Appliance X3-2/X4-2 storage shelf.

The following figure shows the controls and indicators on the Oracle Database Appliance X3-2/ X4-2 storage shelf (DE2-24P) back panel.



Callout	Indicator/LED: Color	State Meaning
1	AC power fault indicator: amber	 On - Indicates an AC power fault.
		 Off - Normal operation.
2	Power supply status indicator: green	 On - The power supply is operating normally.
		 Off - The power supply is unplugged or turned off.
3	Fan fail indicator: amber	 On - The fan is faulty.
		Off - Normal operation.



Callout	Indicator/LED: Color	State Meaning
4	DC power fail indicator: amber	 On - The power supply is faulty. Off - Normal operation.
5	SAS I/O Module status indicators: green or amber	•
6	Reserved	This port is reserved for Oracle Service.
7	Network port (reserved)	This port is reserved for Oracle Service.
8	Host SAS port activity indicators (x4 per port): green	 Random blinking - Indicates host SAS link activity. Off - No link activity.

Oracle Database Appliance Version 1 Status Indicators

Learn about Oracle Database Appliance Version 1 front and back status indicators.

Server Node Front Status Indicators

See a listing of the various system status indicators at the front of an Oracle Database Appliance Version 1 server node.

Server Node Fan Status Indicators

See a listing of the various status indicators for an Oracle Database Appliance Version 1 server node fans.

Server Node Storage and Boot Drive Status Indicators

See a listing of the various status indicators for an Oracle Database Appliance Version 1 server node storage drives.

Server Node Power Supply Status Indicators

See a listing of the various status indicators for an Oracle Database Appliance Version 1 server node power supply.

Server Node Rear Status Indicators

See a listing of the various system status indicators at the rear of an Oracle Database Appliance Version 1 server node.

Server Node Internal LEDs

See a listing of the various internal status indicators (LEDs) for an Oracle Database Appliance Version 1 server node.

• Server Node Ethernet Port Status Indicators


See a listing of the various Ethernet port status indicators at the rear of an Oracle Database Appliance Version 1 server node.



Server Node Front Status Indicators

See a listing of the various system status indicators at the front of an Oracle Database Appliance Version 1 server node.

The following figure shows the general status indicators on the front panel of each Oracle Database Appliance Version 1 server node.





Callout	Indicator/LED: Color	State Meaning
1	Locate button/LED: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off. It is also used to prove physical presence. Indicator Test Mode - Push and hold the Locate button for 5 seconds to activate the push to test feature, which causes all LEDs except disk activity and power supply LEDs to light for 15 seconds.
2	SP OK/Fault: bi-color	 Off - No power is supplied to the SP or it is not functional. Amber - When lit indicates an SP fault. Green - When steady on indicates that Oracle ILOM is fully functional. If blinking, POST diagnostics are running, Oracle ILOM is booting, or firmware is updating. The amber LED indicates the status of the watchdog timer runs continuously, but it times out if it is not reset by Oracle ILOM. If it times out, the amber LED is lit and the green LED is extinguished.
3	Ready to Remove: blue	 Off - Normal operation. Fast Blink - The system is preparing a customer-replaceable unit (CRU) (disk drive, fan module, or power supply) for safe removal but it is not ready yet. Steady on - The CRU can be safely removed.
4	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in system or a subsystem within the chassis.



Callout	Indicator/LED: Color	State Meaning
5	Power/OK: green	This LED indicates the operational state of the chassis. This LED can be in the following states:
		 Off - AC power is not present or the Oracle ILOM boot has not completed.
		Standby blink - Standby power is on and Oracle ILOM can be accessed, but full chassis power is off. The LED blinks at a 10 percent duty cycle (0.1 second on, 2.9 seconds off), that is, the light is on for a very short period of time.
		 Slow blink - The startup sequence has been initiated on the host. The LED blinks at a 50 percent duty cycle, which is noticeably longer than the STANDBY BLINK. This pattern should begin immediately following powering on the system. This status indicates either 1) power-on self-test (POST) diagnostics running on system host or 2) the host is transitioning from the powered-on state to the standby state on shutdown. Steady on - The system is powered on and all host POST tests passed. The system is one of the following states: 1) the system host is ready to boot, or 2) the system host is booting the operating system (OS), or 3) the system host is running
6	Over temperature: ember	the OS. Off - Normal operation.
·	Over temperature: amber	 Steady on - The system is experiencing an over- temperature warning condition.
		This is a warning indication, not a fatal over temperature. Failure to correct this can result in the system over heating and shutting down.



Callout	Indicator/LED: Color	State Meaning
7	Rear Component Failure: amber	 Off - Normal operation. Steady on - The system has detected a power supply fault, a fan fault, or a rear 2.5-inch disk drive fault.
		This fault condition is associated with chassis components located in the rear of the chassis. This fault might be caused by:
		 Power supply failure (AC fault, 12V/3.3Vaux fault, or power supply fan fault)
		Rear fan failureRear 2.5-inch disk failure

Server Node Fan Status Indicators

See a listing of the various status indicators for an Oracle Database Appliance Version 1 server node fans.

Each fan module for Oracle Database Appliance Version 1 has a single bi-colored LED indicating both fan OK and fan fault conditions. The LED lights green to indicate that the fan module is properly plugged into the system and operating within the expected RPM range for a given power management setting. The LED lights amber to indicate a fan fault.

(i) Note

The LEDs on the fan modules are not lit amber on initial system power-on. The fan amber LED only lights if Oracle ILOM detects a failure that indicates a faulty fan module or a missing fan that should be installed.

The following figure shows the fan module status indicators viewable from the rear of each server node.





Indicator/LED: Color	State Meaning
OK: green	 Steady on - The fan is functioning normally. Off - Chassis 3.3V_Standby power is off or there is a fan fault.
Service Required: amber	 Off - Normal operation. Steady on - A fault has been detected with the fan.
	The front and rear panel Service Required LEDs are also lit if the system detects a fan module fault.

Server Node Storage and Boot Drive Status Indicators

See a listing of the various status indicators for an Oracle Database Appliance Version 1 server node storage drives.

Each storage drive for Oracle Database Appliance Version 1 includes three LEDs. They are the same on the front storage drives and the rear-mounted boot drives.

The following figure shows the storage and boot drive status indicators for a server node.



Callout	Indicator/LED: Color	State Meaning
1	Ready to Remove: blue	 Off - Normal operation. Fast blink - The system is preparing a disk drive for safe removal but it is not ready yet. Steady on - The disk drive can be safely removed.
2	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in the disk drive.
3	OK/Activity: green	 On - The drive is installed and recognized by the system but there is no drive activity. Blink - The LED blinks randomly in response to data being written to or read from the drive. Off - The drive is powered off or the installed drive is not recognized by the system.



Server Node Power Supply Status Indicators

See a listing of the various status indicators for an Oracle Database Appliance Version 1 server node power supply.

There are three status LEDs on each power supply for Oracle Database Appliance Version 1.

The following figure shows the power supply status indicators viewable from the rear of each server node.



Callout	Indicator/LED: Color	State Meaning
1	OK: green	 On - The power supply is operating normally. Off - The power supply is unplugged or turned off.
2	Service Required: amber	 On - The power supply is faulty. The front REAR PS LED and the front and rear panel Service Required LEDs are also lit if the system detects a power supply fault. Off - Normal operation.
3	AC Present: green	 On - The power supply is plugged in and AC power is available, regardless of system power state. Off - The power supply is unplugged or turned off.




Server Node Rear Status Indicators

See a listing of the various system status indicators at the rear of an Oracle Database Appliance Version 1 server node.

Each server node in Oracle Database Appliance Version 1 has four summary status LEDs that are located on its back panel.

The following figure shows the status indicators viewable from the rear of each server node.



Callout	Indicator/LED: Color	State Meaning
1	Locate: white	 Off - Normal operation. Fast blink - This LED blinks to help locate the system. Operators can turn this indicator on and off remotely using Oracle ILOM. Pressing this button toggles the fast blink on or off. Indicator Test Mode - Push and hold the Locate button for 5 seconds to activate the push to test feature, which causes all LEDs except disk activity and power supply LEDs to light for 15 seconds.
2	Ready to Remove: blue	 Off - Normal operation. Fast Blink - The system is preparing a customer-replaceable unit (CRU) (disk drive, fan module, or power supply) for safe removal but it is not ready yet. Steady on - The CRU can be safely removed.



Callout	Indicator/LED: Color	State Meaning
3	Service Required: amber	 Off - Normal operation. Steady on - A fault is present in system or a subsystem within the chassis.
4	Power/OK: green	This LED indicates the operational state of the chassis. This LED can be in the following states:
		 Off - AC power is not present or the Oracle ILOM boot has not completed.
		 Standby blink - Standby power is on and Oracle ILOM can be accessed, but full chassis power is off. The LED blinks at a 10 percent duty cycle (0.1 second on, 2.9 seconds off), that is, the light is on for a very short period of time. Slow blink - The startup sequence has been initiated on the host. The LED blinks at a 50 percent duty cycle, which is noticeably longer than the STANDBY BLINK. This pattern should begin immediately following powering on the system. This status indicates either 1) power-on self-test (POST) diagnostics running on system host or 2) the host is transitioning from the powered-on state to the standby state on shutdown. Steady on - The system is powered on and all host POST tests passed. The system is one of the following states: 1) the system host is ready to boot, or 2) the
		system host is booting the operating system (OS), or 3) the system host is running the OS.

Server Node Internal LEDs

See a listing of the various internal status indicators (LEDs) for an Oracle Database Appliance Version 1 server node.

The following section describes the internal LEDs for Oracle Database Appliance Version 1. Each server node contains the following internal LEDs:



Note

A super capacitor (located on the motherboard) provides power to light the server node fault LEDs for up to 15 minutes after the server node is removed from a powered-on system chassis. After approximately 15 minutes, the capacitor discharges enough so that it cannot light the fault LEDs.

Fault Remind Power Good LED.

This green LED lights each time the Fault Remind button is pressed, if the capacitor has enough of a charge to light the fault LEDs. This LED is located next to the Fault Remind button.

For the location of Fault Remind button and the Fault Remind Power Good LED, see Remove Faulty DIMMs.

Memory DIMM Fault LEDs

Each DIMM slot has an adjacent DIMM fault LED. If a DIMM fails, the adjacent LED lights when the Fault Remind button is pressed.

For the location of Fault Remind button and the DIMM fault LEDs, see Remove Faulty DIMMs.

CPU Fault LEDs

Both CPUs have an associated CPU fault LED. If a CPU fails, the associated LED lights when the Fault Remind button is pressed.


For the location of CPU fault LEDs, see Remove Processor (CPU).

Server Node Ethernet Port Status Indicators

See a listing of the various Ethernet port status indicators at the rear of an Oracle Database Appliance Version 1 server node.

Each server node in Oracle Database Appliance Version 1 has two host Ethernet ports (NETO and NET1) and an SP network management port (NET MGT). Each of these has two LEDs that indicate link activity and port speed.

The following figure shows the status indicators viewable from the rear of each server node.





Callout	Indicator/LED: Color	State Meaning
1	Link Activity: green	Lights to indicate link activity.
2	Link Speed: bi-colored	Green - Link established at fastest speed.
		Amber - Link established at next fastest speed or slower speeds.
		Off - Link at slowest speed, which is 10 Mbps.

Preparing Oracle Database Appliance for Service

How to prepare the Oracle Database Appliance for servicing.

- Preparing Oracle Database Appliance X8-2 Series for Service Learn how to prepare an Oracle Database Appliance X8 series system for service.
- Preparing Oracle Database Appliance X7-2 Series for Service Learn how to prepare an Oracle Database Appliance X7 series system for service.
- Preparing Oracle Database Appliance X6-2 Series for Service Learn how to prepare an Oracle Database Appliance X6 series system for service.
- Preparing Oracle Database Appliance X3-2/X4-2/X5-2 for Service Learn how to prepare an Oracle Database Appliance X3-2/X4-2/X5-2 system for service.
- Preparing Oracle Database Appliance Version 1 for Service Learn how to prepare an Oracle Database Appliance Version 1 system for service.

Preparing Oracle Database Appliance X8-2 Series for Service

Learn how to prepare an Oracle Database Appliance X8 series system for service.

This section describes how to prepare an Oracle Database X8-2 series system for service. If you have some other Oracle Database Appliance model, select the appropriate link listed in Preparing Oracle Database Appliance for Service.

Most service procedures are performed on a single appliance component. Service procedures that require a single server node to be powered off can be performed without shutting down the entire appliance. Before powering off any component for service, refer to the Deployment and User's Guide for the Oracle Database Appliance X8 series for any special instructions or commands that must be performed on the appliance to prepare it for service.



(i) Note

The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X8-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X8-2-HA
Safety Precautions
Safety Symbols
Electrostatic Discharge Safety
Required Tools
Powering Down the Server
Disconnect Cables From the Server



Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
Extend the Server to the Maintenance Position	Extend the Server to the Maintenance Position
Remove the Server From the Rack	Remove the Server From the Rack
Take Antistatic Measures	Take Antistatic Measures
Remove the Server Top Cover	Remove the Server Top Cover

Preparing Oracle Database Appliance X7-2 Series for Service

Learn how to prepare an Oracle Database Appliance X7 series system for service.

This section describes how to prepare an Oracle Database X7-2 series system for service. If you have some other Oracle Database Appliance model, select the appropriate link listed in Perparing Oracle Database Appliance for Service.

Most service procedures are performed on a single appliance component. Service procedures that require a single server node to be powered off can be performed without shutting down the entire appliance. Before powering off any component for service, refer to the *Deployment and User's Guide* for the Oracle Database Appliance X7 series for any special instructions or commands that must be performed on the appliance to prepare it for service.



The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X7-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
Safety Precautions	Safety Precautions
Safety Symbols	Safety Symbols
Electrostatic Discharge Safety	Electrostatic Discharge Safety
Required Tools	Required Tools
Powering Down the Server	Powering Down the Server
Disconnect Cables From the Server	Disconnect Cables From the Server
Extend the Server to the Maintenance Position	Extend the Server to the Maintenance Position
Remove the Server From the Rack	Remove the Server From the Rack
Take Antistatic Measures	Take Antistatic Measures
Remove the Server Top Cover	Remove the Server Top Cover

Preparing Oracle Database Appliance X6-2 Series for Service

Learn how to prepare an Oracle Database Appliance X6 series system for service.

This section describes how to prepare an Oracle Database X6-2 series system for service. If you have some other Oracle Database Appliance model, select the appropriate link listed in Preparing Oracle Database Appliance for Service.



Most service procedures are performed on a single appliance component. Service procedures that require a single server node to be powered off can be performed without shutting down the entire appliance. Before powering off any component for service, refer to the Deployment and User's Guide for the Oracle Database Appliance X6 series for any special instructions or commands that must be performed on the appliance to prepare it for service.

(i) Note

The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X6-2 and Oracle Server X6-2L (including Storage Server X6-2 Extreme Flash version) documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
Safety Precautions	Safety Precautions	Safety Precautions
Safety Symbols	Safety Symbols	Safety Symbols
Electrostatic Discharge Safety	Electrostatic Discharge Safety	Electrostatic Discharge Safety
Required Tools	Required Tools	Required Tools
Powering Down the Server	Powering Down the Server	Powering Down the Server
Disconnect Cables From the Server	Disconnect Cables From the Server	<u>Disconnect Cables From the Server</u>
Extend the Server to the Maintenance Position	Extend the Server to the Maintenance Position	Extend the Server to the Maintenance Position
Remove the Server From the Rack	Remove the Server From the Rack	Remove the Server From the Rack
Take Antistatic Measures	Take Antistatic Measures	Take Antistatic Measures
Remove the Server Top Cover	Remove the Server Top Cover Remove the Server Fan Assembly Door	Remove the Server Top Cover

Preparing Oracle Database Appliance X3-2/X4-2/X5-2 for Service

Learn how to prepare an Oracle Database Appliance X3-2/X4-2/X5-2 system for service.

This section describes how to prepare an Oracle Database X3-2/X4-2/X5-2 series system for service. If you have some other Oracle Database Appliance model, select the appropriate link listed in Preparing Oracle Database Appliance for Service.

Most service procedures are performed on a single appliance component. Service procedures that require a single server node to be powered off can be performed without shutting down the entire appliance. Before powering off any component for service, refer to the Deployment and User's Guide for your model for any special instructions or commands that must be performed on the appliance to prepare it for service.





The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Sun Server X3-2, Sun Server X4-2, and Oracle Server X5-2 documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
Safety Precautions	Safety Precautions	Safety Precautions
Safety Symbols	Safety Symbols	Safety Symbols
Electrostatic Discharge Safety	Electrostatic Discharge Safety	Electrostatic Discharge Safety
Required Tools	Required Tools	Required Tools
Powering Down the Server	Powering Down the Server	Powering Down the Server
Disconnect Cables From the Server	Disconnect Cables From the Server	Disconnect Cables From the Server
Extend the Server to the Maintenance Position	Extend the Server to the Maintenance Position	Extend the Server to the Maintenance Position
Remove the Server From the Rack	Remove the Server From the Rack	Remove the Server From the Rack
Take Antistatic Measures	Take Antistatic Measures	Take Antistatic Measures
Remove the Server Top Cover	Remove the Server Top Cover	Remove the Server Top Cover

Preparing Oracle Database Appliance Version 1 for Service

Learn how to prepare an Oracle Database Appliance Version 1 system for service.

This section describes how to prepare an Oracle Database Version 1 system for service. If you have some other Oracle Database Appliance model, select the appropriate link listed in Preparing Oracle Database Appliance for Service.

- Component Replacement Policy (CRUs and FRUs)
- Safety Information
- Required Tools
- Obtaining the Chassis Serial Number
- Shutting Down a Server Node and Powering Off the System
- Performing Electrostatic Discharge and Antistatic Prevention Measures
- Removing Server Nodes From the System Chassis
- Removing the Server Node Top Cover
- Removing the Middle Section of the System Top Cover

Servicing CRUs That Do Not Require System Power Off

Perform tasks for servicing hot plug components in the Oracle Database Appliance.

Hot-pluggable components can be replaced with the system powered on.

Note

Hot-pluggable components can also be replaced with the system powered off. If you choose this method, first power off the system as described in Preparing Oracle
Database Appliance for Service.

- Oracle Database Appliance X8-2 Series Server Node Hot-Pluggable Components
 Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X8-2 series server.
- Oracle Database Appliance X7-2 Series Server Node Hot-Pluggable Components
 Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X7-2 series server.
- Oracle Database Appliance X6-2 Series Server Node Hot-Pluggable Components
 Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X6-2 series server.
- Oracle Database Appliance X3-2/X4-2/X5-2 Series Server Node Hot-Pluggable Components

Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X3-2/X4-2/X5-2 series server.

- Oracle Database Appliance Storage Shelf Hot-Pluggable Components
 Perform hot plug tasks on an Oracle Database Appliance X3-2/X4-2/X5-2 and X6-2-HA/X7-2-HA/X8-2-HA storage shelf.
- Oracle Database Appliance Version 1 Hot-Pluggable Components
 This section describes how to perform hot plug tasks on an Oracle Database Appliance Version 1 system.

Oracle Database Appliance X8-2 Series Server Node Hot-Pluggable Components

Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X8-2 series server.

This section describes how to service customer-replaceable components that do not require server power off for an Oracle Database X8-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing CRUs That Do Not Require System Power Off.</u>





In certain storage expansion scenarios (explained in the following procedures), adding optional storage might require that the appliance be powered off.

If you are servicing storage shelf hot plug components, see <u>Oracle Database Appliance Storage Shelf Hot-Pluggable Components</u>.

Hot-pluggable components are those that can be removed and installed while the system is running. These are designated as Customer Replaceable Units (CRUs).



After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.

Refer to the following table for hot-plug component instructions for your appliance.

(i) Note

Some of the links in the following table take you to instructions *outside* of the Oracle Database Appliance library to the Oracle Server X8-2L documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
Servicing NVMe Storage Drives (CRU) Caution: An NVMe drive must first be powered off before removal. If you do not power off the NVMe drive before removal you can crash the operating system. Oracle Database Appliance uses special commands to remove or add NVMe storage.	Front mounted storage drives are not supported in the server nodes for this product.
Servicing Internal M.2 Flash SSDs (CRU) Note: For detailed instructions on replacing an M.2 Flash SSD boot drive and returning it to service, go to https://support.oracle.com/ and do a search on Doc ID 2626865.1.	1 9
Servicing Fan Modules (CRU) Servicing Power Supplies (CRU)	Servicing Fan Modules (CRU) Servicing Power Supplies (CRU)

<u>Servicing NVMe Storage Drives (CRU)</u>
 Perform tasks for servicing NVMe drives in an Oracle Database Appliance X8 series system.

Servicing NVMe Storage Drives (CRU)

Perform tasks for servicing NVMe drives in an Oracle Database Appliance X8 series system.



- Replacing an NVMe Storage Drive
 Replace an NVMe drive in an Oracle Database Appliance X8 series system.
- Adding NVMe Expansion Storage
 Add NVMe storage to an Oracle Database Appliance X8-2M. Note that the Oracle Database Appliance X8-2S does not support additional storage.

Replacing an NVMe Storage Drive

Replace an NVMe drive in an Oracle Database Appliance X8 series system.

Before removing an NVMe drive it must be powered off. After installing an NVMe drive it must be powered on. Failed drives are automatically powered off after 5 minutes.

If you remove an NVMe drive without first powering it off, you can crash the operating system. Oracle Database Appliance uses special commands to add or remove NVMe storage.

The instructions describe how to replace an NVMe drive using the odaadmcli power on/off commands for an Oracle Database X8-2 series system.

The odaadmcli commands listed here must be run as the root user.

1. Identify the NVMe drive to be replaced. Type the following command at the host:

```
# odaadmcli show disk
```

For example, the drive names pd_00 and pd_01 are seen by the host as NVMe0 and NVMe1 and correspond to front drive slots 0 and 1, respectively.

- 2. Unmount and power off the drive to be replaced. Do one of the following:
 - a. If you are replacing a failed drive, check to see if its blue ready-to-remove light is lit.
 If a drive has failed, it should power off automatically and light its blue ready-to-remove indicator after 5 minutes.
 - **b.** If the drive being replaced doesn't already have its blue ready-to-remove indicator lit, type the following command from the host to unmount and turn off power to the drive:


```
# odaadmcli power disk off pd_xx
```


Where pd_xx is the name of the disk to be replaced as described in step 1.

Before proceeding to the next step confirm that the blue ready-to-remove indicator on the drive is lit.

3. Push the latch release button on the front of the drive to open the drive latch [1], grasp the latch, and pull the drive out of the drive slot [2] as shown in the following figure.









4. Align the replacement drive with the drive slot.

The drive is physically addressed according to the slot in which it is installed. It is important to install a replacement drive in the same slot as the drive that was removed.

5. With the drive latch in the open position, slide the drive into the slot until the drive is fully seated [1] and then close the drive latch to lock the drive in place [2] as shown in the following figure.





6. Power on and remount the replacement drive. Type the following command from the host:

odaadmcli power disk on pd_xx

Where pd_xx is the name of the disk being replaced as described in step 1.

It can take a few minutes for the power-on operation to complete. Once complete, the drive's green OK indicator will light.

7. To check the status of the replacement disk, type the following command from the host:

odaadmcli show disk


For additional information, refer to the Oracle Database Appliance *Deployment and User's Guide*.

Adding NVMe Expansion Storage

Add NVMe storage to an Oracle Database Appliance X8-2M. Note that the Oracle Database Appliance X8-2S does not support additional storage.

• The Oracle Database Appliance X8-2M supports ten expansion slots for NVMe drives. These are slots labeled 2 through 11 as seen from the front of the system (callouts 2 through 11 in the following illustration). Storage drives can be added in sets of two. For information about supported optional storage drives, refer to the Owner's Guide.





If your Oracle Database Appliance X8-2M has software release 18.7, 19.4 or 19.5, all storage must be added BEFORE you initially power-on the system and install system software. Once the system is provisioned and running you cannot add storage.

If your system is running Oracle Database Appliance release 18.8, 19.6 or later version, you can add storage while the system is running and use the appliance CLI software commands to expand the storage configuration.

- When expanding storage, populate slots starting with the lowest numbered available slot (for example, slot 2 as seen on the front panel).
- The drive power-up and storage expansion odaadmcli commands listed here should only be run after all new disk drives have been physically installed. Once you expand storage, you cannot revert to a previous storage configuration (for example, the default installation with only two NVMe drives).
- Remove the drive filler panel of an unpopulated slot by using your finger to pry open the panel release latch and pulling the filler out of the drive slot.



(i) Note

Replace filler panels with drives one at a time to ensure proper system cooling.

Open the latch of the new drive by pressing the release button on the drive.

⚠ Caution

Do not over-rotate the latch outwards when opening. Doing so can damage it.

- Insert the new drive by sliding the drive into the slot until the drive is fully seated. Then close the drive latch to lock the drive in place.
- Repeat steps 1 3 for each new drive.

For the Oracle Database Appliance X8-2M, the name for these drives to the host will be pd_02, pd_03, pd_04, etc., matching the numbering of their respective drive slots up to pd 11.

5. Power on each of the new drives by entering the appropriate commands from the host using the following command format:

odaadmcli power disk on pd_##

Where ## is the number of the drive being powered on (02 through 11).

It can take a few minutes for the power-on operation to complete. Once complete, the green OK indicators will light for the newly installed drives.





(i) Note

Do not attempt to power on and expand storage on one new disk and then power on and expand storage on the next new disk. Before you can expand storage, all the new disks must be powered on with their green OK indicators lit.

Expand the system storage to include the new drives. Type the following command from the host:

odaadmcli expand storage -ndisk number_of_disks

Where number_of_disks is the number of disks being added. The system will then detect and use the new storage.

For additional information, refer to the Oracle Database Appliance Deployment and User's Guide.

Oracle Database Appliance X7-2 Series Server Node Hot-Pluggable Components

Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X7-2 series server.

This section describes how to service customer-replaceable components that do not require server power off for an Oracle Database X7-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Servicing CRUs That Do Not Require System Power Off.

If you are servicing storage shelf hot plug components, see Oracle Database Appliance Storage Shelf Hot-Pluggable Components.

Hot-pluggable components are those that can be removed and installed while the system is running. These are designated as Customer Replaceable Units (CRUs).



Note

After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.

Refer to the following table for hot-plug component instructions for your appliance.



(i) Note

Some of the links in the following table take you to instructions *outside* of the Oracle Database Appliance library to the Oracle Server X7-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.



Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
Servicing NVMe Storage Drives (CRU) Caution: An NVMe drive must first be powered off before removal. If you do not power off the NVMe drive before removal you can crash the operating system. Oracle Database Appliance uses special commands to remove or add NVMe storage.	Front mounted storage drives are not supported in the server nodes for this product.
Servicing Fan Modules (CRU)	Servicing Fan Modules (CRU)
Servicing Power Supplies (CRU)	Servicing Power Supplies (CRU)

Servicing NVMe Storage Drives (CRU)

Perform tasks for servicing NVMe drives in an Oracle Database Appliance X7 series system.

Servicing NVMe Storage Drives (CRU)

Perform tasks for servicing NVMe drives in an Oracle Database Appliance X7 series system.

- Replacing an NVMe Storage Drive
 Replace an NVMe drive in an Oracle Database Appliance X7 series system.
- Adding NVMe Expansion Storage
 Add NVMe storage to an Oracle Database Appliance X7-2M.

Replacing an NVMe Storage Drive

Replace an NVMe drive in an Oracle Database Appliance X7 series system.

Before removing an NVMe drive it must be powered off. After installing an NVMe drive it must be powered on. Failed drives are automatically powered off after 5 minutes.

⚠ Caution

If you remove an NVMe drive without first powering it off, you can crash the operating system. Oracle Database Appliance uses special commands to add or remove NVMe storage.

The instructions describe how to replace an NVMe drive using the odaadmcli power on/off commands for an Oracle Database X7-2 series system.

The odaadmcli commands listed here must be run as the root user.

Identify the NVMe drive to be replaced. Type the following command at the host:

odaadmcli show disk

For example, the drive names pd_00 and pd_01 are seen by the host as NVMe0 and NVMe1 and correspond to front drive slots 0 and 1, respectively.

- 2. Unmount and power off the drive to be replaced. Do one of the following:
 - a. If you are replacing a failed drive, check to see if its blue ready-to-remove light is lit.
 If a drive has failed, it should power off automatically and light its blue ready-to-remove indicator after 5 minutes.




b. If the drive being replaced doesn't already have its blue ready-to-remove indicator lit, type the following command from the host to unmount and turn off power to the drive:


odaadmcli power disk off pd_xx

Where pd_xx is the name of the disk to be replaced as described in step 1.

Before proceeding to the next step confirm that the blue ready-to-remove indicator on the drive is lit.

3. Push the latch release button on the front of the drive to open the drive latch [1], grasp the latch, and pull the drive out of the drive slot [2] as shown in the following figure.







4. Align the replacement drive with the drive slot.

The drive is physically addressed according to the slot in which it is installed. It is important to install a replacement drive in the same slot as the drive that was removed.

5. With the drive latch in the open position, slide the drive into the slot until the drive is fully seated [1] and then close the drive latch to lock the drive in place [2] as shown in the following figure.





6. Power on and remount the replacement drive. Type the following command from the host:

odaadmcli power disk on pd_xx

Where pd xx is the name of the disk being replaced as described in step 1.

It can take a few minutes for the power-on operation to complete. Once complete, the drive's green OK indicator will light.



To check the status of the replacement disk, type the following command from the host:


odaadmcli show disk

For additional information, refer to the Oracle Database Appliance *Deployment and User's Guide*.

Adding NVMe Expansion Storage

Add NVMe storage to an Oracle Database Appliance X7-2M.

• The **Oracle Database Appliance X7-2M** supports six expansion slots for NVMe drives. These are slots labeled 2 through 7 as seen from the front of the system (callouts 1 through 6 in the following illustration). Storage drives can be added in sets of three. For information about supported optional storage drives, refer to the *Owner's Guide*.



If you have the default configuration of only two NVMe drives (seen as pd_00 and pd_01 from the host), you can expand storage by either three (3) or six (6) NVMe drives.

- When expanding storage, populate slots starting with the lowest numbered available slot (for example, slot 2 as seen on the front panel).
- The drive power-up and storage expansion odaadmcli commands listed here should only be run after all new disk drives have been physically installed. Once you expand storage, you cannot revert to a previous storage configuration (for example, the default installation with only two NVMe drives).
- The odaadmcli commands listed here must be run as the root user.
- 1. Remove the drive filler panel of an unpopulated slot by using your finger to pry open the panel release latch and pulling the filler out of the drive slot.



Replace filler panels with drives one at a time to ensure proper system cooling.

2. Open the latch of the new drive by pressing the release button on the drive.

⚠ Caution

Do not over-rotate the latch outwards when opening. Doing so can damage it.

3. Insert the new drive by sliding the drive into the slot until the drive is fully seated. Then close the drive latch to lock the drive in place.



- Repeat steps 1 3 for each new drive.
 - For the **Oracle Database Appliance X7-2M**, the name for these drives to the host will be pd_02, pd_03, pd_04, etc., matching the numbering of their respective drive slots up to pd_07.
- 5. Power on the new drives by entering the appropriate commands from the host.
 - If you are adding three drives, type:

```
# odaadmcli power disk on pd_02
# odaadmcli power disk on pd_03
# odaadmcli power disk on pd_04
```

If you are adding six drives, additionally type:

```
# odaadmcli power disk on pd_05
# odaadmcli power disk on pd_06
# odaadmcli power disk on pd 07
```

It can take a few minutes for the power-on operation to complete. Once complete, the green OK indicators will light for the newly installed drives.

Note

Do not attempt to power on and expand storage on one new disk and then power on and expand storage on the next new disk. Before you can expand storage, all the new disks must be powered on with their green OK indicators lit.

6. Expand the system storage to include the new drives. Type the following command from the host:

```
# odaadmcli expand storage -ndisk number_of_disks
```

Where *number_of_disks* is the number of disks being added. The system will then detect and use the new storage.

For additional information, refer to the Oracle Database Appliance *Deployment and User's Guide*.

Oracle Database Appliance X6-2 Series Server Node Hot-Pluggable Components

Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X6-2 series server.

This section describes how to service customer-replaceable components that do not require server power off for an Oracle Database X6-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing CRUs That Do Not Require System Power Off.</u>

If you are servicing storage shelf hot plug components, see <u>Oracle Database Appliance Storage Shelf Hot-Pluggable Components</u>.

Hot-pluggable components are those that can be removed and installed while the system is running. These are designated as Customer Replaceable Units (CRUs).





After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.

Refer to the following table for hot-plug component instructions for your appliance.

Note

Some of the links in the following table take you to instructions *outside* of the Oracle Database Appliance library to the Oracle Server X6-2 and Oracle Server X6-2L (including Storage Server X6-2 Extreme Flash version) documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
Servicing Non-NVMe Storage Drives (CRU)	Servicing Non-NVMe Storage Drives (CRU)	Servicing Non-NVMe Storage Drives (CRU)
Servicing NVMe Storage Drives (CRU)	Servicing NVMe Storage Drives (CRU)	Front mounted storage drives are not supported in the server nodes
Caution: An NVMe drive must first be powered off before removal. If you do not power off the NVMe drive before removal you can crash the operating system. Oracle Database Appliance uses special commands to remove or add NVMe storage.	Caution: An NVMe drive must first be powered off before removal. If you do not power off the NVMe drive before removal you can crash the operating system. Oracle Database Appliance uses special commands to remove or add NVMe storage.	for this product.
Servicing Fan Modules (CRU)	Servicing Fan Modules (CRU)	Servicing Fan Modules (CRU)
Servicing Power Supplies (CRU)	Servicing Power Supplies (CRU)	Servicing Power Supplies (CRU)

<u>Servicing NVMe Storage Drives (CRU)</u>
 Perform tasks to service NVMe drives in an Oracle Database Appliance X6 Series system.

Servicing NVMe Storage Drives (CRU)

Perform tasks to service NVMe drives in an Oracle Database Appliance X6 Series system.

This section describes servicing NVMe drives in an Oracle Database Appliance X6-2 series system.

- Replacing an NVMe Storage Drive
 Replace an NVMe drive in an Oracle Database Appliance X6 series system.
- Adding NVMe Expansion Storage
 Add NVMe storage in an Oracle Database Appliance X6 series system.



Replacing an NVMe Storage Drive

Replace an NVMe drive in an Oracle Database Appliance X6 series system.

Before removing an NVMe drive it must be powered off. After installing an NVMe drive it must be powered on. Failed drives are automatically powered off after 5 minutes.

⚠ Caution

If you remove an NVMe drive without first powering it off, you can crash the operating system. Oracle Database Appliance uses special commands to add or remove NVMe storage.

The instructions describe how to replace an NVMe drive using the odaadmcli power on/off commands for an Oracle Database X6-2 series system.

The odaadmcli commands listed here must be run as the root user.

1. Identify the NVMe drive to be replaced. Type the following command at the host:

odaadmcli show disk

For example, the drive names pd_00 and pd_01 are seen by the host as NVMe0 and NVMe1 and correspond to front drive slots 0 and 1, respectively.


- 2. Unmount and power off the drive to be replaced. Do one of the following:
 - a. If you are replacing a failed drive, check to see if its blue ready-to-remove light is lit.
 If a drive has failed, it should power off automatically and light its blue ready-to-remove indicator after 5 minutes.
 - b. If the drive being replaced doesn't already have its blue ready-to-remove indicator lit, type the following command from the host to unmount and turn off power to the drive:

```
# odaadmcli power disk off pd_xx
```

Where pd_xx is the name of the disk to be replaced as described in step 1.

Before proceeding to the next step confirm that the blue ready-to-remove indicator on the drive is lit.

3. Push the latch release button on the front of the drive to open the drive latch [1], grasp the latch, and pull the drive out of the drive slot [2] as shown in the following figure.






4. Align the replacement drive with the drive slot.

The drive is physically addressed according to the slot in which it is installed. It is important to install a replacement drive in the same slot as the drive that was removed.

5. With the drive latch in the open position, slide the drive into the slot until the drive is fully seated [1] and then close the drive latch to lock the drive in place [2] as shown in the following figure.



6. Power on and remount the replacement drive. Type the following command from the host:

odaadmcli power disk on pd_xx

Where pd_xx is the name of the disk being replaced as described in step 1.

It can take a few minutes for the power-on operation to complete. Once complete, the drive's green OK indicator will light.

7. To check the status of the replacement disk, type the following command from the host:


odaadmcli show disk

For additional information, refer to the Oracle Database Appliance *Deployment and User's Guide*.

Adding NVMe Expansion Storage

Add NVMe storage in an Oracle Database Appliance X6 series system.

The Oracle Database Appliance X6-2S/X6-2M supports two expansion slots for NVMe drives. These are slots labeled NVMe2 and NVMe3 as seen from the front of the system (callouts 1 and 2 in the following illustration). When adding NVMe storage, you must populate both of these slots. For information about supported optional storage drives, refer to the Owner's Guide.






If you have the default configuration of only two NVMe drives (seen as pd_00 and pd_01 from the host), you can expand storage by adding two (2) NVMe drives.

The Oracle Database Appliance X6-2L supports three expansion slots for NVMe drives.
 These are slots labeled NVMe2, NVMe5, and NVMe8 as seen from the front of the system (callouts 1, 2 and 3 in the following illustration). When adding NVMe storage, you must populate all three of these slots.

(i) Note

Drive slots NVMe9, NVMe10 and NVMe11 are not supported for this product.



If you have the default configuration of NVMe drives (seen as pd_00 , pd_01 , pd_03 , pd_04 , pd_06 and pd_07 from the host), you can expand storage by adding three (3) NVMe drives.

- The drive power-up and storage expansion odaadmcli commands listed here should only be run after all new disk drives have been physically installed. Once you expand storage, you cannot revert to a previous storage configuration (for example, the default factory storage configuration).
- The odaadmcli commands listed here must be run as the root user.
- 1. Remove the drive filler panel of an unpopulated slot by using your finger to pry open the panel release latch and pulling the filler out of the drive slot.

(i) Note

Replace filler panels with drives one at a time to ensure proper system cooling.

2. Open the latch of the new drive by pressing the release button on the drive.

⚠ Caution

Do not over-rotate the latch outwards when opening. Doing so can damage it.

Insert the new drive by sliding the drive into the slot until the drive is fully seated. Then close the drive latch to lock the drive in place.



- Repeat steps 1 3 for each new drive.
 - For the Oracle Database Appliance X6-2S/X6-2M, the name for these drives to the host will be pd_02 and pd_03, matching the numbering of their respective drive slots.
 - For the Oracle Database Appliance X6-2L, the name for these drives to the host will be pd_02, pd_05 and pd_08, matching the numbering of their respective drive slots.
- 5. Power on the new drives by entering the appropriate commands from the host.
 - For the Oracle Database Appliance X6-2S/X6-2M, type:

```
# odaadmcli power disk on pd_02
# odaadmcli power disk on pd_03
```

For the **Oracle Database Appliance X6-2L**, type:

```
# odaadmcli power disk on pd_02
# odaadmcli power disk on pd_05
# odaadmcli power disk on pd_08
```

It can take a few minutes for the power-on operation to complete. Once complete, the green OK indicators will light for the newly installed drives.

(i) Note

Do not attempt to power on and expand storage on one new disk and then power on and expand storage on the next new disk. Before you can expand storage, all the new disks must be powered on with their green OK indicators lit.

6. Expand the system storage to include the new drives. Type the following command from the host:

```
# odaadmcli expand storage
```

The system will then detect and use the new storage.

For additional information, refer to the Oracle Database Appliance *Deployment and User's Guide*.

Oracle Database Appliance X3-2/X4-2/X5-2 Series Server Node Hot-Pluggable Components

Provides instructions on how to perform hot plug tasks on an Oracle Database Appliance X3-2/X4-2/X5-2 series server.

This section describes how to service customer-replaceable components that do not require server power off for an Oracle Database X3-2/X4-2/X5-2 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing CRUs That Do Not Require System Power Off.</u>

If you are servicing storage shelf hot plug components, see <u>Oracle Database Appliance Storage Shelf Hot-Pluggable Components</u>.

Hot-pluggable components are those that can be removed and installed while the system is running. These are designated as Customer Replaceable Units (CRUs).





After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.

Refer to the following table for hot-plug component instructions for your appliance.



The links in the following table take you to instructions *outside* of the Oracle Database Appliance library to the Sun Server X3-2, Sun Server X4-2, and Oracle Server X5-2 documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
Servicing Storage Drives (CRU)	Servicing Storage Drives (CRU)	Servicing Storage Drives (CRU)
Note that for bare metal installations of this appliance, you must run the oakcli add disk -local command after replacing a failed disk in a server node. Refer to the Administration and Reference Guide for details.	Note that for bare metal installations of this appliance, you must run the oakcli add disk -local command after replacing a failed disk in a server node. Refer to the Deployment and User's Guide for details.	
Servicing Fan Modules (CRU)	Servicing Fan Modules (CRU)	Servicing Fan Modules (CRU)
Servicing Power Supplies (CRU)	Servicing Power Supplies (CRU)	Servicing Power Supplies (CRU)

Oracle Database Appliance Storage Shelf Hot-Pluggable Components

Perform hot plug tasks on an Oracle Database Appliance X3-2/X4-2/X5-2 and X6-2-HA/X7-2-HA/X8-2-HA storage shelf.

This section describes replacing hot-pluggable components for the Oracle Database Appliance storage shelf. Only certain versions of Oracle Database Appliance support a storage shelf. If you have Oracle Database Appliance Version 1, go to Oracle Database Appliance Version 1 Hot-Pluggable Components.



(i) Note

In certain storage expansion scenarios (explained in the following procedures), adding optional storage might require that the appliance be powered off.

A storage shelf, or expansion storage shelf, are only supported with the following Oracle Database Appliance products:



- Oracle Database Appliance X6-2-HA/X7-2-HA/X8-2-HA support the DE3-24C shelf.
- Oracle Database Appliance X5-2 supports the DE2-24C shelf.
- Oracle Database Appliance X3-2/X4-2 support the DE2-24P shelf.

Hot-pluggable components are those that can be removed and installed while the system is running. These are designated as Customer Replaceable Units (CRUs).

Data loss. Do not remove power from both power supplies of the storage shelf or storage expansion shelf (if equipped) while any databases are running. If you must power off the storage shelf or expansion storage shelf, stop the database first.

(i) Note

After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.

<u>Servicing Storage Shelf Components</u>
 Perform hot plug tasks on an Oracle Database Appliance storage shelf.

Servicing Storage Shelf Components

Perform hot plug tasks on an Oracle Database Appliance storage shelf.

Under most circumstances, Oracle Database Appliance storage shelf components can all be replaced while the storage shelf is powered-on and running. Any exceptions will be described in the following procedures.

- Adding Optional Oracle Database Appliance X8-2-HA Storage Shelf Drives (CRU)
 Add disk storage in an Oracle Database Appliance X8-2-HA storage shelf.
- Adding Optional Oracle Database Appliance X7-2-HA Storage Shelf Drives (CRU)
 Add disk storage in an Oracle Database Appliance X7-2-HA storage shelf.
- Adding Optional Oracle Database Appliance X6-2-HA Storage Shelf Drives (CRU)
 Add disk storage in an Oracle Database Appliance X6-2-HA storage shelf.
- Replace a Storage Shelf HDD or SSD (CRU)
 Replace a storage disk in an Oracle Database Appliance storage shelf.
- Replace a Storage Shelf Power Supply (CRU)
 Replace a power supply in an Oracle Database Appliance storage shelf.
- Replace a Storage Shelf I/O Module (CRU)
 Replace an IO module in an Oracle Database Appliance storage shelf.


Adding Optional Oracle Database Appliance X8-2-HA Storage Shelf Drives (CRU)

Add disk storage in an Oracle Database Appliance X8-2-HA storage shelf.

The **Oracle Database Appliance X8-2-HA storage shelf** partially-populated base configuration supports storage expansion with either 7.68 TB SSDs (available in six-packs) or



14 TB HDDs (available in an eighteen-pack). Depending on your initial base storage shelf configuration, there can be up to eighteen expansion slots. These slots are labeled 6-23 as seen from the front of the system (callouts 6 through 23 in the following illustration).



 If your system has Oracle Database Appliance X8-2-HA software release 18.7, 19.4 or 19.5, all storage must be added BEFORE you initially power-on the system and install system software. Once the system is provisioned and running you cannot add storage.

If your system is running **Oracle Database Appliance release 18.8, 19.6 or later version:**

- For a high performance shelf, you can add up to eighteen 7.68 TB SSDs (available in six-packs). You can add storage with the system running and use the appliance CLI software commands to expand the storage configuration.
- For a high capacity shelf, you can add eighteen 14 TB HDDs (available in an eighteen-pack). You must power off the appliance, add storage, then re-image and redeploy the appliance software. This is required to reconfigure the appliance from the default high performance mode to high capacity mode.
- Expanding the base configuration storage shelf with 7.68 TB SSDs for high performance. The base configuration has slots 0-5 with 7.68 TB drives for DATA/RECO. Expansion SSDs are available in six-packs and are populated in shelf storage slots from the bottom up to also be used for DATA/RECO, as follows:
 - The first six expansion drives go into slots 6-11.
 - The second six expansion drives go into slots 12-17.
 - The third six expansion drives go into slots 18-23.


The following illustration shows the expanded drive configuration for 7.68 TB SSDs.





• Expanding the base configuration storage shelf with 14 TB HDDs for high capacity. When expanding the storage shelf with HDDs, the base configurations SSDs will be used for FLASH and the HDDs will be used for DATA/RECO. Expansion HDDs are available in an eighteen-pack and populate the empty shelf storage slots (slots 6-23).

The following illustration shows the expanded drive configuration for 14 TB HDDs.




- Once you expand storage to support additional disks, you cannot revert to the base configuration (no drives in slots 6-23).
- If you plan on adding another storage shelf, it must be populated identically to your first storage shelf.
- The odaadmcli commands listed here must be run as the root user.
- 1. Do one of the following:
 - If you are adding 7.68 TB SSDs to the storage shelf, leave the appliance powered on and proceed to the next step.
 - If you are adding 14 TB HDDs to the storage shelf, power off the appliance and proceed to the next step.
- 2. To install the new drives into the storage shelf, do the following:
 - a. Remove one of the empty slot drive filler panels by pressing its release button [1] and removing it from the drive slot [2] as shown in the following figure.





① Note


Replace filler panels with drives one at a time to ensure proper storage shelf chassis cooling.



- Open the drive lever of the new drive by pressing the release button on the drive.
- Slide the new drive into the drive slot [1] until it engages with the backplane connector and then close the lever to fully seat the drive and lock it into place [2] as shown in the following figure.

Check that the drive is locked in place and flush with the other drives.





- d. Repeat steps a through c until all of the new drives are installed in the storage shelf.
- **3.** Do one of the following:
 - If you added 7.68 TB SSDs to the storage shelf, check that the OK indicator on each new drive is steady green to indicate that it is ready. Then expand the system storage to include the new drives by typing the following command from the primary server node (node 0):

odaadmcli expand storage -ndisk number_of_disks -enclosure 0

Where *number_of_disks* is the number of disks being added. The system will then detect and use the new storage. It can take up to 12 minutes to update the configuration. For additional storage commands, refer to the *Deployment and User's Guide*.

- If you added 14 TB HDDs to the storage shelf, power on the appliance, then re-image and redeploy the appliance software as described in the *Deployment and User's Guide*
- 4. If you are also adding a storage expansion shelf (can only be added to a system with an identically and fully populated storage shelf), you can do so after successfully completing the previous step.

Refer to the Oracle Database Appliance *Owner's Guide* for information on installing a storage expansion shelf into a rack.

Refer to the Oracle Database Appliance *Deployment and User's Guide* for information on cabling and storage expansion commands for a storage expansion shelf.


Adding Optional Oracle Database Appliance X7-2-HA Storage Shelf Drives (CRU)

Add disk storage in an Oracle Database Appliance X7-2-HA storage shelf.

The **Oracle Database Appliance X7-2-HA storage shelf** partially-populated base configuration supports 15 expansion slots for either 7.68 TB SAS SSDs (available in five-



packs) or 14 TB SAS HDDs (available in a fifteen-pack). These expansion slots are labeled 5-19 as seen from the front of the system (callouts 5 through 19 in the following illustration).



- Expanding the base configuration storage shelf with 7.68 TB SSDs for high performance. The base configuration has slots 20-23 populated with 800GB drives for REDO and slots 0-4 with 3.2 TB drives for DATA/RECO. Note that 3.2 TB SSDs are no longer available. Storage expansions options are:
 - If you are running Oracle Database Appliance software release 18.7, you must power off the system to remove any existing 3.2 TB SSDs and replace them with 7.68 TB SSDs. You cannot have both types of drives in the storage shelf. After the new storage is added you must perform clean-up, redeploy the appliance software, and restore the database from a backup after adding the new storage.
 - If you are running Oracle Database Appliance software release 18.8, 19.6 or later version, your 7.68 TB SSDs can be added with the system running without replacing the existing 3.2 TB SSDs. Note that the 7.68 TB SSDs will be formatted as 3.2 TB SSDs after being added to the system to match the existing 3.2 TB drives.


Expansion drives are available in five-packs and are populated in shelf storage slots from the bottom up, as follows:

- The first five expansion drives go into slots 5-9.
- The second five expansion drives go into slots 10-14.
- The third five expansion drives go into slots 15-19.

When you expand storage, you must first install all of your expansion disks (5, 10 or 15). Once you expand storage to support additional disks, you cannot revert to the base configuration (no drives in slots 5-19).

The following illustration shows an example expanded drive configuration with 7.68 TB SSDs (existing 3.2 TB SSDs replaced).






- Expanding the base configuration storage shelf with 14 TB HDDs for high capacity. The base configuration has slots 20-23 populated with 800GB drives for REDO and slots 0-4 with 3.2 TB drives for DATA/RECO. For a high capacity shelf, you can add up to fifteen 14 TB HDDs (available in five-packs). Note that 10 TB HDDs are no longer available. In order to support 14 TB HDDs in the system you must be running Oracle Database Appliance software release 18.7, 18.8, 19.6 or later version. In addition:
 - The storage shelf must be powered off and the five 3.2 TB SSDs already in the base configuration must be moved to slots 15 -19 and the new storage installed.
 - After the new storage is added, perform clean-up, redeploy the appliance software, and restore the database from a backup.

Once you expand storage to support additional disks, you cannot revert to the base configuration (no drives in slots 5-19).

The following illustration shows the expanded drive configuration with 14 TB HDDs.



- The storage expansion shelf is no longer available for this product.
- The odaadmcli commands listed here must be run as the root user.
- Do one of the following:
 - If your appliance is running **Oracle Database Appliance release 18.7** and you are adding 7.68 TB SDDs to the storage shelf and replacing existing 3.2 TB SSDs, power off the appliance and proceed to the next step.
 - If your appliance is running Oracle Database Appliance release 18.8, 19.6 or later version and you are adding 7.68 TB SDDs to the storage shelf and not replacing existing 3.2 TB SSDs, leave the appliance powered on and proceed to the next step.
 - If your appliance is running Oracle Database Appliance release 18.7, 18.8, 19.6 or later version and you are adding 14 TB HDDs to the storage shelf, power off the




appliance and move the 3.2 TB DATA/RECO drives from shelf storage slots 0-4 to slots 15-19. Proceed to the next step.

- To install the new drives into the storage shelf, do the following:
 - Remove one of the empty slot drive filler panels by pressing its release button [1] and removing it from the drive slot [2] as shown in the following figure.

(i) Note


Replace filler panels with drives one at a time to ensure proper storage shelf chassis cooling.



- Open the drive lever of the new drive by pressing the release button on the drive.
- Slide the new drive into the drive slot [1] until it engages with the backplane connector and then close the lever to fully seat the drive and lock it into place [2] as shown in the following figure.

Check that the drive is locked in place and flush with the other drives.






- d. Repeat steps a through c until all of the new drives are installed in the storage shelf.
- 3. Do one of the following:
 - If your appliance is running **Oracle Database Appliance release 18.7** and you added 7.68 TB SSDs and replaced existing 3.2 TB SSDs with 7.68 TB SSDs, power on the appliance and perform cleanup, redeploy the appliance and restore the database as described in the *Deployment and User's Guide* for the appliance.
 - If your appliance is running **Oracle Database Appliance release 18.8, 19.6 or later version** and you added 7.68 TB SSDs to the shelf and did not replace existing 3.2 TB SSDs, check that the OK indicator on each new drive is steady green to indicate that it is ready. Then expand the system storage to include the new drives by typing the following command from the primary server node (node 0):
 - # odaadmcli expand storage -ndisk number_of_disks -enclosure 0
 - Where *number_of_disks* is the number of disks being added. The system will then detect and use the new storage.
 - If your appliance is running Oracle Database Appliance software release 18.7, 18.8, 19.6 or later version and you added 14 TB HDDs to the shelf and moved the existing 3.2 TB SSDs, power on the appliance and perform cleanup, redeploy the appliance and restore the database as described in the *Deployment and User's Guide* for the appliance.

Adding Optional Oracle Database Appliance X6-2-HA Storage Shelf Drives (CRU)

Add disk storage in an Oracle Database Appliance X6-2-HA storage shelf.

The **Oracle Database Appliance X6-2-HA storage shelf** partially-populated base configuration supports ten expansion slots for 7.68 TB SAS SSD drives. These are slots labeled 10-19 as seen from the front of the system (callouts 10 through 19 in the following illustration). When adding to the storage shelf, you must populate all of these slots at the same time.





• If your system is running Oracle Database Appliance software release 18.7, 18.8, 19.6 or later version, 7.68 TB SAS SSDs can be used for storage expansion (1.6 TB SSDs are no longer available). However, this means that you must also replace any existing 1.6 TB SSDs with 7.68 TB SSDs, perform clean-up, redeploy the appliance software, and restore the database from a backup. You cannot have both types of drives in the storage shelf.


If you expand storage, you must first add all of the disks and then expand storage on all the new disks at the same time. Once you expand storage to support disks in slots 10-19, you cannot revert to the base configuration (no drives in slots 10-19).

- The storage expansion shelf is no longer available for this product.
- 1. To install the new drives into the storage shelf, do the following:
 - a. Remove one of the drive filler panels from slots 10-19 by pressing its release button [1] and removing it from the drive slot [2] as shown in the following figure.

(i) Note


Replace filler panels with drives one at a time to ensure proper storage shelf chassis cooling.





- **b.** Open the drive lever of the new drive by pressing the release button on the drive.
- c. Slide the new drive into the drive slot [1] until it engages with the backplane connector and then close the lever to fully seat the drive and lock it into place [2] as shown in the following figure.

Check that the drive is locked in place and flush with the other drives.





- **d.** Repeat steps a through c until all of the empty drive slots in the storage shelf are filled with the new drives
- Replaced any existing 1.6 TB SSDs with 7.68 TB SDDs.
- 3. Power on the appliance and perform cleanup, redeploy the appliance and restore the database as described in the *Deployment and User's Guide* for the appliance.

Replace a Storage Shelf HDD or SSD (CRU)

Replace a storage disk in an Oracle Database Appliance storage shelf.

Note

After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take several minutes to complete.

1. Locate the failed drive on the front of the storage shelf.

Look for the drive with its Service Required indicator and/or Ready-to-Remove indicator lit.

Equipment damage. Do not remove a drive unless you have an immediate replacement.


Remove the drive:

• For the DE3-24C, press the release button [1] to release the drive lever and then, rotate the lever open and, grasping the drive body, slide the drive out of the storage shelf [2] as shown in the following figure.


(i) Note

For the DE2-24C, slide the release latch as indicated by the debossed arrow to release the drive lever.





• For the DE2-24P, slide the release latch as indicated by the debossed arrow to release the drive lever and then, rotate the lever open and, grasping the drive body, slide the drive out of the storage shelf as shown in the following figure.




3. Install the replacement drive:

• For the DE2-24C and DE3-24C, open the drive lever on the replacement drive. Slide the new drive into the drive slot [1] until it engages with the backplane connector and then close the lever to fully seat the drive and lock it into place [2] as shown in the following figure.


Check that the drive is locked in place and flush with the other drives.





• For the DE2-24P, open the drive lever on the replacement drive. Slide the drive into the drive slot until it engages with the backplane connector and then close the lever to fully seat the drive and lock it into place as shown in the following figure.

Check that the drive is locked in place and flush with the other drives.



Once installed, the system should automatically detect and use the replacement drive.
 Ensure that the green OK indicator for the replacement drive lights to show that the drive is ready.

This can take a few minutes to complete.




Replace a Storage Shelf Power Supply (CRU)

Replace a power supply in an Oracle Database Appliance storage shelf.

The storage shelf and the storage expansion shelf each have two power supplies. Indicators (LEDs) on the power supplies indicate their operation state.


The power supplies are redundant and one can be replaced while the appliance is running.

Example figure showing a DE3-24C power supply:



Example figure showing a DE2-24C or DE2-24P power supply:






Callout	Description
1	AC power fail indicator
2	Fan fail indicator
3	Power supply status indicator
4	DC power fail indicator
5	Release lever
6	AC connector
7	On/Off switch


If any of the indicators are amber, or if the power supply status indicator does not light, replace the power supply.

- 1. Ensure the power supply on/off switch is in the "O" off position.
- 2. Disconnect the power cord tie strap from the power cord, and unplug the power cord from the power supply.
- **3.** Remove the power supply unit using the procedure for your storage shelf model:
 - For the DE3-24C, grasp the power supply handle, push the release button [1], and slide the power supply out of the chassis [2] as shown in the following figure.





• For the DE2-24C or DE2-24P, push the ejector release button [1], grasp the power supply ejector handle and rotate it to the open position [2] as shown in the following figure. Slide the power supply out of the chassis.



4. Install the replacement power supply unit using the procedure for your storage shelf model:



- For the DE3-24C, slide the replacement power supply module into the chassis. When fully installed, you should hear a click of the release lever returning to the locked position.
- For a DE2-24C or DE2-24P, open the ejector handle arm on the replacement power supply. Slide the replacement power supply module into the chassis. Push the lever fully closed until you hear or feel a click.
- **5.** Plug the power cord into the new power supply and attach the power cord tie strap to the power cord.
- 6. Place the power supply on/off switch to the "I" on position.
 The Power/OK status LED should be a steady green, and all other indicators should be off.

Replace a Storage Shelf I/O Module (CRU)


Replace an IO module in an Oracle Database Appliance storage shelf.

Storage Shelf SAS I/O modules are fully redundant and can be replaced while the appliance is running.

Note


After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.

- 1. Disconnect the cables from the I/O module (the various models are shown below). Be sure to mark the cables so you can return them to their proper connectors.
 - Example figure showing the DE3-24C (callout descriptions are listed in the table below):




 Example figure showing the DE2-24C (callout descriptions are listed in the table below):






 Example figure showing the DE2-24P (callout descriptions are listed in the table below):




Callout	Description
1	I/O module locking levers
2	I/O module 1 (top)
3	I/O module 0 (bottom)

- 2. Remove the I/O module using the procedure for your storage shelf model:
 - For the DE3-24C, using your thumb and forefinger, pinch the release buttons [1] together to release the locking lever [2] as shown in the following figure. Grasp the lever and remove the I/O module from the chassis [3] as shown in the following figure.





• For the DE2-24C or DE2-24P, using your thumb and forefinger, squeeze the release button [1] toward the locking lever hole to release the lever [2]. Grasp the lever and remove the I/O module from the chassis.



- 3. Open the lever in the new I/O module if it is not already open.
- 4. Slide the new I/O module into the disk shelf and close the locking lever.

⚠ Caution

Equipment damage. Be careful not to damage the connector pins at the back of the I/O module.

- 5. Reconnect the cables.
- 6. Verify that the new I/O module is working correctly.
 - After approximately 60 seconds, the power LED should be solid green and the Fault/Locate LED should be off.



For each port that has a cable connected, all four activity LEDs should be solid green.

Oracle Database Appliance Version 1 Hot-Pluggable Components

This section describes how to perform hot plug tasks on an Oracle Database Appliance Version 1 system.

This section describes how to service customer-replaceable components that do not require server power off for an Oracle Database Version 1 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing CRUs That Do Not Require System Power Off.</u>

Only certain versions of Oracle Database Appliance support a storage shelf (the Oracle Database Appliance Version 1 does not). If you have Oracle Database Appliance that supports a storage shelf and you need to service its components, go to Oracle Database Appliance X3-2/X4-2/X5-2 and X6-2-HA/X7-2-HA/X8-2-HA Storage Shelf Hot-Pluggable Components.

Hot-pluggable components are those that can be removed and installed while the system and the server nodes are running. These are designated as Customer Replaceable Units (CRUs).

In Oracle Database Appliance Version 1, the following devices are hot-pluggable:

- Storage and Boot Drives. See <u>Servicing Storage Drives and Boot Drives (CRU)</u>.
- Fan modules. See Servicing Fan Modules (CRU)
- Power supplies. See Servicing Power Supplies (CRU)

Servicing CRUs That Require System Power Off

Perform tasks for servicing customer-replaceable units (CRUs) for the Oracle Database Appliance that require you to power off system components.

Note

The servicing of hot-plug components such as the HDDs, SDDs, power supplies, and fans is described in Servicing CRUs That Do Not Require System Power Off.

- <u>Servicing Oracle Database Appliance X8-2 Series CRUs</u>
 Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X8 series system.
- <u>Servicing Oracle Database Appliance X7-2 Series CRUs</u>
 Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X7 series system.
- <u>Servicing Oracle Database Appliance X6-2 Series CRUs</u>
 Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X6 series system.
- <u>Servicing Oracle Database Appliance X3-2/X4-2/X5-2 CRUs</u>
 Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X3-2/X4-2/X5-2 system.
- <u>Servicing Oracle Database Appliance Version 1 CRUs</u>
 This section describes how to perform CRU service tasks requiring system power off for Oracle Database Appliance Version 1 system.

Servicing Oracle Database Appliance X8-2 Series CRUs

Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X8 series system.

This section describes how to service customer-replaceable components that require server power off for an Oracle Database X8-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Servicing CRUs That Require System Power Off.

(i) Note

When adding DIMMs to the system, refer to the "Optional Component Installation" section in the *Owner's Guide* for supported configurations.



This section describes how to service customer-replaceable units (CRUs) that require you to power off the server.



For the Oracle Database Appliance X8-2-HA, all of the CRUs on the storage shelf and the storage expansion shelf can be replaced while the power is on. See <u>Oracle Database Appliance Storage Shelf Hot-Pluggable Components</u> for storage shelf component replacement procedures.

Note

The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X8-2L documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
CRU List	CRU List
Servicing DIMMs (CRU)	Servicing DIMMs (CRU)
Adding Optional Public Network PCIe Cards (CRU)	Adding Optional Public Network PCIe Cards (CRU)
Servicing PCIe Cards (CRU)	Servicing PCIe Cards (CRU)
Servicing the Oracle PCIe NVMe Switch Card (CRU)	This product does not have a PCIe NVMe Switch Card.
The NVMe Switch Card location:	
 Oracle Database Appliance X8-2S: slot 9 	
 Oracle Database Appliance X8-2M: slots 3, 4, 8 and 9 	
Servicing Internal USB Flash Drives (CRU)	Servicing Internal USB Flash Drives (CRU)
Servicing the Battery (CRU)	Servicing the Battery (CRU)

Adding Optional Public Network PCIe Cards in Oracle Database Appliance X8-2
 Describes installation sequence for adding optional public network PCIe cards to the Oracle Database Appliance X8-2.

Adding Optional Public Network PCIe Cards in Oracle Database Appliance X8-2

Describes installation sequence for adding optional public network PCIe cards to the Oracle Database Appliance X8-2.

The Oracle Database Appliance X8-2 series systems support up to three optional public network cards (or three network cards per node if you have an X8-2-HA).

- If possible, order any optional public network cards when you initially buy the system and have the cards factory installed.
- If your Oracle Database Appliance is running software release 18.7 and you want to add optional public network cards after your appliance has been delivered from the factory, the following rules apply:



- All optional network cards should be installed **BEFORE** you initially power-on the system and install system software. Once the system is provisioned and running, adding PCIe cards afterwards will require that you perform clean-up, redeploy the appliance software, and restore the database from a backup.
- All optional network cards must be the same type and model (refer to the table below).
- You must install optional network cards in the proper order and slots (refer to the table below).
- If your Oracle Database Appliance is running software release 18.8, 19.6 or later version and you want to add or replace public network cards after your appliance has been delivered from the factory, the following rules apply:
 - You can install any of the supported network cards listed in the table below.
 - You must install optional network cards in the proper order and slots (refer to the table below).
 - If you want to replace an existing network card, you must first delete the network card and its network interface using the appliance oftware. Then replace the physical network card with the new one. When the appliance is restarted the new network card will be used. For specific instructions on software removal or configuration of a public network card, refer to the Deployment and User's Guide.



(i) Note

You cannot replace the factory installed public network card installed in PCIe slot 7. Also, for the Oracle Database Appliance X8-2-HA, you cannot replace the factory installed cluster interconnect network card installed in PCIe slot 1.

The following table describes the supported network cards and the order in which they can be installed in the system.

Description	Oracle Database	Oracle Database	Oracle Database
2 003pus	Appliance X8-2S	Appliance X8-2M	Appliance X8-2-HA (per node)
Supported public network PCIe cards:	 Oracle Dual Port 25 Gb Ethernet Adapter Oracle Quad Port 10GBase-T Adapte 	Gb Ethernet Adapter Oracle Quad Port	 Oracle Dual Port 25 Gb Ethernet Adapter Oracle Quad Port 10GBase-T Adapter
Installation order:	 By default, the server comes with a public network card installed in PCIe slo 7. 	public network card	with a public
	A second public network card can be installed in PCIe slo 8.	t installed in PCIe slot 2.	2. A second public
	 A third public network card can be installed in PCIe slo 10. 		



Description	Oracle Database Appliance X8-2S	Oracle Database Appliance X8-2M	Oracle Database Appliance X8-2-HA (per node)
Installation intructions:	Servicing PCIe Cards	Servicing PCIe Cards	Servicing PCIe Cards
	(CRU)	(CRU)	(CRU)

Servicing Oracle Database Appliance X7-2 Series CRUs

Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X7 series system.

This section describes how to service customer-replaceable components that require server power off for an Oracle Database X7-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Servicing CRUs That Require System Power Off.



(i) Note

When adding DIMMs to the system, refer to the "Optional Component Installation" section in the *Owner's Guide* for supported configurations.

This section describes how to service customer-replaceable units (CRUs) that require you to power off the server.

(i) Note

For the Oracle Database Appliance X7-2-HA, all of the CRUs on the storage shelf and the storage expansion shelf can be replaced while the power is on. See Oracle Database Appliance Storage Shelf Hot-Pluggable Components for storage shelf component replacement procedures.

(i) Note

The links in the following table take you to instructions outside of the Oracle Database Appliance library to the Oracle Server X7-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
CRU List	CRU List
Servicing DIMMs (CRU)	Servicing DIMMs (CRU)
Servicing PCIe Risers (CRU)	Servicing PCIe Risers (CRU)
Servicing PCIe Cards (CRU)	Servicing PCIe Cards (CRU)



Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
Servicing Internal M.2 Flash SSDs (CRU)	Servicing Internal M.2 Flash SSDs (CRU)
Note: For detailed instructions on replacing an M.2 Flash SSD boot drive and returning it to service, go to https://support.oracle.com/ and do a search on Doc ID 2403097.1.	Note: For detailed instructions on replacing an M.2 Flash SSD boot drive and returning it to service, go to https://support.oracle.com/ and do a search on Doc ID 2403097.1.
Servicing Internal USB Flash Drives (CRU)	Servicing Internal USB Flash Drives (CRU)
Servicing the Battery (CRU)	Servicing the Battery (CRU)

Servicing Oracle Database Appliance X6-2 Series CRUs

Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X6 series system.

This section describes how to service customer-replaceable components that require server power off for an Oracle Database X6-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing CRUs That Require System Power Off.</u>

(i) Note

When adding DIMMs to the system, refer to the "Optional Component Installation" section in the *Owner's Guide* for supported configurations.

This section describes how to service customer-replaceable units (CRUs) that require you to power off the server.

Note

For the Oracle Database Appliance X6-2-HA, all of the CRUs on the storage shelf and the storage expansion shelf can be replaced while the power is on. See <u>Oracle Database Appliance Storage Shelf Hot-Pluggable Components</u> for storage shelf component replacement procedures.

Note

The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X6-2 and Oracle Server X6-2L (including Storage Server X6-2 Extreme Flash version) documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
CRU List	CRU List	CRU List
Servicing DIMMs (CRU)	Servicing DIMMs (CRU)	Servicing DIMMs (CRU)



Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
Servicing PCIe Risers (CRU)	This system does not have PCIe risers.	Servicing PCIe Risers (CRU)
Servicing PCle Cards (CRU)	Servicing PCIe Cards (CRU)	Servicing PCle Cards (CRU)
Servicing the Oracle PCIe NVMe Switch Card (CRU)	Servicing the Oracle PCIe NVMe Switch Card (CRU)	This product does not have a PCIe NVMe Switch Card.
Note that for this product, the NVMe Switch Card is located in Slot 2.	Note that for this product, the NVMe Switch Cards are located in Slots 2, 5 and 6.	
Servicing Internal USB Flash Drives (CRU)	Servicing Internal USB Flash Drives (CRU)	Servicing Internal USB Flash Drives (CRU)
Servicing the Battery (CRU)	Servicing the Battery (CRU)	Servicing the Battery (CRU)

Servicing Oracle Database Appliance X3-2/X4-2/X5-2 CRUs

Provides instructions on how to perform CRU service tasks requiring system power off for Oracle Database Appliance X3-2/X4-2/X5-2 system.

This section describes how to service customer-replaceable components that require server power off for an Oracle Database X3-2/X4-2/X5-2 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing CRUs That Require System Power Off.</u>

Note

When adding DIMMs to the system, refer to the "Optional Component Installation" section in the *Owner's Guide* for supported configurations.

This section describes how to service customer-replaceable units (CRUs) that require you to power off the server.

(i) Note

All of the CRUs on the storage shelf and the storage expansion shelf can be replaced while the power is on. See <u>Oracle Database Appliance Storage Shelf Hot-Pluggable</u> Components for storage shelf component replacement procedures.

Note

The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Sun Server X3-2, Sun Server X4-2, and Oracle Server X5-2 documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.



Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
CRU Locations	CRU Locations	CRU List
Servicing DIMMs (CRU)	Servicing DIMMs (CRU)	Servicing DIMMs (CRU)
Servicing PCIe Risers (CRU)	Servicing PCIe Risers (CRU)	Servicing PCIe Risers (CRU)
Servicing PCIe Cards (CRU)	Servicing PCIe Cards (CRU)	Servicing PCIe Cards (CRU)
Servicing a DVD Drive (CRU)	Servicing a DVD Drive (CRU)	An optional DVD drive for this system is considered a FRU. See Servicing Oracle Database Appliance X3-2/X4-2/X5-2 FRUs.
This system does not include an internal USB flash drive.	Servicing the Internal USB Flash Drives (CRU)	Servicing the Internal USB Flash Drives (CRU)
	Note that a factory installed flash drive is reserved for future use.	Note that a factory installed flash drive is reserved for future use.
Servicing the Battery (CRU)	Servicing the Battery (CRU)	Servicing the Battery (CRU)

Servicing Oracle Database Appliance Version 1 CRUs

This section describes how to perform CRU service tasks requiring system power off for Oracle Database Appliance Version 1 system.

This section describes how to service customer-replaceable components that require server power off for an Oracle Database Version 1 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Servicing CRUs That Require System Power Off.

This section includes information on how to service the following Oracle Database Appliance Version 1 CRUs:

- Server Node CRU Component Locations
- Servicing Memory Modules (DIMMs) (CRU)
- Servicing PCIe Risers (CRU)
- Servicing PCIe Cards (CRU)
- Servicing the Server Node Battery (CRU)

Servicing FRUs

Perform tasks for servicing field-replaceable units (FRUs) for the Oracle Database Appliance that require you to power off the system and/or server node.

When servicing FRU components, the server node and/or system must be powered down and the AC power cords disconnected.

① Note

Only authorized Oracle Service personnel can service FRU components.

- <u>Servicing Oracle Database Appliance X8-2 Series FRUs</u>
 Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X8 series system.
- <u>Servicing Oracle Database Appliance X7-2 Series FRUs</u>
 Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X7 series system.
- <u>Servicing Oracle Database Appliance X6-2 Series FRUs</u>
 Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X6 series system.
- <u>Servicing Oracle Database Appliance X3-2/X4-2/X5-2 FRUs</u>
 Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X3-2/X4-2/X5-2 system.
- Managing System Faults on Oracle Database Appliance
 How to manage system faults when servicing Oracle Database Appliance.
- <u>Servicing Oracle Database Appliance Version 1 FRUs</u>
 This section describes how to perform FRU service tasks on an Oracle Database Appliance Version 1 system.

Servicing Oracle Database Appliance X8-2 Series FRUs

Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X8 series system.

This section describes how to service field-replaceable components that require server power off for an Oracle Database X8-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Servicing FRUs.

Only authorized Oracle Service personnel can service FRU components.





(i) Note

Most of the links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X8-2L documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
FRU List	FRU List
Servicing Processors (FRU)	Servicing Processors (FRU)
Servicing the Disk Backplane (FRU)	Servicing the Disk Backplane (FRU)
Servicing the Front Indicator Module (FRU)	Servicing the Front Indicator Module (FRU)
Servicing the Temperature Sensor (FRU)	Servicing the Temperature Sensor (FRU)
Servicing the Motherboard (FRU)	Servicing the Motherboard (FRU)
Servicing the NVMe Cables (FRU)	The server nodes for this product do not have NVMe devices.
Component Fault Management	Component Fault Management

Servicing Oracle Database Appliance X7-2 Series FRUs

Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X7 series system.

This section describes how to service field-replaceable components that require server power off for an Oracle Database X7-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Servicing FRUs.

Only authorized Oracle Service personnel can service FRU components.



(i) Note

Most of the links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X7-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
FRU List	FRU List
Servicing Processors (FRU)	Servicing Processors (FRU)
Servicing the Disk Backplane (FRU)	Servicing the Disk Backplane (FRU)
Servicing the Front Indicator Module (FRU)	Servicing the Front Indicator Module (FRU)
Servicing the Temperature Sensor (FRU)	Servicing the Temperature Sensor (FRU)
Servicing the Motherboard (FRU)	Servicing the Motherboard (FRU)
Servicing the NVMe Cables (FRU)	The server nodes for this product do not have NVMe devices.
Servicing the Power, FIM, Disk Backplane Data, and Temperature Sensor Cables (FRU)	Servicing the Power, FIM, Disk Backplane Data, and Temperature Sensor Cables (FRU)



Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
Component Fault Management	Component Fault Management

Servicing Oracle Database Appliance X6-2 Series FRUs

Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X6 series system.

This section describes how to service field-replaceable components that require server power off for an Oracle Database X6-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing FRUs</u>.

Only authorized Oracle Service personnel can service FRU components.



Most of the links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X6-2 and Oracle Server X6-2L (including Storage Server X6-2 Extreme Flash version) documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
FRU List	FRU List	FRU List
Servicing Processors (FRU)	Servicing Processors (FRU)	Servicing Processors (FRU)
Servicing the internal host bus adapter (HBA) (FRU)	Servicing the Internal SAS Host Bus Adapter (HBA) (FRU)	Servicing the internal host bus adapter (HBA) (FRU)
Servicing the Disk Backplane (FRU)	Servicing the Front Storage Drive Backplane (FRU)	Servicing the Disk Backplane (FRU)
	Removing the Rear Storage Drive Backplane (FRU)	
	Installing the Rear Storage Drive Backplane (FRU)	
	Note that for this product, there is a single SAS cable that connects directly from the PCIe HBA in slot 3 to the rear storage drive backplane. It does not route through the chassis mid-wall.	
Servicing the DVD Drive (FRU)	This product does not include a slot for a DVD drive.	Servicing the DVD Drive (FRU)
Servicing the Front Indicator Module (FRU)	Servicing the Front LED/USB Indicator Modules (FRU)	Servicing the Front Indicator Module (FRU)
Servicing the Motherboard (FRU)	Servicing the Motherboard (FRU)	Servicing the Motherboard (FRU)



Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
Servicing the SAS Cables (FRU)	Replace the Internal SAS HBA Cables	Servicing the SAS Cables (FRU)
	Note that for this product, there is a single SAS cable that connects directly from the PCIe HBA in slot 3 to the rear storage drive backplane. It does not route through the chassis mid-wall.	
Servicing the NVMe Cables (FRU)	Servicing the NVMe Cables (FRU)	This product does not have NVMe devices.
Note that the NVMe Switch Card is located in PCIe slot 2 for this product.	Note that the NVMe Switch Cards are located in PCle slots 2, 5 and 6 for this product.	
Servicing the Power, FIM, Disk Backplane Data, and DVD Cables (FRU)	For this product, cabling for Front Indicator Modules and the disk backplanes are included as part of the FRU servicing procedure for those components listed earlier in this table.	Servicing the Power, FIM, Disk Backplane Data, and DVD Cables (FRU)
Component Fault Management	Component Fault Management	Component Fault Management

Servicing the Internal SAS Host Bus Adapter (HBA) (FRU)
 Perform tasks for servicing a SAS HBA in an Oracle Database Appliance X6-2L system.

Servicing the Internal SAS Host Bus Adapter (HBA) (FRU)

Perform tasks for servicing a SAS HBA in an Oracle Database Appliance X6-2L system.

This section describes servicing the internal Oracle Storage 12 Gb/s SAS PCIe RAID HBA in an Oracle Database Appliance X6-2L system.

- Replace the Internal SAS HBA Card
 How to replace a SAS HBA in an Oracle Database Appliance X6-2L system.
- Replace the Internal SAS HBA Cables
 How to replace a SAS HBA cables in an Oracle Database Appliance X6-2L system.

Replace the Internal SAS HBA Card

How to replace a SAS HBA in an Oracle Database Appliance X6-2L system.

⚠ Caution

Ensure that all power is removed from the server before removing or installing PCIe cards. You must disconnect all power cables from the system before performing these procedures.


1. Prepare the server for service.

Refer to <u>Preparing Oracle Database Appliance X6-2 Series for Service</u> for additional details.




- a. Power off the server and disconnect the power cords from the power supplies.
- **b.** Extend the server to the maintenance position.
- c. Attach an antistatic wrist strap.
- d. Remove the server top cover.
- 2. Remove the super capacitor from the chassis.
 - a. Grasp both ends of the cable connector, press in on the release latch, and then unplug the connector [1] as shown in the following figure.

The HBA super capacitor is secured to the air baffle by a recloseable fastener, which allows it to be easily removed and replaced.



- **b.** To separate the HBA super capacitor from the air baffle, place your finger under the rear of the super capacitor and lift up [2] as shown in the previous figure.
- 3. Swivel the air baffle into the upright position to allow access to the super capacitor cable and the SAS HBA card.
- 4. Rotate the PCIe card locking mechanism, and then lift up on the PCIe HBA card to disengage it from the motherboard connectors [1] as shown in the following figure.






- 5. Disconnect the super capacitor cable and the SAS cables from the SAS HBA card [2] as shown in the previous figure.
- 6. Remove the SAS HBA card from the chassis.
- 7. Remove super capacitor cable from the chassis.

The super capacitor cable is routed along the left side of the chassis (when facing the front of the system).

- 8. Unpack the replacement Oracle Storage 12 Gb/s SAS PCIe RAID HBA card and super capacitor, and place them on an antistatic mat.
- 9. If it isn't already, swivel the air baffle into the upright position and install the super capacitor cable along the left side of the chassis and into its access hole in the air baffle.
 - Install the super capacitor cable along the left side of the chassis (when facing the front of the system). Thread the cable connector through the hole on the bottom of the air baffle to where the super capacitor will be installed. Check to ensure it does not interfere with the air baffle when it closes.
- 10. Connect the super capacitor cable to the SAS HBA card, and then reconnect the SAS cables that you unplugged during the removal procedure [1] as shown in the following figure.






11. Insert the SAS HBA card into PCIe slot 3, and rotate the PCIe locking mechanism to secure the PCIe HBA card in place [2] as shown in the previous figure.

(i) Note

PCIe slot 3 is the reserved slot for the Oracle Storage 12 Gb/s SAS PCIe RAID HBA card.

- 12. Install the super capacitor in the chassis.
 - a. Lower the air baffle to the installed position.
 - **b.** Align the recloseable fastener on the super capacitor with the recloseable fastener on the air baffle and press down [1] as shown in the following figure.





- **c.** Connect the super capacitor cable to the super capacitor [2] as shown in the previous figure.
- **13.** Return the server to operation.
 - a. Install the server top cover.
 - **b.** Return the server to the normal rack position.
 - c. Reconnect the power cords to the power supplies and power on the server.
- 14. Use Oracle ILOM to clear any server PCIe card faults.

You can use the Oracle ILOM web interface or the command-line interface (CLI) to manually clear faults. For information on how to use the Oracle ILOM web interface or the CLI to clear server faults, refer to the Oracle Integrated Lights Out Manager (ILOM) Documentation Library at http://www.oracle.com/goto/ilom/docs.

Replace the Internal SAS HBA Cables

How to replace a SAS HBA cables in an Oracle Database Appliance X6-2L system.

These instructions describe replacing SAS cables for the factory installed Oracle Storage 12 Gb/s SAS PCIe RAID HBA in an Oracle Database Appliance X6-2L system.




∴ Caution

The system supplies power to the cables even when the server is powered off. To avoid personal injury or damage to the server, you must disconnect power cords before servicing the cables.

1. Prepare the server for service.


Refer to <u>Preparing Oracle Database Appliance X6-2 Series for Service</u> for additional details.

- a. Power off the server and disconnect the power cords from the power supplies.
- **b.** Extend the server to the maintenance position.
- c. Attach an antistatic wrist strap.
- d. Remove the server top cover.
- 2. Swivel the air baffle into the upright position to allow access to the SAS storage drive cables.
- 3. Disconnect the SAS cable from the rear disk drive backplane [1] and from the card [2] as shown in the following figure.



4. Install the replacement SAS cable to the rear disk drive backplane [1] and the SAS card [2] as shown in the following figure.





- 5. Lower the air baffle to the installed position.
- Return the server to operation.
 - a. Install the server top cover.
 - **b.** Return the server to the normal rack position.
 - c. Reconnect the power cords to the power supplies and power on the server.

Servicing Oracle Database Appliance X3-2/X4-2/X5-2 FRUs

Provides instructions on how to perform FRU service tasks on an Oracle Database Appliance X3-2/X4-2/X5-2 system.

This section describes how to service field-replaceable components that require server power off for an Oracle Database X3-2/X4-2/X5-2 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Servicing FRUs</u>.

Only authorized Oracle Service personnel can service FRU components.



Most of the links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Sun Server X3-2, Sun Server X4-2, and Oracle Server X5-2 documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
FRU Locations	FRU Locations	FRU List
Servicing Processors (FRU)	Servicing Processors (FRU)	Servicing Processors (FRU)
Servicing the Disk Backplane (FRU)	Servicing the Disk Backplane (FRU)	Servicing the Disk Backplane (FRU)



Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
An optional DVD drive for this system is considered a CRU. See Servicing Oracle Database Appliance X3-2/X4-2/X5-2 CRUs.	An optional DVD drive for this system is considered a CRU. See Servicing Oracle Database Appliance X3-2/X4-2/X5-2 CRUs.	Servicing a DVD Drive (FRU)
Servicing the Front Indicator Module (FRU)	Servicing the Front Indicator Module (FRU)	Servicing the Front Indicator Module (FRU)
Servicing the Motherboard (FRU)	Servicing the Motherboard (FRU)	Servicing the Motherboard (FRU)
Servicing the SAS Cables (FRU)	Servicing the SAS Cables (FRU)	Servicing the SAS Cables (FRU)
Component Fault Management	Component Fault Management	Component Fault Management

Managing System Faults on Oracle Database Appliance

How to manage system faults when servicing Oracle Database Appliance.

This section describes how to manage system faults when servicing Oracle Database Appliance X3-2/X4-2/X5-2 and Oracle Database Appliance X6-2/X7-2/X8-2 series systems. If you have Oracle Database Appliance Version 1, go to Servicing Oracle Database Appliance Version 1 FRUs.

Component Fault Management
 Perform component fault management on Oracle Database Appliance X3-2/X4-2/X5-2, X6-2, X7-2, X8-2 series systems.

Component Fault Management

Perform component fault management on Oracle Database Appliance X3-2/X4-2/X5-2, X6-2, X7-2, X8-2 series systems.

Typically, when a faulty component is replaced and the server is returned to service, the fault state of the component in Oracle ILOM is automatically cleared and the component Service Required indicator will turn off. This is the default behavior for all components that have an embedded FRU serial number in the component firmware.

For replaced components that do not have an embedded FRU serial number, or do not automatically clear their fault state after the component has been repaired and the server is returned to service, you can use Oracle ILOM command line interface to manually clear the fault state. Use the following syntax:

```
set /path_to_target clear_fault_action=true
```

Where path to target is the path to the component (such as a DIMM) that had the fault.

In addition, the Fault Management shell can also be used. Use of the Fault Management shell is reserved for Oracle Service. For more information on component fault management:

- For systems with Oracle ILOM 5.0, see <u>Using fmadm to Administer Active Hardware Faults</u> in the Oracle Integrated Lights Out Manager Documentation Library.
- For systems with Oracle ILOM 4.0, see <u>Using fmadm to Administer Active Hardware Faults</u> in the Oracle Integrated Lights Out Manager Documentation Library.
- For systems with Oracle ILOM 3.2, see <u>Using fmadm to Administer Active Hardware Faults</u> in the Oracle Integrated Lights Out Manager Documentation Library.



For systems with Oracle ILOM 3.1, see Using fmadm to Administer Active Hardware Faults in the Oracle Integrated Lights Out Manager Documentation Library.

Servicing Oracle Database Appliance Version 1 FRUs

This section describes how to perform FRU service tasks on an Oracle Database Appliance Version 1 system.

This section describes how to service field-replaceable components that require server power off for an Oracle Database Version 1 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Servicing FRUs.



(i) Note

Only authorized Oracle Service personnel can service FRU components.

This section includes information on how to service the following Oracle Database Appliance Version 1 FRUs:

- Removing and Installing the Air Duct (FRU)
- Servicing Processors (CPUs) (FRU)
- Servicing the Boot Disk Backplane (FRU)
- Servicing the Power Distribution Board (FRU)
- Servicing the Disk Midplane Module (FRU)
- Servicing the Disk Midplane Module HDD Cable (FRU)
- Servicing the Front Indicator Panels (FRU)
- **Servicing Server Node Cables**
- Servicing the Motherboard Assembly (FRU)

Returning Oracle Database Appliance to Operation

Perform tasks to return the Oracle Database Appliance to operation after service.

- Returning Oracle Database Appliance X8-2 Series to Operation
 Provides instructions on how to return an Oracle Database Appliance X8 series system to operation after service.
- Returning Oracle Database Appliance X7-2 Series to Operation
 Provides instructions on how to return an Oracle Database Appliance X7 series system to operation after service.
- Returning Oracle Database Appliance X6-2 Series to Operation Provides instructions on how to return an Oracle Database Appliance X6 series system to operation after service.
- Returning Oracle Database Appliance X3-2/X4-2/X5-2 to Operation
 Provides instructions on how to return an Oracle Database Appliance X3-2/X4-2/X5-2 system to operation after service.
- Powering On an Oracle Database Appliance That Includes a Storage Shelf
 Perform tasks required to power on an Oracle Database Appliance that includes at least one storage shelf (DE2-24P, DE2-24C, or DE3-24C).
- Returning Oracle Database Appliance Version 1 to Operation
 This section describes how to return an Oracle Database Appliance Version 1 system to operation after service.

Returning Oracle Database Appliance X8-2 Series to Operation

Provides instructions on how to return an Oracle Database Appliance X8 series system to operation after service.

This section describes how to return the system to operation after servicing an Oracle Database X8-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Returning Oracle Database Appliance to Operation</u>.



Most of the links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X8-2L documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
Install the Top Cover	Install the Top Cover
Remove Antistatic Measures	Remove Antistatic Measures
Reinstall the Server Chassis Into the Rack	Reinstall the Server Chassis Into the Rack



Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
Return the Server to the Normal Rack Position	Return the Server to the Normal Rack Position
Reconnect Data Cables and Power Cords	Reconnect Data Cables and Power Cords
Powering On Oracle Database Appliance X8-2S/ X8-2M	Powering On an Oracle Database Appliance That Includes a Storage Shelf

Returning Oracle Database Appliance X7-2 Series to Operation

Provides instructions on how to return an Oracle Database Appliance X7 series system to operation after service.

This section describes how to return the system to operation after servicing an Oracle Database X7-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Returning Oracle Database Appliance to Operation.



(i) Note

Most of the links in the following table take you to instructions outside of the Oracle Database Appliance library to the Oracle Server X7-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
Install the Top Cover	Install the Top Cover
Remove Antistatic Measures	Remove Antistatic Measures
Reinstall the Server Chassis Into the Rack	Reinstall the Server Chassis Into the Rack
Return the Server to the Normal Rack Position	Return the Server to the Normal Rack Position
Reconnect Data Cables and Power Cords	Reconnect Data Cables and Power Cords
Powering On Oracle Database Appliance X7-2S/ X7-2M	Powering On an Oracle Database Appliance That Includes a Storage Shelf

Returning Oracle Database Appliance X6-2 Series to Operation

Provides instructions on how to return an Oracle Database Appliance X6 series system to operation after service.

This section describes how to return the system to operation after servicing an Oracle Database X6-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Returning Oracle Database Appliance to Operation.



(i) Note

Most of the links in the following table take you to instructions outside of the Oracle Database Appliance library to the Oracle Server X6-2 and Oracle Server X6-2L (including Storage Server X6-2 Extreme Flash version) documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.



Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
Install the Top Cover	Install the Top Cover Install the Fan Assembly Door	Install the Top Cover
Remove Antistatic Measures	Remove Antistatic Measures	Remove Antistatic Measures
Reinstall the Server Chassis Into the Rack	Reinstall the Server Chassis Into the Rack	Reinstall the Server Chassis Into the Rack
Return the Server to the Normal Rack Position	Return the Server to the Normal Rack Position	Return the Server to the Normal Rack Position
Reconnect Data Cables and Power Cords	Reconnect Data Cables and Power Cords	Reconnect Data Cables and Power Cords
Powering On Oracle Database Appliance X6-2S/X6-2M	Powering On Oracle Database Appliance X6-2L	Powering On an Oracle Database Appliance That Includes a Storage Shelf

Returning Oracle Database Appliance X3-2/X4-2/X5-2 to Operation

Provides instructions on how to return an Oracle Database Appliance X3-2/X4-2/X5-2 system to operation after service.

This section describes how to return the system to operation after servicing an Oracle Database X3-2/X4-2/X5-2 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Returning Oracle Database Appliance to Operation.



(i) Note

Most of the links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Sun Server X3-2, Sun Server X4-2 and Oracle Server X5-2 documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
Install the Top Cover	Install the Top Cover	Install the Top Cover
Remove Antistatic Measures	Remove Antistatic Measures	Remove Antistatic Measures
Reinstall the Server Chassis Into the Rack	Reinstall the Server Chassis Into the Rack	Reinstall the Server Chassis Into the Rack
Return the Server to the Normal Rack Position	Return the Server to the Normal Rack Position	Return the Server to the Normal Rack Position
Reconnect Data Cables and Power Cords	Reconnect Data Cables and Power Cords	Reconnect Data Cables and Power Cords
Powering On an Oracle Database Appliance That Includes a Storage Shelf	Powering On an Oracle Database Appliance That Includes a Storage Shelf	Powering On an Oracle Database Appliance That Includes a Storage Shelf



Powering On an Oracle Database Appliance That Includes a Storage Shelf

Perform tasks required to power on an Oracle Database Appliance that includes at least one storage shelf (DE2-24P, DE2-24C, or DE3-24C).



(i) Note

If you have an Oracle Database Appliance X8-2S/X8-2M, X7-2S/X7-2M, X6-2S/ X6-2M/X6-2L or Oracle Database Appliance Version 1, your system does not support a storage shelf and you should skip this section.

When powering on the system, each server node is powered on separately.

- If you powered off and disconnected the power cords from a storage shelf (and storage expansion shelf if one is present), reconnect the power cords now.
- 2. Power on the storage shelf (and storage expansion shelf if one is present) by switching the power supply On/Off button on each power supply to the On position.

The disks begin to initialize and the power supply LEDs light green. This can take several minutes.



(i) Note

Do not power on the server nodes until the disks on the storage shelf and storage expansion shelf have initialized.

- If you powered off a server node, reconnect any unplugged power cords.
- Power on a server node on using one of the following methods:
 - Press the recessed Power button on the server node front panel.
 - Log in to the Oracle ILOM web interface, click Host Management > Power Control, and select Power On from the Select Action list box.
 - Log in to the Oracle ILOM command-line interface (CLI), and type the following command at the Oracle ILOM CLI prompt.

```
-> start /SYS
```

When the server is powered on and the power-on self-test (POST) code checkpoint tests have completed, the green Power/OK status indicator on the server node front panel lights and remains lit.



(i) Note

If you powered off both server nodes prior to servicing, repeat steps 3 and 4 to power on the second server node.



Refer to other Oracle Database Appliance documentation for any instructions or commands required to return the appliance to service.

Refer to the appropriate *Deployment and User's Guide* for the Oracle Database Appliance X6-2/X7-2/X8-2 series and Oracle Database Appliance X4-2/X5-2, or the *Administration and Reference Guide* for Oracle Database Appliance X3-2 or Oracle Database Appliance Version 1.

Returning Oracle Database Appliance Version 1 to Operation

This section describes how to return an Oracle Database Appliance Version 1 system to operation after service.

This section describes how to return the system to operation after servicing an Oracle Database Version 1 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Returning Oracle Database Appliance to Operation.

- Installing the Server Node Top Cover
- Installing a Server Node Into the System Chassis
- Powering On Oracle Database Appliance Version 1

Server Node Diagnostic Tools and Resetting the Service Processor

Learn about server node diagnostic tools and how to reset the SP.

Diagnostic tools are used to troubleshoot or monitor the performance of your system. Data gathered by the service processor (SP) of each server node helps in monitoring and identifying problems with server node hardware. If the SP hangs or becomes inaccessible, it might need to be reset.

(i) Note

Most of the tools and procedures described in this chapter are reserved for Oracle Service personnel and should not be run on the appliance unless directed to do so by Oracle Service.

Server Node Diagnostic Tools

See a listing of the various Oracle Database Appliance diagnostic tools and where to obtain more information about them.

Resetting the Service Processor

How to reset the service processor (SP) of a server node of an Oracle Database Appliance.

Server Node Diagnostic Tools

See a listing of the various Oracle Database Appliance diagnostic tools and where to obtain more information about them.

Oracle provides a wide selection of diagnostic tools for use with your server node. These tools include lights out management of the system, service processor recovery, power-on self-test (POST), UEFI or Pc-Check diagnostics, as well as hardware LEDs that indicate the status of system components.

Note

The links in the following table take you to instructions **outside** of the Oracle Database Appliance library. Use your browser's Back button to return to the Oracle Database Appliance library.



Diagnostic Tool	What It Does	Where to Find Information
Oracle Integrated Lights Out Manager (ILOM)	Monitors server status, environmental conditions, generates alerts (SNMP traps, IPMI PETs, remote syslog), performs fault isolation, provides remote console access.	Refer to the appropriate Oracle Integrated Lights Out Manager (ILOM) Documentation Library based on your appliance's supported version of Oraclel ILOM.
	Note that all patching/updating of Oracle Database Appliance is done with the regular Oracle Database Appliance Patch Set Bundle. This includes BIOS and SP firmware. This ensures that all software and firmware component versions are supported to work together. Patches are available through My Oracle Support.	Oracle Integrated Lights Out (ILOM) Documentation Library
System indicators and LEDs	Provides at-a-glance status of the system and its components.	Overview of System Status Indicators and LEDs You can also use Oracle ILOM to check server node indicator status. Refer to the appropriate Oracle Integrated Lights Out Manager (ILOM) Documentation Library based on your appliance's supported version of Oracle ILOM. Oracle Integrated Lights Out (ILOM) Documentation Library
Power-On Self-Test (POST)	Tests core components of system: CPUs, memory, and motherboard I/O bridge integrated circuits.	For Oracle Database Appliance X3-2/ X4-2/X5-2 and X6-2/X7-2/X8-2 series, refer to the appropriate <i>Oracle x86</i> Servers Diagnostics Guide based on your appliance's supported version of Oracle ILOM. Oracle x86 Servers Administration, Diagnostics, and Applications Library For the Oracle Database Appliance Version 1, see: Default BIOS Power-On Self-Test (POST) Events BIOS POST F1 and F2 Errors
UEFI Diagnostics (for Oracle Database Appliance X4-2/ X5-2 and X6-2/ X7-2/X8-2 series)	UEFI-based utility that tests and detect problems on all processor, memory, disk drives, and network ports. It is used on newer Oracle systems.	Refer to the appropriate <i>Oracle x86</i> Servers Diagnostics Guide based on your appliance's supported version of Oracle ILOM. Oracle x86 Servers Administration, Diagnostics, and Applications Library
Pc-Check (for Oracle Database Appliance X3-2 and Oracle Database Appliance Version	DOS-based utility that tests all motherboard components (CPU, memory, and I/O), ports, and slots.	Refer to the appropriate <i>Oracle x86</i> Servers Diagnostics Guide based on your appliance's supported version of Oracle ILOM.
1)		Oracle x86 Servers Administration, Diagnostics, and Applications Library



Resetting the Service Processor

How to reset the service processor (SP) of a server node of an Oracle Database Appliance.

There are times when you might need to reset the service processor (such as after a firmware update). You can reset the server node SP using Oracle ILOM without affecting the host OS. However, this action disconnects your current Oracle ILOM session and will not allow any new sessions to be initiated until the reset has completed.

To reset the SP using the Oracle ILOM web interface or the CLI, see Oracle Integrated Lights Out Manager (ILOM) Documentation Library:

https://www.oracle.com/goto/ilom/docs



(i) Note

Be sure to refer to the documentation that applies to the version of Oracle ILOM supported with your appliance. See the "Supported Components and Capabilities" section in the *Oracle Database Appliance Owner's Guide*.

If you are unable to reset the SP using the Oracle ILOM web interface or the CLI (for example, if the SP hangs), then use the SP reset button as described in the following tables.



(i) Note

The links in the following tables take you to instructions **outside** of the Oracle Database Appliance library. Use your browser's Back button to return to the Oracle Database Appliance library.

For Oracle Database Appliance X8-2 series:

Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
Reset the Service Processor From the Server Back Panel	Reset the Service Processor From the Server Back Panel

For Oracle Database Appliance X7-2 series:

Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
Reset the Service Processor From the Server Back Panel	Reset the Service Processor From the Server Back Panel

For Oracle Database Appliance X6-2 series:

Oracle Database Appliance	Oracle Database Appliance	Oracle Database Appliance
X6-2S/X6-2M	X6-2L	X6-2-HA
Reset the Service Processor	Reset the Service Processor	Reset the Service Processor
From the Server Back Panel	From the Server Back Panel	From the Server Back Panel



For Oracle Database Appliance X3-2X4-2/X5-2 and Oracle Database Appliance Version 1:

	acle Database pliance Version 1	Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
1.	Find the SP reset button on the rear of the system, next to the power supply and the Locate button/LED.	Reset the Service Processor From the Server Back Panel	Reset the Service Processor From the Server Back Panel	Reset the Service Processor From the Server Back Panel
	See the "Oracle Database Appliance Version 1 Back Panel" section in the Oracle Database Appliance Owner's Guide.			
2.	Insert a small stylus or non-conductive object into the opening and press the recessed push button switch. The SP resets.			

Server Node Basic Input/Output System (BIOS)

Learn about the server node BIOS Setup Utility.

The Basic Input/Output System (BIOS) has a Setup Utility stored in the BIOS flash memory. The Setup Utility reports system information and can be used to configure the BIOS settings. The configurable data is provided with context-sensitive help and is stored in the system's battery-backed CMOS RAM. If the configuration stored in the CMOS RAM is invalid, the BIOS settings return to their default optimal values.

Note

The BIOS menus shown in this chapter are examples. The BIOS version numbers, menu information, and menu selections are subject to change over the life of the product. You should not change the factory settings unless prompted to do so by Oracle Service personnel.

- Oracle Database Appliance X8-2 Series BIOS Utility
 Learn about the BIOS Setup Utility for an Oracle Database Appliance X8-2 series system.
- Oracle Database Appliance X7-2 Series BIOS Utility
 Learn about the BIOS Setup Utility for an Oracle Database Appliance X7-2 series system.
- Oracle Database Appliance X6-2 Series BIOS Utility
 Learn about the BIOS Setup Utility for an Oracle Database Appliance X6-2 series system.
- Oracle Database Appliance X3-2/X4-2/X5-2 BIOS Utility
 Learn about the BIOS Setup Utility for an Oracle Database Appliance X3-2/X4-2/X5-2 system.
- Oracle Database Appliance Version 1 BIOS Utility
 This section describes BIOS Setup Utility for an Oracle Database Appliance Version 1 system.

Oracle Database Appliance X8-2 Series BIOS Utility

Learn about the BIOS Setup Utility for an Oracle Database Appliance X8-2 series system.

This section describes the BIOS Setup Utility of an Oracle Database X8-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Server Node Basic Input/Output System (BIOS)</u>.

All settings are set to the optimal defaults at startup.



△ Caution

You should not configure system BIOS settings. Oracle Database Appliance patch software will do this for you. The only time you might need to configure BIOS settings would be if requested to do so by Oracle Service.

The following topics are included:

- <u>Setting Up BIOS Configuration Parameters</u>
 Learn about the BIOS configuration parameters for Oracle Database Appliance X8-2 series.
- BIOS Setup Utility Menu Options
 Learn about the BIOS utility menu options for Oracle Database Appliance X8-2 series.

Setting Up BIOS Configuration Parameters

Learn about the BIOS configuration parameters for Oracle Database Appliance X8-2 series.



The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X8-2L documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
Managing the BIOS Configuration	Managing the BIOS Configuration
Accessing the BIOS Setup Utility	Accessing the BIOS Setup Utility
Using UEFI BIOS	Using UEFI BIOS
Common BIOS Setup Utility Tasks	Common BIOS Setup Utility Tasks

BIOS Setup Utility Menu Options

Learn about the BIOS utility menu options for Oracle Database Appliance X8-2 series.



The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Oracle Server X8-2L documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA
BIOS Main Menu Selections	BIOS Main Menu Selections
BIOS Advanced Menu Selections	BIOS Advanced Menu Selections
BIOS IO Menu Selections	BIOS IO Menu Selections



Oracle Database Appliance X8-2S/X8-2M	Oracle Database Appliance X8-2-HA	
BIOS Boot Menu Selections	BIOS Boot Menu Selections	
BIOS Save and Exit Menu Selections	BIOS Save and Exit Menu Selections	

Oracle Database Appliance X7-2 Series BIOS Utility

Learn about the BIOS Setup Utility for an Oracle Database Appliance X7-2 series system.

This section describes the BIOS Setup Utility of an Oracle Database X7-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Server Node Basic Input/Output System (BIOS).

All settings are set to the optimal defaults at startup.



Caution

You should not configure system BIOS settings. Oracle Database Appliance patch software will do this for you. The only time you might need to configure BIOS settings would be if requested to do so by Oracle Service.

The following topics are included:

- **Setting Up BIOS Configuration Parameters** Learn about the BIOS configuration parameters for Oracle Database Appliance X7-2 series.
- **BIOS Setup Utility Menu Options** Learn about the BIOS utility menu options for Oracle Database Appliance X7-2 series.

Setting Up BIOS Configuration Parameters

Learn about the BIOS configuration parameters for Oracle Database Appliance X7-2 series.



(i) Note

The links in the following table take you to instructions outside of the Oracle Database Appliance library to the Oracle Server X7-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
Managing the BIOS Configuration	Managing the BIOS Configuration
Accessing the BIOS Setup Utility	Accessing the BIOS Setup Utility
Using UEFI BIOS	Using UEFI BIOS
Common BIOS Setup Utility Tasks	Common BIOS Setup Utility Tasks



BIOS Setup Utility Menu Options

Learn about the BIOS utility menu options for Oracle Database Appliance X7-2 series.



(i) Note

The links in the following table take you to instructions outside of the Oracle Database Appliance library to the Oracle Server X7-2 documentation library. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X7-2S/X7-2M	Oracle Database Appliance X7-2-HA
BIOS Main Menu Selections	BIOS Main Menu Selections
BIOS Advanced Menu Selections	BIOS Advanced Menu Selections
BIOS IO Menu Selections	BIOS IO Menu Selections
BIOS Boot Menu Selections	BIOS Boot Menu Selections
BIOS Save and Exit Menu Selections	BIOS Save and Exit Menu Selections

Oracle Database Appliance X6-2 Series BIOS Utility

Learn about the BIOS Setup Utility for an Oracle Database Appliance X6-2 series system.

This section describes the BIOS Setup Utility of an Oracle Database X6-2 series system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Server Node Basic Input/Output System (BIOS).

All settings are set to the optimal defaults at startup.



You should not configure system BIOS settings. Oracle Database Appliance patch software will do this for you. The only time you might need to configure BIOS settings would be if requested to do so by Oracle Service.

The following topics are included:

- **Setting Up BIOS Configuration Parameters** Learn about the BIOS configuration parameters for Oracle Database Appliance X6-2 series.
- **BIOS Setup Utility Menu Options** Learn about the BIOS utility menu options for Oracle Database Appliance X6-2 series.

Setting Up BIOS Configuration Parameters

Learn about the BIOS configuration parameters for Oracle Database Appliance X6-2 series.





(i) Note

The links in the following table take you to instructions outside of the Oracle Database Appliance library to the Oracle Server X6-2 and Oracle Server X6-2L documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
Managing the BIOS Configuration	Managing the BIOS Configuration	Managing the BIOS Configuration
Accessing the BIOS Setup Utility	Accessing the BIOS Setup Utility	Accessing the BIOS Setup Utility
Using Legacy or UEFI BIOS	Using Legacy or UEFI BIOS	Using Legacy or UEFI BIOS
Using BIOS for Resource Allocation	Using BIOS for Resource Allocation	<u>Using BIOS for Resource</u> <u>Allocation</u>
Common BIOS Setup Utility Tasks	Common BIOS Setup Utility Tasks	Common BIOS Setup Utility Tasks

BIOS Setup Utility Menu Options

Learn about the BIOS utility menu options for Oracle Database Appliance X6-2 series.



(i) Note

The links in the following table take you to instructions outside of the Oracle Database Appliance library to the Oracle Server X6-2 and Oracle Server X6-2L documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X6-2S/X6-2M	Oracle Database Appliance X6-2L	Oracle Database Appliance X6-2-HA
BIOS Main Menu Selections	BIOS Main Menu Selections	BIOS Main Menu Selections
BIOS Advanced Menu Selections	BIOS Advanced Menu Selections	BIOS Advanced Menu Selections
BIOS IO Menu Selections	BIOS IO Menu Selections	BIOS IO Menu Selections
BIOS Boot Menu Selections	BIOS Boot Menu Selections	BIOS Boot Menu Selections
BIOS Save and Exit Menu Selections	BIOS Save and Exit Menu Selections	BIOS Save and Exit Menu Selections

Oracle Database Appliance X3-2/X4-2/X5-2 BIOS Utility

Learn about the BIOS Setup Utility for an Oracle Database Appliance X3-2/X4-2/X5-2 system.

This section describes the BIOS Setup Utility of an Oracle Database X3-2/X4-2/X5-2 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in Server Node Basic Input/Output System (BIOS).

All settings are set to the optimal defaults at startup.



You should not configure system BIOS settings. Oracle Database Appliance patch software will do this for you. The only time you might need to configure BIOS settings would be if requested to do so by Oracle Service.

The following topics are included:

- Setting Up BIOS Configuration Parameters Learn about the BIOS configuration parameters for Oracle Database Appliance X3-2/X4-2/ X5-2.
- **BIOS Setup Utility Menu Options** Learn about the BIOS utility menu options for Oracle Database Appliance X3-2/X4-2/X5-2.

Setting Up BIOS Configuration Parameters

Learn about the BIOS configuration parameters for Oracle Database Appliance X3-2/X4-2/ X5-2.



(i) Note

The links in the following table take you to instructions **outside** of the Oracle Database Appliance library to the Sun Server X3-2, Sun Server X4-2, and Oracle Server X5-2 documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.

Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
Managing the BIOS Configuration	Managing the BIOS Configuration	Managing the BIOS Configuration
Accessing the BIOS Setup Utility	Accessing the BIOS Setup Utility	Accessing the BIOS Setup Utility
Using Legacy or UEFI BIOS	Using Legacy or UEFI BIOS	Using Legacy or UEFI BIOS
Using BIOS for Resource Allocation	Using BIOS for Resource Allocation	<u>Using BIOS for Resource</u> <u>Allocation</u>
Common BIOS Setup Utility Tasks	Common BIOS Setup Utility Tasks	Common BIOS Setup Utility Tasks

BIOS Setup Utility Menu Options

Learn about the BIOS utility menu options for Oracle Database Appliance X3-2/X4-2/X5-2.



Note

The links in the following table take you to instructions outside of the Oracle Database Appliance library to the Sun Server X3-2, Sun Server X4-2, and Oracle Server X5-2 documentation libraries. Use your browser's Back button to return to the Oracle Database Appliance library.



Oracle Database Appliance X3-2	Oracle Database Appliance X4-2	Oracle Database Appliance X5-2
BIOS Main Menu Selections	BIOS Main Menu Selections	BIOS Main Menu Selections
BIOS Advanced Menu Selections	BIOS Advanced Menu Selections	BIOS Advanced Menu Selections
BIOS IO Menu Selections	BIOS IO Menu Selections	BIOS IO Menu Selections
BIOS Boot Menu Selections	BIOS Boot Menu Selections	BIOS Boot Menu Selections
<u>UEFI Driver Control Menu</u> <u>Selections</u>	UEFI Driver Control Menu Selections	See the Advanced Menu for driver settings.
BIOS Save and Exit Menu Selections	BIOS Save and Exit Menu Selections	BIOS Save and Exit Menu Selections

Oracle Database Appliance Version 1 BIOS Utility

This section describes BIOS Setup Utility for an Oracle Database Appliance Version 1 system.

This section describes the BIOS Setup Utility of an Oracle Database Version 1 system. If you have some other Oracle Database Appliance model, select the appropriate link listed in <u>Server Node Basic Input/Output System (BIOS)</u>.

All settings are set to the optimal defaults at startup.



You should not configure system BIOS settings. Oracle Database Appliance patch software will do this for you. The only time you might need to configure BIOS settings would be if requested to do so by Oracle Service.

The following topics are included:

- BIOS Booting and Setup
- Configuring Support for TPM
- Configuring SP LAN Settings
- Configuring Option ROM Settings in BIOS
- BIOS Setup Utility Hot Keys
- Accessing the BIOS Setup Utility Menus
- BIOS Setup Utility Screens



Servicing the Oracle Database Appliance Version 1

Perform tasks for servicing an Oracle Database Appliance Version 1 (also referred to as "original version" or "V1").

(i) Note

Information in this appendix ONLY applies to the Oracle Database Appliance Version 1 (released in 2011). It does NOT apply to other models of Oracle Database Appliance released afterwards. Refer to the preceding chapters in this document for information on servicing other Oracle Database Appliance models.

- <u>Preparing Oracle Database Appliance Version 1 for Service</u>
 This section describes how to prepare the Oracle Database Appliance Version 1 for service.
- <u>Servicing Hot-Pluggable Components</u>
 Perform tasks to service hot plug components in an Oracle Database Appliance Version 1 system.
- Servicing CRUs That Require Server Node Power Off
 Perform tasks for servicing customer-replaceable units (CRUs) for the Oracle Database Appliance Version 1 that require you to power off the server node.
- <u>Servicing FRUs</u>
 Perform tasks for servicing field-replaceable units (FRUs) for the Oracle Database
 Appliance Version 1 that require you to power off the system and/or server node.
- Returning the Appliance to Operation
 Perform tasks for returning the Oracle Database Appliance Version 1 to operation after servicing.
- Server Node Basic Input/Output System (BIOS)
 Learn about the Oracle Database Appliance Version 1 BIOS.

Preparing Oracle Database Appliance Version 1 for Service

This section describes how to prepare the Oracle Database Appliance Version 1 for service.

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Component Replacement Policy (CRUs and FRUs)
 Listing of CRUs and FRUs for Oracle Database Appliance Version 1.
- <u>Safety Information</u>
 Learn about important safety information before servicing the Oracle Database Appliance Version 1.



Required Tools

Learn about the tools required to service the Oracle Database Appliance Version 1.

Obtaining the Chassis Serial Number

How to obtain the serial number for the Oracle Database Appliance Version 1.

Shutting Down a Server Node and Powering Off the System

This section describes how to shut down the Oracle Database Appliance Version 1 for servicing.

<u>Performing Electrostatic Discharge and Antistatic Prevention Measures</u>
 Learn about ESD and antistatic protection when servicing an Oracle Database Appliance

Version 1.

Removing Server Nodes From the System Chassis

Learn about removing an Oracle Database Appliance Version 1 server node from the chassis.

Removing the Server Node Top Cover

Learn about removing the server node top cover for an Oracle Database Appliance Version 1.

Removing the Middle Section of the System Top Cover

Learn about removing the middle section of an Oracle Database Appliance Version 1 server node top cover.

Component Replacement Policy (CRUs and FRUs)

Listing of CRUs and FRUs for Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The replaceable components in your Oracle Database Appliance Version 1 are designated as either field-replaceable units (FRUs) or customer-replaceable units (CRUs). Some can be replaced with the power on, some require the powering off of a server node, and some require the powering off of the entire system chassis.

- A part designated as a FRU must be replaced by Oracle-qualified service technician.
- A part designated as a CRU can be replaced by a person who is not an Oracle-qualified service technician.

The following table lists replaceable components, their service designation (CRU or FRU), and the system power policy related to servicing the component.

Component	Policy
Storage drives and boot drives (CRU)	Hot-pluggable – Can be removed and replaced when the system is powered on.
Fan modules (CRU)	Hot-pluggable – Can be removed and replaced when the system is powered on.



Component	Policy	
Power supplies (CRU)	Hot-pluggable – Can be removed and replaced when the system is powered on.	
Air duct (FRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
DIMMs (CRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
PCIe risers (CRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
PCIe cards (CRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
Boot disk backplane (FRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
Server node battery (CRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
Processors (CPUs) (FRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
Motherboard (FRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
Server node internal cables (FRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
Power distribution board (FRU)	Cold service, system chassis – Servicing this component requires that the power be completely removed from the system chassis (both server nodes powered off).	
Disk midplane module (FRU)	Cold service, system chassis – Servicing this component requires that the power be completely removed from the system chassis (both server nodes powered off).	
Disk midplane module HDD cable (FRU)	Cold service, server node – Can only be removed and replaced when the server node is powered off. The other server node and the system chassis can remain on.	
Front indicator panels (FRU)	Cold service, system chassis – Servicing this component requires that the power be completely removed from the system chassis (both server nodes powered off).	

Safety Information

Learn about important safety information before servicing the Oracle Database Appliance Version 1.





Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Hazardous voltage present. Never run the system with the top cover removed.

⚠ Caution

Equipment damage. Install the system top cover properly before starting the system.

For your protection, observe the following safety precautions when setting up your equipment:

- Follow all cautions, warnings, and instructions marked on the equipment and described in Important Safety Information for Oracle's Hardware Systems and Oracle Database Appliance Safety and Compliance Guide.
- Ensure that the voltage and frequency of your power source match the voltage and frequency inscribed on the equipment's electrical rating label.
- Follow the electrostatic discharge safety practices as described in this chapter.

Required Tools

Learn about the tools required to service the Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Antistatic wrist strap
- Antistatic mat
- No. 2 10-inch Phillips screwdriver (magnetic tip recommended)
- Flat blade screwdriver
- Stylus or pencil (to press the Clear CMOS button)

Obtaining the Chassis Serial Number

How to obtain the serial number for the Oracle Database Appliance Version 1.



To obtain support for Oracle Database Appliance Version 1, you need to report your product serial number. The product serial number is located on an RFID tag on the front of the system and on the Customer Information Sheet that is included with the system.

Note

Information in this appendix ONLY applies to the Oracle Database Appliance Version 1 (released in 2011). It does NOT apply to other models of Oracle Database Appliance released afterwards. Refer to the preceding chapters in this document for information on servicing other Oracle Database Appliance models

Shutting Down a Server Node and Powering Off the System

This section describes how to shut down the Oracle Database Appliance Version 1 for servicing.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

You can shut down either Oracle Database Appliance Version 1 server node using the front panel power button, or Oracle ILOM. Each method provides a **graceful shutdown** and an **emergency shutdown** option.

∧ Caution

Data loss. To avoid data loss and file system corruption, always use a graceful shutdown unless it is an emergency.

(i) Note

To use Oracle ILOM to shut down a server node, ensure that you have performed its initial configuration as described in "Connecting and Configuring Oracle ILOM" in the Oracle Database Appliance Getting Started Guide.

After you have shut down the server nodes, you can power off the system.

See the following topics in this section to shut down a server node and power off the system chassis:

- Shut Down a Server Node
 How to shut down an Oracle Database Appliance Version 1 server node.
- Power Off the System
 How to power off an Oracle Database Appliance Version 1 server node.



Shut Down a Server Node

How to shut down an Oracle Database Appliance Version 1 server node.

You must shut down the server node before you remove it from the system chassis.

Note


Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- To shut down a server node using the Power button, perform one of the following:
 - Graceful shutdown: Press and release the recessed Power button on the lower lefthand corner of the server node's front panel (see [1] the following figure). This causes Advanced Configuration and Power Interface (ACPI) to perform an orderly shutdown of the system.
 - Emergency shutdown: Press and hold the recessed Power button on the lower lefthand corner of the server node's front panel for at least five seconds until the main power is off and the server node enters standby power mode (see [1] the following figure).

⚠ Caution

Data loss. To avoid data loss and file system corruption, always use a graceful shutdown unless it is an emergency.

When the server node is shut down, the Power/OK LED (see [2] the following figure) on the server node's front panel flashes, indicating that the server node is in standby power mode.





- To shut down a server node using the Oracle ILOM, perform one of the following:
 - Using the Oracle ILOM web interface:
 - a. Open a browser and enter the server node's service processor IP address in the browser's address field.
 - **b.** At the log in page, type a user name (the account must have Reset and Host Control (r) privileges) and password, and click the Log In button.
 - c. Go to Remote Power Control and do one of the following:
 - Select Graceful Shutdown and Power Off from the Select Action list box and then click Save and OK.

The server node shuts down gracefully.

 Select Immediate Power Off from the Select Action list box and then click Save and OK.

The server node shuts down immediately.

⚠ Caution

Data loss. To avoid data loss and file system corruption, use graceful shutdown unless it is an emergency.

- Using the Oracle ILOM CLI:
 - a. Log in to Oracle ILOM using an ssh client. Type:

\$ssh username@sp_ip_address

Where *username* is a user account name with Reset and Host Control (r) privileges and *sp_ip_address* is the IP address of the server node service processor.

- **b.** When prompted, enter the user account password.
- c. Enter the command to shut down the server node:
 - For a graceful shutdown, type:

The server node shuts down gracefully.

For an emergency shutdown, type:

The server node shuts down immediately.

⚠ Caution

Data loss. To avoid data loss and file system corruption, use graceful shutdown unless it is an emergency.



Power Off the System

How to power off an Oracle Database Appliance Version 1 server node.

The appliance database must be shut down before powering off the entire appliance.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Shut down both server nodes.

Shutting down both server nodes places the system in standby power mode.

See Shut Down a Server Node.

Disconnect the AC power cords from the system.

Disconnecting the power cords from the system removes all power from the system.

Performing Electrostatic Discharge and Antistatic Prevention Measures

Learn about ESD and antistatic protection when servicing an Oracle Database Appliance Version 1.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Electrostatic discharge (ESD) sensitive devices, such as the motherboards, PCIe cards, storage drives, and memory cards, require special handling.



Equipment damage. Follow antistatic precautions and do not touch the components along their connector edges.

When handling components such as storage drive assemblies, circuit boards, or PCIe cards:

Attach an antistatic strap to your wrist and then to a metal area on the chassis. Following this practice equalizes the electrical potential between you and the system.





(i) Note

An antistatic wrist strap is not included in the system Accessory Kit. However, antistatic wrist straps are included with some options and components.

- Place ESD-sensitive components on an antistatic mat. The following items can be used as an antistatic mat:
 - Antistatic bag used to wrap a replacement part
 - ESD mat
 - Disposable ESD mat (shipped with some replacement parts or optional system components)

Removing Server Nodes From the System Chassis

Learn about removing an Oracle Database Appliance Version 1 server node from the chassis.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

You must remove the Oracle Database Appliance Version 1 server node from the chassis to remove or replace internal server node components.

Remove a Server Node From the System Chassis How to remove an Oracle Database Appliance Version 1 server node from the chassis.

Remove a Server Node From the System Chassis

How to remove an Oracle Database Appliance Version 1 server node from the chassis.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The removal procedure is the same for both server nodes. Note that you do not need to remove the entire system chassis from the rack to perform service procedures on a server node.





Replacing a server node FRU with a new server node is a service activity that must be performed by an Oracle-qualified service technician. The customer may remove the server node to service other CRU components in the server node.

1. Shut down the server node.


See Shut Down a Server Node.

⚠ Caution

Data loss. To avoid data loss and file system corruption, always use a graceful shutdown unless it is an emergency.

2. To unseat the server node from the system chassis, pull the two latches on the rear of the server node down [1] as shown in the following figure.

The latches are marked by green tabs. Pull the latches down and away from the rear to the system.



3. Slide the server node to the rear and lift it out of the system [2] as shown in the previous figure.

Removing the Server Node Top Cover

Learn about removing the server node top cover for an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.



To gain access to a most of Oracle Database Appliance Version 1 server node's internal components, you must remove the server node's top cover.

Remove the Server Node Top Cover
 How to remove an Oracle Database Appliance Version 1 server node top cover.

Remove the Server Node Top Cover

How to remove an Oracle Database Appliance Version 1 server node top cover.


(i) Note


Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

1. Remove the server node from the system chassis.

See Shut Down a Server Node.

- 2. Remove the top cover.
 - a. To unlatch the server node top cover, press and hold the green release button on the top of the server node cover [1].
 - **b.** Using the indented area near the green release button, slide the cover toward the front of the server node about 0.5 inches (12.7 mm) [1] as shown in the following figure.
 - c. Lift the cover up and remove it [2] as shown in the following figure.





Removing the Middle Section of the System Top Cover

Learn about removing the middle section of an Oracle Database Appliance Version 1 server node top cover.





Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

To gain access to the Oracle Database Appliance Version 1 power distribution board and the disk midplane board you must remove the middle section of the system's top cover.

Remove the Middle Section of System Top Cover How to remove an Oracle Database Appliance Version 1 server node top cover middle section.

Remove the Middle Section of System Top Cover

How to remove an Oracle Database Appliance Version 1 server node top cover middle section.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Power down the server nodes and remove the power cords from the power supplies. For instructions, see Shut Down a Server Node.


System fault. Do not remove the middle section of the system cover while the AC power cords are connected. Otherwise the fault LEDs light and a system fault is logged.

Remove the middle section of the system top cover.

To remove the middle section of the system's top cover, remove the captive Phillips screws that secure it to the system as shown in the following figure.

Hazardous voltage present. Never run the system with the middle section of the system top cover removed.





Servicing Hot-Pluggable Components

Perform tasks to service hot plug components in an Oracle Database Appliance Version 1 system.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.
- For the Oracle Database Appliance Version 1, you must run the oakcli add disk local command after replacing a failed disk. Refer to the Administration and Reference Guide for details.
- <u>Servicing Storage Drives and Boot Drives (CRU)</u>
 Learn about servicing Oracle Database Appliance Version 1 system storage and boot drives.
- <u>Servicing Fan Modules (CRU)</u>
 Perform tasks for servicing system chassis fan modules in an Oracle Database Appliance Version 1.
- <u>Servicing Power Supplies (CRU)</u>
 Perform tasks for servicing system chassis power supplies in an Oracle Database Appliance Version 1.



Servicing Storage Drives and Boot Drives (CRU)

Learn about servicing Oracle Database Appliance Version 1 system storage and boot drives.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Oracle Database Appliance Version 1 has 24 storage drives, located in the front of the chassis, and each server node has 2 boot drives, located in the rear. All storage drives and boot drives are hot-pluggable.

- Storage and Boot Drive Locations
 Learn about storage and boot drive locations.
- Remove a Storage Drive
 How to remove a storage drive from an Oracle Database Appliance Version 1 server node.
- Install a Storage Drive
 How to install a storage drive in an Oracle Database Appliance Version 1 server node.
- Remove a Boot Drive
 How to remove a boot drive from an Oracle Database Appliance Version 1 server node.
- Install a Boot Drive
 How to install a boot drive in an Oracle Database Appliance Version 1 server node.

Storage and Boot Drive Locations

Learn about storage and boot drive locations.

Appliance storage drives. Appliance storage drives are installed at the front of Oracle Database Appliance Version 1. Drive numbering is listed on the drive label on the right side of the appliance [1] as shown in the following figure.



The following table shows slot numbering and the type of the storage drive supported in each slot.





The appliance might include both mechanical hard disk (HDD) and solid state (SSD) drives. Both use the same 2.5 inch disk drive bracket. An SSD has a smaller footprint inside of the bracket than an HDD.

| Drive Slot Numbers
and Types Supported |
|---|---|---|---|
| SSD20 | SSD21 | SSD22 | SSD23 |
| HDD16 | HDD17 | HDD18 | HDD19 |
| HDD12 | HDD13 | HDD14 | HDD15 |
| HDD8 | HDD9 | HDD10 | HDD11 |
| HDD4 | HDD5 | HDD6 | HDD7 |
| HDD0 | HDD1 | HDD2 | HDD3 |

Server Node boot drives. Each appliance server node contains two boot drives that are installed in the back of Oracle Database Appliance and identified on the rear drive panel label [1] as shown in the following figure.



The following table shows the location and numbering of the boot drives.

Callout	Drive Locations and Identification
1	Boot Drives at the back of server node 1. Location and identification of the server node 1 boot drives as listed in Oracle ILOM:
	• /SYS/MB/RHDD1
	• /SYS/MB/RHDD0
2	Boot Drives at the back of server node 0. Location and identification of the server node 0 boot drives as listed in Oracle ILOM:
	• /SYS/MB/RHDD1
	• /SYS/MB/RHDD0



Remove a Storage Drive

How to remove a storage drive from an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Identify the storage drive that you want to remove.


If a drive has failed, its amber Service Required LED will be lit. For information on drive status LEDs, see Storage and Boot Drive Status Indicators. For specific drive locations, see Storage and Boot Drive Locations.


- Remove a storage drive.
 - On the drive you plan to remove, push the storage drive release button to open the latch [1] as shown in the following figure.
 - b. Grasp the latch, swing it open 45 degrees until it unlatches the drive from the slot and slowly pull the drive straight out of the drive slot [1 and 2] as shown in the following figure.

Do not bend the latch too far to the right or exert too much force on the latch when removing the drive.



Equipment damage. Always replace a drive with another drive to maintain proper airflow.








Install a Storage Drive

How to install a storage drive in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Determine the drive slot location for the replacement drive.
 Drives are physically addressed according to the slot in which they are installed. See Storage and Boot Drive Locations for drive locations.
- 2. Slide the drive into the drive slot as far as it will go as shown in the following figure.



3. Close the latch to lock the drive in place.





(i) Note

After a physical insertion or removal action of a storage component (such as a disk or SAS cable), you should wait before performing the next action to allow the system software to fully process the event. This could take up to 3 minutes to complete.

After replacing a disk, if you have a bare metal deployment of Oracle Database Appliance, make the disk available to the appliance using the oakcli command. Type:

#oakcli add disk -local



(i) Note

This command is not supported on virtualized configurations.

Refer to the Administration and Reference Guide for additional details.

Remove a Boot Drive

How to remove a boot drive from an Oracle Database Appliance Version 1 server node.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Identify the boot drive that you want to remove.

The amber Service Required LED might be lit. For specific drive locations, see Storage and Boot Drive Locations.


- Remove the boot drive.
 - To open the drive door, slide the latch to the left [1] as shown in the following figure.
 - b. Pull the door open and push the storage drive release button to open the latch [2 and 3] as shown in the following figure.
 - Grasp the latch, swing it open 45 degrees until it unlatches the drive from the slot and slowly pull the drive straight out of the drive slot [2] as shown in the following figure.

Do not bend the latch too far to the right or exert too much force on the latch when removing the drive.



Equipment damage. Close the door after removing a boot drive to prevent overheating due to improper airflow.






Install a Boot Drive


How to install a boot drive in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Determine the drive slot location for the replacement drive.
 - Drives are physically addressed according to the slot in which they are installed. See <u>Storage and Boot Drive Locations</u> for drive locations.
- 2. Pull open the rear drive door.
- 3. Slide the drive into the drive slot until it is fully seated [1] as shown in the following figure.







- Close the drive latch to lock the drive in place.
- Close the drive door and ensure that the door latch engages [2] as shown in the previous figure.

Equipment damage. Close the door after removing a boot drive to prevent overheating due to improper airflow.

6. Run the following command to ensure that the OS sees the replacement disk.

```
# lsscsi -v | grep ATA
[0:0:0:0]diskATA SEAGATE ST95001N n/a
                                       /dev/sda
[1:0:0:0]diskATA SEAGATE ST95001N n/a
                                      /dev/sdb
```

Servicing Fan Modules (CRU)

Perform tasks for servicing system chassis fan modules in an Oracle Database Appliance Version 1.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Each Oracle Database Appliance Version 1 server node contains two fan modules. Each fan module contains a single, dual-motor, 80 mm, counter-rotating fan assembly that contains two fans. Each fan module is hot-pluggable. For specific information about fan status LEDs, see Server Node Fan Status Indicators.

When a server node is removed from the system, the fans provide sufficient cooling for all 24 front disks and the server node. A door automatically closes off the vacant server node slot to ensure proper cooling. When the server node is replaced, its two fans also cool the 24 front disks and provide cooling to the second server node.



Equipment damage. If a fan module fails, replace it as soon as possible.

- Detecting a Fan Module Failure
 - Learn how to detect a fan module failure in an Oracle Database Appliance Version 1.
- Remove a Fan Module
 - How to remove a fan module in an Oracle Database Appliance Version 1.
- Install a Fan Module
 - How to install a fan module in an Oracle Database Appliance Version 1.



Detecting a Fan Module Failure

Learn how to detect a fan module failure in an Oracle Database Appliance Version 1.

The following LEDs in Oracle Database Appliance Version 1 are lit when a fan module fault is detected:

- Front and rear Service Required LEDs located on each server node
- REAR HDD/PS/FAN LED located on the front of each server node
- Fan Fault Status LED located on the faulty fan module

The system over-temperature LED for a server node might light if a fan fault causes an increase in server node operating temperature. See <u>Oracle Database Appliance Version 1</u> <u>Status Indicators</u> for more information about server node LEDs.

Remove a Fan Module

How to remove a fan module in an Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

This section describes removing a fan module from Oracle Database Appliance Version 1.





Equipment damage. When removing a fan module from a powered on system, it must be replaced within two minutes of removal.

- 1. Identify the faulty fan module with its amber LED.
 - When a fan fails, the Service Required LED lights amber. For information about fan status LEDs, see Server Node Fan Indicators.
- To remove the faulty fan module, press down on the fan release lever [1] as shown in the following figure.
- 3. While holding the release lever down, use the handle on the fan module to pull it out of the server node [2] as shown in the following figure.

The fan door swings shut to ensure proper cooling.







Install a Fan Module

How to install a fan module in an Oracle Database Appliance Version 1.

(i) Note


Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

This section describes installing a fan module from Oracle Database Appliance Version 1.

- Align the fan module in the fan door and slide it into the server node.
 The extender on the side of the fan module pushes the fan door open, allowing the fan module to enter.
- 2. Apply firm pressure to fully seat the fan module.

The fan release lever engages when the fan is fully seated as shown in the following figure.





- 3. Verify that the Fan Fault Status LED on the replacement fan module is lit green.
- 4. Verify that the following fault LEDs on the applicable server node are off:
 - Front and rear Service Required LEDs located on the applicable server node
 - REAR HDD/PS/FAN LED located on the front of the applicable server node

See <u>Oracle Database Appliance Version 1 Status Indicators</u> for more information about system LEDs.

Servicing Power Supplies (CRU)

Perform tasks for servicing system chassis power supplies in an Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Oracle Database Appliance Version 1 is equipped with two hot pluggable power supplies. They are redundant, meaning that the system can operate with a single power supply. This allows you to remove and replace a power supply without shutting the system down.

If a power supply fails and you do not have a replacement available, to ensure proper airflow, leave the failed power supply installed in the system.

For information about power supply status LEDs, see Power Supply Status Indicators.

<u>Detecting a Power Supply Failure</u>
 Learn how to detect a power supply failure in an Oracle Database Appliance Version 1.



Remove a Power Supply

How to remove a power supply from an Oracle Database Appliance Version 1.

Install a Power Supply
 How to install a power supply in an Oracle Database Appliance Version 1.

Detecting a Power Supply Failure

Learn how to detect a power supply failure in an Oracle Database Appliance Version 1.

The following LEDs light up in Oracle Database Appliance Version 1 when the system detects a power supply fault:

- Front and rear Service Required LEDs located on each server node
- REAR HDD/PS/FAN LED located on the front of each server node
- Service Required LED located on the faulty power supply

See <u>Oracle Database Appliance Version 1 Status Indicators</u> for more information about these LEDs.

Remove a Power Supply

How to remove a power supply from an Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

This section describes removing a Power Supply from Oracle Database Appliance Version 1.

∴ Caution


Hazardous voltages. To reduce the risk of electric shock and danger to personal health, follow the instructions.


1. Identify which power supply (0 or 1) requires replacement.

A lit Service Required LED on a power supply indicates that a failure was detected. For information about power supply status LEDs, see Power Supply Status Indicators.

- 2. Disconnect the power cord from the faulty power supply.
- Grasp the power supply handle and press the release latch [1] as shown in the following figure.
- 4. Pull the power supply out of the chassis [2] as shown in the following figure.







Install a Power Supply

How to install a power supply in an Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.


This section describes removing a Power Supply from Oracle Database Appliance Version 1.

⚠ Caution

Hazardous voltages. To reduce the risk of electric shock and danger to personal health, follow the instructions.

- 1. Align the replacement power supply with the empty power supply chassis bay.
- 2. Slide the power supply into the bay until it is fully seated as shown in the following figure. The release latch engages when the power supply is fully seated.





- 3. Reconnect the power cord to the power supply and verify the following:
 - The power supply AC Present LED is lit
 - The power supply Service Required LED is off.
- 4. Verify that the following LEDs are off:
 - Service Required LEDs located on the front of both server nodes
 - REAR HDD/PS/FAN LED located on the front of both server nodes

See <u>Oracle Database Appliance Version 1 Status Indicators</u> for more information about system LEDs.

Servicing CRUs That Require Server Node Power Off

Perform tasks for servicing customer-replaceable units (CRUs) for the Oracle Database Appliance Version 1 that require you to power off the server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

This section includes information on how to service the following Oracle Database Appliance Version 1 CRUs:



Server Node CRU Component Locations

Learn about customer-replaceable server node components in the Oracle Database Appliance Version 1.

• Servicing Memory Modules (DIMMs) (CRU)

Learn about customer-replaceable server node components in the Oracle Database Appliance Version 1.

Servicing PCIe Risers (CRU)

Perform tasks for servicing PCIe risers in the Oracle Database Appliance Version 1.

Servicing PCIe Cards (CRU)

Perform tasks for servicing PCIe cards in the Oracle Database Appliance Version 1.


Servicing the Server Node Battery (CRU)

Learn about servicing a server node system battery in the Oracle Database Appliance Version 1.

Server Node CRU Component Locations

Learn about customer-replaceable server node components in the Oracle Database Appliance Version 1.

Each server node (also called a system controller) in Oracle Database Appliance Version 1 includes the replaceable components shown in the following figure.





Callout	Description
1	DDR3 Memory DIMMs (12)
2	PCIe Cards Mounted on PCIe Riser
3	PCIe Riser
4	Internal HBA PCIe Card
5	Battery

Servicing Memory Modules (DIMMs) (CRU)

Learn about customer-replaceable server node components in the Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle

Each server node in Oracle Database Appliance Version 1 is provisioned with twelve 1333 MHz or 1600 MHz DDR3, 8GB dual rank DIMMs, for a total of 96GB.

The server node supports a maximum memory speed of 1333 MHz, even if 1600 MHz DIMMs are installed.

Before replacing a DIMM see the following:

Database Appliance model.

- **DIMM and CPU Physical Layout** Learn about DIMM and processor layout in the Oracle Database Appliance Version 1.
- Remove Faulty DIMMs How to remove a DIMM from an Oracle Database Appliance Version 1.
- **Install DIMMs** How to install a DIMM in an Oracle Database Appliance Version 1.
- **Error Correction and Parity Protection** Learn about DIMM ECC and parity errors in the Oracle Database Appliance Version 1.

DIMM and CPU Physical Layout

Learn about DIMM and processor layout in the Oracle Database Appliance Version 1.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.




Each processor in Oracle Database Appliance Version 1 has six DIMM slots numbered D0 through D5. D0 is the closest to the processor and D5 is the farthest.

Each slot should contain a 1333 MHz or 1600 MHz DDR3, 8GB dual rank DIMM. No other configurations are supported.

The server node supports a maximum memory speed of 1333 MHz, even if it is configured with 1600 MHz DIMMs.

If the system contains a mixture of 1333 MHz and 1600 MHz DIMMs, then P0 and P1 should be configured the same, so that both sides are symmetrical. For example, if you install only two 1600 MHz DIMMs, they should go into P0, D0 and P1, D0.

The following figure shows the physical layout of the DIMMs and CPUs. When viewing the server node from the front, CPU0 (P0) is on the right.



Each processor socket supports three independent memory channels labeled channel A, B, and C, where channel A is closest to the processor socket. Each channel supports two DIMM slots, is controlled by an independent memory controller, and operates independent of the other channels.

Remove Faulty DIMMs

How to remove a DIMM from an Oracle Database Appliance Version 1.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.



- Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.


c. Remove the server node top cover.

See Removing the Server Node Top Cover.

- 2. Identify the faulty DIMM(s).
 - **a.** To identify the location of a faulty DIMMs, press the Fault Remind button on the motherboard as shown in the following figure.

(i) Note

When the Fault Remind button is pressed, the Fault Remind Power Good LED lights green to indicate that there is sufficient voltage present in the fault remind circuit to light the fault LEDs. If this LED fails to light when you press the Fault Remind button, the capacitor powering the fault remind circuit has lost its charge. This can happen if the Fault Remind button is pressed for a long time with fault LEDs lit or if the server node has been out of the chassis for more then 15 minutes.




Callout	Description
1	Fault Remind Button
2	Fault Remind Power Good LED (green)




b. Note the location of faulty DIMMs.

The amber DIMM fault LEDs light if the adjacent DIMM is faulty as shown in the following figure.



- If the DIMM fault LED is off, the DIMM is operating properly.
- If the DIMM fault Required LED is on (amber), the DIMM is faulty and should be replaced.
- 3. To remove the faulty DIMM(s), do the following:
 - a. Rotate both DIMM slot ejectors outward as far as they go.
 - The ejectors push the DIMM partially up.
 - **b.** Carefully lift the DIMM straight up to remove it from the socket as shown in the following figure.





Callout	Description
1	DIMM connector slot
2	DIMM connector key
3	DIMM ejector lever

4. Replace each faulty DIMM with either another DIMM of the same rank size.

For DIMM replacement instructions, see Install DIMMs.

Do not operate the system with an empty DIMM slot. If you remove a DIMM, you must replace it before starting the server.

Install DIMMs

How to install a DIMM in an Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Unpack the replacement DIMMs and place them on an antistatic mat.
- 2. Ensure that the replacement DIMMs match the system requirements.

The system supports only 1333 MHz or 1600 MHz DDR3, 8GB, dual rank DIMMs obtained from Oracle.


For the best performance, if you combine 1333 MHz and 1600 MHz DIMMs in a single system, they should be configured so that P0 and P1 have the same mixture, in the same DIMM slots. For example, in a 1333 MHz system, if you replace P0, D0 with a 1600 MHz DIMM, you should also replace P1, D0 with a 1600 MHz DIMM.

The server node supports a maximum memory speed of 1333 MHz, even if 1600 MHz DIMMs are installed.

- 3. Ensure that the ejector tabs are in the open position.
- 4. Align the replacement DIMM with the connector.

Align the notch in the DIMM with the key in the connector. The notch ensures that the DIMM is oriented correctly as shown in the following figure.





5. Push the DIMM into the connector until the ejector tabs lock the DIMM in place.

If the DIMM does not easily seat into the connector, verify that the notch in the DIMM is aligned with the key in the connector as shown above. If the notch is not aligned, damage to the DIMM might occur.

- 6. Repeat Step 3 through Step 5 until all replacement DIMMs are installed.
- 7. Return the server node to operation.
 - a. Install the server node top cover.

See <u>Installing the Server Node Top Cover</u>.

- b. Install the server node into the system.
 - See Installing a Server Node Into the System Chassis.
- c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

- 8. Clear the DIMM faults.
 - a. Log in to the server node Oracle ILOM CLI as root.
 - **b.** To view server node faults, type the following command:
 - -> show /SP/faultmgmt

Oracle ILOM lists all known faults. For example:



```
SP/faultmgmt
Targets:
0 (/SYS/MB/P0/D2)
Properties:
Commands:
cd
show
```

c. To clear the DIMM fault, type the following command:

```
-> set /SYS/MB/Px/Dn clear_fault_action=true
```

For example, to clear a fault on the DIMM in location D2 on CPU0:

```
-> set /SYS/MB/P0/D2 clear_fault_action=true
Are you sure you want to clear /SYS/MB/P0 (y/n)? y
Set 'clear fault action' to 'true'
```

Error Correction and Parity Protection

Learn about DIMM ECC and parity errors in the Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 server node's processor provides parity protection on its internal cache memories, and error-correcting code (ECC) protection of the data. The server node detects and posts the following errors to the Oracle ILOM event log:

- Correctable and uncorrectable memory ECC errors
- Uncorrectable CPU internal errors

Advanced ECC corrects up to 4 bits in error on nibble boundaries, as long as they are all in the same DRAM. If a DRAM fails, the DIMM continues to function.

To clear a fault once the faulty DIMM has been replaced, type the following in the Oracle ILOM CLI:

```
-> set clear_fault_action=true
```

For more information on clearing DIMM faults, see the <u>Oracle Integrated Lights Out Manager</u> (Oracle ILOM) 3.0 Documentation Collection.

Servicing PCIe Risers (CRU)

Perform tasks for servicing PCIe risers in the Oracle Database Appliance Version 1.





Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

PCIe cards in Oracle Database Appliance Version 1 are installed on a vertical riser. You must remove the riser to remove and replace a PCIe card. Also, you must remove the PCIe riser when replacing the motherboard.

⚠ Caution

These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices as described in Performing Electrostatic Discharge and Antistatic Prevention Measures.

- Remove PCle Riser From Server Nodes

 How to remove a PCle riser from an Oracle Database Appliance Version 1 server node.
- Install PCIe Riser in Server Nodes
 How to install a PCIe riser in an Oracle Database Appliance Version 1 server node.

Remove PCIe Riser From Server Nodes

How to remove a PCIe riser from an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

c. Remove the server node top cover.

See Removing the Server Node Top Cover.

- 2. If you are servicing a PCIe card, locate its position on the riser.
- 3. Disconnect any data cables connected to the cards on the PCIe riser being removed.




To disconnect a cable from a PCIe card, press the latch, push in toward the connector, and then pull out to remove the cable.

Note the location of all cables for reinstallation later.

- Ensure that the latch adjacent to the location where PCIe riser is installed is in the open (down) position [1] as shown in the following figure.
 - If the latch is in the closed position, it prevents you from removing the PCIe riser.
- Loosen the three green captive Phillips screws that secure the PCIe riser to the server node [1] as shown in the following figure.

Access these screws from the rear of the server node.



- Loosen the green captive Phillips screw that secures the PCIe riser to the motherboard [2].
- To lift the PCIe riser out of the server node, grasp the front-most side plastic tab with one hand and the rear of the riser with the other hand, and lift it straight up and out of the server node [2].
- Place the PCIe riser and any cards attached to it on an antistatic mat.

Install PCIe Riser in Server Nodes

How to install a PCIe riser in an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.


- Before installing the PCIe riser, ensure that the latch adjacent to the location where PCIe riser is to be installed is in the open (down) position [2].
- Install the PCIe riser.



a. Ensure that any PCIe cards installed in the PCIe riser are properly seated, and that the card's locking bracket is flush with the recess in the riser and is engaging the locking tab.

For instructions for installing a PCle card into a PCle riser, see <u>Install PCle Card in PCle Riser</u>.

- b. Lower the PCIe riser, and any cards attached to it, into the server node and push the riser down until it seats into the connector on the motherboard [1] as shown in the following figure.
- **c.** Tighten the green captive Phillips screw that secures the riser to the motherboard [1] as shown in the following figure.



d. Tighten the three green captive Phillips screws that secure the PCIe riser to the chassis [2] as shown in the previous figure.

Access these screws from the rear of the server node.

- 3. Return the server node to operation.
 - a. Install the server node top cover.

See Installing the Server Node Top Cover.

b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

- c. Reconnect any data cables to the PCIe card connectors on the system rear panel.
- d. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

- 4. Clear PCIe riser faults.
 - a. Log in to the Oracle ILOM CLI as root.
 - b. Type:
 - -> show /SP/faultmgmt

Oracle ILOM lists all known faults. For example:

SP/faultmgmt
Targets:



```
0 (/SYS/MB/RISER)
Properties:
Commands:
cd
show
```

c. To clear PCIe riser faults, use the set command. For example:

```
-> set /SYS/MB/RISER clear_fault_action=true
Are you sure you want to clear /SYS/MB/RISER (y/n)? y
Set 'clear_fault_action' to 'true'
```

Servicing PCIe Cards (CRU)

Perform tasks for servicing PCIe cards in the Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

PCIe cards in Oracle Database Appliance Version 1 are installed on a vertical riser. You must remove the riser to remove and replace a PCIe card. See Servicing PCIe Risers (CRU).

∧ Caution

These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices as described in Performing Electrostatic Discharge and Antistatic Prevention Measures.

- PCIe Card Configuration
 - Learn about PCIe cards in the Oracle Database Appliance Version 1.
- Remove PCIe Card From PCIe Riser

How to remove a PCIe card from an Oracle Database Appliance Version 1 server node.

- Install PCIe Card in PCIe Riser
 - How to install a PCIe card in an Oracle Database Appliance Version 1 server node.
- Remove Primary HBA PCIe Card From Motherboard
 - How to remove the primary HBA card from an Oracle Database Appliance Version 1 server node.
- Install Primary HBA PCIe Card in Motherboard
 - How to install the primary HBA card in an Oracle Database Appliance Version 1 server node.



PCIe Card Configuration

Learn about PCIe cards in the Oracle Database Appliance Version 1.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 PCIe expansion system includes one standalone low-profile slot on the motherboard and a PCIe riser with three slots. These are provisioned as follows:

- Motherboard slot: A low-profile, dual-port SAS-2 HBA used internally
- PCIe slot 2: Dual-port SAS-2 HBA used internally
- PCIe slot 1: Quad-port 1-Gb Ethernet NIC
- PCIe slot 0: Dual-port 10-Gb Ethernet NIC

Caution

If you replace a PCIe card, ensure the replacement is identical to the card you are replacing.

Remove PCIe Card From PCIe Riser

How to remove a PCIe card from an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

Remove the server node top cover.

See Removing the Server Node Top Cover.



2. Locate the PCIe card in the PCIe riser that you want to remove.

See the "Oracle Database Appliance Version 1 Back Panel" section of the *Oracle Database Owner's Guide* for the location of the PCIe slots.

- 3. If necessary, make a note of where the PCIe cards are installed.
- 4. Disconnect all data cables from the PCIe card.


To disconnect a cable from the PCIe card, press the latch, push in toward the connector, and then pull out to remove the cable.

Note the location of all cables for reinstallation later.

5. Remove the PCIe riser.

See Remove PCIe Riser From Server Nodes.

- 6. Remove the PCIe card from the riser.
 - a. Carefully disconnect the PCIe card from the riser connector and remove it from the riser board connector as shown in the following figure.



b. Place the PCIe card on an antistatic mat.



Install PCIe Card in PCIe Riser

How to install a PCIe card in an Oracle Database Appliance Version 1 server node.


(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Unpack the replacement PCIe card and place it on an antistatic mat.
- 2. Locate the proper PCIe slot for the card you are replacing.
- Remove the PCIe riser.

See Remove PCIe Riser From Server Nodes.

- 4. Insert the PCIe card into the correct slot on the riser.
 - a. Press down on the PCIe card until its bracket [3] comes in contact with the recessed area [1] on the PCIe riser as shown in the following figure.
 - **b.** Ensure the card bracket engages the PCIe riser locking tab [2] as shown in the following figure.





Callout	Description
1	Recessed area on the PCle riser
2	PCIe riser locking tab
3	PCIe card bracket

5. Install the PCIe riser.

See Install PCIe Riser in Server Nodes.

- 6. Reconnect any cables to the PCIe card that you unplugged during the removal procedure.
- **7.** Return the server node to operation.
 - a. Install the server node top cover.

See <u>Installing the Server Node Top Cover</u>.

b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

- c. Reconnect any data cables to the PCIe card connectors on the system rear panel.
- **d.** Power on the server node.

See Powering On Oracle Database Appliance Version 1.

- 8. Clear the PCIe card fault.
 - a. Log in to the server node as >root> using the Oracle ILOM CLI.
 - b. To view server node faults, type the following command to list all known faults on the system:
 - -> show /SP/faultmgmt

Oracle ILOM lists all known faults, for example:

```
SP/faultmgmt
Targets:
0 (/SYS/MB/RISER/PCIE2)
Properties:
Commands:
cd
show
```

c. To clear PCIe riser faults, use the set command. For example:

```
-> set /SYS/MB/RISER clear_fault_action=true
Are you sure you want to clear /SYS/MB/RISER (y/n)? y
Set 'clear_fault_action' to 'true'
```

d. To clear a PCIe card fault, use the set command. For example, to clear a fault on PCIe 2:

```
-> set /SYS/MB/RISER/PCIE2 clear_fault_action=true
Are you sure you want to clear /SYS/MB/RISER/PCIE2 (y/n)? y
Set 'clear_fault_action' to 'true'
```



Remove Primary HBA PCIe Card From Motherboard

How to remove the primary HBA card from an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.


c. Remove the server node top cover.


See Removing the Server Node Top Cover.

- 2. Remove the primary PCIe card.
 - a. Locate the Primary HBA PCIe card next to the rear-mounted disk drives.
 - b. Disconnect the data cables from the PCIe card by pressing each cable's release latch and removing the cable [1] as shown in the following figure.

Note

There are two data cables that connect the PCIe card to the server node disk drive backplane. Note their location for reinstallation later.







- Grasp the PCIe card and lift it up and out of the server node [2] as shown in the previous figure.
- Place the PCIe card on an antistatic mat.

Install Primary HBA PCIe Card in Motherboard

How to install the primary HBA card in an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Unpack the replacement PCIe card and place it on an antistatic mat.



Note

To install a replacement HBA PCIe card into the primary HBA PCIe slot on the motherboard, a special metal bracket mounted to the PCIe card is required. The standard low-profile or full-height metal bracket standard on PCIe cards must be replaced with this unique metal bracket (available on the original primary HBA) before installation.


- Install the internal PCIe card.
 - a. Locate the internal PCIe card connector next to the rear-mounted disk drives.
 - b. As you install the PCIe card, align the notch on the PCIe card with the key on the server node chassis wall and press down on the PCIe card to seat it into the connector [1] as shown in the following figure.



↑ Caution

If the notch and key are not aligned, damage to the PCIe card might occur.





- c. Reconnect the cables to the primary HBA card connectors that you disconnected during the removal procedure [2] as shown in the previous figure.
- 3. Return the server node to operation.
 - a. Install the server node top cover.

See Installing the Server Node Top Cover.

b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

- Clear the primary HBA card fault.
 - a. Log in to the server node as root using the Oracle ILOM CLI.
 - b. To view server node faults, type the following command to list all known faults on the server node:
 - -> show /SP/faultmgmt

Oracle ILOM lists all known faults, for example:

SP/faultmgmt
Targets:
0 (/SYS/MB/HBA)
Properties:
Commands:
cd

c. To clear the internal PCIe card fault, use the set command. For example:

```
-> set /SYS/MB/HBA clear_fault_action=true
Are you sure you want to clear /SYS/MB/HBA (y/n)? y
Set 'clear_fault_action' to 'true'
```

Servicing the Server Node Battery (CRU)

Learn about servicing a server node system battery in the Oracle Database Appliance Version 1.



① Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 battery maintains the date and time for the Oracle ILOM service processor when the server node is removed from the system and, therefore, is powered off. If the server node fails to maintain the proper time when powered off, replace the battery.

↑ Caution

These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

Remove Battery

How to remove the system battery in an Oracle Database Appliance Version 1 server node.

Install Battery

How to install the system battery in an Oracle Database Appliance Version 1 server node.

Remove Battery

How to remove the system battery in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.


c. Remove the server node top cover.

See Removing the Server Node Top Cover.

Remove the battery.



- a. Place you finger between the battery and the server node side wall and push the battery away from the side wall.
- b. Twist the battery (either clockwise or counter-clockwise) and lift it out as shown in the following figure.



Install Battery

How to install the system battery in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Unpack the replacement battery.
- Press the new battery into the battery holder with the positive side (+) facing the server node side wall.
- 3. If the service processor is configured to synchronize with a network time server using the Network Time Protocol (NTP), the Oracle ILOM clock is reset as soon as the server node is powered on and connected to the network. Otherwise, proceed to the next step.
- If the service processor is not configured to use NTP, you must reset the Oracle ILOM clock using the Oracle ILOM CLI or the web interface.

For instructions, see the <u>Oracle Integrated Lights Out Manager (Oracle ILOM) 3.0</u> Documentation.

- 5. Return the server node to operation.
 - a. Install the server node top cover.

See <u>Installing the Server Node Top Cover</u>.



b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Servicing FRUs

Perform tasks for servicing field-replaceable units (FRUs) for the Oracle Database Appliance Version 1 that require you to power off the system and/or server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

(i) Note

Only authorized Oracle Service personnel can service field-replaceable unit (FRU) components.

Removing and Installing the Air Duct (FRU)

Learn about removing and installing the air duct for an Oracle Database Appliance Version 1.

Servicing Processors (CPUs) (FRU)

Learn about servicing processors in an Oracle Database Appliance Version 1 server module.

• Servicing the Boot Disk Backplane (FRU)

Learn about servicing the boot disk backplane in an Oracle Database Appliance Version 1 server module.

Servicing the Power Distribution Board (FRU)

Learn about servicing the power distribution board in an Oracle Database Appliance Version 1.

Servicing the Disk Midplane Module (FRU)

Learn about servicing the disk midplane module in an Oracle Database Appliance Version 1

Servicing the Disk Midplane Module HDD Cable (FRU)

Learn about servicing the disk midplane module HDD cable in an Oracle Database Appliance Version 1.

Servicing the Front Indicator Panels (FRU)

Learn about servicing the front indicator panel of an Oracle Database Appliance Version 1.

Servicing Server Node Cables

Perform tasks for servicing the Oracle Database Appliance Version 1 server node cables.



Servicing the Motherboard Assembly (FRU)

Learn about servicing the motherboard in an Oracle Database Appliance Version 1 server node.

Removing and Installing the Air Duct (FRU)

Learn about removing and installing the air duct for an Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The air duct for the Oracle Database Appliance Version 1 must be removed to service the CPUs.

The air duct is a FRU and can only be replaced by an Oracle-qualified service technician.

Equipment overheating. Ensure that the air duct is installed correctly before powering on the server.

Remove Air Duct

How to remove an air duct in an Oracle Database Appliance Version 1 server node.

Install Air Duct

How to install an air duct in an Oracle Database Appliance Version 1 server node.

Remove Air Duct

How to remove an air duct in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.




Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

c. Remove the server node top cover.

See Removing the Server Node Top Cover.

- 2. Remove the air duct.
 - a. From the rear of the server node, grasp the middle/rear of the air duct with your right hand and lift it up to a 45 degree angle [1] as shown in the following figure.

The air duct swings up and away from the rear of the system.



b. Grasp the left end of the plastic air duct with your left hand to hold it at a 45 degree angle, and with your right hand press gently down on the middle of the air duct until it bends enough to disengage its hinges from their sockets and allow removal of the air duct [2] as shown in the previous figure.

Install Air Duct

How to install an air duct in an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

⚠ Caution

Equipment overheating. Ensure that the air duct is installed correctly before powering on the server.

- Install the air duct into the chassis.
 - a. From the rear of the server node, insert the air duct's right hinge into the right-side socket [2], and place the left hinge on top of the left-side socket.



- b. Grasp the left end of the air duct with your left hand to hold it at a 45 degree angle, and, with your right hand, press gently down on the middle of the air duct until it bends enough to insert the left hinge into the left-side socket [2].
- **c.** Carefully lower the air duct to its closed position, with particular attention given to the SAS cables [1].

Ensure that the openings on each side of the air duct fit around the cables and not on top of them.

⚠ Caution

Equipment overheating. Verify that the air duct is fully closed.

- 2. Return the server node to operation.
 - a. Install the server node top cover.

See Installing the Server Node Top Cover.

- **b.** Install the server node into the system.
 - See Installing a Server Node Into the System Chassis.
- c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Servicing Processors (CPUs) (FRU)

Learn about servicing processors in an Oracle Database Appliance Version 1 server module.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The CPU is a FRU and can only be replaced by an Oracle-qualified service technician.

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

- Remove Processor (CPU)
 - How to remove a processor from an Oracle Database Appliance Version 1 server node.
- Install Processor (CPU)

How to install a processor in an Oracle Database Appliance Version 1 server node.



Remove Processor (CPU)

How to remove a processor from an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

⚠ Caution

Equipment overheating. If you remove a CPU/heatsink from the system, you should replace it or install a CPU filler before you return the server to operation; otherwise, the system might overheat due to improper airflow.

- Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

c. Remove the server node top cover.

See Removing the Server Node Top Cover.

d. Remove the air duct.

See Remove Air Duct.

- 2. Remove the CPU.
 - a. Identify which CPU to remove.
 - b. To identify the location of the faulty CPU, press the Fault Remind button on the motherboard.


Note

When the Fault Remind button is pressed, the Fault Remind Power Good indicator (LED) lights green to indicate that there is sufficient voltage present in the fault remind circuit to light the fault indicators. If this indicator fails to light when you press the Fault Remind button, the capacitor powering the fault remind circuit has lost its charge. This can happen if the Fault Remind button is pressed for a long time with fault indicators lit or if the server node has been out of the chassis for more then 15 minutes.

c. The fault LED for the faulty CPU lights.




The fault LED is located next to the CPU as shown in the following figure.



- · If CPU fault LED is off: CPU is operating properly.
- If CPU fault LED is on (amber): CPU is faulty and should be replaced.

Viewing the server node from the front, CPU0 (P0) is on the right side of the server node.

d. Using a Phillips screwdriver, turn one captive screw on the heatsink counterclockwise two full turns, then turn the other screw two full turns, and keep alternating between the two screws until they are removed [2] as shown in the following figure.





- e. Twist the heatsink slightly to break the grease seal, then lift it off and place it upside down on a flat surface to prevent the thermal grease from contaminating other components.
- f. Using the wipes supplied with the replacement CPU, carefully clean the thermal grease from both the bottom of the heatsink and the top of the CPU.

Equipment damage. When cleaning the top of the CPU, be careful not to get the thermal grease on your fingers, the CPU socket or other associated components as this could result in contamination.

- g. Disengage the CPU release lever by pushing down and moving it to the side away from the CPU, and then rotating the lever upward [3] as shown in the previous figure.
- h. Raise the pressure frame on the CPU to the open position [3].
- i. Use your index finger to carefully lift up the edge of the CPU or protective cap that is farthest from the socket alignment slots [4] as shown in the previous figure, then firmly grasp both sides of the CPU or protective cap with your thumb and index finger on your other hand [4], and carefully lift the CPU or protective cap up and out of the socket [5] as shown in the previous figure.

Install Processor (CPU)


How to install a processor in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Attach an antistatic wrist strap.
 - See Performing Electrostatic Discharge and Antistatic Prevention Measures.
- 2. Unpack the replacement CPU.
 - The CPU replacement kit includes a new CPU, wipes, and a tube of thermal grease.
- Install the CPU.
 - a. Grasp the sides of the CPU firmly with your thumb and index finger, tilt it at a 45 degree angle, orient it with the socket alignment tabs [2] as shown in the following figure.





- b. Carefully lower the end of the CPU with the alignment tabs into the socket, support the raised end of the CPU with the index finger on your other hand, and lower the CPU into the socket [3] as shown in the previous figure.
- c. Lower the pressure frame to the closed position, ensuring that the pressure frame sits flat around the periphery of the CPU [4-1] as shown in the previous figure. Then engage the release lever by rotating it downward and slipping it under the catch [4-2].
- d. Ensure that there is no debris on the top of the CPU die.
- Use the syringe (supplied with the new or replacement CPU) to apply approximately 0.1 ml of thermal grease to the center of the top of the CPU. Do not distribute the grease.
- f. Orient the heatsink so that the DIMM SIDE label on the top of the heatsink is facing the memory modules (DIMMs) and the two captive Phillips screws align with the mounting studs.
 - Each heatsink is labeled to indicate which side of the heatsink faces the memory modules (DIMMs) when the heatsink is properly oriented.
- g. Tighten the two Phillips screws alternately two full turns at a time until the screws are fully seated [5] as shown in the previous figure.
- 4. Return the server node to operation.
 - a. Install the air duct.
 - See Install Air Duct.
 - b. Install the server node top cover.
 - See Installing the Server Node Top Cover.
 - c. Install the server node into the system.
 - See Installing a Server Node Into the System Chassis.



d. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

- 5. Clear the CPU faults.
 - a. Log in to the server node as root using the Oracle ILOM CLI.
 - **b.** To view server node faults, type the following command to list all known faults on the system:

```
-> show /SP/faultmgmt
```

Oracle ILOM lists all known faults, for example:

```
SP/faultmgmt
Targets:
0 (/SYS/MB/P0)
Properties:
Commands:
cd
show
```

- **c.** To clear the fault, type the following command:
- -> set /SYS/MB/Pn clear_fault_action=true

For example, to clear a fault on P0:

```
-> set /SYS/MB/P0 clear_fault_action=true
Are you sure you want to clear /SYS/MB/P0 (y/n)? y
Set 'clear_fault_action' to 'true'
```

Servicing the Boot Disk Backplane (FRU)

Learn about servicing the boot disk backplane in an Oracle Database Appliance Version 1 server module.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 boot disk backplane (BDB) serves as an interface between the motherboard and the rear-mounted disk drives.

The boot disk backplane is a FRU and can only be replaced by an Oracle-qualified service technician.

⚠ Caution

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.



Remove Boot Disk Backplane

How to remove the boot disk backplane from an Oracle Database Appliance Version 1 server node.

Install Boot Disk Backplane

How to install the boot disk backplane in an Oracle Database Appliance Version 1 server node.

Remove Boot Disk Backplane

How to remove the boot disk backplane from an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.


c. Remove the server node top cover.


See Removing the Server Node Top Cover.

2. Unseat the boot disk drives.

See Remove a Boot Drive.

- 3. Remove the boot disk backplane.
 - **a.** Disconnect the power and data cables [1] as shown in the following figure.







- b. Remove the four Phillips screws that secure the boot disk backplane to the rearmounted disk drives assembly and remove the backplane [2] as shown in the previous figure.
- 4. Place the boot disk backplane on an antistatic mat.

Install Boot Disk Backplane

How to install the boot disk backplane in an Oracle Database Appliance Version 1 server node.

① Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Install the boot disk backplane.
 - a. Position the boot disk backplane on the rear-mounted disk drives assembly and install and tighten the four Phillips screws to secure the backplane [2] as shown in the previous figure.
 - b. Reconnect the power cable and the data cables [1] as shown in the previous figure.
- 2. Return the server node to operation.
 - a. Re-seat the boot disk drives.

See Install a Boot Drive.

b. Install the server node top cover.

See Installing the Server Node Top Cover.

c. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

d. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Servicing the Power Distribution Board (FRU)

Learn about servicing the power distribution board in an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 power distribution board (PDB) distributes power from the power supplies to all system components.



The power distribution board is a FRU and can only be replaced by an Oracle-qualified service technician.

⚠ Caution

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

⚠ Caution

Equipment damage. Remove all power from the system before removing or installing the power distribution board. Power down both server nodes (also called system controllers) and disconnect the power cords from the system before performing these procedures. For instructions, see Shutting Down a Server Node and Powering Off the System.

- Remove Power Distribution Board

 How to remove the power distribution board from an Oracle Database Appliance Version 1.
- <u>Install Power Distribution Board</u>
 How to install the power distribution board in an Oracle Database Appliance Version 1.

Remove Power Distribution Board

How to remove the power distribution board from an Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Prepare the system for service.
 - a. Power off the system.

See Shutting Down a Server Node and Powering Off the System.

- **b.** Disconnect the power cords from the system.
- c. If the system is installed in a rack, remove it.

For information on racking the system chassis, see the *Oracle Database Appliance Owner's Guide*.

d. Remove both power supplies from the system.

See Remove a Power Supply.


e. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.



- 2. Remove both server nodes from the system.
 - See Removing Server Nodes From the System Chassis.
- 3. Remove the middle section of the system top cover.
 - See Removing the Middle Section of the System Top Cover.
- 4. Remove the power distribution board.
 - **a.** Disconnect the ribbon cable connector on the power distribution board [1] as shown in the following figure.

The ribbon cable is located between the power distribution board and the chassis side wall. It connects the power distribution board to the disk midplane.



b. Remove the two Phillips screws that secure the power distribution board to the chassis [2] as shown in the previous figure.

You access the screws through two holes in the side of the chassis.

c. Carefully remove the chassis interlock switch connector from the power distribution board [3] as shown in the previous figure.

To gain access to the chassis interlock switch connector, grasp the power distribution board with both hands, slide it to the rear of the system chassis to unplug it from the disk midplane module, and lift it up until you can grasp and remove the connector.

d. Lift the power distribution board out of the system chassis [4] as shown in the previous figure.



Place the power distribution board on the antistatic mat

Install Power Distribution Board


How to install the power distribution board in an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Install the power distribution board into the system chassis.
 - Lower the power distribution board partially into the system [1] as shown in the following figure.

Figure A-1 Installing the Power Distribution Board



- **b.** Reconnect the chassis interlock switch cable [2] as shown in the previous figure.
- c. Align the power distribution board with the two power connectors on the disk midplane module and slide the power distribution board forward until the connectors seat.



- d. To secure the power distribution board to the system, use the holes in the system side wall to access and tighten the two Phillips screws [3] as shown in the previous figure.
- e. Reconnect the power distribution board ribbon cable [4] as shown in the previous figure.
- 2. Return the system to operation.
 - a. Install both server nodes into the system.
 - See Installing a Server Node Into the System Chassis.
 - **b.** Install the middle section of the top cover.
 - Install and tighten the Phillips screws that secure the middle section of the top cover to the system chassis.
 - c. Install both power supplies into the system.
 - See **Install a Power Supply**.
 - d. If the system was installed in a rack, reinstall it into the rack.
 - See the Oracle Database Appliance Owner's Guide for instructions.
 - e. Reconnect the power cords to the system and power on the system.
 - See Powering On Oracle Database Appliance Version 1.

Servicing the Disk Midplane Module (FRU)

Learn about servicing the disk midplane module in an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 disk midplane interconnects the front disk drives to the server nodes, the front indicator modules, and the power distribution board (PDB).

The disk midplane board is a FRU and can only be replaced by an Oracle-qualified service technician.

∧ Caution

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.



Equipment damage. Remove all power from the system before removing or installing the power distribution board. Power down both server nodes (also called system controllers) and disconnect the power cords from the system before performing these procedures. For instructions, see Shutting Down a Server Node and Powering Off the System.

- Remove Disk Midplane Module

 How to remove the disk midplane module from an Oracle Database Appliance Version 1.
- Install Disk Midplane Module
 How to install the disk midplane module in an Oracle Database Appliance Version 1.

Remove Disk Midplane Module

How to remove the disk midplane module from an Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the system for service.
 - a. Power off the system.

See Shutting Down a Server Node and Powering Off the System.

- **b.** Disconnect the power cords from the system.
- c. If the system is installed in a rack, remove it.

See the *Oracle Database Appliance Owner's Guide* for information on racking the system chassis.

d. Remove both power supplies from the system.

See Remove a Power Supply.

e. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

2. Remove all of the front storage drives.

See Remove a Storage Drive.

Remove both server nodes from the system.

See Removing Server Nodes From the System Chassis.


4. Remove the middle section of the system top cover.

See Removing the Middle Section of the System Top Cover.

Loosen the two captive Phillips screws that secure the side-wall cover to the chassis and remove the cover.



The side-wall cover is positioned under the middle section of the system top cover. Before you can remove the side-wall cover, you must remove the middle section of the system top cover as shown in the following figure.




6. Remove the power distribution board.

See Remove Power Distribution Board.

- 7. Remove the disk midplane module.
 - a. Before disconnecting the two front indicator module (FIM) cable connectors from the disk midplane module, label them: the lower connector on the disk midplane is for SNO and the upper connector is for SN1.
 - **b.** Disconnect the two FIM cable connectors from the disk midplane module [1] as shown in the following figure.





- c. Remove the Phillips screw that secures the disk midplane module to the disk drive cage [2] as shown in the previous figure.
- d. To remove the disk midplane module from the system chassis, lift the board up about 0.25 inches (6.35 mm) to clear the standoffs that hold it in place [3] as shown in the previous figure.

To remove the board, you might need to move the bottom of the board away from the disk drive cage to disengage the standoff located at the top left corner of the board. Then, you should be able to lift the board up and out of the system.

There are four columns of standoffs, four in the left-most column and three in each of the remaining columns.

- e. Lift the disk midplane module up and out of the system [4] as shown in the previous figure.
- f. Place the board on an antistatic mat.




Install Disk Midplane Module

How to install the disk midplane module in an Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Install the disk midplane module.
 - a. Move the front indicator module (FIM) cable connectors toward the rear of the system so that the disk midplane module is not installed over them.
 - **b.** Lower the disk midplane module in the system chassis [1] as shown in the following figure.



c. Position the disk midplane module against the disk drive cage, tilting the top slightly forward so that it fits over the top-most standoff on the left side and then position board so that it fits over the remaining 12 standoffs, then push downward on the board to engage the standoffs [2] as shown in the previous figure.



- d. To secure the disk midplane module to the disk drive cage, install the Phillips screw [3] as shown in the previous figure.
- Reconnect the two FIM cable connectors to the receptacles on the disk midplane module [4] as shown in the previous figure.
 - Ensure that the FIM connectors are properly connected. The lower connector on the disk midplane is for SNO and the upper connector is for SN1.
- Install the power distribution board into the system.

See Install Power Distribution Board.

- Position the side-wall cover into the chassis and tighten the two captive Phillips screws to secure the side-wall cover to the chassis.
- Install the middle section of the system's top cover.
 - Install and tighten the Phillips screws that secure the middle section of the top cover to the system chassis.
- Reinstall all of the front storage drives.

See Install Storage Drive.

Install both server nodes into the system.

See Installing a Server Node Into the System Chassis.

- Return the system to operation.
 - Install both power supplies into the system.

See Install a Power Supply.

- If the system was installed in a rack, reinstall it into the rack.
 - See the Oracle Database Appliance Owner's Guide for instructions.
- Reconnect the power cords to the system and power on the system.

See Powering On Oracle Database Appliance Version 1.

Servicing the Disk Midplane Module HDD Cable (FRU)

Learn about servicing the disk midplane module HDD cable in an Oracle Database Appliance Version 1.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 HDD cable connects the power distribution board to the disk midplane module.

The disk midplane module HDD cable is a FRU and can only be replaced by an Oraclequalified service technician.



△ Caution

Equipment damage. Remove all power from the system before removing or installing the power distribution board. Power down both server nodes (also called system controllers) and disconnect the power cords from the system before performing these procedures. For instructions, see Shutting Down a Server Node and Powering Off the System.

Remove Disk Midplane Module HDD Cable

How to remove the disk midplane module HDD cable from an Oracle Database Appliance Version 1.

• Install Disk Midplane Module HDD Cable

How to install the disk midplane module HDD cable in an Oracle Database Appliance Version 1.

Remove Disk Midplane Module HDD Cable

How to remove the disk midplane module HDD cable from an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the system for service.
 - a. Power off the system.

See Shutting Down a Server Node and Powering Off the System.

- **b.** Disconnect the power cords from the system.
- **c.** If the system is installed in a rack, remove it.

See the Oracle Database Appliance Owner's Guide for instructions.

d. Attach an antistatic wrist strap.


See Performing Electrostatic Discharge and Antistatic Prevention Measures.

2. Remove the middle section of the system top cover.

See Removing the Middle Section of the System Top Cover.

3. Disconnect the HDD ribbon cable connector located on the power distribution board [1] as shown in the following figure.





4. Disconnect the HDD ribbon cable connector located on the disk midplane module [2] as shown in the previous figure.

Install Disk Midplane Module HDD Cable

How to install the disk midplane module HDD cable in an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Reconnect the HDD ribbon cable connector located on the disk midplane module [2]).
- 2. Reconnect the HDD ribbon cable connector located on the power distribution board [1].
- Return the system to operation.
 - Install the middle section of the system top cover.
 Install and tighten the Phillips screws that secure the middle section of the top cover to the system chassis.
 - b. If the system was installed in a rack, reinstall it into the rack.
 See the Oracle Database Appliance Owner's Guide for instructions.
 - Reconnect the power cords to the system and power on the system.
 See <u>Powering On Oracle Database Appliance Version 1</u>.

Servicing the Front Indicator Panels (FRU)

Learn about servicing the front indicator panel of an Oracle Database Appliance Version 1.



① Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 front indicator panels contain the LEDs and indicators on the front of the system. Each server node has its own front indicator panel, which sits behind the ears on the system chassis.

The front indicator panels are FRUs and can only be replaced by an Oracle-qualified service technician.

△ Caution

Equipment damage. Remove all power from the system before removing or installing the power distribution board. Power down both server nodes (also called system controllers) and disconnect the power cords from the system before performing these procedures. For instructions, see Shutting Down a Server Node and Powering Off the System.

- Remove Front Indicator Panel
 How to remove a front indicator panel from an Oracle Database Appliance Version 1.
- <u>Install Front Indicator Panel</u>
 How to install a front indicator panel in an Oracle Database Appliance Version 1.

Remove Front Indicator Panel

How to remove a front indicator panel from an Oracle Database Appliance Version 1.

(i) Note


Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the system for service.
 - a. Power off the system (both server nodes).
 See Shutting Down a Server Node and Powering Off the System.
 - **b.** Disconnect the power cords from the system.
 - c. If the system is installed in a rack, remove it.
 - See the *Oracle Database Appliance Owner's Guide* for information on racking the system chassis.
 - d. Attach an antistatic wrist strap.



See Performing Electrostatic Discharge and Antistatic Prevention Measures.

Remove the adjacent disk drives [1] as shown in the following figure.
 Be sure to mark them so that you can return them to the correct drive bays later.



- Unscrew the three Phillips screws from the back of the ear bezel [2] as shown in the previous figure.
- **4.** Remove four more Phillips screws from the inside of the drive bays [3] as shown in the previous figure.
- Remove the ear bezel [4] as shown in the previous figure.
 The ear bezel and indicator panels remain connected to the ribbon cables.
- **6.** Disconnect the ribbon cables from the indicator panel you wish to change [5] as shown in the previous figure.
- 7. Remove the screw that holds the indicator panel to the ear bezel [6] as shown in the previous figure.

Make sure you remove the correct indicator panel. There are two indicator panels on the ear bezel.




Install Front Indicator Panel

How to install a front indicator panel in an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

1. Use the Phillips screw to attach the new indicator panel to the ear bezel [1] as shown in the following figure.



2. Connect the ribbon cable to the indicator panel [2] as shown in the previous figure.



- 3. Place the ear bezel on the chassis [3] as shown in the previous figure.
- 4. Fasten the four Phillips screws inside the drive bays [4] as shown in the previous figure.
- Fasten the three Phillips screws on the back of the ear bezel [5] as shown in the previous figure.
- 6. Replace the disk drives in the drive bays [6] as shown in the previous figure.

Use the marks to ensure that you return each drive to its original bay.

- 7. Return the system to operation.
 - a. Reinstall the system into the rack.

See the Oracle Database Appliance Owner's Guide for instructions.

b. Reconnect the power cords to the system and power on the system.

See Powering On Oracle Database Appliance Version 1.

Servicing Server Node Cables

Perform tasks for servicing the Oracle Database Appliance Version 1 server node cables.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The internal server node cables are FRUs and can only be replaced by an Oracle-qualified service technician.



Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

- Servicing Fan Power Cables (FRU)
 - Learn about servicing fan cables in an Oracle Database Appliance Version 1 server node.
- Servicing the HBA PCIe Card Cables (FRU)

Learn about servicing HBA PCIe card cables in an Oracle Database Appliance Version 1 server node.

- Servicing the SAS Expander Cable (FRU)
 - Learn about servicing SAS expander cables in an Oracle Database Appliance Version 1 server node.
- Servicing the Boot Disk Backplane Cables (FRU)
 Learn about servicing boot disk backplane cables in an Oracle Database Appliance Version 1.



Servicing Fan Power Cables (FRU)

Learn about servicing fan cables in an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Each Oracle Database Appliance Version 1 server node has two fans and each fan has a separate power cable.

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

- Remove Fan Power Cables
 How to remove fan cables in an Oracle Database Appliance Version 1 server node.
- <u>Install Fan Power Cables</u>
 How to install fan cables in an Oracle Database Appliance Version 1 server node.

Remove Fan Power Cables

How to remove fan cables in an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.


Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

c. Remove the server node top cover.

See Removing the Server Node Top Cover.



2. Disconnect the fan power cables [1] and remove them from the server node [2] as shown in the following figure.



Install Fan Power Cables

How to install fan cables in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Reconnect the fan power cables.
- 2. Return the server node to operation.
 - a. Install the server node top cover.

See <u>Installing the Server Node Top Cover</u>.

b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Servicing the HBA PCIe Card Cables (FRU)

Learn about servicing HBA PCIe card cables in an Oracle Database Appliance Version 1 server node.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 PCle card cables are used to connect the internal PCle card, the primary HBA and a riser-mounted PCle card, and the secondary HBA to the motherboard. See the following sections for instructions.

The PCIe card cables are FRUs and can only be replaced by an Oracle-qualified service technician.

△ Caution

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

- Remove PCIe Card Cables From Primary HBA PCIe Card
 How to remove the primary HBA cables in an Oracle Database Appliance Version 1 server node.
- Install PCIe Card Cables From Primary HBA PCIe Card
 How to install the primary HBA cables in an Oracle Database Appliance Version 1 server node.
- Remove PCIe Card Cables From Secondary HBA PCIe Card
 How to remove the secondary HBA cables in an Oracle Database Appliance Version 1 server node.
- Install PCIe Card Cables From Secondary HBA PCIe Card
 How to install the secondary HBA cables in an Oracle Database Appliance Version 1 server node.

Remove PCIe Card Cables From Primary HBA PCIe Card

How to remove the primary HBA cables in an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - a. Attach an antistatic wrist strap.



See Performing Electrostatic Discharge and Antistatic Prevention Measures.


b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

c. Remove the server node top cover.

See Removing the Server Node Top Cover.

- 2. Disconnect the primary HBA PCIe card cables and remove them from the server node.
 - **a.** Loosen the three green, captive Phillips screws that secure the server node's front cover and remove the cover [1] as shown in the following figure.



b. Disconnect the two cables from the primary HBA PCIe card and remove the cables [2] as shown in the previous figure.

To remove each cable connector, push the connector inward, press down on the connector to release it, and pull the connector out.

Install PCIe Card Cables From Primary HBA PCIe Card

How to install the primary HBA cables in an Oracle Database Appliance Version 1 server node.

① Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Reconnect the PCIe card cables.
 - a. Reconnect the two PCIe card cables to the primary HBA PCIe card and the connectors on the motherboard [2].



Notice that there are two sets of connectors on the motherboard. Be sure to connect the cables to the connector on the right in each set (looking at the connectors from the rear of the server node).

- b. Position the server node's front cover onto the server node and tighten the three green, captive Phillips screws that secure the server node's front cover to the motherboard [1].
- Return the server node to operation.
 - a. Install the server node top cover.

See Installing the Server Node Top Cover.

b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Remove PCIe Card Cables From Secondary HBA PCIe Card

How to remove the secondary HBA cables in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

Remove the server node top cover.


See Removing the Server Node Top Cover.

Disconnect the PCIe card cables and remove them from the server node.

The Secondary HBA PCIe Card sits in the top slot on the PCIe riser (PCIe slot 2)

a. Loosen the three green, captive Phillips screws that secure the server node's front cover and remove the cover [1] as shown in the following figure.





b. Disconnect the two secondary HBA PCIe card cables and remove the cables [2] as shown in the previous figure.

To remove each cable connector, push the connector inward, press down on the connector to release it, and pull the connector out.

Install PCIe Card Cables From Secondary HBA PCIe Card

How to install the secondary HBA cables in an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Reconnect the PCIe card cables.
 - a. Reconnect the two PCIe card cables between to the secondary PCIe card and the connectors on the motherboard [2].
 - The Secondary HBA PCIe Card sits in the top slot on the PCIe riser (PCIe slot 2)
 - Notice that there are two sets of connectors on the motherboard. Be sure to connect the cables to connector on the left in each set (looking at the connectors from the rear of the server node).
 - b. Position the server node's front cover onto the server node and tighten the three green, captive Phillips screws that secure the server node's front cover to the motherboard [1].
- 2. Return the server node to operation.
 - a. Install the server node top cover.
 - See Installing the Server Node Top Cover.
 - **b.** Install the server node into the system.



See Installing a Server Node Into the System Chassis.

c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Servicing the SAS Expander Cable (FRU)

Learn about servicing SAS expander cables in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The SAS expander cable is a FRU and can only be replaced by an Oracle-qualified service technician.

∴ Caution

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

Remove SAS Expander Cable

How to remove the SAS expander cable in an Oracle Database Appliance Version 1 server node.

Install SAS Expander Cable

How to install the SAS expander cable in an Oracle Database Appliance Version 1 server node.

Remove SAS Expander Cable

How to remove the SAS expander cable in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.



b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.


c. Remove the server node top cover.

See Removing the Server Node Top Cover.

d. Remove the PCIe riser.

See Remove PCIe Riser From Server Nodes.

- 2. Disconnect the SAS expander cable and remove it from the server node.
 - a. Loosen the three green, captive Phillips screws that secure the server node's front cover and remove the cover [1] as shown in the following figure.



b. Disconnect both cable connectors from the motherboard and remove the cable [2] as shown in the previous figure.

Push the connector inward, press down on the connector to release it, and pull the connector out.

Install SAS Expander Cable

How to install the SAS expander cable in an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Reconnect the SAS expander cable.
 - a. Reconnect the SAS expander cable connectors to the motherboard [2].



- b. Position the server node's front cover onto the server node and tighten the three green, captive Phillips screws that secure the server node's front cover to the motherboard [1].
- 2. Return the server node to operation.
 - a. Install the PCIe riser.

See Install PCIe Riser in Server Nodes.

b. Install the server node top cover.

See Installing the Server Node Top Cover.

c. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

d. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Servicing the Boot Disk Backplane Cables (FRU)

Learn about servicing boot disk backplane cables in an Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The SAS expander cable is a FRU and can only be replaced by an Oracle-qualified service technician.

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

Remove Boot Disk Backplane Cables

How to remove the boot disk backplane cables in an Oracle Database Appliance Version 1 server node.

Install Boot Disk Backplane Cables

How to install the boot disk backplane cables in an Oracle Database Appliance Version 1 server node.




Remove Boot Disk Backplane Cables

How to remove the boot disk backplane cables in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Prepare the server node for service.
 - a. Attach an antistatic wrist strap.
 - See <u>Performing Electrostatic Discharge and Antistatic Prevention Measures</u>.
 - **b.** Remove the server node from the system.
 - Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.
 - c. Remove the server node top cover.
 - See Removing the Server Node Top Cover.
- Disconnect the power cable and hard disk drive (HDD) cables and remove them from the server node.
 - a. Disconnect the power cable and HDD cables from the motherboard [1] as shown in the following figure.



b. Disconnect the power cable and HDD cables from the boot disk backplane [2] as shown in the previous figure.



Install Boot Disk Backplane Cables

How to install the boot disk backplane cables in an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- 1. Reconnect the power cable and hard disk drive (HDD) cables.
 - a. Reconnect the power cable and HDD cables to the boot disk backplane [2].
 - b. Reconnect the power cable and HDD cables to the motherboard [1].
- 2. Return the server node to operation.
 - a. Install the server node top cover.

See Installing the Server Node Top Cover.

b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Servicing the Motherboard Assembly (FRU)

Learn about servicing the motherboard in an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Each Oracle Database Appliance Version 1 server node has a motherboard assembly. The service strategy for the motherboard is to remove the replaceable components from the server node and then return the server node with the motherboard in place to Oracle for repair or replacement.


The motherboard assembly is a FRU and can only be replaced by Oracle Service personnel.



⚠ Caution

Equipment damage. These procedures require that you handle components that are sensitive to static discharge. This sensitivity can cause the component to fail. To avoid damage, ensure that you follow antistatic practices.

The following figure shows the components that must be removed from the server node.



Callout	Description
1	CPUs and Heatsinks
2	Memory modules (DIMMs)
3	PCIe Cards mounted on the PCIe Riser
4	PCIe Riser
5	Fan Modules (2)
6	Internally Mounted PCIe Card
7	Boot Disk Drives (2)
8	Boot Disk Drive Backplane
9	Battery

• Remove Replaceable Components From Motherboard Assembly

How to remove components from a server node in order to replace the motherboard assembly in an Oracle Database Appliance Version 1.



Install Replaceable Components in Motherboard Assembly

How to install components from a server node to a new motherboard assembly in an Oracle Database Appliance Version 1.

Remove Replaceable Components From Motherboard Assembly

How to remove components from a server node in order to replace the motherboard assembly in an Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Prepare the server node for service.
 - Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.

Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

c. Remove the server node top cover.

See Removing the Server Node Top Cover.

2. With the exception the SAS expander cable, disconnect and remove all internal cables from the server node.

(i) Note

To identify the SAS expander cable, see **Install SAS Expander Cable**.

The cables for the fans, the primary and secondary HBA PCIe cards, and the boot disk backplane must be removed.

Fan power cables

See Remove Remove Fan Power Cables.

Primary HBA PCIe card data cables

See Remove PCIe Card Cables From Primary HBA PCIe Card.

Secondary HBA PCIe card data cables

See Remove PCIe Card Cables From Secondary HBA PCIe Card.



⚠ Caution

Equipment damage. The HBA data cables are delicate. Ensure that they are removed and safely out of the way when servicing the motherboard.

Boot disk board cables.

See Remove Boot Disk Backplane Cables.

- 3. Remove the following components from the server node.
 - Fan modules

Remove a Fan Module.

Boot disk drives

Remove a Boot Drive.

Boot disk drive backplane

Remove Boot Disk Backplane.

Memory modules (DIMMS)

Remove Faulty DIMMs.

PCIe riser and attached PCIe cards

Remove PCIe Riser From Server Nodes.

CPUs

Remove Processor (CPU).

Internal primary HBA PCIe card

Remove Primary HBA PCIe Card From Motherboard.

Battery

Remove Battery.

Install Replaceable Components in Motherboard Assembly

How to install components from a server node to a new motherboard assembly in an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

1. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

- 2. Install the following components into the server node.
 - Fan modules



See Install a Fan Module.

Boot disk drives

See Install a Boot Drive.

Memory modules (DIMMS)

See Install DIMMs.

PCIe riser and attached PCIe cards

See Install PCIe Riser in Server Nodes.

CPUs

See Install Processor (CPU).

Internal primary HBA PCIe card

See Install Primary HBA PCIe Card in Motherboard.

- Reconnect and install the following cables.
 - Fan module power cables.

See Servicing the Fan Power Cables (FRU).

Internal PCIe card data cables.

See Servicing the PCIe Card Cables (FRU).



Equipment damage. The disk drive data cables are delicate. Handle them carefully.

Boot disk backplane cables.

See Servicing the Boot Disk Backplane Cables (FRU).

- Return the server node to operation.
 - a. Install the server node top cover.

See <u>Installing the Server Node Top Cover</u>.

b. Install the server node into the system.

See Installing a Server Node Into the System Chassis.

- c. Reconnect all external data cables from the PCIe card(s) that are installed in the PCIe riser.
- d. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

Returning the Appliance to Operation

Perform tasks for returning the Oracle Database Appliance Version 1 to operation after servicing.





Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

This section describes returning Oracle Database Appliance Version 1 to operation after servicing.

- <u>Installing the Server Node Top Cover</u>
 Learn about replacing an Oracle Database Appliance Version server node top cover.
- Installing a Server Node Into the System Chassis
 Learn about installing an Oracle Database Appliance Version 1 server node in the chassis.
- <u>Powering On Oracle Database Appliance Version 1</u>
 Learn about powering on an Oracle Database Appliance Version 1.

Installing the Server Node Top Cover

Learn about replacing an Oracle Database Appliance Version server node top cover.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

⚠ Caution

Hazardous voltage present. Do not run the system with the top cover removed.

⚠ Caution

Equipment damage. Install the top cover properly before starting the system.

If you removed the top cover from an Oracle Database Appliance Version 1 server node, perform the following procedure to replace it.

<u>Install Server Node Top Cover</u>
 How to install a top cover for an Oracle Database Appliance Version 1 server node.



Install Server Node Top Cover


How to install a top cover for an Oracle Database Appliance Version 1 server node.




Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

1. Place the top cover down on the server node [1] as shown in the following figure.

The cover should hang over the front of the chassis by 0.5 inches (12.7 mm) and all six of the standoffs on the underside of the cover (three on each side) should fit into the slots on the top of the chassis side walls.





2. Slide the top cover toward the rear of the server node until it seats [2] as shown in the previous figure.

Installing a Server Node Into the System Chassis

Learn about installing an Oracle Database Appliance Version 1 server node in the chassis.

① Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

If you removed a server node from an Oracle Database Appliance Version 1, perform the following procedure to reinstall it.

<u>Install Server Node Into System Chassis</u>
 How to install a server node into an Oracle Database Appliance Version 1 chassis.



Install Server Node Into System Chassis

How to install a server node into an Oracle Database Appliance Version 1 chassis.


(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

(i) Note

Replacing a server node FRU with a new server node is a service activity that must be performed by an Oracle-qualified service technician. The customer may remove the server node to service other customer serviceable components in the server node.

- 1. Before inserting the server node into the system chassis, ensure that both release latches on the rear of the server node are in the open position.
- 2. Slide the server node into the rear of the system chassis [1] until the server node is close enough for its release latches come in contact with and engage the chassis [2] as shown in the following figure.





To re-seat the server node in the system chassis, grasp both release latches, one on each side of the server node, and push them upward simultaneously to the closed position [3] as shown in the previous figure.

Equipment damage. Always use the release latches to re-seat the server node into the system chassis as described in this procedure. Failure to do so might damage the connectors on the front of the server node and/or the connectors on the disk midplane module.

4. Reinstall the system chassis into the rack.

Follow the instructions listed in the "Inserting Oracle Database Appliance Version 1 Into a Rack" section in the Oracle Database Appliance Owner's Guide.

Powering On Oracle Database Appliance Version 1

Learn about powering on an Oracle Database Appliance Version 1.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Each server node is powered on separately.



(i) Note

To use Oracle ILOM to power on a server node, ensure that you have performed its initial configuration as described in "Connecting and Configuring Oracle ILOM" in the Oracle Database Appliance Getting Started Guide.

Power On Oracle Database Appliance Version 1 How to power on an Oracle Database Appliance Version 1.

Power On Oracle Database Appliance Version 1

How to power on an Oracle Database Appliance Version 1.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.



① Note

Replacing a server node FRU with a new server node is a service activity that must be performed by an Oracle-qualified service technician. The customer may remove the server node to service other customer serviceable components in the server node.

 Ensure that the power cord (or cords) are connected to the power supplies on the rear of the server node that was serviced.

Once plugged in, the server node goes into the standby power state. The SP status LED on the front panel of the server node lights green and goes from slow blink to steady on. The Power/OK LED on the front panel of the server node lights green and goes to standby blink. It might take about five minutes for the LED to reach standby blink after the power cord is inserted.

For the location of the SP status LED and Power/OK LED, see <u>Oracle Database Appliance</u> Version 1 Status Indicators.


Standby power state indicates that the server node's service processor is active, but the server node host is powered off.

2. Power on a server node by performing one of the following procedures:

(i) Note

If you powered off a single server node without shutting down the appliance, perform this step only for that server node. If you shut down the appliance completely, then perform this step for both server nodes.

Using the server node's Power button: Momentarily press and release the recessed Power button on the front panel [1] as shown in the following figure.





On the server node, the green Power/OK LED (see [2] in the previous figure) blinks while the server node is booting, and remains steady on when the server node is operational.

- Using the Oracle ILOM web interface:
 - a. Open a browser and enter the server node's service processor IP address in the browser's address field.
 - **b.** At the log in page, type a user name (the account must have Reset and Host Control (r) privileges) and password, and click the Log In button.
 - **c.** Go to Remote Power Control and select **Power On** from the Select Action list box and then click Save and OK.

On the server node, the green Power/OK LED [2] blinks while the server node is booting, and remains steady on when the server node is operational.

- Using the Oracle ILOM CLI:
 - a. Log in to Oracle ILOM using an ssh client. Type:

```
$ ssh username@sp_ip_address
```

Where username is a user account name with Reset and Host Control (r) privileges and $sp_ip_address$ is the IP address of the server node service processor.

- **b.** When prompted, enter the user account password.
- c. Enter the command to power on the server node:

```
-> start /SYS
```

On the server node, the green Power/OK LED [2] blinks while the server node is booting, and remains steady on when the server node is operational.

Server Node Basic Input/Output System (BIOS)

Learn about the Oracle Database Appliance Version 1 BIOS.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

This section describes the Oracle Database Appliance Version 1 BIOS utility.

All settings are set to the optimal defaults at startup.

You should not configure system BIOS settings. Oracle Database Appliance patch software will do this for you. The only time you might need to configure BIOS settings would be if requested to do so by Oracle Service.



BIOS Booting and Setup

Learn about the power-on sequence and tests performed by BIOS during Oracle Database Appliance Version 1 bootup.

Clearing Server Node CMOS NVRAM

Learn about clearing CMOS for an Oracle Database Appliance Version 1 server node.

Ethernet Port Naming and Boot Order

Learn about Ethernet port naming and boot order for an Oracle Database Appliance Version 1.

Configuring Support for TPM

Learn about Trusted Platform Module for an Oracle Database Appliance Version 1 server node.

Configuring SP LAN Settings

Learn about configuring the service processor LAN settings for an Oracle Database Appliance Version 1 server node.

Configuring Option ROM Settings in BIOS

Learn about configuring option ROM for an Oracle Database Appliance Version 1 server node.

BIOS Setup Utility Hot Keys

Learn about BIOS Setup hot keys for an Oracle Database Appliance Version 1.

Accessing the BIOS Setup Utility Menus

Learn how to access BIOS Setup for an Oracle Database Appliance Version 1 server node.

BIOS Setup Utility Screens

Learn about BIOS Setup utility screens for an Oracle Database Appliance Version 1 server node.

BIOS Booting and Setup

Learn about the power-on sequence and tests performed by BIOS during Oracle Database Appliance Version 1 bootup.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Default BIOS Power-On Self-Test (POST) Events

Learn about the default POST events for an Oracle Database Appliance Version 1.

• BIOS POST F1 and F2 Errors

Learn about POST F1 and F2 errors for an Oracle Database Appliance Version 1.

How BIOS POST Memory Testing Works

Learn about POST memory tests for an Oracle Database Appliance Version 1.



Default BIOS Power-On Self-Test (POST) Events

Learn about the default POST events for an Oracle Database Appliance Version 1.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

When an Oracle Database Appliance Version 1 server node (also called a system controller) starts, the BIOS performs a power-on self-test that checks the hardware to ensure that all components are present and functioning properly. The following table identifies the events that can occur during BIOS POST, as well as specifies whether these events can prevent the host from powering-on.

Event	Cause	Boot Continues on Host?
User password violation	Attempt to enter password fails three times	No
Setup password violation	Attempt to enter password fails three times	No
Correctable ECC	Memory Correctable ECC (error correction code) error is detected	Does not apply
Uncorrectable ECC	Memory Uncorrectable ECC error is detected	Does not apply
No system memory	No physical memory is detected in the system	No
No usable system memory	All installed memory has experienced an unrecoverable failure	No
Hard disk controller failure	No disk controller is found	Yes
Keyboard failure	Keyboard cannot be initialized	Yes
Boot media failure	No removable boot media is found	Yes
No video device	No video controller is found	No
Firmware (BIOS) ROM corruption	BIOS checksum fails and the boot block is not corrupted	No
System restart	System boot is initiated	Yes
Initiated by hard reset	Boot process is started by hard reset	Yes
Memory initialization	Memory sizing is occurring System firmware progress	Does not apply
Primary processor initialization	Primary CPU initialization System firmware progress	Does not apply
Initiated by warm reset	Boot process is started by warm reset	Does not apply
Embedded controller management	Management controller initialization	Does not apply



Event	Cause	Boot Continues on Host?
Secondary processor(s) initialization	Secondary CPU initialization asserted System firmware progress	Does not apply
Video initialization	When BIOS initializes keyboard	Does not apply
Keyboard controller initialization	When BIOS initializes keyboard	Does not apply
Option ROM initialization	BIOS initializes Option ROMs System firmware progress	Does not apply
Option ROM space exhausted	BIOS cannot install an Option ROM (typically a plug-in card driver) into memory from that device preventing booting	Yes
User initiated system set up	User initiated access to BIOS Setup Utility	Does not apply
	System firmware progress	
User initiated boot to OS	System boot is initiated System firmware progress	Does not apply
No bootable media	No media from which to boot	No
PXE server not found	Boot error - PXE server not found	No. BIOS tries next
	F12 key was pressed but BIOS fails to boot from PXE server	boot device.
ACPI Power state	Soft-off power applied	Does not apply

BIOS POST F1 and F2 Errors

Learn about POST F1 and F2 errors for an Oracle Database Appliance Version 1.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Each Oracle Database Appliance Version 1 power-on-self-test (POST) diagnostic is a low-level test designed to detect faults in a specific hardware component. If the POST diagnostic discloses an F1 or F2 error, it typically reports the following information about the error:

- Type of error detected
- When or where the error occurred

The following table lists some of the F1 and F2 error messages that could appear during the POST diagnostics along with instructions for how to possibly resolve the error reported.

BIOS POST Error Message	Error Type	Resolution
Uncorrectable Error Detected on Last Boot:IOH(0) Protocol Error (Please Check SP Log for more Details)	IOH error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details.



BIOS POST Error Message	Error Type	Resolution
Uncorrectable Error Detected on Last Boot:IOH(0) QPI [x] Error (Please Check SP Log for more Details)	IOH error	 Press F1 to continue. Check the fault management function and the SP event log in Oracle ILOM for more details. Where QPI [x] equals 0 for QPI Link 0 or 1 for QPI Link 1.
Uncorrectable Error Detected on Last Boot:IOH(0) PCI-E [x] Error (Please Check SP Log for more Details)	IOH error	 Press F1 to continue. Check the fault management function and the SP event log in Oracle ILOM for more details. Where PCI-E [x] port number can range from 1
Uncorrectable Error Detected on Last Boot:IOH(0) ESI Error (Please Check SP Log for more Details)	IOH error	 to 10 depending on the PCI root port on IOH. Press F1 to continue. Check the fault management function and the SP event log in Oracle ILOM for more details.
Uncorrectable Error Detected on Last Boot:IOH(0) Thermal Error (Please Check SP Log for more Details)	IOH error	 Press F1 to continue. Check the fault management function and the SP event log in Oracle ILOM for more details.
Uncorrectable Error Detected on Last Boot:IOH(0) DMA Error (Please Check SP Log for more Details)	IOH error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details.
Uncorrectable Error Detected on Last Boot:IOH(0) Miscellaneous Error (Please Check SP Log for more Details)	IOH error	 Press F1 to continue. Check the fault management function and the SP event log in Oracle ILOM for more details.
Uncorrectable Error Detected on Last Boot:IOH(0) VTd Error (Please Check SP Log for more Details)	IOH error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details.
BMC Not Responding	Oracle ILOM error	 Press F1 to continue. This error message might display if during the SP/BIOS communication an internal error occurs. This error might require you to restart the SP.
 Primary Slave Hard Disk Error Primary Master Hard Disk Error Secondary Master Hard Disk Error Secondary Slave Hard Disk Error These error messages are not supported on Oracle Database Appliance. 	IDE/ATAPI error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details. These type of error messages display when the BIOS is attempting to configure IDE/ATAPI devices in POST.
Timer Error	8254 timer error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details. This type of error typically indicates an error while programming the count register of channel 2 of the 8254 timer. This could indicate a problem with system hardware.



BIOS POST Error Message	Error Type	Resolution
RAM R/W test failed	Memory test failure	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details. This type of error typically indicates that the RAM read/write test failed.
KBC BAT Test failed	Keyboard controller basic assurance test error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details. Keyboard controller BAT test failed. This error might indicate a problem with keyboard controller initialization.
Display memory test failed	Video display error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details.
CMOS Battery Low	CMOS battery error	 Press F2 to enter BIOS Setup Utility to load system defaults. Check the SP event log in Oracle ILOM for more details. If necessary, replace CMOS battery.
CMOS Checksum BadCMOS Date/Time Not Set	CMOS error	 Press F2 to enter BIOS Setup Utility to load system defaults. Check the SP event log in Oracle ILOM for more details.
Password check failed	Password check error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details. This type of error indicates that the password entered does not match the password specified in the BIOS Setup Utility. This condition might occur for both Supervisor and User password verification.
Keyboard/Interface Error	Keyboard controller error	 Press F1 to continue. Check the SP event log in Oracle ILOM for more details. This type of error indicates that the Keyboard Controller failure. This error might indicate a problem with system hardware.
S.M.A.R.T error on the drive	S.M.A.R.T device error	•

How BIOS POST Memory Testing Works

Learn about POST memory tests for an Oracle Database Appliance Version 1.





Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS POST memory testing is performed as follows:

- 1. The first megabyte of DRAM is tested by the BIOS before the BIOS code is copied from ROM to DRAM.
- 2. After existing out of DRAM, the BIOS performs a simple memory test (where a write/read of every location with the pattern 55aa55aa is performed).



The simple memory test is performed only if Quick Boot is not enabled from the Boot Settings Configuration screen. Enabling Quick Boot causes the BIOS to skip the memory test.

The BIOS polls the memory controllers for both correctable and non-correctable memory errors and logs those errors into the SP.

Clearing Server Node CMOS NVRAM

Learn about clearing CMOS for an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

You can clear the CMOS NVRAM by pressing the CLR CMOS button on the Oracle Database Appliance Version 1 server node motherboard. This action sets the BIOS to defaults values, which clears the BIOS user and supervisor passwords.

You can also set or reset the BIOS password from the BIOS Setup Utility. See <u>BIOS Security Menu Screen</u> for more information.

Data loss. You should not perform this procedure unless instructed to do so by Oracle Service.



Reset BIOS Password and Clear CMOS NVRAM Using CLR CMOS Button
 How to clear CMOS in an Oracle Database Appliance Version 1 server node.

Reset BIOS Password and Clear CMOS NVRAM Using CLR CMOS Button

How to clear CMOS in an Oracle Database Appliance Version 1 server node.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

(i) Note

Clearing CMOS of a server node is a service activity that must be performed by an Oracle-qualified service technician. The customer may perform the procedure if directed to do so by Oracle Service.

- 1. Prepare the server node for service.
 - a. Attach an antistatic wrist strap.

See Performing Electrostatic Discharge and Antistatic Prevention Measures.

b. Remove the server node from the system.


Power is removed from the server node when you remove it from the system. See Removing Server Nodes From the System Chassis.

c. Remove the server node top cover.

See Removing the Server Node Top Cover.

2. Using a stylus, press and release the CLR CMOS button as shown in the following figure.





- 3. Return the server node to operation.
 - a. Install the server node top cover.

See Installing the Server Node Top Cover.

- b. Install the server node into the system.
 - See Installing a Server Node Into the System Chassis.
- c. Power on the server node.

See Powering On Oracle Database Appliance Version 1.

When the server node powers on and boots, it displays a message that indicates that NVRAM has been cleared.

The CMOS NVRAM, including the BIOS password is cleared to its default state.

The default state for the BIOS passwords is that no password is required. To set a BIOS password, see <u>BIOS Security Menu Screen</u>.

4. Verify that the Power/OK LED is lit on the server node.

Ethernet Port Naming and Boot Order

Learn about Ethernet port naming and boot order for an Oracle Database Appliance Version 1.

Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.



Each Oracle Database Appliance Version 1 server node supports two 10/100/1000Base-T Gigabit Ethernet ports on the rear of the chassis. For port locations, see the *Oracle Database* Appliance Owner's Guide.

The device naming for the Ethernet interfaces is reported differently by different interfaces and operating systems. See the following table for the physical (BIOS) and logical (operating system) naming conventions used for each interface.

Interface	NET0	NET1
BIOS	NET0	NET1
Oracle Linux	eth0	eth1

The order in which the BIOS detects the Ethernet ports during boot time, and the corresponding drivers that control those ports, are listed below:

- NET 0 (INTEL NIC 0)
- 2. NET 1 (INTEL NIC 1)

Configuring Support for TPM

Learn about Trusted Platform Module for an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

If you intend to use the Oracle Database Appliance Version 1 Trusted Platform Module (TPM) feature set, you must configure the server node to support this feature.

TPM enables you to administer the TPM security hardware in your server node. For additional information about implementing this feature, see the Trusted Platform Module Management documentation.

Configure TPM Support in BIOS How to configure TPM in an Oracle Database Appliance Version 1 server node.

Configure TPM Support in BIOS

How to configure TPM in an Oracle Database Appliance Version 1 server node.



(i) Note


Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.



Access the BIOS Setup Utility menus.

For instructions, see Accessing the BIOS Setup Utility Menus.

When BIOS is started, the main BIOS Setup Utility top-level System Overview screen appears. See the following figure for an example:



2. In the BIOS Setup Utility screen, select the Advanced menu option.


The Advanced Settings screen appears. See the following figure for an example:



3. In the Advanced Settings screen, select Trusted Computing and press Enter.

The Trusted Computing screen appears. See the following figure for an example:






- In the Trusted Computing screen, select the TCG/TPM Support.
 A pop-up dialog box appears.
- 5. In the pop-up dialog box, set the TCG/TPM Support option to Yes and click OK.

Note

Even if the TCG/TPM Support was already set to Yes in the dialog shown above, continue on and complete the remaining steps of this procedure to ensure that all TPM configuration requirements are satisfied.

The updated Trusted Computing dialog appears and shows that the TCG/TPM Support setting has changed to Yes. See the following figure for an example:








(i) Note

In the above screen, the Execute TPM Command setting shows the default, Don't Change.


- 6. In the Trusted Computing screen, select the Execute TPM Command option setting. A pop-up dialog box appears.
- 7. In the pop-up dialog box, set the Execute TPM Command option to Enabled and click OK.

The updated Trusted Computing screen appears and shows that the Execute TPM Command setting has changed to Enabled. See the following figure for an example:



- Press F10 to save the changes and exit the BIOS Setup Utility.
- To verify that TPM support is configured, do the following:
 - Reboot the server node.
 - b. To enter the BIOS Setup Utility, press the F2 key while the system is performing the power-on self-test (POST).
 - When BIOS is started, the main BIOS Setup Utility top-level screen appears.
 - c. Select Advanced, then select Trusted Computing and press Enter.
 - The updated Trusted Computing screen appears.
 - Confirm that the TCG/TPM Support setting is set to Yes and the TPM Enabled/Disable Status is set to Enabled. See the following figure for an example:





10. Press F10 to exit the BIOS Setup Utility.

This completes the TPM configuration.

Configuring SP LAN Settings

Learn about configuring the service processor LAN settings for an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

You can assign an IP address for the Oracle Database Appliance Version 1 server node SP from the BIOS Setup Utility on the IPMI LAN configuration menu. Alternatively, you can also specify the LAN settings for the SP using Oracle ILOM. For instructions for setting the IP address in Oracle ILOM, see *Oracle Integrated Lights Out Manager (Oracle ILOM)* 3.0 Documentation Collection.

Configure LAN Settings for SP
 How to configure SP LAN settings in an Oracle Database Appliance Version 1 server node.



Configure LAN Settings for SP

How to configure SP LAN settings in an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

Access the BIOS Setup Utility menus.

For instructions, see Accessing the BIOS Setup Utility Menus.

- In the BIOS Setup Utility menus, use the arrow keys (or Tab key) to navigate to the Advanced menu.
- In the Advanced menu, select IPMI Configuration.
- 4. In the IPMI Configuration menu, select LAN Configuration.

The LAN Configuration screen appears.

5. In the LAN Configuration screen, use the arrow keys to select and specify the appropriate LAN configuration settings. See the following figure for an example:



- 6. After making the necessary changes, select Commit and press Enter to apply the changes.
- 7. Press F10 to save the changes and exit BIOS.

Configuring Option ROM Settings in BIOS

Learn about configuring option ROM for an Oracle Database Appliance Version 1 server node.





Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS Option ROM space is 128 Kbytes. Of these 128 Kbytes, approximately 80 Kbytes are used by the VGA controller, the disk controller, and the network interface card. Approximately 48 Kbytes remain to be shared by the Option ROMs on all bootable PCI-Express plug-in cards.

Enable or Disable Option ROM Settings
 How to configure option ROM settings in an Oracle Database Appliance Version 1 server node.

Enable or Disable Option ROM Settings

How to configure option ROM settings in an Oracle Database Appliance Version 1 server node.



Information in this section ONLY applies to the Oracle Database Appliance Version1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011),refer to the preceding chapters in this document for information on servicing yourOracle Database Appliance model.

1. Access the BIOS Setup Utility menus.

For instructions, see Accessing the BIOS Setup Utility Menus.

In the BIOS Setup Utility menus, use the arrow keys (or Tab key) to navigate to the Boot menu.

The Boot menu appears. See the following figure for an example:



3. In the Boot menu, highlight the Option ROM setting, and then press Enter.



- 4. Check whether the settings in your screen output match what is shown above. If they do not match, proceed to the next step. If they match, proceed to Step 7 and exit BIOS.
- 5. To change the settings, in the Boot menu listing the Option ROM settings, highlight the applicable Option ROM setting to modify, then press Enter.

A dialog box appears listing the available settings.

- 6. In the dialog box, do one of the following:
 - Select Enabled to enable the Option ROM setting.
 - Select Disabled to disable the Option ROM setting.
- 7. Press F10 to save the changes and exit the BIOS Setup Utility.

BIOS Setup Utility Hot Keys

Learn about BIOS Setup hot keys for an Oracle Database Appliance Version 1.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The following table provides a description of the Oracle Database Appliance Version 1 BIOS Setup Utility Oracle ILOM Remote Console keys and the directly attached keyboard keys, and the corresponding serial connection key combinations.

Oracle ILOM Remote Console	Serial Connection Hot Key	Function
F1	Ctrl+Q (Press and hold the Control key and type Q)	Access the BIOS Setup Utility if there is an error during the boot process.
F2	Ctrl+E	Enter BIOS Setup Utility when the system has completed the power- on self-test (POST).
F7	Ctrl+D	Discard changes, but do not exit.
F8	Ctrl+P	Select the BBS Popup menu, which allows you to select a boot device.
F9	Ctrl+O	Load optimal BIOS defaults.
F10 Note that F10 is not supported on the Oracle ILOM Remote Console; instead, use the arrow keys to navigate to the Exit menu and press Enter.	Ctrl+S	Save changes and exit.
F12	Ctrl+N	Boot the server node from the network (PXE boot).



Accessing the BIOS Setup Utility Menus

Learn how to access BIOS Setup for an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

You can access Oracle Database Appliance Version 1 BIOS Setup Utility screens from the following interfaces:

- Use a USB keyboard, mouse, and VGA monitor connected directly to the server node.
- Use a terminal (or terminal emulator connected to a computer) through the serial port on the back panel of the server node.
- Connect to the server node using the Oracle ILOM Remote Console.

The following procedure describes the steps for accessing the BIOS Setup Utility menus.

Access BIOS Setup Utility Menus How to access BIOS Setup menus for an Oracle Database Appliance Version 1 server node.

Access BIOS Setup Utility Menus

How to access BIOS Setup menus for an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Power-on or power-cycle the server node.
- The system BIOS boot screen appears. See the following figure for an example:





- To enter the BIOS Setup Utility, do the following:
 - a. Wait for the last line of the screen output to change to Initializing USB Controllers..Done


This will take several seconds.

b. When Done appears, press the F2 key immediately.

(i) Note

If there is an error during the boot process, you can press ${\tt F1}$ to access the BIOS Setup Utility.

The BIOS Setup Utility Main screen appears. See the following figure for an example:







(i) Note

If the BIOS Setup Utility dialog does not appear, you waited too long to press the F2 key. When Done appears on the screen, you must press the F2 key immediately. Try again.

- 4. Use the left and right arrow keys to select the different menu options.
- 5. As you select each menu option, the top-level screen for that menu option appears.
- 6. To select an option on a top-level screen, use the up and down arrow keys to scroll up and down the options presented.

Only options that can be modified are highlighted when you press the up and down arrow keys.

- If a field can be modified, as you select the option, user instructions for modifying the option appear in the right column of the screen.
- If a field is a link to a sub-screen, instructions to press the Enter key to access the subscreen appear in the right column.
- 7. Modify the setup field and press the Esc key to save the changes and exit the screen.

Some screens present a confirmation dialog box that enables unwanted changes to be retracted.

- 8. On sub-screens that only provide configuration information and cannot be modified, press the Esc key to exit the screen.
- 9. To continue modifying other setup parameters, repeat Step 4 through Step 8. Otherwise, go to Step 10.
- 10. Press and release the right arrow key until the Exit menu screen appears.
- 11. Follow the instructions on the Exit menu screen to save or discard your changes and exit the BIOS Setup Utility.

BIOS Setup Utility Screens

Learn about BIOS Setup utility screens for an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The BIOS utility includes seven top-level screens, many of which include sub-screens. Arrow keys provide navigation, and the options or fields that you can configure appear in color. Online instructions provide additional information.



(i) Note

The screens shown are examples. The version numbers and the screen items and selections shown are subject to change over the life of the product.

BIOS Setup Utility Screen Overview

Learn about BIOS Setup utility screens for an Oracle Database Appliance Version 1 server node.

BIOS Main Menu Screen

Learn about BIOS Setup main screen for an Oracle Database Appliance Version 1 server module.

BIOS Advanced Menu Screen

Learn about BIOS Setup Advanced screen for an Oracle Database Appliance Version 1 server module.

BIOS PCI Menu Screen

Learn about BIOS Setup PCI screen for an Oracle Database Appliance Version 1 server module.

BIOS Boot Menu Screen

Learn about BIOS Setup Boot screen for an Oracle Database Appliance Version 1 server module.

BIOS Security Menu Screen

Learn about BIOS Setup Security screen for an Oracle Database Appliance Version 1 server module.

BIOS Chipset Menu Screen

Learn about BIOS Setup Chipset screen for an Oracle Database Appliance Version 1 server module.

BIOS Exit Menu Screen

Learn about BIOS Exit utility screens for an Oracle Database Appliance Version 1 server node.

BIOS Setup Utility Screen Overview

Learn about BIOS Setup utility screens for an Oracle Database Appliance Version 1 server node.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.


The following table contains summary descriptions of the Oracle Database Appliance Version 1 top-level BIOS setup screens.



Screen	Description	See This Section
Main	General product information, including BIOS type, processor, memory, and time/date.	BIOS Main Menu Screen
Advanced	Configuration information for the CPU, memory, IDE, Super IO, trusted computing, USB, PCI, MPS and other information.	BIOS Advanced Menu Screen
PCI	Configure the system to clear NVRAM during system boot.	BIOS PCI Menu Screen
Boot	Configure the boot device priority (storage drives and boot disk drives).	BIOS Boot Menu Screen
Security	Set or change the user and supervisor passwords.	BIOS Security Menu Screen
Chipset	View the configuration of system chip set.	BIOS Chipset Menu Screen
Exit	Save changes and exit, discard changes and exit, discard changes, or load optimal or fail-safe defaults.	BIOS Exit Menu Screen

The following figure shows a map of the BIOS Setup screens.





BIOS Main Menu Screen

Learn about BIOS Setup main screen for an Oracle Database Appliance Version 1 server module.




(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS Main screen provides general product information, including BIOS, processor, system memory, and system time/date. See the following figure for an example:





BIOS Advanced Menu Screen

Learn about BIOS Setup Advanced screen for an Oracle Database Appliance Version 1 server module.




(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS Advanced screen provides detailed configuration information for the CPU, memory, IDE, Super IO, trusted computing, USB, PCI, MPS and other system information. See the following figure for an example:






BIOS PCI Menu Screen

Learn about BIOS Setup PCI screen for an Oracle Database Appliance Version 1 server module.

(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS PCI screen enables you to configure the server node to clear NVRAM during system boot. See the following figure for an example:





BIOS Boot Menu Screen

Learn about BIOS Setup Boot screen for an Oracle Database Appliance Version 1 server module.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS Boot screen enables you to configure the boot device priority (storage drives and the DVD-ROM drive). See the following figure for an example:



BIOS Security Menu Screen

Learn about BIOS Setup Security screen for an Oracle Database Appliance Version 1 server module.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS Security screen enables you to set or change the supervisor and user passwords. See the following figure for an example:





The default state is for the passwords to be unconfigured (not required).

- If you configure a supervisor password, users must enter it to access BIOS setup.
- If you configure a user password, users must enter it before booting an OS.

BIOS Chipset Menu Screen

Learn about BIOS Setup Chipset screen for an Oracle Database Appliance Version 1 server module.



Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS Chipset screen enables you to set the chipset parameters. See the following figure for an example:





BIOS Exit Menu Screen


Learn about BIOS Exit utility screens for an Oracle Database Appliance Version 1 server node.



Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

The Oracle Database Appliance Version 1 BIOS Exit options enable you to save changes and exit, discard changes and exit, discard changes, or load optimal defaults. See the following figure for an example:



Exit From the BIOS Setup Utility How to access BIOS Exit menu for an Oracle Database Appliance Version 1 server node.

Exit From the BIOS Setup Utility

How to access BIOS Exit menu for an Oracle Database Appliance Version 1 server node.



(i) Note

Information in this section ONLY applies to the Oracle Database Appliance Version 1. If you do NOT have an Oracle Database Appliance Version 1 (released in 2011), refer to the preceding chapters in this document for information on servicing your Oracle Database Appliance model.

- Use the up and down arrow keys to scroll up and down the BIOS Exit options.
- Press Enter to select the option.



A confirmation dialog box appears that enables you to save the changes and exit the Setup Utility or cancel the exit option.



(i) Note

The confirmation dialog box is only shown below for the Save Changes and Exit option screen. The other exit confirmation screens work in a similar way.

Figure A-2 BIOS Setup Utility Save and Exit Screen



Index

Α

A	BIOS (continued)
air duct	accessing the setup utility (continued) Oracle Database Appliance X8-2 series, 2
installing	advanced menu options
Oracle Database Appliance Version 1,	·
A-50	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
removing	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance Version 1,	Oracle Database Appliance X7-2 series, 4
A-49	Oracle Database Appliance X8-2 series, 2
antistatic wrist strap	advanced screen
described	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1,	A-117
A-8	boot menu options
Oracle Database Appliance X3-2/X4-2/ X5-2, 3	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X8-2 series, 2
	boot screen
В	Oracle Database Appliance Version 1, A-119
battery	chipset screen
installing	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1, 7,	A-120
A-47	common tasks
Oracle Database Appliance X3-2/X4-2/ X5-2, 6	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
Oracle Database Appliance X6-2 series, 5	Oracle Database Appliance X6-2 series, 4
Oracle Database Appliance X7-2 series, 4	Oracle Database Appliance X7-2 series, 3
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X8-2 series, 2
removing	configuring Trusted Platform Module (TPM)
Oracle Database Appliance Version 1, 7,	Oracle Database Appliance Version 1, A-103
A-46	exit screens
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance Version 1,
X5-2, 6	A-121
Oracle Database Appliance X6-2 series, 5	exiting the setup utility
Oracle Database Appliance X7-2 series, 4	
Oracle Database Appliance X8-2 series, 1 BIOS	Oracle Database Appliance Version 1, A-121
accessing the setup utility	I/O menu options
Oracle Database Appliance Version 1, A-111	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X6-2 series, 5
X5-2, 6	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X6-2 series, 4	Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance X7-2 series, 3	

BIOS (continued)	BIOS (continued)
LAN settings	POST events
Oracle Database Appliance Version 1, A-108	Oracle Database Appliance Version 1, A-96
legacy and UEFI modes	resetting password
Oracle Database Appliance X3-2/X4-2/ X5-2, 6	Oracle Database Appliance Version 1, A-101
Oracle Database Appliance X6-2 series, 4	save and exit options
Oracle Database Appliance X7-2 series, 3 Oracle Database Appliance X8-2 series, 2	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
main menu options	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance X3-2/X4-2/ X5-2, 6	Oracle Database Appliance X7-2 series, 4 Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance X6-2 series, 5	security screen
Oracle Database Appliance X7-2 series, 4	Oracle Database Appliance Version 1,
Oracle Database Appliance X8-2 series, 2	A-119
main screen	setup screens overview
Oracle Database Appliance Version 1, A-116	Oracle Database Appliance Version 1, A-114
managing configurations	setup screens summary
Oracle Database Appliance X3-2/X4-2/ X5-2, 6	Oracle Database Appliance Version 1, <i>A-113</i>
Oracle Database Appliance X6-2 series, 4 Oracle Database Appliance X7-2 series, 3	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
Oracle Database Appliance X8-2 series, 2	Oracle Database Appliance X6-2 series, 5
memory testing	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2 series, 2
A-99	setup utility hot keys
Oracle Database Appliance X3-2/X4-2/ X5-2, 1	Oracle Database Appliance Version 1, A-110
Oracle Database Appliance X6-2 series, 1	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X7-2 series, 1	X5-2, <mark>6</mark>
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2 series, 4
option ROM settings	Oracle Database Appliance X7-2 series, 3
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2 series, 2
A-109	UEFI driver control options
overview, 1	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance Version 1, 7	X5-2, 6
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X6-2 series, 5
X5-2, 5	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X6-2 series, 4	Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance X7-2 series, 3	using for resource allocation
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X3-2/X4-2/
PCI screen	X5-2, 6
Oracle Database Appliance Version 1,	Oracle Database Appliance X6-2 series, 4
A-118	Oracle Database Appliance X7-2 series, 3
POST errors	Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance Version 1, A-97	BIOS Setup Utility accessing
Oracle Database Appliance X3-2/X4-2/ X5-2, 1	Oracle Database Appliance Version 1, <i>A-111</i>
Oracle Database Appliance X6-2 series, 1	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X7-2 series, 1	X5-2, 6
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2 series, 4
,	Oracle Database Appliance X7-2 series, 3
	Oracle Database Appliance X8-2 series, 2

boot disk backplane cables installing	cold service components CRUs
Oracle Database Appliance Version 1, A-84	Oracle Database Appliance Version 1, 7, A-27
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X3-2/X4-2/
X5-2, 10 Oracle Database Appliance X6-2 series, 3	X5-2, 6 Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X8-2 series, 1
removing	FRUs
Oracle Database Appliance Version 1, A-83	Oracle Database Appliance X3-2/X4-2/ X5-2, <i>10</i>
Oracle Database Appliance X3-2/X4-2/ X5-2, 10	Oracle Database Appliance X6-2 series, 3
Oracle Database Appliance X6-2 series, 3	Oracle Database Appliance X7-2 series, 2 Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X7-2 series, 3 Oracle Database Appliance X7-2 series, 2	CPUs
Oracle Database Appliance X8-2 series, 1	clearing faults
boot drive	Oracle Database Appliance Version 1,
installing in server node	A-54
Oracle Database Appliance Version 1,	Oracle Database Appliance X3-2/X4-2/
A-19	X5-2, X6-2 series, X7-2 series
removing from server node	and X8-2 series, 11
Oracle Database Appliance Version 1,	installing
A-18	Oracle Database Appliance Version 1, A-54
С	Oracle Database Appliance X3-2/X4-2/ X5-2, <i>10</i>
cables	Oracle Database Appliance X6-2 series, 3
reconnecting power and data cables after	Oracle Database Appliance X7-2 series, 2
servicing	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance Version 1,	population rules
A-92	Oracle Database Appliance Version 1,
Oracle Database Appliance X3-2/X4-2/	A-28
X5-2, 3	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X6-2 series, 2	X5-2, 10 Oracle Database Appliance V6 2 series 2
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X6-2 series, 3 Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X7-2 series, 2 Oracle Database Appliance X8-2 series, 1
Servicing Oracle Detabase Appliance Version 1	removing
Oracle Database Appliance Version 1, A-73	Oracle Database Appliance Version 1,
chassis interlock switch	A-52
disconnecting	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance Version 1,	X5-2, <i>10</i>
A-59	Oracle Database Appliance X6-2 series, 3
reconnecting	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2 series, 1
A-61	servicing
CLR CMOS button	Oracle Database Appliance Version 1,
location of	A-51
Oracle Database Appliance Version 1, A-101, A-103	Oracle Database Appliance X3-2/X4-2/ X5-2, <i>10</i>
CMOS NVRAM	Oracle Database Appliance X6-2 series, 3
clearing	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance Version 1, A-100	Oracle Database Appliance X8-2 series, 1

CRUs	DIMMs (continued)
component locations	removing (continued)
Oracle Database Appliance Version 1, 7, A-27	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X6-2 series, 5
X5-2, 6	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X6-2 series, 5	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X7-2 series, 4	servicing
Oracle Database Appliance X8-2 series, 1 removal that does not require system power	Oracle Database Appliance Version 1, 7, A-28
off, 1 servicing non-hotplug components, 1	Oracle Database Appliance X3-2/X4-2/ X5-2, 6
	Oracle Database Appliance X6-2 series, 5
D	Oracle Database Appliance X7-2 series, 4
	Oracle Database Appliance X8-2 series, 1
date and time	disk backplane
resetting after battery replacement	installing
Oracle Database Appliance Version 1, 7 Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance Version 1, A-58
X5-2, 6	removing
Oracle Database Appliance X6-2 series, 5 Oracle Database Appliance X7-2 series, 4	Oracle Database Appliance Version 1, A-57
Oracle Database Appliance X8-2 series, 1	servicing boot disk backplane
diagnostic tools	Oracle Database Appliance Version 1,
summary of, 1	A-56
diagnostics	servicing disk backplane
available tools, 1 DIMMs	Oracle Database Appliance X3-2/X4-2/ X5-2, <i>10</i>
clearing faults	Oracle Database Appliance X6-2 series, 3
Oracle Database Appliance Version 1, A-32	Oracle Database Appliance X7-2 series, 2 Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X3-2/X4-2/	disk drives
X5-2, X6-2 series, X7-2 series	adding NVMe storage to the server
and X8-2 series, 11	Oracle Database Appliance X6-2 series,
ECC and parity errors	13
Oracle Database Appliance Version 1, A-34	Oracle Database Appliance X7-2 series, 9 Oracle Database Appliance X8-2M, 4
installing	adding optional drives to the storage shelf
Oracle Database Appliance Version 1, 7,	Oracle Database Appliance X6-2-HA, 25
A-32	Oracle Database Appliance X7-2-HA, 21
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X8-2-HA, 17
X5-2, 6	location in system
Oracle Database Appliance X6-2 series, 5	Oracle Database Appliance Version 1,
Oracle Database Appliance X7-2 series, 4	A-14
Oracle Database Appliance X8-2 series, 1	replacing boot drives in server node
population rules	Oracle Database Appliance Version 1, A-14
Oracle Database Appliance Version 1, 7,	
A-28	replacing in server node
Oracle Database Appliance X3-2/X4-2/ X5-2, 6	Oracle Database Appliance Version 1, 37 Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X6-2 series, 5	X5-2, 15 Oracla Databasa Appliance X6.2 series
Oracle Database Appliance X7-2 series, 4 Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2 series, 10
removing	Oracle Database Appliance X7-2 series, 6
Oracle Database Appliance Version 1, 7, A-29	Oracle Database Appliance X8-2 series, 1

disk drives (continued)	Ethernet ports (continued)
replacing in storage shelf	LEDs (continued)
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X6-2-HA, 42
X5-2 and X6-2-HA/X7-2-HA/X8-2-	Oracle Database Appliance X6-2L, 37
HA, 28	Oracle Database Appliance X6-2S/
replacing NVMe storage	X6-2M, 33
Oracle Database Appliance X6-2 series,	Oracle Database Appliance X7-2-HA, 25
12	Oracle Database Appliance X7-2S/
Oracle Database Appliance X7-2 series, 7	X7-2M, 21
Oracle Database Appliance X8-2 series, 3	Oracle Database Appliance X8-2-HA, 12
disk midplane module	Oracle Database Appliance X8-2S/
installing	X8-2M, 7
Oracle Database Appliance Version 1,	naming and boot priority
A-66	Oracle Database Appliance Version 1,
removing	A-102
Oracle Database Appliance Version 1,	Oracle Database Appliance X3-2/X4-2/
A-63	X5-2, 6
servicing	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance Version 1,	Oracle Database Appliance X7-2 series, 4
A-62	Oracle Database Appliance X8-2 series, 2
disk midplane module HDD cable	•••
installing	Г
Oracle Database Appliance Version 1,	F
A-69	fan cables
removing	installing
Oracle Database Appliance Version 1,	Oracle Database Appliance Version 1,
A-68	A-75
servicing	removing
Oracle Database Appliance Version 1,	Oracle Database Appliance Version 1,
A-67	A-74
	servicing
_	Oracle Database Appliance Version 1,
E	A-74
electrostatic discharge (ESD)	fans
precautions	detecting faults using LEDs
Oracle Database Appliance Version 1,	Oracle Database Appliance Version 1,
A-8	A-21
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X3-2/X4-2, 55
X5-2, 3	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2S/
emergency shutdown	X6-2M, 31
server node	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance Version 1,	Oracle Database Appliance X7-25/
A-5	X7-2M, 18
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X8-2-HA, <i>10</i>
X5-2, 3	Oracle Database Appliance X8-2H, 4
	·
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X7-2 series, 2	installing
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance Version 1,
Ethernet ports	A-22
Cracle Database Appliance Version 1, 72	removing Oracle Database Appliance Version 1
Oracle Database Appliance Version 1, 72	Oracle Database Appliance Version 1,
Oracle Database Appliance X3-2/X4-2, 58	A-21
Oracle Database Appliance X5-2, 50	

fans (continued)	front indicator panels
replacing in server node	servicing
Oracle Database Appliance Version 1, 37	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X3-2/X4-2/	X5-2, 10
X5-2, 15	Oracle Database Appliance X6-2 series, 3
Oracle Database Appliance X6-2 series,	Oracle Database Appliance X7-2 series, 2
10	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X7-2 series, 6	FRUS
Oracle Database Appliance X8-2 series, 1	cold service components
faults	Oracle Database Appliance Version 1, 12 component locations
clearing CPU faults Oracle Database Appliance Version 1,	Oracle Database Appliance Version 1,
A-54	A-2
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X3-2/X4-2/
X5-2, X6-2 series, X7-2 series	X5-2, <u>10</u>
and X8-2 series, 11	Oracle Database Appliance X6-2 series, 3
clearing DIMM faults	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2 series, 1
A-32	managing component faults, 11
Oracle Database Appliance X3-2/X4-2/	servicing non-hotplug FRU components, 1
X5-2, X6-2 series, X7-2 series	
and X8-2 series, 11	G
clearing PCIe card faults	
Oracle Database Appliance Version 1,	graceful shutdown
A-41 Oracle Database Appliance V2 2/V4 2/	server node
Oracle Database Appliance X3-2/X4-2/ X5-2, X6-2 series, X7-2 series	Oracle Database Appliance Version 1,
and X8-2 series, 11	A-5 Oracle Detabase Appliance V2 2/V4 2/
clearing PCIe riser faults	Oracle Database Appliance X3-2/X4-2/ X5-2, 3
Oracle Database Appliance Version 1,	Oracle Database Appliance X6-2 series, 2
A-36	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X8-2 series, 1
X5-2, X6-2 series, X7-2 series	μμ
and X8-2 series, 11	Н
clearing the primary HBA card faults	<u>п</u>
Oracle Database Appliance Version 1,	HBA
A-44	installing
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X3-2/X4-2/
X5-2, X6-2 series, X7-2 series	X5-2, <i>10</i>
and X8-2 series, 11	Oracle Database Appliance X6-2 series, 3
managing Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X7-2 series, 2
X5-2, X6-2 series, X7-2 series	Oracle Database Appliance X8-2 series, 1
and X8-2 series, 11	installing primary HBA cables
front indicator panel	Oracle Database Appliance Version 1,
installing	A-77
Oracle Database Appliance Version 1,	installing secondary HBA cables Oracle Database Appliance Version 1,
A-72	Oracle Database Appliance version 1, $A-79$
removing	installing the primary HBA card
Oracle Database Appliance Version 1,	Oracle Database Appliance Version 1,
A-70	A-44
servicing	primary and secondary cards
Oracle Database Appliance Version 1,	Oracle Database Appliance Version 1,
A-69	A-39

HBA (continued)	L
removing	L CDo
Oracle Database Appliance X3-2/X4-2/	LEDs
X5-2, 10	AC OK
Oracle Database Appliance X6-2 series, 3	Oracle Database Appliance Version 1, 69
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X3-2/X4-2, 58
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X5-2, 50
removing primary HBA cables	Oracle Database Appliance X6-2-HA, 42
Oracle Database Appliance Version 1,	Oracle Database Appliance X6-2L, 37
A-76	Oracle Database Appliance X6-2S/
removing secondary HBA cables	X6-2M, 33
Oracle Database Appliance Version 1,	Oracle Database Appliance X7-2-HA, 25
A-78	Oracle Database Appliance X7-2S/
removing the primary HBA card	X7-2M, <i>21</i>
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2-HA, 12
A-43	Oracle Database Appliance X8-2S/
replacing a SAS HBA cables	X8-2M, 7
Oracle Database Appliance X6-2L, 8	Activity
replacing a SAS HBA card	Oracle Database Appliance Version 1, 68
Oracle Database Appliance X6-2L, 4	Oracle Database Appliance X3-2/X4-2, 55
servicing HBA card	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X6-2L, 4	Oracle Database Appliance X6-2-HA, 39
servicing HBA card cables	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance Version 1,	Oracle Database Appliance X6-2S/
A-75	X6-2M, 31
servicing HBA SAS cables	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X6-2L, 4	Oracle Database Appliance X7-2S/
host bus adapter (HBA) cables	X7-2M, 18
servicing SAS cables	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X8-2M, 4
X5-2, 10	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X6-2 series, 3	CPU
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X8-2 series, 1	X5-2, <u>10</u>
hot-plug components	Oracle Database Appliance X6-2 series, 3
server node	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance Version 1, 37	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X3-2/X4-2/	DC OK
X5-2, <i>15</i>	Oracle Database Appliance Version 1, 69
Oracle Database Appliance X6-2 series,	Oracle Database Appliance X3-2/X4-2, 58
10	Oracle Database Appliance X5-2, 50
Oracle Database Appliance X7-2 series, 6	Oracle Database Appliance X6-2-HA, 42
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2L, 37
hot-pluggable components, 1	Oracle Database Appliance X6-2S/
1 33 1 ,	X6-2M, 33
	Oracle Database Appliance X7-2-HA, 25
I	Oracle Database Appliance X7-2S/
I/O modulo	X7-2M, <i>21</i>
I/O module	Oracle Database Appliance X8-2-HA, 12
replacing in storage shelf	Oracle Database Appliance X8-2S/
Oracle Database Appliance X3-2/X4-2/	X8-2M, 7
X5-2 and X6-2-HA/X7-2-HA/X8-2-	DIMM
HA, 34	
ILOM	Oracle Database Appliance Version 1, 7
used as diagnostic tool, 1	Oracle Database Appliance X3-2/X4-2/
	X5-2, 6
	Oracle Database Appliance X6-2 series, 5

LEDs (continued)	LEDs (continued)
DIMM (continued)	Locate (continued)
Oracle Database Appliance X7-2 series, 4	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2 series, 1	X6-2M, 31
Ethernet ports	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance Version 1, 72	Oracle Database Appliance X7-2S/
Oracle Database Appliance X3-2/X4-2, 58	X7-2M, <i>18</i>
Oracle Database Appliance X5-2, 50	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance X6-2-HA, 42	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X6-2L, 37	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X6-2S/	OK
X6-2M, 33	Oracle Database Appliance Version 1, 67
Oracle Database Appliance X7-2-HA, 25	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X7-2S/	Oracle Database Appliance X5-2, 48
X7-2M, 21	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X8-2-HA, 12	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X8-2S/	Oracle Database Appliance X6-2S/
X8-2M, 7	X6-2M, 31
fans	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance Version 1, 67	Oracle Database Appliance X7-25/
Oracle Database Appliance X3-2/X4-2, 55	X7-2M, 18
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X6-2S/	Oracle Database Appliance Version 1, 63
X6-2M/, 31	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X5-2, 47
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2-HA, 39
X7-2M/, 18	Oracle Database Appliance X6-2S/X6-2M/
Oracle Database Appliance X8-2-HA, 10	X6-2L, 30
Oracle Database Appliance X8-2M/, 4	Oracle Database Appliance X7-2-HA, 22
Oracle Database Appliance X8-2S/, 2	Oracle Database Appliance X7-2S/X7-2M, 17
general status	Oracle Database Appliance X8-2-HA, 9
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2S/X8-2M, 1
Oracle Database Appliance X5-2, 48	Over Temperature
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance Version 1, 64
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X6-2S/	Oracle Database Appliance X5-2, 48
X6-2M, 31	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2S/
X7-2M, 18	X6-2M, 31
Oracle Database Appliance X8-2-HA, 10	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X7-2S/
Oracle Database Appliance X8-2S, 2	X7-2M, <i>18</i>
internal	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance Version 1, 71	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X6-2 series, 3	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X7-2 series, 2	power supplies
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X3-2/X4-2, 55
Locate	Oracle Database Appliance X5-2, 48
Oracle Database Appliance Version 1, 64	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X6-2S/
Oracle Database Appliance X6-2-HA, 39	X6-2M, 31
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance X7-2-HA. 23

LEDs (continued)	LEDs (continued)
power supplies (continued)	server node rear Locate (continued)
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2S/
X7-2M, 18	X6-2M, 31
Oracle Database Appliance X8-2-HA, 10	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X7-2S/
Oracle Database Appliance X8-2S, 2	X7-2M, 18
Power/OK	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance Version 1, 64	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X5-2, 48	server node rear Locate push to test
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance Version 1, 70
Oracle Database Appliance X6-2L, 35	server node rear Power/OK
Oracle Database Appliance X6-2S/	Oracle Database Appliance Version 1, 70
X6-2M, 31	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X5-2/X4-2, 33
Oracle Database Appliance X7-2-HA, 23	• • • • • • • • • • • • • • • • • • • •
$X7-2M$, $\frac{18}{}$	Oracle Database Appliance X6-2-HA, 39
•	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2-HA, 10	X6-2M, <i>31</i> , <i>35</i>
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance X7-2S/
Ready to Remove	X7-2M, 18
Oracle Database Appliance Version 1, 64,	Oracle Database Appliance X8-2-HA, 10
68	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X5-2, 48	server node rear Ready to Remove
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance Version 1, 70
Oracle Database Appliance X6-2L, 35	server node rear Service Required
Oracle Database Appliance X6-2S/	Oracle Database Appliance Version 1, 70
X6-2M, 31	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2-HA, 39
X7-2M, <i>18</i>	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X8-2-HA, 10	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2M, 4	X6-2M, 31
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance X7-2-HA, 23
rear component failure	Oracle Database Appliance X7-2S/
Oracle Database Appliance Version 1, 64	X7-2M, 18
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X6-2L, 35	server node Service Required
Oracle Database Appliance X6-2S/	Oracle Database Appliance X3-2/X4-2, 55
X6-2M, 31	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2L, 35
X7-2M, 18	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2-HA, 10	X6-2M, 31
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance X7-2S/
server node rear Locate	X7-2M, 18
Oracle Database Appliance Version 1, 70	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance No 25, 2
Oracle Database Appliance X6-21, 35	
Oracle Database Appliance Au-ZE, 33	

LEDs (continued)	motherboard assembly (continued)
Service Required	servicing
Oracle Database Appliance Version 1, 64,	Oracle Database Appliance Version 1,
67–69	A-84
SP OK/Fault	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance Version 1, 64	X5-2, 10 Oracle Database Appliance V6 2 series 2
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X6-2 series, 3 Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X5-2, 48 Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X7-2 series, 2 Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X6-21, 35	Oracle Database Appliance 70-2 series, 1
Oracle Database Appliance X6-2S/	N.I.
X6-2M, 31	N
Oracle Database Appliance X7-2-HA, 23	network cards
Oracle Database Appliance X7-2S/	adding
X7-2M, <i>18</i>	Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance X8-2-HA, 10	network ports
Oracle Database Appliance X8-2M, 4	naming and boot order
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance Version 1,
storage and boot drives	A-102
Oracle Database Appliance Version 1, 68	Oracle Database Appliance X3-2/X4-2/
storage devices Oracle Database Appliance X3-2/X4-2, 55	X5-2, 6
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance X8-2 series, 2 NVMe drives
Oracle Database Appliance X6-2S/	adding to server node
X6-2M, 31	Oracle Database Appliance X6-2 series,
Oracle Database Appliance X7-2-HA, 23	11
Oracle Database Appliance X7-2S/	Oracle Database Appliance X7-2 series, 7
X7-2M, <i>18</i>	Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance X8-2-HA, 10	replacing in server node
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X6-2 series,
Oracle Database Appliance X8-2S, 2	11
storage shelf back panel Oracle Database Appliance X3-2/X4-2, 62	Oracle Database Appliance X7-2 series, 7
Oracle Database Appliance X5-2/X4-2, 62 Oracle Database Appliance X5-2, 54	Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance X6-2-HA, 46	
Oracle Database Appliance X7-2-HA, 29	0
Oracle Database Appliance X8-2-HA, 16	antion DOM cattings
storage shelf front panel	option ROM settings configuring
Oracle Database Appliance X3-2/X4-2, 61	Oracle Database Appliance Version 1,
Oracle Database Appliance X5-2, 52	A-108
Oracle Database Appliance X6-2-HA, 44	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X7-2-HA, 27	X5-2, 6
Oracle Database Appliance X8-2-HA, 14	Oracle Database Appliance X6-2 series, 4
	Oracle Database Appliance X7-2 series, 3
M	Oracle Database Appliance X8-2 series, 2
	Oracle Database Appliance Version 1
motherboard assembly	servicing, A-1
installing components Oracle Database Appliance Version 1	Oracle Integrated Lights Out Manager (Oracle
Oracle Database Appliance Version 1, A-87	ILOM)
removing components	server node power off procedures Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1,	Oracle Database Appliance version 1, $A-5$
A-86	Oracle Database Appliance X3-2/X4-2/
	X5-2, 3

Oracle Integrated Lights Out Manager (Oracle ILOM) (co	ontinu @d) le cards (continued)
server node power off procedures (continued)	removing from PCIe riser (continued)
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X8-2 series, 1	removing in Oracle Database Appliance X6-2
server node power on procedures	series, 3
dual node Oracle Database Appliance	
	removing in Oracle Database Appliance X7-2
with storage shelf, 4	series, 2
Oracle Database Appliance Version 1,	removing in Oracle Database Appliance X8-2
A-92	series, 1
Oracle Database Appliance X3-2/X4-2/	removing the primary HBA card
X5-2, 3	Oracle Database Appliance Version 1,
Oracle Database Appliance X6-2 series, 2	A-43
Oracle Database Appliance X7-2 series, 2	servicing
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance Version 1, 7,
SP reset, 3	A-38
used as diagnostic tool, 1	Oracle Database Appliance X3-2/X4-2/
	X5-2, 6
	Oracle Database Appliance X6-2 series, 5
P	Oracle Database Appliance X7-2 series, 4
De Obrack 4	Oracle Database Appliance XY 2 series, 4
Pc-Check, 1	PCIe riser
PCIe cards	clearing faults
adding	<u> </u>
Oracle Database Appliance X8-2 series, 2	Oracle Database Appliance Version 1,
clearing faults	A-36
Oracle Database Appliance Version 1,	Oracle Database Appliance X3-2/X4-2/
A-41	X5-2, X6-2 series, X7-2 series
Oracle Database Appliance X3-2/X4-2/	and X8-2 series, 11
X5-2, X6-2 series, X7-2 series	installing
and X8-2 series, 11	Oracle Database Appliance Version 1, 7,
installing in Oracle Database Appliance X6-2	A-36
series, 3	Oracle Database Appliance X3-2/X4-2/
installing in Oracle Database Appliance X7-2	X5-2, 6
series, 2	Oracle Database Appliance X6-2 series, 5
	Oracle Database Appliance X7-2 series, 4
installing in Oracle Database Appliance X8-2	Oracle Database Appliance X8-2 series, 1
series, 1	removing
installing in PCIe riser	Oracle Database Appliance Version 1, 7,
Oracle Database Appliance Version 1, 7,	· ·
A-41	A-35
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X3-2/X4-2/
X5-2, 6	X5-2, 6
Oracle Database Appliance X6-2 series, 5	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance X7-2 series, 4	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X8-2 series, 1
installing the primary HBA card	servicing
Oracle Database Appliance Version 1,	Oracle Database Appliance Version 1, 7,
А-44	A-34
primary and secondary HBA	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance Version 1,	X5-2, 6
A-39	Oracle Database Appliance X6-2 series, 5
	Oracle Database Appliance X7-2 series, 4
removing from PCIe riser	Oracle Database Appliance X1-2 series, 4 Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance Version 1, 7,	• • • • • • • • • • • • • • • • • • • •
A-39	power distribution board
Oracle Database Appliance X3-2/X4-2/	installing
X5-2, 6	Oracle Database Appliance Version 1,
Oracle Database Appliance X6-2 series 5	A-61

power distribution board (continued)	power supply
removing	detecting faults using LEDs
Oracle Database Appliance Version 1, A-59	Oracle Database Appliance Version 1, A-24
servicing	installing
	<u> </u>
Oracle Database Appliance Version 1, A-58	Oracle Database Appliance Version 1, A-25
power off	removing
appliance	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1,	A-24
A-8, A-9	power-on self test events
power on	Oracle Database Appliance Version 1, A-96
Oracle Database Appliance Version 1, A-92	power-on self-test (POST), 1
returning the system to operation, 1	power-on self-test (POST) events
power supplies	Oracle Database Appliance X3-2/X4-2/X5-2,
replacing in server node	X6 series, X7 series and X8 series, 1
Oracle Database Appliance Version 1, 37,	powering off
A-23	emergency shutdown
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance Version 1,
X5-2, <i>15</i>	A-5
Oracle Database Appliance X6-2 series,	Oracle Database Appliance X3-2/X4-2/ X5-2, 3
Oracle Database Appliance X7-2 series, 6	Oracle Database Appliance X6-2 series, 2
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X7-2 series, 2
replacing in storage shelf	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X3-2/X4-2/	graceful shutdown
X5-2, X6-2-HA, X7-2-HA and	Oracle Database Appliance Version 1,
X8-2-HA, 31	A-5
server node	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance Version 1, 37	X5-2, 3
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X6-2 series, 2
X5-2, <i>15</i>	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X6-2 series,	Oracle Database Appliance X8-2 series, 1
10	powering on
Oracle Database Appliance X7-2 series, 6	dual node Oracle Database Appliance with
Oracle Database Appliance X8-2 series, 1	storage shelf, 4
status indicators	Oracle Database Appliance Version 1, 5
Oracle Database Appliance Version 1, 69	Oracle Database Appliance X3-2/X4-2/X5-2, 3
Oracle Database Appliance X3-2/X4-2,	Oracle Database Appliance X6-2 series, 2
55, 58	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X5-2, 48, 50	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X6-2-HA, 39,	γ,,
42	Б
Oracle Database Appliance X6-2L, 35, 37	R
Oracle Database Appliance X6-2S/	replaceable components
X6-2M, <i>31</i> , <i>33</i>	·
Oracle Database Appliance X7-2-HA, 23,	cold service components
25	Oracle Database Appliance Version 1, 7,
Oracle Database Appliance X7-2S/	A-2
X7-2M, 18, 21	Oracle Database Appliance X3-2/X4-2/
	X5-2, 6
Oracle Database Appliance X8-2-HA, <i>10</i> ,	Oracle Database Appliance X6-2 series, 5
12 Oracle Database Appliance VO 2M 4	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X8-2S, 2	hot service components
Oracle Database Appliance X8-2S/	Oracle Database Appliance Version 1, 37,
X8-2M, 7	A-2

replaceable components (continued)	server node (continued)
hot service components (continued)	back panel indicators (continued)
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X6-2S/
X5-2, <i>15</i>	X6-2M, 31
Oracle Database Appliance X6-2 series,	Oracle Database Appliance X7-2-HA, 23
10	Oracle Database Appliance X7-2S/
Oracle Database Appliance X7-2 series, 6	X7-2M, 18
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X8-2-HA, 10
replacing	Oracle Database Appliance X8-2M, 4
hot and cold service components	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance Version 1,	CPU LEDs
A-2	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X3-2/X4-2/	X5-2, <u>10</u>
X5-2, 3	Oracle Database Appliance X6-2 series, 3
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X8-2 series, 1	DIMM internal LEDs
required tools	Oracle Database Appliance Version 1, 7
servicing components	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance Version 1,	X5-2, 6
A-4	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X7-2 series, 4
X5-2, 3	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X6-2 series, 2	installing a boot drive
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance Version 1,
Oracle Database Appliance X8-2 series, 1	А-19
reset Oracle ILOM SP, 3	installing a storage drive
	Oracle Database Appliance Version 1,
6	A-17
S	installing in the chassis
safety information	Oracle Database Appliance Version 1,
servicing	A-91
· · · · · · · · · · · · · · · · · · ·	internal LEDs
Oracle Database Appliance Version 1, A-3	Oracle Database Appliance Version 1, 71
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X3-2/X4-2, 55
X5-2, 3	Oracle Database Appliance X5-2, 48
	Oracle Database Appliance X6-2 series, 3
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2S/
SAS expander cable	X6-2M, 31
installing	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance Version 1,	Oracle Database Appliance X7-2-HA, 23
A-81	Oracle Database Appliance X7-2-11A, 25
removing	X7-2M, 18
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2 series, 1
A-80	Oracle Database Appliance X8-2-HA, 10
servicing SAS expander cable	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance Version 1,	·
A-80, A-82	Oracle Database Appliance X8-2S, 2
server node	powering off
back panel indicators	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1, 70	A-5 Oracle Detabase Appliance V2 2/V4 2/
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X5-2, 48	X5-2, 3
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X6-2 series, 2
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance X7-2 series, 2

server node (continued)	server node (continued)
powering off (continued)	slide out from rack to maintenance position (continued)
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X8-2 series, 1
reconnecting power and data cables	server node top cover
Oracle Database Appliance Version 1,	installing
A-92	Oracle Database Appliance Version 1,
Oracle Database Appliance X3-2/X4-2/	A-90
X5-2, 3	service processor reset, 3
Oracle Database Appliance X6-2 series, 2	servicing
Oracle Database Appliance X7-2 series, 2	boot disk backplane
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance Version 1,
reinstalling in rack	A-56
Oracle Database Appliance X3-2/X4-2/	cables
X5-2, 3	Oracle Database Appliance Version 1,
Oracle Database Appliance X6-2 series, 2	A-73
Oracle Database Appliance X7-2 series, 2	CPUs
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance Version 1,
reinstalling in the chassis	A-51
Oracle Database Appliance Version 1, 5	Oracle Database Appliance X3-2/X4-2/
removing a boot drive	X5-2, 10
Oracle Database Appliance Version 1,	Oracle Database Appliance X6-2 series, 3
A-18	Oracle Database Appliance X7-2 series, 2
removing a storage drive	Oracle Database Appliance X8-2 series, 2
Oracle Database Appliance Version 1,	customer-replaceable server node
A-16	components
removing from chassis	Oracle Database Appliance Version 1,
	A-26
Oracle Database Appliance Version 1, A-9	DIMMs
removing from rack	Oracle Database Appliance Version 1, 7, A-28
Oracle Database Appliance X3-2/X4-2/ X5-2, <i>3</i>	
	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X6-2 series, 2	X5-2, 6 Oracle Database Appliance V6.2 series. 5
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X6-2 series, 5 Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X8-2 series, 1	
removing the top cover	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance Version 1,	disk backplane
A-11 Orocle Detabase Appliance V2 2/V4 2/	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X3-2/X4-2/	X5-2, 10
X5-2, 3	Oracle Database Appliance X6-2 series, 3
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X8-2 series, 1	disk midplane module
removing the top cover middle section	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1,	A-62
A-12	disk midplane module HDD cable
slide into rack from maintenance position	Oracle Database Appliance Version 1,
Oracle Database Appliance X3-2/X4-2/	A-67
X5-2, 3	fan cables
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance Version 1,
Oracle Database Appliance X7-2 series, 2	A-74
Oracle Database Appliance X8-2 series, 1	fan modules
slide out from rack to maintenance position	Oracle Database Appliance Version 1,
Oracle Database Appliance X3-2/X4-2/	A-20
X5-2, 3	field-replaceable components
Oracle Database Appliance X6-2 series, 2	Oracle Database Appliance Version 1,
Oracle Database Appliance X7-2 series. 2	A-48

servicing (continued)	servicing (continued)
front indicator panel	PCIe cards (continued)
Oracle Database Appliance Version 1,	Oracle Database Appliance X6-2 series, 5
A-69	Oracle Database Appliance X7-2 series, 4
front indicator panels	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X3-2/X4-2/	PCIe riser
X5-2, <u>10</u>	Oracle Database Appliance Version 1, 7,
Oracle Database Appliance X6-2 series, 3	A-34
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X8-2 series, 1	X5-2, 6
FRUs	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance Version 1, 12	Oracle Database Appliance X7-2 series, 4
HBA card cables	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance Version 1,	power distribution board
A-75	Oracle Database Appliance Version 1,
HBA SAS cables	A-58
Oracle Database Appliance X3-2/X4-2/	powering on server node
X5-2, 10	Oracle Database Appliance Version 1,
hot-plug components, 1	A-92, A-95
Oracle Database Appliance Version 1, 37	preparing for service
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance Version 1, 4
X5-2, 15	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X6-2 series,	X5-2, 3
Oracle Database Appliance V7 2 series 6	Oracle Database Appliance X6-2 series, 2
Oracle Database Appliance X7-2 series, 6	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X8-2 series, 1
hot-plug components, storage shelf, <i>16</i> hotplug components	preparing the system, 1 Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1,	A-1
A-13	removing a server node from chassis
installing a server node in the chassis	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1,	A-9
A-90	Oracle Database Appliance X3-2/X4-2/
installing a server node top cover	X5-2, 3
Oracle Database Appliance Version 1,	Oracle Database Appliance X6-2 series, 2
A-89, A-90	Oracle Database Appliance X7-2 series, 2
managing component faults, 11	Oracle Database Appliance X8-2 series, 1
motherboard assembly	removing the top cover
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance Version 1,
X5-2, 10	A-10
Oracle Database Appliance X6-2 series, 3	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X7-2 series, 2	X5-2, 3
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2 series, 2
non-hotplug customer replacable	Oracle Database Appliance X7-2 series, 2
components, 1	Oracle Database Appliance X8-2 series, 1
non-hotplug field replacable components, 1	removing the top cover middle section
NVMe cables	Oracle Database Appliance Version 1,
Oracle Database Appliance X6-2 series, 3	A-11
Oracle Database Appliance X7-2 series, 2	replacing a power supply in storage shelf
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance Version 1, A-1	X5-2, X6-2-HA, X7-2-HA and
PCIe cards	X8-2-HA, 31
Oracle Database Appliance Version 1, 7,	replacing disk drives in a storage shelf
A-38	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X3-2/X4-2/	X5-2 and X6-2-HA/X7-2-HA/X8-2-
X5-2, 6	HA, <i>28</i>

servicing (continued)	servicing (continued)
replacing fans in server node	server node BIOS
Oracle Database Appliance Version 1, 37	Oracle Database Appliance Version 1,
Oracle Database Appliance X3-2/X4-2/	A-94
X5-2, <i>15</i>	server node motherboard
Oracle Database Appliance X6-2 series, 10	Oracle Database Appliance Version 1, A-84
Oracle Database Appliance X7-2 series, 6	troubleshooting and diagnostics, 1
Oracle Database Appliance X8-2 series, 1	Setup
replacing hard disk drives in server node	BIOS Setup Utility overview, 1
Oracle Database Appliance Version 1, 37,	Oracle Database Appliance Version 1, 7
A-14	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X3-2/X4-2/	X5-2, 5
X5-2, <i>15</i> Oracle Database Appliance X6-2 series,	Oracle Database Appliance X6-2 series, 4 Oracle Database Appliance X7-2 series, 3
10	Oracle Database Appliance X1-2 series, 3 Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X7-2 series, 6	shut down
Oracle Database Appliance X8-2 series, 1	server node
replacing I/O module in storage shelf	Oracle Database Appliance Version 1,
Oracle Database Appliance X3-2/X4-2/	A-6
X5-2 and X6-2-HA/X7-2-HA/X8-2-	shutdown procedures
HA, <i>34</i>	emergency shutdown
replacing power supplies in server node	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1, 37,	A-5
A-23	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X3-2/X4-2/	X5-2, 3
X5-2, <i>15</i>	Oracle Database Appliance X6-2 series, 2
Oracle Database Appliance X6-2 series,	Oracle Database Appliance X7-2 series, 2
10	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X7-2 series, 6	graceful shutdown
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance Version 1,
resetting the SP, 1	A-5 Oracle Database Appliance V2 2/V4 2/
returning the appliance to operation Oracle Database Appliance Version 1, 5,	Oracle Database Appliance X3-2/X4-2/ X5-2, 3
A-88	Oracle Database Appliance X6-2 series, 2
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X7-2 series, 2
X5-2, 3	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X6-2 series, 2	shutting down
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance Version 1, 4
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X3-2/X4-2/X5-2, 3
returning the system to operation, 1	Oracle Database Appliance X6-2 series, 2
SAS expander cable	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2 series, 1
A-80, A-82	preparing the system for servicing, 1
server node air ducts	SP LAN settings
Oracle Database Appliance Version 1,	configuring
A-49	Oracle Database Appliance Version 1,
server node battery	A-107
Oracle Database Appliance Version 1, 7, A-45	standby power state
	dual node Oracle Database Appliance with
Oracle Database Appliance X3-2/X4-2/ X5-2, 6	storage shelf, 4 Oracle Database Appliance Version 1, A-92
Oracle Database Appliance X6-2 series, 5	Oracle Database Appliance X3-2/X4-2/X5-2, 3
Oracle Database Appliance X7-2 series, 4	Oracle Database Appliance X6-2 series, 2
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X7-2 series, 2
2.11.12 = 11.11.12.12.1. pp.11.1.120 / 10 = 00.1.00 j =	Oracle Database Appliance X8-2 series, 1

status indicators	status indicators (continued)
AC OK	DIMM (continued)
Oracle Database Appliance Version 1, 69	Oracle Database Appliance X6-2 series, 5
Oracle Database Appliance X3-2/X4-2, 58	Oracle Database Appliance X7-2 series, 4
Oracle Database Appliance X5-2, 50	Oracle Database Appliance X8-2 series, 1
Oracle Database Appliance X6-2-HA, 42	Ethernet ports
Oracle Database Appliance X6-2L, 37	Oracle Database Appliance Version 1, 72
Oracle Database Appliance X6-2S/	Oracle Database Appliance X3-2/X4-2, 58
X6-2M, 33	Oracle Database Appliance X5-2, 50
Oracle Database Appliance X7-2-HA, 25	Oracle Database Appliance X6-2-HA, 42
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2L, 37
X7-2M, <i>21</i>	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2-HA, 12	X6-2M, 33
Oracle Database Appliance X8-2S/	Oracle Database Appliance X7-2-HA, 25
X8-2M, 7	Oracle Database Appliance X7-2S/
Activity	X7-2M, <i>21</i>
Oracle Database Appliance Version 1, 68	Oracle Database Appliance X8-2-HA, 12
Oracle Database Appliance X3-2/X4-2, 58	Oracle Database Appliance X8-2S/
Oracle Database Appliance X5-2, 50	X8-2M, 7
Oracle Database Appliance X6-2-HA, 42	fans
Oracle Database Appliance X6-2L, 37	Oracle Database Appliance Version 1, 67
Oracle Database Appliance X6-2S/	Oracle Database Appliance X3-2/X4-2, 55
X6-2M, 33	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X7-2-HA, 25	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2L, 35
X7-2M, <i>21</i>	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2-HA, 12	X6-2M, 31
Oracle Database Appliance X8-2S/	Oracle Database Appliance X7-2-HA, 23
X8-2M, 7	Oracle Database Appliance X7-2S/
CPU	X7-2M, 18
Oracle Database Appliance Version 1,	Oracle Database Appliance X8-2-HA, 10
A-52	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance X8-2S, 2
X5-2, 10	general status
Oracle Database Appliance X6-2 series, 3	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X8-2 series, 1	Oracle Database Appliance X6-2-HA, 39
DC OK	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance Version 1, 69	Oracle Database Appliance X6-2S/
Oracle Database Appliance X3-2/X4-2, 58	X6-2M, 31
Oracle Database Appliance X5-2, 50	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X6-2-HA, 42	Oracle Database Appliance X7-2S/
Oracle Database Appliance X6-2L, 37	X7-2M, 18
Oracle Database Appliance X6-2S/	Oracle Database Appliance X8-2-HA, 10
X6-2M, 33	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X7-2-HA, 25	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X7-2S/	internal
X7-2M, <i>21</i>	Oracle Database Appliance Version 1, 71
Oracle Database Appliance X8-2-HA, 12	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X8-2S/	X5-2, 10
X8-2M, 7	Oracle Database Appliance X6-2 series, 3
DIMM	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance Version 1, 7,	Oracle Database Appliance X8-2 series, 1
A-29	Locate
Oracle Database Appliance X3-2/X4-2/	Oracle Database Appliance Version 1, 64
X5-2, 6	Oracle Database Appliance X3-2/X4-2, 55

status indicators (continued)	status indicators (continued)
Locate (continued)	Power/OK (continued)
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X6-2S/
Oracle Database Appliance X6-2L, 35	X6-2M, 31
Oracle Database Appliance X6-2S/	Oracle Database Appliance X7-2-HA, 23
X6-2M, 31	Oracle Database Appliance X7-2S/
Oracle Database Appliance X7-2-HA, 23	X7-2M, 18
Oracle Database Appliance X7-2S/	Oracle Database Appliance X8-2-HA, 10
X7-2M, 18	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X8-2-HA, 10	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X8-2M, 4	Ready to Remove
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance Version 1, 64,
Oracle Database Appliance Version 1, 63	68
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X5-2, 47	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X6-2S/X6-2M/	Oracle Database Appliance X6-2L, 35
X6-2L, 30	Oracle Database Appliance X6-2S/
Oracle Database Appliance X7-2-HA, 22	X6-2M, 31
Oracle Database Appliance X7-2S/X7-2M, 17	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X8-2-HA, 9	Oracle Database Appliance X7-2S/
Oracle Database Appliance X8-2S/X8-2M, 1	X7-2M, <i>18</i>
Over Temperature	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance Version 1, 64	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X5-2, 48	rear component failure
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance Version 1, 64
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X6-2S/	Oracle Database Appliance X5-2, 48
X6-2M, 31	Oracle Database Appliance X6-2-HA, 39
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2S/
X7-2M, 18	X6-2M, 31
Oracle Database Appliance X8-2-HA, 10	Oracle Database Appliance X7-2-HA, 23
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X7-2S/
Oracle Database Appliance X8-2S, 2	X7-2M, 18
power supplies	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance Version 1, 69	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X5-2, 48	server node
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance Version 1, 64
Oracle Database Appliance X6-2L, 35	server node rear Locate
Oracle Database Appliance X6-2S/	Oracle Database Appliance Version 1, 70
X6-2M, 31	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2-HA, 39
X7-2M, <u>18</u>	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X8-2-HA, 10	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2M, 4	X6-2M, 31
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance X7-2-HA, 23
Power/OK	Oracle Database Appliance X7-2S/
Oracle Database Appliance Version 1, 64	X7-2M, <u>18</u>
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X8-2S, 2

status indicators (continued)	status indicators (continued)
server node rear Locate push to test	Service Required (continued)
Oracle Database Appliance Version 1, 70	Oracle Database Appliance X7-2-HA, 23
server node rear Power/OK	Oracle Database Appliance X7-2S/
Oracle Database Appliance Version 1, 70	X7-2M, <u>18</u>
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X6-2-HA, 39	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X6-2L, 35	storage devices
Oracle Database Appliance X6-2S/	Oracle Database Appliance Version 1, 68
X6-2M, 31	Oracle Database Appliance X3-2/X4-2, 55
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X5-2, 48
Oracle Database Appliance X7-2S/	Oracle Database Appliance X6-2-HA, 39
X7-2M, 18	Oracle Database Appliance X6-2L, 35
Oracle Database Appliance X8-2-HA, 10	Oracle Database Appliance X6-2S/
Oracle Database Appliance X8-2M, 4	X6-2M, 31
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance X7-2-HA, 23
server node rear Ready to Remove	Oracle Database Appliance X7-2S/
Oracle Database Appliance Version 1, 70	X7-2M, 18
server node rear Service Required	Oracle Database Appliance X8-2-HA, 10
Oracle Database Appliance Version 1, 70	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance X8-2S, 2
Oracle Database Appliance X5-2, 48	storage
Oracle Database Appliance X6-2-HA, 39	adding NVMe storage to the server
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance X6-2 series,
Oracle Database Appliance X6-2S/	13
X6-2M, <i>31</i>	Oracle Database Appliance X7-2 series, 9
Oracle Database Appliance X7-2-HA, 23	Oracle Database Appliance X8-2M, 4
Oracle Database Appliance X7-2S/	replacing NVMe storage
X7-2M, 18	Oracle Database Appliance X6-2 series,
Oracle Database Appliance X8-2-HA, 10	12
Oracle Database Appliance X8-2M, 4	Oracle Database Appliance X7-2 series, 7
Oracle Database Appliance X8-2S, 2	Oracle Database Appliance X8-2 series, 3
server node SP OK/Fault	storage drive
Oracle Database Appliance Version 1, 64	installing in server node
Oracle Database Appliance X3-2/X4-2, 55	Oracle Database Appliance Version 1,
Oracle Database Appliance X5-2, 48	A-17
Oracle Database Appliance X6-2-HA, 39	removing from server node
Oracle Database Appliance X6-2L, 35	Oracle Database Appliance Version 1,
Oracle Database Appliance X6-2S/	A-16
X6-2M, 31	storage shelf
Oracle Database Appliance X7-2-HA, 23	adding optional drives to the ODA X6-2-HA
Oracle Database Appliance X7-2S/	storage shelf, 25
X7-2M, 18	adding optional drives to the ODA X7-2-HA
Oracle Database Appliance X8-2-HA, 10	storage shelf, 21
Oracle Database Appliance X8-2M, 4	adding optional drives to the ODA X8-2-HA
Oracle Database Appliance X8-2S, 2	storage shelf, 17
Service Required	replacing a power supply, 17
Oracle Database Appliance Version 1, 64,	replacing a SAS I/O module, 17
67–69	replacing a storage drive, 17
Oracle Database Appliance X3-2/X4-2, 55	replacing storage drives
Oracle Database Appliance X5-2, 48	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X6-2-HA, 39	X5-2 and X6-2-HA/X7-2-HA/X8-2-
Oracle Database Appliance X6-2L, 35	HA, 28
Oracle Database Appliance X6-2S/	servicing hot-plug components, 16
X6-2M, 31	

storage shelf indicators	top cover (continued)
back panel	install (continued)
Oracle Database Appliance X3-2/X4-2, 62	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X5-2, 54	X5-2, 3
Oracle Database Appliance X6-2-HA, 46	Oracle Database Appliance X6-2 series, 2
Oracle Database Appliance X7-2-HA, 29	Oracle Database Appliance X7-2 series, 2
Oracle Database Appliance X8-2-HA, 16	Oracle Database Appliance X8-2 series, 1
front panel	server node
Oracle Database Appliance X3-2/X4-2, 61	Oracle Database Appliance Version 1,
Oracle Database Appliance X5-2, 52	A-11
Oracle Database Appliance X6-2-HA, 44	Oracle Database Appliance X3-2/X4-2/
Oracle Database Appliance X7-2-HA, 27	X5-2, 3
Oracle Database Appliance X8-2-HA, 14	Oracle Database Appliance X6-2 series, 2
	Oracle Database Appliance X7-2 series, 2
т	Oracle Database Appliance X8-2 series, 1
1	top cover middle section
tools	server node
required for service	Oracle Database Appliance Version 1,
Oracle Database Appliance Version 1,	A-12
A-4	troubleshooting
Oracle Database Appliance X3-2/X4-2/	diagnostics and resetting the SP, 1
X5-2, 3	Trusted Platform Module (TPM)
Oracle Database Appliance X6-2 series, 2	support for
Oracle Database Appliance X7-2 series, 2	Oracle Database Appliance Version 1,
Oracle Database Appliance X8-2 series, 1	A-103
top cover	Oracle Database Appliance X3-2/X4-2/
install	X5-2, 6
Oracle Database Appliance Version 1, 5	Oracle Database Appliance X6-2 series, 5
	Oracle Database Appliance X7-2 series, 4
	Oracle Database Appliance X8-2 series. 2