



BEA WebLogic RFID Enterprise Server™

Release Notes

Version 2.0™
Revised: October 12, 2006

Copyright

Copyright © 1995-2006 BEA Systems, Inc. All Rights Reserved.

Restricted Rights Legend

This software is protected by copyright, and may be protected by patent laws. No copying or other use of this software is permitted unless you have entered into a license agreement with BEA authorizing such use. This document is protected by copyright and may not be copied photocopied, reproduced, translated, or reduced to any electronic medium or machine readable form, in whole or in part, without prior consent, in writing, from BEA Systems, Inc.

Information in this document is subject to change without notice and does not represent a commitment on the part of BEA Systems. THE DOCUMENTATION IS PROVIDED “AS IS” WITHOUT WARRANTY OF ANY KIND INCLUDING WITHOUT LIMITATION, ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE. FURTHER, BEA SYSTEMS DOES NOT WARRANT, GUARANTEE, OR MAKE ANY REPRESENTATIONS REGARDING THE USE, OR THE RESULTS OF THE USE, OF THE DOCUMENT IN TERMS OF CORRECTNESS, ACCURACY, RELIABILITY, OR OTHERWISE.

Trademarks and Service Marks

Copyright © 1995-2006 BEA Systems, Inc. All Rights Reserved. BEA, BEA JRocket, BEA WebLogic Portal, BEA WebLogic Server, BEA WebLogic Workshop, Built on BEA, Jolt, JoltBeans, SteelThread, Top End, Tuxedo, and WebLogic are registered trademarks of BEA Systems, Inc. BEA AquaLogic, BEA AquaLogic Data Services Platform, BEA AquaLogic Enterprise Security, BEA AquaLogic Interaction, BEA AquaLogic Interaction Analytics, BEA AquaLogic Interaction Collaboration, BEA AquaLogic Interaction Content Services, BEA AquaLogic Interaction Data Services, BEA AquaLogic Interaction Integration Services, BEA AquaLogic Interaction Process, BEA AquaLogic Interaction Publisher, BEA AquaLogic Interaction Studio, BEA AquaLogic Service Bus, BEA AquaLogic Service Registry, BEA Builder, BEA Campaign Manager for WebLogic, BEA eLink, BEA Kodo, BEA Liquid Data for WebLogic, BEA Manager, BEA MessageQ, BEA SALT, BEA Service Architecture Leveraging Tuxedo, BEA WebLogic Commerce Server, BEA WebLogic Communications Platform, BEA WebLogic Enterprise, BEA WebLogic Enterprise Platform, BEA WebLogic Enterprise Security, BEA WebLogic Express, BEA WebLogic Integration, BEA WebLogic Java Adapter for Mainframe, BEA WebLogic JDriver, BEA WebLogic Log Central, BEA WebLogic Mobility Server, BEA WebLogic Network Gatekeeper, BEA WebLogic Personalization Server, BEA WebLogic Personal Messaging API, BEA WebLogic Platform, BEA WebLogic Portlets for Groupware Integration, BEA WebLogic Real Time, BEA WebLogic RFID Compliance Express, BEA WebLogic RFID Edge Server, BEA WebLogic RFID Enterprise Server, BEA WebLogic Server Process Edition, BEA WebLogic SIP Server, BEA WebLogic WorkGroup Edition, BEA Workshop for WebLogic Platform, BEA Workshop JSP, BEA Workshop JSP Editor, BEA Workshop Struts, BEA Workshop Studio, Dev2Dev, Liquid Computing, and Think Liquid are trademarks of BEA Systems, Inc. Accelerated Knowledge Transfer, AKT, BEA Mission Critical Support, BEA Mission Critical Support Continuum, and BEA SOA Self Assessment are service marks of BEA Systems, Inc.

All other names and marks are property of their respective owners.

Contents

- 1. WebLogic RFID Enterprise Server Known Issues and Recommendations
 - Known Issues 1-1

WebLogic RFID Enterprise Server Known Issues and Recommendations

WebLogic RFID Enterprise Server 2.0 is the first release of the RFID Enterprise Server from BEA Systems. Previously, this product was the ConnectTerra RFTagAware Enterprise Server. You can now reach technical support through the standard BEA means. Select **Support** on the BEA Web site, at www.bea.com, for more information.

The following sections document known problems and workarounds in WebLogic RFID Enterprise Server 2.0.

Known Issues

The following section describes problems that were found in WebLogic RFID Enterprise Server 2.0. Entries include a description of the problem, and a workaround or solution where appropriate.

Tracking Number	Description and Workaround
CR277574	<p>When starting the PointBase RDBMS, invoke the <code>startPointBase</code> and <code>startPointBaseConsole</code> scripts that are located in the <code>WL_HOME\common\bin</code> directory. Do not use the scripts that are located in the <code>BEA_HOME\user_projects\domains\DOMAIN_NAME\bin</code> directory.</p>
CR286935	<p>Uninstalling WebLogic RFID Enterprise Server does not remove the <code><domain-component-info></code> elements and their contents from the file <code>BEA_HOME\user_projects\domains\DOMAIN_NAME\init-info\domain-info.xml</code>.</p> <p>If you remove Enterprise Server component deployments from the domain and then try to re-install them, you will not succeed.</p> <p>Workaround or Solution:</p> <p>Manually delete the <code><domain-component-info></code> elements and their contents from the <code>domain-info.xml</code> file that pertain to the WebLogic RFID Enterprise Server. Specifically, remove those named <i>Reporting Service</i>, <i>Event Service and Data Exchange Service</i>, <i>Serial Number Assignment Service</i>, and <i>Edge Management</i>.</p>
CR287825	<p>In the Master Data Administration Console, once a Master Data Type has entries associated with it, you cannot modify it in any way, including changing the field display order.</p> <p>Workaround or Solution:</p> <p>Export the Master Data Type, delete all its entries in the Console, change the sequence attribute in the Master Data Type Attribute Meta XML, and then re-import it.</p>
CR289184	<p>A <code>FatalDataStoreException</code> is thrown if you start WebLogic Enterprise Server before starting the database.</p>
CR289605	<p>In the Query Subscription Administration Console, when adding subscription parameters, the table displays 10 parameters per page; this is not configurable.</p>
CR289618 CR291543	<p>In the Query Subscription Administration Console, when selecting items from drop-down lists, if you select multiple items (this sometimes happens when using the mouse wheel), an exception is thrown.</p> <p>Workaround or Solution:</p> <p>Select only one item at a time. If possible, avoid using the mouse wheel when selecting items from drop-down lists.</p>
CR290724	<p>When capturing SGLN and GRAI tags with a <code>company_prefix</code> containing 12 digits, the <code>EPC.REFERENCE</code> field gets the value 0 instead of null.</p>

Tracking Number	Description and Workaround
CR284279	In this release of Enterprise Server, there is no QuickStart application, therefore, ignore the <code>quickstart</code> scripts located in the <code>RFID_ENTERPRISE_HOME\common\bin</code> directory.
CR281682	The <code>FILTER_VALUE</code> column is no longer in the Event repository. The filter value is only relevant when searching for tag EPCs; this release of Enterprise Server only allows searching on pure identity EPCs.
CR291842	When installing on UNIX, using a leading backslash (<code>\</code>) in the install directory path causes the Configuration Wizard to fail silently.
CR292047	<p>In the Query Subscription Administration Console, to use authentication on a JMS destination, enter the relevant properties in the Naming Service Properties text field.</p> <p>For example,</p> <pre>java.naming.security.authentication=<i>auth</i> java.naming.security.principal=<i>name</i> java.naming.security.credentials=<i>cred</i></pre> <p>Caution: The values will be stored unencrypted in the database. Therefore, you must either ensure the security of your database or consider the JMS queue password unimportant, if revealed.</p>
CR293031	If your PointBase database connection is lost, you must restart the Enterprise Server after restoring your database connection.
CR293561	<p>When using an Internet Explorer browser to access the Reporting Service or Serial Number Assignment Service Consoles, highlighting an item in a drop-down list and then scrolling rapidly using the mouse wheel may cause an unexpected error.</p> <p>Workaround or Solution:</p> <p>Start a new browser session.</p>
CR292759	The Configuration Wizard displays a list of all the JDKs found in BEA Home. When selecting a JDK for use with WebLogic RFID Enterprise Server 2.0, you must select a JDK version 1.5 or higher.
CR293614	When issuing a <code>poll()</code> request which includes Order By and Order Direction parameters, events will be ordered within each event group but not for the entire event list. The event list includes events grouped by Event Type.

Tracking Number	Description and Workaround
CR279910	<p>If you are using an Oracle database, before running the <code>initEventServiceDatabase</code> script, you must first uncomment this line in the <code>BEA_HOME\user_projects\domains\DOMAIN_NAME\config\kodo.properties</code> file:</p> <pre>#kodo.jdbc.DBDictionary: oracle (TimestampTypeName=TIMESTAMP)</pre>
CR294268	<p>In the Reporting Service Console, Location Selection Criteria > Search Locations table, pressing Enter, Add, or Delete after putting values in the Value text fields results in losing the values.</p> <p>Workaround or Solution:</p> <p>Create the full number of search criteria rows before putting values in the text fields.</p>
CR244182	<p>In the Edge Server Administration Console, the wrong ECSpec Subscriber subscription properties page might be displayed after selecting an ECSpec Subscriber to edit.</p> <p>Workaround or Solution:</p> <p>Click Cancel on the ECSpec Subscriber subscription properties page. Then re-select the ECSpec Subscriber edit link.</p>
CR288549	<p>When you first access the Master Data Administration Console from the Enterprise Server Home page, you will see the following error messages:</p> <pre><Oct 3, 2006 2:45:05 PM EDT> <Error> <netuix> <BEA-423266> <No setter for property :: encoding.> <Oct 3, 2006 2:45:10 PM EDT> <Error> <netuix> <BEA-423137> <There was an error loading the requested URI /PortalConfig/home/HomePage.jsp.></pre> <p>Subsequent accessing the Master Data Administration Console Home page displays the following error message:</p> <pre><Oct 3, 2006 2:45:10 PM EDT> <Error> <netuix> <BEA-423137> <There was an error loading the requested URI /PortalConfig/home/HomePage.jsp.></pre> <p>Workaround or Solution:</p> <p>Disregard these messages; they have no effect on the application.</p>
CR295191	<p>In the Edge Server Administration Console, PLC Stack Light RFID devices always display an UP Device Status regardless of their actual state.</p>

Tracking Number	Description and Workaround
CR295240	<p>If you are using Microsoft SQL Server 2005 and a Microsoft JDBC driver, the Configuration Wizard does not properly construct the connection URL (it lacks the database name component).</p> <p>Workaround or Solution:</p> <p>To use the Microsoft SQL Server 2005 JDBC driver, follow these steps:</p> <ol style="list-style-type: none"> Download and install the driver from the MSDN Web site (follow the Microsoft instructions). Edit this file, <code>C:\BEA_HOME\user_projects\applications\DOMAIN_NAME\kodo.ear\kodo.rar\META-INF\ra.xml</code>, by adding <code>;databasename=<db_name></code> to the Connection URL (replace <code><db_name></code> with the actual database name). Edit this file, <code>C:\BEA_HOME\user_projects\domains\DOMAIN_NAME\config\kodo.properties</code>, by adding <code>;databasename=<db_name></code> to the Connection URL (replace <code><db_name></code> with the actual database name). Add <code>sqljdbc.jar</code> to the classpath in the following database initialization scripts: <code>C:\BEA_HOME\user_projects\domains\DOMAIN_NAME\bin\initEventServiceDatabase</code> <code>C:\BEA_HOME\user_projects\domains\DOMAIN_NAME\bin\initSerialNumberDatabase</code> Add <code>sqljdbc.jar</code> to the <code>C:\BEA_HOME\user_projects\domains\DOMAIN_NAME\lib</code> directory. In the WebLogic Server Administration Console, delete the existing credential map: navigate to Security Realms > myrealm > Credential Mappings, select the check box next to the existing credential mapping Resource Identifier, and click Delete. In the WebLogic Server Administration Console, create a new credential map (click New), with these fields (leave the other fields blank): Remote Host = Connection URL (the same value as in the <code>ra.xml</code> and <code>kodo.properties</code> files) Local User = <code>rfiduser</code> Remote User and Remote Password = database login username and password Restart WebLogic Server. <p>Note: These steps also apply to all other supported JDBC drivers that are not shipped with the product.</p>

Tracking Number	Description and Workaround
CR295481	<p>Upon startup, the Enterprise Server displays multiple repeats of the following message in the console window:</p> <pre data-bbox="301 456 1166 591"><Oct 5, 2006 4:35:28 PM EDT> <Warning> <WorkManager> <BEA-002919> <Unable to find a WorkManager with name weblogic.wsee.mdb.DispatchPolicy. Dispatch policy weblogic.wsee.mdb.DispatchPolicy will map to the default WorkManager for the application bea_wls9_async_response></pre> <p>Workaround or Solution: Disregard these messages.</p>
CR291322	<p>When using Pointbase RDBMS as the enterprise data store, capture operations might yield the exception:</p> <pre data-bbox="301 769 1116 821">kodo.util.DataStoreException: Data exception -- row already exist in index I_EPC_M_URI on table EPC</pre> <p>Workaround or Solution: This exception is harmless; you can ignore it.</p>
CR296046	<p>When configuring a SQL Server database for use with the Enterprise Server, select a case-insensitive collation option (for example, <code>_CI</code>), otherwise, the database initialization scripts will fail. For more information on collation options, see SQL Server Books Online.</p>
