

Oracle® Tuxedo® Mainframe Adapter for OSI TP

Error Messages

Release 10g R3

September 2008

ORACLE®

Tuxedo® Mainframe Adapter for OSI TP Error Messages, Release 10g R3

Copyright © 2007, 2008, Oracle and/or its affiliates. All rights reserved.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this software or related documentation is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, the following notice is applicable:

U.S. GOVERNMENT RIGHTS Programs, software, databases, and related documentation and technical data delivered to U.S. Government customers are "commercial computer software" or "commercial technical data" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, duplication, disclosure, modification, and adaptation shall be subject to the restrictions and license terms set forth in the applicable Government contract, and, to the extent applicable by the terms of the Government contract, the additional rights set forth in FAR 52.227-19, Commercial Computer Software License (December 2007). Oracle USA, Inc., 500 Oracle Parkway, Redwood City, CA 94065.

This software is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications which may create a risk of personal injury. If you use this software in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure the safe use of this software. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software in dangerous applications.

Oracle is a registered trademark of Oracle Corporation and/or its affiliates. Other names may be trademarks of their respective owners.

This software and documentation may provide access to or information on content, products and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services.

Contents

Error and Informational Messages

Error and Informational Messages

The Oracle Tuxedo Mainframe Adapter for OSI TP software issues the following error and informational messages:

1:	<NW_UNISYS messages>
	DESCRIPTION General message to log NW_UNISYS messages
	ACTION Corrective action is given in the messages, otherwise contact Unisys Customer Support.
1000:ERROR	Tried to write more than maxlen:len=%ld, maxlen=%ld
	DESCRIPTION An internal error has been detected while processing the transaction blob record.
	ACTION Contact Unisys Customer Support.
1001:ERROR	Can't create file %s in APPDIR for storing OSITP blob
	DESCRIPTION The Transaction blob file specified could not be created in the APPDIR directory.
	ACTION Check the file privileges of the APPDIR directory.
1002:ERROR	Can't write to OSITP blob file %s in APPDIR

	DESCRIPTION	The GWOSITP software was unable to write to the Transaction blob file specified.
	ACTION	Check to make sure there is sufficient space available in the APPDIR directory.
1100:ERROR	Unable to retrieve Network context, shutdown Gateway!	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support.
1101:ERROR	Unable to retrieve file descriptor, shutdown Gateway!	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support.
1102:INFO	Unable to obtain svc (%s) info from shared memory, request rejected!	
	DESCRIPTION	The requested remote service could not be found in Domain remote service section of shared memory.
	ACTION	Use dmunloadcf command to verify that the remote service specified is defined in the current configuration. If this service is not shown to exists in the current configuration, add it to the DM_REMOTE_SERVICES section of the domain configuration file, shutdown the gateway, rerun dmloadcf, and reboot the OSITP gateway process.
1103:ERROR	Find network transaction failed, shutdown Gateway!	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support
1104:ERROR	Can not create Network Context, request rejected!	

	DESCRIPTION	A network context structure could not be created for the current tpcall. It is possible that the necessary memory could not be allocated.
	ACTION	Adjust system parameters to allow more memory and restart the OSITP Gateway process.
1105:ERROR	Could not retrieve Network context, shutdown Gateway!	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support
1106:ERROR	Unable to obtain remote domain info from shared memory	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support
1108:WARN	Transaction table full, request rejected!	
	DESCRIPTION	The number of current transaction exceeds the number allocated to this gateway as defined by the domain configuration parameter MAXTRAN or the total number of transaction allocated as defined by the TUXCONFIG parameter MAXGTT.
	ACTION	Increase the appropriate Transaction parameter and restart the OSITP Gateway process and domain if necessary.
1110:ERROR	Unable to set nettxid in shmem	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support
1111:ERROR	Cannot associate with network transaction	
	DESCRIPTION	An attempt to start this transaction failed either because this transaction is shown to have already completed or was aborted.

	ACTION	No action is necessary.
1115:ERROR	Could not find RDOM %s cache entry	
	DESCRIPTION	The specified Remote domain should have already been placed in Cache. Either the rdom name or the cache memory has been corrupted.
	ACTION	Contact Unisys Customer Support
1117:ERROR	Cannot set remote domain for transaction	
	DESCRIPTION	The Maximum number of remote domains for a given transaction has been exceeded.
	ACTION	Increase the MAXRDOM parameter in the domain configuration file, rerun dmloadcf, and restart the OSITP Gateway, or reduce the number of remote domains involved in a single transaction.
1118:INFO	Resumed with BLOCKING timeout	
	DESCRIPTION	A blocking timeout has occurred on a request to a remote host.
	ACTION	Examine the ULOG for more information concerning the reason for the failure. Check configuration and increase the BLOCKTIME value, if needed.
1121:ERROR	Bad action state	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support
1122:ERROR	Couldn't retrieve TRAN table from shmem, shutdown Gateway!	
	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support
1123:ERROR	Unable to obtain local tdomain address from shmem	

	DESCRIPTION	An internal error has been detected while processing the action.
	ACTION	Contact Unisys Customer Support.
1124:ERROR	Unable to get remote service information from shared memory	
	DESCRIPTION	The remote service name specified was not found in the DM_REMOTE_SERVICES shared memory tables.
	ACTION	Check the domain configuration file DM_REMOTE_SERVICES section and verify that the Remote service specified has been defined. If not defined, correct the and restart any necessary processes.
1125:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A tpcall was received and the dialog was not in the FREE state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1126:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A tpconnect was received and the dialog was not in the FREE state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1127:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A tpsend was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1128:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	

	DESCRIPTION	A tpsend was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1129:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A Network reply was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1130:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A Network failure was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1131:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A Network tpcall was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1132:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A Network tpconnect was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1133:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	

	DESCRIPTION	A Network tpsend was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1134:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A MSG reply was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1135:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A MSG tpdconnect was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1136:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A MSG failure was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1137:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	A tpconnect confirm was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1138:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	

	DESCRIPTION	A tpconnect fail was received and the dialog was not in a valid state. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1139:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1140:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	An invalid dialog state was encountered. An internal processing error has occurred while processing a transaction.
	ACTION	Contact Unisys Customer Support.
1141:ERROR	Internal error, shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred while processing this action.
	ACTION	Look for prior Userlog messages for more information. Contact Unisys Customer Support.
1142:WARN	Can't find input message buffer, ACALL event deleted!	
	DESCRIPTION	A reply was received for an ACALL event which has been deleted and no longer exists.
	ACTION	No action is necessary.
1143:ERROR	More than one tpcall to AUTOPREPARE svc (%s) attempted, request rejected	
	DESCRIPTION	An attempt to make more than one tpcall within a transaction to an AUTOPREPARE service was attempted. This tpcall was rejected.
	ACTION	Modify the client code or remove the AUTOPREPARE setting on the Service.

1250:ERROR	copy_local_service: Memory error on Local Service
	DESCRIPTION An internal error has been detected while copying a Local Service.
	ACTION Contact Unisys Customer Support.
1251:ERROR	copy_remote_domain: Memory error
	DESCRIPTION An internal error has been detected while copying a Remote Domain.
	ACTION Contact Unisys Customer Support.
1252:ERROR	copy_remote_service: Memory error on remote Service
	DESCRIPTION An internal error has been detected while copying a Remote Service.
	ACTION Contact Unisys Customer Support.
1253:ERROR	gwnwUtility_getLocalConfig: Memory error
	DESCRIPTION An internal error has been detected while getting the local configuration.
	ACTION Contact Unisys Customer Support.
1254:ERROR	gwnwUtility_getLocalConfig: Error walking though LDOM list
	DESCRIPTION An internal error has been detected while walking the LDOM list.
	ACTION Contact Unisys Customer Support.
1255:ERROR	read_cfg_in_file: Error allocating receive buffer
	DESCRIPTION An internal error has been detected while allocating the receive buffer.
	ACTION Contact Unisys Customer Support.
1256:WARNING	read_cfg_in_file: Can't send request to service DMADM. Tperno = %d
	DESCRIPTION The gateway has attempted to call the DMADM server to obtain the OSITP configuration information. The DMADM server did not respond.

	ACTION	If running in a Multiple Machine (MP) configuration the DMADM service is required. In this case you need to modify the ubbconfig file and add DMADM as a service. See OSI-TP Uses guide for help. Reprocess the file with tmlloadcf. Then rerun tmboot. If running in the single machine (SHM) configuration the DMADM service is not needed and this message can be ignored.
1257:ERROR	read_cfg_in_file: Bad version # of BDMCONFIG file	
	DESCRIPTION	The binary file "BDMCONFIG" contains an internal version number which is incompatible with this version of OSITP.
	ACTION	Reprocess your DMCONFIG file with dmlloadcf to create a new binary "BDMCONFIG" file.
1258:ERROR	read_cfg_in_file: Memory error on local domains	
	DESCRIPTION	An internal error has been detected while processing the local domains.
	ACTION	Contact Unisys Customer Support.
1259:ERROR	read_cfg_in_file: Memory error on Remote domains	
	DESCRIPTION	An internal error has been detected while processing the remote domains.
	ACTION	Contact Unisys Customer Support.
1260:ERROR	Unable to allocate memory for Remote domains	
	DESCRIPTION	An internal error has been detected while processing the remote domains.
	ACTION	Contact Unisys Customer Support.
1261:ERROR	read_cfg_in_file: Memory error on Local services	
	DESCRIPTION	An internal error has been detected while processing Local Services.
	ACTION	Contact Unisys Customer Support.

1262:ERROR	read_cfg_in_file: Memory error on Remote services
	DESCRIPTION An internal error has been detected while processing Remote Services.
	ACTION Contact Unisys Customer Support.
1263:ERROR	read_cfg_in_file: fopen error on input file %s
	DESCRIPTION Error opening input file.
	ACTION Verify file exists and is accessible by you.
1264:ERROR	read_cfg_in_file: Read error on # of Version number.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1265:ERROR	Encode of AE Title (%s) failed for RDOM (%s)
	DESCRIPTION An error occurred while encoding the AE Title for the indicated remote domain.
	ACTION Contact Unisys Customer Support.
1266:ERROR	read_cfg_in_file: Read error on # of Local domains.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1267:ERROR	Encode of AE Title (%s) failed for LDOM (%s)
	DESCRIPTION An error occurred while encoding the AE Title for the indicated local domain.
	ACTION Check the definition of the AE Title for this local domain in the dmconfig file and correct. Shutdown the Gateway, rerun dmloadcf and reboot the Gateway process.
1268:ERROR	read_cfg_in_file: Read error on local domains
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.

1269:ERROR	read_cfg_in_file: Read error on # of Remote domains.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1271:ERROR	read_cfg_in_file: Read error on Remote domains.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1273:ERROR	read_cfg_in_file: Read error on # of Local services.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1275:ERROR	read_cfg_in_file: Read error on Local Services.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1276:ERROR	read_cfg_in_file: Read error on # of Remote services.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1278:ERROR	read_cfg_in_file: Read error on Remote Services.
	DESCRIPTION Error processing binary configuration file.
	ACTION Reprocess dmconfig text file with dmloadcf.
1279:ERROR	BDMCONFIG environment variable is not set.
	DESCRIPTION The environment variable BDMCONFIG is not set.
	ACTION Set the environment variable BDMCONFIG to the fully qualified name of the BDMCONFIG file.
1325:ERROR	ioptr_init_char failed

	DESCRIPTION	An internal error occurred; gw_nw_buf_encode failed to initialize ioptr structure. The vbuf for which the ioptr was to be initialized is corrupted.
	ACTION	Contact Unisys Customer Support.
1326:ERROR	ASN.1 ENCODE failed %s	
	DESCRIPTION	The Gateway process was unable to encode the typed buffer.
	ACTION	Look for further errors which indicate the type and subtype of the buffer which could not be encoded. Check the encoding types and the typed buffer definitions to ensure that they are compatible. Correct any discrepancies and restart the OSITP Gateway process if necessary.
1328:ERROR	ASN.1 DECODE failed %s	
	DESCRIPTION	The Gateway process was unable to decode the typed buffer.
	ACTION	Look for further errors which indicate the type and subtype of the buffer which could not be decoded. Check the encoding types and the typed buffer definitions to ensure that they are compatible. Correct any discrepancies and restart the OSITP Gateway process if necessary.
1329:ERROR	tpalloc failed: %s	
	DESCRIPTION	An Internal error has occurred while trying to perform a tpalloc.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1341:ERROR	Unable to process typed buffer, type=%s subtype=%s	
	DESCRIPTION	The Gateway process was unable to convert the specified buffer to an ASN.1 encoded buffer.

	ACTION	Check the encoding types and the typed buffer definitions to ensure that they are compatible. If buffer conversion is being performed, check to make that the data conversion specified is valid. Correct any discrepancies and restart the OSITP Gateway process if necessary.
1347:ERROR	Unable to reconstruct typed buffer, type=%s subtype=%s	
	DESCRIPTION	The Gateway process was unable to convert an ASN1 encoded buffer to the specified buffer.
	ACTION	Check the encoding types and the typed buffer definitions to ensure that they are compatible. If buffer conversion is being performed, check to make that the data conversion specified is valid. Correct any discrepancies and restart the OSITP Gateway process if necessary.
1348:ERROR	INRECTYPE buffer type (%s) cannot be converted to NATIVE A SERIES buffer.	
	DESCRIPTION	The buffer type, specified by INRECTYPE, to be converted to a NATIVE A SERIES buffer is not a valid type for this conversion. Only buffers of type X_COMMON, X_C_TYPE, VIEW, and VIEW32 are valid.
	ACTION	Check to make sure you are calling this service with the correct buffer type, or that the encoding of NATIVE_A_SERIES is correct.
1349:ERROR	Buffer type (%s) cannot be converted to a NATIVE A SERIES buffer.	
	DESCRIPTION	The buffer type to be converted to a NATIVE A SERIES buffer is not a valid type for this conversion. Only buffers of type X_COMMON, X_C_TYPE, VIEW, and VIEW32 are valid.

	ACTION	Check to make sure you are calling this service with the correct buffer type or that the encoding of NATIVE_A_SERIES is correct.
1350:ERROR	read_cfg_in_file: fopen error on input file %s	
	DESCRIPTION	DMADM had a problem opening the binary configuration file, BDMCONFIG.
	ACTION	Make sure the binary configuration file, BDMCONFIG, exists and is accessible to you.
1351:ERROR	Bad File Handle for binary file	
	DESCRIPTION	An internal error was detected in DMADM while trying to process the binary configuration file (BDMCONFIG).
	ACTION	Contact Unisys Customer Support.
1352:ERROR	tpalloc failed in DMADM	
	DESCRIPTION	An internal error was detected in DMADM.
	ACTION	Contact Unisys Customer Support.
1353:ERROR	BDMCONFIG environment variable is not set.	
	DESCRIPTION	The environment variable BDMCONFIG is not set.
	ACTION	Set the environment variable BDMCONFIG to the fully qualified name of the BDMCONFIG file.
1509:ERROR	Invalid conversation context	
	DESCRIPTION	An internal error has been detected.
	ACTION	Contact Unisys Customer Support.
1511:ERROR	Protocol error, msg state(%d), shutdown Gateway!	
	DESCRIPTION	An internal error has been detected.
	ACTION	Contact Unisys Customer Support.

1513:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.
1514:ERROR	Protocol error, dial state(%d), shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.
1515:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.
1517:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.
1518:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.
1521:ERROR	Could not find transaction node, shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.
1526:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.
1530:ERROR	Could not find transaction node, shutdown Gateway!
	DESCRIPTION An internal error has been detected.
	ACTION Contact Unisys Customer Support.

1601:ERROR	Can not create Network Context, request rejected!	
	DESCRIPTION	A Network Context structure could not be allocated for the requested tpconnect. There is not enough process memory available to allocate the structure necessary for processing the requested tpconnect.
	ACTION	Increase system parameters to allow more process memory and restart the Gateway.
1602:ERROR	Could not retrieve Network context, shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support
1603:ERROR	Could not retrieve Network context, shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support
1604:INFO	Unable to obtain svc (%s)info from shared memory, request rejected!	
	DESCRIPTION	The service requested could not be found in the shared memory DM_REMOTE_SERVICES section. The shared memory has been corrupted.
	ACTION	Contact Unisys Customer Support.
1605:WARN	Transaction table full, request rejected!	
	DESCRIPTION	The number of outstanding Transactions has exceeded the Maximum number allowed as defined by the Local Domains MAXTRAN or the Machines definition MAXGTT.
	ACTION	Increase either the MAXTRAN or MAXGTT configuration parameter and restart the Gateway.
1606:WARN	Unable to create gwnwClientAgent, request rejected!	

	DESCRIPTION	There is not enough process memory available to allocate the structure necessary for processing the requested tpconnect.
	ACTION	Increase system parameters to allow more process memory and restart the Gateway.
1607:ERROR	Unable to obtain remote domain info from shared memory	
	DESCRIPTION	The remote domain could not be found in the shared memory DM_REMOTE_DOMAINS section. The shared memory has been corrupted.
	ACTION	Contact Unisys Customer Support.
1608:ERROR	Conversation identifier is invalid	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1609:ERROR	Couldn't retrieve TRAN table from shmem	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1610:ERROR	Unable to set nettxid in shmem	
	DESCRIPTION	An attempt to set the network transaction id in shared memory failed. This could indicate that the shared memory tables have been corrupted.
	ACTION	Contact Unisys Customer Support.
1611:ERROR	Cannot associate with network transaction	
	DESCRIPTION	An attempt to start this transaction failed either because this transaction is shown to have already completed or was aborted.
	ACTION	No action is necessary.
1612:ERROR	Cannot set remote domain for transaction	

	DESCRIPTION	An attempt to set the remote domain for this transaction failed.
	ACTION	Contact Unisys Customer Support.
1613:ERROR	Invalid action index	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1614:ERROR	Invalid incoming conversation context	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1615:ERROR	Conversation identifier is NULL	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1616:ERROR	Invalid action index	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1617:ERROR	Invalid conversation context	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1619:INFO	Resumed with blocking timeout	
	DESCRIPTION	This conversation incurred a blocking timeout and will be aborted.
	ACTION	Examine the ULOG for more information concerning the reason for the failure. Check configuration and increase the BLOCKTIME value, if needed.
1620:ERROR	Bad action state	
	DESCRIPTION	An internal processing error has occurred.

	ACTION	Contact Unisys Software Support.
1621:ERROR	Could not find RDOM %s cache entry	
	DESCRIPTION	The remote domain id specified for this service could not be found in the remote domain cache. This could indicate that the configuration file is incorrect or that there has been corruption of the remote domain cache.
	ACTION	Check the domain configuration file and make sure that the remote domain specified is defined in the file correctly. If in error, correct the error, shutdown the gateway, reload the configuration file, and restart the gateway.
1622:ERROR	Invalid outgoing conversation context	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Software Support.
1705:INFO	Found transaction without log record	
	DESCRIPTION	A previous transaction was found, however a log record for this transaction did not exist. This transaction will be rolled back.
	ACTION	No Action necessary.
1706:ERROR	Create transaction node failed, shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1714:WARN	log record refused	
	DESCRIPTION	The transaction log record could not be recovered. The transaction will be rolled back.
	ACTION	No action is necessary.
1717:ERROR	Unable to create action to handle restarted transaction!	
	DESCRIPTION	An internal processing error has occurred.

	ACTION	Contact Unisys Customer Support.
1725:ERROR	Create transaction node failed, shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1726:ERROR	Unable to create action to handle restarted transaction!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1728:ERROR	Unable to create action to handle restarted transaction!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1752:ERROR	Can't find view file, %s	
	DESCRIPTION	The specified view file could not be found.
	ACTION	Check to make sure that the view file exists and the VIEWFILES or VIEWFILES32 environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR or VIEWDIR32 environment variable.
1753:ERROR	APDU buffer overflow	
	DESCRIPTION	The APDU buffer allocated was not large enough to hold the data contained in the view buffer.
	ACTION	Contact Unisys Customer Support.
1754:ERROR	Memory allocation error	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1755:ERROR	APDU buffer overflow	

	DESCRIPTION	The APDU buffer allocated was not large enough to hold the data contained in the view buffer.
	ACTION	Contact Unisys Customer Support.
1756:ERROR	Memory allocation error	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1757:ERROR	APDU buffer overflow	
	DESCRIPTION	The APDU buffer allocated was not large enough to hold the data contained in the view buffer.
	ACTION	Contact Unisys Customer Support.
1758:ERROR	Memory allocation error	
	DESCRIPTION	An internal error occured; An attempt to allocate a buffer failed.
	ACTION	Contact Unisys Technical Support
1759:ERROR	Invalid data type for X_C_TYPE	
	DESCRIPTION	The data type contained in the view is not a valid X_C_TYPE buffer data type. Valid X_C_TYPE data types are short, int, long, char, float, double, decimal, string, and carray.
	ACTION	Look for further error which indicate the name of the VIEW buffer which is in error. Correct the View buffer to contain the correct data types or define the buffer as X_C_TYPE.
1760:ERROR	VIEW32 file %s not found	
	DESCRIPTION	The specified view file could not be found.

	ACTION	Check to make sure that the view file exists and the VIEWFILES32 environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR32 environment variable.
1761:ERROR	Can't find view file %s	
	DESCRIPTION	The specified view file could not be found.
	ACTION	Check to make sure that the view file exists and the VIEWFILES or VIEWFILES32 environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR or VIEWDIR32 environment variable.
1762:ERROR	Missing data element in received Data Stream	
	DESCRIPTION	The X_C_TYPE buffer did not contain the expected data element as defined by the destination VIEW.
	ACTION	Look for further User Log messages which indicate what the VIEW Type and Subtype was involved, then make sure the source VIEW and destination VIEW definitions are identical. Correct the VIEWS and restart the necessary gateway process.
1763:ERROR	APDU buffer overflow	
	DESCRIPTION	The APDU buffer allocated was not large enough to hold the data contained in the view buffer.
	ACTION	Contact Unisys Customer Support.
1764:ERROR	Missing data element in received Data Stream	
	DESCRIPTION	The X_C_TYPE buffer did not contain the expected data element as defined by the destination VIEW.

	ACTION	Look for further User Log messages which indicate what the VIEW Type and Subtype was involved, then make sure the source VIEW and destination VIEW definitions are identical. Correct the VIEWS and restart the necessary gateway process.
1765:ERROR	APDU buffer overflow	
	DESCRIPTION	The APDU buffer allocated was not large enough to hold the data contained in the view buffer.
	ACTION	Contact Unisys Customer Support.
1766:ERROR	Missing data element in received Data Stream	
	DESCRIPTION	The X_C_TYPE buffer did not contain the expected data element as defined by the destination VIEW.
	ACTION	Look for further User Log messages which indicate what the VIEW Type and Subtype was involved, then make sure the source VIEW and destination VIEW definitions are identical. Correct the VIEWS and restart the necessary gateway process.
1767:ERROR	Invalid data type for %s	
	DESCRIPTION	The data type contained in the view is not a valid X_C_TYPE buffer data type. Valid X_C_TYPE data types are short, int, long, char, float, double, decimal, string, and carray.
	ACTION	Look for further error which indicate the name of the VIEW buffer which is in error. Correct the View buffer to contain the correct data types or define the buffer as X_C_TYPE.
1901:ERROR	Invalid Buffer Type	
	DESCRIPTION	A null buffer was passed to a service call/service reply.

	ACTION	Make sure the buffer is allocated, and the buffer is not NULL
1902:ERROR	Invalid Buffer Type	
	DESCRIPTION	Buffer type not defined in the buffer type switch
	ACTION	Examine the application and the configuration to determine which buffer type is being used. GWOSITP only supports standard TUXEDO buffer types over the domain gateway. If the buffer type is VIEW, VIEW32, then also examine the environment variables VIEWDIR, VIEWFILES, VIEWDIR32, and VIEWFILES32
1903:ERROR	Unable to obtain svc info from svcinfo	
	DESCRIPTION	An internal error occurred; gw_nw_buf_encode failed to obtain remote service information
	ACTION	Contact Unisys Technical Support
1904:ERROR	Unable to obtain INRECTYPE for remote service	
	DESCRIPTION	An internal error occurred; gw_nw_buf_encode failed to obtain INRECTYPE for remote service
	ACTION	Contact Unisys Technical Support
1905:ERROR	Can't find LSVC entry by rname %s	
	DESCRIPTION	An internal error occurred; gw_nw_buf_encode failed to obtain local service information
	ACTION	Contact Unisys Technical Support
1906:ERROR	Unable to obtain INRECTYPE for local service	
	DESCRIPTION	An internal error occurred; gw_nw_buf_encode failed to obtain INRECTYPE for local service

	ACTION	Contact Unisys Technical Support
1907:ERROR	Received type(%s:%s) does not match INBUFTYPE(%s:%s)	
	DESCRIPTION	Buffer received by the gateway does not match INBUFTYPE configuration
	ACTION	Reconfigure INBUFTYPE to match incoming buffer type and subtype
1908:ERROR	VIEW file %s not found	
	DESCRIPTION	The specified view file could not be found.
	ACTION	Check to make sure that the view file exists and the VIEWFILES environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR environment variable.
1909:ERROR	Conversion invalid from (%s) to (%s)	
	DESCRIPTION	Conversion from a 16:bit buffer to 32:bit buffer, or vice versa, is not allowed
	ACTION	Make sure conversion specified is between 16-bit buffers, or between 32-bit buffers
1910:ERROR	INRECTYPE not configured for (%s)	
	DESCRIPTION	Buffers of type FML / FML32 cannot be transmitted to a remote system
	ACTION	Configure INRECTYPE to VIEW, X_C_TYPE, or X_COMMON
1911:ERROR	VIEW file (%s) not found	
	DESCRIPTION	Could not find the listed view file
	ACTION	Verify VIEWDIR and VIEWFILES environment variables
1912:ERROR	VIEW file (%s) not found	
	DESCRIPTION	Could not find the listed view file

	ACTION	Verify VIEWDIR32 and VIEWFILES32 environment variables
1913:ERROR	Invalid buffer type specified	
	DESCRIPTION	Buffer type not defined in the buffer type switch
	ACTION	Examine the application and the configuration to determine which buffer type is being used. GWOSITP only supports standard TUXEDO buffer types over the domain gateway. If the buffer type is VIEW, VIEW32, then also examine the environment variables VIEWDIR, VIEWFILES, VIEWDIR32, and VIEWFILES32
1914:ERROR	Memory allocation failure	
	DESCRIPTION	An internal error occurred; gw_nw_buf_encode failed to allocate XATMI_typed_buffer
	ACTION	Contact Unisys Technical Support
1915:ERROR	Invalid Buffer Type	
	DESCRIPTION	Buffer type not defined in the buffer type switch
	ACTION	Examine the application and the configuration to determine which buffer type is being used. GWOSITP only supports standard TUXEDO buffer types over the domain gateway. If the buffer type is VIEW, VIEW32, then also examine the environment variables VIEWDIR, VIEWFILES, VIEWDIR32, and VIEWFILES32
1916:ERROR	Memory allocation failure	
	DESCRIPTION	An internal error occurred; gw_nw_buf_encode failed to allocate ap_osi_vbuf
	ACTION	Contact Unisys Technical Support

1917:ERROR	Encode failed
	DESCRIPTION An internal error occurred; gw_nw_buf_encode failed to encode typed buffer
	ACTION Contact Unisys Technical Support
1918:ERROR	Conversion invalid from (%s) to (%s)
	DESCRIPTION Buffers of type FML and FML32 cannot be transmitted to a remote system
	ACTION Remove INRECTYPE or reconfigure INRECTYPE to a different type such as a VIEW
1919:ERROR	Received type(%s:%s) does not match OUTRECTYPE(%s:%s)
	DESCRIPTION Buffer received by the gateway does not match OUTRECTYPE configuration
	ACTION Reconfigure OUTRECTYPE to match incoming buffer type and subtype
1920:ERROR	OUTBUFTYPE(%s:%s) invalid for received type(%s)
	DESCRIPTION Received type cannot be converted to OUTBUFTYPE
	ACTION Configure OUTBUFTYPE to X_OCTET, STRING, or CARRAY
1921:ERROR	Cannot open %s:%s
	DESCRIPTION Could not find the listed view file
	ACTION Verify VIEWDIR and VIEWFILES environment variables
1922:ERROR	FML incompatible field in %s:%s
	DESCRIPTION The listed view contains packed decimal data type. Views containing this type cannot be used for FML-to-view or view-to-view conversions

	ACTION	Remove packed decimal fields from the input FML or view, or send the same view structure to the local gateway that is sent to the remote gateway
1923:ERROR	Cannot convert view (%s) not mapped to FML	
	DESCRIPTION	Listed view is not mapped to FML
	ACTION	Recompile the view WITHOUT the '-n' option of the view compiler
1924:ERROR	tpalloc for %s failed	
	DESCRIPTION	Allocation of an TUXEDO typed buffer failed
	ACTION	Contact Unisys Technical Support
1925:ERROR	Fvstof failed for %s:%s	
	DESCRIPTION	The conversion of a C structure to a fielded buffer failed
	ACTION	Contact Unisys Technical Support
1926:ERROR	Cannot open %s:%s	
	DESCRIPTION	Could not find the listed view file
	ACTION	Verify VIEWDIR and VIEWFILES environment variables
1927:ERROR	Cannot convert view (%s) not mapped to FML	
	DESCRIPTION	Listed view is not mapped to FML
	ACTION	Recompile the view WITHOUT the '-n' option of the view compiler
1928:ERROR	tpalloc for %s:%s failed	
	DESCRIPTION	Allocating a typed buffer for the listed view failed
	ACTION	Contact Unisys Technical Support
1929:ERROR	Fvftos failed for %s:%s	

	DESCRIPTION	The conversion of a fielded buffer to a C structure failed
	ACTION	Contact Unisys Technical Support
1930:ERROR	Unable to obtain svc info from svcinfo	
	DESCRIPTION	An internal error occurred; gw_nw_buf_decode failed to obtain remote service information
	ACTION	Contact Unisys Technical Support
1931:ERROR	Unable to obtain OUTRECTYPE for remote service	
	DESCRIPTION	An internal error occurred; gw_nw_buf_decode failed to obtain OUTRECTYPE for remote service
	ACTION	Contact Unisys Technical Support
1932:ERROR	Can't find LSVC entry by rname <%s>	
	DESCRIPTION	An internal error occurred; gw_nw_buf_decode failed to obtain local service information
	ACTION	Contact Unisys Technical Support
1933:ERROR	Unable to obtain OUTRECTYPE for local service	
	DESCRIPTION	An internal error occurred; gw_nw_buf_decode failed to obtain OUTRECTYPE for local service
	ACTION	Contact Unisys Technical Support
1934:ERROR	ioptr_init_char failed	
	DESCRIPTION	An internal error occurred; gw_nw_buf_decode failed to initialize ioptr
	ACTION	Contact Unisys Technical Support
1935:ERROR	Memory allocation failure	

	DESCRIPTION	An internal error occurred; gw_nw_buf_decode failed to allocate XATMI_typed_buffer
	ACTION	Contact Unisys Technical Support
1936:ERROR	Invalid Buffer Type	
	DESCRIPTION	Buffer type not defined in the buffer type switch
	ACTION	Examine the application and the configuration to determine which buffer type is being used. GWOSITP only supports standard TUXEDO buffer types over the domain gateway. If the buffer type is VIEW, VIEW32, then also examine the environment variables VIEWDIR, VIEWFILES, VIEWDIR32, and VIEWFILES32
1937:ERROR	conversion invalid from < %s > to < %s >	
	DESCRIPTION	Conversion from a 16-bit buffer to 32-bit buffer, or vice versa, is not allowed
	ACTION	Make sure conversion specified is between two 16-bit buffers, or between two 32-bit buffers
1947:ERROR	Service < %s > is denied Access	
	DESCRIPTION	The user has been denied access to the specified service. The Remote domain from which this call was initiated is not specified in the Access Control list for this service.
	ACTION	Check the Access Control list and add the Remote Domain if necessary and restart the Gateway process.
1949:ERROR	Undefined buffer type	
	DESCRIPTION	An internal processing error has occurred. The ASN.1 buffer type to convert the view to is not X_OCTET, X_COMMON, or X_C_TYPE.

	ACTION	Contact Unisys Customer Support.
1950:ERROR	Not a typed buffer	
	DESCRIPTION	An internal processing error has occurred. The buffer to convert to X_OCTET was null.
	ACTION	Contact Unisys Customer Support.
1951:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1952:ERROR	Not a typed buffer	
	DESCRIPTION	An internal processing error has occurred. The buffer to convert to X_COMMON was null.
	ACTION	Contact Unisys Customer Support.
1953:ERROR	Can't find view file	
	DESCRIPTION	The specified view file could not be found.
	ACTION	Check to make sure that the view file exists and the VIEWFILES or VIEWFILES32 environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR or VIEWDIR32 environment variable.
1954:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1955:ERROR	APDU buffer overflow	

	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1956:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1957:ERROR	APDU buffer overflow	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1958:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1959:ERROR	Buffer size error	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1960:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1961:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.

	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1962:ERROR	Invalid data type for X_COMMON	
	DESCRIPTION	The data type contained in the view is not a valid X_COMMON buffer data type. Valid X_COMMON data types are short, long, char, string, and carray.
	ACTION	Look for further error which indicate the name of the VIEW buffer which is in error. Correct the View buffer to contain the correct data types or define the buffer as X_C_TYPE.
1963:ERROR	Not a typed buffer	
	DESCRIPTION	An internal processing error has occurred. The buffer to convert to X_OCTET was null.
	ACTION	Contact Unisys Customer Support.
1964:ERROR	Can't find view file	
	DESCRIPTION	The specified view file could not be found.
	ACTION	Check to make sure that the view file exists and the VIEWFILES or VIEWFILES32 environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR or VIEWDIR32 environment variable.
1965:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1966:ERROR	APDU buffer overflow	
	DESCRIPTION	An Internal processing error has occurred.

	ACTION	Contact Unisys Customer Support.
1967:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1968:ERROR	APDU buffer overflow	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1969:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1970:ERROR	Buffer size error	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1971:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
1972:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.

1973:ERROR	Invalid data type for X_C_TYPE
	DESCRIPTION The data type contained in the view is not a valid X_C_TYPE buffer data type. Valid X_C_TYPE data types are short, int, long, char, float, double, decimal, string, and carray.
	ACTION Look for further error which indicate the name of the VIEW buffer which is in error. Correct the View buffer to contain the correct data types or define the buffer as X_C_TYPE.
1974:ERROR	Undefined buffer type
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
1975:ERROR	Not a typed buffer
	DESCRIPTION An internal processing error has occurred. The buffer to convert to X_OCTET was null.
	ACTION Contact Unisys Customer Support.
1976:ERROR	Not a typed buffer
	DESCRIPTION An internal processing error has occurred. The buffer to convert to X_C_TYPE was null.
	ACTION Contact Unisys Customer Support.
1977:ERROR	Can't find view file
	DESCRIPTION The specified view file could not be found.
	ACTION Check to make sure that the view file exists and the VIEWFILES or VIEWFILES32 environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR or VIEWDIR32 environment variable.
1978:ERROR	APDU buffer overflow

	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1979:ERROR	APDU buffer overflow	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1980:ERROR	Invalid data type for X_C_TYPE	
	DESCRIPTION	The data type contained in the view is not a valid X_C_TYPE buffer data type. Valid X_C_TYPE data types are short, int, long, char, float, double, decimal, string, and carray.
	ACTION	Look for further error which indicate the name of the VIEW buffer which is in error. Correct the View buffer to contain the correct data types or define the buffer as X_C_TYPE.
1981:ERROR	Not a typed buffer	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1982:ERROR	Can't find view file	
	DESCRIPTION	The specified view file could not be found.
	ACTION	Check to make sure that the view file exists and the VIEWFILES or VIEWFILES32 environment variables contain the specified view file name. Also check to make sure that the view file is located in the directory specified by the VIEWDIR or VIEWDIR32 environment variable.
1983:ERROR	APDU buffer overflow	
	DESCRIPTION	An Internal processing error has occurred.

	ACTION	Contact Unisys Customer Support.
1984:ERROR	APDU buffer overflow	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1985:ERROR	APDU buffer overflow	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1986:ERROR	Invalid data type for X_COMMON	
	DESCRIPTION	The data type contained in the view is not a valid X_COMMON buffer data type. Valid X_COMMON data types are short, long, char, string, and carray.
	ACTION	Look for further error which indicate the name of the VIEW buffer which is in error. Correct the View buffer to contain the correct data types or define the buffer as X_C_TYPE.
1987:ERROR	Invalid Buffer Type	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
1988:ERROR	Can't get local service < %s > from configuration file	
	DESCRIPTION	The service requested could not be found in the shared memory section defined by DM_LOCAL_SERVICES.
	ACTION	Check the configuration files and verify that the service is defined as in the DM_LOCAL_SERVICES section. If necessary, Add the service definition and restart the OSITP Gateway process.
1990:ERROR	Incoming request not allowed access to any local services	

	DESCRIPTION	An incoming service call was denied access because the Remote Domain is not specified the ACL List for the local service.
	ACTION	Look for further error messages which specify the local service which has been denied access. If access is required, add the remote domain to the services ACL list.
1997:ERROR	Can't find LSVC entry by rname %s	
	DESCRIPTION	The requested service could not be found in the shared memory DM_LOCAL_SERVICES section.
	ACTION	Check the DM_LOCAL_SERVICES section of the configuration file for the requested service. If not found add the service and restart the OSITP Gateway process.
1999:ERROR	Invalid Buffer Type	
	DESCRIPTION	The buffer type is not a valid buffer type.
	ACTION	Look for further error which indicate the name of the buffer which is in error.
2000:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2001:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2002:ERROR	View file must be specified	

	DESCRIPTION	The VIEW32 buffer did not have a buffer subtype.
	ACTION	Check the tmalloc call and make sure it specifies a subtype. Look for further User log messages which specify the buffer in error.
2003:ERROR	Invalid Buffer Type	
	DESCRIPTION	The buffer to be converted to X_C_TYPE is not a valid tmalloc buffer.
	ACTION	Check the tmalloc call and make sure it specifies a subtype. Look for further User log messages which specify the buffer in error.
2004:ERROR	VIEW32 file is required	
	DESCRIPTION	The VIEW32 buffer did not have a buffer subtype.
	ACTION	Check the tmalloc call and make sure it specifies a subtype. Look for further User log messages which specify the buffer in error.
2005:ERROR	Missing data element in received Data Stream	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2006:ERROR	Missing data element in received Data Stream	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2007:ERROR	Missing data element in received Data Stream	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2008:ERROR	Missing data element in received Data Stream	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.

2009:ERROR	Missing data element in received Data Stream
	DESCRIPTION An Internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2010:ERROR	Missing data element in received Data Stream
	DESCRIPTION An Internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2011:ERROR	Request block is invalid
	DESCRIPTION An Internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2012:ERROR	Memory allocation error
	DESCRIPTION An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2013:ERROR	Request block is invalid
	DESCRIPTION An Internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2014:ERROR	Memory allocation error
	DESCRIPTION An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2015:ERROR	Request block is invalid
	DESCRIPTION An Internal processing error has occurred.
	ACTION Contact Unisys Customer Support.

2016:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2017:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2018:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2019:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2020:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2021:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2022:ERROR	Memory allocation error

	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2023:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2024:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2025:ERROR	ASN.1 DECODE failed, out of short integer range	
	DESCRIPTION	The value to decode was larger than what would fit into a short integer.
	ACTION	Modify the VIEW field to use a long integer, recompile the VIEW as necessary.
2026:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2027:ERROR	ASN.1 DECODE failed, out of short integer range	
	DESCRIPTION	The value to decode was larger than what would fit into a short integer.
	ACTION	Modify the VIEW field to use a long integer, recompile the VIEW as necessary.
2028:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2029:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2030:ERROR	Received type does not match definition	

		DESCRIPTION	The received type does not match the definition specified by the VIEW.
		ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2031:ERROR	Request block is invalid		
		DESCRIPTION	An Internal processing error has occurred.
		ACTION	Contact Unisys Customer Support.
2032:ERROR	Received type does not match definition		
		DESCRIPTION	The received type does not match the definition specified by the VIEW.
		ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2033:ERROR	Received type does not match definition		
		DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2034:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2035:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2036:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2037:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2038:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2039:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2040:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2041:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2042:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2043:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2044:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.

2045:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2046:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2047:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2048:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2049:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2050:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2051:ERROR	Memory allocation error
DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.

	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2052:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2053:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2054:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2055:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2056:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2057:ERROR	Memory allocation error	

	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2058:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2059:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2060:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2061:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2062:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2063:ERROR	Memory allocation error	

	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2064:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2065:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2066:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2067:ERROR	ASN.1 DECODE failed, out of short integer range	
	DESCRIPTION	The value to decode was larger than what would fit into a short integer.
	ACTION	Modify the VIEW field to use a long integer, recompile the VIEW as necessary.

2068:ERROR	Received type does not match definition
DESCRIPTION	The received type does not match the definition specified by the VIEW.
ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2069:ERROR	ASN.1 DECODE failed, out of short integer range
DESCRIPTION	The value to decode was larger than what would fit into a short integer.
ACTION	Modify the VIEW field to use a long integer, recompile the VIEW as necessary.
2070:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2071:ERROR	Received type does not match definition
DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2072:ERROR	ASN.1 DECODE failed, out of integer range	
	DESCRIPTION	The value to decode was larger than what would fit into a integer.
	ACTION	Modify the VIEW field to use a field which allows larger values, recompile the VIEW as necessary.
2073:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2074:ERROR	ASN.1 DECODE failed, out of integer range	
	DESCRIPTION	The value to decode was larger than what would fit into a integer.

	ACTION	Modify the VIEW field to use a field which allows larger values, recompile the VIEW as necessary.
2075:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2076:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2077:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2078:ERROR	Request block is invalid	

	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2079:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2080:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2081:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2082:ERROR	Received type does not match definition	

		DESCRIPTION	The received type does not match the definition specified by the VIEW.
		ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2083:ERROR	ASN.1 DECODE failed, float range out of local limit		
		DESCRIPTION	The value to decode was larger than what would fit into a float.
		ACTION	Modify the VIEW field to use a double, recompile the VIEW as necessary.
2084:ERROR	Received type does not match definition		
		DESCRIPTION	The received type does not match the definition specified by the VIEW.
		ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2085:ERROR	ASN.1 DECODE failed, float range out of local limit		
		DESCRIPTION	The value to decode was larger than what would fit into a float.

	ACTION	Modify the VIEW field to use a double, recompile the VIEW as necessary.
2086:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2087:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2088:ERROR	ASN.1 DECODE failed, double range out of local limit	
	DESCRIPTION	The value to decode was larger than what would fit into a double.
	ACTION	Modify VIEW field to correct the problem.
2089:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2090:ERROR	ASN.1 DECODE failed, double range out of local limit	
	DESCRIPTION	The value to decode was larger than what would fit into a double.
	ACTION	Modify VIEW field to correct the problem.
2091:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2092:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2093:ERROR	Received type does not match definition	

		DESCRIPTION	The received type does not match the definition specified by the VIEW.
		ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2094:ERROR	Received type does not match definition		
		DESCRIPTION	The received type does not match the definition specified by the VIEW.
		ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2095:ERROR	Received type does not match definition		
		DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2096:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2097:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2098:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2099:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2100:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2101:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2102:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2103:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2104:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2105:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2106:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2107:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2108:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2109:ERROR	Request block is invalid	

	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2110:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2111:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2112:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2113:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2114:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2115:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2116:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2117:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.

ACTION		Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2118:ERROR	Received type does not match definition	
DESCRIPTION		The received type does not match the definition specified by the VIEW.
ACTION		Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2119:ERROR	Request block is invalid	
DESCRIPTION		An Internal processing error has occurred.
ACTION		Contact Unisys Customer Support.
2120:ERROR	Received type does not match definition	
DESCRIPTION		The received type does not match the definition specified by the VIEW.

	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2121:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2122:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2123:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2124:ERROR	Memory allocation error	

	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2125:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2126:ERROR	Request block is invalid	
	DESCRIPTION	An Internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2127:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2128:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2129:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.

2130:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2131:ERROR	Received type does not match definition
DESCRIPTION	The received type does not match the definition specified by the VIEW.
ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2132:ERROR	Received type does not match definition
DESCRIPTION	The received type does not match the definition specified by the VIEW.
ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2133:ERROR	Request block is invalid
DESCRIPTION	An Internal processing error has occurred.
ACTION	Contact Unisys Customer Support.

2134:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2135:ERROR	Received type does not match definition	
	DESCRIPTION	The received type does not match the definition specified by the VIEW.
	ACTION	Look for further error messages which specify the VIEW buffer type in error. This can occur when the VIEW definition used by the calling program does not match the VIEW definition used by the receiving process. Check the VIEW definitions of client and server to make sure that are identical. If a VIEW definition has been modified, make sure the associated Gateway process has been restart as VIEW definitions are cached by the Gateways.
2136:ERROR	Memory allocation error	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for the buffer conversion.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2137:ERROR	%s is encountered while encoding VIEW %s/%s member/type (%d/%s) to a NATIVE A SERIES buffer.	

	DESCRIPTION	A data conversion error has occurred while trying to encode the specified VIEW to a NATIVE A SERIES type buffer. The field in error is identified by the member index and type.
	ACTION	Examine the specified VIEW to ensure that all field types are valid for NATIVE A SERIES compatible fields. Refer to the section on NATIVE A SERIES data conversion in the Oracle Tuxedo Mainframe Adapter for OSI TP <i>User Guide</i> to determine the exact cause of the error.
2138:ERROR	%s encountered while decoding a NATIVE A SERIES buffer to a VIEW %s/%s member/type (%d/%s).	
	DESCRIPTION	A data conversion error has occurred while trying to decode a NATIVE A SERIES buffer into the specified VIEW. The field in error is identified by the VIEW member index and type.
	ACTION	Examine the specified VIEW to ensure that all field types are valid for NATIVE A SERIES compatible fields. Refer to the section on NATIVE A SERIES data conversion in the Oracle Tuxedo Mainframe Adapter for OSI TP <i>User Guide</i> to determine the exact cause of the error.
2139:ERROR	ASN.1 buffer type received was not a valid NATIVE A SERIES, but the buffer type received is from a different encoding type.	
	DESCRIPTION	The remote domain encoding type is specified as NATIVE A SERIES, but the buffer type received is from a different encoding type.
	ACTION	Check the encoding type of the Remote domain to ensure that the encoding type is NATIVE A SERIES.
2200:ERROR	Cannot malloc fd structures	

	DESCRIPTION	An Internal error has occurred while trying to allocate space for internal structures.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2201:INFO	libgwo build: %s - %s	
	DESCRIPTION	This line indicates the time and date that the gwnwinit.c module was built.
	ACTION	No action is necessary.
2202:ERROR	Malloc communication control structure failed	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for internal structures.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2203:INFO	GWOSITP is exiting	
	DESCRIPTION	The OSITP Gateway process is exiting.
	ACTION	No action is necessary.
2204:WARN	Specified environmental variable GW_DFLT_TRANTIME out of valid range, ignored!	
	DESCRIPTION	The GW_DFLT_TRANTIME is larger than what will fit into a long integer.
	ACTION	A default value of 300: seconds will be used. If this is not desired, correct the GW_DFLT_TRANTIME environment variable and restart the Gateway.
2205:WARN	SECURITY is set to %s, but dmconfig LDOM security is not set to DM_PW, userid will not be passed.	

	DESCRIPTION	You have set the SECURITY to USER_AUTH, ACL, MANDATORY_ACL in the ubbconfig file, however, you did not set the SECURITY to DM_PW (link layer security) in the dmconfig file. The userid will not be passed to remote domains.
	ACTION	If this is not the desired result, change the SECURITY in the dmconfig file for this local domain to DM_PW and check to make sure that any OSITPX remote domains for which the userid is to have passed has the OPTION set to SECURITY_SUPPORTED.
2212:ERROR	Malloc CID string buffer failed	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for internal structures.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2213:ERROR	Error occured while processing remote domains.	
	DESCRIPTION	An internal error has occured while processing the remote domain configuration parameters
	ACTION	Look for prior errors in the log that identify the exact problem. Then check the remote domain configurations for errors. If unable to identify the problem, contact Unisys Customer Support.
2235:ERROR	Internal data structure not allocated yet	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2236:ERROR	Invalid input parameter	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.

2237:ERROR	Internal protocol error, missing routing information
DESCRIPTION	An internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2238:ERROR	Remote OSITP domain not defined locally
DESCRIPTION	An incoming service call was received from a remote domain which is not defined in the DM_REMOTE_DOMAINS section of the configuration file.
ACTION	Add the necessary remote domain definition to DM_REMOTE_DOMAIN and DM_OSITP sections of the configuration file and restart the Gateway.
2239:ERROR	Internal data structure not allocated yet
DESCRIPTION	An internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2240:ERROR	Invalid input parameter
DESCRIPTION	A remote domain name was a NULL string.
ACTION	Contact Unisys Customer Support.
2241:ERROR	Internal data structure not allocated yet
DESCRIPTION	An internal processing error has occurred.
ACTION	Contact Unisys Customer Support.
2242:ERROR	Remote OSITP domain (%s) not defined in DM_OSITP
DESCRIPTION	An incoming service call was received from the specified remote domain which is not defined in the DM_REMOTE_DOMAINS section of the configuration file.
ACTION	Add the necessary remote domain definition to DM_REMOTE_DOMAINS and DM_OSITPX sections of the configuration file and restart the Gateway.

2243:ERROR	Your TMA OSI TP license is either invalid or expired	
	DESCRIPTION	Check your license file to make sure that is has not expired and that it contains the correct OSI TP License information.
	ACTION	Correct the license file and restart the Gateway. For more help Contact Unisys Customer Support.
2244:ERROR	Version of Unisys (%d) and BEA (%d) binaries do not match	
	DESCRIPTION	The versions of the Unisys and BEA dlls and executable are not compatible.
	ACTION	Reinstall the Software and restart the OSITP Gateway. For more help, contact Unisys Customer support.
2300:ERROR	Bad input arguments, unable to create instance	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2307:ERROR	Could not get RDOM Cache entry	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2308:ERROR	RDOM %s OSITP address not configured	
	DESCRIPTION	The OSITP configuration parameters for the specified RDOM are not configured in the domain configuration file.
	ACTION	Verify that a valid entry for the specified RDOM is present in DM_OSITPX section of the domain configuration file. If not, correct the problem and restart the gateway as necessary.
2320:ERROR	Unable to get remote domain information from shmem	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.

2400:ERROR	gwnwpoll error, %s
DESCRIPTION	A bad return code was received from set_new_action or gw_new_action for the specified message type. This is an internal processing error.
ACTION	Look for additional log messages which might be related to this error. Contact Unisys Customer Support.
2401:ERROR	Could not make new action
DESCRIPTION	A bad return code was received by set_new_action from gw_new_action.
ACTION	Look for additional log messages which might be related to this error. Contact Unisys Customer Support.
2402:WARN	Dropping polled action, no free contexts
DESCRIPTION	A bad return code was received in set_new_action from gw_nw_CreateInstance or gw_nw_GetNwCtxByAction.
ACTION	Look for additional log messages which might be related to this error. Contact Unisys Customer Support.
2403:ERROR	Could not make new action
DESCRIPTION	A bad return code was received by set_new_action from gw_new_action.
ACTION	Look for additional log messages which might be related to this error. Contact Unisys Customer Support.
2404:WARN	Dropping polled action, no free contexts
DESCRIPTION	A bad return code was received by set_new_action from gw_nw_SetNwCtx.
ACTION	Look for additional log messages which might be related to this error. Contact Unisys Customer Support.

2405:ERROR	queue entry type unknown - %x
	DESCRIPTION A protocol error has occurred in gw_nw_poll. An invalid entry type has been encountered.
	ACTION Contact Unisys Customer Support.
2406:WARN	Dropping polled action, context has been free
	DESCRIPTION Network data has been received for a Network Context which no longer exists.
	ACTION No action necessary.
2500:WARN	Call to service (%s) aborted due to lack of system Resources
	DESCRIPTION Not enough system resources were available to complete the processing of this service call.
	ACTION For more information Contact Unisys Customer Support.
2501:ERROR	Call to service (%s) failed with TPNOENT"
	DESCRIPTION The remote service requested does not exist at the remote domain.
	ACTION Either the service requested does not exists or the service requested exists but is not the correct type (conversational/non-conversational).
2502:ERROR	User <%s> is denied access to Service <%s>
	DESCRIPTION The user does not have access to services.
	ACTION The userid is not a valid userid. The userid must be added to the tpusr file by the Tuxedo System Administrator.
2504:ERROR	Cannot create shared mem nettxid
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2506:WARN	Transaction table full, rejecting remote request!

	DESCRIPTION	The number of outstanding transactions exceeds the maximum allowed under the current configuration. This could be the MAXGTT or MAXTRAN value.
	ACTION	To allow more transactions, increase the appropriate configuration parameter and reload the appropriate configuration file and restart the gateway process.
2507:ERROR	OSI TP protocol error, shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2508:ERROR	Unable to assign id to incoming conversation	
	DESCRIPTION	The maximum number of conversations allowed, as defined by MAXCONV, has been exceeded.
	ACTION	To allow more conversations, increase the appropriate configuration parameter and reload the appropriate configuration file and restart the gateway process.
2510:ERROR	No conversation id associated with this fd	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2515:ERROR	Blocking timeout occurred, deleting fd	
	DESCRIPTION	A blocking timeout has occurred on a request to a remote host.
	ACTION	Examine the ULOG for more information concerning the reason for the failure. Check configuration and increase the BLOCKTIME value, if needed.
2519:ERROR	Conversation id not found	
	DESCRIPTION	An internal processing error has occurred.

	ACTION	Contact Unisys Customer Support.
2542:ERROR	Protocol error, DiaFSM state(%d), shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2544:ERROR	Could not find transaction node, shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2557:ERROR	Protocol error, dial state(%d), shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2558:ERROR	Protocol error, dial state(%d), shutdown Gateway!	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2600:ERROR	Invalid conversation context	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2601:ERROR	Unable to send	
	DESCRIPTION	An attempt to send a reply to the called failed.
	ACTION	Look for further Stack vendor errors for more information as to why this failure occurred.
2803:ERROR	Invalid transaction node	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2804:ERROR	Could not find transaction node!	
	DESCRIPTION	An internal processing error has occurred.

	ACTION	Contact Unisys Customer Support.
2805:ERROR	Unable to obtain remote domain info from shared memory	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2806:ERROR	Unable to obtain ositp info from rdom	
	DESCRIPTION	The DM_OSITPX section for a remote domain is not defined in the domain configuration file.
	ACTION	Make the necessary corrections to the domain configuration file, reload the file, and restart the OSITP gateway process.
2808:ERROR	Cannot realloc fd structures	
	DESCRIPTION	An Internal error has occurred while trying to allocate space for Network Context structure.
	ACTION	Increase the system parameters to allow more memory per process and restart the OSITP gateway process.
2809:ERROR	Remote domain name(%s) not found	
	DESCRIPTION	The specified remote domain is not defined in the domain configuration file.
	ACTION	Add the remote domain information to the domain configuration file, reload the file, and restart the OSITP gateway process.
2815:ERROR	gw_tx_end returned failure	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2821:ERROR	Invalid input transaction id	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.

2822:ERROR	Exceeding local transaction limit	
	DESCRIPTION	The number of local transaction allowed, as defined by MAXTRAN, has been exceeded.
	ACTION	To increase the number allowed, Increase the MAXTRAN parameter and restart the OSITP gateway process.
2823:ERROR	Branch does not belong to this transaction	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2826:ERROR	Exceeding local transaction limit	
	DESCRIPTION	The number of local transaction allowed, as defined by MAXTRAN, has been exceeded.
	ACTION	To increase the number allowed, Increase the MAXTRAN parameter and restart the OSITP gateway process.
2829:ERROR	Branch does not belong to this transaction	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2830:ERROR	Transaction branch does not exist	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2831:ERROR	Invalid input file descriptor	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2833:ERROR	Transaction branch already exists	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.

2834:ERROR	Invalid input file descriptor
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2844:ERROR	Corrupted or uninitialized file descriptor
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2845:ERROR	Allocating Network Transaction table failed
	DESCRIPTION The memory could not be allocated for the Network Transaction table.
	ACTION Adjust system parameters to allow more memory or fewer Transactions and restart the OSITP Gateway process.
2847:ERROR	Bad input transaction identification
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2849:ERROR	Bad input transaction identification
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2850:ERROR	Invalid transaction look up table entry
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2851:ERROR	Invalid or corrupted network context descriptor %d
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2853:ERROR	Invalid conversation descriptor %d
	DESCRIPTION An internal processing error has occurred.

	ACTION	Contact Unisys Customer Support.
2854:ERROR	Invalid action descriptor %d	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2855:ERROR	Invalid context descriptor %d	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2856:ERROR	Invalid action descriptor %d	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2857:ERROR	Invalid context descriptor %d	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2858:WARN	Possible orphaned conversation %d	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2859:ERROR	Invalid action descriptor	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2860:ERROR	Invalid file descriptor	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2861:ERROR	Invalid file descriptor	
	DESCRIPTION	An internal processing error has occurred.

	ACTION	Contact Unisys Customer Support.
2862:ERROR	Invalid action descriptor %d	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2863:ERROR	Maximum system context limit already reached	
	DESCRIPTION	The Maximum number (32767) of system context structures have been created. It is possible that there is a memory leak.
	ACTION	Contact Unisys Customer Support.
2864:ERROR	Corrupted or uninitialized file descriptor	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2865:ERROR	Invalid conversation descriptor	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2866:ERROR	Invalid file descriptor	
	DESCRIPTION	An internal processing error has occurred.
	ACTION	Contact Unisys Customer Support.
2867:WARN	Remote domain(%s) XATMI encoding not specified, use default	
	DESCRIPTION	The XATMI encoding type for the Remote Domain has not been configured in the DM_OSITPX section. The default XATMI encoding type is being used.
	ACTION	No action is necessary, unless the default encoding type is not desired. If the default is not desired, add the XATMI_ENCODING parameter value for the specified remote domain, reload the domain config file, and restart the OSITP gateway process.

2868:ERROR	Remote OSITP domain %s address not configured	
	DESCRIPTION	The DM_OSITPX section is not defined for the given Remote Domain.
	ACTION	Add the DM_OSITPX section to the configuration file, reload the domain config file, and restart the OSITP gateway process.
2869:ERROR	Wrong remote domain type(%s)	
	DESCRIPTION	The remote domain type is not OSITP.
	ACTION	Contact Unisys Customer Support.
2872:ERROR	Cannot get status of security file	
	DESCRIPTION	The security file does not exist.
	ACTION	Check the configuration and make sure the security file exists or reconfigure the system such that security is off.
2873:ERROR	Cannot find appkey for user name [%s]	
	DESCRIPTION	The specified username appkey does not exists in the security file.
	ACTION	Add the user appkey to the security file or use a username which is defined in the security file.
2874:ERROR	Cannot find user name for appkey [%d]	
	DESCRIPTION	The specified appkey does not exists in the security file.
	ACTION	Add the user appkey to the security file or use a username whose appkey is defined in the security file.
2875:ERROR	Cannot open security file %s	
	DESCRIPTION	The security file does not exist.
	ACTION	Check the configuration and make sure the security file exists or reconfigure the system such that security is off.

2902:ERROR	failed to insert blob segment into transaction table!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support.
2903:ERROR	Event stack overflow, shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2904:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2908:ERROR	Could not find transaction table entry, shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2914:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2916:ERROR	Could not find transaction node, shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2917:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2918:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support

2919:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2920:ERROR	Protocol error, msg state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2921:ERROR	Could not find transaction node, shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2922:ERROR	Could not find transaction node, shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2928:ERROR	Could not find transaction node, shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2929:ERROR	Could not find transaction node, shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2935:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2936:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support

2937:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2939:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2940:ERROR	Protocol error, node state(%d), shutdown Gateway!
	DESCRIPTION An internal processing error has occurred.
	ACTION Contact Unisys Customer Support
2947:WARN	No OSI/TP service provider, shutdown OSITP domain gateway
	DESCRIPTION The local OSITP domain is not defined in the DM_OSITPX section of the domain configuration file.
	ACTION Check the domain configuration file definition and add the DM_OSITPX information for the Local Domain if necessary, reload the domain configuration file and restart the OSITP gateway process.

