

**Oracle® Real User Experience Insight**

Installation Guide

Release 6.5.1 for Linux x86-64

**E18052-02**

October 2010

Oracle Real User Experience Insight Installation Guide, Release 6.5.1 for Linux x86-64

E18052-02

Copyright © 2010 Oracle and/or its affiliates. All rights reserved.

Primary Author: Paul Coghlan

Contributing Author: Eddy Vervest

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this software or related documentation is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, the following notice is applicable:

U.S. GOVERNMENT RIGHTS Programs, software, databases, and related documentation and technical data delivered to U.S. Government customers are "commercial computer software" or "commercial technical data" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, duplication, disclosure, modification, and adaptation shall be subject to the restrictions and license terms set forth in the applicable Government contract, and, to the extent applicable by the terms of the Government contract, the additional rights set forth in FAR 52.227-19, Commercial Computer Software License (December 2007). Oracle USA, Inc., 500 Oracle Parkway, Redwood City, CA 94065.

This software is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications which may create a risk of personal injury. If you use this software in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure the safe use of this software. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software in dangerous applications.

Oracle is a registered trademark of Oracle Corporation and/or its affiliates. Other names may be trademarks of their respective owners.

This software and documentation may provide access to or information on content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services.

---

---

# Contents

<b>Preface</b> .....	ix
Audience .....	ix
Documentation Accessibility .....	x
Related Documents .....	xi
Conventions .....	xi
<b>1 Getting Started</b>	
1.1 What is RUEI? .....	1-1
1.1.1 Data Collection .....	1-1
1.1.2 Product Architecture .....	1-2
1.2 Security .....	1-2
1.3 Connection Options .....	1-3
1.3.1 Copy Ports .....	1-3
1.3.2 TAPs .....	1-4
1.4 Installation and Deployment Options .....	1-5
1.4.1 Local and Remote Database Installations .....	1-6
1.4.2 Scalability Options .....	1-6
1.4.3 VM Platform Support .....	1-7
1.5 Hardware Requirements .....	1-7
1.5.1 Single-Server Requirements .....	1-7
1.5.2 Reporter Requirements .....	1-8
1.5.3 Collector Requirements .....	1-8
1.5.4 Deployment Best Practices .....	1-9
1.5.5 Data Retention Policies .....	1-10
1.5.6 Full Session Replay Storage Requirements .....	1-11
1.5.7 Memory Requirements .....	1-12
1.6 Software Requirements .....	1-13
1.7 Network Requirements .....	1-13
1.8 Client Requirements .....	1-14
1.9 Overview .....	1-15
<b>2 Installing the Linux Operating System</b>	
2.1 Introduction .....	2-1
2.2 Download ISO Image and Burn DVD .....	2-2
2.3 Run Installer .....	2-2

2.4	Set up Disk Partitioning .....	2-2
2.5	Network Configuration.....	2-4
2.6	Package Installation.....	2-4
2.7	Post-Installation Wizard .....	2-5
2.8	Create Additional Users and Reboot .....	2-8
2.9	Verify NTP Daemon Operation .....	2-9

### 3 Installing the Required Components

3.1	Mounting the Linux DVD.....	3-1
3.2	Installing Collector-Only System Prerequisites.....	3-1
3.3	Installing the Database Prerequisites .....	3-1
3.3.1	Installing the Reporter Prerequisites .....	3-2
3.3.2	Installing All Requirements Using a Yum Repository (Alternative) .....	3-2
3.4	Installing and Configuring the Oracle Database.....	3-3
3.4.1	Creating the Database User Accounts and Groups .....	3-3
3.4.2	Configuring the Kernel Parameter Settings.....	3-4
3.4.3	Setting Shell Limits for the Oracle User .....	3-4
3.4.4	Creating the Database Directory .....	3-4
3.4.5	Configuring the Oracle User's Environment.....	3-5
3.4.6	Creating an Oracle init Script File .....	3-8

### 4 Installing the RUEI Software

4.1	Obtaining the RUEI Software.....	4-1
4.2	Unpacking the RUEI Software .....	4-1
4.3	Generic Installation Tasks.....	4-1
4.3.1	The RUEI Configuration File .....	4-2
4.3.2	Installing Java .....	4-2
4.4	Remote Collector Installation.....	4-3
4.5	Reporter Installation .....	4-3
4.5.1	Installing the Apache Web Server and PHP .....	4-3
4.5.1.1	PHP Configuration.....	4-3
4.5.1.2	Avoiding rsvg Warnings .....	4-4
4.5.2	Installing the Oracle Database Instant Client .....	4-4
4.5.3	Installing the php-oci8 Module.....	4-4
4.5.4	Installing the Zend Optimizer .....	4-4
4.5.5	Creating the RUEI Database Instance .....	4-5
4.5.6	Installation of the Reporter Software.....	4-6
4.6	Configuring the Network Interface.....	4-7
4.7	Enabling Multibyte Fonts (Optional, but Recommended) .....	4-7
4.8	Mail (MTA) Configuration (Optional, Reporter Only).....	4-8
4.9	SNMP (Reporter Only).....	4-8
4.10	Configuring Automatic Browser Redirection (Optional) .....	4-8
4.11	Configuring Reporter Communication (Split-Server Setup Only) .....	4-8
4.12	Verifying Successful Installation of RUEI .....	4-9

## 5 Upgrading to RUEI 6.5.1

5.1	Upgrading From RUEI 5.x to 6.5.1 .....	5-1
5.1.1	Upgrading Accelerator packages .....	5-1
5.1.2	Upgrading the Reporter System .....	5-1
5.1.3	Upgrading the Collector System(s) .....	5-4
5.2	Upgrading From RUEI 6.x to 6.5.1 .....	5-6
5.2.1	Upgrading Accelerator packages .....	5-6
5.2.2	Upgrading the Reporter System .....	5-6
5.2.3	Upgrading the Remote Collector System(s) .....	5-8
5.3	Rolling Back to Version 6.5.0 .....	5-8
5.4	Rolling Back to Version 6.0.x .....	5-10
5.5	Rolling Back to Version 5.1.x .....	5-11
5.5.1	Rolling Back Remote Collector Systems .....	5-13
5.6	Rolling Back to Version 5.0.x .....	5-13
5.6.1	Rolling Back Remote Collector Systems .....	5-15

## 6 Configuring RUEI

6.1	Introduction .....	6-1
6.2	Performing Initial RUEI Configuration .....	6-1
6.3	Configuring a Collector System .....	6-4
6.3.1	Resetting a Collector System .....	6-4
6.4	Performing Post-Installation Configuration .....	6-5
6.4.1	Specifying the Cookie Technology .....	6-5
6.4.2	Adding/Uploading HTTPS SSL Keys .....	6-5
6.4.3	Specifying How Users are Identified .....	6-5
6.4.4	Naming Pages .....	6-5
6.4.5	Specifying the Scope of Monitoring .....	6-6
6.4.6	Authorizing Initial Users .....	6-6
6.5	Verifying and Evaluating Your Configuration .....	6-6
6.5.1	Viewing a Traffic Summary .....	6-6
6.5.2	Confirming Data Collection .....	6-7

## 7 Installing and Configuring SSO Authentication Integration

7.1	Turning off the Default Web Server .....	7-1
7.2	Reporter System Without Local Database .....	7-1
7.2.1	Creating the Oracle User .....	7-1
7.2.2	Setting up the Oracle HTTP Server Environment .....	7-2
7.2.3	Creating the Installation Directory .....	7-2
7.3	Reporter System With Local Database .....	7-2
7.4	Installing Oracle HTTP Server .....	7-2
7.5	Verifying the Oracle HTTP Server Configuration .....	7-5

## 8 Configuring the Oracle Access Manager (OAM)

8.1	Creating an OAM Access Gate for RUEI .....	8-1
8.2	Downloading and Installing the Access Gate Software .....	8-4

8.3	Configuring the Access Gate Software on the RUEI Server .....	8-4
8.4	Configuring the Required Session Traffic Definitions .....	8-5

## A Generic Database Instance Setup

A.1	Overview .....	A-1
A.2	Creating the Database Instance.....	A-1
A.3	Using Compressed Tablespaces.....	A-2
A.4	Creating Additional Tablespaces.....	A-2
A.5	DRCP Connection Pooling .....	A-2
A.6	Rescheduling Oracle Database Maintenance.....	A-2
A.7	Creating the RUEI Database User .....	A-3
A.8	Setting up the Connection Data .....	A-3
A.9	Setting up the Oracle Wallet.....	A-4

## B The ruei-check.sh Script

## C Setting the Maximum Data Group Size

C.1	Maximum Group Size and Condensation.....	C-1
C.2	Setting the Maximum Group Size .....	C-1
C.3	Reviewing the Effects of Changing the Maximum Group Size .....	C-3
C.4	Managing the Maximum Size of the Database.....	C-3

## D Verifying Monitored Network Traffic

D.1	Introduction .....	D-1
D.2	Creating Traffic Snapshots .....	D-2
D.3	Analyzing Traffic Information .....	D-4

## E Troubleshooting

E.1	Running the ruei-check.sh Script.....	E-1
E.2	The ruei-prepare-db.sh Script Fails .....	E-2
E.3	Starting Problems.....	E-2
E.4	Data Collection Problems .....	E-3
E.5	Data Processing Problems .....	E-4
E.6	E-Mail Problems.....	E-4
E.7	SSL Decryption Problems .....	E-4
E.8	Missing Packages and Fonts Error Messages .....	E-5
E.9	ORA-xxxxx Errors.....	E-6
E.10	Oracle DataBase Not Running .....	E-6
E.11	General (Non-Specific) Problems .....	E-6
E.12	Network Interface Not Up.....	E-7
E.13	Memory Allocation Error During Upgrade Procedure.....	E-7
E.14	OAM-Related Problems .....	E-7
E.15	ruei-check.sh Script Reports PHP Timezone Error .....	E-8

**F Installation Checklist**

**G Third-Party Licenses**

**Index**



---

---

# Preface

Oracle Real User Experience Insight (RUEI) provides you with powerful analysis of your network and business infrastructure. You can monitor the real-user experience, define Key Performance Indicators (KPIs) and Service Level Agreements (SLAs), and trigger alert notifications for incidents that violate them.

## Audience

This document is intended for the following people:

- System administrators responsible for the installation of RUEI. This assumes a sound understanding of the Linux operating system.
- The person within your organization designated as RUEI Super Administrator (that is, the `admin` used). They are responsible for post-installation configuration, and system maintenance.

Some familiarity with network and Web technology is assumed. In particular, you should have a sound understanding of network topology, and a good operational knowledge of your organization's network and application environment.

This guide is organized as follows:

- [Chapter 1, "Getting Started"](#) introduces RUEI. In particular, how it monitors data traffic, the role of the Reporter and Collector modules, and the supported configurations.
- [Chapter 2, "Installing the Linux Operating System"](#) describes the procedure for installing the base operating system.
- [Chapter 3, "Installing the Required Components"](#) describes the procedure for installing all the components required by RUEI.
- [Chapter 4, "Installing the RUEI Software"](#) describes the procedure for preparing the server system(s) for RUEI, and installing the RUEI software.
- [Chapter 5, "Upgrading to RUEI 6.5.1"](#) describes the procedure for upgrading an existing RUEI 5.0.x, 6.0.x, or 6.5.0 installation to release 6.5.1.
- [Chapter 6, "Configuring RUEI"](#) describes the procedure for initially configuring RUEI. This procedure is performed by the person within the organization who has been assigned the role of RUEI Super Administrator.
- [Chapter 7, "Installing and Configuring SSO Authentication Integration"](#) describes the procedure for installing and configuring the Oracle HTTP server. This is an optional part of the RUEI installation process, and is only required if you intend to use the Oracle Single Sign-Off (SSO) service to authenticate RUEI users.

- [Chapter 8, "Configuring the Oracle Access Manager \(OAM\)"](#) describes the procedure for configuring OAM. This is an optional part of the RUEI installation process, and is only required if you intend to identify users within OAM-based network traffic.
- [Appendix A, "Generic Database Instance Setup"](#) describes how you can setup an Oracle database instance for use by the RUEI Reporter that is running on a platform other than Oracle Linux 5.x or RedHat Enterprise Linux 5.x.
- [Appendix B, "The ruei-check.sh Script"](#) provides a detailed explanation of the `ruei-check.sh` script. It is strongly that you use this script to verify successful installation, and to troubleshoot any issues that occur during the installation process.
- [Appendix C, "Setting the Maximum Data Group Size"](#) provides a detailed explanation of how the default maximum Data Browser group sizes can be increased to provide more accurate reporting of monitored traffic.
- [Appendix D, "Verifying Monitored Network Traffic"](#) describes how you can use the TCP diagnostic facility to verify that RUEI "sees" all required network traffic. It is *strongly* recommended that a network engineer within your organization validates collected network traffic after installation and configuration of RUEI.
- [Appendix E, "Troubleshooting"](#) highlights the most common issues encountered when installing RUEI, and offers solutions to quickly locate and correct them. It should be reviewed before contacting Customer Service.
- [Appendix F, "Installation Checklist"](#) provides a checklist of actions that should be completed, and the information gathered, before starting to install the RUEI software.
- [Appendix G, "Third-Party Licenses"](#) contains licensing information about certain third-party products included with RUEI.

## Documentation Accessibility

Our goal is to make Oracle products, services, and supporting documentation accessible to all users, including users that are disabled. To that end, our documentation includes features that make information available to users of assistive technology. This documentation is available in HTML format, and contains markup to facilitate access by the disabled community. Accessibility standards will continue to evolve over time, and Oracle is actively engaged with other market-leading technology vendors to address technical obstacles so that our documentation can be accessible to all of our customers. For more information, visit the Oracle Accessibility Program Web site at <http://www.oracle.com/accessibility/>.

### Accessibility of Code Examples in Documentation

Screen readers may not always correctly read the code examples in this document. The conventions for writing code require that closing braces should appear on an otherwise empty line; however, some screen readers may not always read a line of text that consists solely of a bracket or brace.

### Accessibility of Links to External Web Sites in Documentation

This documentation may contain links to Web sites of other companies or organizations that Oracle does not own or control. Oracle neither evaluates nor makes any representations regarding the accessibility of these Web sites.

## Deaf/Hard of Hearing Access to Oracle Support Services

To reach Oracle Support Services, use a telecommunications relay service (TRS) to call Oracle Support at 1.800.223.1711. An Oracle Support Services engineer will handle technical issues and provide customer support according to the Oracle service request process. Information about TRS is available at

<http://www.fcc.gov/cgb/consumerfacts/trs.html>, and a list of phone numbers is available at <http://www.fcc.gov/cgb/dro/trsphonebk.html>.

## Related Documents

For more information, see the following documents in the Oracle Real User Experience Insight (RUEI) documentation set:

- *Oracle Real User Experience Insight User's Guide*.

The latest version of this and other RUEI books can be found at the following location:

<http://www.oracle.com/technetwork/documentation/realuserei-091455.html>

## Conventions

The following text conventions are used in this document:

<b>Convention</b>	<b>Meaning</b>
<b>boldface</b>	Boldface type indicates graphical user interface elements associated with an action, or terms defined in text or the glossary.
<i>italic</i>	Italic type indicates book titles, emphasis, or placeholder variables for which you supply particular values.
monospace	Monospace type indicates commands within a paragraph, URLs, code in examples, text that appears on the screen, or text that you enter.



# Getting Started

This chapter introduces the role of Oracle Real User Experience Insight (or RUEI for short), its architecture, attachment, and deployment options.


## 1.1 What is RUEI?

The usage of Web applications and services continues to grow. This includes not only the use of the Internet as a marketing channel, but also Extranet-based supply chain and back-office integration, and Intranet deployment of internal applications. Increasingly, it also includes the utilization of Web services which implement clearly defined business functions. RUEI is designed for measuring, analyzing, and improving the availability and performance of all of these deployment scenarios.

### 1.1.1 Data Collection

Typically, RUEI is installed before the Web servers, behind a firewall in the DMZ (as shown in [Figure 1-1](#)). The data collection method is based on Network Protocol Analysis (NPA) technology. This method is 100% non-intrusive. Hence, it does not place any load on a Web server, or require installing software agents that will impact performance. In addition, it does not require any change to the current application or infrastructure. When a new application release is deployed, or when an additional Web server is added, there is no or very little change required to RUEI's monitoring environment.

**Figure 1-1 How RUEI Collects Data**




When an object is requested by a visitor, RUEI sees the request and measures the time the Web server requires to present the visitor with the requested object. At this point, RUEI knows who requested the page (the client IP), which object was requested, and from which server the object was requested (server IP).

When the Web server responds and sends the requested object to the visitor, RUEI sees that response. At this point, RUEI can see whether there is a response from the server, whether this response is correct, how much time the Web server required to generate the requested object, and the size of the object. In addition, RUEI can also see whether the object was completely received by the visitor, or if the visitor aborted the download (that is, proof of delivery). Hence, RUEI can determine the time taken for the object to traverse the Internet to the visitor, and calculate the Internet throughput between the visitor and the server (that is, the connection speed of the visitor).

## 1.1.2 Product Architecture

RUEI is based on a three layer product architecture, as shown in [Figure 1–2](#).

**Figure 1–2 RUEI Product Architecture**



The monitored data packets are processed by the following layers:

- **Data collection**  
This layer is responsible for acquiring raw data and delivering it to the Data processor. This data can be collected from multiple sources. The available attachment options are described later in this section.
- **Data processing**  
This layer converts the raw data into OLAP data sets. These comprise the multidimensional data structure that is viewable within the data browser.
- **Data presentation (reporter)**  
This layer is RUEI's analysis and reporting environment. This is a Web-based information portal that can be accessed from any selected browser. The interface between the data processing and data presentation layer is based on open db calls.

## 1.2 Security

To read HTTP(S) data streams, a proprietary software module reassembles TCP/IP packet streams. Because the data collectors do not have an assigned IP number, and

the software using these data collectors does not have a functional IP stack, RUEI is not able to respond to incoming traffic received on the data collectors. This makes RUEI "invisible" to the monitored networks, and completely secure.

---

---

**Note:** Because of the non-intrusive way in which RUEI collects data, it is not possible for it to request retransmission in the event of an error on the measurement port.

---

---

Data collection can be configured to log encrypted data. To facilitate this, a copy of the Web server's private SSL keys needs to be set up in the data collector. In addition, RUEI can be configured to omit logging of sensitive data in the arguments of POST requests of forms or content; so called *data masking* (or blinding).

## 1.3 Connection Options

RUEI supports the use of both copy ports<sup>1</sup> and TAPs<sup>2</sup> for monitoring network traffic (10/100 Mbps and 1/10 Gbps Ethernet connections are supported). Copy ports and TAPs are available for copper or fibre-based network infrastructures. While both devices allow non-intrusive monitoring of network traffic, there are differences between these two connection options. These are highlighted in the rest of this section.

### Monitoring SSL and Forms Traffic

Be aware that SSL and Oracle Forms traffic are particularly sensitive to disruptions in the TCP packet stream. This is because they require state information to be maintained for the duration of the connection, and any lost packets can cause that information to be lost, preventing RUEI from accurately monitoring and reporting the connection.

Therefore, you should ensure that each Collector is connected to a reliable network device, such as a TAP. In addition, it is *strongly* recommended that you regular review the information available through the Collector Statistics window (select **System**, then **Status**, and then **Collector status**) to verify the integrity of the TCP packet stream. Particular attention should be paid to the reported TCP and SSL connection errors.

### 1.3.1 Copy Ports

A copy port is a switch that starts to build up a Layer 2 forwarding table on the basis of the source MAC address of the different packets that the switch receives. After this forwarding table is built, the switch forward traffic that is destined for a MAC address directly to the corresponding port.


For example, after the Web server MAC in [Figure 1-3](#) is learned, unicast traffic from the browser to the Web server is only forwarded to the Web server port. Therefore, the Collector does not see this traffic.

---

<sup>1</sup> Copy ports are also known as Switched Port Analyzer (SPAN) ports which is a feature of Cisco switches.

<sup>2</sup> Test Access Port (TAP) devices are provided by specialist vendors, such as NetOptics Inc.

**Figure 1–3 Network Connection Using a Copy Port**




In the configuration shown in the lower part of [Figure 1–3](#), the Collector is attached to a port that is configured to receive a copy of every packet that the browser sends and receives. This port is called a copy port. Copy ports can copy traffic from any or all data ports to a single unused port and prevents bi-directional traffic on the port to protect against backflow or traffic into the network.

Be aware that activating a copy port on a switch can have a performance impact. Typically, copy ports support a wide range of configuration options, and for further information about these options you should consult your switch documentation or contact the vendor.

### 1.3.2 TAPs

TAPs can be placed between any two network devices (such as routers and firewalls). Any monitoring device connected to a TAP receives the same traffic as if it were in-line, including all errors. This is achieved through the TAP duplicating all traffic on the link, and forwarding it to the monitoring port(s). The example shown in [Figure 1–4](#) illustrates a typical TAP deployment for one Collector.

**Figure 1–4 Network Monitoring Using a TAP****Important**

Unlike copy ports, in the event of power failure, TAPs continue to allow data to flow between network devices. In addition, copy ports are prone to packet loss when under load. TAP devices are available for copper or fibre-based infrastructures. Moreover, they can be easily deployed when and where required, but without reconfiguration of switches or engineers needing to re-cable a network link. For these reasons, the use of TAPs is *strongly* recommended over that of copy ports.

Broadly speaking, there are three types of TAPs: network, regeneration, and aggregation TAPs. RUEI supports the use of network and regeneration TAPs. The use of aggregation TAPs is *not* recommended because they can lose data, and do not provide an acceptable level of accuracy. However, the deployment of multiple Collectors, or the connection of multiple links directly to one Collector, is available for the aggregation of data from multiple streams. In addition, be aware that when capturing data with a network-TAP device, the use of cascaded TAP configurations is not supported.

## 1.4 Installation and Deployment Options

A RUEI system can be configured in two different ways: as a Reporter, or as a Collector. Each installation option is reviewed in the following sections.

**Reporter**

Here, the Reporter provides a browser-based interface to the collected data. After processing, this data is stored in an Oracle database. This database can reside locally (that is, on the Reporter system), or on a remote database server.


Note that each Reporter installation also contains a local Collector instance. The Reporter can either be configured to just process information gathered by this local Collector (this is a single-server configuration similar to the one shown in [Figure 1–5](#)), or can (optionally) be configured to receive information from additional Collector

installations. Note the local Collector instance on the Reporter system can also be disabled if not required.

**Collector**

If a RUEI system is installed as a Collector, it submits the data it gathers to a Reporter system. Multiple Collectors can be attached to the same Reporter. Split server #1 in Figure 1–5 is an example of a single Collector split-server configuration, while split server #2 is an example of a split-server configuration using two Collectors. Note that a direct network connection is required between the Collector(s) systems and the Reporter system.

**Figure 1–5 Configuration Options**



**1.4.1 Local and Remote Database Installations**

As mentioned earlier, the data available via the Reporter system is stored in an Oracle database. This database can reside locally on the Reporter system, or on a remote database server (such as a database cluster).

The use of a remote database server provides a number of potential advantages over a locally installed database. In particular, it offers easier integration with existing security and back-up policies, as well as improved performance through the use of dedicated servers.

Currently, RUEI 6.5 supports the Oracle 11g database. While the procedure for 11gR1 is described, 11gR2 is also supported. However, be aware that the requirements for 11gR2 differ from those described in this guide. Note the Oracle 10g database is not supported.

**1.4.2 Scalability Options**

The use of multiple Collectors may be considered when there is a need to monitor very high levels of data traffic. In addition, this deployment also provides the possibility of

enhanced security. For example, by placing the Collector(s) outside the office network, while placing the Reporter system within the network.

Split-server configuration #1 in [Figure 1-5](#) shows an example of a typical DMZ installation. The Collector is located in the DMZ, and the Reporter is within the server network environment. Note that the local Collector instance is disabled. Split-server configuration #2 shows an example of a deployment consisting of two Collectors. This could, for example, be used between two data centers (both monitoring the DMZ), where one data center acts as a failover for the other.

Split-server configuration #3 shows an example of a deployment in which both data lines are monitored in the same reporting environment. It also features the use of offloading to a database on a separate server. Note this deployment assumes that the traffic on each line is mutually exclusive. It also shows an example of a deployment used for security reasons. While the traffic from Web servers A and B are monitored and reported, the traffic from Web server C is not. This is also the reason why the Collectors are not placed above the switch.

For security reasons, it is recommended that access to the Reporter system is restricted to trusted IP ranges. Similarly, you may want to locate the Reporter system inside the internal network to maximize its security. The Collector's data gathering ports should be in the DMZ.

### 1.4.3 VM Platform Support

Note that the Collector cannot be run on any operating system other than Oracle or RedHat Enterprise Linux. In addition, because the Collector requires direct control of the physical network card, no VM platform is certified to run the Collector software.

## 1.5 Hardware Requirements

The required minimum system specifications for the selected configuration (as explained in [Section 1.4, "Installation and Deployment Options"](#)) are described in the following sections.

### Network Cards

It is recommended that you carefully consider the selection of network cards for your infrastructure. Depending on the connection option you selected in [Section 1.3, "Connection Options"](#), both copper and fibre-based network cards may be required. If necessary, consult both your network and systems management teams.

---

**Note:** For more information about required and recommended system specifications, please contact Customer Support.

---

### 1.5.1 Single-Server Requirements

**Table 1-1** *Single-Server System Minimum Requirements*

Element	Requirements
CPU	64-bit Intel or AMD dual-CPU, dual-core processor (> 2 G Hz) or equivalent.
Memory	16 GB.
Disk space	Minimum 400 GB HDD free space. <sup>1,2</sup>

**Table 1–1 (Cont.) Single-Server System Minimum Requirements**

Element	Requirements
Network interfaces	When using a network-TAP device <sup>3</sup> , a minimum of three network interfaces is required: <ul style="list-style-type: none"> <li>■ Two interfaces for network traffic capturing.</li> <li>■ One interface for network services.</li> </ul>
GSM modem (optional)	Optional support for a GSM modem to send text messages messages. The modem needs to be either GSM07.05 or GSM07.07 compatible. It can be connected through a serial or USB port. If USB is used, RUEI uses the first available port (ttyUSB0). Alternative methods of sending text messages are available (http/e-mail).

<sup>1</sup> To ensure acceptable performance of the RUEI installation, it is recommended to use high performance disk systems, with a minimum supported I/O rate of 70 MB/s. When monitoring high volumes of traffic, more powerful disk systems may be required. (Hardware) RAID-5, RAID-10, or equivalent storage configurations are strongly recommended.

<sup>2</sup> This may need to be increased if Enriched data exchange is enabled.

<sup>3</sup> When capturing data with a network-TAP device, the use of cascaded TAP configurations is not supported.

## 1.5.2 Reporter Requirements

**Table 1–2 Reporter System Minimum Requirements**

Element	Requirements
CPU	64-bit Intel or AMD dual-CPU, dual-core processor (> 2 G Hz) or equivalent.
Memory	16 GB.
Disk space	Minimum 400 GB HDD free space <sup>1,2</sup> .
Network interfaces	A minimum of 1 network interface is required.
GSM modem (optional)	Optional support for a GSM modem to send text messages. The modem needs to be either GSM07.05 or GSM07.07 compatible. It can be connected through a serial or USB port. If USB is used, RUEI uses the first available port (ttyUSB0). Alternative methods of sending text messages are available (http/e-mail).

<sup>1</sup> To ensure acceptable performance of the RUEI installation, it is recommended to use high performance disk systems, with a minimum supported I/O rate of 70 MB/s. When monitoring high volumes of traffic, more powerful disk systems may be required. (Hardware) RAID-5, RAID-10, or equivalent storage configurations are strongly recommended.

<sup>2</sup> This may need to be increased if Enriched data exchange is enabled.

## 1.5.3 Collector Requirements

The requirements for Collector systems are shown in [Table 1–3](#).

**Table 1–3 Collector System Minimum Requirements**

Element	Requirement
CPU	64-bit Intel or AMD dual-core processor or equivalent.
Memory	8 GB.
Disk space	Minimum 200 GB HDD free space.

**Table 1–3 (Cont.) Collector System Minimum Requirements**

Element	Requirement
Network interfaces	<p>When using a network-TAP<sup>1</sup> device, a minimum of three network interfaces are required:</p> <ul style="list-style-type: none"> <li>■ Two interfaces for network traffic capturing<sup>2</sup>.</li> <li>■ One interface for communication with the Reporter system.</li> </ul> <p>When using a network-copy port, a minimum of two network interfaces are required:</p> <ul style="list-style-type: none"> <li>■ One interface for network traffic capturing.</li> <li>■ One interface for communication with the Reporter system.</li> </ul>

<sup>1</sup> Capturing data with a network-TAP device prevents the use of a cascaded TAPs configuration.

<sup>2</sup> For up and down stream traffic. Note that the use of TAPs that integrate up and down stream traffic on one line is not recommended.

---



---

**Important:** Please note that an Intel (or compatible) 64-bit platform is a *strict* requirement for both the hardware and the operating system in all deployment scenarios.

---



---

## 1.5.4 Deployment Best Practices

This section presents a best practices framework within which to optimize your RUEI deployment. It is recommended that you carefully review the following information.

### Planning Your Deployment

It is important that the nature of the monitored network environment is clearly understood before deciding upon your RUEI deployment strategy. This includes not only the basic network connectivity, ports, addressing, and physical device requirements, but also a sound understanding of the monitored applications.

Moreover, before deploying RUEI, the basic traffic flows within the network must have been identified. This should include information about average and peak volumes of traffic. Any physical deployment requirements (such as space limitations, distances, power planning, rack space and layout, or cabling) should also have been identified.

You can use the checklist presented in [Appendix F, "Installation Checklist"](#) to capture much of this information.

### Forms-Based Traffic

If you are planning to monitor Forms-based traffic, be aware that the memory requirements may be higher than those outlined in [Section 1.5, "Hardware Requirements"](#). This is especially the case in deployments with heavy levels of Forms traffic. In this case, you should consider a split-server deployment.

### Full Session Replay

If you are planning to make use of the Full Session Replay facility, you may need to configure additional storage capacity. This is explained in [Section 1.5.6, "Full Session Replay Storage Requirements"](#).

**Encrypted Traffic**

If a significant level of the monitored traffic is encrypted, this can increase the CPU overhead. In this case, it is recommended that you consider configuring additional CPUs or, alternatively, a split-server deployment.

**Very High Levels of Traffic**

When very high levels of traffic are being monitored (that is, more than 10 million page views per day), you should consider a split-server deployment. Alternatively, consider the use of a remote database. The latter has the effect of significantly reducing (by up to 30%) the CPU overhead on the Reporter system. Monitored environments with more than 20 million page views per day should consider the use of both a split-server deployment and a remote database.

**1.5.5 Data Retention Policies**

As explained in the *Oracle Real User Experience Insight User's Guide*, the availability of specific data within the Data Browser, as well as reports based on that data, depends on the Reporter data retention policies defined for your RUEI installation. By default, RUEI retains information on daily, monthly, and yearly levels for 32 days, 13 months, and 5 years, respectively. In addition, information about failed pages, URLs, and services is retained for 15 days. The maximum amount of database storage required to maintain the default data retention policies is shown in [Table 1–4](#).

**Table 1–4 Default Required Database Storage**

Type of data retained	Default retention policy	DB space required per period (GB)	Total DB space required (GB)
Failed pages/URLs/services	15	1.5	22.5
Daily <sup>1</sup>	32	1	32
Monthly	13	1	13
Yearly	5	1	5
Suites <sup>2</sup>	15	0.5 <sup>3</sup>	7.5
Additional overhead			10
Total required DB space			90

<sup>1</sup> This includes the All pages, All sessions, All functions, All transactions, Key pages, and URL diagnostics groups.

<sup>2</sup> Suites use the Daily retention policy setting.

<sup>3</sup> 0.5 GB is required per day for each configured suite type.

Be aware that, in addition to the database storage required for each retained type of data, appropriately 10 GB of database storage is also required for other purposes. This includes KPIs, SLAs, and processing requirements. In [Table 1–4](#), it is assumed that one suite type is configured.

If you modify the default Reporter data retention policies, it is recommended that you use the **Calculate** facility to see the effect your new retention policy would have on required database storage. Note that the projected database utilization is based on previous database utilization, rather than maximum database usage.

The default amount of database storage available to the Reporter is 200 GB, and for most deployments, this will meet your operational requirements.

### Example - Increasing the Number of Groups

Consider the following situation. You have decided to retain information on daily, monthly, and yearly levels for 90 days, 24 months, and 5 years, respectively, and failed pages, URLs, and services information should be retained for 90 days. For the purposes of this example, it is assumed that only one suite type is configured. The maximum amount of database storage required to maintain this data is shown in [Figure 1-5](#).

**Table 1-5 Required Database storage**

Type of data retained	Default retention policy	DB space required per period (GB)	Total DB space required (GB)
Failed pages/URLs/services	90	1.5	135
Daily	90	1	90
Monthly	24	1	24
Yearly	5	1	5
Suites	90	0.5	45
Additional overhead			10
Total required DB space			264

### Maximum Data Browser Group Sizes

In addition to modifying the data retention policy settings, you can also modify the maximum size to which Data Browser groups are allowed to grow before data is condensed. This is fully explained in [Appendix C, "Setting the Maximum Data Group Size"](#).

## 1.5.6 Full Session Replay Storage Requirements

If you are planning to make use of the Full Session Replay facility, you may need to configure additional storage capacity available to the Collector system. This should be a separate device (not a partition of the Collector server's existing hard drive), and made accessible to the RUEI file system. The procedure to do this, together with guidance on storage requirements, is described in the rest of this section. Note that this procedure must be repeated for each Collector for which full session replay information is required.

### Configuring Additional Storage for Full Session Replay

To configure the additional required storage, do the following:

1. Mount the device. For example, under `/mnt/external_storage`.
2. Temporarily stop the Collector by issuing the following command:

```
appsensor stop wg
```

3. Move the `$APPSENSOR_HOME/wg/REPLAY` directory to the new device. In the above example, this is `/mnt/external_storage`, and the result is that the replay files are now located in the `/mnt/external_storage/REPLAY` directory.
4. Create a symbolic link from `/mnt/external_storage/REPLAY` to `$APPSENSOR_HOME/wg/REPLAY`.
5. Restart the Collector by issuing the following command:  

```
appsensor start wg
```
6. Calculate the required storage capacity. To do so, multiply the average number of daily page views by the average page size. Then, multiply this number by the number of days you wish full session replay data to be retained. Use [Table 1–6](#) as guidance.

**Table 1–6 Full Session Replay Storage Estimates**

Page views per day (millions)	Low page weight (~10 Kb)		Medium page weight (~50 Kb)		High page weight (~100 Kb)	
	Size per day (GB)	Disk I/O (MB/sec)	Size per day (GB)	Disk I/O (MB/sec)	Size per day (GB)	Disk I/O (MB/sec)
0.5	5	0.1	25	0.3	50	0.6
2	20	0.2	100	1.2	200	2.3
5	50	0.6	250	2.9	500	5.8
10	100	1.2	500	5.8	1000	11.6
20	200	2.3	1000	11.6	2000	23.1
50	500	5.8	2500	28.9	5000	57.9

---

**Important:** [Table 1–6](#) is intended for guidance only. It is *strongly* recommended that you regularly review average page sizes and daily page views, and adjust the required storage size as necessary.

---



---

**Note:** Be aware that FSR functionality uses a significant number of non-sequential read operations. Please consult your hardware vendor for information on how to optimize your I/O performance.

---

7. Select **Configuration**, then **General**, then **Advanced settings**, and then **Collector data retention policy**. Click the **Full session replay storage size (GB)** setting. Specify (in gigabytes) the required storage size. Note that the maximum that can be specified is 100 TB. When ready, click **Save**.

## 1.5.7 Memory Requirements

When calculating the amount of RAM required by your RUEI installation, it is recommended that you consider the following:

- For the Reporter system, each million visitor sessions per day requires 256 MB. Hence, 3 million visitor sessions per day would require 768 MB. In addition, each million page views requires 100 MB - 256 MB. Note that exact amount depends the length of monitored URLs, average session duration, and the number of events (such as custom dimensions).

- For each Collector system, each 10,000 hits requires 200 MB, and each 1000 SSL connections require 1 MB. In addition, up to 600 MB of network traffic can be buffered before individual TCP sessions start to be dropped. Up to 600 MB should also be assumed for content checks (such as XPath queries and error strings). Note that if you define a large number of content checks, or specify that they contain NLS character sets, the memory required may increase.

## 1.6 Software Requirements

The following GNU/Linux distributions are supported:

- Oracle Linux 5.x.
- RedHat Enterprise Linux 5.x.

### Encrypting Sensitive Data

If sensitive data needs to be encrypted, you have the opportunity to encrypt your entire disk configuration during the disk partitioning phase of the Linux installation procedure. For more information, see [Section 2.4, "Set up Disk Partitioning"](#).

## 1.7 Network Requirements

- All server system clocks should be synchronized via NTP using UDP port 123.
- Support DNS information requests over TCP and UDP port 53.
- Support reports and e-mail alerts using TCP port 25.
- Support SNMP traps on request from an SNMP Manager using UDP port 161/162.
- The RUEI user interface is accessible over HTTPS port 443.
- In the case of a remote database setup, access to TCP port 1521 is required between the Reporter and remote database server.
- Each remote Collector system should be accessible by the Reporter system over TCP port 22. It is recommended all other ports be blocked.

### Collector-Reporter Bandwidth

The amount data transferred between a remote Collector and the Reporter system largely depends on the type and level of network application traffic monitored by RUEI. In addition, the configuration of RUEI (such as defined functional errors, content checks, and page naming schemes) also influences the size of Collector files that need to be transferred to the Reporter system.

At peak times, the amount of data that needs to be transferred will be higher than during low traffic periods. Note that the exact amount of the data transmission from a remote Collector to the Reporter system can only be determined after the actual RUEI deployment.

For an initial deployment, the following simple rule can be used: each 5 million daily page views will result in a peak transfer of approximately 125 MB at peak time, and approximately 1 GB per day. Hence, typically only a few percent of the actual monitored traffic will be stored by a Collector and transferred to the Reporter. When you want or need to minimize this data transfer, it is recommended that you minimize the amount of monitored HTTP traffic which is not required by RUEI. For example, by using a subnet or VLAN-filtered network.

## Firewall Requirements

Table 1–7 shows the firewall requirements for your RUEI deployment.

**Table 1–7 RUEI Firewall Rules**

From	To	Port(s)	Socket type	Required	Description
Reporter	Collector	22 (SSH)	TCP	Y	Each remote Collector system must be accessible by the Reporter system over TCP port 22.
Reporter	NTP server	123 (NTP)	UDP	Y	All server system clocks must be synchronized via NTP.
Collector	NTP server	123 (NTP)	UDP	Y	All server system clocks must be synchronized via NTP.
Remote DB server	NTP server	123 (NTP)	UDP	Y	All server system clocks must be synchronized via NTP.
Reporter	DNS server	53 (DNS)	TCP/UDP	N <sup>1</sup>	Support DNS information requests.
Collector	DNS server	53 (DNS)	TCP/UDP	N <sup>1</sup>	Support DNS information requests.
Remote DB server	DNS server	53 (DNS)	TCP/UDP	N <sup>1</sup>	Support DNS information requests.
Reporter	Mail server	25 (SMTP)	TCP	N	Support reports and E-mail requests.
Reporter	SNMP Manager server	161, 162 (SNMP)	UDP	N	Support SNMP traps on request from an SNMP Manager.
Client browsers	Reporter	443 (HTTPS)	TCP	Y	The RUEI user interface is accessible over HTTPS.

<sup>1</sup> Optional, but *strongly* recommended.

## 1.8 Client Requirements

The workstations that will access the RUEI user interface must have one of the following browsers installed:

- Mozilla Firefox 3.0.
- Internet Explorer 6 SP2.
- Internet Explorer 7.

Note that JavaScript must be enabled. No other browser plug-ins are required.

In addition, the workstation should have a screen resolution of 1024 \* 768 (or higher).

---



---

**Important:** Ensure that any pop-up blocker within the browser has been disabled.

---



---

### AJAX Support

RUEI uses AJAX to enhance its user interaction. Internet Explorer relies on the MSXML control to facilitate AJAX. The AJAX dependencies can trigger a security warning when using strict security settings.

Internet Explorer 6 does not properly support transparent images in the PNG format. RUEI uses a well know fix (AlphaImageLoader) for this problem which relies on DirectX. If you are experiencing browser crashes with IE 6, you may need to update your version of DirectX. The PNG fix can trigger a security warning when using strict security settings.


## 1.9 Overview

The process of preparing the server system, and installing the RUEI software, has the following phases:

1. Install the Linux operating system. This is described in [Chapter 2, "Installing the Linux Operating System"](#).
2. Install all prerequisites for RUEI. This is described in [Chapter 3, "Installing the Required Components"](#).
3. Install the RUEI software. This is described in [Chapter 4, "Installing the RUEI Software"](#). The procedure for upgrading an existing 5.x or 6.0.x installation to release 6.5 is also described.
4. Perform an initial configuration of the RUEI installation. This is described in [Chapter 6, "Configuring RUEI"](#).
5. Install and configure the Oracle HTTP server. Note that this is only required if you intend to use the Oracle Single Sign-on (SSO) service to authenticate RUEI users. This is described in [Chapter 7, "Installing and Configuring SSO Authentication Integration"](#).

The procedure to install the required components depends on whether you are installing a Reporter or Collector system, and whether the Reporter system should use a locally installed database or a remote one. [Figure 1-6](#) shows the recommended installation and configuration path.

Figure 1-6 Installation Procedure





---

---

# Installing the Linux Operating System

This chapter describes the procedure for installing Oracle Linux 5.4. However, the procedure for installing Oracle or RedHat Enterprise Linux 5.x is very similar.

## 2.1 Introduction

The procedure for installing Oracle Linux 5.4 is fully described in the product documentation. This section presents a summary of that procedure, and assumes a sound knowledge of Linux system administration.

For information on vendor-specific variations, consult the appropriate documentation. The installation procedure described is based on the use of a DVD media package.

### Obtaining the Linux Operating System

The Oracle Linux 5.4 software is available from the Oracle E-Delivery Web site (<http://edelivery.oracle.com/linux>).

### Planning Network Interfaces

For remote access, one interface with a fixed IP address is required for each server. For a Collector (and an all-in-one RUEI server), one (SPAN/copy) or two (TAP) interfaces without IP address, are required.

For explanation of the RUEI global settings specified in the rest of this section, see [Section 4.3.1, "The RUEI Configuration File"](#).

### Planning the Software Installation Location

Depending on installation location of the database and the RUEI software, the necessary disk space needs to be carefully planned. During operating system installation, you will need this information at hand during the disk partitioning phase.

The following are the disk space requirements when using the default installation locations indicated throughout this guide:

- Database Disk Space Requirements
  - /u01/app/oracle 300 GB (ORACLE\_BASE).
- Reporter and Collector Disk Space Requirements
  - /opt/ruei 1 GB (RUEI\_HOME).
  - /var/opt/ruei 100GB (RUEI\_DATA).

This means that for an all-in-one RUEI server installation, a minimum of 400 GB is required. In the case of a high-traffic implementation, involving a dedicated

remote Collector, a minimum of 200 GB of disk space is recommended for `/var/opt/ruei` (RUEI\_DATA).

---

---

**Note:** As of RUEI release 5.1, a Collector only system does not require any database.

---

---

## 2.2 Download ISO Image and Burn DVD

1. Download the appropriate ISO image. This guide assumes you are using the DVD version of Oracle Linux 5.4.
2. Unzip the files.
3. Burn the ISO file to DVD. Note that this requires the use of a DVD-burning utility (such as UltraISO or Magic ISO Maker).

---

---

**Note:** According to your corporate policy, the Linux installation procedure may use a different procedure to that described in the following sections.

---

---

## 2.3 Run Installer

---

---

**Note:** After installing Linux on the first node, repeat the Linux installation procedure for each system.

---

---

1. Ensure that server system is able to boot from DVD. Insert the Oracle Linux DVD, and power on.
2. When the Oracle Linux boot screen appears, press **Enter** to start the installation process.
3. When asked to test the DVD media, select **Skip**. After a short interval, the installer goes into GUI mode. (The media test is not necessary because the DVD burning software would have informed you of any errors on the media).
4. At the Welcome to Oracle Linux screen, click **Next**.
5. Select the appropriate options from the Language and Keyboard settings screens.
6. If the installer detects a previous version of Linux, you are prompted to "Install Enterprise Linux" or "Upgrade an existing installation". Select "Install Enterprise Linux", and click **Next**.

---

---

**Important:** Oracle recommends that you install the Linux operating system with the default software packages (RPMs), and that you do not customize the RPMs during installation. This installation includes most required packages, and helps you limit manual checks of package dependencies.

---

---

## 2.4 Set up Disk Partitioning

1. When prompted, select the default **Remove Linux partitions on selected drives and create default layout** option, and check the option **Review and modify**

**partitioning layout.** When prompted to confirm your selection, select **Yes**. Click **Next** to continue.

---

**Important:** For security reasons, it is *strongly* recommended you check the **Encrypt System** check box so that all sensitive data is stored in a secure manner. A passphrase is required during booting the system.

---

2. When prompted to confirm the removal of all partitions, click **Yes**.
3. Review and modify (if necessary) the automatically selected disk partitions.

For most automatic layouts, the installer assigns 100 MB for `/boot`, 2 GB for swap, and the remainder is assigned to the root (`/`) partition. Ensure the specified SWAP space is sufficient. See [Table 2-1](#) and [Table 2-2](#) for required disk space and swap space requirements.

The installer creates a disk configuration using the Logical Volume Manager (LVM). For example, it will partition the first hard drive (`/dev/sda` in the described configuration) into two partitions: one for the `/boot` partition (`/dev/sda1`), and the remainder of the disk dedicated to a LVM named `VolGroup00` (`/dev/sda2`). The LVM Volume Group (`VolGroup00`) is then partitioned into two LVM partitions: one for the root file system (`/`), and another for swap. If you have selected a non-standard layout, ensure that the system meets the required disk space specifications shown in [Table 2-1](#). Ensure enough swap space is allocated for Oracle Linux. Its required swap space is shown in [Table 2-2](#).

**Table 2-1 Required Disk Space Specifications**

Partition	Minimum Required Disk Space (GB)
ORACLE_BASE (default <code>/u01/app/oracle</code> ) <sup>1</sup>	300
RUEI_HOME (default <code>/opt/ruei</code> )	1
RUEI_DATA (default <code>/var/opt/ruei/</code> )	100

<sup>1</sup> This is the example location of the database used throughout this guide.

**Table 2-2 Required Swap Space**

Available RAM	Swap Space Required
Up to 8192 MB	Equal to the size of RAM.
More than 8192 MB	0.75 times the size of RAM.

---

**Important:** The Reporter server requires high performance data storage. RAID-10 or RAID-5 (or equivalent) storage configurations with high performance disks are strongly recommended.

---



---

**Note:** The requirements shown in [Table 2-1](#) and [Table 2-2](#) can vary depending upon the composition and volume of monitored data. For more information, please contact Customer Support.

---

4. Accept the GRUB boot loader, as well as all default values, and click **Next**.

## 2.5 Network Configuration

1. Ensure that a static IP address is assigned to the interface used to access the RUEI Web interface. In addition, the assigned IP address and host name should be configured in the `/etc/hosts` file. If necessary, ensure that all Reporter and Collector systems are correctly defined in the DNS system.
2. Ensure that the network interface(s) used for network packet monitoring are administratively *up*, but *without* an IP address.

---

---

**Important:** Make the network interface *up* status permanent (after a reboot) by setting the ONBOOT parameter of the capturing interfaces to *yes*. The network interfaces configuration can be found in `/etc/sysconfig/networking/devices/ifcfg-ethX` (where *X* represents the necessary network interface). Alternatively, use the graphical utility **system-config-network** to perform the above actions.

---

---

## 2.6 Package Installation

1. Select the appropriate time zone for your environment, and click **Next**.

---

---


**Important:** In distributed environments, all time zones specified for Reporter and Collector systems *must* be identical.

---

---

2. Specify a root password, and click **Next**.
3. At the additional tasks dialog box shown in [Figure 2-1](#), leave the **Customize later** radio button checked, leave all the check boxes unchecked, and click **Next**.

Figure 2–1 Additional Tasks Dialog Box



4. At the **About to install** screen, click **Continue** to start the installation.
5. At the prompt screen, click **Next** to begin installation of Linux.
6. Upon successful installation, remove the DVD, and click **Reboot**.

---


**Important:** It is *strongly* recommended that you use the settings described above, and do not perform a "minimal" installation of Oracle Linux. This can lead to a wide range of problems, further described in [Section E.8, "Missing Packages and Fonts Error Messages"](#).

---

## 2.7 Post-Installation Wizard

1. When the system boots for the first time, a post-installation wizard appears, and allows you to finalize the operating system configuration settings. Click **Forward**.
2. At the User license agreement screen, read the license terms. You will not be able to proceed until you have accepted them. Then click **Forward**.
3. Use the screen shown in [Figure 2–2](#) to allow only secure WWW (HTTPs) and SSH traffic. Be aware that, by default, SSH traffic is enabled, but secure WWW (HTTPS) traffic is not. Note that, when prompted with a warning about not setting the firewall, click **Yes**.

Figure 2–2 Firewall Configuration



4. Use the screen shown in [Figure 2–3](#) to disable Security Enhanced Linux (SELinux). Click **Forward**. Note that you are prompted with a warning that changing the SELinux setting requires rebooting the system so that the entire system can be relabeled. Click **Yes**.

**Figure 2–3 SELinux Configuration**

---

---


**Important:** Security Enhanced Linux (SELinux) must be disabled for correct operation of RUEI.

---

---

5. Accept the default setting on the Kdump screen (disabled), and click **Forward**.
6. Adjust the date and time settings using the screen shown in [Figure 2–4](#). The use of NTP is strongly recommended, and is required in a split-server deployment. Click **OK**.

Figure 2–4 Date and Time Settings




---

**Important:** In distributed environments, all time zones specified for Reporter and Collector systems *must* be identical.

---

## 2.8 Create Additional Users and Reboot

1. Create any additional required (non-Oracle) operating system user accounts. Note that during the installation of the RUEI software, the `moniforce1` user account is created. The creation of the `oracle1` user is described in a later section. Do *not* create either user account at this point.
2. If prompted, confirm the detection of a sound card.
3. On the Additional CDs screen, click **Finish**.
4. Because the SELinux option has been changed (to disabled), you are prompted to reboot the system. Click **OK**.
5. After reboot, use the `root` user account, and the password you specified during installation to logon.

<sup>1</sup> This is the default user names used throughout this guide. For a complete explanation of the settings used by RUEI, see [Section 4.3.1, "The RUEI Configuration File"](#).

---



---

**Text Mode Installation (Optional):** When using the text mode installation, by default:

- Firewall: HTTPS (TCP 443) is blocked.
- Security: SE Linux is enabled.

Allow HTTPS traffic (TCP 443) and disable SELinux using the `system-config-securitylevel` utility.

---



---

## 2.9 Verify NTP Daemon Operation

Because the NTP daemon is a critical component of RUEI, especially in a split Reporter-Collector configuration, it is recommended that you verify that it is activated in at least run level 5 during boot. Use the following commands:

```
chkconfig --list | grep ntp
ntpd      0:off  1:off  2:off  3:off  4:off  5:off  6:off
chkconfig ntpd on
chkconfig --list | grep ntp
ntpd      0:off  1:off  2:on   3:on   4:on   5:on   6:off
/etc/init.d/ntpd start
Starting ntpd:                                [ OK ]
```

Note that if the NTP daemon is not already running, you can start it with the command

```
/etc/init.d/ntpd restart
```

The following sample output show when the NTP daemon is synchronized (indicated by an "\*").

```
ntpq -pn
      remote                refid          st t when poll reach  delay  offset jitter
=====
*194.171.167.130            .PPS.           1 u 994 1024 377    6.429  0.041  0.093
+80.85.129.25              130.235.20.3    3 u 725 1024 377    4.435  0.673  0.129
+82.94.235.106            135.81.191.59  2 u 678 1024 377    1.709  1.774  0.020
127.127.1.0                .LOCL.          10 l 8   64 377    0.000  0.000  0.001
```

---



---

**Important:** In distributed environments, all time zones specified for Reporter and Collector systems *must* be identical.

---



---



---

---

## Installing the Required Components

This chapter describes the procedure for installing all required components prior to installing RUEI. The installation of the RUEI software itself is described in [Chapter 4, "Installing the RUEI Software"](#).

---

---

**Note:** It is assumed throughout this guide that the installation is performed as the `root` user, unless indicated otherwise.

---

---

### 3.1 Mounting the Linux DVD

If the Linux DVD is mounted automatically, the content is located in the directory `/media/Enterprise Linux dvd 20090908` (the date depends on the downloaded version of the DVD). If the DVD is not automatically mounted, use the following commands to mount it:

```
mkdir -p /mnt/dvd
mount /dev/dvd /mnt/dvd
```

---

---

**Note:** In the rest of this chapter it is assumed the Linux operating system DVD is mounted on `/mnt/dvd`.

---

---

### 3.2 Installing Collector-Only System Prerequisites

Besides the base operating system, you do not need to install any additional RPM packages. You should proceed directly to [Chapter 4, "Installing the RUEI Software"](#).

### 3.3 Installing the Database Prerequisites

Note the procedure described in this section is only required for a Reporter system with a local database.

1. Install all prerequisites for the Oracle database using the following commands:

```
cd /mnt/dvd/Server
rpm -Uvh kernel-headers-2.6.18-*.el5.x86_64.rpm \
elfutils-libelf-devel-0.137-*.el5.x86_64.rpm \
elfutils-libelf-devel-static-0.137-*.el5.x86_64.rpm \
glibc-devel-2.5-* \
glibc-headers-2.5-*.x86_64.rpm \
gcc-4.1.2-*.el5.x86_64.rpm \
gcc-c++-4.1.2-*.el5.x86_64.rpm \
```

```
libstdc++-devel-4.1.2-*.el5.x86_64.rpm \
libgomp-4.4.0-*.el5.x86_64.rpm \
libaio-devel-0.3.106-*.x86_64.rpm \
sysstat-7.0.2-*.el5.x86_64.rpm
```

### 3.3.1 Installing the Reporter Prerequisites

1. Issue the following command to install all prerequisites for the Reporter:

```
rpm -Uvh httpd-2.2.3-*.el5.x86_64.rpm \
apr-1.2.7-11.*.x86_64.rpm \
apr-util-1.2.7-*.x86_64.rpm \
php-5.1.6-*.x86_64.rpm \
mod_ssl-2.2.3-*.el5.x86_64.rpm \
distcache-1.4.5-*.x86_64.rpm \
php-common-5.1.6-*.x86_64.rpm \
php-cli-5.1.6-*.x86_64.rpm \
php-mbstring-5.1.6-*.x86_64.rpm \
php-ldap-5.1.6-*.x86_64.rpm \
gmp-4.1.4-*.el5.x86_64.rpm \
postgresql-libs-8.1.11-*.el5_1.1.x86_64.rpm \
lm_sensors-2.10.7-*.el5.x86_64.rpm \
net-snmp-5.3.2.2-*.el5.x86_64.rpm \
net-snmp-utils-5.3.2.2-*.el5.x86_64.rpm \
perl-XML-Twig-3.26-*.fc6.noarch.rpm \
perl-XML-Parser-2.34-*.x86_64.rpm
```

2. Issue the following the commands to install all optional fonts. Alternatively, install the multi-byte character sets necessary to meet your NLS requirements.

```
rpm -Uvh fonts-*
```

3. Continue with the rest of the installation procedure from [Section 3.4.1, "Creating the Database User Accounts and Groups"](#).

### 3.3.2 Installing All Requirements Using a Yum Repository (Alternative)

As an alternative to manual installation, you can use a Yum repository to install the required RPMs. This requires a working Yum repository. For information on Yum repositories, see <http://linux.duke.edu/projects/yum/>. Install the necessary Oracle database packages using the following commands:

```
yum -y install gcc
yum -y install gcc-c++
yum -y install compat-libstdc++-33
yum -y install libstdc++-devel
yum -y install elfutils-libelf-devel
yum -y install glibc-devel
yum -y install libaio-devel
yum -y install sysstat
```

Install the necessary Reporter packages using the following commands:

```
yum -y install perl-URI
yum -y install perl-XML-Twig
yum -y install net-snmp-utils
yum -y install sendmail-cf
yum -y install httpd
yum -y install mod_ssl
yum -y install php
yum -y install php-mbstring
```

```

yum -y install php-ldap
yum -y install bitstream-vera-fonts
yum -y install librsvg2
yum -y install xorg-x11-xinit
yum -y install fonts-*

```

## 3.4 Installing and Configuring the Oracle Database

This section describes the procedure for installing the Oracle database. This section can be skipped if you preparing a Reporter server with a remote database or a Collector system. Continue with the installation procedure at [Chapter 4, "Installing the RUEI Software"](#).

Download Oracle Database 11g Release 1 (11.1.0.6.0) Standard Edition, Standard Edition One, and Enterprise Edition from the Oracle database home page (<http://www.oracle.com/technology/software/products/database/index.html>).

The procedure for installing the Oracle database is fully described in the product documentation. This section presents a summary of that procedure.

The information in this guide is based on the *Oracle Database 11g for Linux x86-64 Quick Installation Guide*. It is recommended that you download and review it. It is available from the Oracle Database Documentation Library ([http://download.oracle.com/docs/cd/B28359\\_01/install.111/b32285/toc.htm](http://download.oracle.com/docs/cd/B28359_01/install.111/b32285/toc.htm)).

---



---

**Note:** The Oracle database's maximum memory usage is set by the `MEMORY_TARGET` parameter. By default, this is set to 40% of the available server RAM. For example, in a system with 16 GB RAM, it is set to approximately 6.4 GB. Note that if extra RAM is added to the server system to increase performance, it is not made available to the Oracle database until the `MEMORY_TARGET` parameter is manually increased.

Information about automatic memory management is available from the Oracle Database Documentation Library ([http://download.oracle.com/docs/cd/B28359\\_01/server.111/b28310/memory003.htm#ADMIN11200](http://download.oracle.com/docs/cd/B28359_01/server.111/b28310/memory003.htm#ADMIN11200)).

---



---

### 3.4.1 Creating the Database User Accounts and Groups

1. Create two groups (`dba` and `oinstall`) with the following commands:

```

/usr/sbin/groupadd dba
/usr/sbin/groupadd oinstall

```

2. Create the `oracle` user, and specify `oinstall` as the primary group and `dba` as the secondary group, with the following command:

```

/usr/sbin/useradd -g oinstall -G dba oracle

```

3. Set the `oracle` user password with the following command:

```

passwd oracle

```

### 3.4.2 Configuring the Kernel Parameter Settings

1. Modify the `/etc/sysctl.conf` file to satisfy the Oracle installer's requirements by adding the following lines:

```
kernel.sem = 250 32000 100 128
net.ipv4.ip_local_port_range = 1024 65000
net.core.rmem_default = 4194304
net.core.rmem_max = 4194304
net.core.wmem_default = 262144
net.core.wmem_max = 262144
fs.file-max = 6553600
```

2. Make these changes effective immediately with the following command:

```
/sbin/sysctl -p
```

### 3.4.3 Setting Shell Limits for the Oracle User

1. To improve the performance of the software, you must increase the shell limits for the `oracle` user. Add the following lines to the `/etc/security/limits.conf` file:

```
oracle soft nproc 2047
oracle hard nproc 16384
oracle soft nofile 1024
oracle hard nofile 65536
```

2. If not already present, add the following lines to the `/etc/pam.d/login` file:

```
session required /lib64/security/pam_limits.so
session required pam_limits.so
```

3. Depending on the `oracle` user's default shell, you need to make changes to it. For the Bourne, Bash, or Korn shell, add the following lines to the bottom of the `/etc/profile` file:

```
if [ $USER = "oracle" ]; then
    if [ $SHELL = "/bin/ksh" ]; then
        ulimit -p 16384
        ulimit -n 65536
    else
        ulimit -u 16384 -n 65536
    fi
fi
```

For information about other shells, you should refer to the *Oracle Database 11g Release 1 for Linux x86-64 Quick Installation Guide* available at the following location:

[http://download.oracle.com/docs/cd/B28359\\_01/install.111/b32285/toc.htm](http://download.oracle.com/docs/cd/B28359_01/install.111/b32285/toc.htm)

### 3.4.4 Creating the Database Directory

Throughout this guide it is assumed that the directory `/u01/app` is the root of the Oracle installation. This is specified in the `ORACLE_BASE` environment variable.

1. Enter the following command to display information about all mounted file systems:

```
df -k
```

This command displays information about all the file systems mounted on the system, including:

- The physical device name.
  - The total amount, used amount, and available amount of disk space.
  - The mount point directory for that file system.
2. Create the necessary subdirectories in the mount point directory that you identified and set the appropriate owner, group, and permissions for them using commands similar to the following:

```
mkdir -p /u01/app
chown -R oracle:oinstall /u01/app
chmod -R 775 /u01/app
```

### 3.4.5 Configuring the Oracle User's Environment

1. Logon to the system as the `oracle` user.
2. Add or edit the `umask` setting in the `~/ .bash_profile` file to the following:
 


```
umask 022
```
3. Make the setting active for the current shell by issuing the following command:
 

```
. ~/.bash_profile
```
4. Set the `ORACLE_BASE` environment variable to define the location of the root of the Oracle directory tree:
 

```
export ORACLE_BASE=/u01/app/oracle
```
5. Unzip the Oracle database installation zip file. This creates the directory `database`. Then, run the graphical installer (note this will not run under user `root`). Ensure that your X Window environment is properly set up. In addition, when logging on remotely with SSH, ensure X forwarding is enabled. Use the following commands:
 

```
cd <location of the zip file>
unzip linux_11gR1_database.zip
./database/runInstaller
```
6. Use the installation wizard, and specify the values shown in [Figure 3-1](#).


**Figure 3–1 Select Installation Method**



Note that the **Create Starter Database** check box should be unchecked.

7. When ready, click **Next**. Specify the values shown in [Figure 3–2](#). When ready, click **Next**.

**Figure 3–2 Specify Inventory Directory and Credentials**



---


**Important:** Any warnings or errors reported during database installation (especially any missing prerequisites) must be resolved before proceeding. See [Section 3.3.2, "Installing All Requirements Using a Yum Repository \(Alternative\)"](#) and [Appendix E, "Troubleshooting"](#) for information about required components.

---

If all dependencies are met, you can click **Next**.

- When installation is almost complete, you are prompted to run two scripts, `orainstRoot.sh` and `root.sh`, as `root`. This is shown in [Figure 3-3](#).

**Figure 3-3 Configuration Scripts**



Run the two scripts indicated in [Figure 3-3](#). They should be run in a terminal window as `root`. You will receive output similar to the following:

```
/u01/app/oraInventory/orainstRoot.sh
Changing permissions of /u01/app/oraInventory to 770.
Changing groupname of /u01/app/oraInventory to oinstall.
The execution of the script is complete
```

Finished product-specific root actions.

The second script generates the following output:

```
/u01/app/oracle/product/11.1.0/db_1/root.sh
Running Oracle 11g root.sh script...
```

The following environment variables are set as:

```
ORACLE_OWNER= oracle
ORACLE_HOME= /u01/app/oracle/product/11.1.0/db_1
```

Enter the full pathname of the local bin directory: [/usr/local/bin]:

```
Copying dbhome to /usr/local/bin ...
Copying oraenv to /usr/local/bin ...
Copying coraenv to /usr/local/bin ...
```

```
Creating /etc/oratab file...
```

Entries will be added to the `/etc/oratab` file as needed by Database Configuration Assistant when a database is created. Finished running generic part of `root.sh` script. Now product-specific root actions will be performed.

On completion of each script, return the dialog shown in [Figure 3-3](#), and click **OK**. In the main installer screen, verify that the message "The installation of Oracle database 11g was successful" appears. Click **Exit**, and confirm by clicking **Yes**.

### 3.4.6 Creating an Oracle init Script File

1. Logon as the root user.
2. Create an `/etc/init.d/oracledb` script file to start and stop the Oracle database. An example of this initialization script is available in the RUEI installation zip file (`/root/RUEI/extra/oracledb`) explained in [Chapter 4, "Installing the RUEI Software"](#). Note that you will need to modify the settings for the `ORACLE_BASE` and `ORACLE_HOME` environment variables shown above if you selected a different installation directory for the Oracle database.
3. Make the script file executable and use it to start the Oracle database with the following commands:

```
chmod +x /etc/init.d/oracledb
/sbin/chkconfig --add oracledb
/sbin/service oracledb start
```

The Oracle database is now installed, and the database listener should be up and running.



---

---

## Installing the RUEI Software

This chapter describes the procedure for installing the Apache Web server and RUEI software. The procedure for upgrading an existing RUEI 5.x installation to release 6.5 is described in [Chapter 5, "Upgrading to RUEI 6.5.1"](#). The post-installation configuration procedure is described in [Chapter 6, "Configuring RUEI"](#).

### 4.1 Obtaining the RUEI Software

The RUEI software is available from the Oracle E-Delivery Web site (<http://edelivery.oracle.com>). Select the following media pack criteria:

- Oracle Enterprise Manager
- Linux x86-64

### 4.2 Unpacking the RUEI Software

Copy the downloaded RUEI zip file to `/root` directory on the server, and unzip it. Use the following commands:

```
cd /root
unzip package_name.zip
```

The following directories are created which contain the software needed to complete the RUEI installation:

- `/root/RUEI/65`
- `/root/RUEI/ZendOptimizer`
- `/root/RUEI/IC`
- `/root/RUEI/PHP`
- `/root/RUEI/Java`
- `/root/RUEI/extra`

### 4.3 Generic Installation Tasks

All steps described in this section must be performed regardless of your planned installation (that is, a Reporter with local database, a Reporter with remote database, or a Collector).

### 4.3.1 The RUEI Configuration File

The `/etc/ruei.conf` file specifies the settings used within your installation. Note that all components in your RUEI environment (such as the remote database and Collectors) require the same global `/etc/ruei.conf` configuration file. The settings shown in [Table 4-1](#) are defined.

**Table 4-1 RUEI Settings.**

Setting	Description <sup>1</sup>	Value
RUEI_HOME <sup>2</sup>	Home directory of the RUEI software.	<code>/opt/ruei</code>
RUEI_DATA <sup>2</sup>	Directory for RUEI data files.	<code>/var/opt/ruei</code>
RUEI_USER	The RUEI operating system user.	<code>moniforce</code>
RUEI_GROUP	The RUEI operating system group.	<code>moniforce</code>
RUEI_DB_INST <sup>3</sup>	The database instance name.	<code>ux</code>
RUEI_DB_USER <sup>4</sup>	The database user name.	<code>UXINSIGHT</code>
RUEI_DB_TNSNAME <sup>5</sup>	The database connect string.	<code>uxinsight</code>

<sup>1</sup> Be aware that all variables specified in this table are the values used throughout this guide, and can be modified as required.

<sup>2</sup> The directory name cannot exceed 50 characters in length.

<sup>3</sup> The database instance name cannot exceed 8 characters in length.

<sup>4</sup> The database user name cannot exceed 30 characters in length.

<sup>5</sup> The alias name cannot exceed 255 characters in length.

There is no need to change the settings for `JAVA_HOME` and `INSTANTCLIENT_DIR` if you intend to use the software contained on the RUEI distribution pack.

1. Create the `moniforce` group and user. The home directory of `moniforce` should be set to `/var/opt/ruei`, with read permissions for group members.

```
/usr/sbin/groupadd moniforce
/usr/sbin/useradd moniforce -g moniforce -d /var/opt/ruei
chmod -R 750 /var/opt/ruei
chown -R moniforce:moniforce /var/opt/ruei
```

2. An example of the configuration file is included in the RUEI distribution pack. Ensure the file is readable by the `RUEI_USER` user by issuing the following commands:

```
cp /root/RUEI/extra/ruei.conf /etc/
chmod 644 /etc/ruei.conf
chown moniforce:moniforce /etc/ruei.conf
```

In case of a remote database installation, the `ruei.conf` file needs to be identical with that of the Reporter system.

### 4.3.2 Installing Java

For both Reporter and Collector systems you need to install the Java Runtime Environment (JRE). Java is bundled within the RUEI distribution pack.

1. Issue the following commands:

```
cd /root/RUEI/Java
chmod +x ./jre-1_5_0_22-linux-amd64-rpm.bin
./jre-1_5_0_22-linux-amd64-rpm.bin
```

Note you are prompted to accept the Java licence agreement. You cannot continue until you have done so.

2. This installs the necessary Java software in the directory `/usr/java/jre1.5.0_22`. To make the install directory version independent, create a more generic symlink using the following command:

```
ln -s /usr/java/jre1.5.0_22 /usr/java/jre
```

## 4.4 Remote Collector Installation

This section can be skipped for Reporter or remote database servers.

Logon to the Collector system as the `root` user, and do the following:

1. The RUEI file and directory locations are fixed. Therefore, it is necessary to use the exact directory name described below. Create the RUEI application root directory using the following command:

```
mkdir -p /opt/ruei
chmod 750 /opt/ruei
```

2. Change to the RUEI root directory and run the `ruei-install.sh` script using the following commands:

```
cd /root/RUEI/65
chmod +x ruei-install.sh ruei-check.sh
./ruei-install.sh collector
```

3. In addition to the actions described above, you need to configure the network interfaces. This is fully described in [Section 4.6, "Configuring the Network Interface"](#). Moreover, you also need to setup a password-less remote login from the Reporter system to the newly created Collector system. The necessary configuration steps are described in [Section 4.11, "Configuring Reporter Communication \(Split-Server Setup Only\)"](#).

## 4.5 Reporter Installation

This section describes the procedure for installing the required components for a Reporter system. These include the Apache Web server, the Oracle database Instant Client, and the Zend Optimizer.

### 4.5.1 Installing the Apache Web Server and PHP

This section describes the installation and configuration of the Apache Web server, and the components that use it.

#### 4.5.1.1 PHP Configuration

1. Ensure that the Web server starts automatically after re-boot by issuing the following command:

```
/sbin/chkconfig httpd on
```

2. Edit the `/etc/sysconfig/httpd` file to include the following line at the bottom of the file:

```
source /etc/ruei.conf
```

3. Create the following settings in the `/etc/php.d/ruei.ini` file:

```
session.gc_maxlifetime = 14400
memory_limit = 96M
upload_max_filesize = 128M
post_max_size = 128M
```

#### 4.5.1.2 Avoiding rsvg Warnings

RUEI uses rsvg for graph generation. In order to avoid warnings about a missing directory, create the empty `.gnome2` directory using the following command:

```
mkdir -p /var/www/.gnome2
```

### 4.5.2 Installing the Oracle Database Instant Client

Install the Oracle database Instant Client and SQLplus extension with the following commands as the `root` user:

```
cd /root/RUEI/IC
rpm -Uhv oracle-instantclient11.2-basic-*.rpm
rpm -Uhv oracle-instantclient11.2-sqlplus-*.rpm
```

### 4.5.3 Installing the php-oci8 Module

Install the `php-oci8` module (this is part of the RUEI distribution set) using the following commands:

```
cd /root/RUEI/PHP
rpm -Uhv php-oci8-11gR2-5*
```

### 4.5.4 Installing the Zend Optimizer

Go to the directory containing the Zend Optimizer code, unpack the tar file, and run the Zend optimizer installer. Read the license agreement. You will not be able to proceed until you have accepted the license terms. Accept all default settings, and allow the installer to restart the Apache Web server. Issue the following commands:

```
cd /root/RUEI/ZendOptimizer
tar zxvf ZendOptimizer-3.3.3-linux-glibc23-x86_64.tar.gz
cd ZendOptimizer-3.3.3-linux-glibc23-x86_64
./install
```

---

---

**Note:** If you upgrade your system packages (for example, using Yum), this can overwrite changes you previously made to the `/etc/php.ini` file. Therefore, you should be prepared to re-install the Zend Optimizer. When doing so, ensure the Zend Optimizer installer indicates the location of the `php.ini` file as `/etc/php.ini` and not `/usr/local/Zend/etc/php.ini`.

---

---

#### Additional Information

It is recommended you move the Zend configuration lines created in the `/etc/php.ini` file to the RUEI-specific PHP configuration file `/etc/php.d/ruei.ini` to prevent upgrade issues. If you performed a default installation of the Zend Optimizer, this involves moving the following lines:

```
[Zend]
zend_extension_manager.optimizer=/usr/local/Zend/lib/Optimizer-3.3.3
zend_extension_manager.optimizer_ts=/usr/local/Zend/lib/Optimizer_TS-3.3.3
```

```
zend_optimizer.version=3.3.3

zend_extension=/usr/local/Zend/lib/ZendExtensionManager.so
zend_extension_ts=/usr/local/Zend/lib/ZendExtensionManager_TS.so
```

## 4.5.5 Creating the RUEI Database Instance

The RUEI database can reside either locally (that is, on the Reporter server) or on a remote database server. In this section you will create the database instance required for RUEI, and generate the "connection data" required for the Reporter to connect to this database instance.

You will need the following scripts to be present on the system where the database instance (RUEI\_DB\_INST) will be created:

- `ruei-prepare-db.sh`: creates the database instance, Oracle wallet, and database connect files.
- `ruei-check.sh`: this is a hardware and environment check utility, and is automatically invoked by `ruei-prepare-db.sh`. The script can also be used as a stand-alone troubleshooting utility. For a complete description of the script, refer to [Appendix B, "The ruei-check.sh Script"](#).

The four "connection data" files created during the procedure described in this section are as follows:

- `cwallet.sso`
- `ewallet.p12`
- `sqlnet.ora`
- `tnsnames.ora`

The RUEI configuration file (`/etc/ruei.conf`) also needs to be present on the database server and configured as described in [Section 4.3.1, "The RUEI Configuration File"](#).

Do the following:

1. Copy the `ruei-prepare-db.sh` and `ruei-check.sh` scripts to the server on which you intend to run the database instance, and make them executable for the `oracle` user. These scripts can be found in the RUEI distribution zip (`/root/RUEI/65`).
2. Review the settings in the `/etc/ruei.conf` file to match your needs as described in [Section 4.3.1, "The RUEI Configuration File"](#).
3. Logon to the database server as the `oracle` user on the database server, and set the `ORACLE_HOME` environment variable. You need to run the `ruei-prepare-db.sh` script as the `oracle` user. This script creates the RUEI\_DB\_INST database, but only after a number of hardware and software environment checks have been performed. The actual checks performed depend on the system type you are currently installing.

The script prompts you for the RUEI database user password<sup>1</sup>. This enables the RUEI application to login to the database automatically. The script also creates the "connection data" files for you now.

<sup>1</sup> The database password is also used as the Oracle wallet password. Both passwords must be between 8 and 30 characters in length, and contain both numbers and letters. For information on changing the Oracle wallet password, please consult the appropriate Oracle documentation.

If you run the `ruei-prepare-db.sh` script for a combined Reporter/Database server, all files are placed automatically in the correct location<sup>2</sup>. In case of a remote database, a separate `.tar` file is generated, and you will need to perform the extra step 4.

Issue the following commands:

```
chmod +x ruei-prepare-db.sh ruei-check.sh
export ORACLE_HOME=/u01/app/oracle/product/11.1.0/db_1
./ruei-prepare-db.sh
```

If you ran the above commands on a combined Reporter/Database server you can skip step 4 and proceed to step 5.

4. This step only applies when using a remote database.

In the case of a Reporter system using a remote database, you will need to copy the generated `/tmp/ruei-database-configuration.tar` file in step 3 from the database server to the Reporter system. The `/tmp/ruei-database-configuration.tar` file must be extracted on the Reporter server in the directory `/var/opt/ruei` (RUEI\_DATA). The permissions of the files need to be set so that the specified RUEI\_USER (`moniforce`) can use them.

Copy the generated `.tar` file, which holds connection data files to the Reporter system. Logon to the Reporter server and extract the `.tar` file using the following commands:

```
cd /var/opt/ruei
tar xvf path-to-tar-file/ruei/database-configuration.tar
chown moniforce:moniforce cwallet.sso ewallet.p12 sqlnet.ora tnsnames.ora
```

5. Because logging of the database can consume a large amount of disk space, it is recommended that you install a clean-up script to avoid the usage of unnecessary disk space. Copy the (example) script to the `oracle` user directory and activate it via `cron` using the following commands:

```
mkdir -p /home/oracle/bin
cp /root/RUEI/extra/ruei-clean.sh /home/oracle/bin
chmod +x /home/oracle/bin/ruei-clean.sh
su - oracle -c 'echo "10 0 * * * /home/oracle/bin/ruei-clean.sh" | crontab'
```

## 4.5.6 Installation of the Reporter Software

1. The RUEI directory locations are flexible. Therefore, it is necessary to use the exact directory name described as configured in the `/etc/ruei.conf` file. Create the RUEI application root directory using the following command:

```
mkdir -p /opt/ruei
chmod 750 /opt/ruei
```

---

**Note:** The specified RUEI\_HOME and RUEI\_DATA directories must have 750 permissions defined for them.

---

2. Make the `apache` and `moniforce` members of two additional groups using the following commands:

<sup>2</sup> If you do not know the root password, you can select the "remote database" option, and manually extract the connection tar file. This is described in step 4.

```
/usr/sbin/usermod -aG moniforce apache
/usr/sbin/usermod -aG uucp apache
/usr/sbin/usermod -aG uucp moniforce
```

3. Go to the directory which holds the RUEI software, and install the RUEI packages. You can specify `reporter` or `collector` to the `ruei-install.sh` script depending on the required installation:

```
cd /root/RUEI/65
chmod +x ruei-install.sh
./ruei-install.sh reporter
```

4. Re-start the Apache Web server using the following command:

```
/sbin/service httpd restart
```

5. Verify that the RUEI software was correctly installed by issuing the following command:

```
./ruei-check.sh postinstall
```

6. As the `moniforce` user, set the RUEI admin user password to enable logging onto the RUEI interface with the following commands:

```
su - moniforce
set-admin-password
```

You are prompted to enter and confirm the password.

---



---

**Note:** When defining the admin user password, bear the following in mind:

- The password must have at least eight characters, and contain at least one non-alphanumeric character (such as \$, @, &, and !).
  - The initial password must be changed within seven days.
  - The user name and password are case sensitive.
- 
- 

## 4.6 Configuring the Network Interface

This section is only relevant to Reporter and Collector systems.

Make the monitoring network interface `up` status permanent (after a reboot) by setting the `ONBOOT` parameter of the capturing interfaces to `yes` in the interface configuration files. The network interfaces configuration can be found in `/etc/sysconfig/network-scripts/ifcfg-ethX` (where `X` represents the necessary network interface). Alternatively, use the graphical utility **system-config-network** to set the appropriate interfaces to "activate device when computer starts".

## 4.7 Enabling Multibyte Fonts (Optional, but Recommended)

This section is only relevant to the Reporter system.

For PDF generation with multibyte character content, additional fonts need to be enabled. These fonts need to be made available to Java. Use the following command to copy (or move) the RUEI-installed fonts to the appropriate Java directory:

```
cp /opt/ruei/gui/include/bi_publisher/fonts/* \
```

```
/usr/java/jre/lib/fonts/
```

## 4.8 Mail (MTA) Configuration (Optional, Reporter Only)

This section is only relevant to the Reporter system.

RUEI assumes a working local MTA for sending PDF reports and E-mail alerts. By default, Linux uses the Sendmail MTA. By default, Sendmail will deliver the E-mail directly to the destination MTA. If this behavior is not according to your needs or policies, sending mail via a SmartHost (relay) might be an alternative. To configure a SmartHost in Sendmail, do the following:

1. Install the Sendmail configuration utility by going to the directory containing the uploaded RPM and issuing the following command:

```
rpm -Uhv sendmail-cf-8.13.8-*.el5.x86_64.rpm
```

2. Find the line which contains the Smart Host setting in `/etc/mail/sendmail.mc`. Modify the `SMART_HOST` setting to your needs. For example:

```
define('SMART_HOST', 'my.example')dnl
```

3. Generate the new configuration into a new `sendmail.cf` by executing the following command:

```
make -C /etc/mail
```

4. Restart Sendmail. For example:

```
/etc/init.d/sendmail restart
```

---

---

**Note:** Extensive information about the configuration of the Sendmail MTA is available at <http://www.sendmail.org>.

---

---

## 4.9 SNMP (Reporter Only)

You can download the RUEI MIB definition file through the Reporter interface. This definition file can be added to the SNMP manager. The procedure for downloading the MIB file is described in the *Oracle Real User Experience Insight User's Guide*.

## 4.10 Configuring Automatic Browser Redirection (Optional)

This section is only relevant to Reporter systems.

To have the browser automatically redirected to the correct RUEI path, create the file `/var/www/html/index.html` with the following content:

```
<head>
<meta http-equiv="REFRESH" content="0;URL=/ruei/">
</head>
```

## 4.11 Configuring Reporter Communication (Split-Server Setup Only)

This section is only relevant to a Reporter system with remote Collector(s).

A password-less SSH connection must be setup between the `Moniforce` user from the Reporter system to each Collector system. Do the following:

1. Logon to the Reporter server as `root`. Issue the following commands:

```
su - moniforce
ssh-keygen -P ""
```

Press **Enter** to accept the defaults.

2. Logon as `root` to each of the Collector systems and become the `moniforce` user by issuing the following command:

```
su - moniforce
```

3. Create the `.ssh` directory (if it does not already exist) for the `moniforce` user on each Collector system by issuing the following commands:

```
mkdir ~/.ssh
chmod 700 ~/.ssh
```

4. Copy the SSH key on the Reporter system to the required location on the Collector system by issuing the following commands:

```
cd ~/.ssh
ssh root@Reporter cat /var/opt/ruei/.ssh/id_rsa.pub >> authorized_keys
```

(you will need to specify the Reporter system `root` password)

```
chmod 600 authorized_keys
```

5. Check that it is now possible to execute a remote command (as `moniforce` user) on the Reporter system without using a password. For example:

- Logon as `root` on the Reporter server.
- Logon as `moniforce` user: `su - moniforce`.
- Execute a remote `pwd` command: `ssh Collector pwd`.
- Enter `yes` to the question "Are you sure you want to continue connecting (yes/no)?".
- The command should return `/var/opt/ruei`.

6. The above steps must be performed for each Collector!

---



---

**Note:** If the connection between the Reporter and the Collector(s) has not been correctly configured, you will receive an authorization error when you try to register the remote Collector.

---



---

## 4.12 Verifying Successful Installation of RUEI

On completion of the Initial Setup Wizard (described in [Section 6.2, "Performing Initial RUEI Configuration"](#)), you can verify your installation by selecting **System**, the **Status**. All system indicators should report OK. Note Status notification will indicate "Unknown" because no system alerts have yet been configured. This is fully described in the *Oracle Real User Experience Insight User's Guide*.



---

---

## Upgrading to RUEI 6.5.1

This chapter describes the procedure for upgrading an existing RUEI 5.x or 6.x installation to release 6.5.1. The post-installation configuration procedure is described in [Chapter 6, "Configuring RUEI"](#).

If the DVD is not automatically mounted, use the following commands to mount it:

```
mkdir -p /mnt/dvd
mount /dev/dvd /mnt/dvd
```

---

---

**Note:** In the rest of this chapter it is assumed that the RUEI DVD is mounted on `/mnt/dvd`.

---

---

Note that the upgrade procedure described below should be performed as the `root` user unless indicated otherwise.

### 5.1 Upgrading From RUEI 5.x to 6.5.1

This section describes the procedure for upgrading from an existing RUEI 5.x installation to release 6.5.1.

---

---

**Important:** Before proceeding with the upgrade, make a backup of your configuration. Select **Configuration**, then **System**, then **Maintenance**, and then **Backup and restore**. The configuration backup is required in case of a rollback. In addition, it is *strongly* recommended that you create a database backup. Information on database backup procedures is available at <https://support.oracle.com/CSP/ui/flash.html>.

---

---

#### 5.1.1 Upgrading Accelerator packages

As of version 6.5.1, all supported accelerators are automatically installed as part of the Reporter installation procedure. Note that the use of some accelerators requires additional Oracle product licenses. You should ensure that you are licensed to use a product before configuring suites based upon it. For further information, please consult your Oracle representative.

#### 5.1.2 Upgrading the Reporter System

Do the following:

1. Copy the RUEI distribution pack (Vxxx.zip) to the Reporter system /root directory, and unzip it. Issue the following commands:

```
cd /root
unzip Vxxx.zip
```

2. Install the XML:Twig module by issuing the following commands:

```
cd /mnt/dvd/Server
rpm -Uhv perl-XML-Twig-3.26-*.fc6.noarch.rpm \
perl-XML-Parser-2.34-*.x86_64.rpm
```

3. Install the Java Runtime Environment (JRE). Note that this step can be skipped if you are upgrading from RUEI 5.1. Issue the following commands:

```
cd /root/RUEI/Java
chmod +x ./jre-1_5_0_22-linux-amd64-rpm.bin
./jre-1_5_0_22-linux-amd64-rpm.bin
ln -s /usr/java/jre1.5.0_22 /usr/java/jre
```

Note you are prompted to accept the Java license agreement. You cannot continue until you have done so.

This installs the JRE from a standalone package bundled with the RUEI distribution set, rather than the one built into the database.

4. Temporarily stop all processing by issuing the following command:

```
cd /root/RUEI/extra
chmod +x ruei-upgrade-5.x-6.5.sh
./ruei-upgrade-5.x-6.5.sh stop_ruei
```

5. Install the new Oracle Instant client by issuing the following commands:

```
cd /root/RUEI/IC
rpm -Uhv oracle-instantclient11.2-*
```

6. Install the new PHP OCI module by issuing the following commands:

```
cd /root/RUEI/PHP
rpm -Uhv php-oci8-11gR2-*
```

7. Update the logical links by issuing the following commands:

```
ln -sf /usr/lib64/oracle/11.2/php-oci8/oci8.ini /etc/php.d/oci8.ini
ln -sf /usr/lib64/oracle/11.2/php-oci8/oci8.so /usr/lib64/php/modules/oci8.so
```

Note the use of the force (-f) option.

8. For each Collector system, issue the following commands:

```
cd /root/RUEI/extra
./ruei-upgrade-5.x-6.5.sh stop_collector Collector-IP-address
```

where **Collector-IP-address** is the IP address of the collector system. Note that this command must also be issued for the local Collector (localhost).

9. Note that this step can be skipped if you are upgrading from RUEI 5.1. Update the /etc/ruei.conf file by issuing the following commands:

```
cp /etc/ruei.conf /etc/ruei.conf.50
cp /root/RUEI/extra/ruei.conf.upgrade /etc/ruei.conf
chmod 644 /etc/ruei.conf
source /etc/ruei.conf
```

```
chown $RUEI_USER:$RUEI_GROUP /etc/ruei.conf
```

**10. Update the RUEI database instance by issuing the following commands:**

```
cd /root/RUEI/65
cp ruei-prepare-db.sh /home/oracle
cp ruei-check.sh /home/oracle
chmod +x /home/oracle/ruei-*.sh
su - oracle
export ORACLE_HOME=/u01/app/oracle/product/11.1.0/db_1
./ruei-prepare-db.sh
exit
```

Upon completion, you should again be the root user.

**11. Upgrade the RUEI Reporter RPMs by issuing the following commands:**

```
cd /root/RUEI/extra
./ruei-upgrade-5.x-6.5.sh rpm_pre_install
cd /root/RUEI/65
chmod u+x ./ruei-install.sh
./ruei-install.sh *.rpm
cd /root/RUEI/extra
./ruei-upgrade-5.x-6.5.sh rpm_post_install
```

---

**Note:** When upgrading a Reporter system that has little or no replay data on its local Collector, "\*LTS?\*" errors can be reported. These can be safely ignored.

---

**12. Important:** if you do not perform the action described in this step, the currently defined Error Page Replay (EPR) and Full Session Replay (FSR) settings are applied for *each* monitored application. Depending on the number of monitored applications, and your previous settings, the amount of required disk space can significantly increase. For example, if data retention was set to 50 GB, and five applications are monitored by a Collector, the Collector will reserve up to 50 GB per application upon upgrading to version 6.5 (that is, a total Collector disk space of 250 GB).

If this would require too much disk space to be reserved on a Collector system, you can issue the following command to limit the total reserved disk space to its current defined setting:

```
./ruei-upgrade-5.x-6.5.sh resize_replay_store
```

In this case, the total reserved disk space is shared equally among the currently defined applications. For example, if the current data retention setting was 100 GB, and there are 10 monitored applications, this would result in 10 GB of disk space being available for each application. Note that, if you choose to use the above command, it may result in the loss of existing (the oldest) replay data.

**13. Note that this step can be skipped if you are upgrading from RUEI 5.1. Enable additional fonts for PDF generation. Because the PDF generator uses Java libraries, these need to be made available to Java. Copy (or move) the RUEI included fonts to the appropriate Java directory. For example:**

```
cp /opt/ruei/gui/include/bi_publisher/fonts/* \
/usr/java/jre/lib/fonts/
```

- Note that this step can be skipped if you are upgrading from 5.1. If the export report functionality has been customized with a `.htaccess` file (described in the *Oracle Real User Experience Insight User's Guide*), you will need to move the RUEI configuration file to its new location. For example:

```
mv /var/www/ruei/.htaccess /opt/ruei/gui
```

- Restart the Apache Web server by issuing the following command:

```
/sbin/service httpd restart
```

---

---

**Important:** At this point you should complete the Collector upgrade procedure described below *before* proceeding with step 16.

---

---

- Restart processing (*after* you have upgraded all Collector systems) by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-upgrade-5.x-6.5.sh start_ruei
```

The procedure for upgrading the Reporter system is complete.

### Important

After completion of the upgrade procedure, it is recommended that you pay particular attention to the following:

- The default URL prefix masking action is set to "No replay". Review this setting (as described in the *Oracle Real User Experience Insight User's Guide*) to determine whether it meets your operational requirements.
- During and after the upgrade procedure, if error or information messages appear in the event log (select **System**, then **Status**, and then **Event log**), you should mark them as read after completing the upgrade procedure, and monitor whether new messages are reported. In the event of re-occurring error messages, you should contact Customer Support.
- For each Collector system, review its data retention policies (select **Configuration**, then **General**, then **Advanced settings**, and then **Collector data retention policy**).

## 5.1.3 Upgrading the Collector System(s)

Note that steps 1 through 4 are *only* required if you are upgrading from RUEI version 5.0. If you are upgrading from RUEI version 5.1, you should proceed directly to step 5.

Do the following:

- Remove the line containing the entry `/home/oracle/bin/ruei-clean.sh` from Oracle's `crontab` file by issuing the following commands:

```
su - oracle
crontab -e
exit
```

- Stop the Oracle database, and remove the installation script so that it will no longer be started after a reboot, by issuing the following commands:

```
service oracledb stop
chkconfig --del oracledb
```

Note that if stopping the Oracle database service seems to take an usually long period of time, you should open a second terminal and kill any running process called `rsynclogdird`.

3. Stop the Apache Web server by issuing the following commands:

```
service httpd stop
chkconfig --del httpd
```

4. De-install all RUEI RPMs (except `ux-collector`) by issuing the following command:

```
rpm -qa | grep ^ux-.*-5.0 | grep -v ^ux-collector | xargs rpm -e
```

5. Copy the RUEI distribution pack (`Vxxx.zip`) to the Collector system `/root` directory, and unzip it. Issue the following commands:

```
cd /root
unzip Vxxx.zip
cd /root/RUEI/65
```

6. Install the Java Runtime Environment (JRE). Note that this step can be skipped if you are upgrading from RUEI 5.1. Issue the following commands:

```
cd /root/RUEI/Java
chmod +x ./jre-1_5_0_22-linux-amd64-rpm.bin
./jre-1_5_0_22-linux-amd64-rpm.bin
ln -s /usr/java/jre1.5.0_22 /usr/java/jre
```

Note you are prompted to accept the Java license agreement. You cannot continue until you have done so.

This installs the JRE from a standalone package bundled with the RUEI distribution set, rather than the one built into the database.

7. Note that this step can be skipped if you are upgrading from RUEI 5.1. Update the `/etc/ruei.conf` file by issuing the following commands:

```
cp /etc/ruei.conf /etc/ruei.conf.50
cp /root/RUEI/extra/ruei.conf.upgrade /etc/ruei.conf
chmod 644 /etc/ruei.conf
source /etc/ruei.conf
chown $RUEI_USER:$RUEI_GROUP /etc/ruei.conf
```

8. Convert the Replay store and upgrade the RUEI Collector RPM by issuing the following commands:

```
cd /root/RUEI/extra
chmod +x ruei-upgrade-5.x-6.5.sh
./ruei-upgrade-5.x-6.5.sh convert_replay_store
cd /root/RUEI/65
chmod +x ruei-install.sh
./ruei-install.sh collector
cd /root/RUEI/extra
./ruei-upgrade-5.x-6.5.sh convert_replay_store2
```

Repeat the above steps for each Collector system in your RUEI infrastructure.

Note steps 1 through 4 are *only* required if you are upgrading from RUEI 5.0. If you are upgrading from RUEI 5.1, you should proceed directly to step 5.

At this point, you should return to step 13 of the Reporter system upgrade procedure.

## 5.2 Upgrading From RUEI 6.x to 6.5.1

This section describes the procedure for upgrading from an existing RUEI 6.x installation to release 6.5.1.

---

---

**Important:** Before proceeding with the upgrade, make a backup of your configuration. Select **Configuration**, then **System**, then **Maintenance**, and then **Backup and restore**. The configuration backup is required in case of a rollback.

---

---

### 5.2.1 Upgrading Accelerator packages

As of version 6.5.1, all supported accelerators are automatically installed as part of the Reporter installation procedure. Note that the use of some accelerators requires additional Oracle product licenses. You should ensure that you are licensed to use a product before configuring suites based upon it. For further information, please consult your Oracle representative.

### 5.2.2 Upgrading the Reporter System

The Reporter upgrade procedure described in this section applies to both single server installations as well as dedicated Reporter systems.

Do the following:

1. Login to the Reporter as `root`. Within the `/root` directory, unzip the RUEI zip file, and go to the directory containing the application files. Use the following commands:

```
cd /root
unzip Vxxxx.zip
```

2. Stop all processing on the Reporter and Collector system(s) using the following commands:

```
cd /root/RUEI/extra
chmod +x ruei-upgrade-6.x-6.5.1.sh
./ruei-upgrade-6.x-6.5.1.sh stop_ruei
```

3. Install the new Oracle Instant client by issuing the following commands:

```
cd /root/RUEI/IC
rpm -Uhv oracle-instantclient11.2-*
```

4. Install the new PHP OCI module by issuing the following commands:

```
cd /root/RUEI/PHP
rpm -Uhv php-oci8-11gR2-*
```

5. Update the logical links by issuing the following commands:

```
ln -sf /usr/lib64/oracle/11.2/php-oci8/oci8.ini /etc/php.d/oci8.ini
ln -sf /usr/lib64/oracle/11.2/php-oci8/oci8.so /usr/lib64/php/modules/oci8.so
```

Note the use of the `force (-f)` option.

6. Update the `/etc/ruei.conf` configuration file to use the new Oracle Instant client. Replace the line

```
export INSTANTCLIENT_DIR=/usr/lib/oracle/11.1/client64
```

with the line

```
export INSTANTCLIENT_DIR=/usr/lib/oracle/11.2/client64
```

7. Restart the Apache Web server by issuing the following command:

```
service httpd restart
```

8. On the system where the database resides, update the RUEI database instance by issuing the following commands:

```
cd /root/RUEI/65
cp rui-prepare-db.sh /home/oracle
cp rui-check.sh /home/oracle
chmod +x /home/oracle/rui-*.sh
su - oracle
export ORACLE_HOME=/u01/app/oracle/product/11.1.0/db_1
./rui-prepare-db.sh
exit
```

Upon completion, you should again be the root user.

9. For each required Collector system, perform the steps indicated in the following section. Upon completion, proceed to step 10.
10. Install the new versions of the RPMs using the following commands:

```
cd /root/RUEI/65
chmod +x rui-install.sh
./rui-install.sh *.rpm
```

11. Perform the necessary upgrade actions by executing the following commands:

```
cd /root/RUEI/extra
./rui-upgrade-6.x-6.5.1.sh rpm_post_install
```

12. This step should be performed *only* if you are upgrading from RUEI version 6.0.x. Otherwise, it should be skipped.

**Important:** if you do not perform the action described in this step, the currently defined Error Page Replay (EPR) and Full Session Replay (FSR) settings are applied for *each* monitored application. Depending on the number of monitored applications, and your previous settings, the amount of required disk space can significantly increase. For example, if data retention was set to 50 GB, and five applications are monitored by a Collector, the Collector will reserve up to 50 GB per application upon upgrading to version 6.5 (that is, a total Collector disk space of 250 GB).

If this would require too much disk space to be reserved on a Collector system, you can issue the following command to limit the total reserved disk space to its currently defined settings:

```
./rui-upgrade-6.x-6.5.1.sh resize_replay_store
```

In this case, the total reserved disk space for each application becomes the current setting divided by the current number of applications. For example, if the current data retention setting was 100 GB, and there are currently 10 monitored applications, this would result in 10 GB of disk space being available for each application. Note that, if you choose to use the above command, it may result in the loss of existing (the oldest) replay data.

13. Restart processing using the following commands:

```
cd /root/RUEI/extra
./ruei-upgrade-6.x-6.5.1.sh start_ruei
```

---

---

**Note:** During and after the upgrade procedure, if error or information messages appear in the event log (select **System**, then **Status**, and then **Event log**), you should mark them as read after completing the upgrade procedure, and monitor whether new messages are reported. In the event of re-occurring error messages, you should contact Customer Support.

---

---

### 5.2.3 Upgrading the Remote Collector System(s)

For each required remote Collector system, login as `root`. Within the `/root` directory, unzip the RUEI zip file, go to the directory containing the application files, and install the new versions of the RPMs. Do the following:

1. Unzip the RUEI distribution package using the following commands:

```
cd /root
unzip Vxxxx.zip
```

2. Upgrade the Collector RPMs using the following commands:

```
cd /root/RUEI/65
chmod +x ruei-install.sh
./ruei-install.sh collector
```

3. This step should be performed *only* if you are upgrading from RUEI version 6.0.x. Otherwise, it should be skipped.

Convert the Replay store by issuing the following commands:

```
cd /root/RUEI/extra
chmod +x ruei-upgrade-6.x-6.5.1.sh
./ruei-upgrade-6.x-6.5.1.sh convert_replay_store
```

---

---

**Note:** The script may fail if there is no replay data on the system, or if executed twice.

---

---

## 5.3 Rolling Back to Version 6.5.0

This section describes the procedure to rollback to version 6.5.0 after upgrading to version 6.5.1. Note that the Collector included in the Reporter installation is automatically rolled back during the described procedure. However, remote Collector systems must be individually rolled back. The procedure to do this is described later in this section.

---

---

**Important:** Be aware that it may not be possible to restore your system to its exact state prior to upgrading. It is *strongly* recommended that you contact Customer Support before rolling back an upgrade.

---

---

1. Login to the Reporter system as `root`. Within the `/root` directory, unzip the RUEI 6.5.0 distribution zip file, and go to the directory containing the application files. Use the following commands:

```
cd /root
unzip Vxxx.zip
```

---



---

**Important:** Ensure that the directory where you place the 6.5.0 distribution pack does not conflict with the 6.5.1 release. In addition, if your RUEI installation makes use of accelerator packages (such as Oracle E-Business Suite or Siebel), repeat the unzipping for all previously installed accelerator packages.

---



---

2. Stop all processing on the Reporter system by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-rollback-6.5.1-6.5.0.sh stop_ruei
```

3. Remove all unused accelerator packages. Use the following command to list all installed accelerators:

```
rpm -qa | grep ^ux-suites
```

Use the following command to remove any appropriate accelerator:

```
rpm -e ux-suites-name
```

where *name* is the appropriate accelerator.

4. Execute the RPM pre-installation phase by issuing the following command:

```
./ruei-rollback-6.5.1-6.5.0.sh rpm_pre_install
```

5. Restore the previous RPMs by issuing the following commands:

```
cd /root/RUEI/65
chmod +x ruei-install.sh
./ruei-install.sh *.rpm
```

6. Rollback all required remote Collectors (using the procedure described in the next section). Upon completion, continue to step 5. If your installation does not make use of a remote Collector, proceed directly to step 6.
7. Restore the RUEI configuration backup you created prior to upgrading by selecting **Configuration**, then **System**, then **Maintenance**, then **Backup and restore**, and then select **Restore system from file**.
8. Restart processing by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-rollback-6.5.1-6.5.0.sh start_ruei
```

### Rolling Back Remote Collector Systems

Do the following:

1. Login to the remote Collector system as `root`. Within the `/root` directory, unzip the 6.0 distribution zip file, and go to the directory containing the application files. Issue the following commands:

```
cd /root
unzip Vxxx.zip
```

---



---

**Important:** Ensure that the directory where you place the 6.5.0 distribution pack does not conflict with the 6.5.1 release.

---



---

2. Restore the previous RPMs by issuing the following commands:

```
cd /root/RUEI/extra
chmod +x ruei-rollback-6.5.1-6.5.0.sh
cd /root/RUEI/65
chmod +x ruei-install.sh
./ruei-install.sh ux-collector-*.rpm
```

Upon completion for all required Collectors, return to step 5 above.

## 5.4 Rolling Back to Version 6.0.x

This section describes the procedure to rollback to version 6.0.x after upgrading to version 6.5.1. Note that the Collector included in the Reporter installation is automatically rolled back during the described procedure. However, remote Collector systems must be individually rolled back. The procedure to do this is described later in this section.

---

---

**Important:** Be aware that it may not be possible to restore your system to its exact state prior to upgrading. It is *strongly* recommended that you contact Customer Support before rolling back an upgrade.

---

---

1. Login to the Reporter system as `root`. Within the `/root` directory, unzip the RUEI 6.0.x distribution zip file, and go to the directory containing the application files. Use the following commands:

```
cd /root
unzip Vxxx.zip
```

---

---

**Important:** Ensure that the directory where you place the 6.0.x distribution pack does not conflict with the 6.5.1 release. In addition, if your RUEI installation makes use of accelerator packages (such as Oracle E-Business Suite or Siebel), repeat the unzipping for all previously installed accelerator packages.

---

---

2. Stop all processing on the Reporter system by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-rollback-6.5.1-6.0.x.sh stop_ruei
chmod +x ruei-rollback-6.5.1-6.0.x.sh
./ruei-rollback-6.5.1-6.0.x.sh convert_replay_store
```

3. Remove all unused accelerator packages. Use the following command to list all installed accelerators:

```
rpm -qa | grep ^ux-suites
```

Use the following command to remove any appropriate accelerator:

```
rpm -e ux-suites-name
```

where *name* is the appropriate accelerator.

4. Restore the previous RPMs by issuing the following commands:

```
cd /root/RUEI/60
```

```
rpm -e ux-lang-zh_cn
chmod +x ruei-install.sh
./ruei-install.sh *.rpm
```

5. Rollback all required remote Collectors (using the procedure described in the next section). Upon completion, continue to step 5. If your installation does not make use of a remote Collector, proceed directly to step 5.
6. Restore the RUEI configuration backup you created prior to upgrading by selecting **Configuration**, then **System**, then **Maintenance**, then **Backup and restore**, and then select **Restore system from file**.
7. Restart processing by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-rollback-6.5.1-6.0.x.sh start_ruei
```

### Rolling Back Remote Collector Systems

Do the following:

1. Login to the remote Collector system as `root`. Within the `/root` directory, unzip the 6.0.x distribution zip file, and go to the directory containing the application files. Issue the following commands:

```
cd /root
unzip Vxxx.zip
```

---

**Important:** Ensure that the directory where you place the 6.0.x distribution pack does not conflict with the 6.5.1 release.

---

2. Restore the previous RPMs by issuing the following commands:

```
cd /root/RUEI/extra
chmod +x ruei-rollback-6.5.1-6.0.x.sh
./ruei-rollback-6.5.1-6.0.x.sh convert_replay_store
cd /root/RUEI/60
chmod +x ruei-install.sh
./ruei-install.sh ux-collector-*.rpm
```

Upon completion for all required Collectors, return to step 5 above.

## 5.5 Rolling Back to Version 5.1.x

This section describes the procedure to rollback to version 5.1.x after upgrading to version 6.5.1. Note that the Collector included in the Reporter installation is automatically rolled back during the described procedure. However, remote Collector systems must be individually rolled back. The procedure to do this is described later in this section.

---

**Important:** Be aware that it may not be possible to restore your system to its exact state prior to upgrading. It is *strongly* recommended that you contact Customer Support before rolling back an upgrade.

In addition, you will require a configuration backup of your 5.1.x installation, as well as the 5.1.x and 6.5.1 distribution packages to perform the described rollback procedure.

---

Do the following:

1. Login to the Reporter system as `root`. Within the `/root` directory, unzip the previous 5.1.x distribution package, and go to the directory containing the application files. Issue the following commands:

```
mkdir /root/rollback51
cd /root/rollback51
unzip Vxxx.zip
```

---

---

**Important:** If your RUEI installation makes use of accelerator packages (such as Oracle E-Business Suite or Siebel), repeat the unzipping for all previously installed accelerator packages.

---

---

2. Stop all RUEI processing by issuing the following commands:

```
cd /root/RUEI/extra
chmod +x ./ruei-rollback-6.5.1-5.x.sh
./ruei-rollback-6.5.1-5.x.sh stop_ruei
```

3. Execute the RPM pre-install phase by issuing the following command:

```
./ruei-rollback-6.5.1-5.x.sh rpm_pre_install
```

4. Remove all unused accelerator packages. Use the following command to list all installed accelerators:

```
rpm -qa | grep ^ux-suites
```

Use the following command to remove any appropriate accelerator:

```
rpm -e ux-suites-name
```

where *name* is the appropriate accelerator.

5. Remove the ADF RPM and downgrade existing Reporter RPMs by issuing the following commands:

```
rpm -e ux-adf
cd /root/RUEI/65
./ruei-install.sh /root/rollback51/RUEI/51/*.rpm
```

6. Execute the RPM post-install phase by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-rollback-6.5.1-5.x.sh rpm_post_install
```

7. Re-start the Apache Web server by issuing the following command:

```
service httpd restart
```

At this point, you should rollback all remote Collector systems (using the procedure described below). Proceed to step 7 *after* you have rolled back all remote Collector systems. If your installation does not make use of remote Collector systems, you should proceed directly to step 7.

8. Restart RUEI processing by issuing the following commands:

```
cd /root/RUEI/extra
chmod +x ./ruei-rollback-6.5.1-5.x.sh
./ruei-rollback-6.5.1-5.x.sh start_ruei
```

Be aware that this phase can take a considerable amount of time.

9. Restore the RUEI configuration backup you created prior to upgrading by selecting **Configuration**, then **System**, then **Maintenance**, then **Backup and restore**, and then select **Restore system from file**.

### Troubleshooting Rollback Problems

The rollback script `ruei-rollback-6.5.1-5.x.sh` logs its actions in the file `/tmp/ruei-rollback-6.5.1-5.x.log`. If you encountered any problems during the rollback, please attach this file to any request to Customer Support.

## 5.5.1 Rolling Back Remote Collector Systems

This section describes the procedure to rollback remote Collector systems to version 5.1.x after upgrading to version 6.5.1.

Do the following:

1. Login to the remote Collector system as `root`. Within the `/root` directory, unzip the previous 5.1.x distribution package, and go to the directory containing the application files. Issue the following commands:

```
mkdir /root/rollback51
cd /root/rollback51
unzip Vxxx.zip
```

2. Restore the Collector replay store by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-rollback-6.5.1-5.x.sh convert_replay_store
```

3. Restore the previous Collector RPMs by issuing the following commands:

```
cd /root/RUEI/65
./ruei-install.sh /root/rollback51/RUEI/51/ux-collector-*.rpm
```

Repeat the above procedure for each required remote Collector system. When ready, return to the Reporter rollback procedure.

## 5.6 Rolling Back to Version 5.0.x

This section describes the procedure to rollback to version 5.0.x after upgrading to version 6.5.1. Note that the Collector included in the Reporter installation is automatically rolled back during the described procedure. However, remote Collector systems must be individually rolled back. The procedure to do this is described later in this section.

---



---

**Important:** Be aware that it may not be possible to restore your system to its exact state prior to upgrading. It is *strongly* recommended that you contact Customer Support before rolling back an upgrade.

In addition, you will require a configuration backup of your 5.0.x installation, as well as the 5.0.x and 6.5.1 distribution packages to perform the described rollback procedure.

---



---

Do the following:

1. Login to the Reporter system as `root`. Within the `/root` directory, unzip the previous 5.0.x distribution package, and go to the directory containing the application files. Issue the following commands:

```
mkdir /root/rollback50
cd /root/rollback50
unzip Vxxx.zip
```

---

---

**Important:** If your RUEI installation makes use of accelerator packages (such as Oracle E-Business Suite or Siebel), repeat the unzipping for all previously installed accelerator packages.

---

---

2. Stop all RUEI processing by issuing the following commands:

```
cd /root/RUEI/extra/
chmod +x ./ruei-rollback-6.5.1-5.x.sh
./ruei-rollback-6.5.1-5.x.sh stop_ruei
```

3. Execute the RPM pre-install phase by issuing the following command:

```
/ruei-rollback-6.5.1-5.x.sh rpm_pre_install
```

4. Remove all unused accelerator packages. Use the following command to list all installed accelerators:

```
rpm -qa | grep ^ux-suites
```

Use the following command to remove any appropriate accelerator:

```
rpm -e ux-suites-name
```

where *name* is the appropriate accelerator.

5. Restore the previous RPMs by issuing the following commands:

```
rpm -e ux-wlp
rpm -e ux-adf
cd /root/rollback50/RUEI/50
rpm -Uhv --oldpackage ux-*
```

6. Execute the RPM post-install phase by issuing the following command:

```
cd /root/RUEI/extra/
./ruei-rollback-6.5.1-5.x.sh rpm_post_install
```

At this point, you should rollback all remote Collector systems (using the procedure described in [Section 5.6.1, "Rolling Back Remote Collector Systems"](#)). Proceed to step 7 *after* you have rolled back all remote Collector systems. If your installation does not make use of remote Collector systems, you should proceed directly to step 7.

7. Re-start the Apache Web server by issuing the following command:

```
service httpd restart
```

8. Restart RUEI processing by issuing the following command:

```
./ruei-rollback-6.5.1-5.x.sh start_ruei
```

9. Restore the backup of the `/etc/ruei.conf` file (as the `root` user) you created at the start of the upgrade procedure by issuing the following commands:

```
mv /etc/ruei.conf /etc/ruei.conf.65.backup
cp /etc/ruei.conf.50 /etc/ruei.conf
```

10. Restore the RUEI configuration backup you created prior to upgrading by selecting **Configuration**, then **System**, then **Maintenance**, then **Backup and restore**, and then select **Restore system from file**.

## 5.6.1 Rolling Back Remote Collector Systems

This section describes the procedure to rollback remote Collector systems to version 5.0.x after upgrading to version 6.5.1.

Do the following:

1. Login to the remote Collector system as `root`. Within the `/root` directory, unzip the previous 5.0.x distribution package, and go to the directory containing the application files. Issue the following commands:

```
mkdir /root/rollback50
cd /root/rollback50
unzip Vxxx.zip
```

2. Restore the Collector replay store by issuing the following commands:

```
cd /root/RUEI/extra
./ruei-rollback-6.5.1-5.x.sh stop_collector
./ruei-rollback-6.5.1-5.x.sh convert_replay_store
```

3. Restore the previous Collector RPMs by issuing the following commands:

```
cd /root/RUEI/65
./ruei-install.sh /root/rollback50/RUEI/50/ux-collector-*.rpm
```

Repeat the above procedure for each required remote Collector system. When ready, return to the Reporter rollback procedure.



---

---

## Configuring RUEI

This chapter describes the procedure for initially configuring RUEI. This task is performed by the individual within your organization who has been assigned the role of RUEI Super Administrator (this is, the `admin` user). For more information about roles, see the *Oracle Real User Experience User's Guide*.

### Important

It is *strongly* recommended that a network engineer within your organization validates collected network traffic after configuring RUEI. The procedure to do this is described in [Appendix D, "Verifying Monitored Network Traffic"](#).

## 6.1 Introduction

In order to get RUEI up and running, you will need to have prepared the server systems for RUEI, and installed the RUEI software. This is described in [Chapter 4, "Installing the RUEI Software"](#). After that, you are required to specify the installation type and mail setup (described in [Section 6.2, "Performing Initial RUEI Configuration"](#)), and then perform some post-installation configuration (described in [Section 6.4, "Performing Post-Installation Configuration"](#)). This is necessary in order to start reporting. It includes deciding how pages and users will be identified, and specifying the scope of monitoring in your network environment. Finally, you will need to define the system's initial users, as described in [Section 6.4.6, "Authorizing Initial Users"](#). Note that if you are installing a split-server configuration, you will need to configure each Collector system. This is described in [Section 6.3, "Configuring a Collector System"](#).

---

---

**Caution:** The configuration of RUEI should be discussed with someone with a detailed knowledge of your organization's network topology.

---

---


## 6.2 Performing Initial RUEI Configuration

In order for RUEI to start data monitoring and reporting, it must be configured with some information about your network infrastructure. Once completed, user traffic reporting is available. Note that this initial configuration can be changed later, as necessary. It is only intended to provide RUEI with sufficient information to start real-user monitoring and reporting.

To perform the initial RUEI configuration, do the following:

1. Start the Initial setup wizard by pointing your browser at `https://Reporter/ruei`. The dialog shown in Figure 6–1 appears:

**Figure 6–1 Logon Dialog Box**



Specify the admin user, and the password defined with the `set-admin-password` script (defined in Section 4.5.6, "Installation of the Reporter Software"). When ready, click **Login**. The dialog shown in Figure 6–2 appears.


Note that the first time a user logs on, they receive a warning that the Web server was unable to verify the identify of the site’s certificate. Depending on your security policies, you can either choose to accept this certificate permanently, temporarily for this session, or reject the certificate. Alternatively, you can purchase a certificate from a Certificate Authority (CA). You can also create an SSL certificate. More information at the following location:

[http://httpd.apache.org/docs/2.2/ssl/ssl\\_faq.html#realcert](http://httpd.apache.org/docs/2.2/ssl/ssl_faq.html#realcert)

**Figure 6–2 Initial Setup Wizard Dialog**



2. Click **Next** to proceed with configuration. The dialog shown in Figure 6–3 appears:

**Figure 6–3 Mail Setup Dialog**


**Initial setup wizard**

**Mail setup**

*Specify the mail settings to use for outgoing mail. Verify the information is correct.*

Return address: \* root@example.com  
The address to where delivery problems are reported.

From address: \* root@example.com

Reply-to address: \*

Mail size limit (Kb): \* 5000  
This is the maximum message size; larger messages are split up (if possible).

Reporter URL: \* http://reporter.example.com  
Specify the exact URL required for mail recipients to connect to this system.

<< Back    Next >>    Cancel

3. Specify the requested information. The e-mail information is used to configure RUEI's interface to your internal network, and will be used for reporting problems. When you have entered the required information, click **Next**. The dialog shown in [Figure 6–4](#) appears.

**Figure 6–4 Settings Overview Dialog**


**Initial setup wizard**

**Settings overview**

*These are the installation settings that are about to be applied. Please verify they are correct before clicking Next.*

Return address: support@example.com


Mail size limit (Kb): 5000

From address: support@example.com

Reply-to address: RUEIsupport@example.com

<< Back    Next >>    Cancel

4. Check that the information specified in the settings overview is correct. You can use **Back** and **Next** to move between dialogs as necessary. When ready, click **Next**. The dialog shown in [Figure 6–5](#) appears.


**Figure 6–5 Applying Settings Dialog**

5. This dialog indicates how far the system has got in applying your specified settings. Typically, this process takes a maximum of 15 minutes. When finished, click **Finish** to close the dialog.

## 6.3 Configuring a Collector System

To register a Collector to a Reporter system, do the following:

1. Within the Reporter system, select **System**, then **Maintenance**, and then **Network data collectors**. The Network data collectors window appears.
2. Select **Configuration**, and then **Register remote Collector**. The Register Collector dialog shown in [Figure 6–6](#) appears.

**Figure 6–6 Register Collector Dialog**

3. Enter the IP address of the Collector. Optionally, you can also specify a brief description of the attached Collector. When ready, click **Register**. On return to the Network data collectors window, the new Collector should be listed.

### 6.3.1 Resetting a Collector System

If for any reason you need to register a Collector system with a different Reporter system than earlier configured, do the following:

1. Logon to the Collector system as the `moniforce` user, and remove the Collector's currently defined Reporter assignment by issuing the following commands:

```
su - moniforce
appsensor delete wg
```

2. Follow the procedure described in [Section 6.3, "Configuring a Collector System"](#) to register the Collector with the required Reporter.

## 6.4 Performing Post-Installation Configuration

In order to start reporting, the RUEI needs certain information about the monitored network environment. It is important to understand that RUEI is designed to work within a wide range of network environments. Therefore, the configuration choices you make will affect the accuracy and usability of the reported data. It is strongly recommended that you carefully review the settings described in this section.

### 6.4.1 Specifying the Cookie Technology

Within RUEI, session information is based on cookies. Therefore, RUEI needs to know and understand the cookie technology (or technologies) your organization is using. The procedure to configure this is described in the *Oracle Real User Experience Insight User's Guide*. The structure of supported cookie technologies is also explained in the *Oracle Real User Experience Insight User's Guide*.

If cookie information is not available, user tracking is based on visitor IP address. This can lead to unreliable session information. For example, in the case of users behind a proxy server, all users coming from that network would be identified as the same user.

### 6.4.2 Adding/Uploading HTTPS SSL Keys

Uploading SSL keys to the system is extremely important if most of your HTTP traffic is based on SSL sessions. Without the SSL keys being available to the system, the Collector will not be able to decrypt the SSL session traffic. In these circumstances, further configuration of cookies, user identification, and application pages would make little sense. Ensure that you upload and activate your HTTPS SSL keys as early on as possible in the configuration process. The management of SSL keys is fully described in the *Oracle Real User Experience Insight User's Guide*.

### 6.4.3 Specifying How Users are Identified

Within RUEI, user identification is first based on the HTTP Authorization field. After that, it is derived from the supplied GET/POST argument within URLs. Therefore, if you are using arguments within URLs, the item within these used for user identification must be specified in order to provide reliable results. This is fully described in the *Oracle Real User Experience Insight User's Guide*.

### 6.4.4 Naming Pages

Page identification within RUEI is based on applications. Essentially, an application is a collection of Web pages. This is because pages on a Web site are typically bound to a particular application. For each page that the system detects, it uses the available application definitions to assign a name to it. Note that information about any pages that could not be identified using these definitions is discarded, and, therefore, not available through reports and the data browser. This is fully described in the *Oracle Real User Experience User's Guide*.

## 6.4.5 Specifying the Scope of Monitoring

Within RUEI, you control the scope of traffic monitoring by specifying which TCP ports the SYSTEM should monitor. Obviously, no information is available for non-monitored ports. In addition, you can restrict monitoring to specific servers and subnets. This is fully described in the *Oracle Real User Experience Insight User's Guide*.

## 6.4.6 Authorizing Initial Users

In order for users to start working with RUEI, you will need to authorize the required users. Only one user, `admin`, is available after installation. The procedure to set the initial `admin` user password is described in [Section 4.5.6, "Installation of the Reporter Software"](#). All other required users must be created and assigned the necessary roles and access permissions through the Reporter GUI. In particular, it is recommended that you create a dedicated Security Officer account to finalize the security-related configuration. User roles, creation and management are fully described in the *Oracle Real User Experience Insight User's Guide*.

Note that user names and passwords are case sensitive. For ease of entry, it is recommended that you do not include any diacritic characters, such as umlauts, within passwords.

## 6.5 Verifying and Evaluating Your Configuration

To ensure the quality and quantity of data being collected and analyzed by your RUEI system, it is strongly advised that you verify the system's configuration using some core metrics. These are described in the following sections.

### 6.5.1 Viewing a Traffic Summary

You can open an overview of the monitored network traffic by selecting **System**, then **Status**, and then **Data processing**. This provides you with immediate information about hits, pages, and session processing, as well as the system load. An example is shown in [Figure 6-7](#):

Figure 6–7 Data Processing Dialog



The precise number of percentage of identified sessions, page views, and hits relies heavily on your exact configuration. If you intend to measure all traffic, it is recommended that at least 80% of sessions, page views, and hits are reported as "identified". It is also recommended that you regularly review the reported numbers and percentages to ensure the quality and quantity of reported data.

---

**Important:** After initial configuration of cookies, user identification, and application page structure, the system will take at least 5 - 10 minutes before the **Sessions/Hits/Page views** tabs are updated with green bars. If, after 20 - 30 minutes after initial configuration, there are no green bars showing on any of the tabs, please review your initial RUEI configuration. If the bars do not indicate any activity at all, please review your system's network card configuration as outlined in [Section 1.7, "Network Requirements"](#)

---

## 6.5.2 Confirming Data Collection

At this point, RUEI should be collecting data from each of its associated Collectors. You can easily check the status of these Collectors by selecting **System**, then **Status**, and then **Collector status**. This opens the Network data collectors window. This is fully described in the *Oracle Real User Experience Insight User's Guide*.

It is important to understand that the data being collected by Collector system(s) is offered to the RUEI data processing module for further analysis. If no data is collected, there is no means by which it can be processed.



---

---

# Installing and Configuring SSO Authentication Integration

This chapter describes the procedure for installing and configuring the Oracle HTTP server. This is an optional part of the RUEI installation process, and is only required if you intend to use the Oracle Single Sign-On (SSO) service to authenticate RUEI users. Note that the Oracle SSO service must be fully installed and configured before it can be used for RUEI user authentication.

The procedure to configure the Reporter system for Oracle SSO user authentication is described in the *Oracle Real User Experience Insight User's Guide*. Note that RUEI must be fully installed before it can be configured for Oracle SSO user authentication.

## 7.1 Turning off the Default Web Server

The Oracle SSO server uses its own Web server in order to prevent conflicts with the currently installed Web server. Therefore, the currently installed Web server needs to be turned off by issuing the following commands:

```
/sbin/service httpd stop
/sbin/chkconfig --del httpd
```

---

---

**Note:** It is recommended that you do *not* un-install the default Linux Apache Web server because this would also un-install the PHP module.

---

---

## 7.2 Reporter System Without Local Database

The procedure described in this section should only be followed if you are installing and configuring the oracle HTTP server for a Reporter that does not a local database. Otherwise, the procedure described in [Section 7.3, "Reporter System With Local Database"](#) should be followed.

### 7.2.1 Creating the Oracle User

This section is only relevant for RUEI installations configured to use a remote database. In this case, the `oracle` user does not yet exist, and so must be created by issuing the following commands:

```
/usr/sbin/groupadd oinstall oinstall
/usr/sbin/useradd -g oinstall oracle
```

## 7.2.2 Setting up the Oracle HTTP Server Environment

This section is only relevant for RUEI installations configured to a remote database. In this case, the following lines need to be added to the `/etc/security/limits.conf` file:

```
oracle soft nofile 16384
oracle hard nofile 65536
```

## 7.2.3 Creating the Installation Directory

Issue the following commands:

```
mkdir -p /u01/app/oracle
chown -R oracle:oinstall /u01/app/oracle
```

## 7.3 Reporter System With Local Database

The procedure described in this section should only be followed if you are installing and configuring the Oracle HTTP server for a Reporter that with a local database. Otherwise, the procedure described in [Section 7.2, "Reporter System Without Local Database"](#) should be followed.

Increase the number of open files limit. Edit the following line in the `/etc/security/limits.conf` file:

```
oracle soft nofile 16384
```


## 7.4 Installing Oracle HTTP Server

Do the following:

1. Login to the Reporter server as the `oracle` user, and unzip the Oracle HTTP Server zip file. Ensure that you have your display environment setup correctly (reference or copy a piece about setting up the X server in other part of the install manual). The installation of Oracle HTTP server needs to be performed as the `oracle` user (only some parts in this chapter require `root` privileges).

```
unzip ofm_webtier_11.1.1.1.0_64_disk1_10f1.zip
cd webtier/Disk1
export ORACLE_BASE=/u01/app/oracle
./runInstaller
```

2. As the installation script runs, you should accept all default values, except for step 5. Here, you must uncheck the two check boxes **Oracle Web Cache** and **Associate selected components with weblogic domain** shown in [Figure 7-1](#).

**Figure 7-1 Configure Components Dialog**

3. After exiting the installation script, set the following environment variables:

```
export ORACLE_HOME=$ORACLE_BASE/product/11.1.1/as_1
export ORACLE_INSTANCE=$ORACLE_HOME/instances/instance1
```

4. Stop the Oracle HTTP server and Oracle Process Manager Notification (OPMN) using the following command:

```
$ORACLE_INSTANCE/bin/opmnctl stopall
```

5. Edit the `$ORACLE_HOME/ohs/bin/apachectl` file to fix the bug 8327898. Change the `prefork` as follows:

```
case ${MPM} in
    async ) _httpd="httpd.async" ;;
    prefork ) _httpd="httpd.prefork" ;;
    * ) _httpd="httpd.worker" ;;
esac
```

Note more information about this bug is available at <https://support.oracle.com/CSP/ui/flash.html>.

6. Edit the `$ORACLE_INSTANCE/config/OPMN/opmn/opmn.xml` file to use the `httpd.prefork` in order so that the PHP module can be loaded. In addition, set the following variables from the `/etc/ruei.conf` configuration file:

```
<environment>
  <variable id="TEMP" value="/tmp"/>
  <variable id="TMP" value="/tmp"/>
  <variable id="OHSMPM" value="prefork"/>
  <variable id="TNS_ADMIN" value="/var/opt/ruei"/>
  <variable id="RUEI_DB_TNSNAME" value="uxinsight"/>
  <variable id="RUEI_DB_USER" value="uxinsight"/>
  <variable id="RUEI_HOME" value="/opt/ruei"/>
```

```

    <variable id="RUEI_DATA" value="/var/opt/ruei"/>
    <variable id="JAVA_HOME" value="/usr/java/jre">
</environment>

```

7. Logon as the `root` user, and change the permissions for the `.apachectl` file so that the Oracle HTTP server can run as the Apache user. Issue the following commands:

```

chown root $ORACLE_HOME/ohs/bin/.apachectl
chmod 6750 $ORACLE_HOME/ohs/bin/.apachectl

```

8. Add `apache` to the `oinstall` group using the following command:

```

usermod -aG oinstall apache

```

9. Logon as the `oracle` user and edit the `$ORACLE_INSTANCE/config/OHS/ohs1/httpd.conf` file for the Oracle HTTP server to run as the Apache user. Edit the following lines:

```

User apache
Group apache

```

10. Create the `$ORACLE_INSTANCE/config/OHS/ohs1/moduleconf/php5.conf` file, and edit it to contain the following:

```

LoadModule php5_module "/usr/lib64/httpd/modules/libphp5.so"
AddHandler php5-script php
AddType    text/html    php

```

11. Copy the `/etc/httpd/conf.d/uxinsight.conf` file and make it available to the Oracle HTTP server using the following command:

```

cp /etc/httpd/conf.d/uxinsight.conf $ORACLE_INSTANCE/config/OHS/ohs1/moduleconf

```

12. Start Oracle Process Manager Notification (OPMN) and the Oracle HTTP server using the following command:

```

oracle$ $ORACLE_INSTANCE/bin/opmnctl startall

```

13. Stop the HTTP server using the following command:

```

$ORACLE_INSTANCE/bin/opmnctl stopproc ias-component=ohs1

```

14. In order to have RUEI running on the default HTTPS port, edit the `$ORACLE_INSTANCE/config/OHS/ohs1/ssl.conf` file, and change the line with the `Listen` directive to the following:

```

Listen 443

```

In addition, edit the `VirtualHost` definition as follows:

```

<VirtualHost *:443>

```

15. Start the Oracle HTTP server using the following command:

```

$ORACLE_INSTANCE/bin/opmnctl startproc ias-component=ohs1

```

16. Stop the Oracle HTTP server using the following command:

```

oracle$ $ORACLE_INSTANCE/bin/opmnctl stopproc ias-component=ohs1

```

17. Create the `$ORACLE_INSTANCE/config/OHS/ohs1/moduleconf/mod_osso.conf` file:

```
LoadModule osso_module "${ORACLE_HOME}/ohs/modules/mod_osso.so"

<IfModule osso_module>
    OssoConfigFile /u01/app/oracle/product/11.1.1/as_
1/instances/instance1/config/OHS/ohs1/osso.conf
    OssoIpCheck off
    OssoIdleTimeout off
</IfModule>
```

**18.** Copy the `osso.conf` file that you received after registering RUEI with the Oracle SSO server to the `$ORACLE_INSTANCE/config/OHS/ohs1` directory.

**19.** Start the Oracle HTTP server using the following command:

```
$ORACLE_INSTANCE/bin/opmnctl startproc ias-component=ohs1
```

## 7.5 Verifying the Oracle HTTP Server Configuration

You can test the Oracle HTTP server for integration with RUEI by directing your browser to `https://Reporter/ruei`. When you select **System**, then **User management**, the **Configure SSO connection** option should be enabled.

For information about enabling Oracle SSO user authentication within RUEI, see the *Oracle Real User Experience User's Guide*.



---

# Configuring the Oracle Access Manager (OAM)

This chapter describes the procedure for configuring the Oracle Access Manager (OAM) for identifying user IDs within OAM-based traffic. The procedure described assumes that you already have a working OAM server. Note that the procedure may need to be modified to reflect the specific configuration of your OAM server.


Be aware that RUEI only supports the monitoring of OAM version 10.1.4.x (or higher), and that the load placed on the OAM infrastructure by RUEI is the equivalent of the monitored Web server.

## 8.1 Creating an OAM Access Gate for RUEI

Do the following:


1. Direct your Web browser to The Access Manager server interface. If you are unsure of the required URL, you should contact the OAM system administrator. The page shown in [Figure 8–1](#) appears.

**Figure 8–1** OAM Server Interface.




2. Click the **Access System Console** link. The page shown in [Figure 8–2](#) appears.

**Figure 8–2 OAM Access Administration.**



3. Click the **Access System Configuration** tab. The page shown in [Figure 8–3](#) appears.

**Figure 8–3 OAM Access System Configuration Page.**



- Click the **Add New Access Gate** option on the left-hand side of the page. The page shown in appears.

**Figure 8–4 Add New Access Gate Page**

### Add New Access Gate

AccessGate Name	<input type="text" value="ruei"/>	
Description	<input type="text"/>	
Hostname	<input type="text"/>	
Port	<input type="text"/>	
Access Gate Password	<input type="password"/>	
Re-type Access Gate Password	<input type="password"/>	
Debug	<input checked="" type="radio"/> Off <input type="radio"/> On	
Maximum user session time (seconds)	<input type="text" value="3600"/>	
Idle Session Time (seconds)	<input type="text" value="3600"/>	
Maximum Connections	<input type="text" value="1"/>	
Transport Security	<input checked="" type="radio"/> Open <input type="radio"/> Simple <input type="radio"/> Cert	
IPValidation	<input type="radio"/> Off <input checked="" type="radio"/> On	
IPValidationException	<input type="text"/>	- +
Maximum Client Session Time (hours)	<input type="text" value="24"/>	
Failover threshold	<input type="text"/>	
Access server timeout threshold	<input type="text"/>	
Sleep For (seconds)	<input type="text" value="60"/>	
Maximum elements in cache	<input type="text" value="100000"/>	
Cache timeout (seconds)	<input type="text" value="1800"/>	
Impersonation username	<input type="text"/>	
Impersonation password	<input type="password"/>	
Re-type impersonation password	<input type="password"/>	
<b>ASDK Client</b>		
Access Management Service	<input checked="" type="radio"/> Off <input type="radio"/> On	
<b>Web Server Client</b>		
Primary HTTP Cookie Domain	<input type="text"/>	
Preferred HTTP Host	<input type="text"/>	
Deny On Not Protected	<input checked="" type="radio"/> Off <input type="radio"/> On	
CachePragnaHeader	<input type="text" value="no-cache"/>	
CacheControlHeader	<input type="text" value="no-cache"/>	
LogOutURLs	<input type="text"/>	- +
<b>User Defined Parameters</b>		
Parameters	Values	
<input type="text"/>	<input type="text"/>	- +
		Add Delete
Save Cancel		

- Provide the following information:
  - **Access Gate Name:** specify a unique ID for the new access gate. For example, ruei.
  - **Hostname:** specify the hostname of the RUEI reporter system.

- **Port:** specify the port RUEI should monitor for OAM-based traffic. This should be port 443.
- **Access Gate Password:** specify the password that should be used to authorize the RUEI Reporter system to access the OAM server.
- **Re-Type Access Gate Password:** confirm the authorization password.
- **Preferred HTTP Host:** specify `SERVER_NAME`.

Note that the remaining fields can left blank or with default values specified.

When ready, click **Save**.

6. Click the **List Access Servers** command button to connect the newly created access gate with the required access server. Select the required access server from the displayed list and, when ready, click **Add**.

Note that if no access server is listed, Click **Add** and add the new access gate to the default access server.

## 8.2 Downloading and Installing the Access Gate Software

Do the following:

1. Download "Disk 1" of the GCC Libraries for the Linux platform from [http://www.oracle.com/technology/software/products/middleware/htdocs/fmw\\_11\\_download.html](http://www.oracle.com/technology/software/products/middleware/htdocs/fmw_11_download.html).

Note that you must click the **Accept** radio button at the top of the page to indicate acceptance of the OTN license agreement before you can download the software.

2. Download the 64-bit OAM Access Server SDK from [http://download.oracle.com/otn/linux/ias/101401/oam\\_int\\_linux\\_v7\\_cd3.zip](http://download.oracle.com/otn/linux/ias/101401/oam_int_linux_v7_cd3.zip).
3. Extract, unzip, and copy the GCC libraries using the following commands:

```
cat as_linux_x86_gcc_runtime_lib_access_manager_101401.cpio | cpio -idmv
unzip Oracle_Access_Manager10_1_4_0_1_linux_GCClib.zip
cp lib* /usr/local/lib/
```

## 8.3 Configuring the Access Gate Software on the RUEI Server

Do the following:

1. Unzip the OAM Access Server SDK distribution set, and run the installer, by issuing the following commands:

```
unzip oam_int_linux_v7_cd3.zip
./Oracle_Access_Manager10_1_4_2_5_linux64_AccessServerSDK
```

By default, the OAM Access Server SDK is installed in `/opt/netpoint/AccessServerSDK/`.

---



---

**Note:** The user specified while running the Access Gate SDK installation wizard should be the same as that specified for RUEI\_USER in the `ruei.conf` file (see [Table 4-1](#)).

---



---

2. Create a trust between RUEI and the access server by creating XML files using the `configureAccessGate` utility. Issue the following commands:

```
cd /opt/netpoint/AccessServerSDK/oblix/tools/configureAccessGate
./configureAccessGate -i /opt/netpoint/AccessServerSDK/ -t AccessGate
```

3. As the utility runs, specify the following information based on the configuration of the access gate you created earlier:

```
Please enter the Mode in which you want the AccessGate to run : 1(Open)
2(Simple) 3(Cert) : 1
```

```
Please enter the AccessGate ID : short_name
```

```
Please enter the Password for this AccessGate :
```

```
Please enter the Access Server ID : accessSrv1
```

```
Please enter the Access Server Host Machine Name : fully_qualified_hostname
```

```
Please enter the Access Server Port : 6021
```

```
Preparing to connect to Access Server. Please wait.
```

```
AccessGate installed Successfully.
```

```
Press enter key to continue ...
```

Where *short\_name* specifies the Access Gate ID, and *fully\_qualified\_hostname* is the Access server system host name.

4. At this point, the RUEI Reporter system is connected to the OAM access server. Update the `OBACCESS_INSTALL_DIR` variable in the `/etc/ruei.conf` configuration file to reflect the installation path of the Access Server SDK. In the case of the default installation path, the required line would be as follows:

```
export OBACCESS_INSTALL_DIR=/opt/netpoint/AccessServerSDK/
```

5. Re-start RUEI processing by selecting **System**, then **Maintenance**, then **System reset**, and select the **Restart system processing** option. When ready, click **Next**. When prompted, confirm the restart.

## 8.4 Configuring the Required Session Traffic Definitions

In order to enable correct tracking of OAM-based sessions, you need to specify the following configuration information within RUEI:

1. Configure all required applications for user identification based on OAM. To do so, click the **User ID** tab within each required application overview, and then click the « **Add new source** » item. Within the **Source type** menu, select the "Oracle Access Manager" option. When ready, click **Save**.
2. Select **Configuration**, then **Applications**, and then **Session tracking**. Ensure that the "Oracle Access Manager" is included in the list of cookie technologies configured for your RUEI installation. By default, this uses the cookie name "ObSSOcookie".

---

---

**Note:** In order for OAM-based traffic to be correctly reported, the masking of the OAM cookie must be configured as "Plain" within the Cookie masking facility (Select **Configuration**, then **Security**, then **Masking**, and then **Cookie masking**).

---

---

Note that until an OAM request has been processed by the RUEI system access gate, the following message is shown when requesting the access servers listing for your access gate:

```
Not Responding  
AM service status mismatch
```



---

---

## Generic Database Instance Setup

This appendix describes how you can setup an Oracle database instance for use by the RUEI Reporter that is running on a platform other than Oracle Linux 5.x or RedHat Enterprise Linux 5.x. RUEI supports Oracle database version 11gR1 and 11gR2.

Note that the approach taken in this appendix is to describe the requirements for a generic database instance, rather than a detailed procedural description. Therefore, a sound working knowledge of Oracle database administration is required.

### Platform Support

While a wide range of platforms are supported for deployment of a remote database, high performance single-threaded platforms designed for large queries by comparatively few users offer the best deployment solutions.

## A.1 Overview

Upon completion, the following parameters and settings should be specified for the new Oracle database instance:

- RUEI\_DB\_INST: the name of the new database instance (as specified in the `/etc/ruei.conf` file). See [Section 4.3.1, "The RUEI Configuration File"](#).
- The instance should be based on the `Data_Warehouse.dbc` template.
- The character set of the instance should be set to `AL32UTF8`.
- The `recyclebin` and `audit_trail` features should be disabled for performance reasons.
- Monitor the `redoLog` file size, and adjust the size if necessary.

Each of these requirements is discussed in more detail in the following sections.

## A.2 Creating the Database Instance

The following discussion assumes that the Oracle database instance is created on the command line. However, you are free to use any suitable utility to specify the required parameters. They should be consistent with the following:

```
dbca -silent -createDatabase -gdbName RUEI_DB_INST -sid RUEI_DB_INST \  
-characterSet AL32UTF8 -templateName Data_Warehouse.dbc -databaseType DATA_WAREHOUSING \  
-redoLogFileSize 500 -initParams recyclebin=off -initParams audit_trail=none
```

## A.3 Using Compressed Tablespaces

For performance reasons, it is *strongly* recommended that you use compressed tablespaces. The following command line instruction can be used to enable compression on the USERS tablespace:

```
alter tablespace USERS default compress;
```

The size of the required database instance is 200 GB (or larger). The required disk space depends on the specified Reporter data retention policy (select **Configuration**, then **General**, then **Advanced settings**, and then **Reporter Data Retention Policy**).

For most RUEI deployments, you will require more than a single datafile in the USERS tablespace. Note that the default datafiles location is used, and you may want to specify a different location for the datafiles. Use the following command to add additional datafiles:

```
alter tablespace USERS add datafile 'user02.dbf' size 5M autoextend on;
```

## A.4 Creating Additional Tablespaces

In addition to the USERS tablespace, three additional tablespaces must be created for the RUEI Reporter system:

- UXCONF: contains RUEI configuration information. Typically, less than 1 GB in size.
- UXSTAT: contains RUEI statistics information used for internal purposes. Typically, only a few GB in size.
- UXTEMP: contains RUEI temporary tables. Typically, several GB in size.

Note that the names of these three tablespaces are fixed and not configurable. The required tablespaces can be created using the following commands:

```
create tablespace UXCONF datafile 'uxconf01.dbf' size 5M reuse autoextend on default compress;  
create tablespace UXSTAT datafile 'uxstat01.dbf' size 5M reuse autoextend on default compress;  
create tablespace UXTEMP datafile 'uxtemp01.dbf' size 5M reuse autoextend on default compress;
```

## A.5 DRCP Connection Pooling

For performance reasons, it is *strongly* recommended that you use a shared pool for all connection to the database. The following is an example of how to activate a shared pool for the database:

```
exec dbms_connection_pool.start_pool;  
exec dbms_connection_pool.configure_pool(inactivity_timeout=>3600, max_think_time=>3600);
```

## A.6 Rescheduling Oracle Database Maintenance

By default, Oracle database maintenance tasks are schedule to run at 22:00. These can have a significant impact on the overall database performance. Therefore, depending on traffic levels on the monitored environment, you may need to reschedule these maintenance tasks to a period with low traffic/load levels (for example, 03:00). For information on how to reschedule planned maintenance tasks, refer to the *Oracle Database Administrator's Guide* available at the following location:

[http://download.oracle.com/docs/cd/B28359\\_01/server.111/b28310/memory003.htm#ADMIN11200](http://download.oracle.com/docs/cd/B28359_01/server.111/b28310/memory003.htm#ADMIN11200)

## A.7 Creating the RUEI Database User

This section explains the creation of the RUEI database user, and permissions it must be assigned.

The RUEI database user is specified in the `RUEI_DB_USER` setting (in the `/etc/ruei.conf` file). It receives the minimum required permissions. However, note that the `dbms_crypto` permission is required for encryption of the SSL private keys that a Collector is using. In addition, because RUEI typically operates in an unattended 7x24 environment, the `PASSWORD_LIFE_TIME` permission should be set to unlimited.

The following examples show how the RUEI database user can be created with the minimum required permissions.

```
create user RUEI_DB_USER
  identified by PASSWORD
  default tablespace USERS
  temporary tablespace TEMP
  profile DEFAULT
  quota 200G on USERS;

alter user RUEI_DB_USER
  quota unlimited on UXCONF
  quota unlimited on UXSTAT
  quota unlimited on UXTEMP;

alter profile DEFAULT
  limit PASSWORD_LIFE_TIME unlimited;

grant
  create session,
  create sequence,
  create table,
  create trigger
  to RUEI_DB_USER;

grant execute on dbms_crypto to RUEI_DB_USER;
```

## A.8 Setting up the Connection Data

After the Oracle database instance has been defined, the connection data needs to be set up. This requires two files, `sqlnet.ora` and `tnsnames.ora`, in the RUEI home directory (`RUEI_DATA`).

The following is an example of the contents of the `sqlnet.ora` file:

```
NAMES.DIRECTORY_PATH = (TNSNAMES)
SQLNET.WALLET_OVERRIDE = TRUE
WALLET_LOCATION = (SOURCE=(METHOD=FILE) (METHOD_DATA=(DIRECTORY=/var/opt/ruei)))
DIAG_SIGHANDLER_ENABLED = FALSE
```

Ensure that the `DIRECTORY` setting points to the directory for RUEI data files (`RUEI_DATA`) specified in the `/etc/ruei.conf` file.

The following is an example of the contents of the `tnsnames.ora` file:

```
uxinsight=(DESCRIPTION=
  (ADDRESS_LIST=(ADDRESS=(PROTOCOL=TCP) (HOST=localhost.localdomain) (PORT=1521)))
  (CONNECT_DATA=(SERVICE_NAME=ruei) (SERVER=POOLED)))
```

In the example above, `uxinsight` is the database alias (`RUEI_DB_TNSNAME`) specified in the `/etc/ruei.conf` file. Ensure that the `HOST` setting specifies your

database. If you specify a host name, ensure that it is also specified in the `/etc/hosts` setup. However, you can also specify an IP address.

## A.9 Setting up the Oracle Wallet

The processing part of RUEI requires non-interactive access to the Oracle database. In order to achieve this, the Oracle `autologin` wallet is used to store passwords securely.

Use the following command to create the Oracle wallet on the database system:

```
mkstore -wrl /dev/shm -create
```

Note that you are prompted for the wallet password.

After the (empty) wallet has been created, you must add the credentials of `RUEI_DB_TNSNAME` and `RUEI_DB_USER` to the Oracle wallet using the following command:

```
mkstore -wrl /dev/shm -createCredential RUEI_DB_TNSNAME RUEI_DB_USER
```

Two wallet files, `ewallet.p12` and `cwallet.sso`, must be moved to the `RUEI_DATA` directory on the Reporter system. Both files should have the ownership of `RUEI_USER` and `RUEI_GROUP`. Note that `ewallet.p12` only needs to be readable by `RUEI_USER`, while `cwallet.sso` needs to be readable by both `RUEI_USER` and `RUEI_GROUP`. On Linux, this can be accomplished by issuing the following commands:

```
chown RUEI_USER:RUEI_GROUP *wallet*
chmod 600 ewallet.p12
chmod 640 cwallet.sso
```

If the Oracle database instance has been set up correctly, it should now be possible to enter the database without being prompted for the password. The `RUEI_USER` on the Reporter system can access the database instance as follows:

```
sqlplus /@RUEI_DB_TNSNAME
```

If this last step fails, you should carefully review the information in this appendix before proceeding with your RUEI deployment.

## The ruei-check.sh Script

This appendix provides a detailed explanation of the checks performed by the `ruei-check.sh` script. It is *strongly* recommended that you use this script to verify successful installation, and to troubleshoot any installation issues.

When started, the script prompts you to specify which role or roles the system is required to perform. For example:

- 1 - Reporter + Collector + Database
- 2 - Reporter + Collector
- 3 - Reporter + Database
- 4 - Collector only
- 5 - Reporter only
- 6 - Database only

Please specify which role(s) this system should perform: `x`

In the above example, the script will check the system to verify that it meets the requirements for both a Reporter and Collector installation with a local database.

The checks performed in the order shown in [Table B-1](#), and are divided into three types: pre-installation, system, and post-installation checks. Whether a specific check is performed depends on the selected role(s).

**Table B-1** *ruei-check.sh* Checks.

Check	Role						Description
	1	2	3	4	5	6	
<b>System checks</b>							
Architecture	.	.	.	.	.	.	Must be x86_64.
Operating system	.	.	.	.	.	.	Must be Oracle/RedHat Linux 5.x.
Memory	.	.	.	.	.	.	Must be at least 4 GB. Recommended 16 GB for Reporter installation. Recommended 8 GB for a Collector only or remote database installation.
Swap space	.	.	.	.	.	.	Must be at least 3/4 of the installed system memory <sup>1</sup> .
Disk space for \$RUEI_HOME	.	.	.	.	.	.	The disk space for the specified \$RUEI_HOME location must be at least 512 MB.
Disk space for \$RUEI_DATA	.	.	.	.	.	.	The disk space for the specified \$RUEI_DATA location must be at least 100 GB.
Disk containing \$RUEI_DATA	.	.	.	.	.	.	The specified \$RUEI_DATA location must be local. Remote file systems (such as NFS) are not supported.

**Table B-1 (Cont.) ruei-check.sh Checks.**

Check	Role						Description
	1	2	3	4	5	6	
Disk speed on \$RUEI_DATA	.	.	.	.	.	.	The disk speed of the specified \$RUEI_DATA location must be at least 40 MB/s (120 MB/s or more is recommended).
SELinux	.	.	.	.	.	.	SELinux must be disabled.
Network interfaces	.	.	.	.	.	.	Must have at least one interface must be Up without an IP address (as described in <a href="#">Section 2.5, "Network Configuration"</a> ).
Hostname	.	.	.	.	.	.	The system's configured IP address and hostname must be specified in the <code>/etc/hosts</code> file.
DNS	.	.	.	.	.	.	The configured DNS server must resolve the system's configured hostname to its IP address.
HTTPD autostart	.	.	.	.	.	.	Must be configured to start automatically.
HTTPD up	.	.	.	.	.	.	Must be up.
Database autostart	.	.	.	.	.	.	Must be configured to start automatically.
SSHD autostart	.	.	.	.	.	.	Must be configured to start automatically.
SSHD up	.	.	.	.	.	.	Must be up.
SSHD	.	.	.	.	.	.	Attempts to check if the SSH is not firewalled.
NTPD autostart	.	.	.	.	.	.	Must be configured to start automatically.
NTPD up	.	.	.	.	.	.	Must be up.
NTPD	.	.	.	.	.	.	Must be synchronized with a time server.
PHP CLI	.	.	.	.	.	.	PHP must be available on the command line.
PHP settings	.	.	.	.	.	.	<code>session.gc_maxlifetime</code> must be set to 14400. <code>memory_limit</code> must be set to 96M. <code>post_max_size</code> must be set to 128M. <code>upload_max_filesize</code> must be set to 128M. Zend Optimizer must be available. (These appear as individual checks, and are only performed if the above check is passed).
PHP timezone	.	.	.	.	.	.	PHP must return the same timezone as the Reporter operating system. See <a href="#">Section E.15, "ruei-check.sh Script Reports PHP Timezone Error"</a> for additional information.
RSVG	.	.	.	.	.	.	The <code>~apache/.gnome2</code> directory must exist.
<b>Pre-install checks</b>							
Disk space for database data directory	.	.	.	.	.	.	Must be 300 GB. (If on the same partition as \$RUEI_DATA, must be 400 GB).
Disk containing database data directory	.	.	.	.	.	.	Must be local. (Remote file systems, such as NFS, are not supported).
Disk speed of database data directory	.	.	.	.	.	.	Must be at least 40 MB/s (120 MB/s is recommended).
\$RUEI_USER user exists	.	.	.	.	.	.	The specified \$RUEI_USER user must exist.
apache user exists	.	.	.	.	.	.	User <code>apache</code> must exist.

**Table B-1 (Cont.) ruei-check.sh Checks.**

Check	Role						Description
	1	2	3	4	5	6	
User apache in group \$RUEI_GROUP	.	.	.	.	.	.	User apache must be a member of the specified group \$RUEI_GROUP.
User apache in group uucp	.	.	.	.	.	.	User apache must be a member of the group uucp.
User \$RUEI_USER in group uucp	.	.	.	.	.	.	The specified \$RUEI_USER user must be in group uucp.
User root must have umask of 0022	.	.	.	.	.	.	User root must have the umask 0022.
User root can write to /etc/http/conf.d	.	.	.	.	.	.	User root must be able to write to the /etc/http/conf.d directory.
User root can write to /etc/init.d	.	.	.	.	.	.	User root must be able to write to the /etc/init.d directory.
User root can write to /etc/ld.so.conf.d	.	.	.	.	.	.	User root must be able to write to the /etc/ld.so.conf.d directory.
User root can write to \$RUEI_HOME	.	.	.	.	.	.	User root must be able to write to the specified \$RUEI_HOME directory.
User root can write to \$RUEI_DATA	.	.	.	.	.	.	User root must be able to write to the specified \$RUEI_DATA directory.
User root can write to /tmp	.	.	.	.	.	.	User root must be able to write to the /tmp directory.
/etc/sysconfig/httpd must call /etc/ruei.conf	.	.	.	.	.	.	The /etc/sysconfig/httpd script must call the /etc/ruei.conf configuration file.
\$RUEI_USER user able to contact database	.	.	.	.	.	.	The specified \$RUEI_USER user must be able to connect to the database.
oci8 PHP extension available	.	.	.	.	.	.	The oci8 PHP extension must be available.
\$RUEI_USER user able to contact database via PHP	.	.	.	.	.	.	The specified \$RUEI_USER user must be able to connect to the database via PHP.
\$RUEI_USER user must have umask 0027	.	.	.	.	.	.	The specified \$RUEI_USER user must have a umask of 0027.
\$RUEI_USER user able to read \$RUEI_HOME	.	.	.	.	.	.	The specified \$RUEI_USER user must be able to read the specified \$RUEI_HOME directory.
\$RUEI_USER user able to write to \$RUEI_DATA	.	.	.	.	.	.	The specified \$RUEI_USER user must be able to read the specified \$RUEI_DATA directory.
/etc/ruei.conf syntactically correct	.	.	.	.	.	.	The /etc/ruei.conf configuration file must be a syntactically correct shell script.
User root able to contact database after loading ruei.conf	.	.	.	.	.	.	The root user must be able to connect to the database after the environment specified in the ruei.conf configuration file has been loaded.
wm_concat available	.	.	.	.	.	.	The wm_concat database function (used by suites) must be available.
\$JAVA_HOME value valid	.	.	.	.	.	.	The value specified for \$JAVA_HOME in the /etc/ruei.conf configuration file must be valid.
<b>Post-install checks</b>							
Reporter RPM check	.	.	.	.	.	.	The ux-collector, ux-core, ux-generic, ux-ipdb, ux-gui, ux-lang-en, ux-adf, ux-wlp, ux-suites-eps, ux-suites-jde, ux-suites-sbl, ux-suites-psft, and ux-suites-flex RPMs must be installed and have the same version (for example, 5.1.0).

**Table B-1 (Cont.) ruei-check.sh Checks.**

Check	Role						Description
	1	2	3	4	5	6	
Collector RPM check				•			The <code>ux-collector</code> RPM must have been installed.
Java shared objects	•	•		•			The Java path must have been correctly added to the <code>LD_LIBRARY_PATH</code> (see <a href="#">Section 4.3, "Generic Installation Tasks"</a> ).
GUI reachable	•	•	•		•		The Reporter GUI must be reachable via the local hostname on the secure interface (note if a self-signed certificate is found, a warning is generated).
Reporter GUI can reach database	•	•	•		•		The Reporter GUI must be able to contact to the database.
Core binaries in path	•	•	•		•		The specified <code>\$RUEI_USER</code> user must be able to call the core binaries without specifying a full name.

<sup>1</sup> If memory is added to meet the memory requirement, this check may start failing.

---

---

## Setting the Maximum Data Group Size

This appendix provides a detailed explanation of how the default maximum Data Browser group sizes can be increased to provide more accurate reporting of monitored traffic. It is *strongly* recommended that you carefully review the information presented before modifying the default settings.

### C.1 Maximum Group Size and Condensation

In order to optimize performance, individual groups are not permitted to grow to unlimited sizes. Each main group table has a maximum permitted size. By default, this is 600 MB. There is no limit for session diagnostics information.

The maximum size of a group is managed by *condensing*. This is the process by which the number of rows within the group table are reduced by moving the least used data to a "other" group. For example, rows within the client-browser/version dimension might contain a small number of rows for rarely seen Mozilla Firefox versions. In this case, the number of rows within the table is reduced by replacing these with a single "other-firefox" row.

You might consider increasing the maximum size of the groups if the information you require is regularly being condensed. For example, required individual page names or user IDs are only reported as "other". Broadly speaking, this approach is recommended in the case of high levels of network traffic.

### C.2 Setting the Maximum Group Size

If the maximum group size is set to more than 150% (that is, 900 MB), it is *strongly* recommended that the database is configured as a remote database. The maximum recommended group size is 300%<sup>1</sup> (that is, 1.8 GB). Be aware that response times to Data Browser queries may take longer to process if the maximum group size is increased.

It is important to note that custom dimensions have a significant impact on the condensing process. Incorrect configuration of custom dimensions can result in excessive condensing. For example, product names (or similar highly selective attributes) should not be configured as custom dimensions because that will skew the condensing process. Specifically, each page/product combination becomes a separate candidate for condensing, and only high frequency combinations will remain visible after condensing.

---

<sup>1</sup> Be aware that increasing the maximum group size will impact reporting performance. It is recommended that you incrementally increase the setting and verify that performance is acceptable.

To determine the current data group sizes, issue the following command as the defined RUEI\_USER user:

```
cop stats %date_filter
```

where *date\_filter* specifies the date for which you want to view group sizes. Note that if you specify today's date, because the groups are still growing, the reported sizes may not represent their final sizes. Therefore, it is recommended that you issue the query for a previous day's date (for example, yesterday). A group's size is always reported as compressed and needs to be approximately doubled to determine its uncompressed size.

An example command and sample output would appear as follows:

```
cop stats %20091110
```

DATA ROWS		DATA SIZE		cube name
data	desc	data	desc	
705532	565699	<b>300.0</b> MB	30.0 MB	wg_visit_dy_20091110
918028	48727	<b>303.0</b> MB	4.0 MB	wg_trans_dy_20091110
319163	1043110	169.0 MB	96.0 MB	wg_slowurl_dy_20091110
937011	222760	439.0 MB	11.0 MB	wg_sesdiag_dy_20091110
005411	005320	2.1 MB	0.3 MB	wg_service_dy_20091110
834063	126196	<b>315.0</b> MB	20.0 MB	wg_page_dy_20091110
019008	001026	4.0 MB	5.0 MB	wg_kpi_dy_20091110
000345	004598	0.8 MB	0.6 MB	wg_keypage_dy_20091110
286384	967535	168.0 MB	88.0 MB	wg_failurl_dy_20091110
000378	005544	0.4 MB	0.2 MB	wg_failsrv_dy_20091110
<b>632973</b>	2175464	363.0 MB	151.0 MB	wg_failpg_dy_20091110

In the above example, it appears that the daily All pages (*wg\_page\_dy*), and two other groups have reached their maximum limits (300 MB of compressed data), and data is being condensed. Note that the Failed pages group (*wg\_failpg\_dy*), although it has over 300 MB of data, has not reached its limit of 1.4 million rows.

To set the maximum group size, issue the following commands:

```
$ su - moniforce
$ sqlplus /@${RUEI_DB_TNSNAME}
SQL> update UXS_CONFIG set VALUE='900000000'
      where NAME='cube_max_size';
```

where the value specifies (in bytes) the maximum group size. In the above example, this is 900 MB (that is, 150%).

Note that the Failed URLs, Failed services, and Failed pages groups do not use the maximum group size setting. Instead, their size is controlled through the *event\_max\_fail* setting. This specifies the maximum number of rows that can be added to the group's main database table during a 5-minute period. By default, this is 5000 rows. For the Slow URLs group, the *event\_max\_slow* setting is used, and specifies the number of the slowest URLs that are recorded within each 5-minute period. By default, this is 5000 rows.

Note that if you change the *event\_max\_fail* or the *event\_max\_slow* setting, you should also review the *daily\_max\_fail* setting. This specifies the maximum number of rows that the groups' tables can contain. This is derived from the formula  $288 * \text{event\_max\_fail}$ . The default, is 1.4 million rows.

To activate the above changes, you need to issue the following commands:

```
$ sqlplus /@${RUEI_DB_TNSNAME}
```

```
SQL> update UXS_CONFIG set VALUE='10000' where NAME='event_max_fail';
SQL> update UXS_CONFIG set VALUE='4320000' where NAME='daily_max_fail';
```

Note that the `event_max_fail` setting is limited to 10,000 rows.

### Example - Increasing Maximum Group Size

Consider the case in which the maximum main group table size is increased to 900 MB (that is, 150% of the default maximum size). The maximum required database storage is indicated in [Table C](#).

**Table C-1** Default Required Database storage

Type of data retained	Default retention policy	Maximum group size (%)	DB space required per period (GB)	Total DB space required (GB)
Failed pages/URLs/services	15	150%	4.5	67.5
Daily	32	150%	3	96
Monthly	13	150%	3	39
Yearly	5	150%	3	15
Suites	15	150%	1.5	22.5
Additional overhead				10
Total required DB space				250

## C.3 Reviewing the Effects of Changing the Maximum Group Size

After increasing the maximum group size setting, it is *strongly* recommended that you carefully review the effect of the change on the performance of the Reporter system. You should wait at least a full day, and select **System**, then **Status**, and the **Data processing**. Review the system load and determine whether the Reporter system can handle the additional processing overhead that increasing the maximum group size setting represents.

---

**Important:** Increasing the data group sizes can have a significant impact on overall system performance. Therefore, any changes to data group sizes should be carefully planned, and performed in manageable steps.

---

## C.4 Managing the Maximum Size of the Database

By default, the RUEI database is limited to a maximum size of 960 GB. This should be enough to meet your operational requirements. However, if the maximum database size is ever reached, processing automatically stops. You will then need to modify the Reporter data retention policies to reflect the size of available database storage, or increase the maximum database size, before processing can continue.



---

---

## Verifying Monitored Network Traffic


This appendix describes how you can use the TCP diagnostic facility to verify that RUEI "sees" all required network traffic. It is *strongly* recommended that a network engineer within your organization validates collected network traffic after installation and configuration of RUEI.

### D.1 Introduction

The TCP diagnostics utility allows you to create 1-minute snapshots of the network traffic seen by a selected Collector. This snapshot can then be used to help determine whether there are gaps in the expected traffic flow. For example, there could be unconfigured port numbers, or an incorrectly specified VLAN ID.

The TCP traffic can be analyzed across client and server IP and MAC address, as well as port number and VLAN ID. Each snapshot's scope in terms of network traffic information is shown in [Figure D-1](#).

**Figure D-1** Example Network Topology




## D.2 Creating Traffic Snapshots

To create a TCP traffic snapshot, do the following:


1. Within the **Configuration** facility, click the **Show Collector status** icon. Alternatively, select **System**, then **Status**, and then **Collector status**. The Network data Collectors window shown in [Figure D-2](#) opens. This is fully explained in the *Oracle Real User Experience User's Guide*.

**Figure D-2 Network Data Collectors**




2. Click the required Collector. The **System (localhost)** item refers to the Collector instance running on the Reporter system. Other Collectors within the network are represented by their IP address.
3. Click the **TCP diagnostics** tab. A panel similar to the one shown in [Example D-3](#) appears.

**Figure D-3 TCP Diagnostics**



4. Click the **New snapshot** icon in the toolbar. The dialog shown in [Figure D-4](#) appears.

**Figure D-4** New TCP Traffic Snapshot Dialog



5. Use the **Apply filters** check box to specify whether the create traffic snapshot should be created to report all traffic seen by the selected Collector, or only that traffic that fits the Collector’s currently defined filters (see the *Oracle Real User Experience Insight User’s Guide* for more information). These are shown in the lower part of the dialog. Note that you can also view them by clicking the **View snapshot filters** icon on the toolbar. When ready, click **Create snapshot**.

---

**Note:** The maximum number of traffic snapshots across all Collector systems in your RUEI installation is 15. When this maximum is reached, the oldest snapshot is automatically replaced by the newly created snapshot.

---

6. There is a 1-minute delay while the snapshot is created. Upon completion, an overview of the newly created snapshot’s details is presented. An example is shown in [Figure D-5](#).

**Figure D-5** TCP Traffic Snapshot Overview

Dimension level		Value				
Server VLAN/ID	Client VLAN/ID	Server IP/Address	Server TCP/Port	Server packets	Client packets	Status
0	0	10.161.59.165	80	12,942	15,149	✓
0	0	10.161.59.167	443	1,463	1,202	✓
0	0	10.161.59.165	443	1,064	824	✓


## D.3 Analyzing Traffic Information

To analysis a created snapshot, do the following:

1. Select the required snapshot from the snapshot menu, or click it via the TCP diagnostics main panel (shown in [Figure D-3](#)). Snapshots created with applied filters are indicated with a tick character in the **Filtered** column. You can view the applied filters by clicking the tick character.
2. An overview of the selected snapshot (similar to the one shown in [Figure D-5](#)) appears. Note that you can click a selectable item to filter on it. For example, the list of reported items should be restricted to those that include a particular server IP address. You can remove a filter by clicking the **Remove** icon beside it in the filters section of the panel.

Optionally, use the sort menu (shown in [Figure D-6](#)) to the right of the snapshot menu to select the primary column used for the displayed items.

**Figure D-6 Sort Menu**



3. The **Status** column shown in [Figure D-5](#) indicates whether a possible problem may exist with the TCP traffic monitored during the snapshot. In the event of a fail status being reported, you can mouse over the status icon to see additional information. Possible identified problems are explained in [Table D-1](#).

**Table D-1 Identify Problems and Possible Causes**

Status	Description
Client/server packet ratio is too high.	The number of client packets compared to server packets seems to be unusually large. This could indicate that the Collector cannot see both directions of traffic due (or is seeing duplicate traffic in one direction), or there is a server-related issue (for example, it is switched off).
Server/client packet ratio is too high.	The number of server packets compared to client packets seems to be usually large. This could indicate that the Collector cannot see both directions of traffic due (or seeing duplicate traffic in one direction), or there is a client-related issue (for example, unacknowledged server packets).
Insufficient number of server and client packets for analysis.	There was insufficient traffic (TCP packets) to perform a reliable client/server ratio analysis. A minimum of 100 packets is required. This may because normal traffic levels to the server are low. Otherwise, it may indicate routing issues with RUEI being unable to see some portions of network traffic.
Server VLAN ID does not match client VLAN ID.	This would normally indicate a routing issue. For example, traffic from the client to the server is being routed via one VLAN, but the traffic back from the server to the client is being routed via another VLAN. Be aware that RUEI can only monitor traffic on one VLAN segment at a time.



---

---

## Troubleshooting

This appendix highlights the most common problems encountered when installing RUEI, and offers solutions to locate and correct them. The information in this appendix should be reviewed before contacting Customer Support.

### Support Web sites

Information on a wide variety of topics is available via the Oracle Web site ([http://www.oracle.com/enterprise\\_manager/user-experience-management.html](http://www.oracle.com/enterprise_manager/user-experience-management.html)). It is recommended that you visit it regularly for support announcements.

In addition, detailed technical information is available via the Support Web site (<https://metalink.oracle.com>). This includes information about service pack availability, FAQs, training material, tips and tricks, and the latest version of the product documentation. A valid user name and password is required to access this Web site.

### Contacting Customer Support

If you experience problems with the installation or configuration of the RUEI, you can contact Customer Support. However, before doing so, it is strongly recommended that you create a Helpdesk report file of your installation. To do so, select **System**, then **Configuration**, and then **Helpdesk report**. This file contains extended system information that is extremely useful to Customer Support when handling any issues that you report.

## E.1 Running the rui-check.sh Script

It is recommended you use the `rui_check.sh` script to troubleshoot installation issues. When first run, the script requires you to specify an installation type (`reporter`, `collector`, or `database`). Be aware this selection is saved to file. Therefore, if you want to run the script and be able to specify a different installation type, you need to delete the file `/tmp/rui-system-type` using the following command:

```
rm /tmp/rui-system-type
```

You can specify the parameters shown in [Table E-1](#):

**Table E-1** *ruei-check.sh Parameters*

Parameter	Description
system	Performs basic system checks, as well as a number of prerequisites checks. These include interfaces that can be monitorable interfaces, that the Oracle database starts correctly, and that the Apache Web server, PHP, and Zend optimizer are correctly configured.
preinstall	Checks whether the Oracle database is correctly configured.
postinstall	Checks if the RUEI RPMs have been installed correctly.
all	Performs all the above checks in the indicated sequences.

For example:

```
cd /root/RUEI/60
./ruei-check.sh all
```

## E.2 The ruei-prepare-db.sh Script Fails

If the `ruei-prepare-db.sh` script fails, this can be because the database listener has not been started correctly due to a failing DNS look up. To resolve this problem, do the following:

- Ensure the `/etc/hosts` file includes your host.
- Ensure entries in the `/etc/nsswitch.conf` file are specified in the required (sequence hosts: files DNS).

---



---

**Note:** The `ruei-prepare-db.sh` script can be run with the `--clean` option to remove the current database and install a new one.

---



---

## E.3 Starting Problems

If the system does not seem to start, or does not listen to the correct ports, do the following:

- Restart each Collector service. To do so, select **System**, then **Maintenance**, then **Network data collectors**, select each attached Collector, and select the **Restart** option from the menu. This is described in more detail in the *Oracle Real User Experience Insight User's Guide*.
- Review your network filter definitions. This is described in the *Oracle Real User Experience Insight User's Guide*. In particular, ensure that no usual network filters have been applied. This is particularly important in the case of VLANs.
- Ensure that RUEI is listening to the correct protocols and ports. This is described in the *Oracle Real User Experience Insight User's Guide*.
- Verify that the Collector interfaces are *up*. This is described in the [Section 2.5, "Network Configuration"](#).

### Resources and Log Files

If during, or directly after running the Initial setup wizard (described in [Section 6.2, "Performing Initial RUEI Configuration"](#)), the system returns an error, there are the following resources and log files available to help you in debugging:

- `/var/opt/ruei/processor/log/gui_debug.log`: a proprietary debug and log file that shows low-level system information. Although its contents may be difficult to read, you can find standard system error messages listed here.
- `/var/log/httpd/access_log` and `/error_log`: the Apache daemon access and error log files. If any part of the HTTP or PHP execution of the RUEI user interface is in error, it will show up in these log files. (Note that these are *not* the log files used by RUEI for HTTP data analysis).

### Root-Cause Analysis

Before starting to address specific issues, it is important to understand the basic operation of data collection, data processing, and data reporting. Any root-cause analysis of RUEI problems should take the following:

- Verify data collection. Select **System**, then **Status**, and then **Collector status**. Select a Collector from the displayed list, and verify that the system interfaces are showing traffic activity on TCP, Ethernet, and HTTP level.
- In addition, verify that there are no problems with the SSL data decryption. It is normal that some errors occur (especially shortly after startup). But if SSL traffic is to be decrypted, the error rate can never be 100%.
- Verify data processing. Select **System**, then **Status**, then **Data processing**. A screen similar to the one shown in [Figure 6-7](#) appears. It should indicate some activity.

## E.4 Data Collection Problems

If the data collection service is not running, or will not start, do the following:

- Use the TCP diagnostics facility to verify that RUEI "sees" all required network traffic. The use of this tool is described in [Appendix D, "Verifying Monitored Network Traffic"](#).
- Ensure the network cards used for data collection are running in promiscuous mode. This can be verified by issuing the command `ifconfig ethN` (where *N* is the number of the network interface being used for data collection). It should return an output similar to the following:

```
ethn      Link encap:Ethernet  HWaddr 00:15:17:3E:26:AF
          UP BROADCAST RUNNING PROMISC MULTICAST  MTU:1500  Metric:1
          RX packets:0 errors:0 dropped:0 overruns:0 frame:0
          TX packets:0 errors:0 dropped:0 overruns:0 carrier:0
          collisions:0 txqueuelen:1000
          RX bytes:0 (0.0 GiB)  TX bytes:0 (0.0 GiB)
          Memory:b9120000-b9140000
```

- If the network interface is not available, make sure the ONBOOT parameter is set to YES, as described in [Section 2.5, "Network Configuration"](#).
- If the network interface is not yet in promiscuous mode, set it by issuing the following command: `ifconfig ethN promisc` (where *N* is the number of the network interface being used for data collection).
- Verify there is *no* IP address assigned to the network interface being used for data collection. If there is a configured IP address, remove it.

---

**Note:** Do not set to 0.0.0.0 or 127.0.0.1. Remove the configured IP address completely.

---

## E.5 Data Processing Problems

If, for any reason, data processing does not start, try to restart it by selecting **System**, then **Maintenance**, and then **System Reset**. The System reset wizard appears. Select the **Restart system processing** option. Note that restarting system processing can take between 5 and 30 minutes.

In general, if no data is being processed, verify your system's configuration as described in [Section 6.5, "Verifying and Evaluating Your Configuration"](#). If you do not apply any configuration to the system, no data processing will take place.

If you are using an environment with multiple Collectors, ensure all Collectors are up and running normally. To do so, select **System**, then **Status**, and then **Collector status**. A failing Collector can become a block to further data processing of the system's data.

## E.6 E-Mail Problems

Sending E-mails is RUEI functionality that is handled on a system level, together with your Mail Transfer Agent (MTA), such as Sendmail or Postfix. If problems occur when sending E-mails, do the following:

- If mail is sent correctly by RUEI to your MTA, the user interface will report "Message sent successfully" when you attempt to send a daily, weekly, or monthly report manually.
- If mail could not be sent correctly by RUEI to your MTA, verify that the MTA is up and running. Alternatively, analyze the mail settings by selecting **System**, then **Maintenance**, and **E-mail configuration**.
- If the mail was sent successfully, but not delivered to the recipient, analyze the operation of your MTA to further identify the root cause of the mails that are not delivered.
- Refer to the `/var/log/maillog` file for reported mailing issues.

Common issues with E-mail delivery often involve an incorrectly configured MTA, or an MTA that is not allowed to send E-mail within the Data Center or corporate network.

## E.7 SSL Decryption Problems

In order to decrypt SSL traffic, the Collector needs to have the SSL key and certificate available. To enable SSL decryption, you should do the following:

- Upload the SSL key through the appropriate Collector.
- Enable the SSL key by entering the required decryption passphrase (when applicable).

The certificate needs to be uploaded to the Collector(s) by selecting **Configuration**, then **Security**, and then **SSL keys**. To check the status of the SSL decryption, select **System**, then **Status**, and then **Collector status**, and select the Collector for which you want SSL decryption analysis. Within the **SSL encryption** page, note the following:

- Decryption errors will occur if there is no SSL key uploaded.
- The percentage of successful decryption will be a low number shortly after uploading and activating the appropriate SSL keys.
- This percentage should rise in the first minutes and hours after uploading the SSL keys.

RUEI accepts PKCS#12 and PEM/DER encoding of SSL keys and certificates. Basically, this means both the certificate and key should be concatenated into one file. If you have separate key and certificate files, you can create a PKCS#12-compliant file by issuing the following command:

```
openssl pkcs12 -export -in certificate.cer -inkey key.key -out pkcs12file.p12
-passout pass:yourpassphrase
```

Where:

- *certificate.cer* is your CA root certificate file.
- *key.key* is the server's SSL key file.
- *pkcs12file.p12* is the output file name for the PKCS#12-encoded file.
- *yourpassphrase* is the passphrase you want to use to protect the file from unwanted decryption.

For example, consider the situation where the CA root certificate filename is *ca\_mydomainroot.cer*, the server's SSL key is *appsrv12.key*, you want the output file to be called *uxssl.p12*, and want to protect this file with the passphrase *thisismysecretphrase*. The following command is required:

```
Openssl pkcs12 -export -in ca_mydomainroot.cer -inkey appsrv12.key -out uxssl.p12
-passout pass:thisismysecretphrase
```

## E.8 Missing Packages and Fonts Error Messages

It is *strongly* recommended that you follow the installation procedure and settings described in [Section 2.6, "Package Installation"](#). In particular, you should not perform a "minimal" installation of Oracle Linux. If you do so, it can lead to a wide range of reported problems, depending on the components not included in the installation, but required by RUEI.

The most common of these are reported `fontconfig` error messages in the `/var/log/http/error_log` file. These can be fixed by installing the following fonts:

- `urw-fonts-noarch v2.3`
- `ghostscript-fonts-noarch v5`
- `dejavu-lgc-fonts-noarch v2`
- `liberation-fonts v0.2`
- `bitmap-fonts v0.3`
- `bistream-vera-fonts-noarch v1.10`

Depending on your language settings, install all other required fonts.

However, other possible error messages include reported missing packages (such as `librsvg2`).

When a Yum repository is available, all dependencies available on the Linux 5.x DVD can be installed by issuing following command:

```
yum -y install gcc gcc-c++ compat-libstdc++-33 glibc-devel libstdc++-devel \
elfutils-libelf-devel glibc-devel libaio-devel sysstat perl-URI net-snmp \
sendmail-cf httpd php php-pear php-mbstring phpldap bitstream-vera-fonts \
librsvg2 xorg-x11-xinit net-snmp-utils perl-XML-Twig
```

However, be aware that additional RPMs shipped with the RUEI installation zip file still need to be installed according to the procedure described in [Section 2.6, "Package Installation"](#).

## E.9 ORA-xxxxx Errors

If you receive any Oracle database errors, do the following:

- Ensure that the `/etc/sysconfig/httpd` file contains the following lines:

```
source /etc/ruei.conf
```

If you have to add these lines, restart the Apache Web server using the following command:

```
service httpd restart
```

- Ensure that the `ewallet.p12` file is readable by the `RUEI_USER` specified user. Additionally, the `cwallet.sso` file should also be readable by the `RUEI_GROUP` specified group. On Linux/UNIX, this can be accomplished by issuing the following commands:

```
chmod 600 ewallet.p12
chmod 640 cwallet.sso
```

- Ensure the same host name is specified in the `/var/opt/ruei/tnsnames.ora`, `/etc/sysconfig/network`, and `/etc/hosts` files.

Note if you make changes to any of these files, you may need to reboot the server.

## E.10 Oracle DataBase Not Running

Verify the Oracle database is up and running by changing to the `moniforce` user and obtaining an SQL\*Plus prompt with the following commands:

```
su - moniforce
sqlplus /@uxinsight
```

You should receive the SQL\*Plus command line without being prompted for a password. This indicates that the Oracle wallet authentication was successful.

If necessary, re-start the Oracle database using the following command:

```
/etc/init.d/oracledb
```

## E.11 General (Non-Specific) Problems

If you are experiencing problems with the reporting module, or find its interface unstable, it is recommended that you do the following:

- Clear all content caching within your browser, and re-start your browser.
- Examine the error log. This is described in the *Oracle Real User Experience Insight User's Guide*.
- Select **System**, then **Status**, and verify correct operation of the core components by then selecting **Data Collection**, **Logfile processing**, and **Data processing**. If any of these components are in error, try to resolve them using the advice provided in this appendix.

## E.12 Network Interface Not Up

If the network interface you intend to use for data collection is not *Up* (that is, the `ONBOOT=YES` parameter was not set), you can bring it immediately using the following command:

```
ifconfig ethN up
```

where *N* represents the necessary network interface.

## E.13 Memory Allocation Error During Upgrade Procedure

The following memory allocation error is received while updating the Reporter RPMs as part of the procedure for upgrading from version 5.1 to 6.0:

```
Cannot allocate memory
```

Make more memory for a socket connection available to the Collector in order for it to start. Issue the following command as the `root` user:

```
/sbin/sysctl -w net.core.optmem_max=65535
```

## E.14 OAM-Related Problems

In order to start isolating OAM-related problems, you should do the following:

1. Logon through the OAM environment to obtain a valid OAM cookie.
2. Logon to the Reporter system as the `moniforce` user.
3. To view the generated session tracking information, issue the following commands:

```
project -
cp $WEBSSENSOR_INI/../../evt/OAM2* $WEBSSENSOR_INI
mklookup --match 'OAM-cookie' '%' '%1[${OAM2Cookie}]'
```

where *OAM-cookie* specifies the name of the OAM cookie. By default, this is `ObSSOCookie`. Alternatively, use the following commands to view user name information:

```
project -
cp $WEBSSENSOR_INI/../../evt/OAM2* $WEBSSENSOR_INI
mklookup --match 'value' '%' '%1[${OAM2UserName}]'
```

where *value* specifies the value of the generated cookie.

The expected output should be similar to one of the following:

```
#1 = 'cn=OblixAnonymous,dc=somebooks,dc=com'
#1 = '' --> the cookie has expired
#1 = 'hash-value'
```

If an error was reported in the output, see the section below for additional diagnostics information.

### Reported Errors

If the following error is received:

```
*ERROR* - obssocookie: could not dlopen()
/opt/netpoint/AccessServerSDK//oblix/lib/libobaccess.so:
/opt/netpoint/AccessServerSDK//oblix/lib/libobaccess.so: cannot open shared
```

```
object file: Permission denied
```

This indicates that the `moniforce` user does not have the necessary permissions. You should logon to the Reporter system as the `moniforce` user, and issue the following commands:

```
find /opt/netpoint/AccessServerSDK -type d -exec chmod o+rx {} \;  
find /opt/netpoint/AccessServerSDK -type f -exec chmod o+r {} \;
```

If the following error is received:

```
*ERROR* - obssockie: could not dlopen()  
/opt/netpoint/AccessServerSDK//oblix/lib/libobaccess.so:  
/opt/netpoint/AccessServerSDK//oblix/lib/libobaccess.so: wrong ELF class:  
ELFCLASS32
```

This indicates that the 32-bit version of the Access Gate SDK was installed instead of the required 64-bit version. The procedure to download and install the required Access Gate SDK is described in [Section 8.2, "Downloading and Installing the Access Gate Software"](#).

If the following error is received:

```
Server is not authenticated to access the the OAM environment
```

This indicates that the creation of a trust between RUEI and the access server (described in [Section 8.3, "Configuring the Access Gate Software on the RUEI Server"](#)) was not successfully performed, and should be repeated.

## E.15 ruei-check.sh Script Reports PHP Timezone Error

The following error is reported by the `ruei-check.sh` script:

```
Checking if the PHP timezone has been set correctly: [FAIL]  
PHP and OS timezones do not match (os: winter +0000, summer +0100. php:  
winter +0100, summer +0200)
```

This can easily be fixed by setting the `TZ` environment variable at the bottom of the `/etc/ruei.conf` file on the Reporter system as follows:

```
export TZ=Europe/Lisbon
```

## Installation Checklist

This appendix provides a checklist of actions that should be complete, and information gathered, before starting to install the RUEI software. These include server and infrastructure readiness and configuration, as well as HTTPS encrypted traffic and alerting issues.

### Server readiness

Base hardware and operating system requirements.

Intel/AMD 64-bit platform (minimum 2 dual-core CPUs).

Network connectivity:

- 10/100 MB NIC for office network connectivity.
- 10/100/1000 MB NIC for data collection connectivity.

Disk space: at least 400 GB (on high-performance RAID-5, RAID-10, or similar).

Memory: at least 16 GB RAM for single server.

OS: Oracle Linux 64-bit or RedHat Enterprise Linux 64-bit 5.x.

The `ruei-check.sh` script reports no errors.

The EBS, JD Edwards, FLEXCUBE, and PeopleSoft configuration zip files are available.

### Infrastructure readiness

Ensure easy placement and accessibility of the system.

Prepare rackspace in the Data Center cabinet with power sockets.

The server is accessible through remote ports:

- Port 80/443 for HTTP(S) traffic to the RUEI Web server.
- Port 22 for remote management over SSH/SCP.
- Port 25 (E-mail).
- Port 123 (NTP).
- Port 161/162 (SNMP).
- Port 1521 (for remote database setup).

Access to the Data Center on the appropriate day and time is arranged.

Network preparation for TAP/copy port is done and cables available in cabinet.

Server configuration completed (see below).

<b>Infrastructure readiness</b>	
<p>Main topology with proxies, load balancers, routers, switches, and so on, is known.</p> <p>Main traffic flows throughout the infrastructure are known.</p> <p>VLAN topology, VLAD IDs, and IP addresses are known.</p> <p>The monitoring position for the RUEI server is located as close as possible to the firewall.</p> <p>The domains, applications, server farm(s), and/or VLANs to be monitored are identified.</p>	

<b>Server configuration</b>	
Complete the details below to for reference during server configuration.	
<p>Host name and domain name (optional).</p> <p>Data Center name.</p> <p>Placement date and time.</p> <p>Server IP, netmask, and default gateway.</p> <p>Server type (Collector/Reporter).</p> <p>NTP server IP and backup.</p> <p>DNS server IP and backup.</p> <p>Mail server and sender mail.</p> <p>Socket 0: collection port to TAP/switch name.</p> <p>Socket 1: collection port to TAP/switch name.</p> <p>Socket 2: rescue/maintenance interface.</p> <p>Socket 3: Office network to switch name.</p> <p>Socket 4: collection port to TAP/switch name.</p> <p>Socket 5: collection port to TAP/switch name.</p>	<reserved>

<b>Data collection configuration</b>	
Once in place, the server will start collecting data. Specify how much data is expected, and the technologies used.	
<p>HTTP traffic (in MB, pageviews, or hits per hour).</p> <p>Base technology for Web applications.</p> <p>Limits on amount of traffic to be captured:</p> <ul style="list-style-type: none"> <li>■ HTTP and HTTPS ports (if other than 80/443 HTTP/HTTPS).</li> <li>■ VLAN traffic and VLAN IDs (optional).</li> </ul> <p>Cookie technology.</p> <p>Page-labelling technology.</p> <p>Blind POST field names (such as <code>passwd</code>).</p> <p>User identification in URL (if other than login).</p> <p>Web service domains or networks.</p>	

---

**Data collection configuration**

XML/SOAP envelopes (max 10).

Chronos/EUM URL (for EBS and Forms).

---

---

**HTTPS enablement**

Specify the contact(s) for the required SSL keys to monitor encrypted traffic.

Name:

Name:

Function:

Function:

E-mail:

E-mail:

Phone/Mobile:

Phone/Mobile:

Keys (if not all):

Keys (if not all):

---

---

**System health notifications**

The system can trigger and send alerts for various components. Specify the users, notification methods, and details for each component.

Name:

Name:

Function:

Function:

E-mail:

E-mail:

Mobile:

Mobile:

Text message:

Text message:

---

---

**Alerting via SNMP (optional)<sup>1</sup>**

SNMP management server.

SNMP community name.

SNMP version.

---

<sup>1</sup> RUEI provides a standard MIB to be imported into the SNMP manager.



---

---

## Third-Party Licenses

This appendix contains licensing information about certain third-party products included with this release of RUEI. Unless otherwise specifically noted, all licenses herein are provided for notice purposes only.

The sections in this appendix describe the following third-party licenses:

- [Apache Software License, Version 2.0](#)
- [OpenSSL](#)
- [PHP](#)
- [Java Runtime Environment](#)

### **Apache Software License, Version 2.0**

Apache License

Version 2.0, January 2004

<http://www.apache.org/licenses/>

#### **TERMS AND CONDITIONS FOR USE, REPRODUCTION, AND DISTRIBUTION**

1. **Definitions.** "License" shall mean the terms and conditions for use, reproduction, and distribution as defined by Sections 1 through 9 of this document.

"Licensor" shall mean the copyright owner or entity authorized by the copyright owner that is granting the License.

"Legal Entity" shall mean the union of the acting entity and all other entities that control, are controlled by, or are under common control with that entity. For the purposes of this definition, "control" means (i) the power, direct or indirect, to cause the direction or management of such entity, whether by contract or otherwise, or (ii) ownership of fifty percent (50%) or more of the outstanding shares, or (iii) beneficial ownership of such entity.

"You" (or "Your") shall mean an individual or Legal Entity exercising permissions granted by this License.

"Source" form shall mean the preferred form for making modifications, including but not limited to software source code, documentation source, and configuration files.

"Object" form shall mean any form resulting from mechanical transformation or translation of a Source form, including but not limited to compiled object code, generated documentation, and conversions to other media types.

"Work" shall mean the work of authorship, whether in Source or Object form, made available under the License, as indicated by a copyright notice that is included in or attached to the work (an example is provided in the Appendix below).

---

"Derivative Works" shall mean any work, whether in Source or Object form, that is based on (or derived from) the Work and for which the editorial revisions, annotations, elaborations, or other modifications represent, as a whole, an original work of authorship. For the purposes of this License, Derivative Works shall not include works that remain separable from, or merely link (or bind by name) to the interfaces of, the Work and Derivative Works thereof.

"Contribution" shall mean any work of authorship, including the original version of the Work and any modifications or additions to that Work or Derivative Works thereof, that is intentionally submitted to Licensor for inclusion in the Work by the copyright owner or by an individual or Legal Entity authorized to submit on behalf of the copyright owner. For the purposes of this definition, "submitted" means any form of electronic, verbal, or written communication sent to the Licensor or its representatives, including but not limited to communication on electronic mailing lists, source code control systems, and issue tracking systems that are managed by, or on behalf of, the Licensor for the purpose of discussing and improving the Work, but excluding communication that is conspicuously marked or otherwise designated in writing by the copyright owner as "Not a Contribution."

"Contributor" shall mean Licensor and any individual or Legal Entity on behalf of whom a Contribution has been received by Licensor and subsequently incorporated within the Work.

**2. Grant of Copyright License.** Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable copyright license to reproduce, prepare Derivative Works of, publicly display, publicly perform, sublicense, and distribute the Work and such Derivative Works in Source or Object form.

**3. Grant of Patent License.** Subject to the terms and conditions of this License, each Contributor hereby grants to You a perpetual, worldwide, non-exclusive, no-charge, royalty-free, irrevocable (except as stated in this section) patent license to make, have made, use, offer to sell, sell, import, and otherwise transfer the Work, where such license applies only to those patent claims licensable by such Contributor that are necessarily infringed by their Contribution(s) alone or by combination of their Contribution(s) with the Work to which such Contribution(s) was submitted. If You institute patent litigation against any entity (including a cross-claim or counterclaim in a lawsuit) alleging that the Work or a Contribution incorporated within the Work constitutes direct or contributory patent infringement, then any patent licenses granted to You under this License for that Work shall terminate as of the date such litigation is filed.

**4. Redistribution.** You may reproduce and distribute copies of the Work or Derivative Works thereof in any medium, with or without modifications, and in Source or Object form, provided that You meet the following conditions:

- You must give any other recipients of the Work or Derivative Works a copy of this License; and
- You must cause any modified files to carry prominent notices stating that You changed the files; and
- You must retain, in the Source form of any Derivative Works that You distribute, all copyright, patent, trademark, and attribution notices from the Source form of the Work, excluding those notices that do not pertain to any part of the Derivative Works; and
- If the Work includes a "NOTICE" text file as part of its distribution, then any Derivative Works that You distribute must include a readable copy of the attribution notices contained within such NOTICE file, excluding those notices

---

that do not pertain to any part of the Derivative Works, in at least one of the following places: within a NOTICE text file distributed as part of the Derivative Works; within the Source form or documentation, if provided along with the Derivative Works; or, within a display generated by the Derivative Works, if and wherever such third-party notices normally appear. The contents of the NOTICE file are for informational purposes only and do not modify the License. You may add Your own attribution notices within Derivative Works that You distribute, alongside or as an addendum to the NOTICE text from the Work, provided that such additional attribution notices cannot be construed as modifying the License. You may add Your own copyright statement to Your modifications and may provide additional or different license terms and conditions for use, reproduction, or distribution of Your modifications, or for any such Derivative Works as a whole, provided Your use, reproduction, and distribution of the Work otherwise complies with the conditions stated in this License.

**5. Submission of Contributions.** Unless You explicitly state otherwise, any Contribution intentionally submitted for inclusion in the Work by You to the Licensor shall be under the terms and conditions of this License, without any additional terms or conditions. Notwithstanding the above, nothing herein shall supersede or modify the terms of any separate license agreement you may have executed with Licensor regarding such Contributions.

**6. Trademarks.** This License does not grant permission to use the trade names, trademarks, service marks, or product names of the Licensor, except as required for reasonable and customary use in describing the origin of the Work and reproducing the content of the NOTICE file.

**7. Disclaimer of Warranty.** Unless required by applicable law or agreed to in writing, Licensor provides the Work (and each Contributor provides its Contributions) on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied, including, without limitation, any warranties or conditions of TITLE, NON-INFRINGEMENT, MERCHANTABILITY, or FITNESS FOR A PARTICULAR PURPOSE. You are solely responsible for determining the appropriateness of using or redistributing the Work and assume any risks associated with Your exercise of permissions under this License.

**8. Limitation of Liability.** In no event and under no legal theory, whether in tort (including negligence), contract, or otherwise, unless required by applicable law (such as deliberate and grossly negligent acts) or agreed to in writing, shall any Contributor be liable to You for damages, including any direct, indirect, special, incidental, or consequential damages of any character arising as a result of this License or out of the use or inability to use the Work (including but not limited to damages for loss of goodwill, work stoppage, computer failure or malfunction, or any and all other commercial damages or losses), even if such Contributor has been advised of the possibility of such damages.

**9. Accepting Warranty or Additional Liability.** While redistributing the Work or Derivative Works thereof, You may choose to offer, and charge a fee for, acceptance of support, warranty, indemnity, or other liability obligations and/or rights consistent with this License. However, in accepting such obligations, You may act only on Your own behalf and on Your sole responsibility, not on behalf of any other Contributor, and only if You agree to indemnify, defend, and hold each Contributor harmless for any liability incurred by, or claims asserted against, such Contributor by reason of your accepting any such warranty or additional liability.

## END OF TERMS AND CONDITIONS

APPENDIX: How to apply the Apache License to your work.

---

To apply the Apache License to your work, attach the following boilerplate notice, with the fields enclosed by brackets "[ ]" replaced with your own identifying information. (Don't include the brackets!) The text should be enclosed in the appropriate comment syntax for the file format. We also recommend that a file or class name and description of purpose be included on the same "printed page" as the copyright notice for easier identification within third-party archives.

Copyright [yyyy] [name of copyright owner]

Licensed under the Apache License, Version 2.0 (the "License"); you may not use this file except in compliance with the License. You may obtain a copy of the License at

<http://www.apache.org/licenses/LICENSE-2.0>

Unless required by applicable law or agreed to in writing, software distributed under the License is distributed on an "AS IS" BASIS, WITHOUT WARRANTIES OR CONDITIONS OF ANY KIND, either express or implied. See the License for the specific language governing permissions and limitations under the License.

## **OpenSSL**

This product includes software developed by the OpenSSL Project for use in the OpenSSL Toolkit (<http://www.openssl.org>).

Copyright © 1998-2007 The OpenSSL Project. All rights reserved.

Copyright © 1995-1998 Eric Young (eay@cryptsoft.com). All rights reserved.

THIS SOFTWARE IS PROVIDED BY THE OPENSOURCE PROJECT "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE OPENSOURCE PROJECT BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE.

## **PHP**

Copyright © 1999-2006 The PHP Group. All rights reserved.

This product includes PHP software, freely available from <http://php.net/software/>.

"THIS SOFTWARE IS PROVIDED BY THE PHP DEVELOPMENT TEAM "AS IS" AND ANY EXPRESS OR IMPLIED WARRANTIES, INCLUDING, BUT NOT LIMITED TO, THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE ARE DISCLAIMED. IN NO EVENT SHALL THE PHP DEVELOPMENT TEAM BE LIABLE FOR ANY DIRECT, INDIRECT, INCIDENTAL, SPECIAL, EXEMPLARY, OR CONSEQUENTIAL DAMAGES (INCLUDING, BUT NOT LIMITED TO, PROCUREMENT OF SUBSTITUTE GOODS OR SERVICES; LOSS OF USE, DATA OR PROFITS; OR BUSINESS INTERRUPTION) HOWEVER CAUSED AND ON ANY THEORY OF LIABILITY, WHETHER IN CONTRACT, STRICT LIABILITY, OR TORT (INCLUDING NEGLIGENCE OR OTHERWISE) ARISING IN ANY WAY OUT OF THE USE OF THIS SOFTWARE, EVEN IF ADVISED OF THE POSSIBILITY OF SUCH DAMAGE."

---

## **Java Runtime Environment**

Oracle is required to provide the following notice as part of the license terms for the Sun JRE that the field of use for the JRE is: (i) general purpose desktop computers, laptops and servers, and (ii) embedded systems (by way of example: embedded applications, cell phones, PDAs, TV devices, digital set top boxes, telematics devices and home gateway devices), provided that the Java Runtime Environment (JRE) is licensed only to run Licensee applications, middleware and database products and the JRE is not licensed to directly run any third party applications. This shall not be understood to prevent third party applications from indirectly and incidentally utilizing the JRE, but only as such is required to enable other Licensee Product functionality.

After installing the JRE, the complete terms of the Sun Microsystems license agreement are available in the file `/usr/java/jre/THIRDPARTYLICENSEREADME.txt`.



---

---

# Index

## A

---

accounts  
  administrator, 4-7  
  database, 3-3  
  operating system, 2-8  
Administrator, 6-1  
AJAX support, 1-14  
Apache Web server, 4-3

## C

---

checklist, B-1, F-1  
client requirements, 1-14  
Collector  
  checking status, 6-7  
  configuring, 6-4  
  description, 1-6  
  registering, 6-4  
  resetting, 6-4  
  upgrading, 5-4  
configuration  
  apache, 4-3  
  Collector, 6-4  
  firewall, 2-6  
  initial RUEI, 6-1  
  MTA, 4-8  
  network, 2-4  
  options, 1-6  
  PHP, 4-3  
  post installation, 6-1  
  Reporter communication, 4-8  
  SELinux, 2-7  
  SNMP, 4-8  
cookie technology, 6-5  
cookies, A-1, D-1  
copy ports, 1-3

## D

---

daily\_max\_fail, C-2  
disk partitioning, 2-2

## E

---

event\_max\_fail, C-2  
event\_max\_slow, C-2

## F

---

full session replay, 1-11

## H

---

hardware requirements, 1-7

## I

---

installation  
  checklist, B-1, F-1  
  data collection, 1-1  
  Java, 4-2  
  Linux, 2-1  
  Oracle database, 3-3  
  Oracle database directory, 3-4  
  remote Collector, 4-3  
  Reporter, 4-6  
  RUEI software, 4-1  
  upgrading to 6.5, 5-1  
  verifying, 4-9  
installation checklist, B-1, F-1  
Instant Client, 4-4  
ISO image, 2-2

## J

---

Java, 4-2, 5-2, 5-5

## L

---

Linux  
  date and time settings, 2-8  
  disk partitioning, 2-2  
  firewall configuration, 2-6  
  installation, 2-1  
  installer, 2-2  
  NTP daemon, 2-9  
  package installation, 2-4  
  user creation, 2-8

## M

---

mail setup, 6-3  
MTA configuration, 4-8  
multibyte fonts, 4-7

## N

---

### network

- configuration, 4-7
- requirements, 1-13
- traffic, 6-6

NTP daemon, 2-9

## O

---

### Oracle database

- init script file, 3-8
- installation, 3-3
- installation directory, 3-4
- Instant Client, 4-4
- kernel settings, 3-4
- required packages, 3-2
- shell limits, 3-4
- user accounts and groups, 3-3
- user's environment, 3-5

## P

---

pages names, 6-5

php-oci8 module, 4-4

## R

---

### Reporter

- description, 1-6
- upgrading, 5-1

### requirements

- client, 1-14
- disk space, 2-3
- hardware, 1-7
- network, 1-13
- software, 1-13
- swap space, 2-3

rsvg warnings, 4-4

### RUEI

- client requirements, 1-14
- configuration file, 4-2
- configuring, 6-1
- confirming data collection, 6-7
- deployment options, 1-5
- hardware requirements, 1-7
- installation checklist, B-1, F-1
- introduction, 1-1
- mail setup, 6-3
- naming pages, 6-5
- network requirements, 1-13
- obtaining software, 4-1
- post-innallation configuration, 6-5
- product architecture, 1-2
- scalability options, 1-6
- scope of monitoring, 6-6
- security, 1-2
- software requirements, 1-13
- troubleshooting, E-1
- verifying, 6-6

ruei-check.sh, B-1, E-1

ruei.conf, 4-2

## S

---

security, 1-2

SELinux, 2-7

Sendmail MTA, 4-8

SNMP, 4-8

software requirements, 1-13

SSL keys, 6-5

## T

---

TAPs, 1-4

TCP diagnostics, A-1, D-1

third-party licenses, G-1

troubleshooting, E-1

## U

---

upgrading to 6.5, 5-1

user identification, 6-5

### users

authorizing, 6-6

identification, 6-5

Linux, 2-8

Oracle database, 3-3

Oracle database environment, 3-5

## W

---

### wizard

initial setup, 6-2

post-installation, 2-5

## Y

---

Yum repository, 3-2

## Z

---

Zend optimizer, 4-4