



Sun Cluster 3.1 Data Service for Sun ONE Application Server Guide

Sun Microsystems, Inc.
4150 Network Circle
Santa Clara, CA 95054
U.S.A.

Part No: 817-3311-10
October 2003, Revision A

Copyright 2003 Sun Microsystems, Inc. 4150 Network Circle, Santa Clara, CA 95054 U.S.A. All rights reserved.

This product or document is protected by copyright and distributed under licenses restricting its use, copying, distribution, and decompilation. No part of this product or document may be reproduced in any form by any means without prior written authorization of Sun and its licensors, if any. Third-party software, including font technology, is copyrighted and licensed from Sun suppliers.

Parts of the product may be derived from Berkeley BSD systems, licensed from the University of California. UNIX is a registered trademark in the U.S. and other countries, exclusively licensed through X/Open Company, Ltd.

Sun, Sun Microsystems, the Sun logo, docs.sun.com, AnswerBook, AnswerBook2, and Solaris are trademarks, registered trademarks, or service marks of Sun Microsystems, Inc. in the U.S. and other countries. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. in the U.S. and other countries. Products bearing SPARC trademarks are based upon an architecture developed by Sun Microsystems, Inc.

The OPEN LOOK and Sun™ Graphical User Interface was developed by Sun Microsystems, Inc. for its users and licensees. Sun acknowledges the pioneering efforts of Xerox in researching and developing the concept of visual or graphical user interfaces for the computer industry. Sun holds a non-exclusive license from Xerox to the Xerox Graphical User Interface, which license also covers Sun's licensees who implement OPEN LOOK GUIs and otherwise comply with Sun's written license agreements.

Federal Acquisitions: Commercial Software—Government Users Subject to Standard License Terms and Conditions.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.

Copyright 2003 Sun Microsystems, Inc. 4150 Network Circle, Santa Clara, CA 95054 U.S.A. Tous droits réservés.

Ce produit ou document est protégé par un copyright et distribué avec des licences qui en restreignent l'utilisation, la copie, la distribution, et la décompilation. Aucune partie de ce produit ou document ne peut être reproduite sous aucune forme, par quelque moyen que ce soit, sans l'autorisation préalable et écrite de Sun et de ses bailleurs de licence, s'il y en a. Le logiciel détenu par des tiers, et qui comprend la technologie relative aux polices de caractères, est protégé par un copyright et licencié par des fournisseurs de Sun.

Des parties de ce produit pourront être dérivées du système Berkeley BSD licenciés par l'Université de Californie. UNIX est une marque déposée aux Etats-Unis et dans d'autres pays et licenciée exclusivement par X/Open Company, Ltd.

Sun, Sun Microsystems, le logo Sun, docs.sun.com, AnswerBook, AnswerBook2, et Solaris sont des marques de fabrique ou des marques déposées, ou marques de service, de Sun Microsystems, Inc. aux Etats-Unis et dans d'autres pays. Toutes les marques SPARC sont utilisées sous licence et sont des marques de fabrique ou des marques déposées de SPARC International, Inc. aux Etats-Unis et dans d'autres pays. Les produits portant les marques SPARC sont basés sur une architecture développée par Sun Microsystems, Inc.

L'interface d'utilisation graphique OPEN LOOK et Sun™ a été développée par Sun Microsystems, Inc. pour ses utilisateurs et licenciés. Sun reconnaît les efforts de pionniers de Xerox pour la recherche et le développement du concept des interfaces d'utilisation visuelle ou graphique pour l'industrie de l'informatique. Sun détient une licence non exclusive de Xerox sur l'interface d'utilisation graphique Xerox, cette licence couvrant également les licenciés de Sun qui mettent en place l'interface d'utilisation graphique OPEN LOOK et qui en outre se conforment aux licences écrites de Sun.

CETTE PUBLICATION EST FOURNIE "EN L'ETAT" ET AUCUNE GARANTIE, EXPRESSE OU IMPLICITE, N'EST ACCORDEE, Y COMPRIS DES GARANTIES CONCERNANT LA VALEUR MARCHANDE, L'APTITUDE DE LA PUBLICATION A REpondre A UNE UTILISATION PARTICULIERE, OU LE FAIT QU'ELLE NE SOIT PAS CONTREFAISANTE DE PRODUIT DE TIERS. CE DENI DE GARANTIE NE S'APPLIQUERAIT PAS, DANS LA MESURE OU IL SERAIT TENU JURIDIQUEMENT NUL ET NON AVENU.



030803@5943



Contents

Preface 5

Installing and Configuring the Sun Cluster HA for Sun ONE Application Server
9

Sun Cluster HA for Sun ONE Application Server Overview 9

 Failover Configuration Overview 10

 Multiple Masters Configuration Overview 11

Task Map: Installing and Configuring Sun Cluster HA for Sun ONE Application Server 13

Planning the Sun ONE Application Server Installation and Configuration 14

 Configuration Restrictions 14

Configuring and Activating Network Resources for Failover 15

 ▼ How to Configure and Activate Network Resources for a Failover Configuration 15

Installing and Configuring Sun ONE Application Server 17

 ▼ How to Install and Configure the Sun ONE Application Server 17

Installing and Configuring the Sun ONE Web Server Plugin 21

 ▼ How to Install and Configure the Sun ONE Web Server Plugin 21

Planning the Sun Cluster HA for Sun ONE Application Server Installation and Configuration 23

 Configuration Planning Questions 23

Installing the Sun Cluster HA for Sun ONE Application Server 23

 ▼ How to Install the Sun Cluster HA for Sun ONE Application Server Packages by Using the Web Start Program 24

 ▼ How to Install the SUNWscs1as Package by Using the scinstall Utility 25

Registering and Configuring the Sun Cluster HA for Sun ONE Application Server	26
▼ How to Register and Configure the Sun Cluster HA for Sun ONE Application Server as a Failover Data Service	27
▼ How to Register and Configure Sun Cluster HA for Sun ONE Application Server as a Service Mastered on Multiple Nodes	29
Configuring Sun Cluster HA for Sun ONE Application Server Extension Properties	31
Configuring the SUNW.HAStoragePlus Resource Type	32
Verifying the Sun Cluster HA for Sun ONE Application Server Installation and Configuration	33
▼ How to Verify the Sun Cluster HA for Sun ONE Application Server Installation and Configuration	33
Understanding Sun Cluster HA for Sun ONE Application Server Fault Monitor Extension Properties	34
Probing Algorithm and Functionality	35
Index	37

Preface

Sun Cluster 3.1 Data Service for Sun ONE Application Server Guide explains how to install and configure Sun™ Cluster HA for Sun ONE Application Server on your Sun Cluster nodes.

This document is intended for system administrators with extensive knowledge of Sun software and hardware. Do not use this document as a planning or presales guide. Before reading this document, you should have already determined your system requirements and purchased the appropriate equipment and software.

The instructions in this document assume knowledge of the Solaris™ operating environment and expertise with the volume manager software that is used with Sun Cluster.

UNIX Commands

This document contains information about commands that are specific to installing and configuring Sun Cluster data services. The document does *not* contain comprehensive information about basic UNIX® commands and procedures, such as shutting down the system, booting the system, and configuring devices. Information about basic UNIX commands and procedures is available from the following sources:

- Online documentation for the Solaris software environment
- Solaris operating environment man pages
- Other software documentation that you received with your system

Typographic Conventions

The following table describes the typographic changes used in this book.

TABLE P-1 Typographic Conventions

Typeface or Symbol	Meaning	Example
AaBbCc123	The names of commands, files, and directories; on-screen computer output	Edit your <code>.login</code> file. Use <code>ls -a</code> to list all files. <code>machine_name%</code> you have mail.
AaBbCc123	What you type, contrasted with on-screen computer output	<code>machine_name%</code> su Password:
<i>AaBbCc123</i>	Command-line placeholder: replace with a real name or value	To delete a file, type rm <i>filename</i> .
<i>AaBbCc123</i>	Book titles, new words, or terms, or words to be emphasized.	Read Chapter 6 in <i>User's Guide</i> . These are called <i>class</i> options. You must be <i>root</i> to do this.

Shell Prompts in Command Examples

The following table shows the default system prompt and superuser prompt for the C shell, Bourne shell, and Korn shell.

TABLE P-2 Shell Prompts

Shell	Prompt
C shell prompt	<code>machine_name%</code>
C shell superuser prompt	<code>machine_name#</code>
Bourne shell and Korn shell prompt	<code>\$</code>
Bourne shell and Korn shell superuser prompt	<code>#</code>

Related Documentation

Information about related Sun Cluster topics is available in the documentation that is listed in the following table.

Topic	Title	Part Number
Data service administration	<i>Sun Cluster 3.1 Data Service Planning and Administration Guide</i>	817-3305
	Sun Cluster 3.1 10/03 Data Services Collection at http://docs.sun.com/db/coll/573.11	
Concepts	<i>Sun Cluster 3.1 10/03 Concepts Guide</i>	817-0519
Software installation	<i>Sun Cluster 3.1 10/03 Software Installation Guide</i>	817-0518
System administration	<i>Sun Cluster 3.1 10/03 System Administration Guide</i>	817-0516
Hardware administration	<i>Sun Cluster 3.1 Hardware Administration Manual</i>	817-0168
	Sun Cluster 3.x Hardware Administration Collection at http://docs.sun.com/db/coll/1024.1	
Data service development	<i>Sun Cluster 3.1 10/03 Data Services Developer's Guide</i>	817-0520
Error messages	<i>Sun Cluster 3.1 10/03 Error Messages Guide</i>	817-0521
Command and function reference	<i>Sun Cluster 3.1 10/03 Reference Manual</i>	817-0522
Release information	<i>Sun Cluster 3.1 Data Services 10/03 Release Notes</i>	817-3324
	<i>Sun Cluster 3.1 10/03 Release Notes</i>	817-0638
	<i>Sun Cluster 3.x Release Notes Supplement</i>	816-3381

Accessing Sun Documentation Online

The docs.sun.comSM Web site enables you to access Sun technical documentation online. You can browse the docs.sun.com archive or search for a specific book title or subject. The URL is <http://docs.sun.com>.

Help

If you have problems installing or using Sun Cluster, contact your service provider and provide the following information:

- Your name and email address (if available)
- Your company name, address, and phone number
- The model and serial numbers of your systems
- The release number of the operating environment (for example, Solaris 8)
- The release number of Sun Cluster (for example, Sun Cluster 3.0)

Use the following commands to gather information about each node on your system for your service provider.

Command	Function
<code>prtconf -v</code>	Displays the size of the system memory and reports information about peripheral devices
<code>psrinfo -v</code>	Displays information about processors
<code>showrev -p</code>	Reports which patches are installed
<code>prtdiag -v</code>	Displays system diagnostic information
<code>scinstall -pv</code>	Displays Sun Cluster release and package version information

Also have available the contents of the `/var/adm/messages` file.

Installing and Configuring the Sun Cluster HA for Sun ONE Application Server

This chapter describes the procedures to install and configure the Sun Cluster HA for Sun ONE Application Server.

This chapter contains the following procedures.

- “How to Configure and Activate Network Resources for a Failover Configuration” on page 15
- “How to Install and Configure the Sun ONE Application Server” on page 17
- “How to Install and Configure the Sun ONE Web Server Plugin” on page 21
- “How to Install the Sun Cluster HA for Sun ONE Application Server Packages by Using the Web Start Program ” on page 24
- “How to Install the SUNWscs1as Package by Using the `scinstall` Utility” on page 25
- “How to Register and Configure the Sun Cluster HA for Sun ONE Application Server as a Failover Data Service” on page 27
- “How to Register and Configure Sun Cluster HA for Sun ONE Application Server as a Service Mastered on Multiple Nodes” on page 29
- “Configuring the SUNW.HAStoragePlus Resource Type” on page 32
- “How to Verify the Sun Cluster HA for Sun ONE Application Server Installation and Configuration” on page 33

Sun Cluster HA for Sun ONE Application Server Overview

Use the information in this section to understand how the Sun Cluster HA for Sun ONE Application Server enables Sun ONE Application Server for high availability. Consult the *Sun Cluster 3.1 Data Service Release Notes* for new Sun Cluster HA for Sun ONE Application Server installation and configuration information.

The Sun ONE Application Server provides a high-performance Java 2 Enterprise Edition (J2EE™) 1.3 compliant platform suitable for broad deployment of application services and web services. It is designed to meet the needs of enterprise customers and can run under the control of Sun Cluster software.

The current implementation of the Sun Cluster HA for Sun ONE Application Server is designed to work with the Sun ONE Application Server 7.0. The Sun ONE Message Queue is packaged with the Sun ONE Application Server installation. See *Sun Cluster 3.1 Data Service for Sun ONE Message Queue* for information about configuring the Sun ONE Message Queue for high availability.

Rich clients can directly connect to the Sun ONE Application Server. Web client connections to the Sun ONE Application Server can be directed through a front-end web server. The Sun ONE Application Server provides a pass-through plugin installation for use with the Sun ONE Web Server.

Implementation of the Sun Cluster HA for Sun ONE Application Server does not assume the existence of programs on which your architecture depends. Programs on which your architecture depends such as databases and web servers should be configured to be highly available, but can run on a different cluster.

See “Planning for Sun Cluster Data Services” in *Sun Cluster 3.1 Data Service Planning and Administration Guide* and the *Sun Cluster 3.1 Concepts Guide* for general information about data services, resource groups, resources, and other related topics.

You can configure the Sun Cluster HA for Sun ONE Application Server in either of the following ways:

- Configure the Sun Cluster HA for Sun ONE Application Server as a failover data service that is mastered on one node at a time.
- Configure the Sun Cluster HA for Sun ONE Application Server as a service that is mastered on multiple nodes at the same time.

See “How to Register and Configure the Sun Cluster HA for Sun ONE Application Server as a Failover Data Service” on page 27 and “How to Register and Configure Sun Cluster HA for Sun ONE Application Server as a Service Mastered on Multiple Nodes” on page 29 for procedural information.

Failover Configuration Overview

The Sun Cluster HA for Sun ONE Application Server is a data service with appropriate extension properties to configure a failover application server mastered by one node at a time. A domain’s administrative server can also be made highly available as a failover resource. Web clients can connect directly to the Sun ONE Application Server.

Use of the Sun ONE Application Server command-line or GUI administration tool is restricted in a clustered environment. Before you configure application instances and the administrative server into resource groups, see “Configuration Restrictions” on page 14 for information about using `asadmin` or the Sun ONE Application Server Administrative Interface in your cluster. See “Configuration Guidelines for Sun Cluster Data Services” in *Sun Cluster 3.1 Data Service Planning and Administration Guide* for more information about configuring resources and resource groups.

Use the standard configuration in this section to plan the installation and configuration of the Sun Cluster HA for Sun ONE Application Server. The Sun Cluster HA for Sun ONE Application Server might support additional configurations. However, you must contact your Enterprise Services representative for information on additional configurations.

The following figure illustrates a standard failover configuration for a Sun ONE Application Server that runs on a two-node cluster. See “Configuration Restrictions” on page 14 for additional information about configuring Sun Cluster HA for Sun ONE Application Server as a failover data service.




FIGURE 1-1 Two-Node Cluster With Failover Data Service Configuration

Multiple Masters Configuration Overview

You can also configure the Sun Cluster HA for Sun ONE Application Server to be mastered on multiple nodes at the same time. The multiple masters configuration provides scalability by using a front-end web tier to direct requests to the application servers. The pass-through plugin that the application server provides must be used with a front-end web tier to direct requests to one of the running Sun ONE Application Server instances.

A highly available Sun ONE Web Server is configured to run on the cluster listening on a logical hostname. If the web tier is running on the same cluster as the application server, the plugin should be configured to pass requests to the cluster private IP addresses. The Sun ONE Web Server instance can also be configured to run on a

different cluster. If the web tier is running on a separate cluster, the plugin is configured to pass requests to the physical hostnames of the cluster members that can run the Sun ONE Application Server resource. An example of a physical hostname is `phys-schost-1`.

The Sun Cluster HA for Sun ONE Application Server configurations that are mastered on multiple nodes can use the private interconnect to direct traffic between the Sun ONE Web Server to the Sun ONE Application Server.

Note – If you configure the Sun Cluster HA for Sun ONE Application Server as a service that is mastered on multiple nodes at the same time, you must install and configure the Sun ONE Web Server. The Sun ONE Web Server configuration must be the same on all cluster nodes.

Multiple instances of the Sun ONE Application Server can be load balanced. To enable load-balancing, install the Sun ONE Application Server plugin into the Sun ONE Web Server configuration. The Sun ONE Web Server can be configured as a failover or scalable resource when it is used as a front-end to the Sun ONE Application Server.

The Sun ONE Application Server instance is configured so that its HTTP Listeners listen on all interfaces (0.0.0.0), which is the default for Sun ONE Application Servers.

Note – For a data service mastered on multiple nodes, the IIOP listeners are not highly available.

The following figure illustrates a configuration for a Sun ONE Application Server that masters the resource on two nodes at the same time.




FIGURE 1-2 Two-Node Cluster With Data Service Mastered on Multiple Nodes

Task Map: Installing and Configuring Sun Cluster HA for Sun ONE Application Server

The following table lists the sections that describe the installation and configuration tasks. Perform these tasks in the order that they are listed.

TABLE 1-1 Task Map: Installing and Configuring the Sun Cluster HA for Sun ONE Application Server

Task	For Instructions
Plan the Sun ONE Application Server installation and configuration	"Planning the Sun ONE Application Server Installation and Configuration" on page 14
Configure and activate network resources	"How to Configure and Activate Network Resources for a Failover Configuration" on page 15
Install and configure the Sun ONE Application Server	"How to Install and Configure the Sun ONE Application Server" on page 17
Install and configure the front-end Sun ONE Web Server	"How to Install and Configure the Sun ONE Web Server Plugin" on page 21
Plan the Sun Cluster HA for Sun ONE Application Server installation and configuration	"Planning the Sun Cluster HA for Sun ONE Application Server Installation and Configuration" on page 23
Install the Sun Cluster HA for Sun ONE Application Server package	"How to Install the SUNWscs1as Package by Using the <code>scinstall</code> Utility" on page 25
Register and Configure the Sun Cluster HA for Sun ONE Application Server as a failover data service	"Registering and Configuring the Sun Cluster HA for Sun ONE Application Server" on page 26
Register and Configure Sun Cluster HA for Sun ONE Application Server as a service mastered on multiple nodes.	"How to Register and Configure Sun Cluster HA for Sun ONE Application Server as a Service Mastered on Multiple Nodes" on page 29
Configure resource extension properties	"Configuring Sun Cluster HA for Sun ONE Application Server Extension Properties" on page 31
Verify the Sun Cluster HA for Sun ONE Application Server installation and configuration	"Verifying the Sun Cluster HA for Sun ONE Application Server Installation and Configuration" on page 33
View and understand fault monitor information	"Understanding Sun Cluster HA for Sun ONE Application Server Fault Monitor" on page 34

Note – If you run multiple data services in your Sun Cluster configuration, you can set up the data services in any order, with the following exception. If the Sun Cluster HA for Sun ONE Application Server depends on Sun Cluster HA for DNS, you must set up DNS first. For details, see *Sun Cluster 3.1 Data Service for Domain Name Service (DNS)* for details. DNS software is included in the Solaris operating environment. If the cluster will obtain the DNS service from another server, configure the cluster to be a DNS client first.

Planning the Sun ONE Application Server Installation and Configuration

Before you install and configure the Sun ONE Application Server, use this section as a checklist.

Configuration Restrictions

Consider the following restrictions and requirements before you start your installation.

- Store static files and data on the local file system of each cluster node. Dynamic data should reside on the cluster file system so that you can view or update the data from any cluster node. The Sun ONE Application Server binaries and configuration files must be highly available and accessible to application server instances that are running on all nodes.
- Do not use the Sun ONE Application Server command-line or GUI administrative tools to start or stop the Sun ONE Application Server instances while application instances are running. Only use these administrative tools while application instances are running if your configuration meets the following conditions.
 - The Sun ONE Application Server is configured as a failover service mastered by one node at a time.
 - All of the application server instances of a domain, including the administrative server, are configured in one resource group.
- If you plan to use the Sun ONE Application Server as a service mastered on multiple nodes, you must set the HTTP and IIOP listeners to listen to the appropriate network resource. This setting is necessary because, by default, the Sun ONE Application Server behavior binds to all IP addresses on the node.

- If you use the Solstice DiskSuite™/Solaris Volume Manager, configure the Sun ONE Application Server software to use UNIX® file system (UFS) logging or raw-mirrored metadevices. See the Solstice DiskSuite/Solaris Volume Manager documentation for information on how to configure raw-mirrored metadevices.
- You must set up the hostnames in your name services before you begin the Sun ONE Application Server installation. You must specify a network resource (IP address) that can fail over between nodes.
- You must not remove or relocate any of the installed files or directories that the Sun ONE Application Server installation places on the cluster file system. For example, do not relocate any of the binaries that are installed with the Sun ONE Application Server software.
- You must install the binaries on the local disks.
- You must configure the network resources that clients use to access the data service and bring the logical hostnames online.

Note – If you run the Sun ONE Application Server with another application server that uses the same network resources, configure the servers to listen on different ports. Configuring the listeners on different ports prevents a port conflict between the two servers.

Configuring and Activating Network Resources for Failover

Before you install and configure the Sun ONE Application Server for a failover data service, set up the network resources that the server uses after installation and configuration. To configure and activate the network resources, use the following command-line procedure. If you are configuring the Sun ONE Application Server for a service that is mastered on multiple nodes at the same time, go to “How to Install and Configure the Sun ONE Application Server” on page 17.

▼ How to Configure and Activate Network Resources for a Failover Configuration

To perform this procedure, you need the following information about your configuration.

- The names of the cluster nodes that can master the data service.

- The hostnames that are used for configuring the network resource that clients use to access the Sun ONE Application Server. Normally, you set up this hostname when you install the cluster. See the *Sun Cluster 3.1 Concepts Guide* for details on network resources.

Note – Perform this procedure on any cluster member.

1. Become superuser on a cluster member.

2. Verify that all of the network addresses that you use have been added to your name service database.

You should have performed this verification during the Sun Cluster installation. See the planning chapter in the *Sun Cluster 3.1 Software Installation Guide*.

Note – To avoid name service look-up failures, ensure that all of the logical hostnames are present in the `/etc/inet/hosts` file on all of the cluster nodes. Configure name service mapping in the `/etc/nsswitch.conf` file on the servers to check the local files before trying to access NIS, NIS+, or DNS.

3. Create a failover resource group to contain the network and application resources.

```
# scrgadm -a -g resource-group [-h nodelist]
```

`-g resource-group` Specifies the name of the resource group. This name can be your choice.

`[-h nodelist]` Specifies an optional comma-separated list of physical node names that identify potential masters. The order here determines the order in which the nodes are considered primary during failover.

Note – Use the `-h` option to specify the order of the node list. If all of the nodes in the cluster are potential masters, you do not need to use the `-h` option.

4. Add network resources to the resource group.

Use the following command to add a logical hostname to a resource group.

```
# scrgadm -a -L -g resource-group -l hostname, ... [-n netiflist]
```

`-L` Specifies that a network resource is being added.

`-g resource-group` Specifies the name of the resource group.

- `-l hostname, ...` Specifies a comma-separated list of network resources.
- `-n netiflist` Specifies an optional, comma-separated list that identifies the IP Networking Multipathing groups that are on each node.

Note – Each element in *netiflist* must be in the form of *netif@node*. *netif* can be given as an IP Networking Multipathing group name, such as *sc_ipmp0*. The node can be identified by the node name or node ID, such as *sc_ipmp0@1* or *sc_ipmp@phys-schost-1*. Sun Cluster does not currently support the use of the adapter name for *netif*.

5. Run the `scswitch` command to enable the resource group and bring the resource group online.

```
# scswitch -Z -g resource-group
```

`-Z` Moves the resource group to the `MANAGED` state, and brings the resource group online

`-g resource-group` Specifies the name of the resource group

Installing and Configuring Sun ONE Application Server

This section describes installation of the Sun ONE Application Server by using the Sun ONE `setup` command. Only the sections that are specific to the Sun Cluster HA for Sun ONE Application Server are included here. See the Sun ONE Application Server 7 documentation for detailed installation instructions including patch requirements.

Use the following procedure to install the Sun ONE Application Server.

▼ How to Install and Configure the Sun ONE Application Server

1. Become superuser on a cluster member.
2. Determine if you are installing the Sun ONE Application Server on Solaris 8.

- If no, proceed to Step 4.
- If yes, perform the following operations:
 - a. **Run the `setup` command from the install directory for the Sun ONE Application Server on all cluster nodes.**
 - b. **Provide the default location for Sun ONE Application Server instances at the `setup` command prompt.**
 Place the server configuration directory on a local filesystem by using the default directory, `/var/opt/SUNWappserver7`. When you create server instances that are managed by Sun Cluster, specify a path to the global file system or HAStoragePlus file system. Ensure that all potential masters of a Sun ONE Application Server instance have access to the Sun ONE Application Server instance configuration files.

Note – The domain created by the `setup` command cannot be used by Sun Cluster.

3. **If you are installing the Sun ONE Application Server on Solaris 8, proceed to Step 5.**
4. **If you are installing the Sun ONE Application Server packaged with Solaris 9, perform the following operations:**
 - a. **Install the Sun ONE Application Server packages on all the nodes of the cluster.**
 - b. **Identify a location on a global file system where you intend to keep the application server configuration files.**
 You can create a separate directory for this file system.

5. **(Optional) On all nodes, create a link to the server configuration directory on the global file system from the default configuration directory.**
 You can either create a link to the server configuration directory or specify the full path to the location on the global file system when you create the Sun ONE Application Server domains in Step 8.

[To create a link for the Sun ONE Application Server packaged with Solaris 9]
`# ln -s /var/appserver /global/appserver`

[To create a link for the unpackaged Sun ONE Application Server]
`# ln -s /var/opt/SUNWappserver7 /global/appserver`

6. **If you are installing the Sun ONE Application Server on Solaris 8, proceed to Step 8.**

7. If you are installing the Sun ONE Application Server packaged with Solaris 9, perform the following operations on all nodes:

a. List the Sun ONE Application Server run control scripts.

```
# ls -l /etc/rc?.d/*appserv
/etc/rc0.d/K05appserv
/etc/rc1.d/K05appserv
/etc/rc2.d/K05appserv
/etc/rc3.d/S84appserv
/etc/rcS.d/K05appserv
```

b. Rename the Sun ONE Application Server run control scripts.

Renaming the run control scripts disables the START and STOP run control scripts that you installed as part of the SUNWasr package (or the SUNWasro package if the unbundled Sun ONE Application Server was installed). This step is necessary because Sun Cluster HA for Sun ONE Application Server starts and stops the Sun ONE Application Server instances after you have configured the data service.

```
# mv /etc/rc0.d/K05appserv /etc/rc0.d/k05appserv
# mv /etc/rc1.d/K05appserv /etc/rc1.d/k05appserv
# mv /etc/rc2.d/K05appserv /etc/rc2.d/k05appserv
# mv /etc/rc3.d/S85appserv /etc/rc3.d/s85appserv
# mv /etc/rcS.d/K05appserv /etc/rcS.d/k05appserv
```

Note – The preceding example changes the first letter in the name of the run control script from uppercase to lowercase. However, you can rename the scripts to be consistent with your normal administration practices.

c. Verify that all of the Sun ONE Application Server run control scripts have been renamed.

```
# ls -l /etc/rc?.d/*appserv
/etc/rc0.d/k05appserv
/etc/rc1.d/k05appserv
/etc/rc2.d/k05appserv
/etc/rc3.d/s85appserv
/etc/rcS.d/k05appserv
```

8. Create a domain with configuration information on the global file system.

```
# asadmin create-domain --path /global/appserver --adminport=4848 \
--adminuser admin --adminpassword password scdomain
```

9. Start the domains administrative server.

```
# /global/appserver/domains/scdomain/admin-server/bin/startserv
```

10. Create new application servers to be made highly available by using the administrative server.

11. Create a log directory on the local disk for each node that the Sun ONE Application Server uses.

For the Sun ONE Application Server to work correctly, the log directory must be located on each node of the cluster, not on the cluster file system. Choose a location on the local disk that is the same for all the nodes in the cluster.

```
schost-1# mkdir -p /var/pathname/domain/instance/logs/
```

Note – If you anticipate large log files, ensure that the file system containing the directory has enough space to handle the files.

12. Change the location of the Sun ONE Application Server `PidLog` to reflect the directory that you created in Step 11. To change the location, edit the `init.conf` file located in the server configuration directory.

13. Change the location of `PID_FILE` in the `stopserv` file to match the value of `PidLog` that you set in Step 12.

14. Change the location of the `Log File`, `Log Root`, and `Transaction Log Location` parameters to reflect the directory that you created in Step 11. To change these parameters, use the Sun ONE Application Server Administrative Interface. See “Configuring the Log Service” in *Sun ONE Application Server 7 Collection (Solaris Edition) Administrator’s Guide* for instructions.

15. Change the location of the `accesslog` parameter to reflect the directory that you created in Step 11. To change this parameter, use the `asadmin` utility. The following is an example of the `asadmin` command used to change the location of `accesslog`. See *Sun ONE Application Server 7 Administrator’s Guide* for additional instructions.

```
% asadmin
asadmin> set server1.virtual-server.server1.property.accesslog=
"/var/pathname/domain/instance/logs/accesslog"
```

16. Ensure that any logical hostnames that the application server uses are configured and are online.

17. If the application server is configured as a failover service, configure the HTTP listener IP address with the logical IP address and the server name with the logical hostname. If the application server is configured as a service mastered on multiple nodes, proceed to Step 18.

This operation must be performed on the primary node of the logical host.

18. Verify that the HTTP listener is returning the correct server name.

The correct server name is usually the hostname that clients will use to access the resources on the application server.

- 19. If the application server is configured as a failover service, configure the IIOP listener with the logical IP address for the Sun Cluster HA for Sun ONE Application Server. If the application server is configured as a service mastered on multiple nodes, proceed to Step 20.**

If the administrative server is to be made highly available, configure only the HTTP listener, the administrative server does not have an IIOP listener.

- 20. Disable the Sun ONE Application Server startup of the Message Queue server by unchecking `Start Enable` for the services under JMS.**

- 21. Start the application server by issuing the `startserv` command.**

```
# /global/appserver/domains/scdomain/server1/bin/startserv
```

If the server does not start, correct the problem. See the Sun ONE Application Server 7 documentation for details.

- 22. Stop the application server by issuing the `stopserv` command.**

```
# /global/appserver/domains/scdomain/server1/bin/stopserv
```

You must stop the server before you proceed to the next part of the installation and configuration process.

Installing and Configuring the Sun ONE Web Server Plugin

This procedure describes installation of the pass-through plugin for configuration with Sun ONE Application Server. Only the sections that are specific to Sun Cluster HA for Sun ONE Application Server are included here. See the Sun ONE Application Server 7 documentation for detailed installation instructions including patch requirements.

▼ How to Install and Configure the Sun ONE Web Server Plugin

- 1. Install the Sun ONE Web Server plugin by using the Sun ONE Application Server 7 documentation.**

2. Are you configuring Sun Cluster HA for Sun ONE Application Server as a failover data service?

If you are configuring Sun Cluster HA for Sun ONE Application Server as a failover data service, installation of the front-end Sun ONE Web Server is optional.

- If no, proceed to Step 3
- If yes, configure the Sun ONE Web Server logical hostname as the server in the pass-through *object* in the `obj.conf` file and proceed to “Planning the Sun Cluster HA for Sun ONE Application Server Installation and Configuration” on page 23.

```
# Service type=magnus-internal/passthrough fn=service-passthrough \  
servers="http://foo-lh-1:80/"
```

3. Is the web server running on the same cluster as the application server?

- If no, proceed to Step 4
- If yes, perform the following operation and proceed to “Planning the Sun Cluster HA for Sun ONE Application Server Installation and Configuration” on page 23:

a. Configure the Sun ONE Web Server plugin with the cluster private IP addresses.

```
# Service type=magnus-internal/passthrough fn=service-passthrough \  
servers="http://172.16.193.1:80/ http://172.16.193.2:80/"
```

Note – You must use the interconnect IP addresses in the plugin configuration. Note that equivalent hostnames such as `clusternode1-priv` do not work in this configuration, and should not be used.

4. Configure the Sun ONE Web Server with the physical hostnames.

```
# Service type=magnus-internal/passthrough fn=service-passthrough \  
servers=http://172.16.193.1:80/ http://172.16.193.2:80/ \  
 \
```

The preceding example assumes that the Sun ONE Application Server instances are configured on port 80 on cluster nodes one and two.

Planning the Sun Cluster HA for Sun ONE Application Server Installation and Configuration

This section contains planning questions for the Sun Cluster HA for Sun ONE Application Server installation and configuration.

Configuration Planning Questions

Use the questions in this section to plan the installation and configuration of Sun Cluster HA for Sun ONE Application Server .

- Will you run Sun Cluster HA for Sun ONE Application Server as a failover data service or as a service mastered on multiple nodes at the same time?
- What resource groups will you use for network addresses, application resources, and the dependencies between network addresses and application resources?
- What is the logical hostname that clients use to access the data service?
- Where will the system configuration files reside?

Installing the Sun Cluster HA for Sun ONE Application Server

If you did not install the Sun Cluster HA for Sun ONE Application Server packages during your initial Sun Cluster installation, perform this procedure to install the packages. Perform this procedure on each cluster node where you are installing the Sun Cluster HA for Sun ONE Application Server packages. To complete this procedure, you need the Sun Cluster Agents CD-ROM.

If you are installing more than one data service simultaneously, perform the procedure in "Installing the Software" in *Sun Cluster 3.1 10/03 Software Installation Guide*.

Install the Sun Cluster HA for Sun ONE Application Server packages by using one of the following installation tools:

- The Web Start program

- The `scinstall` utility

Note – The Web Start program is *not* available in releases earlier than Sun Cluster 3.1 Data Services 10/03.

▼ How to Install the Sun Cluster HA for Sun ONE Application Server Packages by Using the Web Start Program

You can run the Web Start program with a command-line interface (CLI) or with a graphical user interface (GUI). The content and sequence of instructions in the CLI and the GUI are similar. For more information about the Web Start program, see the `installer(1M)` man page.

1. **On the cluster node where you are installing the Sun Cluster HA for Sun ONE Application Server packages, become superuser.**
2. **(Optional) If you intend to run the Web Start program with a GUI, ensure that your `DISPLAY` environment variable is set.**
3. **Load the Sun Cluster Agents CD-ROM into the CD-ROM drive.**
If the Volume Management daemon `vold(1M)` is running and configured to manage CD-ROM devices, it automatically mounts the CD-ROM on the `/cdrom/scdataservices_3_1_vb` directory.

4. **Change to the Sun Cluster HA for Sun ONE Application Server component directory of the CD-ROM.**

The Web Start program for the Sun Cluster HA for Sun ONE Application Server data service resides in this directory.

```
# cd /cdrom/scdataservices_3_1_vb/\
components/SunCluster_HA_SunONE_Application_Server_3.1
```

5. **Start the Web Start program.**

```
# ./installer
```
6. **When you are prompted, select the type of installation.**
 - To install only the C locale, select Typical.
 - To install other locales, select Custom.
7. **Follow instructions on the screen to install the Sun Cluster HA for Sun ONE Application Server packages on the node.**

After the installation is finished, the Web Start program provides an installation summary. This summary enables you to view logs that the Web Start program created during the installation. These logs are located in the `/var/sadm/install/logs` directory.

8. **Exit the Web Start program.**
9. **Unload the Sun Cluster Agents CD-ROM from the CD-ROM drive.**
 - a. **To ensure that the CD-ROM is not being used, change to a directory that does *not* reside on the CD-ROM.**
 - b. **Eject the CD-ROM.**

```
# eject cdrom
```

▼ How to Install the SUNWscs1as Package by Using the `scinstall` Utility

You need the Sun Cluster 3.1 Agents CD-ROM to complete this procedure. Perform this procedure on all cluster members that can master Sun Cluster HA for Sun ONE Application Server.

1. **Load the Sun Cluster 3.1 Agents CD-ROM into the CD-ROM drive.**
2. **Run the `scinstall` utility with no options.**

This step starts the `scinstall` utility in interactive mode.
3. **Choose the menu option, Add Support for New Data Service to This Cluster Node.**

The `scinstall` utility prompts you for additional information.
4. **Provide the path to the Sun Cluster 3.1 Agents CD-ROM.**

The `scinstall` utility refers to the CD as the “data services cd.”
5. **Specify the data service to install. Choose S1AS. S1AS may be on the list of unsupported data services that is displayed after the list of supported data services.**

The `scinstall` utility lists the data service that you selected and asks you to confirm your choice.
6. **Exit the `scinstall` utility.**
7. **Unload the CD from the drive.**

Registering and Configuring the Sun Cluster HA for Sun ONE Application Server

The following procedures describe how to use the `scrgadm` command to register and configure the Sun Cluster HA for Sun ONE Application Server. The Sun Cluster HA for Sun ONE Application Server can be configured as a failover data service or as a service that is mastered by multiple nodes at the same time.

Note – See “Tools for Data Service Resource Administration” in *Sun Cluster 3.1 Data Service Planning and Administration Guide* for general information about registering and configuring data services.

To perform these procedures, you need the following information about your configuration.

- The resource type name for the Sun Cluster HA for Sun ONE Application Server, `SUNW.s1as`.
- The names of the cluster nodes that can master the data service.
- If you configure Sun Cluster HA for Sun ONE Application Server as a failover data service, you must know the network resource that clients use to access the Sun Cluster HA for Sun ONE Application Server. Normally, you set up this network resource when you install the cluster. See “Standard Versus Clustered Client/Server Configuration” in *Sun Cluster 3.1 Concepts Guide* for details on network resources.
- The ports where the Sun ONE Application Server listens including HTTP and IIOP listeners.
- The path to the server configuration data for the Sun ONE Application Server instance.

▼ How to Register and Configure the Sun Cluster HA for Sun ONE Application Server as a Failover Data Service

Perform the following steps to complete a Sun Cluster HA for Sun ONE Application Server failover configuration. You can also use this procedure to configure a domains administrative server to be a failover resource.

1. Become superuser on a cluster member.
2. Add a resource group for Sun ONE Application Server if you have not performed the steps in “Configuring and Activating Network Resources for Failover” on page 15.

```
# scrgadm -a -g resource-group [-h nodelist]
```

3. Add the logical hostname resource to the resource group if you have not performed the steps in “Configuring and Activating Network Resources for Failover” on page 15.

```
# scrgadm -a -L -g resource-group -l logical-hostname
```

4. Register the resource type for the data service.

```
# scrgadm -a -t SUNW.slas
```

-a Adds the data service resource type

-t SUNW.slas Specifies the predefined resource type name

5. Add the application server resource instance to the failover resource group that you created for your network resources.

```
# scrgadm -a -j resource -g resource-group \  
-t SUNW.slas \  
-x Confdir_list=install-directory/domains/domain/server \  
-y Network_resources_used=logical hostname \  
-y Port_list=port/tcp,port/tcp \  
-x Monitor_uri_list=http://logical-hostname[:port][path]
```

The resource group that contains the application resources is the same resource group that you created for your network resources in “Creating a Resource Group” in *Sun Cluster 3.1 Data Service Planning and Administration Guide*.

-j resource

Specifies the Sun ONE Application Server application resource name.

-y Network_resources_used=network-resource

Specifies a comma-separated list of network resources in *resource-group*.

-t SUNW.slas

Specifies the type of resource to add.

-x Confdir_list=install-directory/**domains**/domain/server

Specifies a path for your Sun ONE Application Server configuration directory. The `Confdir_list` extension property is required and must have exactly one entry.

- y `Port_list=port-number/protocol`
Specifies a comma-separated list of the port number and the protocol to be used, for example, `80/tcp`. If the `Monitor Uri_list` is set, the `Port_list` setting is optional.
- x `Monitor Uri_list=logical-hostname[:port][[/path]`
Specifies a comma-separated list of URIs from which Sun Cluster HA for Sun ONE Application Server makes requests. The `Monitor Uri_list` extension property is required if the `Port_list` property is not set.

6. Bring the resource group online.

- ```
scswitch -Z -g resource-group
```
- Z Enables the resource and its monitor.
  - g `resource-group` Specifies the name of the application resource group that is being enabled.

#### 7. Verify that the resource group and application server resource is online.

- ```
# scstat -g  
# ps -ef
```

Example—Registering and Configuring Sun Cluster HA for Sun ONE Application Server as a Failover Data Service

This example shows how to register Sun Cluster HA for Sun ONE Application Server as a failover data service.

Cluster Information

Node names: phys-schost-1, phys-schost-2

Logical hostname: schost-1

Resource group: appsrv-rg (for all resources)

Resources: schost-1 (logical hostname),

SUNW.s1as (Sun ONE Application Server application resource)

(Create a failover resource group.)

```
# scrgadm -a -g appsrv-rg -h phys-schost-1,phys-schost-2
```

(Add a logical hostname resource to the resource group.)

```
# scrgadm -a -L -g appsrv-rg -l schost-1
```

(Register the SUNW.s1as resource type.)

```
# scrgadm -a -t SUNW.s1as
```

(Create a Sun ONE Application Server resource and add it to the resource group.)

```
# scrgadm -a -j appsrv-rs -g appsrv-rg \
```

```

-t SUNW.slas \
-x Confdir_list=/global/appsrv/domains/scdomain/server1 \
-y Network_resources_used=schost-1 \
-y Port_list=80/tcp,3700/tcp \
-x Monitor Uri_list=http://schost-1:80/servlet/monitor

```

(Bring the application resource group online.)

```
# scswitch -Z -g appsrv-rg
```

Example—Registering and Configuring the admin-server as a Failover Data Service

This example shows how the `admin-server` can be configured as part of the failover resource group created in the above example.

Cluster Information

Node names: *phys-schost-1, phys-schost-2*

Logical hostname: *schost-1*

Resource group: *appsrv-rg* (for all resources)

Resources: *schost-1* (logical hostname),

(Create a Sun ONE Application Server resource and add it to the resource group.)

```

# scrgadm -a -j admin-rs -g appserv-rg \
-t SUNW.slas \
-x Confdir_list=/global/appsrv/domains/scdomain/admin-server \
-y Network_resources_used=schost-1 \
-y Port_list=4848/tcp \
-x Monitor Uri_List=http://schost-1:4848

```

▼ How to Register and Configure Sun Cluster HA for Sun ONE Application Server as a Service Mastered on Multiple Nodes

This procedure assumes that you installed the data service packages during your initial Sun Cluster HA for Sun ONE Application Server installation. If you did not install the Sun ONE Application Server packages as part of your initial installation, go to “How to Install the SUNWscslas Package by Using the `scinstall` Utility” on page 25 to install the data service packages.

Before you begin to register and configure Sun Cluster HA for Sun ONE Application Server as a service mastered on multiple nodes at the same time, consider the following requirements.

- You must have the Sun ONE Web Server Plugin installed and configured. See “Installing and Configuring the Sun ONE Web Server Plugin” on page 21.

- You must specify at least one entry for the `Monitor_URI_List` extension property. If there are no deployed applications that need to be monitored, use a simple Uniform Resource Identifier (URI) such as `http://localhost/`.

See “Multiple Masters Configuration Overview” on page 11 for conceptual information related to this procedure.

Note – Do not use the Sun ONE Application Server command-line or GUI administrative tools to start or stop the Sun ONE Application Server instances. The Sun ONE Application Server administrative server might not display the correct status of an application server instance that is configured as a service mastered on multiple nodes.

1. Become superuser on one of the nodes in the cluster that hosts the application server.

2. Add a resource group for the Sun ONE Application Server.

```
# scrgadm -a -g resource-group \  
-y Maximum primaries=value \  
-y Desired primaries=value [-h nodelist]
```

3. Register the resource type for the Sun ONE Application Server.

```
# scrgadm -a -t SUNW.slas
```

4. Add the Sun ONE Application Server resource instance to the resource group.

```
# scrgadm -a -j resource -g resource-group -t SUNW.slas -x  
Confdir_list=install-directory/domains/domain/server -x  
Monitor Uri List=http://localhost[:port][path]
```

```
-j resource
```

Specifies the Sun ONE Application Server application resource name.

```
-t SUNW.slas
```

Specifies the type of resource to add.

```
-x Confdir_list=install-directory/domains/domain/server
```

Specifies a path for your Sun ONE Application Server configuration directory. The `Confdir_list` extension property is required and must have exactly one entry.

```
-x Monitor Uri list=localhost[:port][path]
```

Specifies URIs from which Sun Cluster HA for Sun ONE Application Server makes requests. The `Monitor Uri_list` extension property is required.

5. Verify installation and configuration of the front-end web tier.

See “How to Install and Configure the Sun ONE Web Server Plugin” on page 21 for procedural information.

6. Enable the scalable resource group and its monitor.

```
# scswitch -Z -g resource-group
```

-Z Enables the resource and its monitor.

-g *resource-group* Specifies the name of the application resource group that is being enabled.

EXAMPLE 1-1 Registering and Configuring Sun Cluster HA for Sun ONE Application Server As a Service Mastered on Multiple Nodes

This example shows how to register Sun Cluster HA for Sun ONE Application Server as a service mastered on two nodes at the same time.

Cluster Information

Node names: *phys-schost-1, phys-schost-2*

Resource group: *appsrv-rg* (for all resources)

(Create a scalable resource group.)

```
# scrgadm -a -g appserv-rg -y Maximum primaries=2 \  
-y Desired primaries=2 -h phys-schost-1,phys-schost-2
```

(Register the SUNW.s1as resource type.)

```
# scrgadm -a -t SUNW.s1as
```

(Create a Sun ONE Application Server resource and add it to the resource group.)

```
# scrgadm -a -j appsrv-rs -g appserv-rg -t SUNW.s1as \  
-x Confdir_list=/global/appserver/domains/scdomain/server1 \  
-x Monitor Uri_list=http://localhost:8000/servlet/monitor
```

(Enable the application resource group.)

```
# scswitch -Z -g appserv-rg
```

Configuring Sun Cluster HA for Sun ONE Application Server Extension Properties

Use the command-line `scrgadm -x parameter=value` to configure extension properties when you create the Sun ONE Application Server resource. See the SUNW.s1as(5M) man page for more information about extension properties. See “Standard Properties” in *Sun Cluster 3.1 Data Service Planning and Administration Guide* for details on all Sun Cluster Data Service properties.

Table 1–2 describes the extension properties that you can configure for Sun Cluster HA for Sun ONE Application Server. The only required extension property for creating a Sun Cluster HA for Sun ONE Application Server resource is the `Confdir_list` property. The `Confdir_list` property specifies a directory in which the Sun ONE Application Server configuration files reside. The Tunable entries indicate if you can update the property dynamically or if you can only update the property at creation.

TABLE 1–2 Sun Cluster HA for Sun ONE Application Server Extension Properties

Name/Data Type	Description
Confdir_list (string array)	<p>The path that contains the configuration for a particular Sun ONE Application Server instance. This property must contain one entry.</p> <p>Default: None</p> <p>Range: None</p> <p>Tunable: At creation</p>
Monitor Uri List (string array)	<p>URIs from which the agent gets HTTP requests that the Monitor Uri List property specifies.</p> <p>Default: None</p> <p>Range: None</p> <p>Tunable: Any time</p>

Configuring the SUNW.HAStoragePlus Resource Type

The `SUNW.HAStoragePlus` resource type performs the same functions as `SUNW.HAStorage`, and synchronizes actions between HA storage and the data service.

`SUNW.HAStoragePlus` also has an additional feature to make a local file system highly available. Configuration of the `SUNW.HAStoragePlus` resource type is optional for Sun Cluster HA for Sun ONE Application Server.

See the `SUNW.HAStoragePlus(1)` man page and “Synchronizing the Startups Between Resource Groups and Disk Device Groups” in *Sun Cluster 3.1 Data Service Planning and Administration Guide* for background information.

Verifying the Sun Cluster HA for Sun ONE Application Server Installation and Configuration

This section contains the procedure to verify correct installation of Sun Cluster HA for Sun ONE Application Server.

▼ How to Verify the Sun Cluster HA for Sun ONE Application Server Installation and Configuration

Use this procedure to verify the Sun Cluster HA for Sun ONE Application Server installation and configuration.

1. Start the Sun ONE Application Server under the control of Sun Cluster software.

```
# scswitch -z -g resource-group
```

2. Connect to the Sun ONE Application Server using a web browser, and verify that the Sun ONE Application Server software functions correctly.

3. Run the `scswitch` command to switch the resource group to another cluster node, such as `node2`.

```
# scswitch -z -g resource-group -h node2
```

4. Verify that the resource group and the Sun ONE Application Server resource is online.

```
# scstat -g  
# ps -ef
```

5. Repeat Step 2 and Step 3 on all of the potential primaries of the Sun ONE Application Server resource groups.

Note – After installation, use only the cluster administration command `scswitch(1M)` to manually start and stop Sun ONE Application Server. After you start Sun ONE Application Server, it runs under the control of Sun Cluster software.

Understanding Sun Cluster HA for Sun ONE Application Server Fault Monitor

Use the information in this section to understand the Sun Cluster HA for Sun ONE Application Server Fault Monitor.

This section provides the following information.

- Description of the Sun Cluster HA for Sun ONE Application Server Fault Monitor's probing functionality.
- Conditions, messages, and recovery actions associated with unsuccessful probing.
- Conditions and messages associated with successful probing.

Extension Properties

The Sun Cluster HA for Sun ONE Application Server Fault Monitor uses the following extension properties. You might be able to tune these extension properties.

TABLE 1-3 Sun Cluster HA for Sun ONE Application Server Extension Properties

Name/Data Type	Description
Confdir_list (string array)	The complete path to the Sun ONE Application Server configuration directory is set in this extension property. Default: None Tunable: At creation
Monitor Uri List (string)	A Single URI or list of URIs which can be used by the fault monitor to test the functionality of the Sun ONE Application Server. The fault monitor tests the application server by doing an HTTP GET on the URI. The Monitor Uri List extension property can be used to probe deployed application functionality. Probe deployed applications by setting the property to one or more URIs that are serviced by applications deployed on the Sun ONE Application Server. If the HTTP server return code is 500 (Internal Server Error) or if the connect fails, the probe will take action. See the probe method for more details. Default: Null Tunable: Any time

Probing Algorithm and Functionality

The Sun Cluster HA for Sun ONE Application Server probe sends a request to the server to query the health of the Sun ONE Application Server server. The probe executes the following steps:

1. Probes the Sun ONE Application Server instance according to the time-out value set with the `Probe_timeout` resource property.
2. Connects to the IP address and port combinations defined by the network resource configuration and the `Port_list` setting for the resource group. If the resource is configured without an empty `Port_list` this step is skipped. If connection succeeds, the probe disconnects. If the connection fails, the failure is recorded.

Heavy network traffic, heavy system load, and misconfiguration can cause the query to fail. Misconfiguration can occur if you did not configure the Sun ONE Application Server server to listen on all of the IP address/port combinations that are probed. The Sun ONE Application Server server should service every port for every IP address that is specified for the resource.

3. Connects to the Sun ONE Application Server server and performs an HTTP 1.1 GET check by sending a HTTP request and receiving a response to each of the URIs in `Monitor Uri List`.

The result of the HTTP requests is either failure or success. If all of the requests successfully receive a reply from the Sun ONE Application Server server, the probe returns and continues the next cycle of probing and sleeping.

Heavy network traffic, heavy system load, and misconfiguration can cause the HTTP GET probe to fail. Misconfiguration of the `Monitor Uri List` property can cause a failure if a URI in the `Monitor Uri List` includes an incorrect port or hostname. For example, if the application server instance is listening on logical host `schost-1` and the URI was specified as `http://schost-2/servlet/monitor`, the probe will try to contact `schost-2` to request `/servlet/monitor`.

4. Records a failure in the history log if the reply to the probe is not received within the `Probe_timeout` limit. The probe considers this scenario a failure on the part of the Sun ONE Application Server data service. A Sun ONE Application Server probe failure can be a complete failure or a partial failure.

If the reply to the probe is received within the `Probe_timeout` limit, the HTTP response code is checked. If the response code is 500 "Internal Server Error", the probe is considered a complete failure. All other response codes are ignored.

The following are complete probe failures.

- The following error message is received upon failure to connect to the server. The `%s` indicates the hostname and `%d` indicates the port number.

```
Failed to connect to the host <%s> and port <%d>. Receiving a
response code of 500 "Internal Server Error" HTTP GET
Response Code for probe of %s is 500. Failover will be in
progress
```

- The following error message is received upon failure to successfully send the probe string to the server. The first %s indicates the hostname, the %d indicates the port number, and the second %s indicates further details about the error.

Write to server failed: server %s port %d: %s.

5. The monitor accumulates partial failures that occur within the `Retry_interval` resource property setting until they equal a complete failure.

The following are partial probe failures:

- The following error message is received when there is a failure to disconnect before the `Probe_timeout` setting lapses. The first %d indicates the port number and the %s indicates the resource name.

Failed to disconnect from port %d of resource %s.

- Failure to complete all probe steps within `Probe_timeout` time is a partial failure.
- The following error message is received when there is a failure to read data from the server for other reasons. The first %s indicates the hostname and %d indicates the port number. The second %s indicates further details about the error.

Failed to communicate with server %s port %d: %s

6. Based on the history of failures, a failure can cause either a local restart or a failover of the data service.

Index

A

asadmin command, create-domain, 19
asadmin utility, 11

C

C locale, 24
commands
 asadmin, 19
 node information, 8
 scswitch, 17
 setup, 18
 startserv, 19, 21
 stopserv, 21
configuration restrictions, 14
configuring
 Failover Sun Cluster HA for Sun ONE
 Application Server, 27
 network resources, 15
 Sun Cluster HA for Sun ONE Application
 Server as a service mastered on multiple
 nodes, 29
 SUNW.HAStoragePlus resource type, 32

D

disabling START and STOP,
 /etc/rc0.d/k05appserv, 19

E

/etc/inet/hosts file, 16
/etc/nsswitch file, 16
extension properties, 35

F

failover configuration overview, 10
fault monitor, 34
files
 /etc/inet/hosts, 16
 init.conf file, 20
 installation logs, 25
 /var/opt/appserver, 18
 /var/opt/SUNWappserver7, 18

I

init.conf file, 20
installing
 Sun Cluster HA for Sun ONE Application
 Server
 by using Web Start program, 24
 log files created, 25
 Sun ONE Application Server, 17
 Sun ONE Web Server Plugin, 21
 SUNWscslas, 25

L

locales, 24
log files, installation, 25

M

multiple masters configuration, 29
multiple masters overview, 11

N

network resource configuration, 15

P

parameters
 PidLog, 20
planning
 Sun Cluster HA for Sun ONE Application
 Server installation, 23
 Sun ONE Application Server installation, 14
probe failure error messages, 35
prtconf -v command, 8
prtdiag -v command, 8
psrinfo -v command, 8

R

renaming run control scripts,
 /etc/rc0.d/k05appserv, 19
restrictions, 14

S

scalable, *See* multiple masters configuration
scinstall -pv command, 8
scswitch command, 17
setup command, 18
showrev -p command, 8
startserv command, 19, 21
stopserv command, 21

Sun Cluster HA for Sun ONE Application
Server

 configuring for failover, 27
 configuring for multiple masters, 29
 extension properties, 32, 35
 fault monitor, 34
 installation task map, 13
 overview, 9

Sun ONE Application Server
installation, 14, 17

Sun ONE Web Server Plugin, installation, 21

SUNW.HAStoragePlus resource type,
 configuring for Sun Cluster HA for Sun ONE
 Application Server, 32

SUNWscs1as package installation, 25

V

/var/sadm/install/logs directory, 25
/var/opt/appserver file, 18
/var/opt/SUNWappserver7 file, 18

W

Web Start program, 24