



# Sun™ Management Center 3.5 Version 6 Release Notes for Sun Fire™ Entry-Level Midrange Systems

---

Sun Microsystems, Inc.  
[www.sun.com](http://www.sun.com)

Part No. 819-0795-11  
August 2005, Revision A

Submit comments about this document at: <http://www.sun.com/hwdocs/feedback>

Copyright 2005 Sun Microsystems, Inc., 4150 Network Circle, Santa Clara, California 95054, U.S.A. All rights reserved.

Sun Microsystems, Inc. has intellectual property rights relating to technology that is described in this document. In particular, and without limitation, these intellectual property rights may include one or more of the U.S. patents listed at <http://www.sun.com/patents> and one or more additional patents or pending patent applications in the U.S. and in other countries.

This document and the product to which it pertains are distributed under licenses restricting their use, copying, distribution, and decompilation. No part of the product or of this document may be reproduced in any form by any means without prior written authorization of Sun and its licensors, if any.

Third-party software, including font technology, is copyrighted and licensed from Sun suppliers.

Parts of the product may be derived from Berkeley BSD systems, licensed from the University of California. UNIX is a registered trademark in the U.S. and in other countries, exclusively licensed through X/Open Company, Ltd.

Sun, Sun Microsystems, the Sun logo, docs.sun.com, Sun Management Center, Sun Fire, Netra, Java, and Solaris are trademarks or registered trademarks of Sun Microsystems, Inc. in the U.S. and in other countries.

All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. in the U.S. and in other countries. Products bearing SPARC trademarks are based upon an architecture developed by Sun Microsystems, Inc.

The OPEN LOOK and Sun™ Graphical User Interface was developed by Sun Microsystems, Inc. for its users and licensees. Sun acknowledges the pioneering efforts of Xerox in researching and developing the concept of visual or graphical user interfaces for the computer industry. Sun holds a non-exclusive license from Xerox to the Xerox Graphical User Interface, which license also covers Sun's licensees who implement OPEN LOOK GUIs and otherwise comply with Sun's written license agreements.

U.S. Government Rights—Commercial use. Government users are subject to the Sun Microsystems, Inc. standard license agreement and applicable provisions of the FAR and its supplements.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.

---

Copyright 2005 Sun Microsystems, Inc., 4150 Network Circle, Santa Clara, Californie 95054, Etats-Unis. Tous droits réservés.

Sun Microsystems, Inc. a les droits de propriété intellectuels relatifs à la technologie qui est décrite dans ce document. En particulier, et sans la limitation, ces droits de propriété intellectuelle peuvent inclure un ou plus des brevets américains énumérés à <http://www.sun.com/patents> et un ou les brevets plus supplémentaires ou les applications de brevet en attente dans les Etats-Unis et dans les autres pays.

Ce produit ou document est protégé par un copyright et distribué avec des licences qui en restreignent l'utilisation, la copie, la distribution, et la décompilation. Aucune partie de ce produit ou document ne peut être reproduite sous aucune forme, par quelque moyen que ce soit, sans l'autorisation préalable et écrite de Sun et de ses bailleurs de licence, s'il y en a.

Le logiciel détenu par des tiers, et qui comprend la technologie relative aux polices de caractères, est protégé par un copyright et licencié par des fournisseurs de Sun.

Des parties de ce produit pourront être dérivées des systèmes Berkeley BSD licenciés par l'Université de Californie. UNIX est une marque déposée aux Etats-Unis et dans d'autres pays et licenciée exclusivement par X/Open Company, Ltd.

Sun, Sun Microsystems, le logo Sun, docs.sun.com, Sun Management Center, Sun Fire, Netra, Java et Solaris sont des marques de fabrique ou des marques déposées de Sun Microsystems, Inc. aux Etats-Unis et dans d'autres pays.

Toutes les marques SPARC sont utilisées sous licence et sont des marques de fabrique ou des marques déposées de SPARC International, Inc. aux Etats-Unis et dans d'autres pays. Les produits portant les marques SPARC sont basés sur une architecture développée par Sun Microsystems, Inc.

L'interface d'utilisation graphique OPEN LOOK et Sun™ a été développée par Sun Microsystems, Inc. pour ses utilisateurs et licenciés. Sun reconnaît les efforts de pionniers de Xerox pour la recherche et le développement du concept des interfaces d'utilisation visuelle ou graphique pour l'industrie de l'informatique. Sun détient une licence non exclusive de Xerox sur l'interface d'utilisation graphique Xerox, cette licence couvrant également les licenciées de Sun qui mettent en place l'interface d'utilisation graphique OPEN LOOK et qui en outre se conforment aux licences écrites de Sun.

LA DOCUMENTATION EST FOURNIE "EN L'ÉTAT" ET TOUTES AUTRES CONDITIONS, DECLARATIONS ET GARANTIES EXPRESSES OU TACITES SONT FORMELLEMENT EXCLUES, DANS LA MESURE AUTORISÉE PAR LA LOI APPLICABLE, Y COMPRIS NOTAMMENT TOUTE GARANTIE IMPLICITE RELATIVE À LA QUALITÉ MARCHANDE, À L'APTITUDE À UNE UTILISATION PARTICULIÈRE OU À L'ABSENCE DE CONTREFAÇON.



Adobe PostScript

# Contents

---

Supported Features	1
Supported Software and Environments	2
Recommended Patches	3
Obtaining the Add-On Software	4
Documentation	4
Known Bugs	5
Data Acquisition and FRUI ID Errors Misleading	5
Messages Truncated in LOM Events Table	5
No Alarm Generated for DIMM Errors	5
No Alarm Generated for SIB Errors	5
No Alarm for Ecache Errors	6
Restart picl Daemon After DR Operation	6
Degraded Power Supplies Appear OK	6
Disk, Tape, Network Counts Erroneous	7
Disk Devices Table Reports Erroneous	7
Physical View and Logical View	7



# Sun Management Center 3.5 Version 6 Release Notes for Sun Fire Entry-Level Midrange Systems

---

The *Sun™ Management Center 3.5 Version 6 Release Notes for Sun Fire Entry-Level Midrange Systems* provides late-breaking news for Sun Management Center 3.5 Version 6 software for Sun Fire entry-level midrange systems. This document supplements the *Sun Management Center 3.5 Version 6 Supplement for Sun Fire Entry-Level Midrange Systems* (819-0419-10).

This document contains the following release notes for the Sun Management Center 3.5 Version 6 add-on software for Sun Fire entry-level midrange systems:

- “[Supported Features](#)” on page 1
  - “[Supported Software and Environments](#)” on page 2
  - “[Recommended Patches](#)” on page 3
  - “[Obtaining the Add-On Software](#)” on page 4
  - “[Documentation](#)” on page 4
  - “[Known Bugs](#)” on page 5
- 

## Supported Features

Supported Sun Fire entry-level midrange systems include:

- Sun Fire™ E2900
  - Sun Fire V1280
- 

**Note** – Sun Management Center 3.5 Version 6 does *not* support Netra™ 1280 systems.

---

The Capacity on Demand (COD) 2.0 option is supported. Refer to the description of the FRUID Info Config-Reader table in Chapter 3 of the *Sun Management Center 3.5 Version 6 Supplement for Sun Fire Entry-Level Midrange Systems* for details about identifying COD boards in this release. Also refer to the *Sun Fire Entry-Level Midrange System Administration Guide* for more information about COD.

Refer to the *Sun Management Center 3.5 Version 6 Supplement for Sun Fire Entry-Level Midrange Systems* for detailed information about this software.

---

## Supported Software and Environments

The minimum Sun Fire entry-level midrange systems firmware and operating systems supported in this release are shown in [TABLE 1](#).

**TABLE 1** Minimum Required Software Versions

Host	Required Software	Version
Server machine	Solaris <sup>1</sup> Operating System	8.2/04 9.9/04 10
	Sun Management Center server base software	
	for Solaris 8 or 9	3.5 Update 1
	for Solaris 10	3.5 Update 1b with patch 118389-07
	Sun Management Center Sun Fire Entry-Level Midrange Systems add-on software	3.5 Version 6
Sun Fire Entry-Level Midrange Systems domains	Solaris <sup>1</sup> Operating System	8.2/04 9.9/04 10
	Sun Fire Entry-Level Midrange Systems Firmware	5.17.0
	for COD	5.18.0
	Sun Management Center agent base software	
	for Solaris 8 or 9	3.5 Update 1
	for Solaris 10	3.5 Update 1b with patch 118389-07

**TABLE 1** Minimum Required Software Versions (*Continued*)

Host	Required Software	Version
Workstations (for console layer)	Sun Management Center Sun Fire Entry-Level Midrange Systems add-on software	3.5 Version 6
	Solaris <sup>1</sup> Operating System	Solaris 2.6, 7, 8, 9, 10
	Sun Management Center console base software for Solaris 10	3.5 Update 1 3.5 Update 1b with patch 118389-07

1 Solaris Operating System distribution must be at least "End User Systems Support."

---

## Recommended Patches

---

**Note** – Sun Management Center patch 118389-07 is *required* for Solaris 10. It is also recommended when you are using other releases of Solaris.

---

Solaris software patches might be available for the Sun Management Center 3.5 application. You must install all the patches required for your operating environment before installing the latest update of the Sun Management Center 3.5 software and this add-on.

If you have a Sun service contract, you can download the patches from the following web site:

<http://sunsolve.sun.com>

You can also download the patches from the Sun Management Center product web site:

<http://www.sun.com/sunmanagementcenter>

For more information about the patches required for the latest update to Sun Management Center 3.5 software, see the corresponding *Sun Management Center Software Release Notes*.

---

# Obtaining the Add-On Software

The Sun Management Center 3.5 Version 6 add-on software packages for Sun Fire entry-level midrange systems are supplied in a zip file named

`Sun_MC-3_5_Addon_V6-GA.zip`

on the software download site:

<http://wwws.sun.com/software/download/index.html>

If you don't see the listing for Sun Management Center 3.5 Version 6 under New Downloads, do the following:

- 1. Click on the A-Z Index of All Products.**
  - 2. Click on M.**
  - 3. Scroll down and click on Management Center 3.5 Version 6.**
  - 4. Click on Download.**
  - 5. Log in to the Download Center.**
  - 6. Click on Accept to accept the License Agreement, and click on Continue.**
  - 7. Follow the instructions on the download page.**
- 

# Documentation

For details about using Sun Management Center 3.5 Version 6 for Sun Fire entry-level midrange systems, see the *Sun Management Center 3.5 Version 6 Supplement for Sun Fire Entry-Level Midrange Systems*. Refer to the preface of that document for information about related documentation. Sun documentation can be found here:

<http://www.sun.com/documentation/>

---

## Known Bugs

### Data Acquisition and FRUI ID Errors Misleading

When the domain agent is shut down or rebooted, a critical Data Acquisition Error alarm is generated. Also, in the System table, the Module Status value is reported as FRU ID error. These errors are generated because information cannot be obtained from a domain that is unavailable due to a shutdown or reboot operation. However, the errors do not indicate the domain has been shut down or rebooted. [5107120]

### Messages Truncated in LOM Events Table

Messages in the LOM Events table are truncated at approximately 88 characters.

*Workaround:* To see the full message, use the SC command showlogs.

[5108200]

### No Alarm Generated for DIMM Errors

In this release, DIMM errors do not generate an alarm. [5109109]

### No Alarm Generated for SIB Errors

In this release, System Indicator Board (SIB) errors do not generate an alarm.

*Workaround:* When the FRUID Info table property fields display the value Reading . . . for an extended period, a SIB failure may be indicated. If a failure has occurred, it will be reported in /var/adm/messages.

[6173744]

## No Alarm for Ecache Errors

The Entry-Level Midrange Add-On does not provide alarms when Ecache errors are encountered.

*Workaround:* Look for applicable Ecache error message strings in the file /var/adm/messages.

[6173729]

## Restart picl Daemon After DR Operation

After a DR operation, you must restart the picl daemon so that the tables provided by this add-on software are updated.

In Solaris 8 or 9:

```
# /etc/init.d/picld stop; /etc/init.d/picld start
```

In Solaris 10:

```
# svcadm restart svc:/system(picl:default)
```

[6247392]

## Degraded Power Supplies Appear OK

No alarm is triggered when a power supply is not working properly. Moreover, the values of the PSU Input, PSU Output, and PSU Status properties in the Power Supplies table display an erroneous OK value for a degraded power supply.

*Workaround:* If the fault light indicates a fault (green), log on to the system controller and use the firmware's showboards command to determine which hardware is triggering the fault light.

[6215922]

## Disk, Tape, Network Counts Erroneous

Although the I/O Device table includes Disk Count, Network Count, and Tape Count properties, these values are not displayed. This table reports only PCI cards. [4761961]

## Disk Devices Table Reports Erroneous

The Disk Devices table sometimes fails to report internal disks. [6214527]

## Physical View and Logical View

Not all alarms are displayed in the Physical View and Logical View. [5101456]

