

Troubleshooting Sun Java System Communications Express

Sun Java™ Enterprise System Technical Note



Sun Microsystems, Inc.
4150 Network Circle
Santa Clara, CA 95054
U.S.A.

Part No: 819-5198-11
August 2006

Copyright 2006 Sun Microsystems, Inc. 4150 Network Circle, Santa Clara, CA 95054 U.S.A. All rights reserved.

Sun Microsystems, Inc. has intellectual property rights relating to technology embodied in the product that is described in this document. In particular, and without limitation, these intellectual property rights may include one or more U.S. patents or pending patent applications in the U.S. and in other countries.

U.S. Government Rights – Commercial software. Government users are subject to the Sun Microsystems, Inc. standard license agreement and applicable provisions of the FAR and its supplements.

This distribution may include materials developed by third parties.

Parts of the product may be derived from Berkeley BSD systems, licensed from the University of California. UNIX is a registered trademark in the U.S. and other countries, exclusively licensed through X/Open Company, Ltd.

Sun, Sun Microsystems, the Sun logo, the Solaris logo, the Java Coffee Cup logo, docs.sun.com, Java, and Solaris are trademarks or registered trademarks of Sun Microsystems, Inc. in the U.S. and other countries. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. in the U.S. and other countries. Products bearing SPARC trademarks are based upon an architecture developed by Sun Microsystems, Inc.

The OPEN LOOK and Sun™ Graphical User Interface was developed by Sun Microsystems, Inc. for its users and licensees. Sun acknowledges the pioneering efforts of Xerox in researching and developing the concept of visual or graphical user interfaces for the computer industry. Sun holds a non-exclusive license from Xerox to the Xerox Graphical User Interface, which license also covers Sun's licensees who implement OPEN LOOK GUIs and otherwise comply with Sun's written license agreements.

Products covered by and information contained in this publication are controlled by U.S. Export Control laws and may be subject to the export or import laws in other countries. Nuclear, missile, chemical or biological weapons or nuclear maritime end uses or end users, whether direct or indirect, are strictly prohibited. Export or reexport to countries subject to U.S. embargo or to entities identified on U.S. export exclusion lists, including, but not limited to, the denied persons and specially designated nationals lists is strictly prohibited.

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.

Copyright 2006 Sun Microsystems, Inc. 4150 Network Circle, Santa Clara, CA 95054 U.S.A. Tous droits réservés.

Sun Microsystems, Inc. détient les droits de propriété intellectuelle relatifs à la technologie incorporée dans le produit qui est décrit dans ce document. En particulier, et ce sans limitation, ces droits de propriété intellectuelle peuvent inclure un ou plusieurs brevets américains ou des applications de brevet en attente aux Etats-Unis et dans d'autres pays.

Cette distribution peut comprendre des composants développés par des tierces personnes.

Certaines composants de ce produit peuvent être dérivées du logiciel Berkeley BSD, licenciés par l'Université de Californie. UNIX est une marque déposée aux Etats-Unis et dans d'autres pays; elle est licenciée exclusivement par X/Open Company, Ltd.

Sun, Sun Microsystems, le logo Sun, le logo Solaris, le logo Java Coffee Cup, docs.sun.com, Java et Solaris sont des marques de fabrique ou des marques déposées de Sun Microsystems, Inc. aux Etats-Unis et dans d'autres pays. Toutes les marques SPARC sont utilisées sous licence et sont des marques de fabrique ou des marques déposées de SPARC International, Inc. aux Etats-Unis et dans d'autres pays. Les produits portant les marques SPARC sont basés sur une architecture développée par Sun Microsystems, Inc.

L'interface d'utilisation graphique OPEN LOOK et Sun a été développée par Sun Microsystems, Inc. pour ses utilisateurs et licenciés. Sun reconnaît les efforts de pionniers de Xerox pour la recherche et le développement du concept des interfaces d'utilisation visuelle ou graphique pour l'industrie de l'informatique. Sun détient une licence non exclusive de Xerox sur l'interface d'utilisation graphique Xerox, cette licence couvrant également les licenciés de Sun qui mettent en place l'interface d'utilisation graphique OPEN LOOK et qui, en outre, se conforment aux licences écrites de Sun.

Les produits qui font l'objet de cette publication et les informations qu'il contient sont régis par la législation américaine en matière de contrôle des exportations et peuvent être soumis au droit d'autres pays dans le domaine des exportations et importations. Les utilisations finales, ou utilisateurs finaux, pour des armes nucléaires, des missiles, des armes chimiques ou biologiques ou pour le nucléaire maritime, directement ou indirectement, sont strictement interdites. Les exportations ou réexportations vers des pays sous embargo des Etats-Unis, ou vers des entités figurant sur les listes d'exclusion d'exportation américaines, y compris, mais de manière non exclusive, la liste de personnes qui font objet d'un ordre de ne pas participer, d'une façon directe ou indirecte, aux exportations des produits ou des services qui sont régis par la législation américaine en matière de contrôle des exportations et la liste de ressortissants spécifiquement désignés, sont rigoureusement interdites.

LA DOCUMENTATION EST FOURNIE "EN L'ETAT" ET TOUTES AUTRES CONDITIONS, DECLARATIONS ET GARANTIES EXPRESSES OU TACITES SONT FORMELLEMENT EXCLUES, DANS LA MESURE AUTORISEE PAR LA LOI APPLICABLE, Y COMPRIS NOTAMMENT TOUTE GARANTIE IMPLICITE RELATIVE A LA QUALITE MARCHANDE, A L'APTITUDE A UNE UTILISATION PARTICULIERE OU A L'ABSENCE DE CONTREFACON.

Troubleshooting Sun Java System Communications Express

This technical note describes how to troubleshoot common installation and configuration problems for Sun Java System Communications Express 6 2005Q4.

The component products affected by this technical note are:

- Sun Java System Access Manager 7 2005Q4
- Sun Java System Calendar Server 6 2005Q4
- Sun Java System Communications Express 6 2005Q4
- Sun Java System Directory Server 5 2005Q4
- Sun Java System Messaging Server 6 2005Q4
- Sun Java System Web Server 6.1 2005Q4 SP5

This technical note contain the following sections:

- “Technical Note Revision History” on page 3
- “Troubleshooting Communications Express Installation and Configuration” on page 4
- “Documentation, Support, and Training” on page 11

Technical Note Revision History

Date	Description of Changes
August 2, 2006	Corrected Web Server parameters in the amconfigcommx file. Corrected file name to /etc/opt/SUNWam/config/AMConfig.properties and parameter to com.iplanet.am.directory.host=DS_SERVER_HOSTNAME_FQDN in Step 5 of the task “To Troubleshoot Communications Express.”
June 2, 2006	Re-issue of this technical note for Sun Java Enterprise System 2005Q4.

Troubleshooting Communications Express Installation and Configuration

Currently, installing and configuring Communications Express is not trouble-free. This seems especially true for a two-tiered deployment, with Communications Express on a front-end host separate from a back-end Access Manager host.

The following problem topics will aid you in troubleshooting your deployment:

- “Problem: Unable to Configure Messaging Server” on page 4
- “Problem: Web Server Exceptions” on page 5
- “Problem: User Authentication Failed” on page 8
- “Problem: Communications Express Login Page Redirects to the Messenger Express Login Page” on page 10
- “Problem: Unable to Access the Calendar Tab” on page 10
- “Problem: Log Files Do Not Appear in the /var/opt/SUNWuwc/logs Directory” on page 11

Problem: Unable to Configure Messaging Server

Solution: Check that DNS is running and configured properly.

▼ To Troubleshoot DNS

- 1 **Make sure that the /etc/resolv.conf file has name server entries with the IP addresses of valid name servers. For example:**

```
nameserver 192.168.100.22  
nameserver 192.168.100.23  
nameserver 192.168.100.24  
nameserver 192.168.100.25
```

- 2 **Make sure that the /etc/hosts file has an entry for the fully qualified host name of the server. This fully qualified host name should be listed before the non fully qualified host name. For example:**

```
10.1.82.52 host1.red.example.com host1 loghost
```

Solaris™ 10 Operating System (OS) hosts: Make sure the /etc/inet/iphnodes file also has an entry for the fully qualified host name of the server.

- 3 **Make sure that the /etc/nsswitch.conf file is configured to use files first to resolve host names. The hosts line in the nsswitch.conf file should list files first in its entry:**

```
hosts: files dns nis [NOTFOUND=return]  
# OR (if NIS is not used)  
hosts: files dns
```

Verify that you can resolve a host name to an IP address.

For example:

```
# nslookup host1.red.example.com
Server:      192.168.100.161
Address:     192.168.100.161#53
Name: host1.red.example.com
Address: 10.1.82.52
```

Solaris 10 hosts: Add this additional line to the /etc/nsswitch.conf file:

```
ipnodes: files dns nisplus [NOTFOUND=return]
```

Problem: Web Server Exceptions

Solution: Verify the Web Server and Access Manager SDK configuration.

When configuring Communications Express in a two-tiered deployment, the following steps are involved:

1. Configuring the Communications Express web container's (Sun Java System Web Server 6.1 2005Q4 SP5) server.xml file with all required jar file settings
2. Pointing the Communications Express Identity SSO to the external Access Manager from the uwcauth.properties file
3. Installing the Access Manger SDK on the same Web Server instance where the Communications Express application is running (that is, on the front-end host)

If you see errors such as the following for Web Server, then use the troubleshooting steps that follow.

```
[30/Jun/2005:11:05:33] failure (13862): WebModule[/uwc]: WEB2680: Exception starting filter IdentitySSOAuthFilter
```

▼ To Troubleshoot Communications Express

1. Check if the Web Server runtime owner is root:other. That is, the runtime owner should be the same for Access Manager, Access Manager SDK, and Communications Express. It is preferred that the runtime owner be root:other.

If the runtime owner for Web Server is not root (but webservd), then do the following:

- a. Change the ownership of the /opt/SUNWwbsvr/https-host.domain directory to root:other (recursively).
- b. Edit the /opt/SUNWwbsvr/https-host.domain/config/magnus.conf file and change the line containing "user webservd" to "user root".
- c. Restart Web Server.

2 Check the Access Manager SDK by running the following command from the front-end AM SDK location (host).

```
cd /opt/SUNWam/bin  
. ./amadmin -u amadmin -w password -m http://host:80
```

You should see output similar to the following:

```
Get Sessions: Server Name = http://host1.red.siroe.com:80  
[Current Session] User Id: amAdmin Time Remain: 120 Max Session Time: 120 Idle Time: 0 Max Idle Time: 30  
To invalidate sessions, enter the index numbers  
[CR without a number to exit]:  
Success 0: Successfully completed
```

3 If Step 2 does not work as expected, then check that the Access Manager SDK classpath is correct in the Web Server on the Communications Express host (that is, the front end).

Make sure that /opt/SUNWam/lib/am_services.jar, /opt/SUNWam/lib/am_sdk.jar, and /opt/SUNWam/lib/am_sso_provider.jar are in the classpath suffix of the /opt/SUNWwbsvr/https-host.domainconfig/server.xml file.

Note – Manually editing the server.xml file is generally not recommended. The correct way is to use the /opt/SUNWam/bin/amconfig command. See “Problem: Web Server Exceptions” on page 5.

4 Create a new state file similar to the following for the Access Manager SDK configuration.

a. Change to the directory that contains the amconfig input file template, amsamplesilent.

```
# cd /opt/SUNWam/bin
```

b. Copy the input template file to a new file.

```
# cp amsamplesilent amconfigcommx
```

c. Edit the amconfigcommx file to set the Access Manager SDK configuration parameters as follows (non-default values are shown in bold):

```
DEPLOY_LEVEL=4  
SERVER_PROTOCOL=http ##### (If you need secure access, change to https)  
SERVER_NAME=AM_SERVER_HOSTNAME ##### (Access Manager hostname)  
SERVER_HOST=AM_SERVER_HOSTNAME_FQDN ##### (Access Manager fully qualified domain name)  
SERVER_PORT=AM_SERVER_WEB_CONTAINER_PORT  
ADMIN_PORT=AM_SERVER_WEB_ADMIN_PORT  
DS_HOST=DS_HOSTNAME_FQDN ##### (Directory Server fully qualified domain name)  
DS_DIRMGRPASSWD=DM_PASSWORD  
ROOT_SUFFIX=UG_SUFFIX  
ADMINPASSWD=AMADMIN_PASSWORD  
AMLDAPUSERPASSWD=AMLDAPUSERPASSWORD  
COOKIE_DOMAIN=.example.com ##### (Modify to reflect default domain)  
AM_ENC_PWD="myQDWqCBhvI0bfP/BF/1b7+k/BiEpVcY"  
#### Get from AMConfig.properties file of fully installed Access Manager host
```

```
NEW_OWNER=root
NEW_GROUP=other
WEB_CONTAINER=WS6

SSL_PASSWORD="ssl_password" ##### (If SSL used)

BASEDIR=/opt/SUNWam

CONSOLE_HOST=$SERVER_HOST
CONSOLE_PORT=$SERVER_PORT
CONSOLE_PROTOCOL=$SERVER_PROTOCOL

CONSOLE_REMOTE=true

SERVER_DEPLOY_URI=/amserver
if [ $DEPLOY_LEVEL -eq 2 -o $DEPLOY_LEVEL -eq 12 ]; then
    CONSOLE_DEPLOY_URI=$SERVER_DEPLOY_URI
else
    CONSOLE_DEPLOY_URI=/amconsole
fi
PASSWORD_DEPLOY_URI=/ampassword
COMMON_DEPLOY_URI=/amcommon

DIRECTORY_MODE=4 #####
DS_PORT=389
DS_DIRMGRDN="cn=Directory Manager"
USER_NAMING_ATTR=uid
ORG_NAMING_ATTR=o
ORG_OBJECT_CLASS=sunismanagedorganization
USER_OBJECT_CLASS/inetorgperson
DEFAULT_ORGANIZATION=

JAVA_HOME=/usr/jdk/entsys-j2se

AM_REALM=disabled ##### (For legacy use)

PLATFORM_LOCALE=en_US

XML_ENCODING=ISO-8859-1

NEW_INSTANCE=false

##### Required for Web Server #####
WS61_INSTANCE=https-COMMS_EX_HOSTNAME_FQDN #####Modify to reflect front-end hostname
WS61_HOME=/opt/SUNWwbsvr
WS61_PROTOCOL=$SERVER_PROTOCOL
WS61_HOST=COMMS_EX_HOST #####NOT $SERVER_HOST in an AM SDK remote AM Server configuration
```

```
WS61_PORT=COMMS_EX_PORT #####NOT $SERVER_PORT in an AM SDK remote AM Server configuration
WS61_ADMINPORT=$ADMIN_PORT
WS61_ADMIN="admin"
WS61_IS_SECURE=false

DIRECTORY_MODE=4
DS_PORT=389
DS_DIRMGRDN="cn=Directory Manager"
USER_NAMING_ATTR=uid
ORG_NAMING_ATTR=o
ORG_OBJECT_CLASS=sunismanagedorganization
USER_OBJECT_CLASS/inetorgperson
DEFAULT_ORGANIZATION=

JAVA_HOME=/usr/jdk/entsys-j2se
AM_REALM=disabled
```

5 Make a backup copy of the /etc/opt/SUNWam/config/AMConfig.properties file. Check the content of the following lines in that file:

```
com.ipplanet.am.directory.host=DS_SERVER_HOSTNAME_FQDN
com.ipplanet.am.server.host=AM_SERVER_HOSTNAME_FQDN
com.ipplanet.am.console.host=AM_SERVER_HOSTNAME_FQDN
com.ipplanet.am.profile.host=AM_SERVER_HOSTNAME_FQDN

com.ipplanet.am.naming.url=http://AM_SERVER_HOSTNAME_FQDN:WEBCONTAINER_PORT/amserver/namingservice

com.ipplanet.am.notification.url=http://COMMS_EX_HOSTNAME_FQDN:WEBCONTAINER_PORT/notificationservice
```

6 Run the following command:

```
/opt/SUNWam/bin/amconfig -s Newly_Created_AMSAMPLESILENT
```

- 7 Make sure the default domain contains the Core and LDAP services, which you can find in the Access Manager console under the Services tab.**
- 8 Make sure that the uwcauth.properties reads the complete dn for the variable uwcauth.identity.binddn as shown below:**
- ```
!Bind DN of AdmAdmin
uwcauth.identity.binddn=uid=amadmin,ou=people,o=usergroup
```

## Problem: User Authentication Failed

Solution: Verify operation of Directory Server, availability of user, baseDN, and LDAP service property values.

## ▼ To Troubleshoot Authentication Problems

### 1 Verify that the Directory Server is running.

For example:

```
/usr/bin/ps -ef | grep slapd
. ./ns-slapd -D /var/opt/mps/serverroot/slapd-host1 -i /var/opt/mps/serverroot/slapd-host1
```

### 2 If necessary, start Directory Server using one of the following commands:

For example, if Directory Server 5.2 is the default version:

On Solaris: /usr/sbin/directoryserver start

On Linux: /opt/sun/sbin/directoryserver start

### 3 Check that the user ID in question exists in the directory.

For example:

```
ldapsearch -h host -p port -D dn -w password -s sub -b basedn "uid=uid"
```

This will return the user entry, if it exists, or 'No such object' if the entry does not exist.

### 4 Check the uwcauth.properties file is using the correct baseDN and credentials.

See the following for more information:

"Communications Express Configuration Files" in *Sun Java System Communications Express 6 2005Q4 Administration Guide*

### 5 In an Access Manager deployment, check that the LDAP service property values are valid.

a. Log in to the Access Manager console as amAdmin.

b. Under Identity Management, click the appropriate organization.

c. Choose Services from the View menu.

The services list should have at a minimum Authentication Configuration, and Authentication Modules Core and LDAP. Click the LDAP Properties arrow and verify the information that appears in the Data pane.

d. If the service is not added, continue with the steps that follow.

e. Click Add in the Navigation pane.

A list of available services is displayed in the Data pane.

f. Select the checkbox for Authentication Configuration and click OK.

The Authentication Configuration service will appear in the Navigation pane assuring you that it has been added.

- g. Click the Authentication Configuration Properties arrow.

The Service Instance List is displayed in the Data pane.

- h. Click New to add the service instance.

Type the name and click Submit.

## Problem: Communications Express Login Page Redirects to the Messenger Express Login Page

Solution: Most likely there is a misconfiguration. Verify the SSO settings. See the following for more information:

Chapter 1, “Overview of Communications Express,” in *Sun Java System Communications Express 6 2005Q4 Administration Guide*

## Problem: Unable to Access the Calendar Tab

Solution: Verify that Calendar Server is running, and that the ics.conf file is properly configured.

### ▼ To Verify that Calendar Server is Running

- 1 Verify that the Calendar Server processes are running.

For example:

```
/usr/bin/ps -ef | grep cal
/opt/SUNWics5/cal/lib/cshttpd -d 3
/opt/SUNWics5/cal/lib/enpd -p 57997 -c config/ics.conf
/opt/SUNWics5/cal/lib/csadmin
/opt/SUNWics5/cal/lib/csnotifyd
```

- 2 If necessary, start Calendar Server.

- a. Change to the sbin directory.

On Solaris: /opt/SUNWics5/cal/sbin

On Linux: /opt/sun/calendar/cal/sbin

- b. Enter the following command to start Calendar Server.

./start-cal

## ▼ To Verify the ics.conf File Configuration

- 1 Change to the /etc/opt/SUNWics5/cal/config directory.
- 2 In the ics.conf file, verify that the service.http.allowadminproxy parameter is set to "yes".
- 3 Check if the virtual domain is either set to "yes" or "no" in both the ics.conf and uwauth.properties files. It cannot be "yes" in one file and "no" in the other file.
- 4 If you make edits to either the ics.conf or the uwauth.properties files, restart Calendar Server.

## Problem: Log Files Do Not Appear in the /var/opt/SUNWuwc/logs Directory

Solution: Enable logging. See the following for more information:

“Log Files” in *Sun Java System Communications Express 6 2005Q4 Administration Guide*

## Further Reading

Refer to Chapter 5, “Troubleshooting,” in *Sun Java System Communications Express 6 2005Q4 Administration Guide*.

Refer to Chapter 1, “Access Manager 7 2005Q4 Configuration Scripts,” in *Sun Java System Access Manager 7 2005Q4 Administration Guide*, for more information on Access Manager SDK-only configuration installation notes.

## Documentation, Support, and Training

The Sun web site provides information about the following additional resources:

- Documentation (<http://www.sun.com/documentation/>)
- Support (<http://www.sun.com/support/>)
- Training (<http://www.sun.com/training/>)

## Third-Party Web Site References

Third-party URLs are referenced in this document and provide additional, related information.

---

**Note** – Sun is not responsible for the availability of third-party web sites mentioned in this document. Sun does not endorse and is not responsible or liable for any content, advertising, products, or other materials that are available on or through such sites or resources. Sun will not be responsible or liable for any actual or alleged damage or loss caused or alleged to be caused by or in connection with use of or reliance on any such content, goods, or services that are available on or through such sites or resources.

---

## Sun Welcomes Your Comments

Sun is interested in improving its documentation and welcomes your comments and suggestions. To share your comments, go to <http://docs.sun.com> and click Send Comments. In the online form, provide the full document title and part number. The part number is a 7-digit or 9-digit number that can be found on the book's title page or in the document's URL. For example, the part number of this book is 819-5198.