

SunHSI/S™ 3.0 Release Notes



THE NETWORK IS THE COMPUTER™

Sun Microsystems, Inc.
901 San Antonio Road
Palo Alto, CA 94303-4900 USA
650 960-1300 Fax 650 969-9131

Part No. 805-6942-10
December 1998, Revision A

Send comments about this document to: docfeedback@sun.com

Copyright 1998 Sun Microsystems, Inc., 901 San Antonio Road • Palo Alto, CA 94303 USA. All rights reserved.

This product or document is protected by copyright and distributed under licenses restricting its use, copying, distribution, and decompilation. No part of this product or document may be reproduced in any form by any means without prior written authorization of Sun and its licensors, if any. Third-party software, including font technology, is copyrighted and licensed from Sun suppliers.

Parts of the product may be derived from Berkeley BSD systems, licensed from the University of California. UNIX is a registered trademark in the U.S. and other countries, exclusively licensed through X/Open Company, Ltd.

Sun, Sun Microsystems, the Sun logo, AnswerBook, Java, the Java Coffee Cup, SunHSI/S, SunSolve, SPARCstation, SPARCserver, SPARCcluster, Ultra, Sun Enterprise, OpenBoot, and Solaris are trademarks, registered trademarks, or service marks of Sun Microsystems, Inc. in the U.S. and other countries. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. in the U.S. and other countries. Products bearing SPARC trademarks are based upon an architecture developed by Sun Microsystems, Inc.

The OPEN LOOK and Sun™ Graphical User Interface was developed by Sun Microsystems, Inc. for its users and licensees. Sun acknowledges the pioneering efforts of Xerox in researching and developing the concept of visual or graphical user interfaces for the computer industry. Sun holds a non-exclusive license from Xerox to the Xerox Graphical User Interface, which license also covers Sun's licensees who implement OPEN LOOK GUIs and otherwise comply with Sun's written license agreements.

RESTRICTED RIGHTS: Use, duplication, or disclosure by the U.S. Government is subject to restrictions of FAR 52.227-14(g)(2)(6/87) and FAR 52.227-19(6/87), or DFAR 252.227-7015(b)(6/95) and DFAR 227.7202-3(a).

DOCUMENTATION IS PROVIDED "AS IS" AND ALL EXPRESS OR IMPLIED CONDITIONS, REPRESENTATIONS AND WARRANTIES, INCLUDING ANY IMPLIED WARRANTY OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE OR NON-INFRINGEMENT, ARE DISCLAIMED, EXCEPT TO THE EXTENT THAT SUCH DISCLAIMERS ARE HELD TO BE LEGALLY INVALID.

Copyright 1998 Sun Microsystems, Inc., 901 San Antonio Road • Palo Alto, CA 94303 Etats-Unis. Tous droits réservés.

Ce produit ou document est protégé par un copyright et distribué avec des licences qui en restreignent l'utilisation, la copie, la distribution, et la décompilation. Aucune partie de ce produit ou document ne peut être reproduite sous aucune forme, par quelque moyen que ce soit, sans l'autorisation préalable et écrite de Sun et de ses bailleurs de licence, s'il y en a. Le logiciel détenu par des tiers, et qui comprend la technologie relative aux polices de caractères, est protégé par un copyright et licencié par des fournisseurs de Sun.

Des parties de ce produit pourront être dérivées des systèmes Berkeley BSD licenciés par l'Université de Californie. UNIX est une marque déposée aux Etats-Unis et dans d'autres pays et licenciée exclusivement par X/Open Company, Ltd.

Sun, Sun Microsystems, le logo Sun, AnswerBook, Java, le logo Java Coffee Cup, SunHSI/S, SunSolve, SPARCstation, SPARCserver, SPARCcluster, Ultra, Sun Enterprise, OpenBoot, et Solaris sont des marques de fabrique ou des marques déposées, ou marques de service, de Sun Microsystems, Inc. aux Etats-Unis et dans d'autres pays. Toutes les marques SPARC sont utilisées sous licence et sont des marques de fabrique ou des marques déposées de SPARC International, Inc. aux Etats-Unis et dans d'autres pays. Les produits portant les marques SPARC sont basés sur une architecture développée par Sun Microsystems, Inc.

L'interface d'utilisation graphique OPEN LOOK et Sun™ a été développée par Sun Microsystems, Inc. pour ses utilisateurs et licenciés. Sun reconnaît les efforts de pionniers de Xerox pour la recherche et le développement du concept des interfaces d'utilisation visuelle ou graphique pour l'industrie de l'informatique. Sun détient une licence non exclusive de Xerox sur l'interface d'utilisation graphique Xerox, cette licence couvrant également les licenciés de Sun qui mettent en place l'interface d'utilisation graphique OPEN LOOK et qui en outre se conforment aux licences écrites de Sun.

CETTE PUBLICATION EST FOURNIE "EN L'ETAT" ET AUCUNE GARANTIE, EXPRESSE OU IMPLICITE, N'EST ACCORDEE, Y COMPRIS DES GARANTIES CONCERNANT LA VALEUR MARCHANDE, L'APTITUDE DE LA PUBLICATION A REpondre A UNE UTILISATION PARTICULIERE, OU LE FAIT QU'ELLE NE SOIT PAS CONTREFAISANTE DE PRODUIT DE TIERS. CE DENI DE GARANTIE NE S'APPLIQUERAIT PAS, DANS LA MESURE OU IL SERAIT TENU JURIDIQUEMENT NUL ET NON AVENU.



SunHSI/S 3.0 Release Notes

This document contains important information about the SunHSI/S™ hardware and software.

Note – For access to the Sun™ bug report database, and for information on how to get the latest patches and patch revisions, please visit the SunSolvesm website at <http://sunsolve.sun.com>.

Suggested Maximum Number of SunHSI/S Adapters Per System

The table below lists the suggested maximum number of SunHSI/S adapters per Sun™ system. These numbers were correct at the time of the printing of this document.

TABLE 1 Suggested Maximum Number of Adapters Per System

Sun System	Number of Adapters
SPARCstation™ 4, 5, 10, and 20	1
SPARCserver™ 6xx series	2
SPARCserver 1000/1000E	4
SPARCcenter™ 2000/2000E	4
Ultra™ 1	2
Ultra 2	2

TABLE 1 Suggested Maximum Number of Adapters Per System (Continued)

Sun System	Number of Adapters
Ultra 150	2
Sun Enterprise™ 3000/3500	8
Sun Enterprise 4000/4500/5000/5500	12
Sun Enterprise 6000/6500	16

Note – The SunHSI/S software has been tested on the Solaris™ 2.5.1, 2.6, and 7 operating environments.

Aggregate Network Speed

The *SunHSI/S 3.0 Installation and Administration Guide* (part number: 805-6941-10) indicates that each channel can operate at a maximum speed of 2.048Mbps, with an aggregate bandwidth for all four ports limited to 2.5Mbps. Due to hardware limitations, tests have shown that there is some performance degradation under severe network load and that there may be data corruption at network speeds over 1Mbps. We recommend that you use the SunHSI/S adapter at an aggregate bandwidth less than 1Mbps.

For more information, refer to Sun bug report numbers: 1215620, 1256946, and 4169715.

Performance on Enterprise Servers

The table below shows the SunHSI/S performance limitations on Sun Enterprise servers as tested in these sample configurations.

TABLE 2 SunHSI/S Performance on Enterprise Servers

System type	Number of Adapters in System	Total Number of Links	Maximum Configuration for Each Adapter
Sun Enterprise 6000	16	64	4 ports at 128Kbps/port
Sun Enterprise 6000	16	32	2 ports at 256Kbps/port
Sun Enterprise 5000	8	32	4 ports at 128Kbps/port

TABLE 2 SunHSI/S Performance on Enterprise Servers (*Continued*)

System type	Number of Adapters in System	Total Number of Links	Maximum Configuration for Each Adapter
Sun Enterprise 5000	12	48	4 ports at 64Kbps/port
Sun Enterprise 4000	8	32	4 ports at 128Kbps/port
Sun Enterprise 4000	12	48	4 ports at 64Kbps/port
Sun Enterprise 3000	4	16	4 ports at 128Kbps/port

Note – When you configure 2 ports per adapter, you must use port numbers 1 and 3 or 2 and 4.

In order to attain this performance, your system must operate the following versions of the Solaris operating environment: Solaris 2.5.1 Hardware: 8/97, 11/97, Solaris 2.6, and Solaris 7. You will not achieve this performance from the initial release of the Solaris 2.5.1 environment.

SunHSI/S Adapter is Not a Bootable Device

The OpenBoot™ PROM `show-nets` command mistakenly lists the SunHSI/S adapter as a bootable network device. The adapter is not a bootable device, and you cannot boot the Solaris operating environment over the SunHSI/S interface.

Refer to Sun bug report number 4154158 for more information.

Dynamic Reconfiguration Issues

The dynamic reconfiguration (DR) set of enhancements to the Solaris operating environment provide the capability of dynamically attaching and detaching system boards in certain Sun servers without halting the server. This section describes some dynamic reconfiguration issues with the SunHSI/S hardware and software.

The `cfgadm(1M)` command provides various administration operations helpful when configuring dynamic reconfiguration systems. The `cfgadm unconfigure` option performs hardware specific operations that remove hardware resources from the

system. If you fail to unconfigure a SunHSI/S adapter after using the `cfgadm` command, you cannot unconfigure the adapter again without first rebooting the system. For more information, refer to Sun bug report numbers 4178609 and 4182985.

The dynamic reconfiguration software has a known problem of not being able to suspend a device performing synchronous operations. Because the SunHSI/S adapter performs synchronous operations, you must stop all applications running on the adapter before using the dynamic reconfiguration software to suspend a SunHSI/S device. Refer to Sun bug report numbers 4175663 and 4175670 for more information.

If you have more than one SunHSI/S adapter in your system, stop all applications running on all SunHSI/S adapters before using the `cfgadm` command to suspend and resume a SunHSI/S adapter. You must stop all of the applications running over SunHSI/S adapters because the SunHSI/S software driver is not multi-threaded. For more information, refer to Sun bug report number 4188122.

Sun-4c Systems are Not Supported

The SunHSI/S software does not support Sun-4c systems, which include the SPARCstation 1, 1+, 2, IPC, and IPX systems. When attempting to install the SunHSI/S software on a Sun-4c system, the system will panic because links created during the software installation are not valid on these systems.

Note – This problem is unique to Sun-4c systems, since these machines panic when an invalid attempt to access hardware is made. Refer to Sun bug report number 4188067 for more information.
