

Fibre Channel SBus Card

Product Note



This note applies to the Fibre Channel SBus host adapter card (X1057A, part number 595-3213-02), field replaceable unit (part number F501-2069), and spare (part number #501-2069). This SBus card contains Fcode version 1.33, which is incompatible with some combinations of Solaris® operating environments and SPARCstorage™ Array drivers. It may be necessary to install a software patch on your system.



Caution – The appropriate patch must be installed *before* you install an SBus card containing version 1.33 Fcode.

To determine your SPARCstorage Array driver version, type:

```
pkginfo -l SUNWssadv | grep VERSION
```

To determine your Solaris operating environment version, type:

```
cat /etc/motd
```

Refer to the following table to determine which patch must be installed. The patch is included on the *SPARCstorage Array Software and SPARCstorage Volume Manager 2.1* CD, or contact your local service representative for a copy of the patch.

	Solaris 2.3	Solaris 2.4 Hardware: 11/94
SPARCstorage Array driver 1.0	Patch number 102408-XX	Not supported
SPARCstorage Array driver 2.0	Patch number 102400-XX	Patch number 102347-XX

For Solaris 2.4 Hardware: 3/95, a patch is *not* needed for Fcode version 1.33.



Sun Microsystems Computer Company
A Sun Microsystems, Inc. Business
2550 Garcia Avenue
Mountain View, CA 94043 U.S.A.
415 960-1300 FAX 415 969-9131
Part No.: 802-3237-10
Revision A, March 1995