

**Oracle® Communications
Policy Management**

OSSI XML Interface Definitions Reference

Release 9.7.3

E63621 Revision 01

August 2015

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, delivered to U.S. Government end users are "commercial computer software" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, use, duplication, disclosure, modification, and adaptation of the programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, shall be subject to license terms and license restrictions applicable to the programs. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Xeon are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Opteron, the AMD logo, and the AMD Opteron logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Table of Contents

Chapter 1: About This Guide.....	10
Introduction.....	11
How This Guide is Organized.....	11
Scope and Audience.....	12
Documentation Admonishments.....	12
Related Publications.....	12
Locate Product Documentation on the Oracle Technology Network Site.....	13
Customer Training.....	14
My Oracle Support (MOS).....	14
Emergency Response.....	15
 Chapter 2: Schema Definitions and Request Specifications.....	 16
Schema Definitions.....	17
Request Specification.....	17
 Chapter 3: Common Responses and Commands.....	 19
Common Responses.....	20
Example XML Response for a Successful Operation.....	20
Example XML Response for an Operation that Fails at the System Level.....	20
Example XML Response for an Operation that Includes an Application-level Failure.....	20
Result Codes.....	21
Common Commands.....	21
Get Version.....	22
Distribute Updates.....	22
Serving Gateway/MCC-MNC Mapping.....	23
Query OM Stats Settings.....	23
Query Absolute Values for Statistics.....	24
 Chapter 4: Topology Interface.....	 25
Topology Interface Requests.....	26
Network Elements.....	28

Add Network Element.....	28
Update Network Element.....	30
Add Network Element to Group.....	30
Remove Network Element from Group.....	31
Delete Network Element.....	32
Delete Network Element Group.....	32
Query Network Elements.....	33
Paths.....	35
Add Path.....	35
Update Path.....	36
Delete Path.....	37
Query Path.....	38
Applications.....	39
Add Application.....	39
Update Application.....	40
Delete Application.....	40
Query Application.....	41
Traffic Profiles.....	42
Add Traffic Profile.....	42
Update Traffic Profile.....	43
Delete Traffic Profile.....	44
Query Traffic Profile.....	45
Time Periods.....	46
Add Time Period.....	46
Update Time Period.....	46
Delete Time Period.....	47
.....	47
Charging Servers.....	47
Add Charging Server.....	47
Update Charging Server.....	48
Delete Charging Server.....	49
Query Charging Server.....	49
Match List.....	50
Add Match List.....	51
Update Match List.....	52
Delete Match List.....	52
Query Match List.....	53
Monitoring Key.....	54
Add Monitoring Key.....	54
Update Monitoring Key.....	55
Delete Monitoring Key.....	55

Query Monitoring Key.....	56
AVP Definition.....	57
Add AVP Definition.....	57
Update AVP Definition.....	57
Delete AVP Definition.....	58
Query AVP Definition.....	59
Serving GPRS Support Node.....	60
Add SGSN.....	60
Update SGSN.....	60
Delete SGSN.....	61
Query SGSN.....	62

Chapter 5: Subscriber Interface.....63

Accounts.....	64
Overview.....	64
Add Account.....	64
Update Account.....	65
Delete Account.....	66
Query Account.....	67
Tiers.....	68
Add Tier.....	68
Update Tier.....	69
Delete Tier.....	69
Query Tier.....	70
Quota Profiles.....	71
Add Quota Profile.....	71
Update Quota Profile.....	75
Delete Quota Profile.....	78
Query Quota Profile.....	79
Quota Conventions.....	80
Add Quota Convention.....	80
Update Quota Conventions.....	81
Delete Quota Convention.....	82
Query Quota Convention.....	82
Setting SCTP Settings.....	83

Chapter 6: Operational Measurements Interface Overview.....84

OM Statistics Scheduled Task.....	85
OM Statistics Requests.....	85
Attributes and Child Tags.....	85

Recorded Timestamp and Request Time Range.....	87
OM Statistics Response Format.....	87
Interval Statistics.....	87
Absolute versus Delta Values.....	88
Empty Data Set.....	88
Timezones and Start/End Times.....	88
Counter Reset and Failover.....	89
Comparisons Between the CMP GUI and OM Statistics.....	90

Chapter 7: Operational Measurement Requests.....92

Operational Measurements Requests Overview.....	93
Diameter Event Trigger Statistics.....	94
Topology Update Statistics.....	96
Subscriber Update Statistics.....	97
Policy Server Statistics.....	98
Message Processing Statistics.....	99
Network Element Statistics.....	101
Latency Statistics.....	105
RADIUS Operational Measurement Requests.....	114
RADIUS Accounting Statistics.....	114
RADIUS Accounting Network Element Statistics.....	116
RADIUS-S Statistics.....	117
RADIUS-S Network Element Statistics.....	120
Connected Network Elements Statistics.....	123
Policy Statistics.....	124
Diameter Operational Measurements Requests.....	125
Diameter Sh Statistics.....	126
Diameter Sh Peer Statistics.....	127
Diameter Multi-Protocol Routing Agent (MRA) Policy Charging Enforcement Function Statistics.....	128
Diameter Multi-Protocol Routing Agent (MRA) Policy Charging Enforcement Function Peer Statistics.....	129
Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application (DRMA) Statistics.....	131
Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application (DRMA) over SCTP Response Statistics.....	132
Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application Peer Statistics.....	133
Diameter Multi-Protocol Routing Agent (MRA) Diameter Routing Agent (DRA) Statistics.....	134

Diameter Multi-Protocol Routing Agent (MRA) Application Function (AF)	
Statistics.....	135
Diameter Multi-Protocol Routing Agent (MRA) Application Function (AF) Peer	
Statistics.....	136
Diameter Multi-Protocol Routing Agent (MRA) Bearer Binding and Event Reporting	
Function (Bberf) Statistics.....	138
Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF)	
Statistics.....	139
Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF)	
Peer Statistics.....	140
Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF)	
over SCTP Statistics.....	142
KPI Statistics.....	143
Protocol Error Statistics.....	144
Session Cleanup Statistics.....	149
Timeout Statistics.....	150
Traffic Profile Statistics.....	164
Connection Error Statistics.....	165
Quota Profile Statistics.....	169
Quota Reset Statistics.....	170
Quota Reset All Statistics.....	172
Interval Statistics/PCRF Session License Tracking and Reporting.....	173

Chapter 8: Operational Measurement Requests for SNET.....177

Query PCRF Active Alarm.....	178
Query for HA Server Status and Running Processes.....	179
Diameter KPI Real-Time Statistics.....	181
Diameter Connection Status.....	184
Diameter Application Function Statistics.....	186
Diameter AF Binding Statistics.....	190
Diameter AF Peer Statistics.....	191
Diameter AF Session Service ID Statistics.....	196
Diameter Policy Charging Enforcement Function Statistics.....	197
Diameter PCEF Peer Statistics.....	202
Diameter Gx Session Statistics.....	207
Diameter Message Error Statistics.....	208
Query Network Elements.....	209
Diameter PCEF Session Statistics.....	211
Diameter PCEF Session APN Statistics.....	212

Chapter 9: Operational Measurement Requests for Mediation

Server.....	214
SPR KPI Historical Report.....	215
SPR Diameter Sh Message Statistics.....	217
SPR Active Alarm.....	220
Mediation Server Active Alarm.....	221
Mediation Server HA Statistic.....	222
Mediation Server KPI and OM Statistics.....	223

Chapter 10: Identity Management (IDM).....226

Identity Management Overview.....	227
Add a User.....	227
Update a User.....	233
Query a User.....	237
Delete a User.....	238
Query User Role.....	239
Query User Scope.....	242

Chapter 11: Policy Table Interface.....243

Policy Table Overview.....	244
Exported Policy Table XML.....	244
Add a Policy Table.....	245
Modify a Policy Table.....	245
Delete a Policy Table.....	246

List of Tables

Table 1: Admonishments.....	12
Table 2: OSSI Result Codes.....	21

Chapter 1

About This Guide

Topics:

- [Introduction.....11](#)
- [How This Guide is Organized.....11](#)
- [Scope and Audience.....12](#)
- [Documentation Admonishments.....12](#)
- [Related Publications.....12](#)
- [Locate Product Documentation on the Oracle Technology Network Site.....13](#)
- [Customer Training.....14](#)
- [My Oracle Support \(MOS\).....14](#)
- [Emergency Response.....15](#)

This guide describes the Configuration Management Platform (CMP) OSSI XML interface. This interface allows an operator or third party system to programmatically push configuration information to and retrieve operational statistics from the policy server deployment.

Introduction

This guide describes the OSSI XML interface (Operation Support System Interface). This interface enables an operator or third-party system to programmatically push configuration information to and retrieve operational statistics from the policy server deployment.

Conventions

The following conventions are used throughout this guide:

- **Bold text** in procedures indicates icons, buttons, links, or menu items that you click on.
- *Italic text* indicates variables.
- `Monospace text` indicates text displayed on screen.
- **Monospace bold text** indicates text that you enter exactly as shown.

How This Guide is Organized

The information in this guide is presented in the following order:

- [About This Guide](#) contains general information about this guide, the organization of this guide, and how to get technical assistance.
- [Schema Definitions and Request Specifications](#) describes the Schema Definitions and Request Specifications used within the OSSI XML interface.
- [Common Responses and Commands](#) describes the generic response format for many of the commands used and the commands that are common to the various OSSI interfaces.
- [Topology Interface](#) describes the interface that allows users to manage and query network elements, paths, and other topology-related objects within the system.
- [Subscriber Interface](#) describes the interface that allows users to manage and query subscriber elements within their system.
- [Operational Measurements Interface Overview](#) describes the interface used to retrieve operational counters from the system.
- [Operational Measurement Requests](#) describes the various Operational Measurements (OM) groups and the individual OM statistics that comprise them.
- [Operational Measurement Requests for SNET](#) describes the various Operational Measurements (OM) groups and the individual OM statistics that comprise are compatible with SNET.
- [Operational Measurement Requests for Mediation Server](#) describes the various Operational Measurements (OM) groups and the individual OM statistics that are utilized with the Mediation server.
- [Identity Management \(IDM\)](#) describes the interface that allows the CMP to configure user names, passwords and roles using the OSSI interface.

- [Policy Table Interface](#) describes an interface that allows you to generalize multiple similar policies into a single policy, simplifying processes such as adding new policies, modifying existing policies, and checking consistency among policies.

Scope and Audience

This guide is intended for operators or third party systems who are responsible for pushing configuration information to and retrieving operational statistics from a policy server deployment.

Documentation Admonishments

Admonishments are icons and text throughout this manual that alert the reader to assure personal safety, to minimize possible service interruptions, and to warn of the potential for equipment damage.

Table 1: Admonishments

Icon	Description
 DANGER	Danger: (This icon and text indicate the possibility of <i>personal injury</i> .)
 WARNING	Warning: (This icon and text indicate the possibility of <i>equipment damage</i> .)
 CAUTION	Caution: (This icon and text indicate the possibility of <i>service interruption</i> .)
 TOPPLE	Topple: (This icon and text indicate the possibility of <i>personal injury and equipment damage</i> .)

Related Publications

The Policy Management product set includes the following publications, which provide information for the configuration and use of Policy Management products in the following environments:

Cable

- *Feature Notice*
- *Cable Release Notes*
- *Roadmap to Hardware Documentation*
- *Policy Wizard*
- *CMP Cable User's Guide*
- *Troubleshooting Reference*
- *SNMP User's Guide*
- *OSSI XML Interface Definitions Reference*
- *Platform Configuration User's Guide*
- *Bandwidth on Demand Application Manager User's Guide*
- *PCMM specification PKT-SP-MM-I06* (third-party document, used as reference material for PCMM)

Wireless

- *Feature Notice*
- *Wireless Release Notes*
- *Roadmap to Hardware Documentation*
- *Policy Wizard*
- *CMP Wireless User's Guide*
- *Multi-Protocol Routing Agent User's Guide*
- *Troubleshooting Reference*
- *SNMP User's Guide*
- *OSSI XML Interface Definitions Reference*
- *Analytics Data Stream Reference*
- *Platform Configuration User's Guide*
- *Message Distribution Function Reference*

Wireline

- *Feature Notice*
- *Wireline Release Notes*
- *Roadmap to Hardware Documentation*
- *CMP Wireline User's Guide*
- *Troubleshooting Reference*
- *SNMP User's Guide*
- *OSSI XML Interface Definitions Reference*
- *Platform Configuration User's Guide*

Locate Product Documentation on the Oracle Technology Network Site

Oracle customer documentation is available on the web at the Oracle Technology Network (OTN) site, <http://docs.oracle.com>. You do not have to register to access these documents. Viewing these files requires Adobe Acrobat Reader, which can be downloaded at <http://www.adobe.com>.

1. Access the Oracle Technology Network site at <http://docs.oracle.com>.
2. Click **Industries**.

3. Under the Oracle Communications subheading, click the **Oracle Communications documentation** link.
The Oracle Communications Documentation page appears with Tekelec shown near the top.
4. Click the **Oracle Communications Documentation for Tekelec Products** link.
5. Navigate to your Product and then the Release Number, and click the **View** link (the Download link will retrieve the entire documentation set).
A list of the entire documentation set for the selected product and release appears.
6. To download a file to your location, right-click the **PDF** link, select **Save target as**, and save to a local folder.

Customer Training

Oracle University offers training for service providers and enterprises. Visit our web site to view, and register for, Oracle Communications training:

<http://education.oracle.com/communication>

To obtain contact phone numbers for countries or regions, visit the Oracle University Education web site:

www.oracle.com/education/contacts

My Oracle Support (MOS)

MOS (<https://support.oracle.com>) is your initial point of contact for all product support and training needs. A representative at Customer Access Support (CAS) can assist you with MOS registration.

Call the CAS main number at 1-800-223-1711 (toll-free in the US), or call the Oracle Support hotline for your local country from the list at <http://www.oracle.com/us/support/contact/index.html>. When calling, make the selections in the sequence shown below on the Support telephone menu:

1. Select **2** for New Service Request
2. Select **3** for Hardware, Networking and Solaris Operating System Support
3. Select one of the following options:
 - For Technical issues such as creating a new Service Request (SR), Select **1**
 - For Non-technical issues such as registration or assistance with MOS, Select **2**

You will be connected to a live agent who can assist you with MOS registration and opening a support ticket.

MOS is available 24 hours a day, 7 days a week, 365 days a year.

Emergency Response

In the event of a critical service situation, emergency response is offered by the Customer Access Support (CAS) main number at 1-800-223-1711 (toll-free in the US), or by calling the Oracle Support hotline for your local country from the list at <http://www.oracle.com/us/support/contact/index.html>. The emergency response provides immediate coverage, automatic escalation, and other features to ensure that the critical situation is resolved as rapidly as possible.

A critical situation is defined as a problem with the installed equipment that severely affects service, traffic, or maintenance capabilities, and requires immediate corrective action. Critical situations affect service and/or system operation resulting in one or several of these situations:

- A total system failure that results in loss of all transaction processing capability
- Significant reduction in system capacity or traffic handling capability
- Loss of the system's ability to perform automatic system reconfiguration
- Inability to restart a processor or the system
- Corruption of system databases that requires service affecting corrective actions
- Loss of access for maintenance or recovery operations
- Loss of the system ability to provide any required critical or major trouble notification

Any other problem severely affecting service, capacity/traffic, billing, and maintenance capabilities may be defined as critical by prior discussion and agreement with Oracle.

Chapter 2

Schema Definitions and Request Specifications

Topics:

- [Schema Definitions.....17](#)
- [Request Specification.....17](#)

To simplify integration, the OSSI XML interface uses an XML over HTTP(s) mechanism for requests and responses. Using XML as a transport allows the data to be represented in a portable, vendor-neutral and readable format.

The interface itself is divided into the following areas:

- Common Interface — defines generalized operations performed on the system.
- Topology Interface — allows users to manage and query network elements and paths (mode specific).
- Subscriber Interface — allows users to manage and query subscriber elements, such as accounts and tiers (mode specific).
- Operational Measurements (OM) Interface — allows users to retrieve statistical data from the system.

Each of these interfaces is described in detail in later chapters of this document.

This chapter describes the Schema Definitions and Request Specifications used within the OSSI XML interface.

Schema Definitions

The OSSI XML interface defines specific request and response messages for each of the areas outlined previously. To enable message validation and to accurately specify the syntax of each of the messages, XML schema definitions are provided as follows:

- `OssiXmlRequestResponse.xsd` — defines the `XmlInterfaceRequest` tag and the associated sub-element type definition. This `xsd` is used to validate add/update requests.
- `OssiXmlCommon.xsd` — defines the schema for global types and requests used in all interfaces.
- `OssiXmlTopology.xsd` — defines the schema for the topology interface.
- `OssiXmlSubscriber.xsd` — defines the schema for the subscriber interface such as `AddAccount` and `UpdateAccount`.
- `OssiXmlOm.xsd` — defines the schema for the OM interface and the OSSI OM stats query and response type definition.
- `OssiXmlRuntimeResponse.xsd` - defines the runtime response type such as `SubscriberLog`, `SubscriberRealtimeStats` and `ResponseType`.
- `OssiXmlUserMgr.xsd` - defines the User, Role-related type (such as: `AddRole` and `AddSysAdminUser`).

Request Specification

Each of the requests and responses defined within the previous schema definitions are sent to and received from the Configuration Management Platform (CMP) using HTTP(s) messages. Specifically, an HTTP POST message is sent containing the specific request message. The HTTP response contains a response message indicating status and returning any data as required.

For an application desiring to use the OSSI XML interface, the only requirement is the ability to send an HTTP POST and to process any response. This guide contains examples that use the command line utility `wget` to send an HTTP POST request that contains data specified in an XML file as input and returns an output XML file. The example that follows demonstrates the basic `wget` options; additional options are available but not described here. Please note that the request URL is case sensitive and must be entered as seen here.

Note: The CMP has a global setting that controls how often statistics are available to OSSI. Therefore, the availability of statistics is dependent upon when the statistics are available to OSSI. For more information, refer to the *CMP Wireless User's Guide* and *CMP Cable User's Guide*.

```
> wget --post-file=input.xml --output-document=output.xml
"http://1.2.3.4/mi/xmlInterfaceRequest.do?user=test&pwd=test"
```

Where the following describes each parameter:

- **`--post-file=input.xml`** (Required) — This parameter indicates the request input XML file.
- **`--output-document=output.xml`** (Optional) — This parameter is used to name the output file. If unspecified, the default filename is the URL string indicated in the `wget` request.
- **`http://1.2.3.4/mi/xmlInterfaceRequest.do ?user=test&pwd=test`** (Required) — The HTTP request URL, including the authentication credentials.

Schema Definitions and Request Specifications

- **--timeout=0** (Optional) — This parameter sets the network timeout to seconds. The default for this value is 900 (15min). A value of 0 disables timeout checking completely.
- **--progress=dot** (Optional) — This parameter is used to display the progress bar on the request.

Chapter 3

Common Responses and Commands

Topics:

- [*Common Responses.....20*](#)
- [*Result Codes.....21*](#)
- [*Common Commands.....21*](#)

This chapter describes the generic response format for many of the commands used and the commands that are common to the various OSSI interfaces.

Common Responses

This section describes the generic response format to many of the commands. The response format follows the generic response tag defined in the XSDs. The following are examples of successful and failed operations.

Example XML Response for a Successful Operation

The following is an example of an XML response for a successful operation:

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Successfully imported 2 network elements.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Example XML Response for an Operation that Fails at the System Level

The following is an example of an XML response for an operation that fails at the system level (for example, a malformed request):

```
<?xml version='1.0' ?>
<Response>
  <Result>103</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Incorrectly formatted XML. The element type
      "NetworkElementStats" must be terminated by the matching end-tag
      "</NetworkElementStats>".</Failure>
  </Command>
</Response>
```

Example XML Response for an Operation that Includes an Application-level Failure

The following is an example of an XML response for an operation that includes an application-level failure:

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to import 1 network elements.
      Network Element includes an invalid NetworkElementType.
      Network Element: RouterA</Failure>
  </Command>
</Response>
```

```
</Command>
</Response>
```

Result Codes

Many of the OSSI commands return a numeric result code in their response messages. This code represents the status of the operation at the system level, and shows whether the command itself could be executed or not. The following table describes the possible result codes.

Table 2: OSSI Result Codes

Result Code	Description
0	The command was valid at a system level
100	There was a general failure due to an internal server error
101	The command failed authentication; the account or password does not match between the OSSI and the URL
102	An input stream error occurred (for example, the requested data exceeds maximum size). The maximum size for a single request is 20,000,000 bytes. An example of the error message is: <code>errors.importExport.variableMessageMaxFileSize=Import file exceeds max size of 20M</code>
103	The request is malformed; for example, the XML tags may be invalid. Refer to the XSD of the OSSI query and ensure that no characters appear before the XML header (<code><?xml version="1.0" encoding="UTF-8"?></code>).

Common Commands

This section describes commands that are common to the various OSSI interfaces. These include:

- **Get Version** — allows users to request the OSSI API version number, as a string (for example, “2.0.3”). This enables the user to verify that the OSSI interface being used is the version expected, ensuring that the commands will operate as specified for that version.
- **Distribute Updates** — allows users to trigger an immediate distribution of any pending data changes to the policy servers. This enables the user to queue up many changes in the Configuration Management Platform (CMP) before sending them all at once to the policy servers in the deployment. Alternatively, changes can be distributed one-by-one on a per-command basis. The following types of data are pushed down to the policy servers as part of this request:
 - Topology data, which includes Network Elements and Paths.
 - Tiers
 - Subscriber accounts

- Serving Gateway/MCC-MNC Mapping — allows users to verify input xml files.
- Query OM Stats Setting — allows users to verify the persistent-interval settings for Reset Configuration and Collection Interval.
- Query Absolute Values for Statistics — allows users to retrieve absolute values when **Stats.Interval.Enabled.** is set to false.

Get Version

The following examples show the requests and responses that are defined in the XSDs for the GetVersion tag.

The following is an example of the request that follows the GetVersion tag.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <GetVersion></GetVersion>
</XmlInterfaceRequest>
```

The following example response to the previous request follows the generic Response tag.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">2.2.14</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Distribute Updates

The following examples show the requests and responses that are defined in the XSDs for the DistributeUpdates tag.

The following is an example of the request that follows the DistributeUpdates tag.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <DistributeUpdates></DistributeUpdates>
</XmlInterfaceRequest>
```

The optional ForceSynchronization attribute can be used to force a complete resynchronization of the CMP and Multimedia Policy Engine (MPE) databases. The default value for this attribute is false.

Typically, using this attribute should not be necessary as the system should always be kept in-sync automatically; it is merely provided as a fail-safe measure for unforeseen circumstances. Also note that there is a performance impact from using this attribute, so it should not be used unless deemed necessary by Policy support personnel. The following is an example of this attribute:

```
<?xml version="1.0" encoding="UTF-8" ?>
```

```
<XmlInterfaceRequest>
  <DistributeUpdates ForceSynchronization="true"></DistributeUpdates>
</XmlInterfaceRequest>
```

The following example response to the previous request follows the generic Response tag.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="3">Topology updates successful. Tier updates successful.
    Account updates successful.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Serving Gateway/MCC-MNC Mapping

The following examples show the requests and responses that are defined in the XSDs for the SgwMapping tag.

The following is an example of the request that follows the SgwMapping tag.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes" ?>
<XmlInterfaceRequest>
  <AddSgwMapping>
    <SgwMapping>
      <Name>test</Name>
      <Description>description for the mcc-mnc
      mapping</Description>
      <MccMnc>111111</MccMnc>
      <SgwIpAddress>
        <IpAddress>10.0.0.129</IpAddress>
      </SgwIpAddress>
    </SgwMapping>
  </AddSgwMapping>
</XmlInterfaceRequest>
```

The following example response to the previous request follows the generic Response tag.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1
    Serving Gateway/MCC-MNC Mappings.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Query OM Stats Settings

The following examples show the requests and responses that are defined in the XSDs for the QueryOmStatsSetting tag.

The following is an example of the request that follows the QueryOmStatsSetting tag.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStatsSetting/>
</XmlInterfaceRequest>
```

The following example response to the previous request follows the generic Response tag.

```
<?xml version='1.0' ?>
  <OmStatsSetting>
    <ResetConfiguration>Interval</ResetConfiguration>
    <CollectionInterval>15</CollectionInterval>
  </OmStatsSetting>
```

Query Absolute Values for Statistics

The following examples show the requests and responses that are defined in the XSDs for the Statistics tag.

Note: If Stats.Interval.Enabled is set to true (meaning that Persistent Interval Statistics are in use), then the CMP does not collect absolute counter values.

The following is an example of the request that follows the Statistics tag.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <Statistics/>
</XmlInterfaceRequest>
```

The following example response to the previous request follows the generic Response tag.

```
<?xml version='1.0' ?>
  <Statistics>
    <DiameterAfPeerLatencyStats>
      Absolute statistics values are not available.
    </DiameterAfPeerLatencyStats>
  </Statistics>
```


Chapter 4

Topology Interface

Topics:

- *Topology Interface Requests.....26*
- *Network Elements.....28*
- *Paths.....35*
- *Applications.....39*
- *Traffic Profiles.....42*
- *Time Periods.....46*
- *Charging Servers.....47*
- *Match List.....50*
- *Monitoring Key.....54*
- *AVP Definition.....57*
- *Serving GPRS Support Node.....60*

The Topology Interface allows users to manage and query network elements, paths, and other topology-related objects within the system.

Topology Interface Requests

The Topology Interface consists of the following requests:

- **Network Elements** — A network element represents a node in the network, such as a router, CMTS, PDSN, B-RAS, and so on. The network elements can be organized into logical groups (NetworkGroup) that subdivide the network space. The following are operations that can be requested on Network Elements:
 - **Add Network Element** — Allows users to add new network elements and network element groups. If a network element already exists with the given identifier (Name or NeId), then this is considered an update and the new network element replaces the existing one. All relationships between that network element and other objects in the system will be maintained.
 - **Update Network Element** — Allows users to update existing network elements and network element groups. If no object exists with the given identifier (Name or NeId), then this is a failure condition and the object is not saved.
 - **Add Network Element To Group** — Allows users to associate a network element with a group.
 - **Remove Network Element From Group** — Allows users to remove a network element from within a group.
 - **Delete Network Element** — Allows users to delete a network element.
 - **Delete Network Element Group** — Allows users to delete a network element group.
 - **Query Network Element** — Allows users to query all network elements or a specific network element, returning their configured attributes.
- **Paths** — A path represents a route through the network, and is identified by source and destination network elements. The following are operations that can be requested on Paths:
 - **Add Path** — Allows users to add new paths to the system. If a path already exists with the given identifier (Name), then this is considered an update and the new path replacing the existing one. All relationships between that path and other objects in the system are maintained.
 - **Update Path** — Allows users to update paths within the system. If no object exists with the given identifier (Name), then this is a failure condition and the object is not saved.
 - **Delete Path** — Removes a path from the system.
 - **Query Path** — Allows users to query a specific path or list of paths, returning their configured attributes.
- **Applications** — An application is a service in the network (for example, VoIP) for which quality of service is managed. The following are operations that can be requested on Applications:
 - **AddApplication** — Allows users to add new applications to the system. If an application already exists with the given identifier (Name), then this is considered an update and the new application replaces the existing one. All relationships between that application and other objects in the system are maintained.
 - **UpdateApplication** — Allows users to update application within the system. If no object exists with the given identifier (Name), then this is a failure condition and the object is not saved.
 - **DeleteApplication** — Removes an application from the system.
 - **QueryApplication** — Allows users to query a specific application or list of traffic profiles, returning their configured attributes.

- **Traffic Profiles** — A traffic profile is a set of parameters and their values, which are used in protocol messages to define quality of service for sessions. The following are operations that can be requested on Traffic Profiles:
 - **AddTrafficProfile** — Allows users to add new traffic profiles to the system. If a traffic profile already exists with the given identifier (Name), then this is considered an update and the new traffic profile replaces the existing one. All relationships between that traffic profile and other objects in the system are maintained.
 - **UpdateTrafficProfile** — Allows users to update traffic profiles within the system. If no object exists with the given identifier (Name), then this is a failure condition and the object is not saved.
 - **DeleteTrafficProfile** — Removes a traffic profile from the system.
 - **QueryTrafficProfile** — Allows users to query a specific traffic profile or list of traffic profiles, returning their configured attributes.
- **Time Periods** — A time period defines a set of related time slots, which receives the same quality of service (for example, “the peak time of network usage is Monday through Friday from 9:00 am to 5:00 pm”). The following are operations that can be requested on Time Periods:
 - **AddTimePeriod** — Allows users to add new time periods to the system. If a time period already exists with the given identifier (Name), then this is considered an update and the new time period replaces the existing one. All relationships between that time period and other objects in the system are maintained.
 - **UpdateTimePeriod** — Allows users to update time periods within the system. If no object exists with the given identifier (Name), then this is a failure condition and the object is not saved.
 - **DeleteTimePeriod** — Removes a time period from the system.
 - **QueryTimePeriod** — Allows users to query a specific time period or list of time periods, returning their configured attributes.
- **Charging Servers** — A charging server is a network element that processes accounting information for billing purposes. The following are operations that can be requested on Charging Servers:
 - **AddChargingServer** — Allows users to add new charging servers to the system. If a charging server already exists with the given identifier (Name), then this is considered an update and the new charging server replaces the existing one. All relationships between that charging server and other objects in the system are maintained.
 - **UpdateChargingServer** — Allows users to update charging servers within the system. If no object exists with the given identifier (Name), then this is a failure condition and the object is not saved.
 - **DeleteChargingServer** — Removes a charging server from the system.
 - **QueryChargingServer** — Allows users to query a specific charging server or list of charging servers, returning their configured attributes.
- **Match List** — A match list is a set of values that can be used within one or more policy definitions. The following are operations that can be requested on Match Lists:
 - **AddMatchList** — Allows users to add new match list to the system. If a match list already exists with the given identifier (Name), then this is considered an update and the new match list replaces the existing one. All relationships between that match list and other objects in the system are maintained.
 - **UpdateMatchList** — Allows users to update match lists within the system. If no object exists with the given identifier (Name), then this is a failure condition and the object is not saved.
 - **DeleteMatchList** — Removes a match list from the system.

- QueryMatchList — Allows users to query a specific match list or list of match lists, returning their configured attributes.

Network Elements

A network element represents a node in the network (cable or wireless), such as a router, CMTS, PDSN, B-RAS, and so on. The network elements can be organized into logical groups that subdivide the network space. Network elements have the following attributes that can be requested.

Note: Depending on your system configuration, not all attributes may be present.

Note: The same attributes are also used in the Update Network Element operation.

- Capability — The numerical identity of network element capability type, for example:
 - TDF-Solicit
 - Time-Tariff (PGW,DPI)
 - Usage-Report-26(GGSN,PGW,SWG,DPI)
- SctpEnabled — Whether the Network Element supports diameter over SCTP.
- InitiateDirectConnection — The diameter connection port of the TDF element network.
- TdfPort — The diameter connection port of the TDF element network.
- ReconnectDelay — The delay period after diameter connection fails. The unit is in seconds.
- WatchDogInterval — The time interval of the watch dog monitor.
- ResponseTimeout — The time period before there is a connection response timeout.

The following sections describe the available network tags.

Add Network Element

The following examples show the request and response that are defined in the XSDs for the AddNetworkElement tag.

Note: See [Network Elements](#) for a complete description of Network Elements and Network Element Groups.

Note: For a list of all the attributes that can be associated with a Network Element see: [Topology Interface](#).

Request

This request follows the AddNetworkElement tag defined in the XSDs.

The following example creates a new Network Element to represent a router in the network. It also creates a group, and puts the router in that group.

The router contains the following attributes:

- Name (unique identifier) — Router 23
- Description — Core router for the north east
- HostName (IP address or DNS hostname) — 12.1.1.1
- NeID (another unique identifier) — 112222

- Capacity (aggregate capacity in bps) — 456000

The group contains the following attributes:

- Name— NE Group 1
- Description — All core routers

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <AddNetworkElement>
    <NetworkElement>
      <Name>Router 23</Name>
      <Description>Core router for the north east</Description>
      <HostName>12.1.1.1</HostName>
      <NeId>112222</NeId>
      <NetworkElementType>Router</NetworkElementType>
      <NeSubType></NeSubType>
      <Capacity>456000</Capacity>
    </NetworkElement>
    <NetworkElementGroup>
      <Name>NE Group 1</Name>
      <Description>All core routers</Description>
      <RootGroup>true</RootGroup>
      <ElementRef>
        <Name>router 23</Name>
        <SubGroup>>false</SubGroup>
      </ElementRef>
    </NetworkElementGroup>
  </AddNetworkElement>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

The example XML response that follows represents a successful operation that creates a new network element and/or groups:

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Successfully imported 1 network elements.
    Successfully imported 1 group.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

The example XML response that follows represents an operation that includes both a success and a failure (for example, an attempt to update a group's description field (success), and add an unknown network element "router 24" to the group "NE Group 1" (failed)).

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 groups.</Success>
    <Failure count="1">Failed to update 1 groups. Network Element Group
```

```

update returned an error attempting to add the following: router 24
Group NE Group 1</Failure>
</Command>
</Response>

```

Update Network Element

The following examples show the request and response that are defined in the XSDs for the UpdateNetworkElement tag.

Note: See [Network Elements](#) for a complete description of Network Elements and Network Element Groups.

Note: For a list of all the attributes that can be associated with a Network Element see: [Topology Interface](#).

Request

This request follows the UpdateNetworkElement tag defined in the XSDs.

The following example changes the capacity attribute of the network element named “Router 23” to the new value: 4567000.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <UpdateNetworkElement>
    <NetworkElement>
      <Name>Router 23</Name>
      <Capacity>4567000</Capacity>
    </NetworkElement>
  </UpdateNetworkElement>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 network elements.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Add Network Element to Group

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the AddNetworkElementToGroup tag.

Request

This request follows the AddNetworkElementToGroup tag defined in the XSDs.

The following example adds three network elements (Router 2, Router 34, and Router 131) to a group (Group 1).

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <AddNetworkElementToGroup>
    <GroupName>Group 1</GroupName>
    <Name>Router 2</Name>
    <Name>Router 34</Name>
    <Name>Router 131</Name>
  </AddNetworkElementToGroup>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="3">Added 3 elements to a group.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Remove Network Element from Group

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the RemoveNetworkElementFromGroup tag.

Request

This request follows the RemoveNetworkElementFromGroup tag defined in the XSDs.

The following example removes two network elements (Router 34 and Router 131) from a group (Group 1).

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <RemoveNetworkElementFromGroup>
    <GroupName>Group 1</GroupName>
    <Name>Router 34</Name>
    <Name>Router 131</Name>
  </RemoveNetworkElementFromGroup>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Removed 2 elements from group.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete Network Element

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the DeleteNetworkElement tag.

Request

This request follows the DeleteNetworkElement tag defined in the XSDs.

The following example deletes two network elements (Node 1 and Node 2).

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <DeleteNetworkElement>
    <Name>Node1</Name>
    <Name>Node2</Name>
  </DeleteNetworkElement>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Deleted 2 elements.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete Network Element Group

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the DeleteNetworkElementGroup tag.

Request

This request follows the DeleteNetworkElementGroup tag defined in the XSDs.

The following example deletes two network element groups (Group 1 and Group 2).

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <DeleteNetworkElementGroup>
    <Name>Group 1</Name>
    <Name>Group 2</Name>
  </DeleteNetworkElementGroup>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Deleted 2 network element groups.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Query Network Elements

Note: This query is not available to Policy servers in S-CMP mode.

The following examples show the request and response that are defined in the XSDs for the QueryNetworkElement tag.

Request

This request follows the QueryNetworkElement tag defined in the XSDs.

Example 1 — XML for querying multiple network elements by name.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryNetworkElement>
    <Name>NE A</Name>
    <Name>NE B</Name>
  </QueryNetworkElement>
</XmlInterfaceRequest>
```

Example 2 — XML for querying all network elements and groups.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryNetworkElement>
  </QueryNetworkElement>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > NetworkElement** tag defined in the XSDs.

```
<ConfigurationData version="2.1.6">
  <NetworkElement>
    <Name>vod-1</Name>
    <Description/>
    <HostName/>
    <BackupHostName/>
    <NeId>vod-1</NeId>
    <NetworkElementType>Server</NetworkElementType>
    <NeSubType>None</NeSubType>
    <Capacity>0</Capacity>
    <X>0</X>
    <Y>0</Y>
    <ManualSubnet>
      <IpAddress>88.0.0.0</IpAddress>
      <Mask>8</Mask>
    </ManualSubnet>
  </NetworkElement>
  <NetworkElement>
    <Name>erx-1</Name>
    <Description/>
    <HostName/>
    <BackupHostName/>
    <NeId>erx-1</NeId>
    <NetworkElementType>B-RAS</NetworkElementType>
    <NeSubType>ERX</NeSubType>
    <Capacity>0</Capacity>
    <X>0</X>
    <Y>0</Y>
    <ManualSubnet>
      <IpAddress>1.0.0.0</IpAddress>
      <Mask>8</Mask>
    </ManualSubnet>
    <NEInterface>
      <Name>8/0</Name>
      <Description/>
      <Capacity>0</Capacity>
    </NEInterface>
  </NetworkElement>
  <NetworkElement>
    <Name>router-1</Name>
    <Description/>
    <HostName/>
    <BackupHostName/>
    <NeId>router-1</NeId>
    <NetworkElementType>Router</NetworkElementType>
    <NeSubType>None</NeSubType>
    <Capacity>0</Capacity>
    <X>0</X>
    <Y>0</Y>
  </NetworkElement>
  <NetworkElement>
    <Name>router-2</Name>
    <Description/>
    <HostName/>
    <BackupHostName/>
    <NeId>router-2</NeId>
    <NetworkElementType>Router</NetworkElementType>
    <NeSubType>None</NeSubType>
    <Capacity>0</Capacity>
```

```

        <X>0</X>
        <Y>0</Y>
    </NetworkElement>
    <NetworkElement>
        <Name>mx-1</Name>
        <Description/>
        <HostName>10.60.100.101</HostName>
        <BackupHostName/>
        <NeId/>
        <NetworkElementType>Wireline Gateway</NetworkElementType>
        <NeSubType>MX Series</NeSubType>
        <Capacity>0</Capacity>
        <X>0</X>
        <Y>0</Y>
        <DiameterRealm>juniper.com</DiameterRealm>
        <ManualSubnet>
            <IpAddress>11.0.0.0</IpAddress>
            <Mask>8</Mask>
        </ManualSubnet>
        <Nediameterid>
            <NediameteridStr>mx.juniper.com</NediameteridStr>
        </Nediameterid>
    </NetworkElement>
</ConfigurationData>

```

Paths

A path represents a route through the network, and is identified by source and destination network elements.

Add Path

The following examples show the request and response that are defined in the XSDs for the AddPath tag.

Request

This request follows the AddPath tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
    <AddPath>
        <Path>
            <Name>Path1</Name>
            <Description/>
            <Hops>
                <Hop>
                    <NeName>arris1</NeName>
                </Hop>
                <Hop>
                    <NeName>cisco1</NeName>
                </Hop>
                <Hop>
                    <NeName>moto1</NeName>
                </Hop>
            </Hops>
        </Path>
    </AddPath>
</XmlInterfaceRequest>

```

```

        </Hops>
    </Path>
    <Path>
        <Name>Path2</Name>
        <Description/>
        <Hops>
            <Hop>
                <NeName>moto2</NeName>
            </Hop>
            <Hop>
                <NeName>cisco2</NeName>
            </Hop>
            <Hop>
                <NeName>arris2</NeName>
            </Hop>
        </Hops>
    </Path>
    <Path>
        <Name>Path3</Name>
        <Description/>
        <Hops>
            <Hop>
                <NeName>arris3</NeName>
            </Hop>
            <Hop>
                <NeName>moto3</NeName>
            </Hop>
        </Hops>
    </Path>
</AddPath>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
    <Result>0</Result>
    <Command type="XmlInterfaceResponse">
        <Success count="3">Successfully imported 3 paths.</Success>
        <Failure count="0"></Failure>
    </Command>
</Response>

```

Update Path

The following examples show the request and response that are defined in the XSDs for the UpdatePath tag.

Request

This request follows the UpdatePath tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
    <UpdatePath>
        <Path>

```

```

    <Name>Path1</Name>
    <Hops>
      <Hop>
        <NeName>moto1</NeName>
      </Hop>
      <Hop>
        <NeName>cisco1</NeName>
      </Hop>
      <Hop>
        <NeName>arris2</NeName>
      </Hop>
    </Hops>
  </Path>
</UpdatePath>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 paths.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Delete Path

The following examples show the request and response that are defined in the XSDs for the DeletePath tag.

Request

This request follows the DeletePath tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <DeletePath>
    <Name>Path1</Name>
    <Name>Path2</Name>
  </DeletePath>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Deleted 2 paths.</Success>
    <Failure count="0"></Failure>
  </Command>

```

```

    </Command>
</Response>

```

Query Path

The following examples show the request and response that are defined in the XSDs for the QueryPath tag.

Request

This request follows the QueryPath tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryPath>
    <Name>Path1</Name>
    <Name>Path2</Name>
  </QueryPath>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **ConfigurationData > Path** tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="2.1.6">
  <Path>
    <Name>Path1</Name>
    <Description/>
    <Source>
      <Address>1.1.1.2</Address>
      <Mask>24</Mask>
    </Source>
    <Destination>
      <Address>3.3.3.2</Address>
      <Mask>24</Mask>
    </Destination>
    <Hops>
      <Hop>
        <NeName>arris</NeName>
      </Hop>
      <Hop>
        <NeName>cisco</NeName>
      </Hop>
      <Hop>
        <NeName>moto</NeName>
      </Hop>
    </Hops>
  </Path>
  <Path>
    <Name>Path2</Name>
    <Description/>
    <Source>
      <Address>3.3.3.2</Address>
      <Mask>24</Mask>
    </Source>
    <Destination>
      <Address>1.1.1.2</Address>
    </Destination>
  </Path>
</ConfigurationData>

```

```

        <Mask>24</Mask>
    </Destination>
    <Hops>
        <Hop>
            <NeName>moto</NeName>
        </Hop>
        <Hop>
            <NeName>cisco</NeName>
        </Hop>
        <Hop>
            <NeName>arris</NeName>
        </Hop>
    </Hops>
</Path>
</ConfigurationData>

```

Applications

An application is a service in the network (for example, VoIP) for which Quality of Service (QoS) is managed.

Add Application

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the AddApplication tag.

Request

This request follows the AddApplication tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddApplication>
    <Application>
      <Name>VoD</Name>
      <Description>Video on Demand</Description>
      <LatencySensitive>true</LatencySensitive>
      <Tracked>true</Tracked>
      <UpGatesPerSession>1</UpGatesPerSession>
      <DownGatesPerSession>1</DownGatesPerSession>
      <TrackingTimeoutTime>240</TrackingTimeoutTime>
      <TrackingTimeoutUnit>1</TrackingTimeoutUnit>
    </Application>
  </AddApplication>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>

```

```

<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1 applications.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Update Application

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the UpdateApplication tag.

Request

This request follows the UpdateApplication tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateApplication>
    <Application>
      <Name>VoD</Name>
      <Description>Video on Demand</Description>
      <LatencySensitive>>false</LatencySensitive>
      <UpGatesPerSession>3</UpGatesPerSession>
    </Application>
  </UpdateApplication>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 applications.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Delete Application

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the DeleteApplication tag.

Request

This request follows the DeleteApplication tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <DeleteApplication>
    <Name>VoD</Name>
  </DeleteApplication>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Deleted 1 applications.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Query Application

The following examples show the request and response that are defined in the XSDs for the QueryApplication tag.

Request

This request follows the QueryApplication tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QueryApplication/>
</XmlInterfaceRequest>
```

Response

The response to this request follows the ConfigurationData -> Application tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="2.1.6">
  <Application>
    <Name>VoD</Name>
    <Description>Video on Demand</Description>
    <LatencySensitive>true</LatencySensitive>
    <Tracked>true</Tracked>
    <UpGatesPerSession>1</UpGatesPerSession>
    <DownGatesPerSession>1</DownGatesPerSession>
    <TrackingTimeoutTime>240</TrackingTimeoutTime>
    <TrackingTimeoutUnit>1</TrackingTimeoutUnit>
  </Application>
</ConfigurationData>
```

Traffic Profiles

A traffic profile is a set of parameters and their values, which are used in protocol messages to define QoS for sessions.

Add Traffic Profile

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the AddTrafficProfile tag.

Request

This request follows the AddTrafficProfile tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
XmlInterfaceRequest
  <AddTrafficProfile>
    <QosProfile>
      <Name>default-rule-traffic-profile</Name>
      <ProfileType>0</ProfileType>
      <QosProfileType>Diameter QoS</QosProfileType>
      <QosProfileProfileParam>
        <ProfileParamUid>param.diameter.qosProfile.profileTypeNumber
        </ProfileParamUid>
        <ParamValue>10</ParamValue>
      </QosProfileProfileParam>
      <QosProfileProfileParam>
        <ProfileParamUid>param.diameter.qosProfile.qci
        </ProfileParamUid>
        <ParamValue>3</ParamValue>
      </QosProfileProfileParam>
      <QosProfileProfileParam>
        <ProfileParamUid>param.diameter.qosProfile.maxAuthUL
        </ProfileParamUid>
        <ParamValue></ParamValue>
      </QosProfileProfileParam>
      <QosProfileProfileParam>
        <ProfileParamUid>param.diameter.qosProfile.maxAuthDL
        </ProfileParamUid>
        <ParamValue></ParamValue>
      </QosProfileProfileParam>
      <QosProfileProfileParam>
        <ProfileParamUid>param.diameter.qosProfile.minRateUL
        </ProfileParamUid>
        <ParamValue></ParamValue>
      </QosProfileProfileParam>
      <QosProfileProfileParam>
        <ProfileParamUid>param.diameter.qosProfile.minRateDL
        </ProfileParamUid>
        <ParamValue></ParamValue>
      </QosProfileProfileParam>
      <QosProfileProfileParam>
        <ProfileParamUid>param.diameter.qosProfile.ARP.PriorityLevel
        </ProfileParamUid>
        <ParamValue></ParamValue>
      </QosProfileProfileParam>
    </QosProfile>
  </AddTrafficProfile>
</XmlInterfaceRequest>
```

```

        </QosProfileProfileParam>
        <QosProfileProfileParam>
          <ProfileParamUid>param.diameter.qosProfile.ARP
            .PreemptionCapability</ProfileParamUid>
          <ParamValue></ParamValue>
        </QosProfileProfileParam>
        <QosProfileProfileParam>
          <ProfileParamUid>param.diameter.qosProfile.ARP
            .PreemptionVulnerability</ProfileParamUid>
          <ParamValue></ParamValue>
        </QosProfileProfileParam>
        <QosProfileProfileParam>
          <ProfileParamUid>param.diameter.qosProfile
            .ResourceAllocationNotification</ProfileParamUid>
          <ParamValue></ParamValue>
        </QosProfileProfileParam>
      </QosProfile>
    <QosProfileGroup>
      <Name>group1</Name>
      <Description></Description>
      <RootGroup>true</RootGroup>
      <ElementRef>
        <Name>default-rule-traffic-profile</Name>
        <SubGroup>false</SubGroup>
      </ElementRef>
    </QosProfileGroup>
  </AddTrafficProfile>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1 Traffic Profile(s).</Success>

    <Failure count="0"></Failure>
  </Command>
</Response>

```

Update Traffic Profile

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the UpdateTrafficProfile tag.

Request

This request follows the UpdateTrafficProfile tag defined in the XSDs.

```

<<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateTrafficProfile>
    <QosProfile>

```

```

        <Name>default-rule-traffic-profile</Name>
        <ProfileType>0</ProfileType>
        <QosProfileType>Second Predefined PCC Rule</QosProfileType>
    </QosProfile>
</UpdateTrafficProfile>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
    <Result>0</Result>
    <Command type="XmlInterfaceResponse">
        <Success count="1">Successfully updated 1 Traffic Profile(s).</Success>

        <Failure count="0"></Failure>
    </Command>
</Response>

```

Delete Traffic Profile

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the DeleteTrafficProfile tag.

Request

This request follows the DeleteTrafficProfile tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
    <DeleteTrafficProfile>
        <Name>default-rule-traffic-profile</Name>
    </DeleteTrafficProfile>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
    <Result>0</Result>
    <Command type="XmlInterfaceResponse">
        <Success count="1">Deleted 1 Traffic Profile(s).</Success>
        <Failure count="0"></Failure>
    </Command>
</Response>

```

Query Traffic Profile

The following examples show the request and response that are defined in the XSDs for the QueryTrafficProfile tag that queries all traffic profiles:

Request

This request follows the QueryTrafficProfile tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QueryTrafficProfile/>
</XmlInterfaceRequest>
```

Response

The response to this request follows the ConfigurationData -> QosProfile tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="">
  <QosProfile>
    <Name>default-rule-traffic-profile</Name>
    <ProfileType>0</ProfileType>
    <QosProfileType>Predefined PCC Rule</QosProfileType>
    <QosProfileProfileParam>
      <ProfileParamUid>param.diameter.pccPredefRule.profileTypeNumber
      </ProfileParamUid>
      <ParamValue>11</ParamValue>
    </QosProfileProfileParam>
    <QosProfileProfileParam>
      <ProfileParamUid>param.diameter.pccPredefRule.name
      </ProfileParamUid>
      <ParamValue>PCRF-DEFAULT</ParamValue>
    </QosProfileProfileParam>
    <QosProfileProfileParam>
      <ProfileParamUid>param.diameter.pccPredefRule.description
      </ProfileParamUid>
      <ParamValue>This is the static rule that gets applied by default
      </ParamValue>
    </QosProfileProfileParam>
  </QosProfile>
  <QosProfile>
    <Name>p2p-rule-traffic-profile</Name>
    <ProfileType>0</ProfileType>
    <QosProfileType>Predefined PCC Rule</QosProfileType>
    <QosProfileProfileParam>
      <ProfileParamUid>param.diameter.pccPredefRule.profileTypeNumber
      </ProfileParamUid>
      <ParamValue>11</ParamValue>
    </QosProfileProfileParam>
    <QosProfileProfileParam>
      <ProfileParamUid>param.diameter.pccPredefRule.name </ProfileParamUid>
      <ParamValue>P2P-RATE-LIMIT-64K</ParamValue>
    </QosProfileProfileParam>
    <QosProfileProfileParam>
      <ProfileParamUid>param.diameter.pccPredefRule.description
      </ProfileParamUid>
      <ParamValue>Rule limits bit-torrent and other peer to peer
```

```

applications
    to 64Kbps downstream</ParamValue>
    </QosProfileProfileParam>
</QosProfile>
</ConfigurationData>

```

Time Periods

A time period defines a set of related time slots, which receives the same QoS (for example, “the peak time of network usage is Monday through Friday from 9:00 am to 5:00 pm”).

Add Time Period

Note: This query is not available to Policy servers in NW-CMP mode.

Update Time Period

Note: This query is not available to Policy servers in NW-CMP mode.

Delete Time Slot

Request

This delete timeslot request follows the UpdateTimePeriod tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateTimePeriod>
    <TimePeriod>
      <Name>timeperiod1</Name>
      <Description>ss</Description>
      <Precedence>3</Precedence>
      <TimeSlot operation="delete">
        <Mask>8</Mask>
        <YearStr>2016, 2017</YearStr>
        <MonthMask>2</MonthMask>
        <DayStr>8, 22</DayStr>
        <Reverse>false</Reverse>
        <StartTime>50100000</StartTime>
        <EndTime>53100000</EndTime>
        <StartDate></StartDate>
        <EndDate></EndDate>
      </TimeSlot>
    </TimePeriod>
  </UpdateTimePeriod>
</XmlInterfaceRequest>

```

Response

The response to this request follows the delete timeslot Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1 Time Period(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete Time Period

Note: This query is not available to Policy servers in NW-CMP mode.

Charging Servers

A charging server is a network element that processes accounting information for billing purposes.

Add Charging Server

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the AddChargingServer tag.

Request

This request follows the AddChargingServer tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddChargingServer>
    <ChargingServer>
      <Name>chargingServer_import1</Name>
      <Description></Description>
      <Security>true</Security>
      <HostName>80.20.20.101</HostName>
      <Port>4040</Port>
      <Transport>udp</Transport>
      <Protocol>radius</Protocol>
    </ChargingServer>
    <ChargingServer>
      <Name>chargingServer_import2</Name>
      <Description></Description>
      <Security>false</Security>
      <HostName>12.6.43.201</HostName>
      <Port>7089</Port>
      <Transport>tcp</Transport>
```

```

        <Protocol>tacacs+</Protocol>
    </ChargingServer>
</AddChargingServer>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
    <Result>0</Result>
    <Command type="XmlInterfaceResponse">
        <Success count="2">Successfully imported 2 Charging Server(s).</Success>

        <Failure count="0"></Failure>
    </Command>
</Response>

```

Update Charging Server

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the UpdateChargingServer tag.

Request

This request follows the UpdateChargingServer tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
    <UpdateChargingServer>
        <ChargingServer>
            <Name>chargingServer_3</Name>
            <Description></Description>
            <Security>true</Security>
            <HostName>80.20.20.100</HostName>
            <Port>6040</Port>
            <Transport>tcp</Transport>
            <Protocol>radius</Protocol>
        </ChargingServer>
    </UpdateChargingServer>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
    <Result>0</Result>
    <Command type="XmlInterfaceResponse">
        <Success count="1">Successfully updated 1 Charging Server(s).</Success>

        <Failure count="0"></Failure>
    </Command>

```



```

    </Command>
</Response>

```

Delete Charging Server

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the DeleteChargingServer tag.

Request

This request follows the DeleteChargingServer tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <DeleteChargingServer>
    <Name>chs1</Name>
  </DeleteChargingServer>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Deleted 1 Charging Server(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Query Charging Server

The following examples show the request and response that are defined in the XSDs for the QueryChargingServer tag.

Request

This request follows the QueryChargingServer tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryChargingServer>
    <Name>chargingServer_3</Name>
    <Name>chargingServer_4</Name>
    <Name>chargingServer_import1</Name>
    <Name>chargingServer_import2</Name>
  </QueryChargingServer>
</XmlInterfaceRequest>

```

Response

The response to this request follows the ConfigurationData -> ChargingServer tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="">
  <ChargingServer>
    <Name>chargingServer_3</Name>
    <Description></Description>
    <Security>true</Security>
    <HostName>80.20.20.100</HostName>
    <Port>4040</Port>
    <Transport>udp</Transport>
    <Protocol>radius</Protocol>
  </ChargingServer>
  <ChargingServer>
    <Name>chargingServer_4</Name>
    <Description></Description>
    <Security>>false</Security>
    <HostName>12.6.43.200</HostName>
    <Port>7089</Port>
    <Transport>tcp</Transport>
    <Protocol>tacacs+</Protocol>
  </ChargingServer>
  <ChargingServer>
    <Name>chargingServer_import1</Name>
    <Description></Description>
    <Security>true</Security>
    <HostName>80.20.20.101</HostName>
    <Port>4040</Port>
    <Transport>udp</Transport>
    <Protocol>radius</Protocol>
  </ChargingServer>
  <ChargingServer>
    <Name>chargingServer_import2</Name>
    <Description></Description>
    <Security>>false</Security>
    <HostName>12.6.43.201</HostName>
    <Port>7089</Port>
    <Transport>tcp</Transport>
    <Protocol>tacacs+</Protocol>
  </ChargingServer>
</ConfigurationData>
```

Match List

The match list is a set of values that can be used within one or more policy definitions. When the user writes a policy rule to compare against a value in a list, the list or set of lists to be used for comparison is explicitly specified. For example:

“Where the SGSNIpAddress is contained in MaltaSgsnList, GreekSgsnList”

The Match List Type determines what kind of values can be specified in that list and how those values are matched within the policy rule. Types can be “IPv4 Address” (allows address and subnet), “IPv6 Address”(allows address and prefix), “String”, and “Wildcard”.

Add Match List

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the AddMatchList tag.

Request

This request follows the AddMatchList tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddMatchList>
    <TokenList>
      <Name>match_list_01a_sgsn</Name>
      <Description>This is a match list that will match the given
        SGSN</Description>
      <ItemType>3</ItemType>
      <TokenListItem>
        <Value>44.44.44.44</Value>
      </TokenListItem>
      <TokenListItem>
        <Value>55.55.55.55</Value>
      </TokenListItem>
      <TokenListItem>
        <Value>66.66.66.66</Value>
      </TokenListItem>
    </TokenList>
    <TokenList>
      <Name>match_list_01b_sgsn_black</Name>
      <Description />
      <ItemType>1</ItemType>
      <TokenListItem>
        <Value>44.44.44.44</Value>
      </TokenListItem>
      <TokenListItem>
        <Value>55.55.55.55</Value>
      </TokenListItem>
      <TokenListItem>
        <Value>66.66.66.66</Value>
      </TokenListItem>
    </TokenList>
  </AddMatchList>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Successfully imported 2 Match List(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Update Match List

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the UpdateMatchList tag.

Request

This request follows the UpdateMatchList tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateMatchList>
    <TokenList>
      <Name>match_list_01a_sgsn</Name>
      <Description>This is an updated match list that will match the
        given SGSN</Description>
      <ItemType>3</ItemType>
      <TokenListItem>
        <Value>44.44.44.77</Value>
      </TokenListItem>
      <TokenListItem>
        <Value>66.66.66.77</Value>
      </TokenListItem>
    </TokenList>
  </UpdateMatchList>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 Match List(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete Match List

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the DeleteMatchList tag.

Request

This request follows the DeleteMatchList tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
```

```

    <DeleteMatchList>
      <Name>match_list_01a_sgsn</Name>
    </DeleteMatchList>
  </XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Deleted 1 Match List(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Query Match List

The following examples show the request and response that are defined in the XSDs for the QueryMatchList tag.

Request

This request follows the QueryMatchList tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryMatchList>
    <Name>match_list_01a_sgsn</Name>
    <Name>match_list_01b_sgsn_black</Name>
  </QueryMatchList>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="">
  <TokenList>
    <Name>match_list_01a_sgsn</Name>
    <Description>This is a match list that will match the given
      SGSN</Description>
    <ItemType>3</ItemType>
    <TokenListItem>
      <Value>44.44.44.77</Value>
    </TokenListItem>
    <TokenListItem>
      <Value>66.66.66.77</Value>
    </TokenListItem>
  </TokenList>
  <TokenList>
    <Name>match_list_01b_sgsn_black</Name>
    <Description />
  </TokenList>

```

```

    <ItemType>1</ItemType>
    <TokenListItem>
      <Value>44.44.44.44</Value>
    </TokenListItem>
    <TokenListItem>
      <Value>55.55.55.55</Value>
    </TokenListItem>
    <TokenListItem>
      <Value>66.66.66.66</Value>
    </TokenListItem>
  </TokenList>
</ConfigurationData>

```

Monitoring Key

A monitoring key is a unique character string that identifies the quota profile to be used by a policy and charging control (PCC) rule for usage tracking. The monitoring key is associated with the quota profile by selecting a policy action that grants usage to a selected number of quota profiles.

Add Monitoring Key

The following examples show the request and response that are defined in the XSDs for the AddMonitoringKey tag.

Request

This request follows the AddMonitoringKey tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddMonitoringKey>
    <MonitoringKey>
      <Name>Monitoring Key 1</Name>
      <Description>Monitoring Key 1</Description>
      <MonitoringType>0</MonitoringType>
      <MonitoringKey>KEY_1</MonitoringKey>
    </MonitoringKey>
    <MonitoringKey>
      <Name>Monitoring Key 2</Name>
      <Description></Description>
      <MonitoringType>2</MonitoringType>
      <MonitoringKey>KEY_2</MonitoringKey>
    </MonitoringKey>
  </AddMonitoringKey>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>

```

```

    <Command type="XmlInterfaceResponse">
      <Success count="2">Successfully imported 2
monitoringKey(s).</Success>
      <Failure count="0"></Failure>
    </Command>
  </Response>

```

Update Monitoring Key

The following examples show the request and response that are defined in the XSDs for the UpdateMonitoringKey tag.

Request

This request follows the UpdateMonitoringKey tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateMonitoringKey>
    <MonitoringKey>
      <Name>Monitoring Key 2</Name>
      <Description></Description>
      <MonitoringType>2</MonitoringType>
      <MonitoringKey>KEY_2</MonitoringKey>
    </MonitoringKey>
  </UpdateMonitoringKey>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response> <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 monitoringKey(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Delete Monitoring Key

The following examples show the request and response that are defined in the XSDs for the DeleteMonitoringKey tag.

Request

This request follows the DeleteMonitoringKey tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <DeleteMonitoringKey>
    <MonitoringKey>
      <Name>Monitoring Key 2</Name>

```

```

    </MonitoringKey>
  </DeleteMonitoringKey>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Deleted 1 Monitoring Keys.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Query Monitoring Key

The following examples show the request and response that are defined in the XSDs for the QueryMonitoringKey tag.

Request

This request follows the QueryMonitoringKey tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryMonitoringKey>
    <Name>Monitoring Key 1</Name>
  </QueryMonitoringKey>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **ConfigurationData > MonitoringKey** tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="8.0.0">
  <MonitoringKey>
    <Name>Monitoring Key 1</Name>
    <Description>Monitoring Key 1</Description>
    <MonitoringType>0</MonitoringType>
    <MonitoringKey>KEY_1</MonitoringKey>
  </MonitoringKey>
</ConfigurationData>

```


AVP Definition

An AVP is a Diameter protocol used to encapsulate protocol-specific information with usage monitoring supported by the MPE. Diameter messages such as AAR, CCA, CCR, and RAR, are supported by 3rd Party AVP policy conditions. The supported outgoing messages set or remove 3rd Party AVPs in Diameter.

Add AVP Definition

The following examples show the request and response that are defined in the XSDs for the AddAvpDefinition tag.

Request

This request follows the AddAvpDefinition tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddAvpDefinition>
    <AvpDefinition>
      <Name>AVPSAMPLE:1123</Name>
      <Description></Description>
      <AvpName>AVPSAMPLE</AvpName>
      <AvpCode>0</AvpCode>
      <VendorId>1123</VendorId>
      <MandatoryFlag>>false</MandatoryFlag>
      <ProtectFlag>>false</ProtectFlag>
      <MayencryptFlag>>false</MayencryptFlag>
      <VendorSpecificFlag>>true</VendorSpecificFlag>
      <AvpType>float32</AvpType>
      <RootAvp></RootAvp>
    </AvpDefinition>
  </AddAvpDefinition>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1 AVP Definition(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Update AVP Definition

The following examples show the request and response that are defined in the XSDs for the UpdateAvpDefinition tag.

Request

This request follows the UpdateAvpDefinition tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateAvpDefinition>
    <AvpDefinition>
      <Name>AVPSAMPLE:1123</Name>
      <Description></Description>
      <AvpName>AVPSAMPLE</AvpName>
      <AvpCode>567</AvpCode>
      <VendorId>1123</VendorId>
      <MandatoryFlag>false</MandatoryFlag>
      <ProtectFlag>false</ProtectFlag>
      <MayencryptFlag>false</MayencryptFlag>
      <VendorSpecificFlag>true</VendorSpecificFlag>
      <AvpType>float32</AvpType>
      <RootAvp></RootAvp>
    </AvpDefinition>
  </UpdateAvpDefinition>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1 AVP Definition(s).</Success>

    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete AVP Definition

The following examples show the request and response that are defined in the XSDs for the DeleteAvpDefinition tag.

Request

This request follows the DeleteAvpDefinition tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <DeleteAvpDefinition>
    <AvpDefinition>
      <Name>AVPSAMPLE:1123</Name>
    </AvpDefinition>
  </DeleteAvpDefinition>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Deleted 1 AVP Definition(s)</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Query AVP Definition

The following examples show the request and response that are defined in the XSDs for the QueryAvpDefinition tag.

Request

This request follows the QueryAvpDefinition tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QueryAvpDefinition>
    <AvpDefinition>
      <Name>AVPSAMPLE:1123</Name>
    </AvpDefinition>
  </QueryAvpDefinition>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > AvpDefinition** tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="8.0.0">
  <AvpDefinition>
    <Name>AVPSAMPLE:1123</Name>
    <Description></Description>
    <AvpName>AVPSAMPLE</AvpName>
    <AvpCode>123</AvpCode>
    <VendorId>1123</VendorId>
    <MandatoryFlag>false</MandatoryFlag>
    <ProtectFlag>false</ProtectFlag>
    <MayencryptFlag>false</MayencryptFlag>
    <VendorSpecificFlag>true</VendorSpecificFlag>
    <AvpType>float32</AvpType>
    <RootAvp></RootAvp>
  </AvpDefinition>
</ConfigurationData>
```

Serving GPRS Support Node

A Serving GPRS Support Node (SGSN) may not provide a Gateway GPRS Support Node (GGSN) with accurate or complete mobile country code (MCC) or mobile network code (MNC) information. If not, the GGSN cannot pass this information on to the PCRF (including an MPE device), reducing the PCRF's ability to detect specific roaming scenarios. The MCC/MNC mapping table provides a mechanism for the MPE device to convert an SGSN IP address (a value the GGSN can determine without SGSN input) to the proper MCC/MNC value. You can map multiple serving gateways to each MCC/MNC pair. Once the MCC/MNC values are determined, they can be used in policies to differentiate subscriber treatment based on the specific roaming scenario.

Add SGSN

The following examples show the request and response that are defined in the XSDs for the Add tag.

Request

This request follows the AddSgwMapping tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSgwMapping>
    <SgwMapping>
      <Name>SGSN-1</Name>
      <Description>SGSN-1</Description>
      <MccMnc>12345</MccMnc>
      <SgwIpAddress>
        <IpAddress>10.60.25.33</IpAddress>
      </SgwIpAddress>
    </SgwMapping>
  </AddSgwMapping>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1 Serving Gateway/MCC-MNC
Mapping(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Update SGSN

The following examples show the request and response that are defined in the XSDs for the UpdateSgwMapping tag.

Request

This request follows the UpdateSgwMapping tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateSgwMapping>
    <SgwMapping>
      <Name>SGSN-1</Name>
      <Description>SGSN-1</Description>
      <MccMnc>12345</MccMnc>
      <SgwIpAddress>
        <IpAddress>10.60.25.33</IpAddress>
      </SgwIpAddress>
    </SgwMapping>
  </UpdateSgwMapping>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 Serving Gateway/MCC-MNC
Mapping(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete SGSN

The following examples show the request and response that are defined in the XSDs for the DeleteSgwMapping tag.

Request

This request follows the DeleteSgwMapping tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <DeleteSgwMapping>
    <SgwMapping>
      <Name>SGSN-1</Name>
    </SgwMapping>
  </DeleteSgwMapping>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
```

```

<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Delete 1 Serving Gateway/MCC-MNC mappings.</Success>

    <Failure count="0"></Failure>
  </Command>
</Response>

```

Query SGSN

The following examples show the request and response that are defined in the XSDs for the QuerySgwmapping tag.

Request

This request follows the QuerySgwmapping tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QuerySgwMapping>
    <Name>SGSN-1</Name>
  </QuerySgwMapping>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **ConfigurationData > AvpDefinition** tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="8.0.0">
  <SgwMapping>
    <Name>SGSN-1</Name>
    <Description>SGSN-1</Description>
    <MccMnc>12345</MccMnc>
    <SgwIpAddress>
      <IpAddress>10.60.25.33</IpAddress>
    </SgwIpAddress>
  </SgwMapping>
</ConfigurationData>

```

Chapter 5

Subscriber Interface

Topics:

- [*Accounts.....64*](#)
- [*Tiers.....68*](#)
- [*Quota Profiles.....71*](#)
- [*Quota Conventions.....80*](#)
- [*Setting SCTP Settings.....83*](#)

The Subscriber Interface allows users to manage and query subscriber elements within their system. Subscriber data includes accounts and tiers.

Accounts

An account represents a billable entity that contains the individual users.

Overview

The Subscriber Interface consists of the following requests:

- Accounts — An account represents a billable entity that contains the individual users.
 - *Add Account* — Allows users to add and update subscriber accounts within their system. If an account already exists with the given identifier (Account ID), then this is considered an update and the new account replaces the existing one. All relationships between that account and other objects in the system (for example, tiers) are maintained.
 - *Update Account* — Allows users to update accounts in their system. If no object exists with the given identifier (Account ID), then this is a failure condition and the object is not saved.
 - *Delete Account* — Allows users to delete an account.
 - *Query Account* — Allows users to query a specific account or list of accounts, returning their configured attributes.
- Tiers — A tier represents a class of service or a logical grouping of subscriber accounts.
 - *Add Tier* — Allows users to add new tiers to their system. If a tier already exists with the given identifier (Name), then this is considered an update and the new tier replaces the existing one. All relationships between that tier and other objects in the system (for example, accounts) are maintained.
 - *Update Tier* — Allows users to update tiers within their system. If no object exists with the given identifier (Name), then this is a failure condition and the object is not saved.
 - *Delete Tier* — Allows users to delete a tier.
 - *Query Tier* — Allows users to query a specific tier or list of tiers, returning their configured attributes.

Add Account

The following examples show the request and response that are defined in the XSDs for the AddAccount tag.

Request

This request follows the AddAccount tag defined in the XSDs.

The following example creates an account with the following attributes:

- Account ID — 000123
- Association — to a network element named: Node1
- One user in this account, with the following attributes:
 - User ID — bill_smith@company.com
- One cable modem in this account, with the following attributes:

- MAC address — 10:10:10:10:10:11
- IP address — 30.0.0.3
- Two CPEs behind this cable modem: 10.0.0.3, 20.0.0.3
- Association to a tier named: Premium

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
<AddAccount>
  <Account>
    <AccountId>000123</AccountId>
    <NetworkElementName>Node1</NetworkElementName>
    <EndUser>
      <EndUserId>john_smith@company.com</EndUserId>
    </EndUser>
    <CableModem>
      <CmMacAddr>10:10:10:10:10:11</CmMacAddr>
      <CmIpAddr>30.0.0.3</CmIpAddr>
      <Cpe>
        <CpeIpAddr>10.0.0.3</CpeIpAddr>
      </Cpe>
      <Cpe>
        <CpeIpAddr>20.0.0.3</CpeIpAddr>
      </Cpe>
    </CableModem>
    <TierRef>
      <Name>Premium</Name>
    </TierRef>
  </Account>
</AddAccount>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse" >
    <Success count="1">Successfully imported 1 accounts.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Update Account

The following examples show the request and response that are defined in the XSDs for the UpdateAccount tag.

Request

This request follows the UpdateAccount tag defined in the XSDs.

The following example updates the account identified by ID 000123 to add a new user with ID jane_doe@company.com.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <UpdateAccount>
    <Account>
      <AccountId>000123</AccountId>
      <EndUser operator="add">
        <EndUserId>jane_doe@company.com</EndUserId>
      </EndUser>
    </Account>
  </UpdateAccount>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 accounts.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete Account

The following examples show the request and response that are defined in the XSDs for the DeleteAccount tag.

Request

This request follows the DeleteAccount tag defined in the XSDs.

The following example deletes two accounts: Account1 and Account2.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <DeleteAccount>
    <AccountId>Account1</AccountId>
    <AccountId>Account2</AccountId>
  </DeleteAccount>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
```

```

        <Success count="2">Deleted 2 accounts.</Success>
        <Failure count="0"></Failure>
    </Command>
</Response>

```

Query Account

The following examples show the request and response that are defined in the XSDs for the QueryAccount tag.

Request

This request follows the QueryAccount tag defined in the XSDs.

The following example queries multiple accounts by account ID.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
    <QueryAccount>
        <AccountId>000123</AccountId>
    </QueryAccount>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **ConfigurationData > Account** tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="">
    <Account>
        <AccountId>000123</AccountId>
        <NetworkElementName>Node1</NetworkElementName>
        <EndUser>
            <EndUserId>john_smith@company.com</EndUserId>
        </EndUser>
        <CableModem>
            <CmMacAddr>10:10:10:10:10:11</CmMacAddr>
            <CmIpAddr>30.0.0.3</CmIpAddr>
            <UpServerIndex>0</UpServerIndex>
            <UpChannelIndex>0</UpChannelIndex>
            <DownServerIndex>0</DownServerIndex>
            <DownChannelIndex>0</DownChannelIndex>
            <DocsisVersion>0</DocsisVersion>
            <MaxFlows>0</MaxFlows>
            <MaxClassifiers>0</MaxClassifiers>
            <Cpe>
                <CpeMacAddr>00:00:00:00:00:00</CpeMacAddr>
                <CpeIpAddr>10.0.0.3</CpeIpAddr>
            </Cpe>
            <Cpe>
                <CpeMacAddr>00:00:00:00:00:00</CpeMacAddr>
                <CpeIpAddr>20.0.0.3</CpeIpAddr>
            </Cpe>
        </CableModem>
        <TierRef>
            <Name>Premium</Name>
        </TierRef>
    </Account>
</ConfigurationData>

```

```
</Account>
</ConfigurationData>
```

Tiers

A tier represents a class of service or a logical grouping of subscriber accounts.

Add Tier

The following examples show the request and response that are defined in the XSDs for the AddTier tag.

Request

This request follows the AddTier tag defined in the XSDs.

The following example creates two tiers:

- Tier1: Upstream bandwidth limit: 1 Mbps
- Tier2: Upstream bandwidth limit: 2 Mbps

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <AddTier>
    <Tier>
      <Name>Tier1</Name>
      <Description/>
      <ResourceLimit>
        <ResourceType>0</ResourceType>
        <Direction>1</Direction>
        <LimitValue>1000000</LimitValue>
      </ResourceLimit>
    </Tier>
    <Tier>
      <Name>Tier2</Name>
      <Description/>
      <ResourceLimit>
        <ResourceType>0</ResourceType>
        <Direction>1</Direction>
        <LimitValue>2000000</LimitValue>
      </ResourceLimit>
    </Tier>
  </AddTier>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
```

```

        <Success count="2">Successfully imported 2 tiers.</Success>
        <Failure count="0"></Failure>
    </Command>
</Response>

```

Update Tier

The following examples show the request and response that are defined in the XSDs for the UpdateTier tag.

Request

This request follows the UpdateTier tag defined in the XSDs.

The following example updates the tier named Tier1 to change the upstream bandwidth limit to 555000 bps.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <UpdateTier>
    <Tier>
      <Name>Tier1</Name>
      <ResourceLimit>
        <ResourceType>0</ResourceType>
        <Direction>1</Direction>
        <LimitValue>555000</LimitValue>
      </ResourceLimit>
    </Tier>
  </UpdateTier>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 tier.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Delete Tier

The following examples show the request and response that are defined in the XSDs for the DeleteTier tag.

Request

This request follows the DeleteTier tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" ?>

```

```
<XmlInterfaceRequest>
  <DeleteTier>
    <Name>Tier1</Name>
    <Name>Tier2</Name>
  </DeleteTier>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Deleted 2 Tiers.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Query Tier

The following examples show the request and response that are defined in the XSDs for the QueryTier tag.

Request

This request follows the QueryTier tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryTier>
    <Name>Tier Gold</Name>
    <Name>Tier Bronze</Name>
  </QueryTier>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > Tier** tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="3.0.0">
  <Tier>
    <Name>Tier Gold</Name>
    <Description/>
    <ResourceLimit>
      <ResourceType>0</ResourceType>
      <Direction>1</Direction>
      <LimitValue>9000000</LimitValue>
    </ResourceLimit>
  </Tier>
  <Tier>
    <Name>Tier Bronze</Name>
    <Description/>
    <ResourceLimit>
```

```

        <ResourceType>0</ResourceType>
        <Direction>1</Direction>
        <LimitValue>1000000</LimitValue>
    </ResourceLimit>
</Tier>
</ConfigurationData>

```

Quota Profiles

A Quota sets limits on a subscriber's usage; the Quota Profile defines a specific quota.

Quota Rollovers (Rollovers) allow subscribers to carry forward unused units from one billing cycle to another.

Quota Top-Ups (Top-Ups) allow a subscriber to obtain additional units for an existing plan.

Quota Passes (Passes) allow subscribers to access resources beyond the scope of their normal plan.

Add Quota Profile

Add Quota Plan

The following examples show the request and response that are defined in the XSDs for the AddQuota tag.

Request

This request follows the AddQuota tag defined in the XSDs.

The following example creates two quotas:

- Quota1:
 - quotaType = 0
 - EnableDynamicGrant = true
 - MaxSessionsUsedForDynamicGrant = 20
 - MinGrantSize = 3
- Quota2:
 - quotaType = 1
 - EnableDynamicGrant = false
 - MaxSessionsUsedForDynamicGrant = 10
 - MinGrantSize = 0

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddQuota>
    <Quota>
      <Name>quota1</Name>
      <Description></Description>
      <LimitTotalVolume>>false</LimitTotalVolume>
    </Quota>
  </AddQuota>
</XmlInterfaceRequest>

```

```

    <LimitUpVolume>false</LimitUpVolume>
    <LimitDownVolume>false</LimitDownVolume>
    <TotalVolumeLimit>0</TotalVolumeLimit>
    <UpVolumeLimit>0</UpVolumeLimit>
    <DownVolumeLimit>0</DownVolumeLimit>
    <LimitTime>false</LimitTime>
    <TimeLimit>0</TimeLimit>
    <LimitEvent>false</LimitEvent>
    <EventLimit>0</EventLimit>
    <ReplenishingFrequency>0</ReplenishingFrequency>
    <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
    <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
    <EventThresholdPercentage>0.0</EventThresholdPercentage>
    <EnableInterimReporting>false</EnableInterimReporting>
    <InterimReportingInterval>0</InterimReportingInterval>
    <QuotaExhaustionAction>0</QuotaExhaustionAction>
    <RedirectServerType>1</RedirectServerType>
    <QuotaResetIntervalType>1</QuotaResetIntervalType>
    <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
    <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
    <QuotaResetTimeVariable>0</QuotaResetTimeVariable>
    <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
    <QuotaType>0</QuotaType>
    <MaxLeakageThreshold>1</MaxLeakageThreshold>
    <EnableDynamicGrant>true</EnableDynamicGrant>
    <MaxSessionsUsedForDynamicGrant>20</MaxSessionsUsedForDynamicGrant>

    <MinGrantSize>3</MinGrantSize>
  </Quota>
  <Quota>
    <Name>quota2</Name>
    <Description></Description>
    <LimitTotalVolume>false</LimitTotalVolume>
    <LimitUpVolume>false</LimitUpVolume>
    <LimitDownVolume>false</LimitDownVolume>
    <TotalVolumeLimit>0</TotalVolumeLimit>
    <UpVolumeLimit>0</UpVolumeLimit>
    <DownVolumeLimit>0</DownVolumeLimit>
    <LimitTime>false</LimitTime>
    <TimeLimit>0</TimeLimit>
    <LimitEvent>false</LimitEvent>
    <EventLimit>0</EventLimit>
    <ReplenishingFrequency>0</ReplenishingFrequency>
    <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
    <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
    <EventThresholdPercentage>0.0</EventThresholdPercentage>
    <EnableInterimReporting>false</EnableInterimReporting>
    <InterimReportingInterval>0</InterimReportingInterval>
    <QuotaExhaustionAction>0</QuotaExhaustionAction>
    <RedirectServerType>1</RedirectServerType>
    <QuotaResetIntervalType>1</QuotaResetIntervalType>
    <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
    <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
    <QuotaResetTimeVariable></QuotaResetTimeVariable>
    <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
    <QuotaType>1</QuotaType>
    <MaxLeakageThreshold>1</MaxLeakageThreshold>
    <EnableDynamicGrant>false</EnableDynamicGrant>
    <MaxSessionsUsedForDynamicGrant>10</MaxSessionsUsedForDynamicGrant>

    <MinGrantSize>0</MinGrantSize>
  </Quota>
</AddQuota>
</XmlInterfaceRequest>

```


Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Successfully imported 2 quota(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Add Quota Pass

The following example creates two dynamic quota passes:

- dayPass
 - DynamicQuotaType = 1
 - Priority = 10
 - LimitTotalVolume = true
 - TotalVolumeLimit = 1,000,000
- pass1
 - DynamicQuotaType = 1
 - Priority = 0
 - LimitTotalVolume = false
 - TotalVolumeLimit = 0

Request

This request follows the AddQuota tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddQuota>
    <Quota>
      <Name>dayPass</Name>
      <Description></Description>
      <DynamicQuotaType>1</DynamicQuotaType>
      <Priority>10</Priority>
      <LimitTotalVolume>true</LimitTotalVolume>
      <LimitUpVolume>false</LimitUpVolume>
      <LimitDownVolume>false</LimitDownVolume>
      <TotalVolumeLimit>1000000</TotalVolumeLimit>
      <UpVolumeLimit>0</UpVolumeLimit>
      <DownVolumeLimit>0</DownVolumeLimit>
      <LimitTime>false</LimitTime>
      <TimeLimit>0</TimeLimit>
      <LimitEvent>false</LimitEvent>
      <EventLimit>0</EventLimit>
      <ReplenishingFrequency>0</ReplenishingFrequency>
      <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
      <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
      <EventThresholdPercentage>0.0</EventThresholdPercentage>
```

```

    <EnableInterimReporting>false</EnableInterimReporting>
    <InterimReportingInterval>0</InterimReportingInterval>
    <QuotaExhaustionAction>0</QuotaExhaustionAction>
    <RedirectServerType>1</RedirectServerType>
    <QuotaResetIntervalType>1</QuotaResetIntervalType>
    <QuotaResetDayOfMonth>0</QuotaResetDayOfMonth>
    <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
    <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
    <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
    <QuotaType>1</QuotaType>
    <MaxLeakageThreshold>0</MaxLeakageThreshold>
    <EnableDynamicGrant>false</EnableDynamicGrant>
    <MaxSessionsUsedForDynamicGrant>0</MaxSessionsUsedForDynamicGrant>
    <MinGrantSize>0</MinGrantSize>
    <DurationUnitType>2</DurationUnitType>
    <DurationUnit>0</DurationUnit>
    <ActiveTimePeriod></ActiveTimePeriod>
    <QuotaConvention></QuotaConvention>
  </Quota>
  <Quota>
    <Name>pass1</Name>
    <Description></Description>
    <DynamicQuotaType>1</DynamicQuotaType>
    <Priority>0</Priority>
    <LimitTotalVolume>false</LimitTotalVolume>
    <LimitUpVolume>false</LimitUpVolume>
    <LimitDownVolume>false</LimitDownVolume>
    <TotalVolumeLimit>0</TotalVolumeLimit>
    <UpVolumeLimit>0</UpVolumeLimit>
    <DownVolumeLimit>0</DownVolumeLimit>
    <LimitTime>false</LimitTime>
    <TimeLimit>0</TimeLimit>
    <LimitEvent>false</LimitEvent>
    <EventLimit>0</EventLimit>
    <ReplenishingFrequency>0</ReplenishingFrequency>
    <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
    <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
    <EventThresholdPercentage>0.0</EventThresholdPercentage>
    <EnableInterimReporting>false</EnableInterimReporting>
    <InterimReportingInterval>0</InterimReportingInterval>
    <QuotaExhaustionAction>0</QuotaExhaustionAction>
    <RestrictionFilters></RestrictionFilters>
    <FilterIdList></FilterIdList>
    <RedirectServerType>1</RedirectServerType>
    <RedirectServerAddress></RedirectServerAddress>
    <QuotaResetIntervalType>1</QuotaResetIntervalType>
    <QuotaResetDayOfMonth>0</QuotaResetDayOfMonth>
    <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
    <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
    <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
    <QuotaType>1</QuotaType>
    <MaxLeakageThreshold>0</MaxLeakageThreshold>
    <EnableDynamicGrant>false</EnableDynamicGrant>
    <MaxSessionsUsedForDynamicGrant>0</MaxSessionsUsedForDynamicGrant>
    <MinGrantSize>0</MinGrantSize>
    <DurationUnitType>2</DurationUnitType>
    <DurationUnit>0</DurationUnit>
    <ActiveTimePeriod></ActiveTimePeriod>
    <QuotaConvention></QuotaConvention>
  </Quota>
</AddQuota>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="2">Successfully imported 2 quota
convention(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Update Quota Profile

Update Quota Plan

The following examples show the request and response that are defined in the XSDs for the UpdateQuota tag.

Request

This request follows the UpdateQuota tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateQuota>
    <Quota>
      <Name>quota1</Name>
      <Description></Description>
      <LimitTotalVolume>false</LimitTotalVolume>
      <LimitUpVolume>false</LimitUpVolume>
      <LimitDownVolume>false</LimitDownVolume>
      <TotalVolumeLimit>0</TotalVolumeLimit>
      <UpVolumeLimit>0</UpVolumeLimit>
      <DownVolumeLimit>0</DownVolumeLimit>
      <LimitTime>false</LimitTime>
      <TimeLimit>0</TimeLimit>
      <LimitEvent>false</LimitEvent>
      <EventLimit>0</EventLimit>
      <ReplenishingFrequency>0</ReplenishingFrequency>
      <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
      <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
      <EventThresholdPercentage>0.0</EventThresholdPercentage>
      <EnableInterimReporting>false</EnableInterimReporting>
      <InterimReportingInterval>0</InterimReportingInterval>
      <QuotaExhaustionAction>0</QuotaExhaustionAction>
      <RedirectServerType>1</RedirectServerType>
      <QuotaResetIntervalType>1</QuotaResetIntervalType>
      <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
      <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
      <QuotaResetTimeVariable>d</QuotaResetTimeVariable>
      <QuotaReportOffsetLimit>30</QuotaReportOffsetLimit>
      <QuotaType>0</QuotaType>
      <MaxLeakageThreshold>1</MaxLeakageThreshold>
      <EnableDynamicGrant>true</EnableDynamicGrant>
      <MaxSessionsUsedForDynamicGrant>20</MaxSessionsUsedForDynamicGrant>

      <MinGrantSize>3</MinGrantSize>
```

```

    </Quota>
    <Quota>
      <Name>p1</Name>
      <Description></Description>
      <LimitTotalVolume>false</LimitTotalVolume>
      <LimitUpVolume>false</LimitUpVolume>
      <LimitDownVolume>false</LimitDownVolume>
      <TotalVolumeLimit>0</TotalVolumeLimit>
      <UpVolumeLimit>0</UpVolumeLimit>
      <DownVolumeLimit>0</DownVolumeLimit>
      <LimitTime>false</LimitTime>
      <TimeLimit>0</TimeLimit>
      <LimitEvent>false</LimitEvent>
      <EventLimit>0</EventLimit>
      <ReplenishingFrequency>0</ReplenishingFrequency>
      <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
      <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
      <EventThresholdPercentage>0.0</EventThresholdPercentage>
      <EnableInterimReporting>false</EnableInterimReporting>
      <InterimReportingInterval>0</InterimReportingInterval>
      <QuotaExhaustionAction>0</QuotaExhaustionAction>
      <RedirectServerType>1</RedirectServerType>
      <QuotaResetIntervalType>2</QuotaResetIntervalType>
      <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
      <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
      <QuotaResetTimeVariable></QuotaResetTimeVariable>
      <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
      <QuotaType>1</QuotaType>
      <MaxLeakageThreshold>1</MaxLeakageThreshold>
      <EnableDynamicGrant>false</EnableDynamicGrant>
      <MaxSessionsUsedForDynamicGrant>10</MaxSessionsUsedForDynamicGrant>

      <MinGrantSize>0</MinGrantSize>
    </Quota>
  </UpdateQuota>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 2 quota.</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

The following example updates a dynamic quota with two passes:

Update Quota Pass

- dayPass
 - DynamicQuotaType = 1
 - Priority = 10
 - LimitTotalVolume = true
 - TotalVolumeLimit = 1,000,000

- pass1
 - DynamicQuotaType = 1
 - Priority = 0
 - LimitTotalVolume = false
 - TotalVolumeLimit = 0

Request

This request follows the UpdateQuota tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateQuota>
    <Quota>
      <Name>dayPass</Name>
      <Description></Description>
      <DynamicQuotaType>1</DynamicQuotaType>
      <Priority>10</Priority>
      <LimitTotalVolume>true</LimitTotalVolume>
      <LimitUpVolume>false</LimitUpVolume>
      <LimitDownVolume>false</LimitDownVolume>
      <TotalVolumeLimit>10000000</TotalVolumeLimit>
      <UpVolumeLimit>0</UpVolumeLimit>
      <DownVolumeLimit>0</DownVolumeLimit>
      <LimitTime>false</LimitTime>
      <TimeLimit>0</TimeLimit>
      <LimitEvent>false</LimitEvent>
      <EventLimit>0</EventLimit>
      <ReplenishingFrequency>0</ReplenishingFrequency>
      <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
      <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
      <EventThresholdPercentage>0.0</EventThresholdPercentage>
      <EnableInterimReporting>false</EnableInterimReporting>
      <InterimReportingInterval>0</InterimReportingInterval>
      <QuotaExhaustionAction>0</QuotaExhaustionAction>
      <RedirectServerType>1</RedirectServerType>
      <QuotaResetIntervalType>1</QuotaResetIntervalType>
      <QuotaResetDayOfMonth>0</QuotaResetDayOfMonth>
      <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
      <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
      <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
      <QuotaType>1</QuotaType>
      <MaxLeakageThreshold>0</MaxLeakageThreshold>
      <EnableDynamicGrant>false</EnableDynamicGrant>
      <MaxSessionsUsedForDynamicGrant>0</MaxSessionsUsedForDynamicGrant>
      <MinGrantSize>0</MinGrantSize>
      <DurationUnitType>2</DurationUnitType>
      <DurationUnit>0</DurationUnit>
      <ActiveTimePeriod></ActiveTimePeriod>
      <QuotaConvention></QuotaConvention>
    </Quota>
    <Quota>
      <Name>pass1</Name>
      <Description></Description>
      <DynamicQuotaType>1</DynamicQuotaType>
      <Priority>0</Priority>
      <LimitTotalVolume>false</LimitTotalVolume>
      <LimitUpVolume>false</LimitUpVolume>
      <LimitDownVolume>false</LimitDownVolume>
      <TotalVolumeLimit>0</TotalVolumeLimit>
    </Quota>
  </UpdateQuota>
</XmlInterfaceRequest>
```

```

    <UpVolumeLimit>0</UpVolumeLimit>
    <DownVolumeLimit>0</DownVolumeLimit>
    <LimitTime>>false</LimitTime>
    <TimeLimit>0</TimeLimit>
    <LimitEvent>>false</LimitEvent>
    <EventLimit>0</EventLimit>
    <ReplenishingFrequency>0</ReplenishingFrequency>
    <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
    <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
    <EventThresholdPercentage>0.0</EventThresholdPercentage>
    <EnableInterimReporting>>false</EnableInterimReporting>
    <InterimReportingInterval>0</InterimReportingInterval>
    <QuotaExhaustionAction>0</QuotaExhaustionAction>
    <RestrictionFilters></RestrictionFilters>
    <FilterIdList></FilterIdList>
    <RedirectServerType>1</RedirectServerType>
    <RedirectServerAddress></RedirectServerAddress>
    <QuotaResetIntervalType>1</QuotaResetIntervalType>
    <QuotaResetDayOfMonth>0</QuotaResetDayOfMonth>
    <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
    <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
    <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
    <QuotaType>1</QuotaType>
    <MaxLeakageThreshold>0</MaxLeakageThreshold>
    <EnableDynamicGrant>>false</EnableDynamicGrant>
    <MaxSessionsUsedForDynamicGrant>0</MaxSessionsUsedForDynamicGrant>
    <MinGrantSize>0</MinGrantSize>
    <DurationUnitType>2</DurationUnitType>
    <DurationUnit>0</DurationUnit>
    <ActiveTimePeriod></ActiveTimePeriod>
    <QuotaConvention></QuotaConvention>
  </Quota>
</UpdateQuota>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 quota
convention(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

Delete Quota Profile

The following examples show the request and response that are defined in the XSDs for the DeleteQuota tag.

Request

This request follows the DeleteQuota tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" ?>
  <XmlInterfaceRequest>
    <DeleteQuota>
      <Name> quota1</Name>
    </DeleteQuota>
  </XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Deleted 1 quota</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Query Quota Profile

The following examples show the request and response that are defined in the XSDs for the QueryQuota tag.

Request

This request follows the QueryQuota tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" ?>
  <XmlInterfaceRequest>
    <QueryQuota>
      <Name> quota1</Name>
    </QueryQuota>
  </XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData** > **Quota** tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="8.0.0">
  <Quota>
    <Name>quota1</Name>
    <Description></Description>
    <LimitTotalVolume>false</LimitTotalVolume>
    <LimitUpVolume>false</LimitUpVolume>
    <LimitDownVolume>false</LimitDownVolume>
    <TotalVolumeLimit>0</TotalVolumeLimit>
    <UpVolumeLimit>0</UpVolumeLimit>
    <DownVolumeLimit>0</DownVolumeLimit>
    <LimitTime>false</LimitTime>
    <TimeLimit>0</TimeLimit>
```

```

    <LimitEvent>false</LimitEvent>
    <EventLimit>0</EventLimit>
    <ReplenishingFrequency>0</ReplenishingFrequency>
    <VolumeThresholdPercentage>0.0</VolumeThresholdPercentage>
    <TimeThresholdPercentage>0.0</TimeThresholdPercentage>
    <EventThresholdPercentage>0.0</EventThresholdPercentage>
    <EnableInterimReporting>false</EnableInterimReporting>
    <InterimReportingInterval>0</InterimReportingInterval>
    <QuotaExhaustionAction>0</QuotaExhaustionAction>
    <RedirectServerType>2</RedirectServerType>
    <QuotaResetIntervalType>1</QuotaResetIntervalType>
    <QuotaResetDayOfMonth>0</QuotaResetDayOfMonth>
    <QuotaResetDayOfWeek>0</QuotaResetDayOfWeek>
    <QuotaResetTimeOfDay></QuotaResetTimeOfDay>
    <QuotaResetTimeVariable>d</QuotaResetTimeVariable>
    <QuotaReportOffsetLimit>0</QuotaReportOffsetLimit>
    <QuotaType>0</QuotaType>
    <MaxLeakageThreshold>0</MaxLeakageThreshold>
    <EnableDynamicGrant>false</EnableDynamicGrant>
    <MaxSessionsUsedForDynamicGrant>20</MaxSessionsUsedForDynamicGrant>
    <MinGrantSize>0</MinGrantSize>
  </Quota>
</ConfigurationData>

```

Quota Conventions

A Quota Convention controls how units are consumed and how thresholds are calculated in Quotas, Top-Ups, Rollovers, and Passes. A Quota Convention stores a service provider's configuration preferences for how Quotas, Top-Ups, Rollovers, and Passes are processed.

Add Quota Convention

The following examples show the request and response that are defined in the XSDs for the AddQuotaConvention tag.

Request

This request follows the AddQuotaConvention tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddQuotaConvention>
    <QuotaConvention>
      <Name>quotaConvention_default</Name>
      <Description></Description>
      <RolloverUsage>0</RolloverUsage>
      <PercentageRolloverInterval>20.0</PercentageRolloverInterval>
      <PercentageRolloverMax>0.0</PercentageRolloverMax>
      <BehaviorMask>128</BehaviorMask>
    </QuotaConvention>
    <QuotaConvention>
      <Name>rollover_20150_all</Name>
      <Description></Description>
      <RolloverUsage>0</RolloverUsage>
      <PercentageRolloverInterval>20.0</PercentageRolloverInterval>
    </QuotaConvention>
  </AddQuotaConvention>
</XmlInterfaceRequest>

```



```

        <PercentageRolloverMax>100.0</PercentageRolloverMax>
        <BehaviorMask>223</BehaviorMask>
    </QuotaConvention>
</AddQuotaConvention>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version="1.0" ?>
<Response>
    <Result>0</Result>
    <Command type="XmlInterfaceResponse">
        <Success count="2">Successfully imported 2 quota
convention(s).</Success>
        <Failure count="0"></Failure>
    </Command>
</Response>

```

Update Quota Conventions

The following examples show the request and response that are defined in the XSDs for the UpdateQuotaConvention tag.

Request

This request follows the UpdateQuotaConvention tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
    <UpdateQuotaConvention>
        <QuotaConvention>
            <Name>quotaConvention_default</Name>
            <Description></Description>
            <RolloverUsage>0</RolloverUsage>
            <PercentageRolloverInterval>20.0</PercentageRolloverInterval>
            <PercentageRolloverMax>0.0</PercentageRolloverMax>
            <BehaviorMask>128</BehaviorMask>
        </QuotaConvention>
        <QuotaConvention>
            <Name>rollover_20150_all</Name>
            <Description></Description>
            <RolloverUsage>0</RolloverUsage>
            <PercentageRolloverInterval>20.0</PercentageRolloverInterval>
            <PercentageRolloverMax>100.0</PercentageRolloverMax>
            <BehaviorMask>223</BehaviorMask>
        </QuotaConvention>
    </UpdateQuotaConvention>
</XmlInterfaceRequest>

```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```

<?xml version='1.0' ?>

```

```
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 2 quota
convention(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Delete Quota Convention

The following example shows the request and response that are defined in the XSDs for the DeleteQuotaConvention tag.

Request

This request follows the DeleteQuotaConvention tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <DeleteQuotaConvention>
    <Name>abc</Name>
  </DeleteQuotaConvention>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Deleted 1 Quota Convention(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

Query Quota Convention

The following example shows the request and response that are defined in the XSDs for the QueryQuotaConvention tag.

Request

This request follows the QueryQuotaConvention tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryQuotaConvention>
    <Name>quotaConvention1</Name>
  </QueryQuotaConvention>
</XmlInterfaceRequest>
```

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?> <ConfigurationData
version="9.1.0">
  <QuotaConvention>
    <Name>quotaConvention_default</Name>
    <Description></Description>
    <RolloverUsage>0</RolloverUsage>
    <PercentageRolloverInterval>20.0</PercentageRolloverInterval>
    <PercentageRolloverMax>0.0</PercentageRolloverMax>
    <BehaviorMask>128</BehaviorMask>
  </QuotaConvention>
</ConfigurationData>
```

Setting SCTP Settings

When enabled, this feature allows you to set diameter connections using SCTP.

To enable or disable processing of SCTP procedures, or to change configuration attributes:

1. From the **Policy Server** section of the navigation pane, select **Global Configuration Settings**.
The content tree displays a list of global configuration settings.
2. From the content tree, select **SCTP Settings**.
The SCTP Settings page opens in the work area set to *True*.
3. On the SCTP Settings page, click **Modify**.
The SCTP Settings page opens.
4. Enter a value for the configuration attribute:
 - a) **SCTP Enabled** — Check mark to enable this feature. It will automatically begin listening for incoming SCTP connections.

Note: If datasource is not supported by SCTP, then the default is unchecked (disabled) for a TCP connection.
5. When you finish, click **Save** (or **Cancel** to discard your changes).
The SCTP Settings page closes.

The SCTP Settings attribute is configured.

Chapter 6

Operational Measurements Interface Overview

Topics:

- *OM Statistics Scheduled Task.....85*
- *OM Statistics Requests.....85*
- *OM Statistics Response Format.....87*
- *Timezones and Start/End Times.....88*
- *Counter Reset and Failover.....89*
- *Comparisons Between the CMP GUI and OM Statistics.....90*

The Operational Measurements (OM) XML interface is used to retrieve operational counters from the system. This chapter describes the interface and how it should be used.

OM Statistics Scheduled Task

The OM interface requires that the “OM Statistics” scheduled task be running on the Configuration Management Platform (CMP). This task performs the function of collecting the operational counters from the MPEs in the network and recording them in the CMP database; the data is then available to be queried via the OM XML interface (See *CMP Wireless User’s Guide* or *CMP Cable User’s Guide* for more information). This task can be configured by the user to poll at intervals between 5 minutes and 24 hours, with a default value of 15 minutes, and keeps the data available for query for 1 to 30 days, with the default value being 7 days. The recommended settings for this task varies with each deployment, dependant on the volume of data being collected.

When OM requests are made, the data for the response is taken from the information that has been collected by this task. Without the data that is collected through this scheduled task, there would be no data available for OM queries.

Most values returned as part of the response are presented (by default) as deltas, representing the positive change between the start time and end time. In order to calculate a delta there must be a minimum of two recorded values available, so the OM Statistics task must have been run at least twice in order to provide any data through the OM XML interface.

OM Statistics Requests

OM statistic requests consist of the following:

- [Attributes and Child Tags](#)
- [Recorded Timestamp and Request Time Range](#)

Attributes and Child Tags

The following attributes can be used with any of the OM Statistics requests as part of the “QueryOMStats” tag:

- **DeltaCount** — The values for statistics which are cumulative in nature (for example, monotonically increasing counters) are returned by default as a delta value. For these cumulative statistics, the delta value returned represents the positive change in that value since the last recorded time period. By setting the DeltaCount attribute to “false” the user can request that all statistics be returned as absolute values instead, that is the total values since the beginning of time.

Some statistics are always returned as absolute values. These non-cumulative statistics have values that can increase or decrease over time, for example Upstream and Downstream Bandwidth or active Session Counts. These statistics are explicitly called out in this document as always returning “absolute” values.

The following is an example of the DeltaCount attribute:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats DeltaCount="false">
```

```
<StartTime>2006-10-12T11:15:00Z</StartTime>
<EndTime>2006-10-12T11:25:00Z</EndTime>
<NetworkElementStats></NetworkElementStats>
</QueryOmStats>
```

- **AggregateTimeSamples** — The `AggregateTimeSamples` attribute allows the user to request that all sample buckets in the response be aggregated into a single sample bucket. This allows users to request data for a time period and see a summary of all recorded data for that specific time period, rather than all the individual samples that make up the requested time period.

The following is an example of the `AggregateTimeSamples` attribute:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats AggregateTimeSamples="true">
  <StartTime>2006-10-12T11:15:00Z</StartTime>
  <EndTime>2006-10-12T11:25:00Z</EndTime>
  <NetworkElementStats/>
</QueryOmStats>
```

The following child tags are available for OM XML Commands:

- **StartTime/EndTime** — These tags define the time range over which you want statistical data returned. All statistic data recorded by the OM Statistics task over that requested time range is returned. Also, the `EndTime` tag is an optional tag. If no `EndTime` tag is specified, then the time range extends from the `StartTime` and continues until the current time. This provides a means to capture the most up-to-date data.

The following is an example of the `StartTime/EndTime` child tags:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:35:00Z</EndTime>
  <PolicyServerStats/>
  <IsComplete>true</IsComplete>
</QueryOmStats>
```

- **PolicyServer** — This optional tag, specified as a child tag of some individual statistic groups, allows the user to request statistics specific to an individual or a set of MPEs. The default behavior displays statistics for all MPEs.

The following is an example of the `PolicyServer` child tag:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:35:00Z</EndTime>
  <PolicyServerStats>
    <PolicyServer>Atlanta105</PolicyServer>
  </PolicyServerStats>
</QueryOmStats>
```

Recorded Timestamp and Request Time Range

The OM Statistics task runs on a scheduled interval. The statistics, however, are time stamped as they are received from the MPEs to increase accuracy. For example, while the OM Statistics task may start at 12:00:00, the statistics recorded for MPE1 may not be time stamped until 12:00:01, and MPE2 at 12:00:02, and so on.

This detail impacts the way the captured data should be requested through the XML interface so as to ensure all the desired data is returned as part of the response. To ensure correct results, if the intent is to retrieve data for a full 24 hour period, then the start and end times should extend beyond the intended 24 hour period to ensure that any delayed results returned for an MPE are included in the response.

For example, to retrieve statistics recorded for the entire day of March 10, the following request time range is recommended (note that the EndTime is 15 minutes past midnight):

```
<StartTime>2008-03-10T00:00:00Z</StartTime>
<EndTime>2008-03-11T00:15:00Z</EndTime>
```

OM Statistics Response Format

The XSD defines the schema for responses to OM XML requests. Results are returned in **Sample** buckets representing a range of time. If Persistent Interval Statistics are enabled (Stats.Interval.Enabled), this range is determined by the **Stats Collection Period**, found under **Global Configuration Settings > Stats Settings** on the CMP, but also includes any **Manual** runs of the task initiated by the user.

If Stats.Interval.Enabled is set to false (meaning that Persistent Interval Statistics are not enabled), then the CMP collects absolute counter values only; this range is determined by the interval settings of the OM Statistics scheduled task and includes any **Manual** runs of the task initiated by the user.

Responses do not return data sets that exceed a maximum size. In this case, a user is directed to reduce the scope of their query to accommodate for the size limitation of the XML response.

Interval Statistics

In the interval-statistics mode, all numeric data generated by MPEs are reset at regular intervals controlled by the Stats Collection Period. When in Interval mode, a reset occurs on the hour and then every 5, 10, 15, 20, 30 or 60 minutes afterwards depending on the value of the Stats Collection Period. See the *CMP Wireless User Guide* for details on setting interval statistics.

When in Interval Mode, the XML request and response will look similar to the example below.

Request:

```
<QueryOmStatsSetting/>
```

Response:

```
<OmStatsSetting>
  <ResetConfiguration>Interval</ResetConfiguration>
  <CollectionInterval>15</CollectionInterval>
</OmStatsSetting>
```

Absolute versus Delta Values

For all cumulative statistics (for example, monotonically increasing counters), the returned values are presented as deltas, by default. These deltas represent the positive change in value between the start and end times. This behavior can optionally be changed to return absolute values for all statistics (see [OM Statistics Requests](#)).

Non-cumulative statistics, those statistics whose value can either increase or decrease between intervals, are returned as absolute values. This prevents negative value responses as a result of a delta calculation. For example, in “NetworkElementStats” the Upstream Bandwidth, Downstream Bandwidth, and “active” Session Counts are returned as absolute values. These absolute statistics are explicitly called out in this document as always returning “absolute” values. All absolute data points are taken as the value at the End Time of the reported Sample.

Empty Data Set

Requests that do not result in any statistics contain the following message:

Not enough statistical data available to fulfill request.

If you receive this message, check the request parameters or select a different time range, as the message indicates that for the parameters submitted as part of the request there is not enough recorded data to respond.

```
<IsComplete>false</IsComplete>
```

The OM Statistics Task must have been run at least two times within the specified time range (StartTime and EndTime). The task itself runs on a schedule but the data is recorded dynamically as it is received from the MPEs so this should be taken into account when requesting a particular range of time. Oracle recommends that users start with a larger time window for testing and narrow that down, adjusting the scheduled task as needed, until the desired data is returned. This message could also occur if recorded data is unavailable for a specific parameter, such as a certain Network Element or MPE name.

Timezones and Start/End Times

OM responses include “Sample” buckets, each with a specified start and end time. These values are returned in UTC (Coordinated Universal Time) format, which is the international time standard. The CMP is unaware of the timezone of the originating request and is therefore unable to return a “localized” timezone to the user.

The XSDs define request/responses with the following:

```
<!-- Time Range -->
<xsd:element name="StartTime" type="xsd:dateTime" minOccurs="1" maxOccurs="1"/>
<xsd:element name="EndTime" type="xsd:dateTime" minOccurs="1" maxOccurs="1"/>
```

The type is defined as “**xsd:dateTime**”. This is a UTC format. This data type describes instances identified by the combination of a date and a time.

Its lexical space is the extended format:

[-]CCYY-MM-DDThh:mm:ss[Z|(+|-)hh:mm]

The time zone may be specified as Z (UTC) or (+|-)hh:mm. Time zones that are not specified are considered localized to the MPE Manager.

The following are examples of valid values for xsd:dateTime:

- Example 1—2007-03-26T21:32:52Z - UTC format. This is the default response format for all timestamps. It is also the recommend format for user requests.
- Example 2—2007-03-26T21:32:52+02:00 - Localized time with 2 hour offset to UTC time.
- Example 3—2007-03-26T19:32:52 - Localized time. This will be interpreted as localized to the MPE Manager.
- Example 4—2007-03-26T19:32:52+00:00 - Localized time with no offset.

Note: All date and time numbers are two digits. For example, 3:00am, April 5th is written as “2008-04-05T03:00:00” and not “2008-4-5T3:00:00”.

A request to retrieve statistics can be made either in UTC or as a time that is localized to the CMP. It is recommended that users make their requests in UTC format to remain consistent with the UTC output. UTC is also recommended, as end users may not be aware they are making requests from a different timezone than the CMP and therefore may not be accounting for that difference when analyzing results. If the MPEs, CMP, and end user are all in different timezones then the user would be attempting to correlate values and draw conclusions from the reported statistics across all of those timezones.

Counter Reset and Failover

MPEs write historical data to a distributed comcol database and save it for 24 hours.

Note: CMP stores cluster-level interval stats to its own database. Data is available for external OSS system to retrieve after the end of the next interval period.

There are two cases where statistics can be reset:

- The user can click the “Reset All Counters” button on the Policy Server “Reports” page of the CMP Graphical User Interface (GUI). This button is typically used to reset counters as a baseline from which to run tests (refer to *CMP User Guide* for detailed description of this page.).
- The user can enable the Interval mode; when configured, numeric values are reset at regular intervals controlled by the Stats Collection Period. When in Interval mode, a reset will occur on the hour and then every 5, 10, 15, 20, 30 or 60 minutes afterwards depending on the value of the

Stats Collection Period. (When interval periods are changed, the database is purged.) See the *CMP User Guide* for details.

In either case, all memory counters are reset to 0. This means that the delta values calculated for the time period during which the reset occurred are not accurate.

For example, if at the `StartTime` the `SuccessSessionCount` value was 100, and a reset occurred resetting the count to 0, then the next reported delta would be -100. If the `SuccessSessionCount` started at 100, and during the sample time period, five successful sessions completed, then a reset occurred after which 10 more sessions completed successfully, then the resulting delta for that time period would be -90. This example shows that some information is lost; the response will indicate this with the `IsComplete` flag set to `false`. In either case, the value could not be seen as an accurate representation of activity for that time and should be ignored. For this reason, negative delta values are always returned as "0".

The CMP will get incomplete interval stats from MPE/MRA in the following conditions:

- The active MPE blade switches over one or more times within an interval period.
- MPE has initially started up.
- Under high-load conditions, the MPE cannot store data to the database at the end of an interval cycle (within a margin of a few seconds).

Comparisons Between the CMP GUI and OM Statistics

Relationships between the OM XML responses and the CMP Reports GUI can be drawn and used for comparison.

The OM XML interface persists statistic values over time. This tool is intended for historical analysis of statistics and can be used to track usage. The interface allows users to request data over a user-defined time range and returns data for that period. The default behavior for this interface is to return data as delta values. The delta is calculated as the positive change in value between the start and end times returned in "Sample" buckets. Certain non-cumulative statistics are always reported as absolutes and those individual statistics are explicitly documented. This behavior can also be changed to return absolute values for all statistics; even those which are cumulative in nature (see [OM Statistics Requests](#)).

The "Reports" page in the Policy Server section of the CMP GUI displays statistics in real time (Refer to the *CMP User's Guide* for details). The intent of this page is for monitoring current statistics. The page dynamically updates the displayed statistics every 10 seconds. These statistics are categorized by protocol. The default behavior of this page displays statistics as absolute values. There is a "Show Deltas" button at the top of the page; this button can be used to switch the display to calculated delta values. The delta value shown is the difference between the current value and the last refresh of the page (approximately 10 seconds).

The top section on any statistics page, contained within the CMP GUI, usually correlates with the "Message Processing Stats" of the OM XML interface. The individual statistics for each Network Element can be found in the section at the bottom of the reporting page. These statistics correlate with the "Network Element Stats" of the OM XML interface.

Labels for specific statistics may differ between the CMP GUI and the OM XML interface responses. The specific types of statistics displayed may also differ by protocol. While the CMP GUI can use labels and statistics specific to a certain protocol, the OM XML interface requests must use generic language across protocols in order to remain consistent with published XSD definitions.

Operational Measurements Interface Overview

For deployments that collect statistics across multiple protocols, for example PCMM and DQoS, the CMP GUI displays statistics for each protocol individually. However, in the XML Interface, the statistics for available protocols are summarized in the response. For example, session count statistics for PCMM and DQoS would be added together to display with each network element. Statistics for individual protocols are not be displayed separately.

Additional details for the GUI's Reports/Statistics section of the CMP GUI can be found in the *CMP User's Guide*.

Chapter 7

Operational Measurement Requests

Topics:

- *Operational Measurements Requests Overview.....93*
- *Diameter Event Trigger Statistics.....94*
- *Topology Update Statistics.....96*
- *Subscriber Update Statistics.....97*
- *Policy Server Statistics.....98*
- *Message Processing Statistics.....99*
- *Network Element Statistics.....101*
- *Latency Statistics.....105*
- *RADIUS Operational Measurement Requests.114*
- *Connected Network Elements Statistics.....123*
- *Policy Statistics.....124*
- *Diameter Operational Measurements Requests.....125*
- *KPI Statistics.....143*
- *Protocol Error Statistics.....144*
- *Session Cleanup Statistics.....149*
- *Timeout Statistics.....150*
- *Traffic Profile Statistics.....164*
- *Connection Error Statistics.....165*
- *Quota Profile Statistics.....169*
- *Quota Reset Statistics.....170*
- *Quota Reset All Statistics.....172*
- *Interval Statistics/PCRF Session License Tracking and Reporting.....173*

This chapter defines the various Operational Measurements (OM) groups and the individual OM statistics that comprise them. For several of the more generic statistics, the instrumentation on the Multimedia Policy Engine (MPE) and the Multi-Protocol Routing Agent (MRA) may differ by protocol, and therefore specific statistics may increment differently across those protocols.

Operational Measurements Requests Overview

The OM interface consists of the following requests, grouped by category:

- OSSI XML interface statistics
 - Topology Update Statistics — retrieves statistics on all updates made through the Topology Interface.
 - Subscriber Update Statistics — retrieves statistics on all updates made through the Subscriber Interface.
 - Policy Server Statistics — retrieves statistics on each policy server in the system, including the associated subscribers and network elements.
- Protocol-specific statistics
 - Message Processing Statistics — retrieves statistics on session events.
 - Network Element Statistics — retrieves statistics on session events for specific network elements and interfaces.
 - Reserve Commit Statistics — retrieves statistics on reserve and commit requests specific to the SPC DQoS protocol.
 - Gate Statistics — retrieves statistics on gate set messages, gate status messages, and gate delete messages specific to PCMM, DQoS and SPC DQoS protocols.
 - RADIUS-S Statistics — retrieves statistics on accounting and change-of-authorization messages specific to the RADIUS-S protocol.
 - Connected Network Element Statistics — retrieves statistics, reporting the number of connected network elements on a per-MPE basis. Connected network elements are those that have a connection (for example, COPS) established to the MPE. This statistic is specific to wireline customers.
 - Diameter Statistics — retrieves statistics on Diameter Application Functions, Charging Functions, and Policy Charging Enforcement Functions.
 - Timeout Statistics — retrieves timeout statistics not received in a predefined amount of time, that are tracked per network element, MPE, and MRA.
 - Latency Statistics — retrieves latency statistics information for incoming and outgoing messages tracked per network element, MPE, and MRA.
 - Event Trigger Statistics — retrieves related event trigger statistics used for tracking activity.
 - Session Cleanup Statistics — retrieves the number of session cleanup statistics where sessions are aged-out due to inactivity. The reauthorization is submitted and if it is unresponsive or an error occurs indicating that the session is inactive, then it is removed from the system.
 - Traffic Profile Statistics — retrieves traffic profile statistics which counters the number of times a PCRF attempts to install, remove, or fails.
 - Quota Profile Statistics — retrieves quota profile statistics to counter the number of times the configured threshold reaches a maxed out limit.

Diameter Event Trigger Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterEventTriggerStats tag.

Request

This request follows the **QueryOmStats > DiameterEventTriggerStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <DiameterEventTriggerStats>
    <PolicyServer>PolicyServer</PolicyServer>
  </DiameterEventTriggerStats>
</QueryOmStats>
```

The response to this request follows the **Statistics > DiameterEventTriggerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterEventTriggerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <SGSN_CHANGE>1</SGSN_CHANGE>
      <QOS_CHANGE>1</QOS_CHANGE>
      <RAT_CHANGE>1</RAT_CHANGE>
      <TFT_CHANGE>1</TFT_CHANGE>
      <PLMN_CHANGE>1</PLMN_CHANGE>
      <LOSS_OF_BEARER>1</LOSS_OF_BEARER>
      <RECOVERY_OF_BEARER>1</RECOVERY_OF_BEARER>
      <IP_CAN_CHANGE>1</IP_CAN_CHANGE>
      <GW_PCEF_MALFUNCTION>1</GW_PCEF_MALFUNCTION>
      <RESOURCES_LIMITATION>1</RESOURCES_LIMITATION>
      <MAX_NR_BEARERS_REACHED>1</MAX_NR_BEARERS_REACHED>
      <QOS_CHANGE_EXCEEDING_AUTHORIZATION>1</QOS_CHANGE_EXCEEDING_AUTHORIZATION>

      <RAI_CHANGE>1</RAI_CHANGE>
      <USER_LOCATION_CHANGE>1</USER_LOCATION_CHANGE>
      <OUT_OF_CREDIT>1</OUT_OF_CREDIT>
      <REALLOCATION_OF_CREDIT>1</REALLOCATION_OF_CREDIT>
      <REVALIDATION_TIMEOUT>1</REVALIDATION_TIMEOUT>
      <UE_IP_ADDRESS_ALLOCATE>1</UE_IP_ADDRESS_ALLOCATE>
      <UE_IP_ADDRESS_RELEASE>1</UE_IP_ADDRESS_RELEASE>
      <DEFAULT_EPS_BEARER_QOS_CHANGE>1</DEFAULT_EPS_BEARER_QOS_CHANGE>
      <AN_GW_CHANGE>1</AN_GW_CHANGE>
      <SUCCESSFUL_RESOURCE_ALLOCATION>1</SUCCESSFUL_RESOURCE_ALLOCATION>
      <UE_TIME_ZONE_CHANGE>1</UE_TIME_ZONE_CHANGE>
```

```

    <USAGE_REPORT>1</USAGE_REPORT>
    <USAGE_THRESHOLD_REACHED>1</USAGE_THRESHOLD_REACHED>
    <SERVICE_FLOW_DETECTION>1</SERVICE_FLOW_DETECTION>
  </Sample>
  <IsComplete>true</IsComplete>
</DiameterEventTriggerStats>
</Statistics>

```

Request

This request follows the **QueryOmStats > DiameterConnectionEventTriggerStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <DiameterConnectionEventTriggerStats>
    <Name>NetworkElementName</Name>
    <NeId>NeId</NeId>
    <PolicyServer>PolicyServer</PolicyServer>
  </DiameterConnectionEventTriggerStats>
</QueryOmStats>

```

Response

The response to this request follows the **Statistics > DiameterConnectionEventTriggerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterConnectionEventTriggerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>NetworkElementName</Name>
      <NeId>NeId</NeId>
      <SGSN_CHANGE>1</SGSN_CHANGE>
      <QOS_CHANGE>1</QOS_CHANGE>
      <RAT_CHANGE>1</RAT_CHANGE>
      <TFT_CHANGE>1</TFT_CHANGE>
      <PLMN_CHANGE>1</PLMN_CHANGE>
      <LOSS_OF_BEARER>1</LOSS_OF_BEARER>
      <RECOVERY_OF_BEARER>1</RECOVERY_OF_BEARER>
      <IP_CAN_CHANGE>1</IP_CAN_CHANGE>
      <GW_PCEF_MALFUNCTION>1</GW_PCEF_MALFUNCTION>
      <RESOURCES_LIMITATION>1</RESOURCES_LIMITATION>
      <MAX_NR_BEARERS_REACHED>1</MAX_NR_BEARERS_REACHED>
      <QOS_CHANGE_EXCEEDING_AUTHORIZATION>1</QOS_CHANGE_EXCEEDING_AUTHORIZATION>

      <RAI_CHANGE>1</RAI_CHANGE>
      <USER_LOCATION_CHANGE>1</USER_LOCATION_CHANGE>
      <OUT_OF_CREDIT>1</OUT_OF_CREDIT>
    </Sample>
  </DiameterConnectionEventTriggerStats>
</Statistics>

```

```

    <REALLOCATION_OF_CREDIT>1</REALLOCATION_OF_CREDIT>
    <REVALIDATION_TIMEOUT>1</REVALIDATION_TIMEOUT>
    <UE_IP_ADDRESS_ALLOCATE>1</UE_IP_ADDRESS_ALLOCATE>
    <UE_IP_ADDRESS_RELEASE>1</UE_IP_ADDRESS_RELEASE>
    <DEFAULT_EPS_BEARER_QOS_CHANGE>1</DEFAULT_EPS_BEARER_QOS_CHANGE>
    <AN_GW_CHANGE>1</AN_GW_CHANGE>
    <SUCCESSFUL_RESOURCE_ALLOCATION>1</SUCCESSFUL_RESOURCE_ALLOCATION>
    <UE_TIME_ZONE_CHANGE>1</UE_TIME_ZONE_CHANGE>
    <USAGE_REPORT>1</USAGE_REPORT>
    <USAGE_THRESHOLD_REACHED>1</USAGE_THRESHOLD_REACHED>
    <SERVICE_FLOW_DETECTION>1</SERVICE_FLOW_DETECTION>
  </Sample>
</DiameterConnectionEventTriggerStats>
</Statistics>

```

Note: Only non-zero event trigger counts are included in the response.

Individual statistics are defined as follows for the PCEF and BBERF protocols:

- SGSN_CHANGE (0)
- QOS_CHANGE (1)
- RAT_CHANGE (2)
- TFT_CHANGE (3)
- PLMN_CHANGE (4)
- LOSS_OF_BEARER (5)
- RECOVERY_OF_BEARER (6)
- IP_CAN_CHANGE (7)
- GW_PCEF_MALFUNCTION (8)
- RESOURCES_LIMITATION (9)
- MAX_NR_BEARERS_REACHED (10)
- QOS_CHANGE_EXCEEDING_AUTHORIZATION (11)
- RAI_CHANGE (12)
- USER_LOCATION_CHANGE (13)
- OUT_OF_CREDIT (14)
- REALLOCATION_OF_CREDIT (15)
- REVALIDATION_TIMEOUT (16)
- UE_IP_ADDRESS_ALLOCATE (17)
- UE_IP_ADDRESS_RELEASE (18)
- DEFAULT_EPS_BEARER_QOS_CHANGE (20)
- AN_GW_CHANGE (21)

Topology Update Statistics

The following examples show the request and response that are defined in the XSDs for the TopologyUpdateStats tag.

Request

This request follows the **QueryOmStats > TopologyUpdateStats** tag defined in the XSDs.

The following is an example of a request for a topology update:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:40:00Z</EndTime>
  <TopologyUpdateStats></TopologyUpdateStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > TopologyUpdateStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- **TopologyUpdateCount** — The number of topology changes made in the Configuration Management Platform (CMP) that resulted in changes to an MPE. Topology data includes Network Elements, Paths, Interfaces, and Links. Changes to this data can occur through either the CMP Graphical User Interface (GUI) or the XML interface. The counter increments for each MPE that updates as a result of the change. For example, when a user updates a Network Element, the topology update counter increments for each MPE that the Network Element is associated with.

Batch changes are treated as a single update to an MPE. An OSSl XML interface update may be made across multiple elements but all of those changes are pushed at one time to the MPE. This is treated as a single topology change with regard to the counter.

- **TopologyUpdateFailCount** — The number of topology changes made in the CMP that fail to update an associated MPE. For example, if an MPE is offline while a Network Element is changed, the fail counter will increment once for that failed MPE update.

The following is an example of the TopologyUpdateStats tag:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <TopologyUpdateStats>
    <Sample>
      <StartTime>2006-10-26T14:30:22Z</StartTime>
      <EndTime>2006-10-26T14:35:11Z</EndTime>
      <TopologyUpdateCount>942</TopologyUpdateCount>
      <TopologyUpdateFailCount>6</TopologyUpdateFailCount>
    </Sample>
  </TopologyUpdateStats>
</Statistics>
```

Subscriber Update Statistics

The following examples show the request and response that are defined in the XSDs for the SubscriberUpdateStats tag.

Request

This request follows the **QueryOmStats > SubscriberUpdateStats** tag defined in the XSDs.

The following is an example of a request for subscriber update statistics:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:40:00Z</EndTime>
  <SubscriberUpdateStats></SubscriberUpdateStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > SubscriberUpdateStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- **SubscriberUpdateCount** — The number of subscriber changes made in the CMP that resulted in changes to an MPE. Subscriber data includes accounts and tiers. Changes to this data can occur through either the CMP GUI or the XML Interface. The counter is incremented for each MPE that updates as a result of the change. For example, when a user updates an account, the subscriber update counter increments for each MPE that the account is associated with.

Batch changes are treated as a single update to an MPE. An OSSI XML interface update may be made across multiple accounts but all of those changes are pushed at one time to the MPE. This is treated as a single subscriber change with regard to the counter.
- **SubscriberUpdateFailCount** — The number of subscriber changes made in the CMP that fail to update an associated MPE. For example, if an MPE is offline while an account is changed, the fail counter will increment once for that failed MPE update.

The following is an example of the SubscriberUpdateStats tag:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <SubscriberUpdateStats>
    <Sample>
      <StartTime>2006-10-26T14:30:22Z</StartTime>
      <EndTime>2006-10-26T14:35:11Z</EndTime>
      <SubscriberUpdateCount>942</SubscriberUpdateCount>
      <SubscriberUpdateFailCount>6</SubscriberUpdateFailCount>
    </Sample>
  </SubscriberUpdateStats>
</Statistics>
```

Policy Server Statistics

The following examples show the request and response that are defined in the XSDs for the PolicyServerStats tag.

Request

This request follows the **QueryOmStats > PolicyServerStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:35:00Z</EndTime>
  <PolicyServerStats>
    <PolicyServer>Atlanta105</PolicyServer>
  </PolicyServerStats>
</QueryOmStats>
```

The following is an example of a request for all policy servers in the system:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:40:00Z</EndTime>
  <PolicyServerStats></PolicyServerStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > PolicyServerStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- **TotalNetworkElementCount** — The total (absolute) number of network elements associated with that MPE. The absolute value is the value taken at the EndTime of the reported sample.
- **TotalSubscriberCount** — The total (absolute) number of accounts associated with that MPE.

The following is an example of the PolicyServerStats tag:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <PolicyServerStats>
    <Sample>
      <StartTime>2006-10-26T14:30:22Z</StartTime>
      <EndTime>2006-10-26T14:35:11Z</EndTime>
      <PolicyServer>Atlanta105</PolicyServer>
      <IsComplete>true</IsComplete>
      <TotalNetworkElementCount>52</TotalNetworkElementCount>
      <TotalSubscriberCount>1000000</TotalSubscriberCount>
    </Sample>
  </PolicyServerStats>
</Statistics>
```

Message Processing Statistics

The following examples show the request and response that are defined in the XSDs for the MessageProcessingStats tag.

Request

This request follows the **QueryOmStats > MessageProcessingStats** tag defined in the XSDs.

The following is an example of a request for all policy servers in the system:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:40:00Z</EndTime>
  <MessageProcessingStats/>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > MessageProcessingStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- SessionCount — Session requests received.
- SessionSuccessCount — Session requests successfully created.
- ActiveSessionCount — The absolute value representing the current active session request received.
- SessionFailCount — Session request failures. For example, this could be due to a policy denying a request.
- SessionProtocolFailCount — Number of session failures due to an invalid message or parameter. This count is incremented whenever the MPE determines that an incoming message from the AM has an invalid message and has to be dropped by the MPE.
- SessionPolicyFailCount — Number of session requests that trigger a policy. This count is maintained in the MPE, one per policy. When the condition of a policy triggers, the count for that policy is incremented. The value displayed is a total trigger count. That is, the sum of this value for all the policies. For example, if the definition of a policy is defined as, “when the device usage is greater than 80% of capacity, reject message”. When the MPE executes this policy in response to a request, if the policy triggers (i.e. if the MPE determines that the device usage is > 80%), the trigger count for that policy is incremented.
- PeakTransactionRate — An absolute value representing the peak number of transactions occurring within a given sample period.
- SessionUnknownPathFailCount — The number of session failures resulting from an unknown or nonexistent path.
- SessionUnknownSubscriberCount — The number of session failures resulting from an unknown subscriber ID.

The following is an example of the MessageProcessingStats tag:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <MessageProcessingStats>
    <Sample>
      <StartTime>2006-10-26T14:30:22Z</StartTime>
      <EndTime>2006-10-26T14:35:11Z</EndTime>
      <PolicyServer>Atlanta105</PolicyServer>
      <IsComplete>true</IsComplete>
      <SessionCount>100</SessionCount>
      <SessionSuccessCount>97</SessionSuccessCount>
      <SessionFailCount>3</SessionFailCount>
      <SessionUnknownPathFailCount>0</SessionUnknownPathFailCount>
      <SessionUnknownSubscriberFailCount>0</SessionUnknownSubscriberFailCount>

      <SessionProtocolFailCount>1</SessionProtocolFailCount>
      <SessionPolicyFailCount>2</SessionPolicyFailCount>
```

```

        <PeakTransactionRate>0</PeakTransactionRate>
        <ActiveSessionCount>0</ActiveSessionCount>
    </Sample>
</MessageProcessingStats>
</Statistics>

```

Network Element Statistics

The following examples show the request and response that are defined in the XSDs for the `NetworkElementStats` tag.

Request

This request follows the **QueryOmStats** > **NetworkElementStats** tag defined in the XSDs.

The following is an example of a request for a single network element using the `Name` parameter:

```

<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:35:00Z</EndTime>
  <NetworkElementStats>
    <Name>Router1</Name>
  </NetworkElementStats>
</QueryOmStats>

```

The following is an example of a request for multiple network elements using the `Name(s)` and `NeId(s)` parameters. This example returns statistics for three different network elements:

```

<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2006-10-12T11:15:00Z</StartTime>
  <EndTime>2006-10-12T11:25:00Z</EndTime>
  <NetworkElementStats>
    <Name>Router1</Name>
    <Name>Router2</Name>
    <Name>Router3</Name>
  </NetworkElementStats>
</QueryOmStats>

```

The following is an example of a request for all network elements in the system. This example returns statistics for each network element:

```

<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2006-10-12T11:15:00Z</StartTime>
  <EndTime>2006-10-12T11:25:00Z</EndTime>
  <NetworkElementStats></NetworkElementStats>
</QueryOmStats>

```

Response

The response to this request follows the **Statistics** > **NetworkElementStats** tag defined in the XSDs.

Both Name and NeId are returned along with the statistics and actual recorded times for those statistics. Sample groups are ordered by policy server, network element, available interfaces, and then by time.

This OM Group, by default, contains a combination of delta and absolute values. Individual statistics returned as absolutes are described as follows:

- Name — Unique name identifying the Network Element for the following statistics.
 - NeId — Optional identifier field for the Network Element.
 - InterfaceName — Identifying field for the Network Element's Interface.
 - SessionCount — Current active sessions for that Network Element or Interface. This is a cumulative value and is displayed as an absolute.
 - SessionSuccessCount — Successful sessions.
 - SessionFailCount — Session failures.

Note: Session failures can occur for a variety of reasons, for example, when a gate is created that is greater than the gate limit, the MPE responds with an error code. The default in this instance is "0" which means "no limit".
- AbnormalDisconnectCount — Number of network elements that have disconnected from the MPE abnormally. For example, due to a break in the network.
- Capacity — The currently defined maximum capacity for this Network Element or Interface. This is a static absolute value defined in the CMP for that object.
- BandwidthUpstream — This is the current reserved upstream bandwidth allocated for this Network Element or Interface. This is a non-cumulative value displayed as an absolute.
- BandwidthDownstream — This is the current reserved downstream bandwidth allocated for this Network Element or Interface. This is a non-cumulative value displayed as an absolute.
- MaxBandwidthDownstream — This statistic represents the maximum committed bandwidth flows allocated for this Network Element or Interface. This value is also an absolute value that indicates the peak bandwidth usage in the history of a Network Element.

The following is an example XML response to a multiple network element request:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <NetworkElementStats>
    <Sample>
      <StartTime>2006-10-12T11:18:30Z</StartTime>
      <EndTime>2006-10-12T11:19:20Z</EndTime>
      <PolicyServer>Atlanta105</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>Router1</Name>
      <NeId>12345</NeId>
      <SessionCount>3</SessionCount>
      <SessionSuccessCount>3</SessionSuccessCount>
      <SessionFailCount>0</SessionFailCount>
      <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
      <Capacity>50000000</Capacity>
      <BandwidthUpstream>3000000</BandwidthUpstream>
      <BandwidthDownstream>100000</BandwidthDownstream>
      <Interface>
        <InterfaceName>If1</InterfaceName>
        <SessionCount>3</SessionCount>
        <SessionSuccessCount>3</SessionSuccessCount>
        <SessionFailCount>0</SessionFailCount>
        <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
```

```

        <Capacity>50000000</Capacity>
        <BandwidthUpstream>3000000</BandwidthUpstream>
        <BandwidthDownstream>100000</BandwidthDownstream>
    </Interface>
</Sample>
<Sample>
    <StartTime>2006-10-12T11:19:20Z</StartTime>
    <EndTime>2006-10-12T11:20:10Z</EndTime>
    <PolicyServer>Atlanta105</PolicyServer>
    <IsComplete>true</IsComplete>
    <Name>Router1</Name>
    <NeId>12345</NeId>
    <SessionCount>0</SessionCount>
    <SessionSuccessCount>0</SessionSuccessCount>
    <SessionFailCount>0</SessionFailCount>
    <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
    <Capacity>50000000</Capacity>
    <BandwidthUpstream>3000000</BandwidthUpstream>
    <BandwidthDownstream>100000</BandwidthDownstream>
    <Interface>
        <InterfaceName>If1</InterfaceName>
        <SessionCount>0</SessionCount>
        <SessionSuccessCount>0</SessionSuccessCount>
        <SessionFailCount>0</SessionFailCount>
        <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
        <Capacity>50000000</Capacity>
        <BandwidthUpstream>3000000</BandwidthUpstream>
        <BandwidthDownstream>100000</BandwidthDownstream>
    </Interface>
</Sample>
<Sample>
    <StartTime>2006-10-12T11:20:10Z</StartTime>
    <EndTime>2006-10-12T11:21:00Z</EndTime>
    <PolicyServer>Atlanta105</PolicyServer>
    <IsComplete>true</IsComplete>
    <Name>Router1</Name>
    <NeId>12345</NeId>
    <SessionCount>9</SessionCount>
    <SessionSuccessCount>9</SessionSuccessCount>
    <SessionFailCount>0</SessionFailCount>
    <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
    <Capacity>50000000</Capacity>
    <BandwidthUpstream>3000000</BandwidthUpstream>
    <BandwidthDownstream>100000</BandwidthDownstream>
    <Interface>
        <InterfaceName>If1</InterfaceName>
        <SessionCount>9</SessionCount>
        <SessionSuccessCount>9</SessionSuccessCount>
        <SessionFailCount>0</SessionFailCount>
        <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
        <Capacity>50000000</Capacity>
        <BandwidthUpstream>3000000</BandwidthUpstream>
        <BandwidthDownstream>100000</BandwidthDownstream>
    </Interface>
</Sample>
<Sample>
    <StartTime>2006-10-12T11:18:30Z</StartTime>
    <EndTime>2006-10-12T11:19:20Z</EndTime>
    <PolicyServer>Atlanta105</PolicyServer>
    <IsComplete>true</IsComplete>
    <Name>Router 2</Name>
    <NeId>12341</NeId>
    <SessionCount>11</SessionCount>
    <SessionSuccessCount>11</SessionSuccessCount>

```

```

<SessionFailCount>0</SessionFailCount>
<AbnormalDisconnectCount>0</AbnormalDisconnectCount>
<Capacity>50000000</Capacity>
<BandwidthUpstream>3000000</BandwidthUpstream>
<BandwidthDownstream>100000</BandwidthDownstream>
<Interface>
  <InterfaceName>If2</InterfaceName>
  <SessionCount>11</SessionCount>
  <SessionSuccessCount>11</SessionSuccessCount>
  <SessionFailCount>0</SessionFailCount>
  <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
  <Capacity>50000000</Capacity>
  <BandwidthUpstream>3000000</BandwidthUpstream>
  <BandwidthDownstream>100000</BandwidthDownstream>
</Interface>
</Sample>
<Sample>
  <StartTime>2006-10-12T11:19:20Z</StartTime>
  <EndTime>2006-10-12T11:20:10Z</EndTime>
  <PolicyServer>Atlanta105</PolicyServer>
  <IsComplete>true</IsComplete>
  <Name>Router 2</Name>
  <NeId>12341</NeId>
  <SessionCount>2</SessionCount>
  <SessionSuccessCount>2</SessionSuccessCount>
  <SessionFailCount>0</SessionFailCount>
  <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
  <Capacity>50000000</Capacity>
  <BandwidthUpstream>3000000</BandwidthUpstream>
  <BandwidthDownstream>100000</BandwidthDownstream>
  <Interface>
    <InterfaceName>If2</InterfaceName>
    <SessionCount>2</SessionCount>
    <SessionSuccessCount>2</SessionSuccessCount>
    <SessionFailCount>0</SessionFailCount>
    <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
    <Capacity>50000000</Capacity>
    <BandwidthUpstream>3000000</BandwidthUpstream>
    <BandwidthDownstream>100000</BandwidthDownstream>
  </Interface>
</Sample>
<Sample>
  <StartTime>2006-10-12T11:20:10Z</StartTime>
  <EndTime>2006-10-12T11:21:00Z</EndTime>
  <PolicyServer>Atlanta105</PolicyServer>
  <IsComplete>true</IsComplete>
  <Name>Router 2</Name>
  <NeId>12341</NeId>
  <SessionCount>9</SessionCount>
  <SessionSuccessCount>9</SessionSuccessCount>
  <SessionFailCount>0</SessionFailCount>
  <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
  <Capacity>50000000</Capacity>
  <BandwidthUpstream>3000000</BandwidthUpstream>
  <BandwidthDownstream>100000</BandwidthDownstream>
  <Interface>
    <InterfaceName>If2</InterfaceName>
    <SessionCount>9</SessionCount>
    <SessionSuccessCount>9</SessionSuccessCount>
    <SessionFailCount>0</SessionFailCount>
    <AbnormalDisconnectCount>0</AbnormalDisconnectCount>
    <Capacity>50000000</Capacity>
    <BandwidthUpstream>3000000</BandwidthUpstream>
    <BandwidthDownstream>100000</BandwidthDownstream>
  </Interface>
</Sample>

```



```

        </Interface>
      </Sample>
    </NetworkElementStats>
  </Statistics>

```

Latency Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterAfLatencyStats tag.

Request

This request follows the **QueryOmStats** > **DiameterAfLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <DiameterAfLatencyStats>
      <PolicyServer>PolicyServer</PolicyServer>
    </DiameterAfLatencyStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics** > **DiameterAfLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterAfLatencyStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MaxTransactionInProcessingTime>0</MaxTransactionInProcessingTime>
      <AverageTransactionInProcessingTime>0</AverageTransactionInProcessingTime>

      <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
      <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

      <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
      <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
      <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
      <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
      <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
      <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
      <TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
      <TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
    </Sample>
  </DiameterAfLatencyStats>
</Statistics>

```

```

<TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
<TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
<TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
<TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
<TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
<TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
<TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
<TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

<TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>

<TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>

<TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>

<TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>

<TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
</Sample>
</DiameterAfLatencyStats>
</Statistics>

```

Request

This request follows the **QueryOmStats > DiameterAfPeerLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <DiameterAfPeerLatencyStats>
      <Name>ApplicationName</Name>
    </DiameterAfPeerLatencyStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterAfPeerfLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterAfPeerfLatencyStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>ApplicationName</Name>
      <NeId>NeId</NeId>
      <NetworkElementType>NetworkElementType</NetworkElementType>
      <NetworkElementSubType>NetworkElementSubType</NetworkElementSubType>
      <ConnectAddress>10.60.4.56</ConnectAddress>
      <ConnectPort>3868</ConnectPort>
      <ConnectType>TCP</ConnectType>
    </Sample>
  </DiameterAfPeerfLatencyStats>
</Statistics>

```

```

    <MaxTransactionInProcessingTime>0</MaxTransactionInProcessingTime>
    <AverageTransactionInProcessingTime>0</AverageTransactionInProcessingTime>

    <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
    <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

    <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
    <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
    <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
    <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
    <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
    <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
    <TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
    <TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
    <TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
    <TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
    <TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
    <TransactionTime_Out_0_20_Count>0</TransactionTime_Out_0_20_Count>
    <TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
    <TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
    <TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
    <TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
    <TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

    <TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>

    <TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>

    <TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>

    <TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>

    <TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
  </Sample>
</DiameterAfPeerfLatencyStats>
</Statistics>

```

Request

This request follows the **QueryOmStats** > **PcmmCmtsLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <PcmmCmtsLatencyStats>
      <PolicyServer>PolicyServer</PolicyServer>
    </PcmmCmtsLatencyStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics** > **PcmmCmtsLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>

```

```

<Statistics>
  <PcmmCmtsLatencyStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MaxTransactionInProcessingTime>0</MaxTransactionInProcessingTime>
      <AverageTransactionInProcessingTime>0</AverageTransactionInProcessingTime>

      <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
      <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

      <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
      <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
      <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
      <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
      <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
      <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
      <TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
      <TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
      <TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
      <TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
      <TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
      <TransactionTime_Out_0_20_Count>0</TransactionTime_Out_0_20_Count>
      <TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
      <TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
      <TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
      <TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
      <TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

      <TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>
      <TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>
      <TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>
      <TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>

      <TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
    </Sample>
  </PcmmCmtsLatencyStats>
</Statistics>

```

Request

This request follows the **QueryOmStats > PcmmCmtsPeerLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
  <XmlInterfaceRequest>
    <QueryOmStats>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PcmmCmtsPeerLatencyStats>
        <Name>NetworkElementName</Name>
      </PcmmCmtsPeerLatencyStats>
    </QueryOmStats>
  </XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > PcmmCmtsPeerLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <PcmmCmtsPeerLatencyStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>NetworkElementName</Name>
      <NeId>NeId</NeId>
      <NetworkElementType>NetworkElementType</NetworkElementType>
      <NetworkElementSubType>NetworkElementSubType</NetworkElementSubType>
      <ConnectAddress>10.60.4.56</ConnectAddress>
      <ConnectPort>3868</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <MaxTransactionInProcessingTime>0</MaxTransactionInProcessingTime>
      <AverageTransactionInProcessingTime>0</AverageTransactionInProcessingTime>

      <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
      <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

      <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
      <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
      <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
      <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
      <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
      <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
      <TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
      <TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
      <TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
      <TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
      <TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
      <TransactionTime_Out_0_20_Count>0</TransactionTime_Out_0_20_Count>
      <TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
      <TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
      <TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
      <TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
      <TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

      <TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>

      <TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>

      <TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>

      <TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>

      <TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
    </Sample>
  </PcmmCmtsPeerLatencyStats>
</Statistics>
```

Request

This request follows the **QueryOmStats > PcmmAmLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <PcmmAmLatencyStats>
      <PolicyServer>PolicyServer</PolicyServer>
    </PcmmAmLatencyStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > PcmmAmLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <PcmmAmLatencyStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MaxTransactionInProcessingTime>0</MaxTransactionInProcessingTime>
      <AverageTransactionInProcessingTime>0</AverageTransactionInProcessingTime>

      <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
      <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

      <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
      <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
      <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
      <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
      <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
      <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
      <TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
      <TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
      <TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
      <TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
      <TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
      <TransactionTime_Out_0_20_Count>0</TransactionTime_Out_0_20_Count>
      <TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
      <TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
      <TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
      <TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
      <TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

      <TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>

      <TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>

      <TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>

      <TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>
```

```

    <TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
  </Sample>
</PcmmAmPeerLatencyStats>
</Statistics>

```

Request

This request follows the **QueryOmStats > PcmmAmPeerLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <PcmmAmPeerLatencyStats>
      <Name>ApplicationName</Name>
    </PcmmAmPeerLatencyStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > PcmmAmPeerLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<Statistics>
  <PcmmAmPeerLatencyStats>
    <Sample>
      <StartTime>2013-04-12T01:45:00Z</StartTime>
      <EndTime>2013-04-12T01:00:00Z</EndTime>
      <PolicyServer>policyserver</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>ApplicationName</Name>
      <AmId>AmId</AmId>
      <ConnectAddress>10.60.56.60</ConnectAddress>
      <MaxTransactionInProcessingTime>863</MaxTransactionInProcessingTime>
      <AverageTransactionInProcessingTime>178</AverageTransactionInProcessingTime>

      <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
      <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

      <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
      <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
      <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
      <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
      <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
      <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
      <TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
      <TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
      <TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
      <TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
      <TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
      <TransactionTime_Out_0_20_Count>0</TransactionTime_Out_0_20_Count>
      <TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
      <TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
    </Sample>
  </PcmmAmPeerLatencyStats>
</Statistics>

```

```

    <TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
    <TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
    <TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

    <TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>

    <TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>

    <TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>

    <TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>

    <TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
  </Sample>
</PcmmAmPeerLatencyStats>
</Statistics>

```

Request

This request follows the **QueryOmStats** > **PcmmDpsLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <PcmmDpsLatencyStats>
      <PolicyServer>PolicyServer</PolicyServer>
    </PcmmDpsLatencyStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics** > **PcmmDpsLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <PcmmDpsLatencyStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MaxTransactionInProcessingTime>0</MaxTransactionInProcessingTime>
      <AverageTransactionInProcessingTime>0</AverageTransactionInProcessingTime>

      <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
      <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

      <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
      <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
      <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
      <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
      <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
      <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
    </Sample>
  </PcmmDpsLatencyStats>
</Statistics>

```



```

<TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
<TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
<TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
<TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
<TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
<TransactionTime_Out_0_20_Count>0</TransactionTime_Out_0_20_Count>
<TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
<TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
<TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
<TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
<TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

<TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>
<TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>
<TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>
<TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>
<TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
</Sample>
</PcmmDpsLatencyStats>
</Statistics>

```

Request

This request follows the **QueryOmStats > PcmmDpsPeerLatencyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <PcmmDpsPeerLatencyStats>
      <Name>DpsName</Name>
    </PcmmDpsPeerLatencyStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > PcmmDpsPeerLatencyStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<Statistics>
  <PcmmDpsPeerLatencyStats>
    <Sample>
      <StartTime>2012-06-07T01:00:00Z</StartTime>
      <EndTime>2012-06-07T01:15:00Z</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>DpsName</Name>
      <DpsId>NeId</DpsId>
      <ConnectAddress>10.60.4.56</ConnectAddress>
      <MaxTransactionInProcessingTime>0</MaxTransactionInProcessingTime>
    </Sample>
  </PcmmDpsPeerLatencyStats>
</Statistics>

```

```

<AverageTransactionInProcessingTime>0</AverageTransactionInProcessingTime>

  <MaxTransactionOutProcessingTime>0</MaxTransactionOutProcessingTime>
  <AverageTransactionOutProcessingTime>0</AverageTransactionOutProcessingTime>

  <TransactionTime_In_0_20_Count>0</TransactionTime_In_0_20_Count>
  <TransactionTime_In_20_40_Count>0</TransactionTime_In_20_40_Count>
  <TransactionTime_In_40_60_Count>0</TransactionTime_In_40_60_Count>
  <TransactionTime_In_60_80_Count>0</TransactionTime_In_60_80_Count>
  <TransactionTime_In_80_100_Count>0</TransactionTime_In_80_100_Count>
  <TransactionTime_In_100_120_Count>0</TransactionTime_In_100_120_Count>
  <TransactionTime_In_120_140_Count>0</TransactionTime_In_120_140_Count>
  <TransactionTime_In_140_160_Count>0</TransactionTime_In_140_160_Count>
  <TransactionTime_In_160_180_Count>0</TransactionTime_In_160_180_Count>
  <TransactionTime_In_180_200_Count>0</TransactionTime_In_180_200_Count>
  <TransactionTime_In_gt_200_Count>0</TransactionTime_In_gt_200_Count>
  <TransactionTime_Out_0_20_Count>0</TransactionTime_Out_0_20_Count>
  <TransactionTime_Out_20_40_Count>0</TransactionTime_Out_20_40_Count>
  <TransactionTime_Out_40_60_Count>0</TransactionTime_Out_40_60_Count>
  <TransactionTime_Out_60_80_Count>0</TransactionTime_Out_60_80_Count>
  <TransactionTime_Out_80_100_Count>0</TransactionTime_Out_80_100_Count>
  <TransactionTime_Out_100_120_Count>0</TransactionTime_Out_100_120_Count>

  <TransactionTime_Out_120_140_Count>0</TransactionTime_Out_120_140_Count>

  <TransactionTime_Out_140_160_Count>0</TransactionTime_Out_140_160_Count>

  <TransactionTime_Out_160_180_Count>0</TransactionTime_Out_160_180_Count>

  <TransactionTime_Out_180_200_Count>0</TransactionTime_Out_180_200_Count>

  <TransactionTime_Out_gt_200_Count>0</TransactionTime_Out_gt_200_Count>
</Sample>
</PcmmDpsPeerLatencyStats>
</Statistics>

```

RADIUS Operational Measurement Requests

This section shows the requests and responses for:

- RADIUS Accounting Statistics
- RADIUS Accounting Network Element Statistics
- RADIUS-S Statistics
- RADIUS-S Network Element Statistics

RADIUS Accounting Statistics

The following examples show the request and response that are defined in the XSDs for the RadiusAccountingStats tag.

Request

This request follows the **QueryOmStats > RadiusAccountingStats** tag defined in the XSDs.

The following is an example of a request for all policy servers in the system:

```
<?xml version="1.0" encoding="UTF-8" ?>
- <QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T13:00:00</EndTime>
  - <RadiusAccountingStats>
    <PolicyServer>mpe85</PolicyServer>
  </RadiusAccountingStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > RadiusAccountingStats** tag defined in the XSDs.

- MessagesInCount — Number of messages in.
- MessagesOutCount — Number of messages out.
- AccountingStartCount — Number of Accounting Start messages received.
- AccountingStopCount — Number of Accounting Stop messages received.
- AccountingUpdateCount — Number of Accounting Interim Update messages received.
- DuplicateMessageCount — Number of duplicate messages received.
- MD5MismatchReceivedCount — Number of messages discarded because of MD5 mismatch errors.
- ActiveSessionCount — Number of active sessions.
- UnknownMessageCount — Number of unknown messages received.
- MaximumActiveSessionsCount — Number of maximum sessions.
- StaleSessionsCount — Number of stale sessions.

The following is an example XML response to a RadiusAccountingStats tag request:

```
<?xml version="1.0" encoding="UTF-8" ?>
- <Statistics>
- <RadiusAccountingStats>
  - <Sample>
    <StartTime>2001-12-31T12:00:00Z</StartTime>
    <EndTime>2001-12-31T12:05:00Z</EndTime>
    <PolicyServer>mpe85</PolicyServer>
    <IsComplete>>true</IsComplete>
    <MessagesInCount>0</MessagesInCount>
    <MessagesOutCount>0</MessagesOutCount>
    <AccountingStartCount>0</AccountingStartCount>
    <AccountingStopCount>0</AccountingStopCount>
    <AccountingUpdateCount>0</AccountingUpdateCount>
    <DuplicateMessageCount>0</DuplicateMessageCount>
    <Md5MismatchReceivedCount>0</Md5MismatchReceivedCount>
    <UnknownMessageCount>0</UnknownMessageCount>
    <ActiveSessionsCount>0</ActiveSessionsCount>
    <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
    <StaleSessionsCount>0</StaleSessionsCount>
  </Sample>
</RadiusAccountingStats>
</Statistics>
```

RADIUS Accounting Network Element Statistics

The following examples show the request and response that are defined in the XSDs for the RadiusAccountingNetworkElementStats tag.

Request

This request follows the **QueryOmStats > RadiusAccountingNetworkElementStats** tag defined in the XSDs.

The following is an example of a request for all policy servers in the system:

```
<?xml version="1.0" encoding="UTF-8" ?>
- <QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T13:00:00</EndTime>
  - <RadiusAccountingNetworkElementStats>
    <Name>Server1</Name>
  </RadiusAccountingNetworkElementStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > RadiusAccountingNetworkElementStats** tag defined in the XSDs.

- Name — Unique name identifying the Network Element for the following statistics.
 - NeId — Optional identifier field for the Network Element.
 - NetworkElementType — Type of the Network Element.
 - NetworkElementSubType — Sub Type of the Network Element.
 - AccountingStartCount — Number of Accounting Start messages received.
 - AccountingStopCount — Number of Accounting Stop messages received.
 - AccountingUpdateCount — Number of Accounting Interim Update messages received.
 - DuplicateMessageCount — Number of duplicate messages received.
 - MD5MismatchReceivedCount — Number of messages disgarded because of MD5 mismatch errors.
 - ActiveSessionCount — Number of active sessions.
 - UnknownMessageCount — Number of unknown messages received.
 - MaximumActiveSessionsCount — Number of maximum sessions.
 - StaleSessionsCount — Number of stale sessions.

The following is an example XML response to a RadiusAccountingNetworkElementStats tag request:

```
<?xml version="1.0" encoding="UTF-8" ?>
- <Statistics>
  - <RadiusAccountingNetworkElementStats>
    - <Sample>
      <StartTime>2001-12-31T12:00:00Z</StartTime>
      <EndTime>2001-12-31T12:05:00Z</EndTime>
      <PolicyServer>mpe85</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>Server1</Name>
      <NeId />
    </Sample>
  </RadiusAccountingNetworkElementStats>
</Statistics>
```

```

<NetworkElementType>NAS</NetworkElementType>
<NetworkElementSubType />
<MessagesInCount>0</MessagesInCount>
<MessagesOutCount>0</MessagesOutCount>
<MessagesDecodedCount>0</MessagesDecodedCount>
<AccountingStartCount>0</AccountingStartCount>
<AccountingStopCount>0</AccountingStopCount>
<AccountingUpdateCount>0</AccountingUpdateCount>
<DuplicateMessageCount>0</DuplicateMessageCount>
<Md5MismatchReceivedCount>0</Md5MismatchReceived
Count>
<UnknownMessageCount>0</UnknownMessageCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
<StaleSessionsCount>0</StaleSessionsCount>
</Sample>
</RadiusAccountingNetworkElementsStats>
</Statistics>

```

RADIUS-S Statistics

The following examples show the request and response that are defined in the XSDs for the RadiusStats tag.

Request

This request follows the **QueryOmStats > RadiusStats** tag defined in the XSDs.

The following is an example of a request for all policy servers in the system:

```

<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2007-10-26T14:30:00Z</StartTime>
  <EndTime>2007-10-26T14:40:00Z</EndTime>
  <RadiusStats></RadiusStats>
</QueryOmStats>

```

Response

The response to this request follows the **Statistics > RadiusStats** tag defined in the XSDs.

- MessagesInCount — Number of messages in.
- MessagesOutCount — Number of messages out.
- AccountingStartCount — Number of Accounting Start messages received.
- AccountingStopCount — Number of Accounting Stop messages received.
- AccountingUpdateCount — Number of Accounting Interim Update messages received.
- AccountingResponseCount — Number of Accounting Responses sent.
- AccessRequestCount — Number of Access-Request messages received.
- AccessAcceptCount — Number of Access-Accept messages sent.
- AccessRejectCount — Number of Access-Reject messages sent.
- ReceivedMd5ErrorCount — Number of received messages dropped because of MD5 errors.
- SendMd5ErrorCount — Number of CoA requests that failed because of MD5 errors.
- ReceivedErrorCount — Number of received messages dropped because of errors.
- CoACount — Number of CoA messages sent.

- CoASuccessCount — Number of CoA-ACK messages received.
- CoAProvisionCount — Number of CoA messages to provision a default QOS profile.
- CoaApplicationCount — Number of CoA messages to adjust QOS for an application request.
- CoANckCount — Number of CoA-NAK messages received.
- NoResponseCount — Number of requests that received no response.
- UnknownGatewayRequestCount — Number of received messages dropped from unknown gateways.
- ResendCount — Number of CoA requests that were retransmitted.
- SendErrorCount — Number of CoA requests that were not sent because of errors.

The following is an example XML response to a RadiusStats tag request:

```
<?xml version="1.0" ?>
<Statistics>
  <RadiusStats>
    <Sample>
      <StartTime>2007-01-29T17:32:59Z</StartTime>
      <EndTime>2007-01-29T17:35:37Z</EndTime>
      <PolicyServer>localhost</PolicyServer>
      <IsComplete>true</IsComplete>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <AccountingStartCount>0</AccountingStartCount>
      <AccountingStopCount>0</AccountingStopCount>
      <AccountingUpdateCount>0</AccountingUpdateCount>
      <AccountingResponseCount>0</AccountingResponseCount>
      <AccessRequestCount>0</AccessRequestCount>
      <AccessAcceptCount>0</AccessAcceptCount>
      <AccessRejectCount>0</AccessRejectCount>
      <ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
      <SendMd5ErrorCount>0</SendMd5ErrorCount>
      <ReceivedErrorCount>0</ReceivedErrorCount>
      <CoACount>0</CoACount>
      <CoASuccessCount>0</CoASuccessCount>
      <CoAProvisionCount>0</CoAProvisionCount>
      <CoaApplicationCount>0</CoaApplicationCount>
      <CoANckCount>0</CoANckCount>
      <NoResponseCount>0</NoResponseCount>
      <UnknownGatewayRequestCount>0</UnknownGatewayRequestCount>
      <ResendCount>0</ResendCount>
      <SendErrorCount>0</SendErrorCount>
    </Sample>
    <Sample>
      <StartTime>2007-01-29T17:35:37Z</StartTime>
      <EndTime>2007-01-29T17:37:13Z</EndTime>
      <PolicyServer>localhost</PolicyServer>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <AccountingStartCount>0</AccountingStartCount>
      <AccountingStopCount>0</AccountingStopCount>
      <AccountingUpdateCount>0</AccountingUpdateCount>
      <AccountingResponseCount>0</AccountingResponseCount>
      <AccessRequestCount>0</AccessRequestCount>
      <AccessAcceptCount>0</AccessAcceptCount>
      <AccessRejectCount>0</AccessRejectCount>
      <ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
      <SendMd5ErrorCount>0</SendMd5ErrorCount>
      <ReceivedErrorCount>0</ReceivedErrorCount>
      <CoACount>0</CoACount>
      <CoASuccessCount>0</CoASuccessCount>
```

```

    <CoAProvisionCount>0</CoAProvisionCount>
    <CoaApplicationCount>0</CoaApplicationCount>
    <CoANckCount>0</CoANckCount>
    <NoResponseCount>0</NoResponseCount>
    <UnknownGatewayRequestCount>0</UnknownGatewayRequestCount>
    <ResendCount>0</ResendCount>
    <SendErrorCount>0</SendErrorCount>
  </Sample>
  <Sample>
    <StartTime>2007-01-29T17:37:13Z</StartTime>
    <EndTime>2007-01-29T17:45:00Z</EndTime>
    <PolicyServer>localhost</PolicyServer>
    <IsComplete>true</IsComplete>
    <MessagesInCount>0</MessagesInCount>
    <MessagesOutCount>0</MessagesOutCount>
    <AccountingStartCount>0</AccountingStartCount>
    <AccountingStopCount>0</AccountingStopCount>
    <AccountingUpdateCount>0</AccountingUpdateCount>
    <AccountingResponseCount>0</AccountingResponseCount>
    <AccessRequestCount>0</AccessRequestCount>
    <AccessAcceptCount>0</AccessAcceptCount>
    <AccessRejectCount>0</AccessRejectCount>
    <ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
    <SendMd5ErrorCount>0</SendMd5ErrorCount>
    <ReceivedErrorCount>0</ReceivedErrorCount>
    <CoACount>0</CoACount>
    <CoASuccessCount>0</CoASuccessCount>
    <CoAProvisionCount>0</CoAProvisionCount>
    <CoaApplicationCount>0</CoaApplicationCount>
    <CoANckCount>0</CoANckCount>
    <NoResponseCount>0</NoResponseCount>
    <UnknownGatewayRequestCount>0</UnknownGatewayRequestCount>
    <ResendCount>0</ResendCount>
    <SendErrorCount>0</SendErrorCount>
  </Sample>
  <Sample>
    <StartTime>2007-01-29T18:30:00Z</StartTime>
    <EndTime>2007-01-29T18:45:00Z</EndTime>
    <PolicyServer>localhost</PolicyServer>
    <IsComplete>true</IsComplete>
    <MessagesInCount>0</MessagesInCount>
    <MessagesOutCount>0</MessagesOutCount>
    <AccountingStartCount>0</AccountingStartCount>
    <AccountingStopCount>0</AccountingStopCount>
    <AccountingUpdateCount>0</AccountingUpdateCount>
    <AccountingResponseCount>0</AccountingResponseCount>
    <AccessRequestCount>0</AccessRequestCount>
    <AccessAcceptCount>0</AccessAcceptCount>
    <AccessRejectCount>0</AccessRejectCount>
    <ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
    <SendMd5ErrorCount>0</SendMd5ErrorCount>
    <ReceivedErrorCount>0</ReceivedErrorCount>
    <CoACount>0</CoACount>
    <CoASuccessCount>0</CoASuccessCount>
    <CoAProvisionCount>0</CoAProvisionCount>
    <CoaApplicationCount>0</CoaApplicationCount>
    <CoANckCount>0</CoANckCount>
    <NoResponseCount>0</NoResponseCount>
    <UnknownGatewayRequestCount>0</UnknownGatewayRequestCount>
    <ResendCount>0</ResendCount>
    <SendErrorCount>0</SendErrorCount>
  </Sample>
</RadiusStats>
</Statistics>

```

RADIUS-S Network Element Statistics

The following examples show the request and response that are defined in the XSDs for the `RadiusNetworkElementStats` tag.

Request

This request follows the **QueryOmStats > RadiusNetworkElementStats** tag defined in the XSDs.

The following is an example of a request for a single network element using the `Name` parameter:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:35:00Z</EndTime>
  <RadiusNetworkElementStats>
    <Name>Router1</Name>
  </RadiusNetworkElementStats>
</QueryOmStats>
```

The following is an example of a request for multiple network elements using the `Name(s)` and `NeId(s)` parameters. This example returns statistics for three different network elements:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2006-10-12T11:15:00Z</StartTime>
  <EndTime>2006-10-12T11:25:00Z</EndTime>
  <RadiusNetworkElementStats>
    <Name>Router1</Name>
    <Name>Router2</Name>
    <Name>Router3</Name>
  </RadiusNetworkElementStats>
</QueryOmStats>
```

The following is an example of a request for all network elements in the system. This example returns statistics for each network element:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2006-10-12T11:15:00Z</StartTime>
  <EndTime>2006-10-12T11:25:00Z</EndTime>
  <RadiusNetworkElementStats></RadiusNetworkElementStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > RadiusNetworkElementStats** tag defined in the XSDs.

Both `Name` and `NeId` are returned along with the statistics and actual recorded times for those statistics. Sample groups are ordered by policy server, network element, and then by time.

- `Name` — Unique name identifying the Network Element for the following statistics.
 - `NeId` — Optional identifier field for the Network Element.
 - `NetworkElementType` — Type of the Network Element.

- NetworkElementSubType — Sub Type of the Network Element.
- AccountingStartCount — Number of Accounting Start messages received.
- AccountingStopCount — Number of Accounting Stop messages received.
- AccountingUpdateCount — Number of Accounting Interim Update messages received.
- AccountingResponseCount — Number of Accounting responses sent.
- AccessRequestCount — Number of Access-Request messages received.
- AccessAcceptCount — Number of Access-Accept messages received.
- AccessRejectCount — Number of Access-Reject messages received.
- ReceivedMd5ErrorCount — Number of received messages dropped because of MD5 errors.
- SendMd5ErrorCount — Number of CoA requests that failed because of MD5 errors.
- ReceivedErrorCount — Number of messages dropped because of errors.
- CoACount — Number of CoA messages sent.
- CoASuccessCount — Number of CoA-ACK messages received.
- CoAProvisionCount — Number of CoA messages to provision a default QoS profile.
- CoaApplicationCount — Number of CoA messages to adjust QoS for an application request.
- CoANckCount — Number of CoA-NAK messages received.
- NoResponseCount — Number of CoA requests that received no response.
- SendErrorCount — Number of CoA requests that were not sent because of errors.
- ResendCount — Number of CoA requests that were retransmitted.

The following is an example XML response to a multiple network element request:

```
<?xml version="1.0" ?>
<Statistics>
  <RadiusNetworkElementStats>
    <Sample>
      <StartTime>2007-01-29T17:32:59Z</StartTime>
      <EndTime>2007-01-29T17:35:37Z</EndTime>
      <PolicyServer>localhost</PolicyServer>
      <Name>simpPDSN</Name>
      <NeId/>
      <NetworkElementType>PDSN</NetworkElementType>
      <NetworkElementSubType>Starent</NetworkElementSubType>
      <AccountingStartCount>0</AccountingStartCount>
      <AccountingStopCount>0</AccountingStopCount>
      <AccountingUpdateCount>0</AccountingUpdateCount>
      <AccountingResponseCount>0</AccountingResponseCount>
      <AccessRequestCount>0</AccessRequestCount>
      <AccessAcceptCount>0</AccessAcceptCount>
      <AccessRejectCount>0</AccessRejectCount>
      <ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
      <SendMd5ErrorCount>0</SendMd5ErrorCount>
      <ReceivedErrorCount>0</ReceivedErrorCount>
      <CoACount>0</CoACount>
      <CoASuccessCount>0</CoASuccessCount>
      <CoAProvisionCount>0</CoAProvisionCount>
      <CoaApplicationCount>0</CoaApplicationCount>
      <CoANckCount>0</CoANckCount>
      <NoResponseCount>0</NoResponseCount>
      <SendErrorCount>0</SendErrorCount>
      <ResendCount>0</ResendCount>
    </Sample>
    <Sample>
      <StartTime>2007-01-29T17:35:37Z</StartTime>
      <EndTime>2007-01-29T17:37:13Z</EndTime>
```

```

<PolicyServer>localhost</PolicyServer>
<Name>simPDSN</Name>
<NeId/>
<NetworkElementType>PDSN</NetworkElementType>
<NetworkElementSubType>Starent</NetworkElementSubType>
<AccountingStartCount>0</AccountingStartCount>
<AccountingStopCount>0</AccountingStopCount>
<AccountingUpdateCount>0</AccountingUpdateCount>
<AccountingResponseCount>0</AccountingResponseCount>
<AccessRequestCount>0</AccessRequestCount>
<AccessAcceptCount>0</AccessAcceptCount>
<AccessRejectCount>0</AccessRejectCount>
<ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
<SendMd5ErrorCount>0</SendMd5ErrorCount>
<ReceivedErrorCount>0</ReceivedErrorCount>
<CoACount>0</CoACount>
<CoASuccessCount>0</CoASuccessCount>
<CoAProvisionCount>0</CoAProvisionCount>
<CoaApplicationCount>0</CoaApplicationCount>
<CoANckCount>0</CoANckCount>
<NoResponseCount>0</NoResponseCount>
<SendErrorCount>0</SendErrorCount>
<ResendCount>0</ResendCount>
</Sample>
<Sample>
  <StartTime>2007-01-29T17:37:13Z</StartTime>
  <EndTime>2007-01-29T17:45:00Z</EndTime>
  <PolicyServer>localhost</PolicyServer>
  <Name>simPDSN</Name>
  <NeId/>
  <NetworkElementType>PDSN</NetworkElementType>
  <NetworkElementSubType>Starent</NetworkElementSubType>
  <AccountingStartCount>0</AccountingStartCount>
  <AccountingStopCount>0</AccountingStopCount>
  <AccountingUpdateCount>0</AccountingUpdateCount>
  <AccountingResponseCount>0</AccountingResponseCount>
  <AccessRequestCount>0</AccessRequestCount>
  <AccessAcceptCount>0</AccessAcceptCount>
  <AccessRejectCount>0</AccessRejectCount>
  <ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
  <SendMd5ErrorCount>0</SendMd5ErrorCount>
  <ReceivedErrorCount>0</ReceivedErrorCount>
  <CoACount>0</CoACount>
  <CoASuccessCount>0</CoASuccessCount>
  <CoAProvisionCount>0</CoAProvisionCount>
  <CoaApplicationCount>0</CoaApplicationCount>
  <CoANckCount>0</CoANckCount>
  <NoResponseCount>0</NoResponseCount>
  <SendErrorCount>0</SendErrorCount>
  <ResendCount>0</ResendCount>
</Sample>
<Sample>
  <StartTime>2007-01-29T17:45:00Z</StartTime>
  <EndTime>2007-01-29T18:00:01Z</EndTime>
  <PolicyServer>localhost</PolicyServer>
  <Name>simPDSN</Name>
  <NeId/>
  <NetworkElementType>PDSN</NetworkElementType>
  <NetworkElementSubType>Starent</NetworkElementSubType>
  <AccountingStartCount>0</AccountingStartCount>
  <AccountingStopCount>0</AccountingStopCount>
  <AccountingUpdateCount>0</AccountingUpdateCount>
  <AccountingResponseCount>0</AccountingResponseCount>
  <AccessRequestCount>0</AccessRequestCount>

```

```

        <AccessAcceptCount>0</AccessAcceptCount>
        <AccessRejectCount>0</AccessRejectCount>
        <ReceivedMd5ErrorCount>0</ReceivedMd5ErrorCount>
        <SendMd5ErrorCount>0</SendMd5ErrorCount>
        <ReceivedErrorCount>0</ReceivedErrorCount>
        <CoACount>0</CoACount>
        <CoASuccessCount>0</CoASuccessCount>
        <CoAProvisionCount>0</CoAProvisionCount>
        <CoaApplicationCount>0</CoaApplicationCount>
        <CoANckCount>0</CoANckCount>
        <NoResponseCount>0</NoResponseCount>
        <SendErrorCount>0</SendErrorCount>
        <ResendCount>0</ResendCount>
    </Sample>
</RadiusNetworkElementStats>
</Statistics>

```

Connected Network Elements Statistics

The following examples show the request and response that are defined in the XSDs for the ConnectedNetworkElementStats tag.

Request

This request follows the **QueryOmStats > ConnectedNetworkElementStats** tag defined in the XSDs.

The following is an example of a request for all policy servers in the system:

```

<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
    <StartTime>2007-10-26T14:30:00Z</StartTime>
    <EndTime>2007-10-26T14:40:00Z</EndTime>
    <ConnectedNetworkElementStats></ConnectedNetworkElementStats>
</QueryOmStats>

```

Response

The response to this request follows the **Statistics > ConnectedNetworkElementStats** tag defined in the XSDs.

ConnectedNetworkElementCount — The absolute number of network elements maintaining a consistent connection to each MPE. For example, B-RAS and MX elements.

The following is an example XML response to a ConnectedNetworkElementStats tag request:

```

<xml version="1.0" encoding="UTF-8"?>
<Statistics>
    <ConnectedNetworkElementStats>
        <Sample>
            <StartTime>2007-10-26T14:30:22Z</StartTime>
            <EndTime>2007-10-26T14:35:11Z</EndTime>
            <PolicyServer>Atlanta105</PolicyServer>
            <ConnectedNetworkElementCount>52</ConnectedNetworkElementCount>
        </Sample>
    </ConnectedNetworkElementStats>
</Statistics>

```

```
</ConnectedNetworkElementStats>
</Statistics>
```

Policy Statistics

The following examples show the request and response that are defined in the XSDs for the PolicyStats tag.

Request

This request follows the **QueryOmStats > PolicyStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <PolicyStats>
    <PolicyServer>PolicyServer</PolicyServer>
    <Name>PolicyName</Name>
  </PolicyStats>
</QueryOmStats>
```

The following is an example of a request for all policy servers in the system:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2006-10-26T14:30:00Z</StartTime>
  <EndTime>2006-10-26T14:40:00Z</EndTime>
  <PolicyStats></PolicyStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > PolicyStats** tag defined in the XSDs.

- TotalExecTime — the summary of all execution durations, where execution duration is measured starting the beginning of the policy conditions evaluation until the execution finishing.
- MaxExecTime — the longest execution duration of the policy.
- AvgExecTime — the arithmetic average off all execution durations of the policy.
- TriggerCount — number of policies triggered.
- FailCondCount — number of policies that failed because of conditions.
- FailNACount — number of policies that failed because of data not available/applicable.
- FailExcCount — number of policies that failed because of exceptions.

The following is an example XML response to a PolicyStats tag request:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <PolicyStats>
```

```

<Sample>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <PolicyServer>PolicyServer</PolicyServer>
  <IsComplete>true</IsComplete>
  <Name>PolicyName</Name>
  <EvalCount>0</EvalCount>
  <TriggerCount>0</TriggerCount>
  <FailCondCount>0</FailCondCount>
  <FailNACount>0</FailNACount>
  <FailExcCount>0</FailExcCount>
  <TotalExecTime>0</TotalExecTime>
  <AvgExecTime>0</AvgExecTime>
  <MaxExecTime>0</MaxExecTime>
  <MaxExecTime>0</MaxExecTime>
  <HistExecTime_000_020>0</HistExecTime_000_020>
  <HistExecTime_020_040>0</HistExecTime_020_040>
  <HistExecTime_040_060>0</HistExecTime_040_060>
  <HistExecTime_060_080>0</HistExecTime_060_080>
  <HistExecTime_080_100>0</HistExecTime_080_100>
  <HistExecTime_100_150>0</HistExecTime_100_150>
  <HistExecTime_150_200>0</HistExecTime_150_200>
  <HistExecTime_200_250>0</HistExecTime_200_250>
  <HistExecTimePlus_250>0</HistExecTimePlus_250>
</PolicyStats>
<Statistics>

```

Diameter Operational Measurements Requests

- Diameter Sh Peer Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Policy Charging Enforcement Function Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Policy Charging Enforcement Function Peer Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application (DRMA) Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application (DRMA) over SCTP Response Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application Peer Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Diameter Routing Agent (DRA) Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Application Function (AF) Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Application Function (AF) Peer Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Bearer Binding and Event Reporting Function (Bberf) Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF) Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF) Peer Statistics
- Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF) over SCTP Statistics

Diameter Sh Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterShStats tag.

Request

This request follows the **QueryOmStats > DiameterShStats** tag defined in the XSDs.

The following is an example of a request for all policy servers within the system:

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T13:00:00</EndTime>
  <DiameterShStats>
    <PolicyServer>mpe85</PolicyServer>
  </DiameterShStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > DiameterShStats** tag defined in the XSDs.

The following is an example XML response to a DiameterShStats tag request:

```
<?xml version="1.0" encoding="UTF-8" ?>
<Statistics>
  <DiameterShStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00Z</StartTime>
      <EndTime>2001-12-31T12:15:00Z</EndTime>
      <PolicyServer>mpe85</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <UDRMessagesReceivedCount>0</UDRMessagesReceivedCount>
      <UDRMessagesSentCount>0</UDRMessagesSentCount>
      <UDASuccessMessagesReceivedCount>0</UDASuccessMessagesReceivedCount>
      <UDASuccessMessagesSentCount>0</UDASuccessMessagesSentCount>
      <UDAFailureMessagesReceivedCount>0</UDAFailureMessagesReceivedCount>
      <UDAFailureMessagesSentCount>0</UDAFailureMessagesSentCount>
      <PNRMessagesReceivedCount>0</PNRMessagesReceivedCount>
      <PNRMessagesSentCount>0</PNRMessagesSentCount>
      <PNASuccessMessagesReceivedCount>0</PNASuccessMessagesReceivedCount>
      <PNASuccessMessagesSentCount>0</PNASuccessMessagesSentCount>
      <PNAFailureMessagesReceivedCount>0</PNAFailureMessagesReceivedCount>
      <PNAFailureMessagesSentCount>0</PNAFailureMessagesSentCount>
      <PURMessagesReceivedCount>0</PURMessagesReceivedCount>
      <PURMessagesSentCount>0</PURMessagesSentCount>
      <PUASuccessMessagesReceivedCount>0</PUASuccessMessagesReceivedCount>
      <PUASuccessMessagesSentCount>0</PUASuccessMessagesSentCount>
      <PUAFailureMessagesReceivedCount>0</PUAFailureMessagesReceivedCount>
      <PUAFailureMessagesSentCount>0</PUAFailureMessagesSentCount>
      <SNRMessagesReceivedCount>0</SNRMessagesReceivedCount>
      <SNRMessagesSentCount>0</SNRMessagesSentCount>
      <SNASuccessMessagesReceivedCount>0</SNASuccessMessagesReceivedCount>
      <SNASuccessMessagesSentCount>0</SNASuccessMessagesSentCount>
```

```

    <SNAFailureMessagesReceivedCount>0</SNAFailureMessagesReceivedCount>
    <SNAFailureMessagesSentCount>0</SNAFailureMessagesSentCount>
    <ActiveSessionsCount>0</ActiveSessionsCount>
    <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
    <PeerOkayCount>0</PeerOkayCount>
    <PeerDownCount>0</PeerDownCount>
    <PeerSuspectCount>0</PeerSuspectCount>
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterShStats>
</Statistics>

```

Diameter Sh Peer Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterShPeerStats tag.

Request

This request follows the **QueryOmStats** > **DiameterShPeerStats** tag defined in the XSDs.

The following is an example of a request for all policy servers within the system:

```

<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2013-04-25T12:00:00</StartTime>
  <EndTime>2013-04-25T13:00:00</EndTime>
  <DiameterShPeerStats>
    <Name>server1</Name>
  </DiameterShPeerStats>
</QueryOmStats>

```

Response

The response to this request follows the **Statistics** > **DiameterShPeerStats** tag defined in the XSDs.

The following is an example XML response to a DiameterShPeerStats tag request:

```

<?xml version="1.0" encoding="UTF-8" ?>
<Statistics>
  <DiameterShPeerStats>
    <Sample>
      <StartTime>2013-04-30T15:00:00Z</StartTime>
      <EndTime>2013-04-30T15:15:00Z</EndTime>
      <PolicyServer>Cfg4-S2-MPE-1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>server1</Name>
      <NeId></NeId>
      <NetworkElementType></NetworkElementType>
      <NetworkElementSubType></NetworkElementSubType>
      <ConnectTime>Fri Apr 26 15:46:17 EDT 2013</ConnectTime>
      <DisconnectTime>N/A</DisconnectTime>
      <ConnectAddress>10.240.54.133</ConnectAddress>
      <ConnectPort>3868</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <MessagesInCount>75439</MessagesInCount>
      <MessagesOutCount>75440</MessagesOutCount>
      <MessagesErrorInCount>75439</MessagesErrorInCount>
    </Sample>
  </DiameterShPeerStats>
</Statistics>

```

```

    <MessagesErrorOutCount>0</MessagesErrorOutCount>
    <UDRMessagesReceivedCount>0</UDRMessagesReceivedCount>
    <UDRMessagesSentCount>75440</UDRMessagesSentCount>
    <UDRMessagesTimeoutCount>0</UDRMessagesTimeoutCount>
    <UDASuccessMessagesReceivedCount>0</UDASuccessMessagesReceivedCount>
    <UDASuccessMessagesSentCount>0</UDASuccessMessagesSentCount>
    <UDAFailureMessagesReceivedCount>75439</UDAFailureMessagesReceivedCount>

    <UDAFailureMessagesSentCount>0</UDAFailureMessagesSentCount>
    <PNRMessagesReceivedCount>0</PNRMessagesReceivedCount>
    <PNRMessagesSentCount>0</PNRMessagesSentCount>
    <PNASuccessMessagesReceivedCount>0</PNASuccessMessagesReceivedCount>
    <PNASuccessMessagesSentCount>0</PNASuccessMessagesSentCount>
    <PNAFailureMessagesReceivedCount>0</PNAFailureMessagesReceivedCount>
    <PNAFailureMessagesSentCount>0</PNAFailureMessagesSentCount>
    <PURMessagesReceivedCount>0</PURMessagesReceivedCount>
    <PURMessagesSentCount>0</PURMessagesSentCount>
    <PURMessagesTimeoutCount>0</PURMessagesTimeoutCount>
    <PUASuccessMessagesReceivedCount>0</PUASuccessMessagesReceivedCount>
    <PUASuccessMessagesSentCount>0</PUASuccessMessagesSentCount>
    <PUAFailureMessagesReceivedCount>0</PUAFailureMessagesReceivedCount>
    <PUAFailureMessagesSentCount>0</PUAFailureMessagesSentCount>
    <SNRMessagesReceivedCount>0</SNRMessagesReceivedCount>
    <SNRMessagesSentCount>0</SNRMessagesSentCount>
    <SNRMessagesTimeoutCount>0</SNRMessagesTimeoutCount>
    <SNASuccessMessagesReceivedCount>0</SNASuccessMessagesReceivedCount>
    <SNASuccessMessagesSentCount>0</SNASuccessMessagesSentCount>
    <SNAFailureMessagesReceivedCount>0</SNAFailureMessagesReceivedCount>
    <SNAFailureMessagesSentCount>0</SNAFailureMessagesSentCount>
    <ActiveSessionsCount>0</ActiveSessionsCount>
    <MaximumActiveSessionsCount>2</MaximumActiveSessionsCount>
  </Sample>
</DiameterShPeerStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Policy Charging Enforcement Function Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraPcefStats tag.

Request

This request follows the **QueryOmStats** > **DiameterMraPcefStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2010-04-02T00:01:00</StartTime>
    <EndTime>2011-05-21T23:59:00</EndTime>
    <DiameterMraPcefStats>
      <MRA>mra156</MRA>
    </DiameterMraPcefStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraPcefStats** tag defined in the XSDs. For example:

```
<Statistics>
  <DiameterMraPcefStats>
    <Sample>
      <StartTime>2010-06-04T05:43:15Z</StartTime>
      <EndTime>2010-06-04T05:43:32Z</EndTime>
      <MRA>mra156</MRA>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
      <ASRMessagesSentCount>0</ASRMessagesSentCount>
      <ASASuccessMessagesReceivedCount>0</ASASuccessMessagesReceivedCount>
      <ASASuccessMessagesSentCount>0</ASASuccessMessagesSentCount>
      <ASAFailureMessagesReceivedCount>0</ASAFailureMessagesReceivedCount>
      <ASAFailureMessagesSentCount>0</ASAFailureMessagesSentCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
      <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
      <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
      <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <PeerOkayCount>0</PeerOkayCount>
      <PeerDownCount>0</PeerDownCount>
      <PeerSuspectCount>0</PeerSuspectCount>
      <PeerReopenCount>0</PeerReopenCount>
    </Sample>
  </DiameterMraPcefStats>
</Statistics>
```

Diameter Multi-Protocol Routing Agent (MRA) Policy Charging Enforcement Function Peer Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraPcefPeerStats tag.

Request

This request follows the **QueryOmStats > DiameterMraPcefPeerStats** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
```

```

- <XmlInterfaceRequest>
- <QueryOmStats>
  <StartTime>2013-04-25T00:01:00</StartTime>
  <EndTime>2013-04-25T23:59:00</EndTime>
  - <DiameterMraPcefPeerStats>
    <Name>mra157</Name>
  </DiameterMraPcefPeerStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraPcefPeerStats** tag defined in the XSDs. For example:

```

- <Statistics>
- <DiameterMraPcefPeerStats>
  - <Sample>
    <StartTime>2013-04-25T16:45:00Z</StartTime>
    <EndTime>2013-04-25T17:00:00Z</EndTime>
    <MRA>MRA</MRA>
    <IsComplete>true</IsComplete>
    <Name>mpe.name.com</Name>
    <NeId></NeId>
    <NetworkElementType></NetworkElementType>
    <NetworkElementSubType></NetworkElementSubType>
    <ConnectTime>Fri Jan 25 22:58:27 EST 2013</ConnectTime>
    <DisconnectTime>N/A</DisconnectTime>
    <ConnectAddress>10.15.23.95</ConnectAddress>
    <ConnectPort>3868</ConnectPort>
    <ConnectType>TCP</ConnectType>
    <MessagesInCount>0</MessagesInCount>
    <MessagesOutCount>0</MessagesOutCount>
    <MessagesErrorInCount>0</MessagesErrorInCount>
    <MessagesErrorOutCount>0</MessagesErrorOutCount>
    <RAAMessagesReceivedCount>0</RAAMessagesReceivedCount>
    <RAAMessagesSentCount>0</RAAMessagesSentCount>
    <RAAMessagesTimeoutCount>0</RAAMessagesTimeoutCount>
    <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
    <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
    <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
    <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
    <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
    <CCRMessagesSentCount>0</CCRMessagesSentCount>
    <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
    <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
    <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
    <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
    <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
    <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
    <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
    <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
    <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
    <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
    <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
    <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
    <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
    <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
    <CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
    <CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
    <CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>

```

```

<CAIFailureMessagesSentCount>0</CAIFailureMessagesSentCount>
<CAUSuccessMessagesReceivedCount>0</CAUSuccessMessagesReceivedCount>
<CAUSuccessMessagesSentCount>0</CAUSuccessMessagesSentCount>
<CAUFailureMessagesReceivedCount>0</CAUFailureMessagesReceivedCount>
<CAUFailureMessagesSentCount>0</CAUFailureMessagesSentCount>
<CATSuccessMessagesReceivedCount>0</CATSuccessMessagesReceivedCount>
<CATSuccessMessagesSentCount>0</CATSuccessMessagesSentCount>
<CATFailureMessagesReceivedCount>0</CATFailureMessagesReceivedCount>
<CATFailureMessagesSentCount>0</CATFailureMessagesSentCount>
</Sample>
</DiameterMrpcefPeerStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application (DRMA) Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMrpDrmaStats tag.

Request

This request follows the **QueryOmStats** > **DiameterMrpDrmaStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
- <XmlInterfaceRequest>
- <QueryOmStats>
  <StartTime>2010-04-02T00:01:00</StartTime>
  <EndTime>2011-05-21T23:59:00</EndTime>
- <DiameterMrpDrmaStats>
  <MRA>mra156</MRA>
</DiameterMrpDrmaStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics** > **DiameterMrpDrmaStats** tag defined in the XSDs. For example:

```

- <Statistics>
- <DiameterMrpDrmaStats>
- <Sample>
  <StartTime>2010-06-04T05:43:15Z</StartTime>
  <EndTime>2010-06-04T05:43:32Z</EndTime>
  <MRA>mra156</MRA>
  <IsComplete>true</IsComplete>
  <CurrentConnectionsCount>0</CurrentConnectionsCount>
  <MessagesInCount>0</MessagesInCount>
  <MessagesOutCount>0</MessagesOutCount>
  <DBRMessagesReceivedCount>0</DBRMessagesReceivedCount>
  <DBRMessagesSentCount>0</DBRMessagesSentCount>
  <DBASuccessMessagesReceivedCount>0</DBASuccessMessagesReceivedCount>
  <DBASuccessMessagesSentCount>0</DBASuccessMessagesSentCount>
  <DBAFailureMessagesReceivedCount>0</DBAFailureMessagesReceivedCount>
  <DBAFailureMessagesSentCount>0</DBAFailureMessagesSentCount>

```

```

    <BindingFoundSentCount>0</BindingFoundSentCount>
    <BindingFoundRecvCount>0</BindingFoundRecvCount>
    <BindingNotFoundSentCount>0</BindingNotFoundSentCount>
    <BindingNotFoundRecvCount>0</BindingNotFoundRecvCount>
    <PcrfDownSentCount>0</PcrfDownSentCount>
    <PcrfDownReceivedCount>0</PcrfDownReceivedCount>
    <AllPcrfsDownSentCount>0</AllPcrfsDownSentCount>
    <AllPcrfsDownRecvCount>0</AllPcrfsDownRecvCount>
    <PeerOkayCount>0</PeerOkayCount>
    <PeerDownCount>0</PeerDownCount>
    <PeerSuspectCount>0</PeerSuspectCount>
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterMraDrmaStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application (DRMA) over SCTP Response Statistics

The statistics field can be set to SCTP with the ability to support multiple IP addresses.

The following example shows the SCTP response defined in the XSDs for the DiameterMraDrmaPeerStats tag. This diameter connection is set to SCTP.

Response

The response to this request follows the **Statistics > DiameterMraDrmaPeerStats** tag defined in the XSDs for a SCTP. For example:

```

<Statistics>
  <DiameterMraDrmaPeerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <MRA>MRA</MRA>
      <IsComplete>true</IsComplete>
      <Name>NetworkElementName</Name>
      <ConnectTime>2001-12-31T12:00:00</ConnectTime>
      <DisconnectTime>2001-12-31T12:00:00</DisconnectTime>
      <ConnectType>SCTP</ConnectType>
      <ConnectAddress>10.15.25.110:3868, 10.15.25.119:3868</ConnectAddress>
      <ConnectPort>N/A</ConnectPort>
    </Sample>
  </DiameterMraDrmaPeerStats>
</Statistics>

```

The following example shows the TCP response defined in the XSDs for the DiameterMraDrmaPeerStats tag. This diameter connection is set to TCP.

Response

The response to this request follows the **Statistics > DiameterMraDrmaPeerStats** tag defined in the XSDs for a TCP. For example:

```

<Statistics>
  <DiameterMraDrmaPeerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
    </Sample>
  </DiameterMraDrmaPeerStats>
</Statistics>

```

```

<EndTime>2001-12-31T12:15:00</EndTime>
<MRA>MRA</MRA>
<IsComplete>true</IsComplete>
<Name>NetworkElementName</Name>
<ConnectTime>2001-12-31T12:00:00</ConnectTime>
<DisconnectTime>2001-12-31T12:00:00</DisconnectTime>
<ConnectType>N/A</ConnectType>
<ConnectAddress>10.15.25.110</ConnectAddress>
<ConnectPort>3868</ConnectPort>

```

Diameter Multi-Protocol Routing Agent (MRA) Distributed Routing and Management Application Peer Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraDrmaPeerStats tag.

Request

This request follows the **QueryOmStats > DiameterMraTdfPeerStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
- <XmlInterfaceRequest>
  - <QueryOmStats>
    <StartTime>2010-04-02T00:01:00</StartTime>
    <EndTime>2011-05-21T23:59:00</EndTime>
    - <DiameterMraDrmaPeerStats>
      <Name>mra157</Name>
    </DiameterMraDrmaPeerStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraTdfPeerStats** tag defined in the XSDs. For example:

```

<Statistics>
<DiameterMraTdfPeerStats>
  <Sample>
    <StartTime>2012-05-28T09:30:00Z</StartTime>
    <EndTime>2012-05-28T09:45:00Z</EndTime>
    <MRA>kli-66-mra</MRA>
    <IsComplete>true</IsComplete>
    <Name>kli-63-mpe</Name>
    <NeId/>
    <NetworkElementType/>
    <NetworkElementSubType/>
    <ConnectTime>Fri May 25 05:44:36 EDT 2012</ConnectTime>
    <DisconnectTime>N/A</DisconnectTime>
    <ConnectAddress>10.60.25.64:3868,10.60.25.65:3868</ConnectAddress>
    <ConnectPort>0</ConnectPort>
    <ConnectType/>
    <MessagesInCount>0</MessagesInCount>
    <MessagesOutCount>0</MessagesOutCount>
  </Sample>
</DiameterMraTdfPeerStats>
</Statistics>

```

```

<MessagesErrorInCount>0</MessagesErrorInCount>
<MessagesErrorOutCount>0</MessagesErrorOutCount>
<TSRMessagesReceivedCount>0</TSRMessagesReceivedCount>
<TSRMessagesSentCount>0</TSRMessagesSentCount>
<TSRMessagesTimeoutCount>0</TSRMessagesTimeoutCount>
<TSA SuccessMessagesReceivedCount>0</TSA SuccessMessagesReceivedCount>
<TSA SuccessMessagesSentCount>0</TSA SuccessMessagesSentCount>
<TSA FailureMessagesReceivedCount>0</TSA FailureMessagesReceivedCount>
<TSA FailureMessagesSentCount>0</TSA FailureMessagesSentCount>
<RARMessagesReceivedCount>0</RARMessagesReceivedCount>
<RARMessagesSentCount>0</RARMessagesSentCount>
<RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
<CCRMessagesSentCount>0</CCRMessagesSentCount>
<CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
<CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
<CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
<CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
<CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
<CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
<CCRIMessagesSentCount>0</CCRIMessagesSentCount>
<CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
<CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
<CCRUMessagesSentCount>0</CCRUMessagesSentCount>
<CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
<CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
<CCRTMessagesSentCount>0</CCRTMessagesSentCount>
<CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
<CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
<CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
<CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
<CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
<CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
<CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
<CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
<CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
<CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
<CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
<CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
<CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
</Sample>
</DiameterMraDraStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Diameter Routing Agent (DRA) Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraDraStats tag.

Request

This request follows the **QueryOmStats > DiameterMraDraStats** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
```

```

- <XmlInterfaceRequest>
- <QueryOmStats>
  <StartTime>2010-04-02T00:01:00</StartTime>
  <EndTime>2011-05-21T23:59:00</EndTime>
- <DiameterMraDraStats>
  <MRA>mra156</MRA>
  <MRA>mra106</MRA>
</DiameterMraDraStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraDraStats** tag defined in the XSDs. For example:

```

- <Statistics>
- <DiameterMraDraStats>
- <Sample>
  <StartTime>2010-06-04T05:43:15Z</StartTime>
  <EndTime>2010-06-04T05:43:32Z</EndTime>
  <MRA>mra106</MRA>
  <IsComplete>true</IsComplete>
  <ActiveBindingsCount>0</ActiveBindingsCount>
  <MaximumActiveBindingsCount>0</MaximumActiveBindingsCount>
</Sample>
</DiameterMraDraStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Application Function (AF) Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraAfStats tag.

Request

This request follows the **QueryOmStats > DiameterMraAfStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
- <XmlInterfaceRequest>
- <QueryOmStats>
  <StartTime>2010-04-02T00:01:00</StartTime>
  <EndTime>2011-05-21T23:59:00</EndTime>
- <DiameterMraAfStats>
  <MRA>mra156</MRA>
</DiameterMraAfStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraAfStats** tag defined in the XSDs. For example:

```
- <Statistics>
- <DiameterMraAfStats>
- <Sample>
  <StartTime>2010-06-04T05:43:15Z</StartTime>
  <EndTime>2010-06-04T05:43:32Z</EndTime>
  <MRA>mra156</MRA>
  <IsComplete>true</IsComplete>
  <PendingConnectionsCount>0</PendingConnectionsCount>
  <CurrentConnectionsCount>0</CurrentConnectionsCount>
  <MessagesInCount>0</MessagesInCount>
  <MessagesOutCount>0</MessagesOutCount>
  <ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
  <ASRMessagesSentCount>0</ASRMessagesSentCount>
  <ASRHoSendCount>0</ASRHoSendCount>
  <ASRHoReceivedCount>0</ASRHoReceivedCount>
  <ASRHoTimeoutCount>0</ASRHoTimeoutCount>
  <RARHoSendCount>0</RARHoSendCount>
  <RARHoReceivedCount>0</RARHoReceivedCount>
  <RARHoTimeoutCount>0</RARHoTimeoutCount>
  <ASASuccessMessagesReceivedCount>0</ASASuccessMessagesReceivedCount>
  <ASASuccessMessagesSentCount>0</ASASuccessMessagesSentCount>
  <ASAFailureMessagesReceivedCount>0</ASAFailureMessagesReceivedCount>
  <ASAFailureMessagesSentCount>0</ASAFailureMessagesSentCount>
  <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
  <RARMessagesSentCount>0</RARMessagesSentCount>
  <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
  <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
  <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
  <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
  <STRMessagesReceivedCount>0</STRMessagesReceivedCount>
  <STRMessagesSentCount>0</STRMessagesSentCount>
  <STASuccessMessagesReceivedCount>0</STASuccessMessagesReceivedCount>
  <STASuccessMessagesSentCount>0</STASuccessMessagesSentCount>
  <STAFailureMessagesReceivedCount>0</STAFailureMessagesReceivedCount>
  <STAFailureMessagesSentCount>0</STAFailureMessagesSentCount>
  <AARMessagesReceivedCount>0</AARMessagesReceivedCount>
  <AARMessagesSentCount>0</AARMessagesSentCount>
  <AAASuccessMessagesReceivedCount>0</AAASuccessMessagesReceivedCount>
  <AAASuccessMessagesSentCount>0</AAASuccessMessagesSentCount>
  <AAAFailureMessagesReceivedCount>0</AAAFailureMessagesReceivedCount>
  <AAAFailureMessagesSentCount>0</AAAFailureMessagesSentCount>
  <PeerOkayCount>0</PeerOkayCount>
  <PeerDownCount>0</PeerDownCount>
  <PeerSuspectCount>0</PeerSuspectCount>
  <PeerReopenCount>0</PeerReopenCount>
</Sample>
</DiameterMraAfStats>
</Statistics>
```

Diameter Multi-Protocol Routing Agent (MRA) Application Function (AF) Peer Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraAfPeerStats tag.

Request

This request follows the **QueryOmStats > DiameterMraAfPeerStats** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
- <XmlInterfaceRequest>
- <QueryOmStats>
  <StartTime>2010-04-02T00:01:00</StartTime>
  <EndTime>2011-05-21T23:59:00</EndTime>
- <DiameterMraAfPeerStats>
  <Name>mra157</Name>
</DiameterMraAfPeerStats>
</QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterMraAfPeerStats** tag defined in the XSDs. For example:

```
- <Statistics>
- <DiameterMraAfPeerStats>
- <Sample>
  <StartTime>2010-05-31T07:56:55Z</StartTime>
  <EndTime>2010-05-31T08:00:00Z</EndTime>
  <MRA>mra156</MRA>
  <IsComplete>true</IsComplete>
  <Name>oracle</Name>
  <NeId />
  <NetworkElementType />
  <NetworkElementSubType />
  <ConnectTime>Mon May 31 15:54:23 CST 2010</ConnectTime>
  <DisconnectTime>N/A</DisconnectTime>
  <ConnectAddress>192.168.200.106</ConnectAddress>
  <ConnectPort>56164</ConnectPort>
  <MessagesInCount>0</MessagesInCount>
  <MessagesOutCount>0</MessagesOutCount>
  <MessagesErrorInCount>0</MessagesErrorInCount>
  <MessagesErrorOutCount>0</MessagesErrorOutCount>
  <ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
  <ASRMessagesSentCount>0</ASRMessagesSentCount>
  <ASASuccessMessagesReceivedCount>0</ASASuccessMessagesReceivedCount>
  <ASASuccessMessagesSentCount>0</ASASuccessMessagesSentCount>
  <ASAFailureMessagesReceivedCount>0</ASAFailureMessagesReceivedCount>
  <ASAFailureMessagesSentCount>0</ASAFailureMessagesSentCount>
  <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
  <RARMessagesSentCount>0</RARMessagesSentCount>
  <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
  <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
  <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
  <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
  <STRMessagesReceivedCount>0</STRMessagesReceivedCount>
  <STRMessagesSentCount>0</STRMessagesSentCount>
  <STASuccessMessagesReceivedCount>0</STASuccessMessagesReceivedCount>
  <STASuccessMessagesSentCount>0</STASuccessMessagesSentCount>
  <STAFailureMessagesReceivedCount>0</STAFailureMessagesReceivedCount>
  <STAFailureMessagesSentCount>0</STAFailureMessagesSentCount>
  <AARMessagesReceivedCount>0</AARMessagesReceivedCount>
  <AARMessagesSentCount>0</AARMessagesSentCount>
  <AAASuccessMessagesReceivedCount>0</AAASuccessMessagesReceivedCount>
  <AAASuccessMessagesSentCount>0</AAASuccessMessagesSentCount>
  <AAAFailureMessagesReceivedCount>0</AAAFailureMessagesReceivedCount>
  <AAAFailureMessagesSentCount>0</AAAFailureMessagesSentCount>
```

```

    </Sample>
  </DiameterMraAfPeerStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Bearer Binding and Event Reporting Function (Bberf) Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraBberfStats tag.

Request

This request follows the **QueryOmStats > DiameterMraBberfStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
- <XmlInterfaceRequest>
- <QueryOmStats>
  <StartTime>2010-04-02T00:01:00</StartTime>
  <EndTime>2011-05-21T23:59:00</EndTime>
- <DiameterMraBberfStats>
  <MRA>mra156</MRA>
</DiameterMraBberfStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraBberfStats** tag defined in the XSDs. For example:

```

- <Statistics>
- <DiameterMraBberfStats>
- <Sample>
  <StartTime>2010-06-04T05:43:15Z</StartTime>
  <EndTime>2010-06-04T05:43:32Z</EndTime>
  <MRA>mra156</MRA>
  <IsComplete>true</IsComplete>
  <CurrentConnectionsCount>0</CurrentConnectionsCount>
  <MessagesInCount>0</MessagesInCount>
  <MessagesOutCount>0</MessagesOutCount>
  <MessagesErrorInCount>0</MessagesErrorInCount>
  <MessagesErrorOutCount>0</MessagesErrorOutCount>
  <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
  <RARMessagesSentCount>0</RARMessagesSentCount>
  <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
  <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
  <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
  <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
  <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
  <CCRMessagesSentCount>0</CCRMessagesSentCount>
  <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
  <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
  <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
  <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
  <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>

```

```

    <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
    <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
    <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
    <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
    <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
    <PeerOkayCount>0</PeerOkayCount>
    <PeerDownCount>0</PeerDownCount>
    <PeerSuspectCount>0</PeerSuspectCount>
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterMraBberfStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF) Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraTdfStats tag.

Request

This request follows the **QueryOmStats** > **DiameterMraTdfStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2010-04-02T00:01:00</StartTime>
    <EndTime>2011-05-21T23:59:00</EndTime>
    <DiameterMraTdfStats>
      <MRA>mra156</MRA>
    </DiameterMraTdfStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics** > **DiameterMraTdfStats** tag defined in the XSDs. For example:

```

<Statistics>
  <DiameterMraTdfStats>
    <Sample>
      <StartTime>2012-05-28T09:30:00Z</StartTime>
      <EndTime>2012-05-28T09:45:00Z</EndTime>
      <MRA>kli-66-mra</MRA>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>1</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <TSRMessagesReceivedCount>0</TSRMessagesReceivedCount>
      <TSRMessagesSentCount>0</TSRMessagesSentCount>
      <TSRMessagesTimeoutCount>0</TSRMessagesTimeoutCount>
      <TSASuccessMessagesReceivedCount>0</TSASuccessMessagesReceivedCount>
      <TSASuccessMessagesSentCount>0</TSASuccessMessagesSentCount>
      <TSAFailureMessagesReceivedCount>0</TSAFailureMessagesReceivedCount>
      <TSAFailureMessagesSentCount>0</TSAFailureMessagesSentCount>
    </Sample>
  </DiameterMraTdfStats>
</Statistics>

```

```

<RARMessagesReceivedCount>0</RARMessagesReceivedCount>
<RARMessagesSentCount>0</RARMessagesSentCount>
<RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
<CCRMessagesSentCount>0</CCRMessagesSentCount>
<CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
<CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
<CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
<CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
<CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
<CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
<CCRIMessagesSentCount>0</CCRIMessagesSentCount>
<CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
<CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
<CCRUMessagesSentCount>0</CCRUMessagesSentCount>
<CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
<CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
<CCRTMessagesSentCount>0</CCRTMessagesSentCount>
<CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
<CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
<CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
<CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
<CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
<CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
<CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
<CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
<CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
<CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
<CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
<CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
<CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
<PeerOkayCount>1</PeerOkayCount>
<PeerDownCount>0</PeerDownCount>
<PeerSuspectCount>0</PeerSuspectCount>
<PeerReopenCount>0</PeerReopenCount>
</Sample>
</DiameterMraTdfStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF) Peer Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterMraTdfPeerStats tag.

Request

This request follows the **QueryOmStats > DiameterMraTdfPeerStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
-<XmlInterfaceRequest>
  -<QueryOmStats> <StartTime>2010-04-02T00:01:00</StartTime>
    <EndTime>2011-05-21T23:59:00</EndTime>

```

```

- <DiameterMraTdfPeerStats>
  <Name>mra157</Name>
</DiameterMraTdfPeerStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraTdfPeerStats** tag defined in the XSDs. For example:

```

<Statistics>
  <DiameterMraTdfStats>
    <Sample>
      <StartTime>2012-05-28T09:30:00Z</StartTime>
      <EndTime>2012-05-28T09:45:00Z</EndTime>
      <MRA>kli-66-mra</MRA>
      <IsComplete>true</IsComplete>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>1</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <TSRMessagesReceivedCount>0</TSRMessagesReceivedCount>
      <TSRMessagesSentCount>0</TSRMessagesSentCount>
      <TSRMessagesTimeoutCount>0</TSRMessagesTimeoutCount>
      <TSASuccessMessagesReceivedCount>0</TSASuccessMessagesReceivedCount>
      <TSASuccessMessagesSentCount>0</TSASuccessMessagesSentCount>
      <TSAFailureMessagesReceivedCount>0</TSAFailureMessagesReceivedCount>
      <TSAFailureMessagesSentCount>0</TSAFailureMessagesSentCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
      <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
      <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
      <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
      <CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
      <CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
      <CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
      <CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
      <CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
      <CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
      <CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
      <CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
      <CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>

```

```

    <CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
    <CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
    <CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
    <PeerOkayCount>1</PeerOkayCount>
    <PeerDownCount>0</PeerDownCount>
    <PeerSuspectCount>0</PeerSuspectCount>
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterMraTdfStats>
</Statistics>

```

Diameter Multi-Protocol Routing Agent (MRA) Traffic Detection Function (TDF) over SCTP Statistics

The statistics field can be set to SCTP with the ability to support multiple IP addresses.

The following examples show the SCTP response defined in the XSDs for the DiameterMraDrmaPeerStats tag.

Response

The response to this request follows the **Statistics > DiameterMraTdfPeerStats** tag defined in the XSDs. For example:

The following is an example of this request.

```

<Statistics> <DiameterMraTdfPeerStats>
  <Sample> <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime> <MRA>MRA</MRA>
  <Name>NetworkElementName</Name>
  <ConnectTime>2001-12-31T12:00:00</ConnectTime>
  <DisconnectTime>2001-12-31T12:00:00</DisconnectTime>
  <ConnectType>SCTP</ConnectType>
  <ConnectAddress>10.15.25.110:3868, 10.15.25.119:3868</ConnectAddress>
  <ConnectPort>N/A</ConnectPort>

```

The following example show the TCP response defined in the XSDs for the DiameterMraTdfPeerStats tag. This diameter connection is set to TCP.

Response

The response to this request follows the **Statistics > DiameterMraTdfPeerStats** tag defined in the XSDs. For example:

```

<Statistics>
  <DiameterMraTdfPeerStats> <Sample>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <MRA>MRA</MRA>
    <IsComplete>true</IsComplete>
    <Name>NetworkElementName</Name>
    <ConnectTime>2001-12-31T12:00:00</ConnectTime>
    <DisconnectTime>2001-12-31T12:00:00</DisconnectTime>
    <ConnectType>TCP</ConnectType>
    <ConnectAddress>10.15.25.110</ConnectAddress>
    <ConnectPort>3868</ConnectPort>

```

KPI Statistics

The following examples show the request and response that are defined in the XSDs for the KpiStats tag.

Request

This request follows the **QueryOmStats > KpiStats** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <KpiStats>
  </KpiStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > KpiStats** tag defined in the XSDs. For example:

```
<?xml version="1.0" encoding="UTF-8" ?>
<Statistics>
  <KpiStats>
    <Sample>
      <StartTime>2013-06-27T07:45:00Z</StartTime>
      <EndTime>2013-06-27T07:55:01Z</EndTime>
      <PolicyServer>mpe57</PolicyServer>
      <IsComplete>>false</IsComplete>
      <TransactionStartCount>0</TransactionStartCount>
      <TransactionEndCount>0</TransactionEndCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <CurrentTransactionsPerSecond>0</CurrentTransactionsPerSecond>
      <MaxTransactionsPerSecond>0</MaxTransactionsPerSecond>
      <CurrentTPSPercentageOfCapacity>0</CurrentTPSPercentageOfCapacity>
      <MaxTPSPercentageOfCapacity>0</MaxTPSPercentageOfCapacity>
      <CurrentRXTransactionsPerSecond>0</CurrentRXTransactionsPerSecond>
      <CurrentPCMMTransactionsPerSecond>0</CurrentPCMMTransactionsPerSecond>
      <MaxPCMMTransactionsPerSecond>0</MaxPCMMTransactionsPerSecond>
      <CurrentPCMMtpsPercentageOfCapacity>0</CurrentPCMMtpsPercentageOfCapacity>
      <MaxPCMMtpsPercentageOfCapacity>0</MaxPCMMtpsPercentageOfCapacity>
      <MaxRXTransactionsPerSecond>0</MaxRXTransactionsPerSecond>
      <CurrentRXtpsPercentageOfCapacity>0</CurrentRXtpsPercentageOfCapacity>
      <MaxRXtpsPercentageOfCapacity>0</MaxRXtpsPercentageOfCapacity>
      <LoadSheddingStatus>0</LoadSheddingStatus>
      <LoadSheddingEfficiency>0</LoadSheddingEfficiency>
      <LoadSheddingDistressCount>0</LoadSheddingDistressCount>
      <CurrentSessionCount>0</CurrentSessionCount>
      <MaxSessionCount>0</MaxSessionCount>
      <CurrentSessionPercentageOfCapacity>0</CurrentSessionPercentageOfCapacity>
      <MaxSessionPercentageOfCapacity>0</MaxSessionPercentageOfCapacity>
      <CurrentMPEConnectionCount>0</CurrentMPEConnectionCount>
```

```

<ConfiguredMPEConnectionCount>0</ConfiguredMPEConnectionCount>
<CurrentConnectedNECount>0</CurrentConnectedNECount>
<ConfiguredNECount>1</ConfiguredNECount>
<CurrentProtocolErrorSentCount>0</CurrentProtocolErrorSentCount>
<CurrentProtocolErrorReceivedCount>0</CurrentProtocolErrorReceivedCount>
<ServerACPUUtilizationPercentage>14</ServerACPUUtilizationPercentage>
<ServerAMemoryUtilizationPercentage>78</ServerAMemoryUtilizationPercentage>

<ServerADiskUtilizationPercentage>2</ServerADiskUtilizationPercentage>
<ServerABladeFailureCount>6</ServerABladeFailureCount>
<ServerAUpTimeMillis>16208000</ServerAUpTimeMillis>
<ServerABladeStatus>12</ServerABladeStatus>
<ServerBCPUUtilizationPercentage>0</ServerBCPUUtilizationPercentage>
<ServerBMemoryUtilizationPercentage>0</ServerBMemoryUtilizationPercentage>

<ServerBDiskUtilizationPercentage>0</ServerBDiskUtilizationPercentage>
<ServerBBladeFailureCount>0</ServerBBladeFailureCount>
<ServerBUpTimeMillis>0</ServerBUpTimeMillis>
<ServerBBladeStatus>0</ServerBBladeStatus>
<ServerCCPUUtilizationPercentage>0</ServerCCPUUtilizationPercentage>
<ServerCMemoryUtilizationPercentage>0</ServerCMemoryUtilizationPercentage>

<ServerCDiskUtilizationPercentage>0</ServerCDiskUtilizationPercentage>
<ServerCBladeFailureCount>0</ServerCBladeFailureCount>
<ServerCUpTimeMillis>0</ServerCUpTimeMillis>
<ServerCBladeStatus>0</ServerCBladeStatus>
</Sample>
</KpiStats>
</Statistics>

```

Protocol Error Statistics

The following examples show the request and response that are defined in the XSDs for the ProtocolErrorStats tag.

Request

This request follows the **QueryOmStats** > **ProtocolErrorStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats DeltaCount="false">
    <StartTime>2010-04-02T00:01:00</StartTime>
    <EndTime>2011-05-31T23:59:00</EndTime>
    <ProtocolErrorStats>
      <PolicyServer>rc178</PolicyServer>
    </ProtocolErrorStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics** > **ProtocolErrorStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- **DiameterCommandUnsupported** - The request contained a command code that the receiver did not recognize or support.
- **DiameterUnableToDeliver** - This error is given when the diameter node cannot deliver the message to the destination, either because no host within the realm that supports the required application was available to process the request, or because Destination-Host AVP was given without the associated Destination-Realm AVP.
- **DiameterRealmNotServed** - The intended realm of the request is not recognized.
- **DiameterTooBusy** - The diameter node has too much traffic. When returned, a diameter node attempts to send the message to an alternate peer.
- **DiameterLoopDetected** - An agent detected a loop while trying to get the message to the intended recipient. The message may be sent to an alternate peer if available.
- **DiameterRedirectIndication** - A redirect agent has determined that the request could not be satisfied locally and the initiator of the request should direct the request directly to the server, whose contact information has been added to the response. When set, the Redirect-Host AVP must be present.
- **DiameterApplicationUnsupported** - A request was sent for an application that is not supported.
- **DiameterInvalidHdrBits** - A request was received whose bits in the diameter header were either set to an invalid combination, or to a value that is inconsistent with the command code's definition.
- **DiameterInvalidAvpBits** - A request was received that included an AVP whose flag bits are set to an unrecognized value, or that is inconsistent with the AVP's definition.
- **DiameterUnknownPeer** - A CER was received from an unknown peer.
- **DiameterAuthenticationRejected** - The authentication process for the user failed, most likely due to an invalid password used by the user. The user is then prompted for a new password.
- **DiameterOutOfSpace** - A diameter node received the accounting request but was unable to commit it to stable storage due to a temporary lack of space.
- **ElectionLost** - The peer has lost the election process and has disconnected the transport connection.
- **DiameterEndUserServiceDenied** - The credit-control server denied the service request due to service restrictions. If the CCR contained used-service-units, they are deducted, if possible.
- **DiameterCreditControlNotApplicable** - The credit-control server determined that the service can be granted to the end user, but that no further credit control is needed for the service (for example, the service is free of charge).
- **DiameterCreditLimitReached** - The credit-control server denied the service request because the end user's account could not cover the requested service. If the CCR contained used-service-units, they are deducted, if possible.
- **DiameterAvpUnsupported** - The peer received a message that contained an AVP that is not recognized or supported and was marked with the Mandatory bit.
- **DiameterUnknownSessionId** - The request contained an unknown Session-Id.
- **DiameterAuthorizationRejected** - A request was received for which the user could not be authorized. This error could occur if the requested service is not permitted to the user.
- **DiameterInvalidAvpValue** - The request contained an AVP with an invalid value in its data portion.
- **DiameterMissingAvp** - The request did not contain an AVP that is required by the command code definition. If this value is sent in the Result-Code AVP, a Failed-AVP AVP is included in the message.
- **DiameterResourcesExceeded** - A request was received that cannot be authorized because the user has already expended its allowed resources.
- **DiameterContradictingAvps** - The Home Diameter server has detected AVPs in the request that contradict each other, and is not willing to provide service to the user.
- **DiameterAvpNotAllowed** - A message was received with an AVP that cannot be present.
- **DiameterAvpOccursTooManyTimes** - A message was received that included an AVP that appeared more often than permitted.

- DiameterNoCommonApplication - This error is returned when a CER message is received, and there are no common applications supported between the peers.
- DiameterUnsupportedVersion - This error is returned when a request was received with an unsupported version number.
- DiameterUnableToComply - This error is returned when a request is rejected for unspecified reasons.
- DiameterInvalidBitInHeader - This error is returned when an unrecognized bit in the diameter header is set to one (1).
- DiameterInvalidAvpLength - The request contained an AVP with an invalid length.
- DiameterInvalidMessageLength - This error is returned when a request is received with an invalid message length.
- DiameterInvalidAvpBitCombo - The request contained an AVP with an invalid AVP Flags value.
- DiameterNoCommonSecurity - This error is returned when a CER message is received, but there are no common security mechanisms supported between the peers.
- DiameterUserUnknown - The specified end user is unknown in the credit-control server.
- DiameterRatingFailed - This error code is used to inform the credit-control client that the credit-control server cannot rate the service request due to insufficient rating input, an incorrect AVP combination, or an AVP or AVP value that is not recognized or supported in the rating.
- DiameterErrorInitialParameters - The initial parameters contain an error.
- RadiusSessionContextRemoved - The residual session context has been removed.
- RadiusInvalidEapPacket - An invalid EAP Packet was detected.
- RadiusUnsupportedAttribute - The request contained an unsupported attribute.
- RadiusMissingAttribute - A request was missing a required attribute.
- RadiusNasIdMismatch - The system was unable to match the received NAS to the stored information.
- RadiusInvalidRequest - The system has received an invalid request.
- RadiusUnsupportedService - The requested service is not supported.
- RadiusUnsupportedExtension - The requested extension is not supported.
- RadiusInvalidAttributeValue - The request contains an invalid attribute value.
- RadiusAdministrativelyProhibited - The request is administratively prohibited.
- RadiusRequestNotRoutable - The request cannot be routed.
- RadiusSessionNotFound - The session context cannot be found.
- RadiusSessionNotRemoveable - The session context cannot be removed.
- RadiusProxyProcessingError - An unknown proxy processing error has occurred.
- RadiusResourcesUnavailable - The necessary resources are unavailable.
- RadiusRequestInitiated - A request has been initiated.
- RadiusMultiSessionSelectionUnsupported - The requested multiple-session selection is not supported.
- RadiusLocationInfoRequired - The location information is missing.

```
<?xml version='1.0' ?>
<Statistics>
  <ProtocolErrorStats>
    <Sample>
      <StartTime>2011-02-22T03:45:11Z</StartTime>
      <EndTime>2011-02-22T03:45:33Z</EndTime>
      <PolicyServer>rc178</PolicyServer>
      <DiameterCommandUnsupportedReceived>0</DiameterCommandUnsupportedReceived>
      <DiameterCommandUnsupportedSent>0</DiameterCommandUnsupportedSent>
    </Sample>
  </ProtocolErrorStats>
</Statistics>
```

```

<DiameterUnableToDeliverReceived>0</DiameterUnableToDeliverReceived>
<DiameterUnableToDeliverSent>0</DiameterUnableToDeliverSent>
<DiameterRealmNotServedReceived>0</DiameterRealmNotServedReceived>
<DiameterRealmNotServedSent>0</DiameterRealmNotServedSent>
<DiameterTooBusyReceived>0</DiameterTooBusyReceived>
<DiameterTooBusySent>0</DiameterTooBusySent>
<DiameterLoopDetectedReceived>0</DiameterLoopDetectedReceived>
<DiameterLoopDetectedSent>0</DiameterLoopDetectedSent>
<DiameterRedirectIndicationReceived>0</DiameterRedirectIndicationReceived>

<DiameterRedirectIndicationSent>0</DiameterRedirectIndicationSent>
<DiameterApplicationUnsupportedReceived>0</DiameterApplication
  UnsupportedReceived>
<DiameterApplicationUnsupportedSent>0</DiameterApplicationUnsupportedSent>

<DiameterInvalidHdrBitsReceived>0</DiameterInvalidHdrBitsReceived>
<DiameterInvalidHdrBitsSent>0</DiameterInvalidHdrBitsSent>
<DiameterInvalidAvpBitsReceived>0</DiameterInvalidAvpBitsReceived>
<DiameterInvalidAvpBitsSent>0</DiameterInvalidAvpBitsSent>
<DiameterUnknownPeerReceived>0</DiameterUnknownPeerReceived>
<DiameterUnknownPeerSent>0</DiameterUnknownPeerSent>
<DiameterAuthenticationRejectedReceived>0</DiameterAuthentication
  RejectedReceived>
<DiameterAuthenticationRejectedSent>0</DiameterAuthentication
  RejectedSent>
<DiameterOutOfSpaceReceived>0</DiameterOutOfSpaceReceived>
<DiameterOutOfSpaceSent>0</DiameterOutOfSpaceSent>
<ElectionLostReceived>0</ElectionLostReceived>
<ElectionLostSent>0</ElectionLostSent>
<DiameterEndUserServiceDeniedReceived>0</DiameterEndUserService
  DeniedReceived>
<DiameterEndUserServiceDeniedSent>0</DiameterEndUserServiceDeniedSent>
<DiameterCreditControlNotApplicableReceived>0</DiameterCreditControlNot
  ApplicableReceived>
<DiameterCreditControlNotApplicableSent>0</DiameterCreditControlNot
  ApplicableSent>
<DiameterCreditLimitReachedReceived>0</DiameterCreditLimitReachedReceived>

<DiameterCreditLimitReachedSent>0</DiameterCreditLimitReachedSent>
<DiameterAvpUnsupportedReceived>0</DiameterAvpUnsupportedReceived>
<DiameterAvpUnsupportedSent>0</DiameterAvpUnsupportedSent>
<DiameterUnknownSessionIdReceived>0</DiameterUnknownSessionIdReceived>
<DiameterUnknownSessionIdSent>0</DiameterUnknownSessionIdSent>
<DiameterAuthorizationRejectedReceived>0</DiameterAuthorization
  RejectedReceived>
<DiameterAuthorizationRejectedSent>0</DiameterAuthorizationRejectedSent>
<DiameterInvalidAvpValueReceived>0</DiameterInvalidAvpValueReceived>
<DiameterInvalidAvpValueSent>0</DiameterInvalidAvpValueSent>
<DiameterMissingAvpReceived>0</DiameterMissingAvpReceived>
<DiameterMissingAvpSent>0</DiameterMissingAvpSent>
<DiameterResourcesExceededReceived>0</DiameterResourcesExceededReceived>
<DiameterResourcesExceededSent>0</DiameterResourcesExceededSent>
<DiameterContradictingAvpsReceived>0</DiameterContradictingAvpsReceived>
<DiameterContradictingAvpsSent>0</DiameterContradictingAvpsSent>
<DiameterAvpNotAllowedReceived>0</DiameterAvpNotAllowedReceived>
<DiameterAvpNotAllowedSent>0</DiameterAvpNotAllowedSent>
<DiameterAvpOccursTooManyTimesReceived>0</DiameterAvpOccursTooMany
  TimesReceived>
<DiameterAvpOccursTooManyTimesSent>0</DiameterAvpOccursTooManyTimesSent>
<DiameterNoCommonApplicationReceived>0</DiameterNoCommonApplicationReceived>

<DiameterNoCommonApplicationSent>0</DiameterNoCommonApplicationSent>
<DiameterUnsupportedVersionReceived>0</DiameterUnsupportedVersionReceived>

```

```

<DiameterUnsupportedVersionSent>0</DiameterUnsupportedVersionSent>
<DiameterUnableToComplyReceived>0</DiameterUnableToComplyReceived>
<DiameterUnableToComplySent>0</DiameterUnableToComplySent>
<DiameterInvalidBitInHeaderReceived>0</DiameterInvalidBitInHeaderReceived>

<DiameterInvalidBitInHeaderSent>0</DiameterInvalidBitInHeaderSent>
<DiameterInvalidAvpLengthReceived>0</DiameterInvalidAvpLengthReceived>
<DiameterInvalidAvpLengthSent>0</DiameterInvalidAvpLengthSent>

<DiameterInvalidMessageLengthReceived>0</DiameterInvalidMessageLengthReceived>
<DiameterInvalidMessageLengthSent>0</DiameterInvalidMessageLengthSent>
<DiameterInvalidAvpBitComboReceived>0</DiameterInvalidAvpBitComboReceived>

<DiameterInvalidAvpBitComboSent>0</DiameterInvalidAvpBitComboSent>
<DiameterNoCommonSecurityReceived>0</DiameterNoCommonSecurityReceived>
<DiameterNoCommonSecuritySent>0</DiameterNoCommonSecuritySent>
<DiameterUserUnknownReceived>0</DiameterUserUnknownReceived>
<DiameterUserUnknownSent>0</DiameterUserUnknownSent>
<DiameterRatingFailedReceived>0</DiameterRatingFailedReceived>
<DiameterRatingFailedSent>0</DiameterRatingFailedSent>
<DiameterErrorInitialParametersReceived>0</DiameterErrorInitial
ParametersReceived>
<DiameterErrorInitialParametersSent>2</DiameterErrorInitialParametersSent>

<RadiusSessionContextRemovedReceived>0</RadiusSessionContext
RemovedReceived>
<RadiusSessionContextRemovedSent>0</RadiusSessionContextRemovedSent>
<RadiusInvalidEapPacketReceived>0</RadiusInvalidEapPacketReceived>
<RadiusInvalidEapPacketSent>0</RadiusInvalidEapPacketSent>
<RadiusUnsupportedAttributeReceived>0</RadiusUnsupportedAttributeReceived>

<RadiusUnsupportedAttributeSent>0</RadiusUnsupportedAttributeSent>
<RadiusMissingAttributeReceived>0</RadiusMissingAttributeReceived>
<RadiusMissingAttributeSent>0</RadiusMissingAttributeSent>
<RadiusNasIdMismatchReceived>0</RadiusNasIdMismatchReceived>
<RadiusNasIdMismatchSent>0</RadiusNasIdMismatchSent>
<RadiusInvalidRequestReceived>0</RadiusInvalidRequestReceived>
<RadiusInvalidRequestSent>0</RadiusInvalidRequestSent>
<RadiusUnsupportedServiceReceived>0</RadiusUnsupportedServiceReceived>
<RadiusUnsupportedServiceSent>0</RadiusUnsupportedServiceSent>
<RadiusUnsupportedExtensionReceived>0</RadiusUnsupportedExtensionReceived>

<RadiusUnsupportedExtensionSent>0</RadiusUnsupportedExtensionSent>
<RadiusInvalidAttributeValueReceived>0</RadiusInvalidAttributeValueReceived>

<RadiusInvalidAttributeValueSent>0</RadiusInvalidAttributeValueSent>
<RadiusAdministrativelyProhibitedReceived>0</RadiusAdministratively
ProhibitedReceived>
<RadiusAdministrativelyProhibitedSent>0</RadiusAdministratively
ProhibitedSent>
<RadiusRequestNotRoutableReceived>0</RadiusRequestNotRoutableReceived>
<RadiusRequestNotRoutableSent>0</RadiusRequestNotRoutableSent>
<RadiusSessionNotFoundReceived>0</RadiusSessionNotFoundReceived>
<RadiusSessionNotFoundSent>0</RadiusSessionNotFoundSent>
<RadiusSessionNotRemoveableReceived>0</RadiusSessionNotRemoveableReceived>

<RadiusSessionNotRemoveableSent>0</RadiusSessionNotRemoveableSent>
<RadiusProxyProcessingErrorReceived>0</RadiusProxyProcessingErrorReceived>

<RadiusProxyProcessingErrorSent>0</RadiusProxyProcessingErrorSent>
<RadiusResourcesUnavailableReceived>0</RadiusResourcesUnavailableReceived>

<RadiusResourcesUnavailableSent>0</RadiusResourcesUnavailableSent>
<RadiusRequestInitiatedReceived>0</RadiusRequestInitiatedReceived>

```

```

    <RadiusRequestInitiatedSent>0</RadiusRequestInitiatedSent>
    <RadiusMultiSessionSelectionUnsupportedReceived>0</RadiusMultiSession
      SelectionUnsupportedReceived>
    <RadiusMultiSessionSelectionUnsupportedSent>0</RadiusMultiSessionSelection
      UnsupportedSent>
    <RadiusLocationInfoRequiredReceived>0</RadiusLocationInfoRequiredReceived>
    <RadiusLocationInfoRequiredSent>0</RadiusLocationInfoRequiredSent>
  </Sample>
</ProtocolErrorStats>
</Statistics>

```

Session Cleanup Statistics

The following examples show the request and response that are defined in the XSDs for the `StaleSessionStats` tag.

Request

This request follows the `QueryOmStats > StaleSessionStats` tag defined in the XSDs.

The following is an example of a request for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <StaleSessionStats>
    <PolicyServer>PolicyServer</PolicyServer>
    </ProtocolErrorStats>
  </StaleSessionStats>
</QueryOmStats>

```

Response

The response to this request follows the `Statistics > StaleSessionStats` tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <staleSessionStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <SessionReadyForCleanUp>0</SessionReadyForCleanUp>
      <SessionCleaned>0</SessionCleaned>
      <ReauthorizedSessions>0</ReauthorizedSessions>
      <ReauthorizedTimeouts>0</ReauthorizedTimeouts>
      <ReauthorizedCleaned>0</ReauthorizedCleaned>
    </Sample>
  </staleSessionStats>
</Statistics>

```

Individual statistics are defined as follows:

- **Ready for Cleanup:** GAUGE to track the number of current stale sessions.
- **Removed for Error:** COUNTER to track the number of deleted stale sessions that failed to reauthorize due to an error response.
- **Reauthorized:** COUNTER to track the number of reauthorized stale sessions.
- **Reauthorization Timeouts:** COUNTER to track to the number of timed out reauthorization sessions.
- **Removed for Expiration:** COUNTER to track the number of timed out reauthorization sessions due to age.

Timeout Statistics

The following examples show the response defined in the XSDs for the DiameterAf Stats tag.

The MRA response follows the **Statistics > DiameterAfStats** tag defined in the XSDs.

- **AAR Timeout** — The numeric count of AA-Request messages sent and AA-Answer messages not received in a set amount of time.
- **ASR Timeout** — The numeric count of Abort Session Requests (ASR) messages sent where ASA messages not received in a set amount of time.
- **RAR Timeout** — The numeric count of ReAuthorization Request (RAR) messages sent where RAA messages not received in a set amount of time.
- **STR Timeout** — The numeric count of Session Termination Requests (STR) messages sent where STA messages not received in a set amount of time.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterAfStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      ...
      <ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
      <ASRMessagesSentCount>0</ASRMessagesSentCount>
      <ASRMessagesTimeoutCount>0</ASRMessagesTimeoutCount>
      ...
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      ...
      <STRMessagesReceivedCount>0</STRMessagesReceivedCount>
      <STRMessagesSentCount>0</STRMessagesSentCount>
      <STRMessagesTimeoutCount>0</STRMessagesTimeoutCount>
      ...
      <AARMessagesReceivedCount>0</AARMessagesReceivedCount>
      <AARMessagesSentCount>0</AARMessagesSentCount>
      <AARMessagesTimeoutCount>0</AARMessagesTimeoutCount>
      ...
      <PeerReopenCount>0</PeerReopenCount>
    </Sample>
  </DiameterAfStats>
</Statistics>
```

Response

The MRA response follows the **Statistics > DiameterAfPeerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterAfPeerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <Name>NetworkElementName</Name>
      <NeId>NeId</NeId>
      <NetworkElementType>NetworkElementType</NetworkElementType>
      <NetworkElementSubType>NetworkElementSubType</NetworkElementSubType>
      ...
      <ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
      <ASRMessagesSentCount>0</ASRMessagesSentCount>
      <ASRMessagesTimeoutCount>0</ASRMessagesTimeoutCount>
      ...
      <RRMessagesReceivedCount>0</RRMessagesReceivedCount>
      <RRMessagesSentCount>0</RRMessagesSentCount>
      <RRMessagesTimeoutCount>0</RRMessagesTimeoutCount>
      ...
    <STRMessagesReceivedCount>STRMessagesReceivedCount</STRMessagesReceivedCount>
    <STRMessagesSentCount>STRMessagesSentCount</STRMessagesSentCount>
    <STRMessagesTimeoutCount>0</STRMessagesTimeoutCount>
    ...
    <AARMessagesReceivedCount>AARMessagesReceivedCount</AARMessagesReceivedCount>
    <AARMessagesSentCount>AARMessagesSentCount</AARMessagesSentCount>
    <AARMessagesTimeoutCount>0</AARMessagesTimeoutCount>
    ...
    <AAAFailureMessagesSentCount>0</AAAFailureMessagesSentCount>
  </Sample>
</DiameterAfPeerStats>
</Statistics>
```

The MRA response follows the **Statistics > DiameterPcefStats** tag defined in the XSDs.

- CCR Timeout — The numeric count of CC-Request messages sent and CC-Answer messages not received in a set amount of time.

Note: The number of CCR-I/U/T Timeouts should equal this number combined.

- CCR-I Timeout — The numeric count of CCR-Initial messages sent and CCA-Initial messages not received in a set amount of time.
- CCR-U Timeout — The numeric count of CCR-Update messages sent and CCA-Update messages not received in a set amount of time.
- CCR-T Timeout — The numeric count of CCR-Terminate messages sent and CCA-Terminate messages not received in a set amount of time.
- RAR Timeout — The numeric count of Reauthorization Request messages sent and RAA messages not received in a set amount of time.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterPcefStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      ...
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
      ...
      <PeerSuspectCount>0</PeerSuspectCount>
      <PeerReopenCount>0</PeerReopenCount>
    </Sample>
  </DiameterPcefStats>
</Statistics>
```

The MRA response follows the **Statistics > DiameterPcefPeerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterPcefPeerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <Name>NetworkElementName</Name>
      <NeId>NeId<NeId>
      <NetworkElementType>NetworkElementType</NetworkElementType>
      <NetworkElementSubType>NetworkElementSubType</NetworkElementSubType>
      ...
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      ...
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
```



```

    <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
    <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
    <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
    <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
    <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
    <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
    ...
    <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
  </Sample>
</DiameterPcefPeerStats>
</Statistics>

```

The MRA response follows the **Statistics > DiameterBberfStats** tag defined in the XSDs.

- CCR Timeout — The numeric count of CC-Request messages sent and CC-Answer messages not received in a set amount of time.

Note: The number of CCR-I/U/T Timeouts should equal this number combined.

- CCR-I Timeout — The numeric count of CCR-Initial messages sent and CCA-Initial messages not received in a set amount of time.
- CCR-U Timeout — The numeric count of CCR-Update messages sent and CCA-Update messages not received in a set amount of time.
- CCR-T Timeout — The numeric count of CCR-Terminate messages sent and CCA-Terminate messages not received in a set amount of time.
- RAR Timeout — The numeric count of Reauthorization Request messages sent and RAA messages not received in a set amount of time.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterBberfStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      ...
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      ...
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
      ...
      <PeerReopenCount>0</PeerReopenCount>
    </Sample>
  </DiameterBberfStats>
</Statistics>

```

The following is an example of a response for an MPE:

```
<Statistics>
  <DiameterBberfStats>
    <Sample>
      <StartTime>2012-06-07T01:00:00Z</StartTime>
      <EndTime>2012-06-07T01:15:00Z</EndTime>
      <PolicyServer>kli-63-mpe</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>1</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
      <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
      <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
      <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
      <CCAIISuccessMessagesReceivedCount>0</CCAIISuccessMessagesReceivedCount>
      <CCAIISuccessMessagesSentCount>0</CCAIISuccessMessagesSentCount>
      <CCAIIFailureMessagesReceivedCount>0</CCAIIFailureMessagesReceivedCount>
      <CCAIIFailureMessagesSentCount>0</CCAIIFailureMessagesSentCount>
      <CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
      <CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
      <CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
      <CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
      <CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
      <CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
      <CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
      <CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
      <ActiveSessionsCount>0</ActiveSessionsCount>
      <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
      <PeerOkayCount>1</PeerOkayCount>
      <PeerDownCount>0</PeerDownCount>
      <PeerSuspectCount>0</PeerSuspectCount>
      <PeerReopenCount>0</PeerReopenCount>
    </Sample>
  </DiameterBberfStats>
</Statistics>
```

The MRA response follows the **Statistics > DiameterBberfPeerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterBberfPeerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <Name>NetworkElementName</Name>
      <NeId>NeId</NeId>
      <NetworkElementType>NetworkElementType</NetworkElementType>
      <NetworkElementSubType>NetworkElementSubType</NetworkElementSubType>
      ...
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      ...
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
      ...
      <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
    </Sample>
  </DiameterBberfPeerStats>
</Statistics>
```

The following is an example of a response for an MPE:

```
<Statistics>
  <DiameterBberfPeerStats>
    <Sample>
      <StartTime>2012-06-07T01:00:00Z</StartTime>
      <EndTime>2012-06-07T01:15:00Z</EndTime>
      <PolicyServer>kli-63-mpe</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>mra66</Name>
      <NeId />
      <NetworkElementType />
      <NetworkElementSubType />
      <ConnectTime>Tue Jun 05 02:54:29 EDT 2012</ConnectTime>
      <DisconnectTime>Tue Jun 05 02:54:28 EDT 2012</DisconnectTime>
      <ConnectAddress>10.60.25.66</ConnectAddress>
      <ConnectPort>48526</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>0</MessagesErrorOutCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
```

```

<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
<CCRMessagesSentCount>0</CCRMessagesSentCount>
<CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
<CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
<CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
<CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
<CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
<CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
<CCRIMessagesSentCount>0</CCRIMessagesSentCount>
<CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
<CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
<CCRUMessagesSentCount>0</CCRUMessagesSentCount>
<CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
<CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
<CCRTMessagesSentCount>0</CCRTMessagesSentCount>
<CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
<CCAIISuccessMessagesReceivedCount>0</CCAIISuccessMessagesReceivedCount>
<CCAIISuccessMessagesSentCount>0</CCAIISuccessMessagesSentCount>
<CCAIIFailureMessagesReceivedCount>0</CCAIIFailureMessagesReceivedCount>
<CCAIIFailureMessagesSentCount>0</CCAIIFailureMessagesSentCount>
<CCAUISuccessMessagesReceivedCount>0</CCAUISuccessMessagesReceivedCount>
<CCAUISuccessMessagesSentCount>0</CCAUISuccessMessagesSentCount>
<CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
<CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
<CCATISuccessMessagesReceivedCount>0</CCATISuccessMessagesReceivedCount>
<CCATISuccessMessagesSentCount>0</CCATISuccessMessagesSentCount>
<CCATIFailureMessagesReceivedCount>0</CCATIFailureMessagesReceivedCount>
<CCATIFailureMessagesSentCount>0</CCATIFailureMessagesSentCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
</Sample>
</DiameterBberfPeerStats>
</Statistics>

```

The MRA response follows the **Statistics > DiameterShStats** tag defined in the XSDs.

- UDR Timeout — The numeric count of User Data Request (UDR) messages sent and User Data Answer (UDA) messages not received in a set amount of time.
- PUR Timeout — The numeric count of Profile Update Request (PUR) messages sent and Profile Update Answer (PUA) messages not received in a set amount of time.
- SNR Timeout — The numeric count of Subscription Notification Request (SNR) messages sent and Subscription Notification Answer (SNA) messages not received in a set amount of time.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterShStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <CurrentConnectionsCount>0</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <UDRMessagesReceivedCount>0</UDRMessagesReceivedCount>
      <UDRMessagesSentCount>0</UDRMessagesSentCount>
    </Sample>
  </DiameterShStats>
</Statistics>

```

```

    <UDRMessagesTimeoutCount>0</UDRMessagesTimeoutCount>
    ...
    <PURMessagesReceivedCount>0</PURMessagesReceivedCount>
    <PURMessagesSentCount>0</PURMessagesSentCount>
    <PURMessagesTimeoutCount>0</PURMessagesTimeoutCount>
    ...
    <SNRMessagesReceivedCount>0</SNRMessagesReceivedCount>
    <SNRMessagesSentCount>0</SNRMessagesSentCount>
    <SNRMessagesTimeoutCount>0</SNRMessagesTimeoutCount>
    ...
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterShStats>
</Statistics>

```

The MRA response follows the **Statistics > DiameterTdfStats** tag defined in the XSDs.

CCR Timeout — The numeric count of CC-Request messages sent and CC-Answer messages not received in a set amount of time.

Note: The number of CCR-I/U/T Timeouts should equal this number combined.

- **CCR-I Timeout** — The numeric count of CCR-Initial messages sent and CCA-Initial messages not received in a set amount of time.
- **CCR-U Timeout** — The numeric count of CCR-Update messages sent and CCA-Update messages not received in a set amount of time.
- **CCR-T Timeout** — The numeric count of CCR-Terminate messages sent and CCA-Terminate messages not received in a set amount of time.
- **RAR Timeout** — The numeric count of Reauthorization Request messages sent and RAA messages not received in a set amount of time.

The following is an example of a response for a single policy server:

```

<Statistics>
  <DiameterTdfStats>
    <Sample>
      <StartTime>2012-05-28T09:30:00Z</StartTime>
      <EndTime>2012-05-28T09:45:00Z</EndTime>
      <PolicyServer>kli-63-mpe</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>1</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <TSRMessagesReceivedCount>0</TSRMessagesReceivedCount>
      <TSRMessagesSentCount>0</TSRMessagesSentCount>
      <TSRMessagesTimeoutCount>0</TSRMessagesTimeoutCount>
      <TSASuccessMessagesReceivedCount>0</TSASuccessMessagesReceivedCount>
      <TSASuccessMessagesSentCount>0</TSASuccessMessagesSentCount>
      <TSAFailureMessagesReceivedCount>0</TSAFailureMessagesReceivedCount>
      <TSAFailureMessagesSentCount>0</TSAFailureMessagesSentCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
    </Sample>
  </DiameterTdfStats>
</Statistics>

```

```

<CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
<CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
<CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
<CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
<CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
<CCRIMessagesSentCount>0</CCRIMessagesSentCount>
<CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
<CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
<CCRUMessagesSentCount>0</CCRUMessagesSentCount>
<CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
<CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
<CCRTMessagesSentCount>0</CCRTMessagesSentCount>
<CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
<CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
<CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
<CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
<CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
<CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
<CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
<CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
<CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
<CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
<CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
<CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
<CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
<PeerOkayCount>1</PeerOkayCount>
<PeerDownCount>2</PeerDownCount>
<PeerSuspectCount>0</PeerSuspectCount>
<PeerReopenCount>0</PeerReopenCount>
</Sample>
</DiameterTdfStats>
</Statistics>

```

The following is an example of a response for an MPE:

```

<Statistics>
  <DiameterTdfStats>
    <Sample>
      <StartTime>2012-05-28T09:30:00Z</StartTime>
      <EndTime>2012-05-28T09:45:00Z</EndTime>
      <PolicyServer>kli-63-mpe</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>1</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <TSRMessagesReceivedCount>0</TSRMessagesReceivedCount>
      <TSRMessagesSentCount>0</TSRMessagesSentCount>
      <TSRMessagesTimeoutCount>0</TSRMessagesTimeoutCount>
      <TSASuccessMessagesReceivedCount>0</TSASuccessMessagesReceivedCount>
      <TSASuccessMessagesSentCount>0</TSASuccessMessagesSentCount>
      <TSAFailureMessagesReceivedCount>0</TSAFailureMessagesReceivedCount>
      <TSAFailureMessagesSentCount>0</TSAFailureMessagesSentCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
    </Sample>
  </DiameterTdfStats>
</Statistics>

```

```

    <CCRMessagesSentCount>0</CCRMessagesSentCount>
    <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
    <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
    <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
    <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
    <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
    <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
    <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
    <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
    <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
    <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
    <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
    <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
    <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
    <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
    <CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
    <CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
    <CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
    <CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
    <CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
    <CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
    <CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
    <CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
    <CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
    <CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
    <CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
    <CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
    <ActiveSessionsCount>0</ActiveSessionsCount>
    <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
    <PeerOkayCount>1</PeerOkayCount>
    <PeerDownCount>2</PeerDownCount>
    <PeerSuspectCount>0</PeerSuspectCount>
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterTdfStats>
</Statistics>

```

The MRA response follows the **Statistics > DiameterTdfPeerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<Statistics>
  <DiameterTdfPeerStats>
    <Sample>
      <StartTime>2012-05-28T09:15:00Z</StartTime>
      <EndTime>2012-05-28T09:30:00Z</EndTime>
      <PolicyServer>kli-63-mpe</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>kli-66-mra2</Name>
      <NeId/>
      <NetworkElementType/>
      <NetworkElementSubType/>
      <ConnectTime>Thu May 24 01:23:51 EDT 2012</ConnectTime>
      <DisconnectTime>Fri May 25 04:18:11 EDT 2012</DisconnectTime>
      <ConnectAddress>10.60.25.67:57455,10.60.25.68:57455</ConnectAddress>
      <ConnectPort>0</ConnectPort>
      <ConnectType>SCTP</ConnectType>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>0</MessagesErrorOutCount>
      <TSRMessagesReceivedCount>0</TSRMessagesReceivedCount>
    </Sample>
  </DiameterTdfPeerStats>
</Statistics>

```

```

<TSRMessagesSentCount>0</TSRMessagesSentCount>
<TSRMessagesTimeoutCount>0</TSRMessagesTimeoutCount>
<TSASuccessMessagesReceivedCount>0</TSASuccessMessagesReceivedCount>
<TSASuccessMessagesSentCount>0</TSASuccessMessagesSentCount>
<TSAFailureMessagesReceivedCount>0</TSAFailureMessagesReceivedCount>
<TSAFailureMessagesSentCount>0</TSAFailureMessagesSentCount>
<RARMessagesReceivedCount>0</RARMessagesReceivedCount>
<RARMessagesSentCount>0</RARMessagesSentCount>
<RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
<CCRMessagesSentCount>0</CCRMessagesSentCount>
<CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
<CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
<CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
<CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
<CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
<CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
<CCRIMessagesSentCount>0</CCRIMessagesSentCount>
<CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
<CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
<CCRUMessagesSentCount>0</CCRUMessagesSentCount>
<CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
<CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
<CCRTMessagesSentCount>0</CCRTMessagesSentCount>
<CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
<CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
<CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
<CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
<CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
<CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
<CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
<CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
<CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
<CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
<CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
<CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
<CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
</Sample>
</DiameterTdfPeerStats>
</Statistics>

```

The following is an example of a response for an MPE:

```

<Statistics>
  <DiameterTdfPeerStats>
    <Sample>
      <StartTime>2012-05-28T09:15:00Z</StartTime>
      <EndTime>2012-05-28T09:30:00Z</EndTime>
      <PolicyServer>kli-63-mpe</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>kli-66-mra2</Name>
      <NeId />
      <NetworkElementType />
      <NetworkElementSubType />
      <ConnectTime>Thu May 24 01:23:51 EDT 2012</ConnectTime>
      <DisconnectTime>Fri May 25 04:18:11 EDT 2012</DisconnectTime>
    </Sample>
  </DiameterTdfPeerStats>
</Statistics>

```



```

<ConnectAddress>10.60.25.67:57455,10.60.25.68:57455</ConnectAddress>
<ConnectPort>0</ConnectPort>
<ConnectType />
<MessagesInCount>0</MessagesInCount>
<MessagesOutCount>0</MessagesOutCount>
<MessagesErrorInCount>0</MessagesErrorInCount>
<MessagesErrorOutCount>0</MessagesErrorOutCount>
<TSRMessagesReceivedCount>0</TSRMessagesReceivedCount>
<TSRMessagesSentCount>0</TSRMessagesSentCount>
<TSRMessagesTimeoutCount>0</TSRMessagesTimeoutCount>
<TSA SuccessMessagesReceivedCount>0</TSA SuccessMessagesReceivedCount>
<TSA SuccessMessagesSentCount>0</TSA SuccessMessagesSentCount>
<TSA FailureMessagesReceivedCount>0</TSA FailureMessagesReceivedCount>
<TSA FailureMessagesSentCount>0</TSA FailureMessagesSentCount>
<RARMessagesReceivedCount>0</RARMessagesReceivedCount>
<RARMessagesSentCount>0</RARMessagesSentCount>
<RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
<CCRMessagesSentCount>0</CCRMessagesSentCount>
<CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
<CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
<CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
<CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
<CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
<CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
<CCRIMessagesSentCount>0</CCRIMessagesSentCount>
<CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
<CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
<CCRUMessagesSentCount>0</CCRUMessagesSentCount>
<CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
<CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
<CCRTMessagesSentCount>0</CCRTMessagesSentCount>
<CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
<CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
<CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
<CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
<CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
<CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
<CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
<CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
<CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
<CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
<CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
<CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
<CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
</Sample>
</DiameterTdfPeerStats>
</Statistics>

```

The MRA response follows the **Statistics > DiameterShPeerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics xmlns:xsi="http://www.w3.org/2001/XMLSchema-instance"
xsi:noNamespaceSchemaLocation="ossiXmlOm-edit.xsd">

```

```

<DiameterShPeerStats>
  <Sample>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <PolicyServer>PolicyServer</PolicyServer>
    <Name>NetworkElementName</Name>
    <NeId>NeId</NeId>
    <NetworkElementType>NetworkElementType</NetworkElementType>
    <NetworkElementSubType>NetworkElementSubType</NetworkElementSubType>
    ...
    <UDRMessagesReceivedCount>0</UDRMessagesReceivedCount>
    <UDRMessagesSentCount>0</UDRMessagesSentCount>
    <UDRMessagesTimeoutCount>0</UDRMessagesTimeoutCount>
    ...
    <PURMessagesReceivedCount>0</PURMessagesReceivedCount>
    <PURMessagesSentCount>0</PURMessagesSentCount>
    <PURMessagesTimeoutCount>0</PURMessagesTimeoutCount>
    ...
    <SNRMessagesReceivedCount>0</SNRMessagesReceivedCount>
    <SNRMessagesSentCount>0</SNRMessagesSentCount>
    <SNRMessagesTimeoutCount>0</SNRMessagesTimeoutCount>
    ...
    <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
  </Sample>
</DiameterShPeerStats>
</Statistics>

```

The MRA response follows the **Statistics > DiameterMraDrmaStats** tag defined in the XSDs.

- DBR Timeout — The numeric count of Diameter Binding Request messages sent and Diameter Binding Answer messages not received in a set amount of time.
- RUR Timeout — The numeric count of Diameter Routing Update Request messages sent and Diameter Routing Update messages not received in a set amount of time.
- LNR Timeout — The numeric count of Diameter Load Notify Request messages sent and Diameter Load Notify Answer messages not received in a set amount of time.
- LSR Timeout — The numeric count of Diameter Load Subscription Request messages sent and Diameter Load Subscription Answer messages not received in a set amount of time.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <Sample>
    <StartTime>2001-12-31T12:00:00</StartTime>
    <EndTime>2001-12-31T12:15:00</EndTime>
    <MRA>MRA</MRA>
    <CurrentConnectionsCount>0</CurrentConnectionsCount>
    <MessagesInCount>0</MessagesInCount>
    <MessagesOutCount>0</MessagesOutCount>
    <DBRMessagesReceivedCount>0</DBRMessagesReceivedCount>
    <DBRMessageSentCount>0</DBRMessageSentCount>
    <DBRMessageTimeoutCount>0</DBRMessageTimeoutCount>
    ...
    <RURMessagesReceivedCount>0</RURMessagesReceivedCount>
    <RURMessagesSentCount>0</RURMessagesSentCount>
    <RURMessagesTimeoutCount>0</RURMessagesTimeoutCount>
    ...
    <LNRMessagesReceivedCount>0</LNRMessagesReceivedCount>
    <LNRMessagesSentCount>0</LNRMessagesSentCount>
    <LNRMessagesTimeoutCount>0</LNRMessagesTimeoutCount>
  </Sample>
</Statistics>

```

```

    ...
    <LSRMessagesReceivedCount>0</LSRMessagesReceivedCount>
    <LSRMessagesSentCount>0</LSRMessagesSentCount>
    <LSRMessagesTimeoutCount>0</LSRMessagesTimeoutCount>
    <SQRMessagesReceivedCount>0</SQRMessagesReceivedCount>
    < SQRMessagesSentCount>0</SQRMessagesSentCount>
    < SQRMessagesTimeoutCount>0</SQRMessagesTimeoutCount>
    ...
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterMraDrmaStats>
</Statistics>

```

The MRA response follows the **Statistics > DiameterMraDrmaPeerStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterMraDrmaPeerStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <MRA>MRA</MRA>
      <Name>NetworkElementName</Name>
      <ConnectTime>2001-11-31T12:00:00</ConnectTime>
      <DisconnectTime>2001-12-31T12:00:00</DisconnectTime>
      <ConnectAddress>10.15.25.110</ConnectAddress>
      <ConnectPort>3868</ConnectPort>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>0</MessagesErrorOutCount>
      <DBRMessagesReceivedCount>0</DBRMessagesReceivedCount>
      <DBRMessagesSentCount>0</DBRMessagesSentCount>
      <DBRMessagesTimeoutCount>0</DBRMessagesTimeoutCount>
      ...
      <RURMessagesReceivedCount>0</RURMessagesReceivedCount>
      <RURMessagesSentCount>0</RURMessagesSentCount>
      <RURMessagesTimeoutCount>0</RURMessagesTimeoutCount>
      ...
      <LNRMessagesReceivedCount>0</LNRMessagesReceivedCount>
      <LNRMessagesSentCount>0</LNRMessagesSentCount>
      <LNRMessagesTimeoutCount>0</LNRMessagesTimeoutCount>
      <LSRMessagesReceivedCount>0</LSRMessagesReceivedCount>
      <LSRMessagesSentCount>0</LSRMessagesSentCount>
      <LSRMessagesTimeoutCount>0</LSRMessagesTimeoutCount>
      <SQRMessagesReceivedCount>0</SQRMessagesReceivedCount>
      < SQRMessagesSentCount>0</SQRMessagesSentCount>
      < SQRMessagesTimeoutCount>0</SQRMessagesTimeoutCount>
      ...
      <AllPcrfsDownRecvCount>0</AllPcrfsDownRecvCount>
    </Sample>
  </DiameterMraDrmaPeerStats>
</Statistics>

```

Traffic Profile Statistics

The following examples show the request and response that are defined in the XSDs for the TrafficProfileStats tag.

Request

This request follows the **QueryOmStats** > **TrafficProfileStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <TrafficProfileStats>
    <PolicyServer>PolicyServer</PolicyServer>
    <Name>TrafficProfileName</Name>
  </TrafficProfileStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics** > **TrafficProfileStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <TrafficProfileStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <Name>TrafficProfileName</Name>
      <NumberOfTimesInstalledAttempts>0</NumberOfTimesInstalledAttempts>
      <NumberOfTimesRemovedByPCRF>0</NumberOfTimesRemovedByPCRF>

      <NumberOfTimesFailedOrRemovedByGateway>0</NumberOfTimesFailedOrRemovedByGateway>
    </Sample>
  </TrafficProfileStats>
</Statistics>
```

Individual statistics are defined for Traffic Profiles as follows:

- Install Attempt — COUNTER which tracks the number of times the PCRF attempts to install a specific Traffic Profile.
- Removed by PCRF — COUNTER which tracks the number of times the PCRF initiates the removal of a specific Traffic Profile.
- Failed or Removed by Gateway — COUNTER which tracks the number of times specific Traffic Profiles fail to install on the gateway, and the number of times the gateway removes a rule without PCRF approval.
- NumberOfTimesTotalRetryAttempts — The total number of retry attempts taken to successfully install the rule.
- NumberOfTimesRetryCycles — The number of Retry Cycles taken to successfully install the PCC/ADC rule for which retry mechanism was started.

- **NumberOfTimesFailedAfterMaxRetryCycles** — The number of times a PCC/ADC rule failed to be installed after trying for max number of retries

Connection Error Statistics

The following examples show the request and response that are defined in the XSDs for the **ConnectionErrorStats** tag.

Request

This request follows the **QueryOmStats > ConnectionErrorStats** tag defined in the XSDs.

The following is an example of a request for all connection error statistics:

```
<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats DeltaCount="false">
    <StartTime>2010-04-02T00:01:00</StartTime>
    <EndTime>2011-05-21T23:59:00</EndTime>
    <ConnectionErrorStats>
      <Name>123</Name>
    </ConnectionErrorStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > ConnectionErrorStats** tag defined in the XSDs.

- **DiameterCommandUnsupported** - The request contained a command code that the receiver did not recognize or support.
- **DiameterUnableToDeliver** - This error is given when the diameter node cannot deliver the message to the destination, either because no host within the realm that supports the required application was available to process the request, or because Destination-Host AVP was given without the associated Destination-Realm AVP.
- **DiameterRealmNotServed** - The intended realm of the request is not recognized.
- **DiameterTooBusy** - The diameter node has too much traffic. When returned, a diameter node attempts to send the message to an alternate peer.
- **DiameterLoopDetected** - An agent detected a loop while trying to get the message to the intended recipient. The message may be sent to an alternate peer if available.
- **DiameterRedirectIndication** - A redirect agent has determined that the request could not be satisfied locally and the initiator of the request should direct the request directly to the server, whose contact information has been added to the response. When set, the Redirect-Host AVP must be present.
- **DiameterApplicationUnsupported** - A request was sent for an application that is not supported.
- **DiameterInvalidHdrBits** - A request was received whose bits in the diameter header were either set to an invalid combination, or to a value that is inconsistent with the command code's definition.
- **DiameterInvalidAvpBits** - A request was received that included an AVP whose flag bits are set to an unrecognized value, or that is inconsistent with the AVP's definition.
- **DiameterUnknownPeer** - A CER was received from an unknown peer.
- **DiameterAuthenticationRejected** - The authentication process for the user failed, most likely due to an invalid password used by the user. The user is then prompted for a new password.

- **DiameterOutOfSpace** - A diameter node received the accounting request but was unable to commit it to stable storage due to a temporary lack of space.
- **ElectionLost** - The peer has lost the election process and has disconnected the transport connection.
- **DiameterEndUserServiceDenied** - The credit-control server denied the service request due to service restrictions. If the CCR contained used-service-units, they are deducted, if possible.
- **DiameterCreditControlNotApplicable** - The credit-control server determined that the service can be granted to the end user, but that no further credit control is needed for the service (for example, the service is free of charge).
- **DiameterCreditLimitReached** - The credit-control server denied the service request because the end user's account could not cover the requested service. If the CCR contained used-service-units, they are deducted, if possible.
- **DiameterAvpUnsupported** - The peer received a message that contained an AVP that is not recognized or supported and was marked with the Mandatory bit.
- **DiameterUnknownSessionId** - The request contained an unknown Session-Id.
- **DiameterAuthorizationRejected** - A request was received for which the user could not be authorized. This error could occur if the requested service is not permitted to the user.
- **DiameterInvalidAvpValue** - The request contained an AVP with an invalid value in its data portion.
- **DiameterMissingAvp** - The request did not contain an AVP that is required by the command code definition. If this value is sent in the Result-Code AVP, a Failed-AVP AVP is included in the message.
- **DiameterResourcesExceeded** - A request was received that cannot be authorized because the user has already expended its allowed resources.
- **DiameterContradictingAvps** - The Home Diameter server has detected AVPs in the request that contradict each other, and is not willing to provide service to the user.
- **DiameterAvpNotAllowed** - A message was received with an AVP that cannot be present.
- **DiameterAvpOccursTooManyTimes** - A message was received that included an AVP that appeared more often than permitted.
- **DiameterNoCommonApplication** - This error is returned when a CER message is received, and there are no common applications supported between the peers.
- **DiameterUnsupportedVersion** - This error is returned when a request was received with an unsupported version number.
- **DiameterUnableToComply** - This error is returned when a request is rejected for unspecified reasons.
- **DiameterInvalidBitInHeader** - This error is returned when an unrecognized bit in the diameter header is set to one (1).
- **DiameterInvalidAvpLength** - The request contained an AVP with an invalid length.
- **DiameterInvalidMessageLength** - This error is returned when a request is received with an invalid message length.
- **DiameterInvalidAvpBitCombo** - The request contained an AVP with an invalid AVP Flags value.
- **DiameterNoCommonSecurity** - This error is returned when a CER message is received, but there are no common security mechanisms supported between the peers.
- **DiameterUserUnknown** - The specified end user is unknown in the credit-control server.
- **DiameterRatingFailed** - This error code is used to inform the credit-control client that the credit-control server cannot rate the service request due to insufficient rating input, an incorrect AVP combination, or an AVP or AVP value that is not recognized or supported in the rating.
- **DiameterErrorInitialParameters** - The initial parameters contain an error.
- **RadiusSessionContextRemoved** - The residual session context has been removed.
- **RadiusInvalidEapPacket** - An invalid EAP Packet was detected.
- **RadiusUnsupportedAttribute** - The request contained an unsupported attribute.

- RadiusMissingAttribute - A request was missing a required attribute.
- RadiusNasIdMismatch - The system was unable to match the received NAS to the stored information.
- RadiusInvalidRequest - The system has received an invalid request.
- RadiusUnsupportedService - The requested service is not supported.
- RadiusUnsupportedExtension - The requested extension is not supported.
- RadiusInvalidAttributeValue - The request contains an invalid attribute value.
- RadiusAdministrativelyProhibited - The request is administratively prohibited.
- RadiusRequestNotRoutable - The request can't be routed.
- RadiusSessionNotFound - The session context cannot be found.
- RadiusSessionNotRemoveable - The session context cannot be removed.
- RadiusProxyProcessingError - An unknown proxy processing error has occurred.
- RadiusResourcesUnavailable - The necessary resources are unavailable.
- RadiusRequestInitiated - A request has been initiated.
- RadiusMultiSessionSelectionUnsupported - The requested multiple-session selection is not supported.
- RadiusLocationInfoRequired - The location information is missing.

The following is an example of the ConnectionErrorStats tag:

```
<?xml version="1.0" ?>
<Statistics>
  <ConnectionErrorStats>
    <Sample>
      <StartTime>2011-02-22T03:45:11Z</StartTime>
      <EndTime>2011-02-22T03:45:33Z</EndTime>
      <PolicyServer>rc178</PolicyServer>
      <Name>123</Name>
      <NeId></NeId>
      <DiameterCommandUnsupportedReceived>0</DiameterCommandUnsupportedReceived>

      <DiameterCommandUnsupportedSent>0</DiameterCommandUnsupportedSent>
      <DiameterUnableToDeliverReceived>0</DiameterUnableToDeliverReceived>
      <DiameterUnableToDeliverSent>0</DiameterUnableToDeliverSent>
      <DiameterRealmNotServedReceived>0</DiameterRealmNotServedReceived>
      <DiameterRealmNotServedSent>0</DiameterRealmNotServedSent>
      <DiameterTooBusyReceived>0</DiameterTooBusyReceived>
      <DiameterTooBusySent>0</DiameterTooBusySent>
      <DiameterLoopDetectedReceived>0</DiameterLoopDetectedReceived>
      <DiameterLoopDetectedSent>0</DiameterLoopDetectedSent>
      <DiameterRedirectIndicationReceived>0</DiameterRedirectIndicationReceived>

      <DiameterRedirectIndicationSent>0</DiameterRedirectIndicationSent>
      <DiameterApplicationUnsupportedReceived>0</DiameterApplication
        UnsupportedReceived>
      <DiameterApplicationUnsupportedSent>0</DiameterApplicationUnsupportedSent>

      <DiameterInvalidHdrBitsReceived>0</DiameterInvalidHdrBitsReceived>
      <DiameterInvalidHdrBitsSent>0</DiameterInvalidHdrBitsSent>
      <DiameterInvalidAvpBitsReceived>0</DiameterInvalidAvpBitsReceived>
      <DiameterInvalidAvpBitsSent>0</DiameterInvalidAvpBitsSent>
      <DiameterUnknownPeerReceived>0</DiameterUnknownPeerReceived>
      <DiameterUnknownPeerSent>0</DiameterUnknownPeerSent>
      <DiameterAuthenticationRejectedReceived>0</DiameterAuthentication
        RejectedReceived>
      <DiameterAuthenticationRejectedSent>0</DiameterAuthenticationRejectedSent>

      <DiameterOutOfSpaceReceived>0</DiameterOutOfSpaceReceived>
```

```

<DiameterOutOfSpaceSent>0</DiameterOutOfSpaceSent>
<ElectionLostReceived>0</ElectionLostReceived>
<ElectionLostSent>0</ElectionLostSent>
<DiameterEndUserServiceDeniedReceived>0</DiameterEndUserService
  DeniedReceived>
<DiameterEndUserServiceDeniedSent>0</DiameterEndUserServiceDeniedSent>
<DiameterCreditControlNotApplicableReceived>0</DiameterCreditControlNot
  ApplicableReceived>
<DiameterCreditControlNotApplicableSent>0</DiameterCreditControlNot
  ApplicableSent>
<DiameterCreditLimitReachedReceived>0</DiameterCreditLimitReachedReceived>

<DiameterCreditLimitReachedSent>0</DiameterCreditLimitReachedSent>
<DiameterAvpUnsupportedReceived>0</DiameterAvpUnsupportedReceived>
<DiameterAvpUnsupportedSent>0</DiameterAvpUnsupportedSent>
<DiameterUnknownSessionIdReceived>0</DiameterUnknownSessionIdReceived>
<DiameterUnknownSessionIdSent>0</DiameterUnknownSessionIdSent>
<DiameterAuthorizationRejectedReceived>0</DiameterAuthorization
  RejectedReceived>
<DiameterAuthorizationRejectedSent>0</DiameterAuthorizationRejectedSent>
<DiameterInvalidAvpValueReceived>0</DiameterInvalidAvpValueReceived>
<DiameterInvalidAvpValueSent>0</DiameterInvalidAvpValueSent>
<DiameterMissingAvpReceived>0</DiameterMissingAvpReceived>
<DiameterMissingAvpSent>0</DiameterMissingAvpSent>
<DiameterResourcesExceededReceived>0</DiameterResourcesExceededReceived>
<DiameterResourcesExceededSent>0</DiameterResourcesExceededSent>
<DiameterContradictingAvpsReceived>0</DiameterContradictingAvpsReceived>
<DiameterContradictingAvpsSent>0</DiameterContradictingAvpsSent>
<DiameterAvpNotAllowedReceived>0</DiameterAvpNotAllowedReceived>
<DiameterAvpNotAllowedSent>0</DiameterAvpNotAllowedSent>
<DiameterAvpOccursTooManyTimesReceived>0</DiameterAvpOccursToo
  ManyTimesReceived>
<DiameterAvpOccursTooManyTimesSent>0</DiameterAvpOccursTooManyTimesSent>
<DiameterNoCommonApplicationReceived>0</DiameterNoCommon
  ApplicationReceived>
<DiameterNoCommonApplicationSent>0</DiameterNoCommonApplicationSent>
<DiameterUnsupportedVersionReceived>0</DiameterUnsupportedVersionReceived>

<DiameterUnsupportedVersionSent>0</DiameterUnsupportedVersionSent>
<DiameterUnableToComplyReceived>0</DiameterUnableToComplyReceived>
<DiameterUnableToComplySent>0</DiameterUnableToComplySent>
<DiameterInvalidBitInHeaderReceived>0</DiameterInvalidBitInHeaderReceived>

<DiameterInvalidBitInHeaderSent>0</DiameterInvalidBitInHeaderSent>
<DiameterInvalidAvpLengthReceived>0</DiameterInvalidAvpLengthReceived>
<DiameterInvalidAvpLengthSent>0</DiameterInvalidAvpLengthSent>
<DiameterInvalidMessageLengthReceived>0</DiameterInvalidMessage
  LengthReceived>
<DiameterInvalidMessageLengthSent>0</DiameterInvalidMessageLengthSent>
<DiameterInvalidAvpBitComboReceived>0</DiameterInvalidAvpBitComboReceived>

<DiameterInvalidAvpBitComboSent>0</DiameterInvalidAvpBitComboSent>
<DiameterNoCommonSecurityReceived>0</DiameterNoCommonSecurityReceived>
<DiameterNoCommonSecuritySent>0</DiameterNoCommonSecuritySent>
<DiameterUserUnknownReceived>0</DiameterUserUnknownReceived>
<DiameterUserUnknownSent>0</DiameterUserUnknownSent>
<DiameterRatingFailedReceived>0</DiameterRatingFailedReceived>
<DiameterRatingFailedSent>0</DiameterRatingFailedSent>
<DiameterErrorInitialParametersReceived>0</DiameterErrorInitial
  ParametersReceived>
<DiameterErrorInitialParametersSent>2</DiameterErrorInitialParametersSent>

<RadiusSessionContextRemovedReceived>0</RadiusSessionContext
  RemovedReceived>

```



```

<RadiusSessionContextRemovedSent>0</RadiusSessionContextRemovedSent>
<RadiusInvalidEapPacketReceived>0</RadiusInvalidEapPacketReceived>
<RadiusInvalidEapPacketSent>0</RadiusInvalidEapPacketSent>
<RadiusUnsupportedAttributeReceived>0</RadiusUnsupportedAttributeReceived>

<RadiusUnsupportedAttributeSent>0</RadiusUnsupportedAttributeSent>
<RadiusMissingAttributeReceived>0</RadiusMissingAttributeReceived>
<RadiusMissingAttributeSent>0</RadiusMissingAttributeSent>
<RadiusNasIdMismatchReceived>0</RadiusNasIdMismatchReceived>
<RadiusNasIdMismatchSent>0</RadiusNasIdMismatchSent>
<RadiusInvalidRequestReceived>0</RadiusInvalidRequestReceived>
<RadiusInvalidRequestSent>0</RadiusInvalidRequestSent>
<RadiusUnsupportedServiceReceived>0</RadiusUnsupportedServiceReceived>
<RadiusUnsupportedServiceSent>0</RadiusUnsupportedServiceSent>
<RadiusUnsupportedExtensionReceived>0</RadiusUnsupportedExtensionReceived>

<RadiusUnsupportedExtensionSent>0</RadiusUnsupportedExtensionSent>
<RadiusInvalidAttributeValueReceived>0</RadiusInvalidAttributeValueReceived>

<RadiusInvalidAttributeValueSent>0</RadiusInvalidAttributeValueSent>
<RadiusAdministrativelyProhibitedReceived>0</RadiusAdministratively
  ProhibitedReceived>
<RadiusAdministrativelyProhibitedSent>0</RadiusAdministratively
  ProhibitedSent>
<RadiusRequestNotRoutableReceived>0</RadiusRequestNotRoutableReceived>
<RadiusRequestNotRoutableSent>0</RadiusRequestNotRoutableSent>
<RadiusSessionNotFoundReceived>0</RadiusSessionNotFoundReceived>
<RadiusSessionNotFoundSent>0</RadiusSessionNotFoundSent>
<RadiusSessionNotRemoveableReceived>0</RadiusSessionNotRemoveableReceived>

<RadiusSessionNotRemoveableSent>0</RadiusSessionNotRemoveableSent>
<RadiusProxyProcessingErrorReceived>0</RadiusProxyProcessingErrorReceived>

<RadiusProxyProcessingErrorSent>0</RadiusProxyProcessingErrorSent>
<RadiusResourcesUnavailableReceived>0</RadiusResourcesUnavailableReceived>

<RadiusResourcesUnavailableSent>0</RadiusResourcesUnavailableSent>
<RadiusRequestInitiatedReceived>0</RadiusRequestInitiatedReceived>
<RadiusRequestInitiatedSent>0</RadiusRequestInitiatedSent>
<RadiusMultiSessionSelectionUnsupportedReceived>0</RadiusMultiSession
  SelectionUnsupportedReceived>
<RadiusMultiSessionSelectionUnsupportedSent>0</RadiusMultiSessionSelection
  UnsupportedSent>
<RadiusLocationInfoRequiredReceived>0</RadiusLocationInfoRequiredReceived>

<RadiusLocationInfoRequiredSent>0</RadiusLocationInfoRequiredSent>
</Sample>
</ConnectionErrorStats>
</Statistics>

```

Quota Profile Statistics

The following examples show the request and response that are defined in the XSDs for the QuotaProfileStats tag.

Request

This request follows the **QueryOmStats > QuotaProfileStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<QueryOmStats>
  <StartTime>2001-12-31T12:00:00</StartTime>
  <EndTime>2001-12-31T12:15:00</EndTime>
  <QuotaProfileStats>
    <PolicyServer>PolicyServer</PolicyServer>
  </QuotaProfileStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > QuotaProfileStats** tag defined in the XSDs.

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <QuotaProfileStats>
    <Sample>
      <StartTime>2001-12-31T12:00:00</StartTime>
      <EndTime>2001-12-31T12:15:00</EndTime>
      <PolicyServer>PolicyServer</PolicyServer>
      <Name>QuotaProfileName</Name>
      <NumberOfTimesActivated>0</NumberOfTimesActivated>
      <NumberOfTimesVolumnThresholdReached>0</NumberOfTimesVolumnThresholdReached>

      <NumberOfTimesTimeThresholdReached>0</NumberOfTimesTimeThresholdReached>
      <NumberOfTimesEventThresholdReached>0</NumberOfTimesEventThresholdReached>
    </Sample>
  </QuotaProfileStats>
```

Individual statistics are defined as follows for Quota Profiles:

- Activated — COUNTER which tracks the number of times that a specific Quota Profile is activated.
- Volume Threshold Reached — COUNTER which tracks the number of times the configured volume threshold limit is reached for a specific Quota Profile.
- Time Threshold Reached — COUNTER which tracks the number of times the configured time threshold limit is reached for a specific Quota Profile.
- Event Threshold Reached — COUNTER which tracks the number of times the configured event threshold limit is reached for a specific Quota Profile.

Quota Reset Statistics

The following examples show the request and response that are defined in the XSDs for the QuotaResetStats tag.

Request

This request follows the **QueryOmStats > QuotaResetStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
  <QueryOmStats>
    <StartTime>2015-03-06T00:00:00Z</StartTime>
    <EndTime>2015-03-07T00:00:00Z</EndTime>
    <QuotaResetStats>
      <PolicyServer>MPE001</PolicyServer>
      <PolicyServer>MPE00X</PolicyServer>
      <Quota>DATA_LIM</Quota>
      <Quota>DAY_LIM</Quota>
    </QuotaResetStats>
  </QueryOmStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > QuotaResetStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- **DiameterGxActiveSessionOfReset**: All diameter Gx active sessions number at the beginning of specific quota plan resetting. It can be a fixed value during the quota resetting cycle. (For a monthly quota, it means all sessions over the month.)
- **ActualResetCount**: The actual resetting counter shows the count change per time interval (for example 5 minutes).
- **RARMessageCount**: RAR message counter shows the count change per time interval (for example 5 minutes).
- **PUAFailureCount**: PUA failure counters shows the count change per time interval (for example 5 minutes).

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <QuotaResetStats>
    <Sample>
      <StartTime>2015-03-06T00:00:00Z </StartTime>
      <EndTime>2015-03-06T00:15:00Z </EndTime>
      <PolicyServer>MPE001</PolicyServer>
      <Quota>DAY_LIM</Quota>
      <DiameterGxActiveSessionOfReset>0</DiameterGxActiveSessionOfReset>
      <ActualResetCount>0</ActualResetCount>
      <RARMessageCount>0</RARMessageCount>
      <PUAFailureCount>0</PUAFailureCount>
    </Sample>
    <Sample>
      <StartTime>2015-03-06T23:45:00Z </StartTime>
      <EndTime>2015-03-07T00:00:00Z </EndTime>
      <PolicyServer>MPE001</PolicyServer>
      <Quota>DATA_LIM</Quota>
      <DiameterGxActiveSessionOfReset>0</DiameterGxActiveSessionOfReset>
      <ActualResetCount>0</ActualResetCount>
      <RARMessageCount>0</RARMessageCount>
      <PUAFailureCount>0</PUAFailureCount>
    </Sample>
  </QuotaResetStats>
</Statistics>
```

Quota Reset All Statistics

The following examples show the request and response that are defined in the XSDs for the QuotaResetAllStats tag.

Note: The PolicyServer/Quota statistics are optional. If the PolicyServer/Quota does not exist or is empty, the CMP will not filter the result by PolicyServer/Quota.

Request

This request follows the **QueryOmStats > QuotaResetAllStats** tag defined in the XSDs.

The following is an example of a request for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
  <QueryOmStats>
    <StartTime>2015-03-06T00:00:00Z</StartTime>
    <EndTime>2015-03-07T00:00:00Z</EndTime>
    <QuotaResetAllStats>
      <PolicyServer>MPE001</PolicyServer>
      <PolicyServer>MPE0XX</PolicyServer>
    </QuotaResetStats>
  </QueryOmStats>
</QueryOmStats>
```

Response

The response to this request follows the **Statistics > QuotaResetAllStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- DiameterGxActiveSessionOfReset: All diameter Gx active sessions number at the beginning of specific quota plan resetting. It can be a fixed value during the quota resetting cycle. (For a monthly quota, it means all sessions over the month.)
- ActualResetCount: The actual resetting counter shows the count change per time interval (for example 5 minutes).
- RARMessageCount: RAR message counter shows the count change per time interval (for example 5 minutes).
- PUAFailureCount: PUA failure counters shows the count change per time interval (for example 5 minutes).

The following is an example of a response for a single policy server:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <QuotaResetAllStats>
    <Sample>
      <StartTime>2015-03-06T00:00:00Z </StartTime>
      <EndTime>2015-03-06T00:15:00Z </EndTime>
      <PolicyServer>MPE001</PolicyServer>
      <DiameterGxActiveSessionOfReset>0</DiameterGxActiveSessionOfReset>
      <ActualResetCount>0</ActualResetCount>
      <RARMessageCount>0</RARMessageCount>
      <PUAFailureCount>0</PUAFailureCount>
    </Sample>
  </QuotaResetAllStats>
</Statistics>
```

```

    <Sample>
      <StartTime>2015-03-06T23:45:00Z </StartTime>
      <EndTime>2015-03-07T00:00:00Z </EndTime>
      <PolicyServer>MPE0XX</PolicyServer>
      <DiameterGxActiveSessionOfReset>0</DiameterGxActiveSessionOfReset>
      <ActualResetCount>0</ActualResetCount>
      <RARMessageCount>0</RARMessageCount>
      <PUAFailureCount>0</PUAFailureCount>
    </Sample>
  </QuotaResetAllStats>
</Statistics>

```

Interval Statistics/PCRF Session License Tracking and Reporting

The following XML requests and responses apply to interval statistics and PCRF session license tracking and reporting. The Interval Stats tag allows for the collection of specific maximum values for some counters over a time interval of 15 minutes. By using the OSS/ data collection feature maximums can be collected for each 15-minute interval of a day, over a 30-day period, to determine peak usage times.

The following examples show the request and response that are defined in the XSDs for the IntervalStats tag.

MPE Request

This request follows the **QueryOmStats > IntervalStats** tag defined in the XSDs.

The following is an example of this request for an MPE.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-08-01T10:00:01Z</StartTime>
    <IntervalStats>
      <PolicyServer>name</PolicyServer> (policy server name, if this field
      does not exist, all policy servers are included in response)
    </IntervalStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Where the **TIMESTAMP** is a time stamp in the form:

YYYY-MM-DD-THH:MM:SSZ

MPE Response

The response to this MPE request follows the **Statistics > IntervalStats** tag defined in the XSDs.

Where:

- **IntervalStartTime** — The time when this sub-system began collecting the data presented. If this is the first instance of the sub-system collecting data, this value may be N/A.
- **ConfiguredLength** — This value is always 900 seconds, which is 15 minutes.
- **ActualLength** — The length of the interval. Normally, this is the same value as ConfiguredLength, however there are two cases where these values will differ:

1. Cluster has just started and no data is available (ActualLength = 0)

2. Cluster has started and an interval completed but the software did not start on a quarter boundary (e.g. ActualLength = nnn where nnn is any number between 0 and 900. If the software started 200 seconds after the 15-min boundary, the when the interval is completed, the ActualLength = 700).
- IsComplete — If the ConfiguredLength has completed, then the value is true. If not, then the value is false.
 - IntervalMaxTransactionsPerSecond — The maximum value of the statistic MaxTransactionsPerSecond for the interval reported. As with MaxTransactionsPerSecond, this count does not include SH traffic.
 - IntervalMaxMRABindingCount — The maximum value of the statistic MaxMRABindingCount for the interval reported. This value is 0 on MPES.
 - IntervalMaxSessionCount — The maximum value of the statistic MaxSessionCount for the interval reported.
 - IntervalMaxPDNConnectionCount — The maximum value of the statistic MaxPDNConnectionCount for the interval reported.

For example:

```
<?xml version="1.0" ?>
<Statistics>
  <IntervalStats>
    <Sample>
      <StartTime>2011-05-04T13:23:52Z</StartTime>
      <EndTime>2011-05-04T13:23:52Z</EndTime>
      <PolicyServer>testmpe</PolicyServer>
      <IntervalStartTime>2001-05-04T13:15:00Z</IntervalStartTime>
      <ConfiguredLength>900</ConfiguredLength>
      <ActualLength>12</ActualLength>
      <IsComplete>>false</IsComplete>
      <IntervalMaxTransactionsPerSecond>5</IntervalMaxTransactionsPerSecond>
      <IntervalMaxMRABindingCount>16</IntervalMaxMRABindingCount>
      <IntervalMaxSessionCount>12</IntervalMaxSessionCount>
      <IntervalMaxPDNConnectionCount>12</IntervalMaxPDNConnectionCount>
    </Sample>
    <Sample>
      <StartTime>2011-05-04T13:23:52Z</StartTime>
      <EndTime>2011-05-06T05:57:36Z</EndTime>
      <PolicyServer>testmpe</PolicyServer>
      <IntervalStartTime>2001-08-01T10:00:01Z</IntervalStartTime>
      <ConfiguredLength>900</ConfiguredLength>
      <ActualLength>12</ActualLength>
      <IsComplete>>false</IsComplete>
      <IntervalMaxTransactionsPerSecond>5</IntervalMaxTransactionsPerSecond>
      <IntervalMaxMRABindingCount>16</IntervalMaxMRABindingCount>
      <IntervalMaxSessionCount>12</IntervalMaxSessionCount>
      <IntervalMaxPDNConnectionCount>12</IntervalMaxPDNConnectionCount>
    </Sample>
  </IntervalStats>
</Statistics>
```

MRA Request

This request follows the **QueryOmStats > IntervalStats** tag defined in the XSDs.

The following is an example of this request for an MRA.

Where:

- **IntervalStartTime** — The time when this sub-system began collecting the data presented. If this is the first instance of the sub-system collecting data, this value may be N/A.
- **ConfiguredLength** — This value is always 900 seconds, which is 15 minutes.
- **ActualLength** — The length of the interval. Normally, this is the same value as **ConfiguredLength**, however there are two cases (documented above) where these values will differ:
 1. Cluster has just started and no data is available (**ActualLength** = 0)
 2. Cluster has started and an interval completed but the software did not start on a quarter boundary (e.g. **ActualLength** = nnn where nnn is any number between 0 and 900. If the software started 200 seconds after the 15-min boundary, the when the interval is completed, the **ActualLength** = 700).
- **IsComplete** — If the **ConfiguredLength** has completed, then the value is true. If not, then the value is false.
- **IntervalMaxTransactionsPerSecond** — The maximum value of the statistic **MaxTransactionsPerSecond** for the interval reported.
- **IntervalMaxMRABindingCount** — The maximum value of the statistic **MaxMRABindingCount** for the interval reported.
- **IntervalMaxSessionCount** — The maximum value of the statistic **MaxSessionCount** for the interval reported.
- **IntervalMaxPDNConnectionCount** — The maximum value of the statistic **MaxPDNConnectionCount** for the interval reported.

For example:

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2001-08-01T10:00:01Z</StartTime>
    <IntervalMraStats>
      <MRA>testmra</MRA>
    </IntervalMraStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

MRA Response

The response to this MRA request follows the **Statistics > IntervalStats** tag defined in the XSDs. For example:

```
<?xml version="1.0" ?>
<Statistics>
  <IntervalMraStats>
    <Sample>
      <StartTime>2011-05-04T13:23:52Z</StartTime>
      <EndTime>2011-05-06T08:15:26Z</EndTime>
      <MRA>testmra</MRA>
      <IntervalStartTime>2011-04-04 09:23:52.0</IntervalStartTime>
      <ConfiguredLength>900</ConfiguredLength>
      <ActualLength>12</ActualLength>
      <IsComplete>>false</IsComplete>
      <IntervalMaxTransactionsPerSecond>5</IntervalMaxTransactionsPerSecond>
      <IntervalMaxMRABindingCount>16</IntervalMaxMRABindingCount>
      <IntervalMaxSessionCount>12</IntervalMaxSessionCount>
      <IntervalMaxPDNConnectionCount>12</IntervalMaxPDNConnectionCount>
    </Sample>
  </IntervalMraStats>
</Statistics>
```

```
</IntervalMraStats>  
</Statistics>
```


Operational Measurement Requests for SNET

Topics:

- *Query PCRF Active Alarm.....178*
- *Query for HA Server Status and Running Processes.....179*
- *Diameter KPI Real-Time Statistics.....181*
- *Diameter Connection Status.....184*
- *Diameter Application Function Statistics.....186*
- *Diameter AF Binding Statistics.....190*
- *Diameter AF Peer Statistics.....191*
- *Diameter AF Session Service ID Statistics.....196*
- *Diameter Policy Charging Enforcement Function Statistics.....197*
- *Diameter PCEF Peer Statistics.....202*
- *Diameter Gx Session Statistics.....207*
- *Diameter Message Error Statistics.....208*
- *Query Network Elements.....209*
- *Diameter PCEF Session Statistics.....211*
- *Diameter PCEF Session APN Statistics.....212*

This chapter defines the various Operational Measurements (OM) groups and the individual OM statistics that comprise them for SNET. For several of the more generic statistics, the instrumentation on the Multimedia Policy Engine (MPE) and the Multi-Protocol Routing Agent (MRA) may differ by protocol, and therefore specific statistics may increment differently across those protocols.

Query PCRF Active Alarm

The following examples show the request and response that are defined in the XSDs for the ActiveAlarm tag.

Request

This request follows the **ConfigurationData > ActiveAlarm** tag defined in the XSDs.

The following is an example of a request for of time stamped alarm notifications for Policy Management systems.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryActiveAlarm>
  </QueryActiveAlarm>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > ActiveAlarm** tag defined in the XSDs.

The following is an example XML response to a ActiveAlarm tag request:

```
<?xml version="1.0" encoding="UTF-8"?>
<ConfigurationData>
  <ActiveAlarm>
    <PolicyServer>MPE</PolicyServer>
    <Hostname>kli-63-mpe</Hostname>
    <ServerIP>10.60.25.63</ServerIP>
    <ServerType>MPE</ServerType>
    <Severity>Critical</Severity>
    <AlarmID>31215</AlarmID>
    <InstanceID>1</InstanceID>
    <Description>
      A process is consuming excessive system resources
    </Description>
    <Time>2009-08-19T19:51:28Z</Time>
    <Detail>
      GN_ABVTHRESH/WRN Metric System.RAM_UtilPct above critical threshold
    </Detail>
  </ActiveAlarm>
</ConfigurationData>
```

Individual statistics are defined for the PCRF active alarm are:

- **PolicyServer:** The name of the MPE.
- **Hostname:** Host name of blade server.
- **ServerIP:** The IP address of blade server.
- **ServerType:** The type of PCRF with support type MPE and MRA.
- **Severity:** The alarm severity support. (From high to low: Critical, Major and Minor.)
- **AlarmID:** The identity of alarm event type.
- **InstanceID:** The identity of the alarm event.

- **Time:** The time the alarm last occurred.

Query for HA Server Status and Running Processes

The following examples show the request and response that are defined in the XSDs for the QueryHAServer tag.

Request

This request follows the **ConfigurationData > QueryHAServer** tag defined in the XSDs.

The following is an example of a request for HA server status for Policy Management systems.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryHAServer>
  </QueryHAServer>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > QueryHAServer** tag defined in the XSDs.

The following is an example XML response to a QueryHAServer tag request:

```
<?xml version="1.0" encoding="UTF-8"?>
<ConfigurationData>
  <Server>
    <Cluster>CMP Site1 Cluster</Cluster>
    <ServerIP>10.60.25.69</ServerIP>
    <Hostname>kli-69-cmp</Hostname>
    <BladeStatus>Active</BladeStatus>
    <CPUUtilizationPercentage>24</CPUUtilizationPercentage>
    <MemoryUtilizationPercentage>72</MemoryUtilizationPercentage>
    <DiskUtilizationPercentage>3</DiskUtilizationPercentage>
    <FailureCount>14</FailureCount>
    <UpTimeMillis>7578</UpTimeMillis>
    <Processes>
      <Process>comcolMonitor(28946)</Process>
      <Process>mysqlmgr(28950)</Process>
      <Process>tomcat(28953)</Process>
      <Process>wbsync(28957)</Process>
      <Process>routeMgr(28965)</Process>
      <Process>dc(28967)</Process>
      <Process>qp_ipmgr(23321)</Process>
      <Process>run_qp_networkmgr(23325)</Process>
      <Process>qpcfgd(23328)</Process>
    </Processes>
  </Server>
  <Server>
    <PolicyServer>MPE</PolicyServer>
    <Cluster>cluster-mpe</Cluster>
    <ServerIP>10.60.25.63</ServerIP>
    <Hostname>kli-63-mpe</Hostname>
    <BladeStatus>Active</BladeStatus>
    <CPUUtilizationPercentage>24</CPUUtilizationPercentage>
```

```

    <MemoryUtilizationPercentage>72</MemoryUtilizationPercentage>
    <DiskUtilizationPercentage>3</DiskUtilizationPercentage>
    <FailureCount>14</FailureCount>
    <UpTimeMillis>7578</UpTimeMillis>
    <Processes>
      <Process>comcolMonitor(13540)</Process>
      <Process>policy(13544)</Process>
      <Process>tomcat(13559)</Process>
      <Process>wbsync(13563)</Process>
      <Process>routeMgr(13565)</Process>
      <Process>qp_ipmgr(23321)</Process>
      <Process>run_qp_networkmgr(23325)</Process>
      <Process>qpcfgd(23328)</Process>
    </Processes>
  </Server>
  <Server>
    <MRA>MRA</MRA>
    <Cluster>cluster-mra</Cluster>
    <ServerIP>10.60.25.66</ServerIP>
    <Hostname>kli-66-mra</Hostname>
    <BladeStatus>Active</BladeStatus>
    <CPUUtilizationPercentage>24</CPUUtilizationPercentage>
    <MemoryUtilizationPercentage>72</MemoryUtilizationPercentage>
    <DiskUtilizationPercentage>3</DiskUtilizationPercentage>
    <FailureCount>14</FailureCount>
    <UpTimeMillis>7578</UpTimeMillis>
    <Processes>
      <Process>comcolMonitor(10786)</Process>
      <Process>tomcat(10789)</Process>
      <Process>routing-agent(10800)</Process>
      <Process>wbsync(10804)</Process>
      <Process>routeMgr(10825)</Process>
      <Process>qp_ipmgr(23321)</Process>
      <Process>run_qp_networkmgr(23325)</Process>
      <Process>qpcfgd(23328)</Process>
    </Processes>
  </Server>
  <Server>
    <MRA>MRA</MRA>
    <Cluster>cluster-mra</Cluster>
    <Hostname>kli-39-mra</Hostname>
    <ServerIP>10.60.26.39</ServerIP>
    <BladeStatus>Stby</BladeStatus>
    <CPUUtilizationPercentage>63</CPUUtilizationPercentage>
    <MemoryUtilizationPercentage>101</MemoryUtilizationPercentage>
    <DiskUtilizationPercentage>2</DiskUtilizationPercentage>
    <FailureCount>2</FailureCount>
    <UpTimeMillis>65736</UpTimeMillis>
    <Processes>
      <Process>comcolMonitor(23319)</Process>
      <Process>tomcat(23321)</Process>
      <Process>routing-agent(23325)</Process>
      <Process>wbsync(23328)</Process>
      <Process>qp_ipmgr(23321)</Process>
      <Process>run_qp_networkmgr(23325)</Process>
      <Process>qpcfgd(23328)</Process>
    </Processes>
  </Server>
  <Server>
    <Cluster>med</Cluster>
    <MediationServer>med</MediationServer>
    <Hostname>p70-med-13-94</Hostname>
    <ServerIP>10.113.13.94</ServerIP>
    <BladeStatus>Active</BladeStatus>

```

```

    <CPUUtilizationPercentage>26</CPUUtilizationPercentage>
    <MemoryUtilizationPercentage>49</MemoryUtilizationPercentage>
    <DiskUtilizationPercentage>9</DiskUtilizationPercentage>
    <FailureCount>7</FailureCount>
    <UpTimeMillis>241996</UpTimeMillis>
    <Processes>
      <Process>tomcat(22710)</Process>
      <Process>mediation(22711)</Process>
      <Process>qpcfgd(22712)</Process>
      <Process>qp_ipmgr(22713)</Process>
      <Process>comcolMonitor(22714)</Process>
      <Process>routeMgr(22715)</Process>
      <Process>run_qp_networkmgr(22716)</Process>
      <Process>wbsync(22717)</Process>
    </Processes>
  </Server>
</ConfigurationData>

```

Individual statistics are defined for HA server status are:

- Cluster: The identity of the group to which the HA servers belong.
- PolicyServer: The name of the associate MPE when this blade server belongs to an MPE cluster.
- MRA: The name of the associate MRA when this blade server belongs to an MRA cluster.
- MediationServer: The name of the associate MDF when this blade server belongs to the Mediation cluster.
- HostName: The host name of the blade server.
- ServerIP: IP address of blade server.
- BladeStatus: The HA status of blade server. The status types are: Support Active ,Stby (StandBy) and OOS (Out of Service) options.
- CPUUtilizationPercentage: The percentage of CPU usage.
- MemoryUtilizationPercentage: The percentage of all memory usage including physical memory and virtual memory.
- DiskUtilizationPercentage: The percentage of disk usage.
- FailureCount: HA counter that shows service failure.
- UpTimeMillis: The number of seconds that indicate how long PCRF services have ran since it started.
- Processes: The PCRF processes running on the server.

Diameter KPI Real-Time Statistics

The following examples show the request and response that are defined in the XSDs for the KPIRealTimeStats tag.

Request

This request follows the **QueryOmStats > DiameterRealTimeStats** tag defined in the XSDs.

The following is an example of a request for a multi-site system level summary of performance and operational health indicators.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>

```

```

<QueryOmStats>
  <KpiRealTimeStats>
  </KpiRealTimeStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterKPIRealTimeStats** tag defined in the XSDs.

The following is an example XML response to a DiameterRealTimeStats tag request:

```

<?xml version='1.0' ?>
<Statistics>
  <KpiRealTimeStats>
    <Sample>
      <PolicyServer>MPE</PolicyServer>
      <Cluster>cluster-mpe</Cluster>
      <TransactionStartCount>0</TransactionStartCount>
      <TransactionEndCount>0</TransactionEndCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <CurrentTransactionsPerSecond>0</CurrentTransactionsPerSecond>
      <MaxTransactionsPerSecond>0</MaxTransactionsPerSecond>
      <CurrentTPSPercentageOfCapacity>0</CurrentTPSPercentageOfCapacity>
      <MaxTPSPercentageOfCapacity>0</MaxTPSPercentageOfCapacity>
      <CurrentLTETTransactionsPerSecond>0</CurrentLTETTransactionsPerSecond>
      <CurrentEHRPDTransactionsPerSecond>0</CurrentEHRPDTransactionsPerSecond>
      <CurrentRXTransactionsPerSecond>0</CurrentRXTransactionsPerSecond>
      <LoadSheddingStatus>0</LoadSheddingStatus>
      <LoadSheddingEfficiency>0</LoadSheddingEfficiency>
      <LoadSheddingDistressCount>0</LoadSheddingDistressCount>
      <CurrentMRABindingCount>0</CurrentMRABindingCount>
      <MaxMRABindingCount>0</MaxMRABindingCount>
      <TotalMRABindingCount>0</TotalMRABindingCount>
      <CurrentSessionCount>0</CurrentSessionCount>
      <MaxSessionCount>0</MaxSessionCount>
      <CurrentPDNConnectionCount>0</CurrentPDNConnectionCount>
      <MaxPDNConnectionCount>0</MaxPDNConnectionCount>

      <CurrentPDNConnectionPercentageOfCapacity>0</CurrentPDNConnectionPercentageOfCapacity>

      <MaxPDNConnectionPercentageOfCapacity>0</MaxPDNConnectionPercentageOfCapacity>
      <CurrentSessionPercentageOfCapacity>0</CurrentSessionPercentageOfCapacity>

      <MaxSessionPercentageOfCapacity>0</MaxSessionPercentageOfCapacity>
      <CurrentMPEConnectionCount>0</CurrentMPEConnectionCount>
      <ConfiguredMPEConnectionCount>0</ConfiguredMPEConnectionCount>
      <CurrentDRMAConnectionCount>0</CurrentDRMAConnectionCount>
      <ConfiguredDRMAConnectionCount>0</ConfiguredDRMAConnectionCount>
      <CurrentConnectedNECount>0</CurrentConnectedNECount>
      <ConfiguredNECount>0</ConfiguredNECount>
      <CurrentMRAConnectionCount>0</CurrentMRAConnectionCount>
      <ConfiguredMRAConnectionCount>0</ConfiguredMRAConnectionCount>
      <CurrentSPRConnectionCount>0</CurrentSPRConnectionCount>
      <ConfiguredSPRConnectionCount>1</ConfiguredSPRConnectionCount>
      <CurrentProtocolErrorSentCount>0</CurrentProtocolErrorSentCount>
      <CurrentProtocolErrorReceivedCount>0</CurrentProtocolErrorReceivedCount>

      <CurrentMRABindingPercentageOfCapacity>0</CurrentMRABindingPercentageOfCapacity>
    </Sample>
  </KpiRealTimeStats>
</Statistics>

```

```

    <MaxMRABindingPercentageOfCapacity>0</MaxMRABindingPercentageOfCapacity>
  </Sample>
</KpiRealTimeStats>
</Statistics>

```

Individual statistics are defined for performance and operational health are:

- **PolicyServer:** The name of the MPE.
- **Cluster:** The identity of the HA servers group.
- **TransactionStartCount:** The Diameter ID, (if known), or IP address of the remote system.
- **TransactionEndCount:** The type of connection.
- **MessagesInCount:** The status of the connection (the possible values are protocol-specific).
- **MessagesOutCount:** The timestamp when the connection reached its current state (N/A if the connection has never been established).
- **CurrentTransactionsPerSecond:** The number of current Transactions Per Second (TPS).

Note: A method of measuring how quickly a network can transmit and receive data. Capacities listed with "TPS" units involve the maximum of the receive rate and the transmit rate, and the worst-case assumption is that the transmit and receive rates are the same. Under the TU model, transaction units per second are calculated with the total transaction unit value and the advertised card capacity. This counter is reset if the cluster is restarted.

- **MaxTransactionsPerSecond:** The number of maximum Transaction Per Second (TPS).
- **CurrentTPSPercentageOfCapacity:** The percentage of Transactions Per Second (TPS) capacity for maximum TPS.
- **MaxTPSPercentageOfCapacity:** The percentage of Transactions Per Second (TPS) capacity for maximum TPS.
- **CurrentLTETransactionsPerSecond:** The number of LTE Transactions Per Second (TPS).
- **CurrentEHRPDTransactionsPerSecond:** The number of EHRPD Transactions Per Second (TPS).
- **CurrentRXTransactionsPerSecond:** The number of RX Transactions Per Second (TPS).
- **LoadSheddingStatus:** The number of protocol error messages that have been received from the remote system.
- **LoadSheddingEfficiency:** The number of diameter load shedding efficiency.
- **LoadSheddingDistressCount:** The number of diameter load shedding distress count.
- **CurrentMRABindingCount:** The number of binding count on MRA.
- **MaxMRABindingCount:** The number of maximum binding count on MRA.
- **TotalMRABindingCount:** The number of total MRA binding count on MRA.
- **CurrentSessionCount:** The number of session current count.
- **MaxSessionCount:** The number of session maximum count.
- **CurrentPDNConnectionCount:** The number of the packet data network (PDN) connection current count.
- **MaxPDNConnectionCount:** The number of the packet data network (PDN) connection maximum count.
- **CurrentPDNConnectionPercentageOfCapacity:** The number of the packet data network (PDN) connection count.
- **MaxPDNConnectionPercentageOfCapacity:** The number of the packet data network (PDN) connection count.
- **CurrentSessionPercentageOfCapacity:** The percentage of all session capacity for connection session.
- **MaxSessionPercentageOfCapacity:** The maximum percentage of all session capacity for connection session.

- **CurrentMPEConnectionCount:** The number of current MPE connection counter.
- **ConfiguredMPEConnectionCount:** The number of configured MPE connections.
- **CurrentDRMAConnectionCount:** The number of current disturber router manage agent (DRMA) connections.
- **ConfiguredDRMAConnectionCount:** The number of configured disturber router manage agent (DRMA) connections.
- **CurrentConnectedNECount:** The number of Network Element connections current count.
- **ConfiguredNECount:** The number of Network Element connections configured count.
- **CurrentMRAConnectionCount:** The number of Multi-protocols Routing Agent (MRA) connections current count.
- **ConfiguredMRAConnectionCount:** The number of Multi-protocols Routing Agent (MRA) connections configured count.
- **CurrentSPRConnectionCount:** The number of Subscriber Provisioning Repository (SPR) connections current count.
- **ConfiguredSPRConnectionCount:** The number of Subscriber Provisioning Repository (SPR) connections configured count.
- **CurrentProtocolErrorSentCount:** The number of protocol error messages that have been sent from the remote system.
- **CurrentProtocolErrorReceivedCount:** The number of protocol error messages that have been received from the remote system.
- **CurrentMRABindingPercentageOfCapacity:** The percentage of the total MRA Binding capacity for current usage.
- **MaxMRABindingPercentageOfCapacity:** The percentage of the total MRA Binding capacity for maximum usage.

Diameter Connection Status

The following examples show the request and response that are defined in the XSDs for the `ConnectionRealTimeStats` tag.

Request

This request follows the `QueryOmStats > ConnectionRealTimeStats` tag defined in the XSDs.

The following is an example of a request for an aggregate statistic of connections maintained by managed Policy Management systems.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <ConnectionRealTimeStats>
      <PolicyServer>mpe17-41</PolicyServer>
      <Name>ggsn1</Name>
    </ConnectionRealTimeStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

- **PolicyName:** Name of the connected MPE.

- **Name:** For the AF connection, the name is connected application's diameter identity. For PCEF, the connection name is connected network element's name.

Response

The response to this request follows the **Statistics > ConnectionRealTimeStats** tag defined in the XSDs.

The following is an example XML response to a ConnectionRealTimeStats tag request:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <ConnectionRealTimeStats>
    <Sample>
      <MPE>MPE</MPE>
      <PolicyServer>mpe17-41</PolicyServer>
      <RemoteIdentity>pgw1.oracle.com,pgw2.oracle.com</RemoteIdentity>
      <RemoteName>PGW</RemoteName>
      <Type>Diameter PCEF</Type>
      <Status>down</Status>
      <InternalIdentity></InternalIdentity>
      <RegisteredPeer>true</RegisteredPeer>
      <ConnectAddress>10.60.28.85</ConnectAddress>
      <ConnectPort>36749</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <ConnectCount>4</ConnectCount>
      <ActiveConnectionCount>0</ActiveConnectionCount>
      <ConnectTime>Wed Feb 27 21:26:52 EST 2013</ConnectTime>
      <DisconnectTime>Thu Feb 28 01:43:10 EST 2013</DisconnectTime>
      <MessageInCount>0</MessageInCount>
      <MessageOutCount>0</MessageOutCount>
      <MessageErrorInCount>0</MessageErrorInCount>
      <MessageErrorOutCount>0</MessageErrorOutCount>
    </Sample>
  </ConnectionRealTimeStats>
</Statistics>
```

Individual statistics are defined for the connection status are:

- **Server:** The name of the associated system.
- **Server Type:** Shows the type of server used. (MPE ((Multimedia Policy Engine) 0 or MRA ((Multi-Protocol Routing Agent))
- **Remote Identity:** The Diameter ID.
- **Type:** The connection protocol type.
- **Status:** The status of the connection. (The possible values are protocol-specific).
- **UpConnectTime:** The timestamp when the up connection reached its current state (N/A if the connection has never been established).
- **DownConnectTime:** The timestamp when the down connection reached its current state. (N/A if the connection has never been established).
- **ConnectCount:** The number of times that the connection has been re-established.

Note: This counter is reset if the cluster is restarted.

- **MessagesSentCount:** The number of Diameter or RADIUS protocol messages that have been sent to the remote system.
- **MessagesRecievedCount:** The number of protocol messages that have been received from the remote system.

- **MessagesErrorOutCount:** The number of protocol error messages that have been sent to the remote system.
- **MessagesErrorInCount:** The number of protocol error messages that have been received from the remote system.

Diameter Application Function Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterAfStats tag.

Request

This request follows the **QueryOmStats > DiameterAfStats** tag defined in the XSDs.

The following is an example of a request for a policy server 'MPE' Rx messages statistic within the system.

```
<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2013-02-27T06:10:00Z</StartTime>
    <EndTime>2013-02-27T06:15:00Z</EndTime>
    <DiameterAfStats>
      <PolicyServer>MPE</PolicyServer>
    </DiameterAfStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

This request follows the **QueryOmStats > DiameterAfStats** tag defined in the XSDs.

The following is an example of a request for multi-routing agent server 'MRA' Rx messages statistic within the system.

```
<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2013-02-27T06:10:00Z</StartTime>
    <EndTime>2013-02-27T06:15:00Z</EndTime>
    <DiameterMraAfStats>
      <MRA>MRA</MRA>
    </DiameterMraAfStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterAfStats** tag defined in the XSDs.

The following is an example XML response to a DiameterAfStats tag request:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterAfStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
```

```

<PolicyServer>MPE</PolicyServer>
<IsComplete>>true</IsComplete>
<PendingConnectionsCount>0</PendingConnectionsCount>
<CurrentConnectionsCount>1</CurrentConnectionsCount>
<MessagesInCount>0</MessagesInCount>
<MessagesOutCount>0</MessagesOutCount>
<ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
<ASRMessagesSentCount>0</ASRMessagesSentCount>
<ASRMessagesTimeoutCount>0</ASRMessagesTimeoutCount>
<ASASuccessMessagesReceivedCount>0</ASASuccessMessagesReceivedCount>
<ASASuccessMessagesSentCount>0</ASASuccessMessagesSentCount>
<ASAFailureMessagesReceivedCount>0</ASAFailureMessagesReceivedCount>
<ASAFailureMessagesSentCount>0</ASAFailureMessagesSentCount>
<RARMessagesReceivedCount>0</RARMessagesReceivedCount>
<RARMessagesSentCount>0</RARMessagesSentCount>
<RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<STRMessagesReceivedCount>0</STRMessagesReceivedCount>
<STRMessagesSentCount>0</STRMessagesSentCount>
<STRMessagesTimeoutCount>0</STRMessagesTimeoutCount>
<STASuccessMessagesReceivedCount>0</STASuccessMessagesReceivedCount>
<STASuccessMessagesSentCount>0</STASuccessMessagesSentCount>
<STAFailureMessagesReceivedCount>0</STAFailureMessagesReceivedCount>
<STAFailureMessagesSentCount>0</STAFailureMessagesSentCount>
<AARMessagesReceivedCount>0</AARMessagesReceivedCount>
<AARMessagesSentCount>0</AARMessagesSentCount>
<AARMessagesTimeoutCount>0</AARMessagesTimeoutCount>
<AARInitialMessagesReceivedCount>0</AARInitialMessagesReceivedCount>
<AARInitialMessagesSentCount>0</AARInitialMessagesSentCount>
<AARModificationMessagesReceivedCount>0</AARModificationMessagesReceivedCount>
<AARModificationMessagesSentCount>0</AARModificationMessagesSentCount>
<AAASuccessMessagesReceivedCount>0</AAASuccessMessagesReceivedCount>
<AAASuccessMessagesSentCount>0</AAASuccessMessagesSentCount>
<AAAFailureMessagesReceivedCount>0</AAAFailureMessagesReceivedCount>
<AAAFailureMessagesSentCount>0</AAAFailureMessagesSentCount>
<RxPcmmMessagesTimeoutCount>0</RxPcmmMessagesTimeoutCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
<PeerOkayCount>1</PeerOkayCount>
<PeerDownCount>0</PeerDownCount>
<PeerSuspectCount>0</PeerSuspectCount>
<PeerReopenCount>0</PeerReopenCount>
<AFBindingTryCount>0</AFBindingTryCount>
<AFBindingSuccessCount>0</AFBindingSuccessCount>
<AFBindingFailedCount>0</AFBindingFailedCount>
<PCEFActiveSession>3002</PCEFActiveSession>
</Sample>
</DiameterAfStats>
</Statistics>

```

The following is an example XML response to a DiameterMraAfStats tag request:

```

<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterMraAfStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
      <MRA>MRA</MRA>
    </Sample>
  </DiameterMraAfStats>
</Statistics>

```

```

<IsComplete>true</IsComplete>
<PendingConnectionsCount>0</PendingConnectionsCount>
<CurrentConnectionsCount>2</CurrentConnectionsCount>
<MessagesInCount>0</MessagesInCount>
<MessagesOutCount>0</MessagesOutCount>
<ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
<ASRMessagesSentCount>0</ASRMessagesSentCount>
<ASRMessagesTimeoutCount>0</ASRMessagesTimeoutCount>
<ASASuccessMessagesReceivedCount>0</ASASuccessMessagesReceivedCount>
<ASASuccessMessagesSentCount>0</ASASuccessMessagesSentCount>
<ASAFailureMessagesReceivedCount>0</ASAFailureMessagesReceivedCount>
<ASAFailureMessagesSentCount>0</ASAFailureMessagesSentCount>
<RARMessagesReceivedCount>0</RARMessagesReceivedCount>
<RARMessagesSentCount>0</RARMessagesSentCount>
<RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<STRMessagesReceivedCount>0</STRMessagesReceivedCount>
<STRMessagesSentCount>0</STRMessagesSentCount>
<STRMessagesTimeoutCount>0</STRMessagesTimeoutCount>
<STASuccessMessagesReceivedCount>0</STASuccessMessagesReceivedCount>
<STASuccessMessagesSentCount>0</STASuccessMessagesSentCount>
<STAFailureMessagesReceivedCount>0</STAFailureMessagesReceivedCount>
<STAFailureMessagesSentCount>0</STAFailureMessagesSentCount>
<AARMessagesReceivedCount>0</AARMessagesReceivedCount>
<AARMessagesSentCount>0</AARMessagesSentCount>
<AARMessagesTimeoutCount>0</AARMessagesTimeoutCount>
<AARInitialMessagesReceivedCount>0</AARInitialMessagesReceivedCount>
<AARInitialMessagesSentCount>0</AARInitialMessagesSentCount>
<AARModificationMessagesReceivedCount>0</AARModificationMessagesReceivedCount>
<AARModificationMessagesSentCount>0</AARModificationMessagesSentCount>
<AAASuccessMessagesReceivedCount>0</AAASuccessMessagesReceivedCount>
<AAASuccessMessagesSentCount>0</AAASuccessMessagesSentCount>
<AAAFailureMessagesReceivedCount>0</AAAFailureMessagesReceivedCount>
<AAAFailureMessagesSentCount>0</AAAFailureMessagesSentCount>
<RxPcmmMessagesTimeoutCount>0</RxPcmmMessagesTimeoutCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
<PeerOkayCount>1</PeerOkayCount>
<PeerDownCount>0</PeerDownCount>
<PeerSuspectCount>0</PeerSuspectCount>
<PeerReopenCount>0</PeerReopenCount>
<AFBindingTryCount>0</AFBindingTryCount>
<AFBindingSuccessCount>0</AFBindingSuccessCount>
<AFBindingFailedCount>0</AFBindingFailedCount>
<PCEFActiveSession>3002</PCEFActiveSession>
</Sample>
</DiameterMraAfStats>
</Statistics>

```

Individual statistics are defined for the AF adaptor are:

- **PolicyServer:** The name of the MPE.
- **MRA:** The name of the MRA
- **IsComplete:** Shows if the statistics are complete.
- **PendingConnectionsCount:** The number of pending connections.
- **CurrentConnectionsCount:** The number of current connections.
- **MessagesInCount:** The number of total messages received.

- **MessagesOutCount:** The number of total messages sent.
- **ASRMessagesReceivedCount:** The number of Abort Session Requests (ASR) messages received.
- **ASRMessagesSentCount:** The number of Abort Session Requests (ASR) messages sent.
- **ASRMessagesTimeoutCount:** The number of Abort Session Request messages sent where an ASA message was not received in a predefined amount of time.
- **ASASuccessMessagesReceivedCount:** The number of Abort Session Answers (ASA) messages received.
- **ASASuccessMessagesSentCount:** The number of Abort Session Answers (ASA) messages sent.
- **ASAFailureMessagesReceivedCount:** The number of Abort Session Answers (ASA) messages with failed reception.
- **ASAFailureMessagesSentCount:** The number of Abort Session Answers (ASA) messages sent with failed sending.
- **RARMessagesReceivedCount:** The number of ReAuthorization Request (RAR) messages received.
- **RARMessagesSentCount:** The number of ReAuthorization Request (RAR) messages sent.
- **RARMessagesTimeoutCount:** The number of ReAuthorization Request (RAR) messages sent where an RAA message was not received in a predefined amount of time.
- **RAASuccessMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages successfully received.
- **RAASuccessMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages successfully sent.
- **RAAFailureMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages with failed reception.
- **RAAFailureMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages with failed sending.
- **STRMessagesReceivedCount:** The number of Session Termination Requests (STR) messages received.
- **STRMessagesSentCount:** The number of Session Termination Requests (STR) messages sent.
- **STRMessagesTimeoutCount:** The number of Session Termination Requests (STR) messages sent where an STA message was not received in a predefined amount of time.
- **STASuccessMessagesReceivedCount:** The number of Session Termination Answers (STA) messages successfully received.
- **STASuccessMessagesSentCount:** The number of Session Termination Answers (STA) messages successfully sent.
- **STAFailureMessagesReceivedCount:** The number of Session Termination Answers (STA) messages with failed reception.
- **STAFailureMessagesSentCount:** The number of Session Termination Answers (STA) messages with failed sending.
- **AARMessagesReceivedCount:** The number of AA-Request (AAR) messages received.
- **AARMessagesSentCount:** The number of AA-Request (AAR) messages sent.
- **AARMessagesTimeoutCount:** The number of AA-Request (AAR) messages sent where an AA-Answer message was not received in a predefined amount of time.
- **AARInitialMessagesReceivedCount:** The number of AA-Request (AAR) initial messages received.
- **AARInitialMessagesSentCount:** The number of AA-Request (AAR) initial messages sent.
- **AARModificationMessagesReceivedCount:** The number of AA-Request (AAR) modification messages received.
- **AARModificationMessagesSentCount:** The number of AA-Request (AAR) modification messages sent.

- **AAASuccessMessagesReceivedCount:** The number of AA-Answer (AAA) messages successfully received.
- **AAASuccessMessagesSentCount:** The number of AA-Answer (AAA) messages successfully sent.
- **AAAFailureMessagesReceivedCount:** The number of AA-Answer (AAA) messages successfully received.
- **AAAFailureMessagesSentCount:** The number of AA-Answer (AAA) messages successfully sent.
- **RxPcmmMessagesTimeoutCount:** The number of Rx interface request messages sent where an answer message was not received in a predefined amount of time (Rx is the interface between AF and PCRF).
- **ActiveSessionsCount:** The number of AF active sessions.
- **MaximumActiveSessionsCount:** The number of historical maximum active sessions.
- **PeerOkayCount:** The count of peers whose state is okay.
- **PeerDownCount:** The count of peers whose state is down.
- **PeerSuspectCount:** The count of peers whose state is suspect.
- **PeerReopenCount:** The count of peers whose state is reopened.
- **AFBindingTryCount:** The total number of AF binding attempts.
- **AFBindingSuccessCount:** The number of AF binding successes.
- **AFBindingFailedCount:** The number of AF binding failures.
- **PCEFActiveSession:** The number of PCEF active sessions.

Diameter AF Binding Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterAfSessionStats tag.

Request

This request follows the **QueryOmStats > DiameterAfSessionStats** tag defined in the XSDs.

The following is an example of a request for network element "application1.oracle.com" diameter peer statistic within the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterAfSessionStats>
      <Name>ggsn1.oracle</Name>
    </DiameterAfSessionStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterAfPeerStats** tag defined in the XSDs.

The following is an example XML response to a DiameterAfPeerStats tag request:

```
<?xml version="1.0" encoding="UTF-8"?>
<Statistics>
  <DiameterAfSessionStats>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>application1.oracle.com</Name>
      <NeId></NeId>
      <SessionIdentity>AF-(application1.tekelec.com)</SessionIdentity>
      <ActiveSessionsCount>5</ActiveSessionsCount>
      <MaximumActiveSessionsCount>5</MaximumActiveSessionsCount>
      <AFBindingTryCount>0</AFBindingTryCount>
      <AFBindingSuccessCount>0</AFBindingSuccessCount>
      <AFBindingFailedCount>0</AFBindingFailedCount>
    </Sample>
  </DiameterAfSessionStats>
</Statistics>
```

Individual statistics are defined for Diameter Af Session query are:

- **PolicyServer:** The name of the MPE.
- **IsComplete:** Signifies if the statistics are complete. True is complete, false is incomplete.
- **Name:** The identity of Application.
- **SessionIdentity:** The identity of the session.
- **ActiveSessionsCount:** The number of Rx sessions.
- **MaxActiveSessionsCount:** The maximum number of Rx sessions.
- **AFBindingTryCount:** The total number of AF binding attempts.
- **AFBindingSuccessCount:** The number of AF binding successes.
- **AFBindingFailedCount:** The number of AF binding failures.

Diameter AF Peer Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterAfPeerStats tag.

Request

This request follows the **QueryOmStats > DiameterAfPeerStats** tag defined in the XSDs.

The following is an example of a request for network element "ggsn1.camiant" diameter peer statistic within the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterAfPeerStats>
      <Name>ggsn1.camiant</Name>
    </DiameterAfPeerStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

```
</QueryOmStats>
</XmlInterfaceRequest>
```

This request follows the **QueryOmStats > DiameterMraAfPeerStats** tag defined in the XSDs.

The following is an example of a request for network element "ggsn1.camiant" diameter peer statistic within the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterMraAfPeerStats>
      <Name>ggsn1.camiant</Name>
    </DiameterMraAfPeerStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterAfPeerStats** tag defined in the XSDs.

The following is an example XML response to a DiameterAfPeerStats tag request:

```
<?xml version='1.0' ?>
<Statistics>
  <DiameterAfPeerStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
      <PolicyServer>MPE2</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>ggsn1.camiant</Name>
      <InternalIdentity>mra</InternalIdentity>
      <RegisteredPeer>true</RegisteredPeer>
      <NeId></NeId>
      <NetworkElementType></NetworkElementType>
      <NetworkElementSubType></NetworkElementSubType>
      <ConnectTime>Thu Nov 08 10:41:25 EST 2012</ConnectTime>
      <DisconnectTime>Thu Nov 08 19:15:32 EST 2012</DisconnectTime>
      <ConnectAddress>10.15.17.41</ConnectAddress>
      <ConnectPort>42514</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>0</MessagesErrorOutCount>
      <ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
      <ASRMessagesSentCount>0</ASRMessagesSentCount>
      <ASRMessagesTimeoutCount>0</ASRMessagesTimeoutCount>
      <ASASuccessMessagesReceivedCount>0</ASASuccessMessagesReceivedCount>
      <ASASuccessMessagesSentCount>0</ASASuccessMessagesSentCount>
      <ASAFailureMessagesReceivedCount>0</ASAFailureMessagesReceivedCount>
      <ASAFailureMessagesSentCount>0</ASAFailureMessagesSentCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
```



```

<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<STRMessagesReceivedCount>0</STRMessagesReceivedCount>
<STRMessagesSentCount>0</STRMessagesSentCount>
<STRMessagesTimeoutCount>0</STRMessagesTimeoutCount>
<STASuccessMessagesReceivedCount>0</STASuccessMessagesReceivedCount>
<STASuccessMessagesSentCount>0</STASuccessMessagesSentCount>
<STAFailureMessagesReceivedCount>0</STAFailureMessagesReceivedCount>
<STAFailureMessagesSentCount>0</STAFailureMessagesSentCount>
<AARMessagesReceivedCount>0</AARMessagesReceivedCount>
<AARMessagesSentCount>0</AARMessagesSentCount>
<AARMessagesTimeoutCount>0</AARMessagesTimeoutCount>
<AARInitialMessagesReceivedCount>0</AARInitialMessagesReceivedCount>
<AARInitialMessagesSentCount>0</AARInitialMessagesSentCount>

<AARModificationMessagesReceivedCount>0</AARModificationMessagesReceivedCount>
<AARModificationMessagesSentCount>0</AARModificationMessagesSentCount>
<AAASuccessMessagesReceivedCount>0</AAASuccessMessagesReceivedCount>
<AAASuccessMessagesSentCount>0</AAASuccessMessagesSentCount>
<AAAFailureMessagesReceivedCount>0</AAAFailureMessagesReceivedCount>
<AAAFailureMessagesSentCount>0</AAAFailureMessagesSentCount>
<RxPcmmMessagesTimeoutCount>0</RxPcmmMessagesTimeoutCount>
<AFBindingTryCount>0</AFBindingTryCount>
<AFBindingSuccessCount>0</AFBindingSuccessCount>
<AFBindingFailedCount>0</AFBindingFailedCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
</Sample>
</DiameterAfPeerStats>
</Statistics>

```

The following is an example XML response to a DiameterMraAfPeerStats tag request:

```

<?xml version='1.0' ?>
<Statistics>
  <DiameterMraAfPeerStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
      <MRA>MRA</MRA>
      <IsComplete>true</IsComplete>
      <Name>ggsn1.camiant</Name>
      <InternalIdentity>mra</InternalIdentity>
      <RegisteredPeer>true</RegisteredPeer>
      <NeId></NeId>
      <NetworkElementType></NetworkElementType>
      <NetworkElementSubType></NetworkElementSubType>
      <ConnectTime>Thu Nov 08 10:41:25 EST 2012</ConnectTime>
      <DisconnectTime>Thu Nov 08 19:15:32 EST 2012</DisconnectTime>
      <ConnectAddress>10.15.17.41</ConnectAddress>
      <ConnectPort>42514</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>0</MessagesErrorOutCount>
      <ASRMessagesReceivedCount>0</ASRMessagesReceivedCount>
      <ASRMessagesSentCount>0</ASRMessagesSentCount>
      <ASRMessagesTimeoutCount>0</ASRMessagesTimeoutCount>
      <ASASuccessMessagesReceivedCount>0</ASASuccessMessagesReceivedCount>
      <ASASuccessMessagesSentCount>0</ASASuccessMessagesSentCount>
      <ASAFailureMessagesReceivedCount>0</ASAFailureMessagesReceivedCount>
    </Sample>
  </DiameterMraAfPeerStats>
</Statistics>

```

```

<ASAFailureMessagesSentCount>0</ASAFailureMessagesSentCount>
<RARMessagesReceivedCount>0</RARMessagesReceivedCount>
<RARMessagesSentCount>0</RARMessagesSentCount>
<RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
<RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
<RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
<RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
<RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
<STRMessagesReceivedCount>0</STRMessagesReceivedCount>
<STRMessagesSentCount>0</STRMessagesSentCount>
<STRMessagesTimeoutCount>0</STRMessagesTimeoutCount>
<STASuccessMessagesReceivedCount>0</STASuccessMessagesReceivedCount>
<STASuccessMessagesSentCount>0</STASuccessMessagesSentCount>
<STAFailureMessagesReceivedCount>0</STAFailureMessagesReceivedCount>
<STAFailureMessagesSentCount>0</STAFailureMessagesSentCount>
<AARMessagesReceivedCount>0</AARMessagesReceivedCount>
<AARMessagesSentCount>0</AARMessagesSentCount>
<AARMessagesTimeoutCount>0</AARMessagesTimeoutCount>
<AARInitialMessagesReceivedCount>0</AARInitialMessagesReceivedCount>
<AARInitialMessagesSentCount>0</AARInitialMessagesSentCount>

<AARModificationMessagesReceivedCount>0</AARModificationMessagesReceivedCount>
<AARModificationMessagesSentCount>0</AARModificationMessagesSentCount>
<AAASuccessMessagesReceivedCount>0</AAASuccessMessagesReceivedCount>
<AAASuccessMessagesSentCount>0</AAASuccessMessagesSentCount>
<AAAFailureMessagesReceivedCount>0</AAAFailureMessagesReceivedCount>
<AAAFailureMessagesSentCount>0</AAAFailureMessagesSentCount>
<RxPcmmMessagesTimeoutCount>0</RxPcmmMessagesTimeoutCount>
<AFBindingTryCount>0</AFBindingTryCount>
<AFBindingSuccessCount>0</AFBindingSuccessCount>
<AFBindingFailedCount>0</AFBindingFailedCount>
<ActiveSessionsCount>0</ActiveSessionsCount>
<MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
</Sample>
</DiameterMraAfPeerStats>
</Statistics>

```

Individual statistics are defined for Diameter KTSp Peer query are:

- **PolicyServer:** The name of the MPE.
- **MRA:** Name of the MRA.
- **IsComplete:** Shows if the statistics are complete.
- **Name:** The name of net element.
- **InternalIdentity:** The name of remote MPE or MRA. If remote system is neither MPE nor MRA, This element will be null.
- **RegisteredPeer:** Shows if the Peer is registered in PCRF system. (True = registered).
- **NeId:** The ID of net element.
- **NetworkElementType:** The type of net element, for example, GGSN.
- **NetworkElementSubType:** The sub type of net element.
- **ConnectTime :** The time of the connection.
- **DisconnectTime:** The time of the disconnection.
- **ConnectAddress:** The IP address of connection.
- **ConnectPort:** The connection port.
- **ConnectType:** The connection type, for example TCP.
- **MessagesInCount:** The number of total messages received.
- **MessagesOutCount:** The number of total messages sent.

- **MessagesErrorInCount:** The number of error messages received.
- **MessagesErrorOutCount:** The number of error messages sent.
- **ASRMessagesReceivedCount:** The number of Abort Session Requests (ASR) messages received.
- **ASRMessagesSentCount:** The number of Abort Session Requests (ASR) messages sent.
- **ASRMessagesTimeoutCount:** The number of Abort Session Request messages sent where an ASA message was not received in a predefined amount of time.
- **ASASuccessMessagesReceivedCount:** The number of Abort Session Answers (ASA) messages received.
- **ASASuccessMessagesSentCount:** The number of Abort Session Answers (ASA) messages sent.
- **ASAFailureMessagesReceivedCount:** The number of Abort Session Answers (ASA) messages with failed reception.
- **ASAFailureMessagesSentCount:** The number of Abort Session Answers (ASA) messages sent with failed sending.
- **RARMessagesReceivedCount:** The number of ReAuthorization Request (RAR) messages received.
- **RARMessagesSentCount:** The number of ReAuthorization Request (RAR) messages sent.
- **RARMessagesTimeoutCount:** The number of ReAuthorization Request (RAR) messages sent where an RAA message was not received in a predefined amount of time.
- **RAASuccessMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages successfully received.
- **RAASuccessMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages successfully sent.
- **RAAFailureMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages with failed reception.
- **RAAFailureMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages with failed sending.
- **STRMessagesReceivedCount:** The number of Session Termination Requests (STR) messages received.
- **STRMessagesSentCount:** The number of Session Termination Requests (STR) messages sent.
- **STRMessagesTimeoutCount:** The number of Session Termination Requests (STR) messages sent where an STA message was not received in a predefined amount of time.
- **STASuccessMessagesReceivedCount:** The number of Session Termination Answers (STA) messages successfully received.
- **STASuccessMessagesSentCount:** The number of Session Termination Answers (STA) messages successfully sent.
- **STAFailureMessagesReceivedCount:** The number of Session Termination Answers (STA) messages with failed reception.
- **STAFailureMessagesSentCount:** The number of Session Termination Answers (STA) messages with failed sending.
- **AARMessagesReceivedCount:** The number of AA-Request (AAR) messages received.
- **AARMessagesSentCount:** The number of AA-Request (AAR) messages sent.
- **AARMessagesTimeoutCount:** The number of AA-Request (AAR) messages sent where an AA-Answer message was not received in a predefined amount of time.
- **AARInitialMessagesReceivedCount:** The number of AA-Request (AAR) initial messages received.
- **AARInitialMessagesSentCount:** The number of AA-Request (AAR) initial messages sent.
- **AARModificationMessagesReceivedCount:** The number of AA-Request (AAR) modification messages received.

- **AARModificationMessagesSentCount:** The number of AA-Request (AAR) modification messages sent.
- **AAASuccessMessagesReceivedCount:** The number of AA-Answer (AAA) messages successfully received.
- **AAASuccessMessagesSentCount:** The number of AA-Answer (AAA) messages successfully sent.
- **AAAFailureMessagesReceivedCount:** The number of AA-Answer (AAA) messages successfully received.
- **AAAFailureMessagesSentCount:** The number of AA-Answer (AAA) messages successfully sent.
- **RxPcmmMessagesTimeoutCount:** The number of Rx interface request messages sent where an answer message was not received in a predefined amount of time (Rx is the interface between AF and PCRF).
- **AFBindingTryCount:** The total number of AF binding attempts.
- **AFBindingSuccessCount:** The number of AF binding successes.
- **AFBindingFailedCount:** The number of AF binding failures.
- **ActiveSessionsCount:** The number active sessions.
- **MaximumActiveSessionsCount:** The number of historical maximum active sessions.

Diameter AF Session Service ID Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterAfSessionSidStats tag.

Note: This statistic is not supported by the Multi-Protocol Routing Agent (MRA).

Request

This request follows the **QueryOmStats > DiameterAfSessionSidStats** tag defined in the XSDs.

The following is an example of a request for application with "p-cscf-cshi.network.com" diameter session statistics with the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterAfSessionSidStats>
      <PolicyServer>MPE1</PolicyServer>
      <Name>p-cscf-cshi.network.com</Name>
    </DiameterAfSessionSidStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterAfSessionSidStats** tag defined in the XSDs.

The following is an example XML response to a DiameterAfSessionSidStats tag request:

```
<?xml version='1.0' ?>
```

```

<Statistics>
  <DiameterAfSessionSidStats>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>p-cscf-cshi.network.com</Name>
      <NeId/>
      <ServiceId>612</ServiceId>
      <SessionIdentity>AFSID-(612)-(p-cscf-cshi.oracle.com)</SessionIdentity>
      <DedicatedBearerReqCount>5</DedicatedBearerReqCount>
    </Sample>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>p-cscf-cshi.oracle.com</Name>
      <NeId/>
      <ServiceId>others</ServiceId>
      <SessionIdentity>AFSID-(others)-(p-cscf-cshi.network.com)</SessionIdentity>
      <DedicatedBearerReqCount>5</DedicatedBearerReqCount>
    </Sample>
  </DiameterAfSessionSidStats>
</Statistics>

```

Individual statistics are defined for Diameter Gx Service ID sessions are:

- **PolicyServer:** The name of the MPE.
- **IsComplete:** States whether the statistics are complete. True signifies complete, false signifies incomplete.
- **Name:** The identity of the Application.
- **NeID:** The Integer ID of the Application.
- **ServiceID:** The identity of the service.
- **SessionIdentity:** The identity of the session counter.
- **DedicatedBearerReqCount:** The Gx dedi-bearer request count statistics per Service-id (for example, Gx RAR SID).

Diameter Policy Charging Enforcement Function Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterPcefStats tag.

Request

This request follows the **QueryOmStats > DiameterPcefStats** tag defined in the XSDs.

The following is an example of a request for network element "mpe17-41" diameter peer statistic within the system.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>

```

```

<QueryOmStats>
  <StartTime>2012-11-09T00:01:00</StartTime>
  <EndTime>2012-12-31T23:59:00</EndTime>
  <DiameterPcefStats>
    <PolicyServer>MPE</PolicyServer>
  </DiameterPcefStats>
</QueryOmStats>
</XmlInterfaceRequest>

```

This request follows the **QueryOmStats > DiameterMraPcefStats** tag defined in the XSDs.

The following is an example of a request for network element "mra17-51" diameter peer statistic within the system.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterMraPcefStats>
      <MRA>MRA</MRA>
    </DiameterMraPcefStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterMraPcefStats** tag defined in the XSDs.

The following is an example XML response to a DiameterPcefStats tag request:

```

<?xml version='1.0' ?>
<Statistics>
  <DiameterPcefStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
      <PolicyServer>MPE</PolicyServer>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>1</CurrentConnectionsCount>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>6000</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
      <CCASuccessMessagesSentCount>6000</CCASuccessMessagesSentCount>
      <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
      <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
      <CCRIMessagesReceivedCount>3000</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
    </Sample>
  </DiameterPcefStats>
</Statistics>

```

```

    <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
    <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
    <CCRTMessagesReceivedCount>3000</CCRTMessagesReceivedCount>
    <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
    <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
    <CCAIISuccessMessagesReceivedCount>0</CCAIISuccessMessagesReceivedCount>
    <CCAIISuccessMessagesSentCount>3000</CCAIISuccessMessagesSentCount>
    <CCAIIFailureMessagesReceivedCount>0</CCAIIFailureMessagesReceivedCount>
    <CCAIIFailureMessagesSentCount>0</CCAIIFailureMessagesSentCount>
    <CCAUISuccessMessagesReceivedCount>0</CCAUISuccessMessagesReceivedCount>
    <CCAUISuccessMessagesSentCount>0</CCAUISuccessMessagesSentCount>
    <CCAUIFailureMessagesReceivedCount>0</CCAUIFailureMessagesReceivedCount>
    <CCAUIFailureMessagesSentCount>0</CCAUIFailureMessagesSentCount>
    <CCATISuccessMessagesReceivedCount>0</CCATISuccessMessagesReceivedCount>
    <CCATISuccessMessagesSentCount>3000</CCATISuccessMessagesSentCount>
    <CCATIFailureMessagesReceivedCount>0</CCATIFailureMessagesReceivedCount>
    <CCATIFailureMessagesSentCount>0</CCATIFailureMessagesSentCount>
    <ActiveSessionsCount>3002</ActiveSessionsCount>
    <MaximumActiveSessionsCount>3005</MaximumActiveSessionsCount>
    <PeerOkayCount>1</PeerOkayCount>
    <PeerDownCount>0</PeerDownCount>
    <PeerSuspectCount>0</PeerSuspectCount>
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterPcefStats>
</Statistics>

```

The response to this request follows the **Statistics > DiameterMraPcefStats** tag defined in the XSDs.

The following is an example XML response to a DiameterMraPcefStats tag request:

```

<?xml version='1.0' ?>
<Statistics>
  <DiameterMraPcefStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
      <MRA>MRA</MRA>
      <IsComplete>true</IsComplete>
      <CurrentConnectionsCount>1</CurrentConnectionsCount>
      <MessagesInCount>6000</MessagesInCount>
      <MessagesOutCount>6000</MessagesOutCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>6000</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
      <CCASuccessMessagesSentCount>6000</CCASuccessMessagesSentCount>
      <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
      <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
      <CCRIMessagesReceivedCount>3000</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
    </Sample>
  </DiameterMraPcefStats>
</Statistics>

```

```

    <CCRTMessagesReceivedCount>3000</CCRTMessagesReceivedCount>
    <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
    <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
    <CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
    <CCAISuccessMessagesSentCount>3000</CCAISuccessMessagesSentCount>
    <CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
    <CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
    <CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
    <CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
    <CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
    <CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
    <CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
    <CCATSuccessMessagesSentCount>3000</CCATSuccessMessagesSentCount>
    <CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
    <CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
    <ActiveSessionsCount>3002</ActiveSessionsCount>
    <MaximumActiveSessionsCount>3005</MaximumActiveSessionsCount>
    <PeerOkayCount>1</PeerOkayCount>
    <PeerDownCount>0</PeerDownCount>
    <PeerSuspectCount>0</PeerSuspectCount>
    <PeerReopenCount>0</PeerReopenCount>
  </Sample>
</DiameterMraPcefStats>
</Statistics>

```

Individual statistics are defined for Diameter Pcef query are:

- **PolicyServer:** The name of the MPE.
- **MRA:** The name of the MRA
- **IsComplete:** Shows if the statistics are complete.
- **CurrentConnectionsCount:** The number of current connections.
- **RARMessagesReceivedCount:** The number of ReAuthorization Request (RAR) messages received.
- **RARMessagesSentCount:** The number of ReAuthorization Request (RAR) messages sent.
- **RAASuccessMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages successfully received.
- **RAASuccessMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages successfully sent.
- **RAAFailureMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages with failed reception.
- **RAAFailureMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages that failed during sending.
- **ASRMessagesReceivedCount:** The number of Abort Session Requests (ASR) messages received.
- **ASRMessagesSentCount:** The number of Abort Session Requests (ASR) messages sent.
- **ASRMessagesTimeoutCount:** The number of Abort Session Requests (ASR) messages sent where an ASA message was not received in a predefined amount of time.
- **ASASuccessMessagesReceivedCount:** The count of the number of Abort Session Answers (ASA) messages successfully received.
- **ASASuccessMessagesSentCount:** The number of Abort Session Answers (ASA) messages successfully sent.
- **ASAFailureMessagesReceivedCount:** The number of Abort Session Answers (ASA) messages with failed reception.
- **ASAFailureMessagesSentCount:** The number of Abort Session Answers (ASA) messages that failed during sending.

- **CCRMessagesReceivedCount:** The number of Diameter Credit Control Requests (CCR) messages received.
- **CCRMessagesSentCount:** The number of Diameter Credit Control Requests (CCR) messages sent.
- **CCASuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers (CCA) messages successfully received.
- **CCASuccessMessagesSentCount:** The number of Diameter Credit Control Answers (CCA) messages successfully sent.
- **CCAFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers (CCA) messages with failed reception.
- **CCAFailureMessagesSentCount:** The number of Diameter Credit Control Answers (CCA) messages that failed during sending.
- **CCRIMessagesReceivedCount:** The number of Diameter Credit Control Requests Initial (CCRI) messages received.
- **CCRIMessagesSentCount:** The number of Diameter Credit Control Requests Initial (CCRI) messages sent.
- **CCRUMessagesReceivedCount:** The number of Diameter Credit Control Requests Update (CCRU) messages received.
- **CCRUMessagesSentCount:** The number of Diameter Credit Control Requests Update (CCRU) messages sent.
- **CCRTMessagesReceivedCount:** The number of Diameter Credit Control Requests Terminate (CCRT) messages received.
- **CCRTMessagesSentCount:** The number of Diameter Credit Control Requests Terminate (CCRT) messages sent.
- **CCAIISuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers Initial (CCAI) messages successfully received.
- **CCAIISuccessMessagesSentCount:** The number of Diameter Credit Control Answers Initial (CCAI) messages successfully sent.
- **CCAIFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers Initial (CCAI) messages where reception failed.
- **CCAIFailureMessagesSentCount:** the number of Diameter Credit Control Answers Initial (CCAI) messages that failed during sending.
- **CCAUSuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers Update (CCAU) messages successfully received.
- **CCAUSuccessMessagesSentCount:** The number of Diameter Credit Control Answers Update (CCAU) messages successfully sent.
- **CCAUFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers Update (CCAU) messages reception failed.
- **CCAUFailureMessagesSentCount:** The number of Diameter Credit Control Answers Update (CCAU) messages sending failed.
- **CCATSuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages successfully received.
- **CCATSuccessMessagesSentCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages successfully sent.
- **CCATFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages where reception failed.
- **CCATFailureMessagesSentCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages that failed during sending.

- **RxPcmmMessagesTimeoutCount:** The number of Rx interface request messages sent where an answer message was not received in a predefined amount of time (Rx is the interface between AF and PCRF).
- **ActiveSessionsCount:** The number of AF active sessions.
- **MaximumActiveSessionsCount:** The number of historical maximum active sessions.
- **PeerOkayCount:** The count of peers whose state is okay.
- **PeerDownCount:** The count of peers whose state is down.
- **PeerSuspectCount:** The count of peers whose state is suspect.
- **PeerReopenCount:** The count of peers whose state is reopened.

Diameter PCEF Peer Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterPcefPeerStats tag.

Request

This request follows the **QueryOmStats > DiameterPcefPeerStats** tag defined in the XSDs.

The following is an example of a request for network element "GGSN" diameter peer statistic within the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterPcefPeerStats>
      <Name>GGSN</Name>
    </DiameterPcefPeerStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

This request follows the **QueryOmStats > DiameterMraPcefPeerStats** tag defined in the XSDs.

The following is an example of a request for network element "ggsn1.camiant" diameter peer statistic within the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterMraPcefPeerStats>
      <Name>GGSN</Name>
    </DiameterMraPcefPeerStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterKPcefPeerStats** tag defined in the XSDs.

The following is an example XML response from MPE to a DiameterPcefPeerStats tag request:

```
<?xml version='1.0' ?>
<Statistics>
  <DiameterPcefPeerStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
      <PolicyServer>MPE2</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>GGSN</Name>
      <InternalIdentity>mra</InternalIdentity>
      <RegisteredPeer>true</RegisteredPeer>
      <NeId></NeId>
      <NetworkElementType>GGSN</NetworkElementType>
      <NetworkElementSubType>None</NetworkElementSubType>
      <ConnectTime>Thu Nov 08 10:41:25 EST 2012</ConnectTime>
      <DisconnectTime>Thu Nov 08 19:15:32 EST 2012</DisconnectTime>
      <ConnectAddress>10.15.17.41</ConnectAddress>
      <ConnectPort>42514</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>0</MessagesErrorOutCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
      <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
      <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
      <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
      <CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
      <CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
      <CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
      <CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
      <CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
      <CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
      <CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
      <CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
      <CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
      <CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
      <CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
      <CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
      <ActiveSessionsCount>1</ActiveSessionsCount>
      <MaximumActiveSessionsCount>1</MaximumActiveSessionsCount>
    </Sample>
  </DiameterPcefPeerStats>
</Statistics>
```

```

    </DiameterPcefPeerStats>
  </Statistics>

```

The following is an example XML response MRA to a DiameterMraPcefPeerStats tag request:

```

<?xml version='1.0' ?>
<Statistics>
  <DiameterMraPcefPeerStats>
    <Sample>
      <StartTime>2012-11-09T05:05:00Z</StartTime>
      <EndTime>2012-11-09T05:10:00Z</EndTime>
      <MRA>MRA</MRA>
      <IsComplete>true</IsComplete>
      <Name>GGSN</Name>
      <NeId></NeId>
      <InternalIdentity></InternalIdentity>
      <RegisteredPeer>true</RegisteredPeer>
      <NetworkElementType>GGSN</NetworkElementType>
      <NetworkElementSubType>None</NetworkElementSubType>
      <ConnectTime>Thu Nov 08 10:41:25 EST 2012</ConnectTime>
      <DisconnectTime>Thu Nov 08 19:15:32 EST 2012</DisconnectTime>
      <ConnectAddress>10.15.17.41</ConnectAddress>
      <ConnectPort>42514</ConnectPort>
      <ConnectType>TCP</ConnectType>
      <MessagesInCount>0</MessagesInCount>
      <MessagesOutCount>0</MessagesOutCount>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>0</MessagesErrorOutCount>
      <RARMessagesReceivedCount>0</RARMessagesReceivedCount>
      <RARMessagesSentCount>0</RARMessagesSentCount>
      <RARMessagesTimeoutCount>0</RARMessagesTimeoutCount>
      <RAASuccessMessagesReceivedCount>0</RAASuccessMessagesReceivedCount>
      <RAASuccessMessagesSentCount>0</RAASuccessMessagesSentCount>
      <RAAFailureMessagesReceivedCount>0</RAAFailureMessagesReceivedCount>
      <RAAFailureMessagesSentCount>0</RAAFailureMessagesSentCount>
      <CCRMessagesReceivedCount>0</CCRMessagesReceivedCount>
      <CCRMessagesSentCount>0</CCRMessagesSentCount>
      <CCRMessagesTimeoutCount>0</CCRMessagesTimeoutCount>
      <CCASuccessMessagesReceivedCount>0</CCASuccessMessagesReceivedCount>
      <CCASuccessMessagesSentCount>0</CCASuccessMessagesSentCount>
      <CCAFailureMessagesReceivedCount>0</CCAFailureMessagesReceivedCount>
      <CCAFailureMessagesSentCount>0</CCAFailureMessagesSentCount>
      <CCRIMessagesReceivedCount>0</CCRIMessagesReceivedCount>
      <CCRIMessagesSentCount>0</CCRIMessagesSentCount>
      <CCRIMessagesTimeoutCount>0</CCRIMessagesTimeoutCount>
      <CCRUMessagesReceivedCount>0</CCRUMessagesReceivedCount>
      <CCRUMessagesSentCount>0</CCRUMessagesSentCount>
      <CCRUMessagesTimeoutCount>0</CCRUMessagesTimeoutCount>
      <CCRTMessagesReceivedCount>0</CCRTMessagesReceivedCount>
      <CCRTMessagesSentCount>0</CCRTMessagesSentCount>
      <CCRTMessagesTimeoutCount>0</CCRTMessagesTimeoutCount>
      <CCAISuccessMessagesReceivedCount>0</CCAISuccessMessagesReceivedCount>
      <CCAISuccessMessagesSentCount>0</CCAISuccessMessagesSentCount>
      <CCAIFailureMessagesReceivedCount>0</CCAIFailureMessagesReceivedCount>
      <CCAIFailureMessagesSentCount>0</CCAIFailureMessagesSentCount>
      <CCAUSuccessMessagesReceivedCount>0</CCAUSuccessMessagesReceivedCount>
      <CCAUSuccessMessagesSentCount>0</CCAUSuccessMessagesSentCount>
      <CCAUFailureMessagesReceivedCount>0</CCAUFailureMessagesReceivedCount>
      <CCAUFailureMessagesSentCount>0</CCAUFailureMessagesSentCount>
      <CCATSuccessMessagesReceivedCount>0</CCATSuccessMessagesReceivedCount>
      <CCATSuccessMessagesSentCount>0</CCATSuccessMessagesSentCount>
      <CCATFailureMessagesReceivedCount>0</CCATFailureMessagesReceivedCount>
      <CCATFailureMessagesSentCount>0</CCATFailureMessagesSentCount>
    </Sample>
  </DiameterMraPcefPeerStats>
</Statistics>

```

```

    <ActiveSessionsCount>1</ActiveSessionsCount>
    <MaximumActiveSessionsCount>1</MaximumActiveSessionsCount>
  </Sample>
  <DiameterMraPcefPeerStats>
</Statistics>

```

Individual statistics are defined for Diameter PCRF Peer query are:

- **PolicyServer:** The name of the MPE.
- **MRA:** Name of the MRA.
- **IsComplete:** Shows if the statistics are complete.
- **Name:** The name of the net element.
- **InternalIdentity:** The name of remote MPE or MRA. If remote system is neither MPE nor MRA, This element will be null.
- **RegisteredPeer:** Shows if the Peer is registered in PCRF system. (True = registered).
- **NetId:** The ID of net element.
- **NetworkElementType:** The type of net element, for example, GGSN.
- **NetworkElementSubType:** The sub type of net element.
- **ConnectTime :** The time of the connection.
- **DisconnectTime:** The time of the disconnection.
- **ConnectAddress:** The IP address of connection.
- **ConnectPort:** The connection port.
- **ConnectType:** The connection type, for example TCP.
- **MessagesInCount:** The number of total messages received.
- **MessagesOutCount:** The number of total messages sent.
- **MessagesErrorInCount:** The number of error messages received.
- **MessagesErrorOutCount:** The number of error messages sent.
- **RARMessagesReceivedCount:** The number of ReAuthorization Request (RAR) messages received.
- **RARMessagesSentCount:** The number of ReAuthorization Request (RAR) messages sent.
- **RAASuccessMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages successfully received.
- **RAASuccessMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages successfully sent.
- **RAAFailureMessagesReceivedCount:** The number of ReAuthorization Answers (RAA) messages with failed reception.
- **RAAFailureMessagesSentCount:** The number of ReAuthorization Answers (RAA) messages that failed during sending.
- **ASRMessagesReceivedCount:** The number of Abort Session Requests (ASR) messages received.
- **ASRMessagesSentCount:** The number of Abort Session Requests (ASR) messages sent.
- **ASRMessagesTimeoutCount:** The number of Abort Session Requests (ASR) messages sent where an ASA message was not received in a predefined amount of time.
- **ASASuccessMessagesReceivedCount:** The count of the number of Abort Session Answers (ASA) messages successfully received.
- **ASASuccessMessagesSentCount:** The number of Abort Session Answers (ASA) messages successfully sent.
- **ASAFailureMessagesReceivedCount:** The number of Abort Session Answers (ASA) messages with failed reception.

- **ASAFailureMessagesSentCount:** The number of Abort Session Answers (ASA) messages that failed during sending.
- **CCRMessagesReceivedCount:** The number of Diameter Credit Control Requests (CCR) messages received.
- **CCRMessagesSentCount:** The number of Diameter Credit Control Requests (CCR) messages sent.
- **CCASuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers (CCA) messages successfully received.
- **CCASuccessMessagesSentCount:** The number of Diameter Credit Control Answers (CCA) messages successfully sent.
- **CCAFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers (CCA) messages with failed reception.
- **CCAFailureMessagesSentCount:** The number of Diameter Credit Control Answers (CCA) messages that failed during sending.
- **CCRIMessagesReceivedCount:** The number of Diameter Credit Control Requests Initial (CCRI) messages received.
- **CCRIMessagesSentCount:** The number of Diameter Credit Control Requests Initial (CCRI) messages sent.
- **CCRUMessagesReceivedCount:** The number of Diameter Credit Control Requests Update (CCRU) messages received.
- **CCRUMessagesSentCount:** The number of Diameter Credit Control Requests Update (CCRU) messages sent.
- **CCRTMessagesReceivedCount:** The number of Diameter Credit Control Requests Terminate (CCRT) messages received.
- **CCRTMessagesSentCount:** The number of Diameter Credit Control Requests Terminate (CCRT) messages sent.
- **CCAIISuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers Initial (CCAI) messages successfully received.
- **CCAIISuccessMessagesSentCount:** The number of Diameter Credit Control Answers Initial (CCAI) messages successfully sent.
- **CCAIIFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers Initial (CCAI) messages where reception failed.
- **CCAIIFailureMessagesSentCount:** the number of Diameter Credit Control Answers Initial (CCAI) messages that failed during sending.
- **CCAUSuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers Update (CCAU) messages successfully received.
- **CCAUSuccessMessagesSentCount:** The number of Diameter Credit Control Answers Update (CCAU) messages successfully sent.
- **CCAUFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers Update (CCAU) messages reception failed.
- **CCAUFailureMessagesSentCount:** The number of Diameter Credit Control Answers Update (CCAU) messages sending failed.
- **CCATSuccessMessagesReceivedCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages successfully received.
- **CCATSuccessMessagesSentCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages successfully sent.
- **CCATFailureMessagesReceivedCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages where reception failed.

- **CCATFailureMessagesSentCount:** The number of Diameter Credit Control Answers Terminate (CCAT) messages that failed during sending.
- **ActiveSessionsCount:** The number of AF active sessions.
- **MaximumActiveSessionsCount:** The number of historical maximum active sessions.

Diameter Gx Session Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterPcefSessionStats tag.

Request

This request follows the **QueryOmStats > DiameterPcefSessionStats** tag defined in the XSDs.

The following is an example of a request for network element 'GGSN' diameter peer statistic within the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:01:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterPcefSessionStats>
      <Name>GGSN</Name>
    </DiameterPcefSessionStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterPcefSessionStats** tag defined in the XSDs.

The following is an example XML response to a DiameterPcefSessionStats tag request:

```
<?xml version='1.0' ?>
<Statistics>
  <DiameterPcefSessionStats>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>GGSN</Name>
      <NeId></NeId>
      <SessionIdentity>GX-(ggsn1.camiant)</SessionIdentity>
      <ActiveSessionsCount>5</ActiveSessionsCount>
      <MaximumActiveSessionsCount>5</MaximumActiveSessionsCount>
    </Sample>
  </DiameterPcefSessionStats>
</Statistics>
```

Individual statistics are defined for Diameter Gx sessions are:

- **PolicyServer:** The name of the MPE.

- **IsComplete:** Signifies if the statistics are complete. True is complete, false is incomplete.
- **Name:** The diameter identity of the network element.
- **NeName:** the name of the network element.
- **ActiveSessionsCount:** The number number of Gx sessions.
- **MaxActiveSessionsCount:** The maximum number of Gx sessions.

Diameter Message Error Statistics

The following examples show the request and response that are defined in the XSDs for the MessageErrorStats tag.

Request

This request follows the **QueryOmStats > MessageErrorStats** tag defined in the XSDs.

The following is an example of a request for all connection error statistics.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-12-28T04:55:00Z</StartTime>
    <EndTime>2012-12-28T05:00:00Z</EndTime>
    <MessageErrorStats>
      <Name>GGSN</Name>
    </MessageErrorStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > MessageErrorStats** tag defined in the XSDs.

The following is an example XML response to a MessageErrorStats tag request:

```
<?xml version='1.0' ?>
<Statistics>
  <MessageErrorStats>
    <Sample>
      <StartTime>2012-12-28T04:55:00Z</StartTime>
      <EndTime>2012-12-28T05:00:00Z</EndTime>
      <MRA>MRA45</MRA>
      <IsComplete>true</IsComplete>
      <Name>GGSN</Name>
      <NeId></NeId>
      <MessageCommand>CCA-I</MessageCommand>
      <MessageErrorName>DIAMETER_ERROR_INITIAL_PARAMETERS</MessageErrorName>
      <MessageErrorCode>5140</MessageErrorCode>
      <MessagesErrorInCount>0</MessagesErrorInCount>
      <MessagesErrorOutCount>1</MessagesErrorOutCount>
    </Sample>
  </MessageErrorStats>
</Statistics>
```

Individual statistics are defined for error messages are:

- **MessageCommand:** The command name of the diameter message.
- **MessageErrorName:** The experiment error name in the diameter protocol.
- **MessageErrorCode:** The experiment error code in the diameter protocol.
- **MessagesErrorOutCount:** The number of protocol error messages that have been sent to the remote system.
- **MessagesErrorInCount:** The number of protocol error messages that have been received from the remote system.

Query Network Elements

The following examples show the request and response that are defined in the XSDs for the QueryNetworkElement tag.

Request

This request follows the **ConfigurationData > QueryNetworkElement** tag defined in the XSDs.

The following is an example of a request for for querying multiple network elements by name.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryNetworkElement>
    <Name>CMTS A</Name>
    <Name>CMTS B</Name>
  </QueryNetworkElement>
</XmlInterfaceRequest>
```

The following is an example of a request for for querying all network elements and groups.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryNetworkElement/>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > QueryNetworkElement** tag defined in the XSDs.

The following is an example XML response to a QueryNetworkElement tag request:

```
<?xml version="1.0" encoding="UTF-8"?>
<ConfigurationData version="9.2.0">
  <NetworkElement>
    <Name>GGSN</Name>
    <Description></Description>
    <HostName>1.1.1.1</HostName>
    <BackupHostName></BackupHostName>
    <NetworkElementType>GGSN</NetworkElementType>
    <NeSubType>None</NeSubType>
    <Managed>true</Managed>
    <ReadCommunity></ReadCommunity>
```

```

    <Capability>5</Capability>
    <Capacity>0</Capacity>
    <X>0</X>
    <Y>0</Y>
    <DiameterRealm>oracle.com</DiameterRealm>
    <Fqdn></Fqdn>
    <SctpEnabled>>false</SctpEnabled>
    <InitiateDirectConnection>>false</InitiateDirectConnection>
    <TdfPort>3868</TdfPort>
    <ReconnectDelay>3</ReconnectDelay>
    <WatchDogInterval>30</WatchDogInterval>
    <ResponseTimeout>5</ResponseTimeout>
    <AssociatedMRAIdentity></AssociatedMRAIdentity>
    <BackupTDFIdentity></BackupTDFIdentity>
    <ProtocolTimerProfile></ProtocolTimerProfile>
    <Nediameterid>
      <NediameteridStr>ggsn1.oracle.com</NediameteridStr>
    </Nediameterid>
    <Nediameterid>
      <NediameteridStr>ggsn2.oracle.com</NediameteridStr>
    </Nediameterid>
  </NetworkElement>
</ConfigurationData>

```

Individual statistics are defined for the element network are:

- **Name:** The name of the element network.
- **Description:** The description of the element network.
- **HostName:** The IP address or DNS hostname of the element network.
- **BackupHostName:** The backup IP address or DNS hostname of the element network.
- **NetworkElementType:** The type of element network.
- **NeSubType:** The sub-type of the element network.
- **Managed:** The managed flag of the element network.
- **ReadCommunity:** The reserved element.
- **Capability:** The numerical identity of the network element capability type.
 1. TMO-Gx
 2. SCE-Gx
 3. TDF-Solicit
 4. Time-Tariff
 5. Usage-Report
- **Capacity:** The aggregate capacity in bits per second (bps).
- **X:** A reserved element.
- **Y:** A reserved element.
- **DiameterRealm:** The diameter realm of the element network.
- **SctpEnabled:** Signifies if the support diameter over SCTP is enabled.
- **NasPassphrase:** The reserved element.
- **InitiateDirectConnection:** Signifies if the TDF network element can connect to MPE directly.
- **TdfPort:** The diameter connect port of the TDF element network.
- **ReconnectDelay:** The delay period after the diameter connect failed. The time unit is in seconds.
- **WatchDogInterval:** The time interval used by the watch dog monitor.
- **ResponseTimeout:** The timeout of the connect response.
- **AssociatedMRAIdentity:** The associate MRA of the TDF element network.

- **BackupTDFIdentity:** The backup MRA identity of the TDF element network.
- **Nediameterid:** The diameter identities of the element network.

Diameter PCEF Session Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterPcefSessionStats tag.

Note: This statistic is available only for Multimedia Policy Engine (MPE).

Request

This request follows the **QueryOmStats > DiameterPcefSessionStats** tag defined in the XSDs.

The following is an example of a request for network element "ggsn1.network" diameter session statistics within the system.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2013-02-08T06:45:00Z</StartTime>
    <EndTime>2013-02-08T06:50:00Z</EndTime>
    <DiameterPcefSessionStats>
      <PolicyServer>MPE1</PolicyServer>
      <Name>ggsn1.network</Name>
    </DiameterPcefSessionStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > DiameterPcefSessionStats** tag defined in the XSDs.

The following is an example XML response to a DiameterPcefSessionStats tag request:

```
<?xml version='1.0' ?>
<Statistics>
  <DiameterPcefSessionStats>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>ggsn1.network</Name>
      <NeId/>
      <NeName>GGSN</NeName>
      <SessionIdentity>GX-(ggsn1.network)</SessionIdentity>
      <ActiveSessionsCount>5</ActiveSessionsCount>
      <MaximumActiveSessionsCount>5</MaximumActiveSessionsCount>
      <DuplicatedSessionCount>1</DuplicatedSessionCount>
    </Sample>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
```

```

    <IsComplete>true</IsComplete>
    <Name>pgw-cshi.oracle.com</Name>
    <NeId/>
    <NeName>pgw-cshi</NeName>
    <SessionIdentity>GX-(pgw-cshi.network.com)</SessionIdentity>
    <ActiveSessionsCount>0</ActiveSessionsCount>
    <MaximumActiveSessionsCount>0</MaximumActiveSessionsCount>
    <DuplicatedSessionCount>0</DuplicatedSessionCount>
  </Sample>
</DiameterPcefSessionStats>
</Statistics>

```

Individual statistics are defined for Diameter PCEF Sessions are:

- **PolicyServer:** The name of the Multimedia Policy Engine (MPE).
- **IsComplete:** States whether the statistics are complete. True signifies complete, false signifies incomplete.
- **Name:** The identity of the Network Element.
- **NeID:** The Integer ID of the Network Element.
- **NeName:** The name of the Network Element.
- **SessionIdentity:** The identity of the session counter.
- **MaxActiveSessionsCount:** The maximum number of Gx sessions.
- **DuplicatedSessionCount:** The number of duplicate session statistics per Gx peer.

Diameter PCEF Session APN Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterPcefSessionApnStats tag.

Note: This statistic is available only for Multimedia Policy Engine (MPE).

Request

This request follows the **QueryOmStats > DiameterPcefSessionApnStats** tag defined in the XSDs.

The following is an example of a request for network element "pgw-cshi.network.com" diameter session statistics within the system.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2012-11-09T00:00:00</StartTime>
    <EndTime>2012-12-31T23:59:00</EndTime>
    <DiameterPcefSessionApnStats>
      <PolicyServer>MPE1</PolicyServer>
      <Name>pgw-cshi.network.com</Name>
    </DiameterPcefSessionApnStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics > DiameterPcefSessionApnStats** tag defined in the XSDs.

The following is an example XML response to a DiameterPcefSessionApnStats tag request:

```
<?xml version='1.0' ?>
<Statistics>
  <DiameterPcefSessionApnStats>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>pgw-cshi.network.com</Name>
      <NeName>PGW-cshi</NeName>
      <NeId/>
      <ApnSuffix>lte.apnsuffix.com</ApnSuffix>

      <SessionIdentity>GXAPN-(lte.apnsuffix.com)-(pgw-cshi.element.com)</SessionIdentity>

      <GxAPNReqCount>5</GxAPNReqCount>
    </Sample>
    <Sample>
      <StartTime>2013-02-08T06:45:00Z</StartTime>
      <EndTime>2013-02-08T06:50:00Z</EndTime>
      <PolicyServer>MPE1</PolicyServer>
      <IsComplete>true</IsComplete>
      <Name>pgw-cshi.network.com</Name>
      <NeName>PGW-cshi</NeName>
      <NeId/>
      <ApnSuffix>others</ApnSuffix>
      <SessionIdentity>GXAPN-(others)-(pgw-cshi.network.com)</SessionIdentity>

      <GxAPNReqCount>5</GxAPNReqCount>
    </Sample>
  </DiameterPcefSessionApnStats>
</Statistics>
```

Individual statistics are defined for Diameter PCEF Session APNs are:

- **PolicyServer:** The name of the Multimedia Policy Engine (MPE).
- **IsComplete:** States whether the statistics are complete. True signifies complete, false signifies incomplete.
- **Name:** The identity of the Network Element.
- **NeID:** The Integer ID of the Network Element.
- **NeName:** The name of the Network Element.
- **ApnSuffix:** The identity of the Access Point Name (APN).
- **SessionIdentity:** The identity of the session counter.
- **GxApnReqCount:** The number of Gx successful ccr initial request associated with the current APN.

Chapter 9

Operational Measurement Requests for Mediation Server

Topics:

- *SPR KPI Historical Report.....215*
- *SPR Diameter Sh Message Statistics.....217*
- *SPR Active Alarm.....220*
- *Mediation Server Active Alarm.....221*
- *Mediation Server HA Statistic.....222*
- *Mediation Server KPI and OM Statistics.....223*

This chapter defines the various Operational Measurements (OM) groups and the individual OM statistics that comprise them for the Mediation Server. For several of the more generic statistics, the instrumentation on the Multimedia Policy Engine (MPE) and the Multi-Protocol Routing Agent (MRA) may differ by protocol, and therefore specific statistics may increment differently across those protocols.

SPR KPI Historical Report

The following examples show the request and response that are defined in the XSDs for the KpiStats tag. The interface provides to query an SPR KPI historical report for EMS (queries can be conducted at 10 minute intervals).

Request

This request follows the **QueryOmStats > SprKpiStats** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2013-10-24T01:50:00Z</StartTime>
    <EndTime>2013-10-24T02:00:00Z</EndTime>
    <SprKpiStats>
      <MediationServer>MDF</MediationServer>
    </SprKpiStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > SprKpiStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- StartTime - Start time of the record.
- EndTime - End time of the stats' record.
- MediationServer - Name of the MDF server which collects the SPR statistic report.
- IsComplete - Indicator for the data Integrity.
- Name - Name of the managed SPR.
- ShelfId - The SPR ShelfId.
- SlotId - The SPR SlotId.
- StatisticStartTime - The real start time for the SPR stats.
- StatisticEndTime - The real end time for the SPR stats.
- CpuUserLoad - Counts the CPU user load.
- CpuNiceLoad - CPU nice load.
- CpuSystemLoad - CPU system load.
- CpuIdleLoad - CPU idle load.
- CpuOverallLoad - CPU overall load.
- LoadAverage1Min - Load average value for 1 minute.
- LoadAverage5Min - Load average value for 5 minutes.
- LoadAverage15Min - Load average value for 15 minutes.
- ProcessListSize - The size of the process list.
- ProcessListSizeDelta - The change (delta) of the size in the process list.
- ProcessRateOfChange - The rate of change in the process list.
- MemoryTotal - Total physical memory (Kb).
- MemoryFree - Free physical memory (Kb).

- MemoryUsed - Used physical memory (Kb).
- MemoryPercentFree - Percentage free physical memory (%).
- MemoryPercentUsed - Percentage used physical memory (%).
- SwapMemoryTotal - Total swap memory (Kb).
- SwapMemoryFree - Free swap memory (Kb).
- SwapMemoryUsed - Used swap memory (Kb).
- SwapMemoryPercentFree - Percentage free swap memory (%).
- SwapMemoryPercentUsed - Percentage used swap memory (%).
- FileSystemSize - File system size.
- FileSystemFreeSpace - File system free space.
- FileSystemUsedSpace - File system used space.
- DiskRead - Disk read operation.
- DiskWrite - Disk write operation.
- BandwidthPublicIf - Bandwidth of public interface (in percent).
- DiscardInPacketsPublicIf - Discarded inbound packets on public interface.
- DiscardOutPacketsPublicIf - Discarded outbound packets on public interface.
- ErrorInPacketsPublicIf - Error inbound packets on public interface.
- ErrorOutPacketsPublicIf - Error outbound packets on public interface.

```
<?xml version="1.0" encoding="UTF-8" ?>
<Statistics>
  <SprKpiStats>
    <Sample>
      <StartTime>2013-10-24T01:50:00Z</StartTime>
      <EndTime>2013-10-24T02:00:00Z</EndTime>
      <MediationServer>MDF</MediationServer>
      <IsComplete>true</IsComplete>
      <Name>spr</Name>
      <ShelfId>1</ShelfId>
      <SlotId>1</SlotId>
      <StatisticStartTime>2013-10-24T01:40:00Z</StatisticStartTime>
      <StatisticEndTime>2013-10-24T01:50:00Z</StatisticEndTime>
      <CpuUserLoad>9.0</CpuUserLoad>
      <CpuNiceLoad>0.743067979812622</CpuNiceLoad>
      <CpuSystemLoad>0.8559849858284</CpuSystemLoad>
      <CpuIdleLoad>88.7033004760742</CpuIdleLoad>
      <CpuOverallLoad>11.0</CpuOverallLoad>
      <LoadAverage1Min>0.98</LoadAverage1Min>
      <LoadAverage5Min>0.69</LoadAverage5Min>
      <LoadAverage15Min>0.72</LoadAverage15Min>
      <ProcessListSize>80.5</ProcessListSize>
      <ProcessListSizeDelta>0.0</ProcessListSizeDelta>
      <ProcessRateOfChange>0.0</ProcessRateOfChange>
      <MemoryTotal>3912720.0</MemoryTotal>
      <MemoryFree>1675670.0</MemoryFree>
      <MemoryUsed>2237050.0</MemoryUsed>
      <MemoryPercentFree>42.82</MemoryPercentFree>
      <MemoryPercentUsed>57.0</MemoryPercentUsed>
      <SwapMemoryTotal>0.0</SwapMemoryTotal>
      <SwapMemoryFree>0.0</SwapMemoryFree>
      <SwapMemoryUsed>0.0</SwapMemoryUsed>
      <SwapMemoryPercentFree>0.0</SwapMemoryPercentFree>
      <SwapMemoryPercentUsed>0.0</SwapMemoryPercentUsed>
      <FileSystemSize>1.93195E7</FileSystemSize>
      <FileSystemFreeSpace>1.28423E7</FileSystemFreeSpace>
      <FileSystemUsedSpace>5495800.0</FileSystemUsedSpace>
```



```

        <DiskRead>0.0</DiskRead>
        <DiskWrite>5804.0</DiskWrite>
        <BankwidthPublicIf>0.0023</BankwidthPublicIf>
        <DiscardInPacketsPublicIf>0.0</DiscardInPacketsPublicIf>
        <DiscardOutPacketsPublicIf>0.0</DiscardOutPacketsPublicIf>
        <ErrorInPacketsPublicIf>0.0</ErrorInPacketsPublicIf>
        <ErrorOutPacketsPublicIf>0.0</ErrorOutPacketsPublicIf>
    </Sample>
</SprKpiStats>
</Statistics>

```

SPR Diameter Sh Message Statistics

The following examples show the request and response that are defined in the XSDs for the DiameterShSprStats tag. This tag provides an historical Diameter Sh report for SPR systems that can be queried every five minutes.

Request

This request follows the **QueryOmStats** > **DiameterShSprStats** tag defined in the XSDs.

The following is an example of this request.

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2013-10-26T02:00:00Z</StartTime>
    <EndTime>2013-10-26T02:20:00Z</EndTime>
    <DiameterShSprStats>
      <MediationServer>MDF</MediationServer>
    </DiameterShSprStats>
  </QueryOmStats>
</XmlInterfaceRequest>

```

Response

The response to this request follows the **Statistics** > **DiameterShSprStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- StartTime - Start time of the record.
- EndTime - End time of the stats' record.
- MediationServer - Name of MDF server which collect SPR statistic report.
- IsComplete - Indicator for the data Integrity.
- Name - Name of the managed spr.
- ShelfId - SPR ShelfId.
- SlotId - SPR SlotId.
- StatisticStartTime - Real start time of SPR stats.
- StatisticEndTime - Real end time of SPR stats.
- NumberOfUDR - Counts the number of UDR messages received by the SPR.
- NumberOfUDA - Counts the total number of UDA messages that have been sent by the SPR.
- NumberOfUDADiamSuccess - Counts the number of UDA messages with 'DIAMETER Success' that have been sent by the SPR.

- NumberOfUDADiamUserUnknown - Counts the number of UDA messages with 'DIAMETER User unknown' that have been sent by the SPR.
- NumberOfUDADiamUnableToComply - Counts the number of UDA messages with 'DIAMETER Unable to comply' that have been sent by the SPR.
- NumberOfUDADiamMissingAVP - Counts the number of UDA messages with 'DIAMETER Missing AVP' that have been sent by the SPR.
- NumberOfUDADiamOpNotAllowed - Counts the number of UDA messages with 'DIAMETER Error Operation not allowed' that have been sent by the SPR.
- NumberOfUDADiamDataCannotBeRead - Counts the number of UDA messages with 'DIAMETER Error user data cannot be read' that have been sent by the SPR.
- NumberOfUDADiamRedirectInd - Counts the number of UDA messages with 'DIAMETER Redirect Indication' that have been sent by the SPR.
- NumberOfUDADiamTooBusy - Counts the number of UDA messages with 'DIAMETER Too Busy' that have been sent by the SPR.
- NumberOfPUR - Counts the number of PUR messages received by the SPR.
- NumberOfPUA - Counts the total number of PUA messages that have been sent by the SPR.
- NumberOfPUADiamSuccess - Counts the number of PUA messages with 'DIAMETER Success' that have been sent by the SPR.
- NumberOfPUADiamUserUnknown - Counts the number of PUA messages with 'DIAMETER User unknown' that have been sent by the SPR.
- NumberOfPUADiamUnableToComply - Counts the number of PUA messages with 'DIAMETER Unable to comply' that have been sent by the SPR.
- NumberOfPUADiamMissingAVP - Counts the number of PUA messages with 'DIAMETER Missing AVP' that have been sent by the SPR.
- NumberOfPUADiamCannotBeModified - Counts the number of PUA messages with 'DIAMETER Error user data cannot be modified' that have been sent by the SPR.
- NumberOfPUADiamOpNotOfSync - Counts the number of PUA messages with 'DIAMETER Error user data cannot be modified' that have been sent by the SPR.
- NumberOfPUADiamDataOutOfSync - Counts the number of PUA messages with 'DIAMETER Error transparent data out of sync' that have been sent by the SPR.
- NumberOfPUADiamTooMuchData - Counts the number of PUA messages with 'DIAMETER Error too much data' that have been sent by the SPR.
- NumberOfPUADiamRedirectInd - Counts the number of PUA messages with 'DIAMETER Redirect Indication' that have been sent by the SPR.
- NumberOfPUADiamTooBusy - Counts the number of PUA messages with 'DIAMETER Too Busy' that have been sent by the SPR.
- NumberOfSNR - Counts the number of SNR messages received by the SPR.
- NumberOfSNA - Counts the total number of SNA messages that have been sent by the SPR.
- NumberOfSNADiamSuccess - Counts the total number of SNA messages that have been sent by the SPR.
- NumberOfSNADiamUserUnknown - Counts the number of SNA messages with 'DIAMETER User unknown' that have been sent by the SPR.
- NumberOfSNADiamUnableToComply - Counts the number of SNA messages with 'DIAMETER Unable to comply' that have been sent by the SPR.
- NumberOfSNADiamMissingAVP - Counts the number of SNA messages with 'DIAMETER Missing AVP' that have been sent by the SPR.
- NumberOfSNADiamDataCannotBeNotified - Counts the number of SNA messages with 'DIAMETER Missing AVP' that have been sent by the SPR.

Operational Measurement Requests for Mediation Server

- NumberOfSNADiamOpNotAllowed - Counts the number of SNA messages with 'DIAMETER Error Operation not allowed' that have been sent by the SPR.
- NumberOfSNADiamRedirectInd - Counts the number of SNA messages with 'DIAMETER Redirect Indication' that have been sent by the SPR.
- NumberOfSNADiamTooBusy - Counts the number of SNA messages with 'DIAMETER Redirect Indication' that have been sent by the SPR.
- NumberOfPNA - Counts the number of PNA messages received by the SPR.
- NumberOfPNAFailed - Counts the number of PNA messages with 'DIAMETER Failed' that have been received by the SPR.
- NumberOfPNR - Counts the number of PNR messages sent by the SPR.
- NumberOfPNRRemoteRcd - Counts the number of PNR messages sent by the SPR.
- NumberOfPNRRemoteSent - Counts the number of PNR messages sent by the SPR.

```
<?xml version="1.0" encoding="UTF-8" ?>
<Statistics>
  <DiameterShSprStats>
    <Sample>
      <StartTime>2013-10-26T02:10:00Z</StartTime>
      <EndTime>2013-10-26T02:15:00Z</EndTime>
      <MediationServer>MDF</MediationServer>
      <IsComplete>true</IsComplete>
      <Name>spr</Name>
      <ShelfId>1</ShelfId>
      <SlotId>1</SlotId>
      <StatisticStartTime>2013-10-26T02:00:00Z </StatisticStartTime>
      <StatisticEndTime>2013-10-26T02:10:00Z </StatisticEndTime>
      <NumberOfUDR>1.0</NumberOfUDR>
      <NumberOfUDA>1.0</NumberOfUDA>
      <NumberOfUDADiamSuccess>0</NumberOfUDADiamSuccess>
      <NumberOfUDADiamUserUnknown>0</NumberOfUDADiamUserUnknown>
      <NumberOfUDADiamUnableToComply>0</NumberOfUDADiamUnableToComply>
      <NumberOfUDADiamMissingAVP>0</NumberOfUDADiamMissingAVP>
      <NumberOfUDADiamOpNotAllowed>0</NumberOfUDADiamOpNotAllowed>
      <NumberOfUDADiamDataCannotBeRead>0</NumberOfUDADiamDataCannotBeRead>
      <NumberOfUDADiamRedirectInd>0</NumberOfUDADiamRedirectInd>
      <NumberOfUDADiamTooBusy>0</NumberOfUDADiamTooBusy>
      <NumberOfPUR>0</NumberOfPUR>
      <NumberOfPUA>0</NumberOfPUA>
      <NumberOfPUADiamSuccess>0</NumberOfPUADiamSuccess>
      <NumberOfPUADiamUserUnknown>0</NumberOfPUADiamUserUnknown>
      <NumberOfPUADiamUnableToComply>0</NumberOfPUADiamUnableToComply>
      <NumberOfPUADiamMissingAVP>0</NumberOfPUADiamMissingAVP>
      <NumberOfPUADiamCannotBeModified>0</NumberOfPUADiamCannotBeModified>
      <NumberOfPUADiamOpNotOfSync>0</NumberOfPUADiamOpNotOfSync>
      <NumberOfPUADiamDataOutOfSync>0</NumberOfPUADiamDataOutOfSync>
      <NumberOfPUADiamTooMuchData>0</NumberOfPUADiamTooMuchData>
      <NumberOfPUADiamRedirectInd>0</NumberOfPUADiamRedirectInd>
      <NumberOfPUADiamTooBusy>0</NumberOfPUADiamTooBusy>
      <NumberOfSNR>0</NumberOfSNR>
      <NumberOfSNA>0</NumberOfSNA>
      <NumberOfSNADiamSuccess>0</NumberOfSNADiamSuccess>
      <NumberOfSNADiamUserUnknown>0</NumberOfSNADiamUserUnknown>
      <NumberOfSNADiamUnableToComply>0</NumberOfSNADiamUnableToComply>
      <NumberOfSNADiamMissingAVP>0</NumberOfSNADiamMissingAVP>
      <NumberOfSNADiamDataCannotBeNotified>0</NumberOfSNADiamDataCannotBeNotified>

      <NumberOfSNADiamOpNotAllowed>0</NumberOfSNADiamOpNotAllowed>
      <NumberOfSNADiamRedirectInd>0</NumberOfSNADiamRedirectInd>
      <NumberOfSNADiamTooBusy>0</NumberOfSNADiamTooBusy>
```

```
<NumberOfPNA>0</NumberOfPNA>
<NumberOfPNAFailed>0</NumberOfPNAFailed>
<NumberOfPNR>0</NumberOfPNR>
<NumberOfPNRRemoteRced>0</NumberOfPNRRemoteRced>
<NumberOfPNRRemoteSent>0</NumberOfPNRRemoteSent>
</Sample>
</DiameterShSprStats>
</Statistics>
```

SPR Active Alarm

The following examples show the request and response that are defined in the XSDs for the `SprOamAlarm` tag. This tag provides an historical Diameter Sh report for SPR systems that can be queried every five minutes.

Request

This request follows the **QueryOmStats > SprOamAlarm** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8"?>
<XmlInterfaceRequest>
  <QuerySprOamAlarm >
    <MediationServer>mediation</MediationServer>
  </QuerySprOamAlarm>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > SprOamAlarm** tag defined in the XSDs.

Individual statistics are defined as follows:

- **MediationServer** - MDF server's name whose collect active alarm from Oracle SPR.
- **Name** - Name of the managed spr.
- **ShelfId** - SPR ShelfId.
- **SlotId** - SPR SlotId.
- **SequenceId** - Read only. Numerical identifier uniquely identifies this specific alarm occurrence.
- **AlarmId** - Real start time of SPR stats.
- **Severity** - The severity of the alarm: `AlarmCritical`, `AlarmMajor`, `AlarmMinor`, `AlarmWarning`.
- **Description** - Text description of alarm condition.
- **ComponentInstanceContext** - Represents the specific instance of the module and/or component which generated the alarm Context condition.
- **SetTimeStamp** - The date and time the alarm was generated. Timestamp format: Day - *MMM DD, hh:mm:ss YYYY*.
- **SetBy** - Username of the user that acknowledged the alarm. the value of this parameter is generated by the system.
- **NumberOfOccurance** - Number of occurrence.

- IsAcknowledge - false= alarm not acknowledged, true=alarm has been acknowledged.

```
<?xml version="1.0" encoding="UTF-8" ?>
<ConfigurationData>
  <Spr0amAlarm>
    <MediationServer>mediation</MediationServer>
    <Name>carson_spr</Name>
    <ShelfId>1</ShelfId>
    <SlotId>1</SlotId>
    <SequenceId>26</SequenceId>
    <AlarmId>323</AlarmId>
    <Severity>7</Severity>
    <Description>Time: NTP daemon initializing</Description>
    <ComponentInstanceContext/>
    <SetTimeStamp>Fri Nov 8 01:56:24 2013</SetTimeStamp>
    <SetBy>NodeManager</SetBy>
    <ActTimeStamp/>
    <ActBy/>
    <NumberOfOccurance>1</NumberOfOccurance>
    <IsAcknowledge>>false</IsAcknowledge>
  </Spr0amAlarm>
</ConfigurationData>
```

Mediation Server Active Alarm

The following examples show the request and response that are defined in the XSDs for the QueryActiveAlarm tag. This tag provides an historical Diameter Sh report for SPR systems that can be queried every five minutes.

Request

This request follows the **QueryActiveAlarm** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryActiveAlarm>
  </QueryActiveAlarm>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData > QueryActiveAlarm** tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" ?>
<ConfigurationData>
  <ActiveAlarm>
    <Name>mdf</Name>
    <MediationServer>mdf-server-site-sourl</MediationServer>
    <Hostname>kt-mdf-blade-a</Hostname>
    <ServerIP>192.168.1.115</ServerIP>
    <Severity>Minor</Severity>
```

```
<AlarmId>32509</AlarmId>
<Instance/>
<Description>Server NTP Daemon Not Synchronized</Description>
<Time>2013-11-21T09:01:44Z</Time>
<Details>GN_WARNING/WRN Platform detected an error condition
[cmplatalarm.cxx:252]
^^ Additional details captured in /var/TKLC/log/syscheck/fail_log (timestamp:
1385024504) [cmplatalarm.cxx:256]
^^ [4659:cmplatalarm.cxx:257]</Details>
</ActiveAlarm>
</ConfigurationData>
```

Mediation Server HA Statistic

The following examples show the request and response that are defined in the XSDs for the QueryHAServer tag.

Request

This request follows the **QueryHAServer** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryHAServer>
  </QueryHAServer>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **ConfigurationData** > **Server** tag defined in the XSDs.

Individual statistics are defined as follows:

- MediationServer - MDF server's name.
- Cluster - Topology identity of the HA server group.
- Hostname - Host name of the blade server.
- ServerIP - IP address of the blade server.
- BladeStatus - HA status of the blade server. Support options: Active ,Stby(StandBy) and OOS(Out of Service).
- CPUUtilizationPercentage - CPU usage shown as a percentage.
- MemoryUtilizationPercentage - Percentage of all memory usage including physical memory and virtual memory.
- DiskUtilizationPercentage - Percentage of disk used.
- FailureCount - HA counter of service failure.
- UpTimeMillis - The number of seconds showing how long the PCRf services have ran since it started.
- Processes - The PCRf processes running on the server.

```
<?xml version="1.0" encoding="UTF-8" ?>
```

```
<ConfigurationData>
  <Server>
    <MediationServer>MDF</MediationServer>
    <Cluster>mediation</Cluster>
    <Hostname>jshao-32-102-mediation</Hostname>
    <ServerIP>10.60.32.102</ServerIP>
    <BladeStatus>Active</BladeStatus>
    <CPUUtilizationPercentage>1</CPUUtilizationPercentage>
    <MemoryUtilizationPercentage>127</MemoryUtilizationPercentage>
    <DiskUtilizationPercentage>5</DiskUtilizationPercentage>
    <FailureCount>3</FailureCount>
    <UpTimeMillis>96539</UpTimeMillis>
    <Processes>
      <Process>bandwidth-of-demand(11333)</Process>
      <Process>tomcat(11344)</Process>
      <Process>comcolMonitor(11348)</Process>
      <Process>routeMgr(11349)</Process>
      <Process>wbsync(11350)</Process>
    </Processes>
  </Server>
</ConfigurationData>
```

Mediation Server KPI and OM Statistics

The following examples show the request and response that are defined in the XSDs for the KpiStats tag.

Request

This request follows the **QueryOmStats > KpiStats** tag defined in the XSDs.

The following is an example of this request.

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <QueryOmStats>
    <StartTime>2013-11-09T12:10:00Z</StartTime>
    <EndTime>2013-11-12T12:15:00Z</EndTime>
    <KpiStats>
      <MediationServer>mediation</MediationServer>
    </KpiStats>
  </QueryOmStats>
</XmlInterfaceRequest>
```

Response

The response to this request follows the **Statistics > KpiStats** tag defined in the XSDs.

Individual statistics are defined as follows:

- PrimaryCPUUtilizationPercentage - The snapshot on the CPU utilization percentage for the active server.
- PrimaryMemoryUtilizationPercentage - The snapshot on the Memory utilization percentage for the active server.
- PrimaryDiskUtilizationPercentage - The snapshot on the Disk utilization percentage for the active server.

Operational Measurement Requests for Mediation Server

- PrimaryServerFailureCount - The snapshot on the server failure counter for the active server.
- PrimaryServerStatus - The HA status for the active server.
- SecondaryCPUUtilizationPercentage - The snapshot on the CPU utilization percentage for the standby server.
- SecondaryMemoryUtilizationPercentage - The snapshot on the Memory utilization percentage for the standby server.
- SecondaryDiskUtilizationPercentage - The snapshot on the Disk utilization percentage for the standby server.
- SecondaryServerFailureCount - The snapshot on the server failure counter for the standby server.
- SecondaryServerStatus - The HA status for standby server.
- ServerACPUUtilizationPercentage - The snapshot on the CPU utilization percentage for Server A on the topology setting page.
- ServerAMemoryUtilizationPercentage - The snapshot on the Memory utilization percentage for Server A on the topology setting page.
- ServerADiskUtilizationPercentage - The snapshot on the Disk utilization percentage for Server A on the topology setting page.
- ServerAServerFailureCount - The snapshot on the server failure counter for Server A on the topology setting page.
- ServerAServerStatus - The HA status for Server A on the topology setting page.
- ServerBCPUUtilizationPercentage - The snapshot on the CPU utilization percentage for Server B on the topology setting page.
- ServerBMemoryUtilizationPercentage - The snapshot on the Memory utilization percentage for Server B on the topology setting page.
- ServerBDiskUtilizationPercentage - The snapshot on the Disk utilization percentage for Server B on the topology setting page.
- ServerBServerFailureCount - The snapshot on the server failure counter for Server B on the topology setting page.
- ServerBServerStatus - The HA status for Server B on the topology setting page.
- ServerCCPUUtilizationPercentage - The snapshot on the CPU utilization percentage for Server C on the topology setting page.
- ServerCMemoryUtilizationPercentage - The snapshot on the Memory utilization percentage for Server C on the topology setting page.
- ServerCDiskUtilizationPercentage - The snapshot on the Disk utilization percentage for Server C on the topology setting page.
- ServerCServerFailureCount - The snapshot on the server failure counter for Server C on the topology setting page.
- ServerCServerStatus - The HA status for Server C on the topology setting page.

```
<?xml version="1.0" encoding="UTF-8" ?>
<Statistics>
  <KpiStats>
    <Sample>
      <StartTime>2012-10-30T09:00:00Z</StartTime>
      <EndTime>2012-10-30T09:15:00Z</EndTime>
      <MediationServer>mediation</MediationServer>
      <IsComplete>true</IsComplete>
      <PrimaryCPUUtilizationPercentage>12</PrimaryCPUUtilizationPercentage>
      <PrimaryMemoryUtilizationPercentage>108</PrimaryMemoryUtilizationPercentage>
      <PrimaryDiskUtilizationPercentage>2</PrimaryDiskUtilizationPercentage>
    </Sample>
  </KpiStats>
</Statistics>
```


Operational Measurement Requests for Mediation Server

```
<PrimaryBladeFailureCount>4</PrimaryBladeFailureCount>
<PrimaryUpTimeMillis>23264000</PrimaryUpTimeMillis>
<PrimaryBladeStatus>12</PrimaryBladeStatus>
<SecondaryCPUUtilizationPercentage>0</SecondaryCPUUtilizationPercentage>
<SecondaryMemoryUtilizationPercentage>0</SecondaryMemoryUtilizationPercentage>
<SecondaryDiskUtilizationPercentage>0</SecondaryDiskUtilizationPercentage>

<SecondaryBladeFailureCount>0</SecondaryBladeFailureCount>
<SecondaryUpTimeMillis>0</SecondaryUpTimeMillis>
<SecondaryBladeStatus>0</SecondaryBladeStatus>
<ServerACPUUtilizationPercentage>12</ServerACPUUtilizationPercentage>
<ServerAMemoryUtilizationPercentage>108</ServerAMemoryUtilizationPercentage>

<ServerADiskUtilizationPercentage>2</ServerADiskUtilizationPercentage>
<ServerABladeFailureCount>4</ServerABladeFailureCount>
<ServerAUpTimeMillis>23264000</ServerAUpTimeMillis>
<ServerABladeStatus>12</ServerABladeStatus>
<ServerBCPUUtilizationPercentage>0</ServerBCPUUtilizationPercentage>
<ServerBMemoryUtilizationPercentage>0</ServerBMemoryUtilizationPercentage>

<ServerBDiskUtilizationPercentage>0</ServerBDiskUtilizationPercentage>
<ServerBBladeFailureCount>0</ServerBBladeFailureCount>
<ServerBUpTimeMillis>0</ServerBUpTimeMillis>
<ServerBBladeStatus>0</ServerBBladeStatus>
<ServerCCPUUtilizationPercentage>0</ServerCCPUUtilizationPercentage>
<ServerCMemoryUtilizationPercentage>0</ServerCMemoryUtilizationPercentage>

<ServerCDiskUtilizationPercentage>0</ServerCDiskUtilizationPercentage>
<ServerCBladeFailureCount>0</ServerCBladeFailureCount>
<ServerCUpTimeMillis>0</ServerCUpTimeMillis>
<ServerCBladeStatus>0</ServerCBladeStatus>
</Sample>
</KpiStats>
</Statistics>
```

Chapter 10

Identity Management (IDM)

Topics:

- [Identity Management Overview.....227](#)
- [Add a User.....227](#)
- [Update a User.....233](#)
- [Query a User.....237](#)
- [Delete a User.....238](#)
- [Query User Role.....239](#)
- [Query User Scope.....242](#)

Identity Management (IDM) allows the CMP to configure user names, passwords and roles using the OSSI interface. It also allows querying of user scopes and roles.

Identity Management Overview

The Identity Management system connects to a CMP through an HTTP or HTTPS interface. The user must specify the operation parameter `idm` in the requested URL, similar to `http://127.0.0.1/mi/xmlInterfaceRequest.do?user=supervisor&pwd=password&operation=idm`.

The account used for connecting the OSSI to the CMP is a regular CMP user account, with the default global scope and the following privileges:

- Show Privilege for OSSI Import/Export
- Read-Write Privilege for User Management

The Identity Management feature allows users to perform the following tasks:

- *Add a User* - Create one or more users, or update a current user's parameters by overwriting them with new parameters.
- *Update a User* - Update parameters for one or more users.
- *Query a User* - Query one user if the Name element occurs, or all users if no Name element occurs.
- *Delete a User* - Delete one or more users.
- *Query User Role* - Query one role if the Name element occurs, or all roles if no Name element occurs.
- *Query User Scope* - Query one scope if the Name element occurs, or all scopes if no Name element occurs.

Add a User

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the `AddSysAdminUser` tag.

Successful Request

Request

This request follows the `AddSysAdminUser` tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>The default administrator user with all
privileges</Description>
      <Password>camiant</Password>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name>Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </AddSysAdminUser>
</XmlInterfaceRequest>
```

```

    </SysAdminUser>
  </AddSysAdminUser>
</XmlInterfaceRequest>

```

The AddSysAdminUser operation parameters are:

- Name Required() — 250 characters (string)
- Description (Optional) — 250 characters (string)
- Password (Required) — A clear text
- LockedStatus (Required) — 0 = unlocked; 1 = locked
- RoleRef (Required) — Can specify only one role
- ScopeRef (Required) — Can specify multiple scopes

Request

This request follows the AddSysAdminUser tag defined in the XSDs.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully imported 1 User(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>

```

The AddSysAdminUser errors that a user may receive are:

- ERROR_USER_INVALID_NAME — Invalid User Name for: '{\$UserName}'; UserName is an empty string.
- ERROR_USER_NAME_TOO_LONG — User Name exceeds max length for: '{\$UserName}'; UserName exceeds max length (250 characters).
- ERROR_USER_DESCRIPTION_TOO_LONG — User Description exceeds max length. User: '{\$UserName}'; Description exceeds max length (250 characters)
- ERROR_USER_NOROLE_OR_NOSCOPE — User: '{\$Username}' must have an associated Role and Scope.; Non-Role or non-Scope is defined in OSSI command.
- ERROR_USER_INVALID_ROLE_NAME — Invalid Role Name for: '{\$RoleName}'; RoleName is an empty string, or RoleName exceeds max length (250 characters), or there is more than one Role defined.
- ERROR_USER_INVALID_SCOPE_NAME — Invalid Scope Name for: '{\$ScopeName}'; ScopeName is an empty string, or ScopeName is exceeds max length (250 characters).
- ERROR_USER_ROLE_LINK — The user: {\$UserName}'s associated role does not exist. Please create it first.; RoleName is not defined in CMP.
- ERROR_USER_SCOPE_LINK — The user: {\$UserName}'s associated scope does not exist. Please create it first.; ScopeName is not defined in CMP.
- ERROR_SCHEMA_INVALID — N/A; If the input OSSI command cannot match the schema specification, there will be an error-message response to the operator. For example, if you define a LockStatus with a string, the following message will be reported: "Error parsing import file: Error parsing import file: cvc-datatype-valid.1.2.1: 'ABC' is not a valid value for 'integer'."

ERROR_USER_INVALID_NAME**Request**

This request follows the AddSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSysAdminUser>
    <SysAdminUser>
      <Name></Name>
      <Description>The default administrator user with all
privileges</Description>
      <Password>oracle</Password>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name>Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </AddSysAdminUser>
</XmlInterfaceRequest>
```

Request

The following error response occurs when the user name is invalid.

```
<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to import 1 User(s).

    Invalid User Name for: ''</Failure>
  </Command>
</Response>
```

ERROR_USER_INVALID_ROLE_NAME**Request**

This request follows the AddSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>The default administrator user with all
privileges</Description>
      <Password>oracle</Password>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name></Name>
      </RoleRef>
      <ScopeRef>
```

```

        <Name>Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </AddSysAdminUser>
</XmlInterfaceRequest>

```

Request

The following error response occurs when the role name is invalid.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to import 1 User(s).

    Invalid Role Name for: 'admin1'</Failure>
  </Command>
</Response>

```

ERROR_USER_INVALID_SCOPE_NAME

Request

This request follows the AddSysAdminUser tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>The default administrator user with all
privileges</Description>
      <Password>oracle</Password>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name></Name>
      </ScopeRef>
    </SysAdminUser>
  </AddSysAdminUser>
</XmlInterfaceRequest>

```

Request

The following error response occurs when the scope name is invalid.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to import 1 User(s).

```

```

    Invalid Scope Name for: 'admin1'</Failure>
  </Command>
</Response>

```

ERROR_USER_ROLE_LINK

Request

This request follows the AddSysAdminUser tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>The default administrator user with all
privileges</Description>
      <Password>oracle</Password>
      <LockedStatus>0</LockedStatus>
      <ScopeRef>
        <Name>Not Exist Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </AddSysAdminUser>
</XmlInterfaceRequest>

```

Request

The following error response occurs when the user's associated role does not exist.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to import 1 User(s).

    User: 'admin1' must have an associated Role and Scope.</Failure>
  </Command>
</Response>

```

ERROR_USER_NOROLE_OR_NOSCOPE

Request

This request follows the AddSysAdminUser tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>The default administrator user with all
privileges</Description>
      <Password>oracle</Password>
      <LockedStatus>0</LockedStatus>

```

```

    <RoleRef>
      <Name>Not Exits Administrator</Name>
    </RoleRef>
    <ScopeRef>
      <Name>Global</Name>
    </ScopeRef>
  </SysAdminUser>
</AddSysAdminUser>
</XmlInterfaceRequest>

```

Request

The following error response occurs when the user's role does not exist.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to import 1 User(s).

    The user: admin1's associated role does not exist. Please create it
    first.</Failure>
  </Command>
</Response>

```

Request

This request follows the AddSysAdminUser tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <AddSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>The default administrator user with all
privileges</Description>
      <Password>oracle</Password>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name>Not Exist Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </AddSysAdminUser>
</XmlInterfaceRequest>

```

Request

The following error response occurs when the user's scope does not exist.

```

<?xml version='1.0' ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>

```



```
<Failure count="1">Failed to import 1 User(s).

  The user: admin1's associated scope does not exist. Please create it
first.</Failure>
</Command>
</Response>
```

Update a User

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the UpdateSysAdminUser tag.

Request

This request follows the UpdateSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>New The default administrator user with all
        privileges</Description>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name>Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </UpdateSysAdminUser>
</XmlInterfaceRequest>
```

The UpdateSysAdminUser operation parameters are:

- Name(Required) — 250 characters (string)
- Description (Optional) — 250 characters (string)
- Password(Optional) — A clear text
- LockedStatus (Optional) — 0 = unlocked; 1 = locked
- RoleRef (Optional) — Can specify only one role
- ScopeRef (Optional) — Can specify multiple scopes

The probable errors a user may receive are as follows:

- ERROR_USER_NAME_NOT_EXIST — Specified User does not exist:
'\${UserName}'; The specified user is not in system.
- ERROR_USER_INVALID_NAME — Invalid User Name for: '\${UserName}'; User Name is an empty string.;
- ERROR_USER_NAME_TOO_LONG — User Name exceeds max length for:
'\${UserName}'; UserName exceeds max length (250 characters).

- **ERROR_USER_DESCRIPTION_TOO_LONG** — User Description exceeds max length. User: '{ \$UserName}'; Description exceeds max length (250 characters)
- **ERROR_USER_NOROLE_OR_NOSCOPE** — User: '{ \$Username}' must have an associated Role and Scope.; Non-Role or non-Scope is defined in OSSI command.
- **ERROR_USER_INVALID_ROLE_NAME** — Invalid Role Name for: '{ \$RoleName}'; RoleName exceeds max length (250 characters), or There is more than one Role defined.
- **ERROR_USER_INVALID_SCOPE_NAME** — Invalid Scope Name for: '{ \$ScopeName}'; ScopeName exceeds max length (250 characters).
- **ERROR_USER_ROLE_LINK** — The user: { \$UserName}'s associated role does not exist. Please create it first.; RoleName is an empty string, or RoleName is not defined in CMP.
- **ERROR_USER_SCOPE_LINK** — The user: { \$UserName}'s associated scope does not exist. Please create it first.; ScopeName is an empty string, or ScopeName is not defined in CMP.
- **ERROR_SCHEMA_INVALID** — N/A; If the input OSSI command cannot match the schema specification, there will be an error-message response to the operator. For example, if you define a LockStatus with a string, the following message will be reported: "Error parsing import file: Error parsing import file: cvc-datatype-valid.1.2.1: 'ABC' is not a valid value for 'integer'."

Response

The response to this request follows the generic Response tag defined in the XSDs.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="1">Successfully updated 1 User(s).</Success>
    <Failure count="0"></Failure>
  </Command>
</Response>
```

ERROR_USER_NAME_NOT_EXIST

Request

This request follows the UpdateSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateSysAdminUser>
    <SysAdminUser>
      <Name>NotExistadmin1</Name>
      <Description>New The default administrator user with all
        privileges</Description>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name>Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </UpdateSysAdminUser>
</XmlInterfaceRequest>
```

```
</UpdateSysAdminUser>
</XmlInterfaceRequest>
```

Response

The following error response occurs when the user name does not exist.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to update 1 User(s).

    Specified User does not exist: "NotExistadmin1"</Failure>
  </Command>
</Response>
```

ERROR_USER_NOROLE_OR_NOSCOPE

Request

This request follows the UpdateSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>New The default administrator user with all
        privileges</Description>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>not exist Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name>Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </UpdateSysAdminUser>
</XmlInterfaceRequest>
```

Response

The following error response occurs when the user's specified role does not exist.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to update 1 User(s).

    The user: admin1's associated role does not exist. Please create it
    first.</Failure>
  </Command>
</Response>
```

Request

This request follows the UpdateSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>New The default administrator user with all
        privileges</Description>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
      <ScopeRef>
        <Name>Not exist Global</Name>
      </ScopeRef>
    </SysAdminUser>
  </UpdateSysAdminUser>
</XmlInterfaceRequest>
```

Response

The following error response occurs when the user's specified scope does not exist.

```
<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to update 1 User(s).

    The user: admin1's associated scope does not exist. Please create it
    first.</Failure>
  </Command>
</Response>
```

ERROR_USER_INVALID_ROLE_NAME

Request

This request follows the UpdateSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <UpdateSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
      <Description>New The default administrator user with all
        privileges</Description>
      <LockedStatus>0</LockedStatus>
      <RoleRef>
        <Name>123</Name>
      </RoleRef>
      <RoleRef>
        <Name>Administrator</Name>
      </RoleRef>
    </SysAdminUser>
  </UpdateSysAdminUser>
</XmlInterfaceRequest>
```

```

    <ScopeRef>
      <Name>123</Name>
    </ScopeRef>
  </SysAdminUser>
</UpdateSysAdminUser>
</XmlInterfaceRequest>

```

Response

The following error response occurs when the role name either exceeds the maximum length of 250 characters, or there is more than one Role defined.

```

<?xml version="1.0" ?>
<Response>
  <Result>0</Result>
  <Command type="XmlInterfaceResponse">
    <Success count="0"></Success>
    <Failure count="1">Failed to update 1 User(s).

    Invalid Role Name for: "admin1"</Failure>
  </Command>
</Response>

```

Query a User

The following examples show the request and response that are defined in the XSDs for the QuerySysAdminUser tag. If the Name element occurs, the CMP will query only the corresponding user; otherwise, all users are queried.

Request

This request follows the QuerySysAdminUser tag defined in the XSDs.

```

<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QuerySysAdminUser>
    <Name>admin</Name>
  </QuerySysAdminUser>
</XmlInterfaceRequest>

```

The QuerySysAdminUser operation parameters are as follows:

- Name (Optional) — 250 characters (string)

If the query is successful, the list of users will be returned in XML as a response with the following fields for each user.

The output fields for QuerySysAdminUser operation are as follows:

- Name — The user's name
- Description — The user's description
- Password — The user's password, encrypted
- LockedStatus — 0 = locked, 1 = unlocked

- RoleRef — The associated role
- ScopeRef — The associated scope; there can be multiple scopes.

Response

The response to this request:

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="7.5.0">
  <SysAdminUser>
    <Name>admin</Name>
    <Description>The default administrator user with all
privileges</Description>
    <Password>835154D6D3FA2C3575AA700A54AB9F6492E7ABB7</Password>
    <LockedStatus>0</LockedStatus>
    <RoleRef>
      <Name>Administrator</Name>
    </RoleRef>
    <ScopeRef>
      <Name>Global</Name>
    </ScopeRef>
  </SysAdminUser>
</ConfigurationData>
```

Delete a User

Note: This query is not available to Policy servers in NW-CMP mode.

The following examples show the request and response that are defined in the XSDs for the DeleteSysAdminUser tag.

Successful Deletion

Request

This request follows the DeleteSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <DeleteSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
    </SysAdminUser>
  </DeleteSysAdminUser>
</XmlInterfaceRequest>
```

The DeleteSysAdminUser operation parameters are as follows:

- Name (Required) — 250 characters (string)

The probable DeleteSysAdminUser errors a user may receive are as follows:

- ERROR_DELETE_FAILURE — Message Error deleting User Name: {\$UserName}; The specified user does not exist, or Admin user is specified.

Request

The response to this request:

```
<?xml version='1.0' ?>
<Response>
<Result>0</Result>
<Command type="XmlInterfaceResponse">
<Success count="1">Deleted 1 users.</Success>
<Failure count="0"></Failure>
</Command>
</Response>
```

If deletion is successful, the number of deleted users will be reported.

ERROR_DELETE_FAILURE

Request

This request follows the DeleteSysAdminUser tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <DeleteSysAdminUser>
    <SysAdminUser>
      <Name>admin1</Name>
    </SysAdminUser>
  </DeleteSysAdminUser>
</XmlInterfaceRequest>
```

Request

The response to this request when the specified user name does not exist:

```
<?xml version='1.0' ?>
<Response>
<Result>0</Result>
<Command type="XmlInterfaceResponse">
<Success count="0"></Success>
<Failure count="1">Failed to delete 1 user.
Error deleting User Name: admin1</Failure>
</Command>
</Response>
```

Query User Role

The following examples show the request and response that are defined in the XSDs for the QueryRole tag. If the Name element occurs, the CMP will query the corresponding role with the name; otherwise, it will query all roles.

Request

This request follows the QueryRole tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QueryRole>
    <Name>Administrator</Name>
  </QueryRole>
</XmlInterfaceRequest>
```

QueryRole Operation Parameters

- Name — (Optional) 250 characters (string)

If the query is successful, the list of users will be returned in XML as a response with the following fields for each user.

Output Fields for QueryRole Operation

- Name — The role's name
- Description — The role's description
- RolePrivilege — The privilege with privilege name and access level assigned to the Role. There can be multiple privileges.

Response

The response to this request:

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="7.5.0">
  <Role>
    <Name>Administrator</Name>
    <Description>The default role with all privileges</Description>
    <RolePrivilege>
      <Privilege>policy server</Privilege>
      <Level>40</Level>
    </RolePrivilege>
    <RolePrivilege>
      <Privilege>Network Element</Privilege>
      <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
      <Privilege>Application</Privilege>
      <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
      <Privilege>Policy Library</Privilege>
      <Level>Read, Deploy, and Write</Level>
    </RolePrivilege>
    <RolePrivilege>
      <Privilege>Template Library</Privilege>
      <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
      <Privilege>User Management</Privilege>
      <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
      <Privilege>Manager Event and Audit Logs</Privilege>
      <Level>Read-Write</Level>
    </RolePrivilege>
  </Role>
</ConfigurationData>
```



```

        <Privilege>Tasks</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>License Management</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Traffic Profiles</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>XML Import / Export</Privilege>
        <Level>Show</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Operational Measurements</Privilege>
        <Level>Read-Only</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Charging Server</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Time Period</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Policy Import / Export</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Alarms</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Audit Log User Info</Privilege>
        <Level>Show</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Password Strength</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Event Log</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
    <RolePrivilege>
        <Privilege>Audit Log</Privilege>
        <Level>Read-Write</Level>
    </RolePrivilege>
</Role>
</ConfigurationData>

```

A subset of the RolePrivilege element will be outputted in XML based on the mode selected by the operator. The output XML cannot be imported to the CMP again.

Query User Scope

The following examples show the request and response that are defined in the XSDs for the QueryScope tag. If the Name element occurs, the CMP will query only the corresponding scope, otherwise all scopes are queried.

Request

This request follows the QueryScope tag defined in the XSDs.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<XmlInterfaceRequest>
  <QueryScope>
    <Name>Global</Name>
  </QueryScope>
</XmlInterfaceRequest>
```

If query is successful, the list of the scopes will be returned in XML as a response. If no Ref element occurs, it means the scope is a global scope in system.

QueryScope Operation Parameters

- Name — (Optional) 250 characters (string)

If the query is successful, the list of the roles will be returned in XML as a response.

Output Fields for QueryScope Operation

- Name — The scope's name
- Description — The scope's description
- ResourceControllerGroupRef — The manageable MPES' name set.
- MRAGroupRef — The manageable MRAs' name set.
- NetworkElementGroupRef — The manageable Network Elements' name set.

Response

The response to this request:

```
<?xml version="1.0" encoding="UTF-8" standalone="yes"?>
<ConfigurationData version="7.5.0">
  <Scope>
    <Name>Global</Name>
    <Description>The default scope that automatically contains all items in
the system</Description>
  </Scope>
</ConfigurationData>
```

A subset of the Ref element will be outputted in XML based on the mode selected by the operator. The output XML cannot be imported to the CMP again.

Chapter 11

Policy Table Interface

Topics:

- [Policy Table Overview.....244](#)
- [Exported Policy Table XML.....244](#)
- [Add a Policy Table.....245](#)
- [Modify a Policy Table.....245](#)
- [Delete a Policy Table.....246](#)

Table-driven policies allows you to generalize multiple similar policies into a single policy that represents the policy structure, plus a policy table(s) that captures the differences. These tables make processes such as adding new policies, modifying existing policies, and checking consistency among policies, much simpler and less error prone.

Policy Table Overview

Policy Tables can be imported or exported to the OSSI XML Interface using the CMP. See "Importing to and Exporting from the CMP Database" in the *CMP Wireless User Guide* for details on using the OSSI XML Interface.

Policy tables can be exported to the OSSI XML Interface, and then edited or replaced. Tables can also be imported from the OSSI back to the CMP with changes, as new tables, or to delete an existing table.

The format for both export and import must be the same and must include:

- The policy table's name
- The policy table's description
- The names of the columns
- The data types of the columns
- The designation of which columns are keys
- The policy context variables for key columns
- The values in the cells

Exported Policy Table XML

The exported policy table will be in an XML file; see the example below. Descriptions of the fields are given after the table.

The XML for a policy table must maintain the integrity of the table.

```
<?xml version="1.0" encoding="UTF-8" standalone="yes" ?>
<XmlInterfaceRequest>
<AddPolicyTableData>
  <PolicyTableData>
    <Name>T</Name>
    <Description>ABC</Description>
    <Table>
      <Header>
        <Field Type="smartString255" Key="true" Field="TA">TA</Field>
      </Header>
      <Record Name="1330657994893">
        <Field Field="TA">TA</Field>
      </Record>
      <Record Name="1330657994894">
        <Field Field="TA">TAsssss</Field>
      </Record>
    </Table>
  </PolicyTableData>
  <PolicyTableData>
    <Name>T2</Name>
    <Description>TABLE11111111111111111111111111111111</Description>
    <Table>
      <Header>
        <Field Type="smartString255" Key="true" Field="TA">TA</Field>
      </Header>
      <Record Name="1330657994893">
        <Field Field="TA">TA</Field>
      </Record>
    </Table>
  </PolicyTableData>
</AddPolicyTableData>
</XmlInterfaceRequest>
```

```

</Record>\
<Record Name="1330657994894">
  <Field Field="TA">TAsssss</Field>
</Record>
</Table>
</PolicyTableData>
</AddPolicyTableData>
</XmlInterfaceRequest>

```

Field Name	Description
Name	The name of the Policy Table that was exported
Description	This description is copied from CMP

Add a Policy Table

Note: This query is not available to Policy servers in NW-CMP mode.

You can use the OSSI XML Interface to add a policy table, if the policy-table name does not exist in the CMP; or modify a table.

When naming a new table, the length limitation for the name is 255 characters; the description field is a free-form text that identifies the policy table and has a limit of 250 characters. If the length of either the name or description is exceeded, the import will fail.

The following example imports a Policy Table named "Sample1".

```

<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <AddPolicyTableData>
    <Name>Sample 1</Name>
    <Description>Sample 1</Description>
    <Table>
      <Header>
        <Field Type="smartString255" Key="true" Field="TA">TA</Field>
      </Header>
      <Record Name="1330657994893">
        <Field Field="TA">TA</Field>
      </Record>
      <Record Name="1330657994894">
        <Field Field="TA">TAsssss</Field>
      </Record>
    </Table>
  </AddPolicyTableData>
</XmlInterfaceRequest>

```

Modify a Policy Table

Note: This query is not available to Policy servers in NW-CMP mode.

You can use the OSSI XML Interface to change a policy table that is already in CMP.

If the table name does not already exist in the CMP, the import will fail.

A column cannot be changed or removed if it is being used in a policy or policy template; if the changes in the XML change or remove such a column, the import will fail.

The import allows these types of edits:

- Editing the name and description of policy tables
- Adding, removing, and reordering columns
- Editing a column's name, data type, and key status
- Adding, removing, and reordering rows
- Changing the data within the cells

The following example imports changes for a Policy Table named "Sample 1".

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <UpdatePolicyTableData>
    <Name>Sample 1</Name>
    <Table>
      <Header>
        <Field Type="smartString255" Key="true" Field="TA">TA</Field>
      </Header>
      <Record Name="1330657994893">
        <Field Field="TA">TA</Field>
      </Record>
      <Record Name="1330657994894">
        <Field Field="TA">TAsssss</Field>
      </Record>
    </Table>
  </UpdatePolicyTableData>
</XmlInterfaceRequest>
```

Delete a Policy Table

Note: This query is not available to Policy servers in NW-CMP mode.

You can use the OSSI XML Interface to delete a policy table that is already in CMP.

If the Policy Table is currently used in a policy or policy template, the import will fail.

The following example deletes a Policy Table named "Sample 1".

```
<?xml version="1.0" encoding="UTF-8" ?>
<XmlInterfaceRequest>
  <DeletePolicyTableData>
    <Name>Sample 1</Name>
  </DeletePolicyTableData>
</XmlInterfaceRequest>
```