

Configuring Weblogic Server 12c
Oracle FLEXCUBE Universal Banking
Release 12.4.0.0.0
[May] [2017]



Table of Contents

1. INTRODUCTION	1-1
1.1 PURPOSE OF THIS DOCUMENT.....	1-1
1.2 WEBLOGIC SERVER OVERVIEW	1-1
1.3 PRE-REQUISITES	1-5
2. DOMAIN CONFIGURATION	2-6
2.1 DOMAIN CREATION	2-6
2.2 PACK AND UNPACK DOMAIN	2-16
2.3 START ADMIN SERVER.....	2-16
2.4 START NODE MANAGER	2-16
3. CLUSTER CONFIGURATION.....	3-17
3.1 MACHINES CONFIGURATION	3-18
3.2 DYNAMIC CLUSTER CREATION.....	3-21
3.3 MANAGED SERVER TEMPLATE CONFIGURATION	3-25
3.3.1 <i>Logging</i>	3-25
3.3.2 <i>HTTP Logging</i>	3-27
3.3.3 <i>Stuck Tread Max Time</i>	3-27
4. TUNING	4-28
4.1 GENERAL PARAMETERS	4-28
4.2 JVM TUNING.....	4-28
5. START MANAGED SERVERS.....	5-30
6. DATA SOURCE CREATION AND JDBC CONFIGURATION	6-31
6.1 SETUP REQUIRED FOR OCI DRIVER	6-31
6.2 DATA SOURCE CREATION: NON XA	6-32
6.3 XA DATASOURCE.....	6-36
6.4 JDBC PARAMETERS TUNING.....	6-40
7. JMS RESOURCE CREATION.....	7-41
8. ORACLE WEBLOGIC LOAD BALANCING.....	8-42
9. FREQUENTLY ASKED QUESTIONS.....	9-43
9.1 MACHINE STATUS IS UNREACHABLE.	9-43
9.2 HOW TO RESTART NODE MANAGER?	9-43
9.3 SCALING UP DYNAMIC CLUSTER.....	9-43
9.4 SESSION TIMEOUT	9-45

1. Introduction

1.1 Purpose of this Document

The purpose of this document is to explain the steps required for Configuration and applying best practices in cluster mode for

- FCUBS 12.2
- Weblogic Version 12.1.3.0.0
- JDK 1.7.0_71

1.2 WebLogic Server Overview


This section of the document provides brief explanation on the main components involved in WebLogic server

Domain


A domain is the basic administration unit for WebLogic Server instances. A domain consists of one or more WebLogic Server instances (and their associated resources) that is managed with a single Administration Server. Multiple domains can be defined based on different system administrators' responsibilities, application boundaries, or geographical locations of servers. Conversely, a single domain can be used to centralize all WebLogic Server administration activities.

Each WebLogic Server domain must have one server instance that acts as the Administration Server. Administration Server can be used via the Administration Console or using the command line for configuring all other server instances and resources in the domain.

WebLogic Domain Structure



WebLogic 12c Domain Overview



Administration Server

A domain includes one WebLogic Server instance that is configured as an Administration Server. All changes to configuration and deployment of applications are done through the Administration Server. The Administration Server provides a central point for managing the domain and providing access to the WebLogic Server administration tools.

These tools include the following:

- WebLogic Server Administration Console: Graphical user interface to the Administration Server.
- WebLogic Server Node Manager: A Java program that lets you start and stop server instances - both Administration Servers and Managed Servers - remotely, and to monitor and automatically restart them after an unexpected failure.

Admin server start mode needs to be configured as Production Mode.

Managed Server

In a domain, server instances other than the Administration Server are referred to as Managed Servers. Managed servers host the components and associated resources that constitute your applications—for example, JSPs and EJBs.

When a Managed Server starts up, it connects to the domain's Administration Server to obtain configuration and deployment settings. In a domain with only a single WebLogic Server instance, that single server works as both the administration server and managed server.

Node Manager

The Managed Servers in a production WebLogic Server environment are often distributed across multiple machines and geographic locations.

Node Manager is a Java utility that runs as separate process from WebLogic Server and allows you to perform common operations tasks for a Managed Server, regardless of its location with respect to its Administration Server. While use of Node Manager is optional, it provides valuable benefits if your WebLogic Server environment hosts applications with high availability requirements.

If you run Node Manager on a machine that hosts Managed Servers, you can start and stop the Managed Servers remotely using the Administration Console or from the command line. Node Manager can also automatically restart a Managed Server after an unexpected failure.

Machine

A machine in the Weblogic Serve context is the logical representation of the computer that hosts one or more Weblogic Server instances(servers). The Admin Server uses the machine definitions to start remote servers through the Node Managers that run on those servers. A machine could be a physical or virtual server that hosts an Admin or Managed Server that belongs to a domain.

Managed Server Cluster

Two or more Managed Servers can be configured as a WebLogic Server cluster to increase application scalability and availability. In a WebLogic Server cluster, most resources and services are deployed to each Managed Server (as opposed to a single Managed Server,) enabling failover and load balancing.

The servers within a cluster can either run on the same machine or reside in different machines. To the client, a cluster appears as a single WebLogic Server instance.

Dynamic Cluster

A dynamic cluster is any cluster that contains one or more dynamic servers. Each server in the cluster will be based upon a single shared server template. The server template allows you to configure each server the same and ensures that servers do not need to be manually configured before being added to the cluster. This allows you to easily scale up or down the number of servers in your cluster without the need for setting up each server manually. Changes made to the server template are rolled out to all servers that use that template.

You cannot configure dynamic servers individually; there are no server instance definitions in the config.xml file when using a dynamic cluster. Therefore, you cannot override the server template with server-specific attributes or target applications to an individual dynamic server instance.

When configuring your cluster you specify the maximum number of servers you expect to need at peak times. The specified number of server instances is then created, each based upon your server template. You can then start up however many you need and scale up or down over time according to your needs. If you need additional server instances on top of the number you originally specified, you can increase the maximum number of servers instances (dynamic) in the dynamic cluster configuration.

Server Templates


A single server template provides the basis for the creation of the dynamic servers. Using this single template provides the possibility of every member being created with exactly the same attributes. Where some of the server-specific attributes like Servername, listen-ports, machines, etc. can be calculated based upon tokens.

You can pre-create server templates and let Weblogic clone one when a Dynamic Cluster is created.


When none is available a server template is created with the Dynamic Cluster. The name and the listen ports are the only server template attributes that you provide during Dynamic Cluster creation.

Simplified Configuration with Scalability and Elasticity

Simplified Initial Cluster Configuration



Simplified Operations for Cluster Scale Out



1.3 Pre-Requisites

In this document, we are going to create a domain with two managed servers. The managed servers are going to be created on two different physical servers (nodes). Note that, this document has been prepared based on a test conducted in Linux servers.

This requires Weblogic Server of same version to be installed on both the machines and services

Environment

2 servers where linux is installed, 1 will be primary where admin console will be running along with managed servers and the other where only managed servers will be.

Softwares

- 1) Oracle Weblogic Server 12.1.3 installed on both the machines under same folder structure.
- 2) JDK 1.7 Latest available version installed on both the machines. In this document JDK1.7.0_71 version is used.

Clock Synchronization

The clocks of both the servers participating in the cluster must be synchronized to within one second difference to enable proper functioning of jobs otherwise it will lead to session timeouts.

Enable Graphical User Interface (GUI)

Establish a telnet or SSH connection to primary server. Start X-manager (or any similar tool) in windows desktop. Export DISPLAY environment variable to the machine IP where x-manager is running.

Syntax: export DISPLAY=<ip-address>:<port>

Test using xclock

2. Domain Configuration

2.1 Domain Creation


Weblogic domain creation and configuration will be done from primary server.

From primary server, launch the fusion Middleware configuration wizard using the command **config.sh** available under \$WLS_HOME/common/bin directory.

- 1) In the Welcome screen, select “Create a new domain” option. Enter the domain name and Click on **Next**.

The screenshot shows the 'Configuration Type' window of the Oracle Fusion Middleware Configuration Wizard. The left sidebar contains a list of steps: 'Create Domain' (selected), 'Templates', 'Administrator Account', 'Domain Mode and JDK', 'Advanced Configuration', 'Configuration Summary', 'Configuration Progress', and 'End Of Configuration'. The main area is titled 'What do you want to do?' and has two radio buttons: 'Create a new domain' (selected) and 'Update an existing domain'. Below this, the 'Domain Location' is entered as '/scratch/app/wl12c/user_projects/domains/FCUBSDomain', which is highlighted with a red rectangle. A 'Browse' button is to the right of the text field. At the bottom, there are four buttons: 'Help', '< Back', 'Next >' (highlighted with a red rectangle), and 'Finish'. A 'Cancel' button is also present on the far right. The Oracle Fusion Middleware logo is in the top right corner.

2) Select the required templates from **Available Templates** and click **Next**.



3) Specify Administrator **User Name** and **Password**.

- The specified credentials are used to access Administration console.
- You can use this screen to define the default WebLogic Administrator account for the domain. This account is used to boot and connect to the domain's Administration Server. Click **Next**.

The screenshot shows the 'Administrator Account' configuration window in the Oracle Fusion Middleware console. The left sidebar contains a navigation tree with the following items: 'Create Domain', 'Templates', 'Administrator Account' (highlighted), 'Domain Mode and JDK', 'Advanced Configuration', 'Configuration Summary', 'Configuration Progress', and 'End Of Configuration'. The main content area has the Oracle logo and 'FUSION MIDDLEWARE' text at the top right. Below this, there are three input fields: 'Name' (containing 'weblogic'), 'Password' (masked with dots), and 'Confirm Password' (masked with dots). These three fields are enclosed in a red rectangular box. At the bottom of the main area, there is a text box with the following text: 'Must be the same as the password. Password must contain at least 8 alphanumeric characters with at least one number or special character.' At the bottom of the window, there are four buttons: 'Help', '< Back', 'Next >' (highlighted with a red box), 'Finish', and 'Cancel'.

Administrator Account

ORACLE
FUSION MIDDLEWARE


Create Domain
Templates
Administrator Account
Domain Mode and JDK
Advanced Configuration
Configuration Summary
Configuration Progress
End Of Configuration

Name: weblogic
Password:
Confirm Password:

Must be the same as the password. Password must contain at least 8 alphanumeric characters with at least one number or special character.

Help < Back Next > Finish Cancel

- 4) Select Server Startup as **Production Mode** and the available **JDKs**. Click **Next**.



The image shows the 'Domain Mode and JDK' configuration window in Oracle Fusion Middleware. The window has a sidebar on the left with a list of steps: 'Create Domain', 'Templates', 'Administrator Account', 'Domain Mode and JDK' (highlighted), 'Advanced Configuration', 'Administration Server', 'Node Manager', 'Configuration Summary', 'Configuration Progress', and 'End Of Configuration'. The main area is titled 'Domain Mode and JDK' and contains two sections. The 'Domain Mode' section has two radio buttons: 'Development' and 'Production'. The 'Production' option is selected and highlighted with a red rectangle. Below it, the text reads: 'Require the entry of a username and password, and do not poll for applications to deploy.' The 'JDK' section has two radio buttons: 'Oracle HotSpot 1.7.0_75 /usr/java/jdk1.7.0_75' and 'Other JDK Location:'. The first option is selected. Below the 'Other JDK Location' text is a text input field and a 'Browse' button. At the bottom of the window, there are four buttons: '< Back', 'Next >', 'Finish', and 'Cancel'. The 'Next >' button is highlighted with a red rectangle.

Domain Mode and JDK

Domain Mode

☐ Development
Utilize boot.properties for username and password, and poll for applications to deploy.


☒ **Production**
Require the entry of a username and password, and do not poll for applications to deploy.

JDK


☒ Oracle HotSpot 1.7.0_75 /usr/java/jdk1.7.0_75

☐ Other JDK Location:

5) Select the check box adjacent to **Administration Server** and **Node Manager**. Click **Next**.



6) Specify the Administration server **Listen address** and **Listen port**.



The image shows the 'Administration Server' configuration window in Oracle Fusion Middleware. The left sidebar contains a navigation tree with the following items: 'Create Domain', 'Templates', 'Administrator Account', 'Domain Mode and JDK', 'Advanced Configuration', 'Administration Server' (selected), 'Node Manager', 'Configuration Summary', 'Configuration Progress', and 'End Of Configuration'. The main configuration area is titled 'Administration Server' and contains the following fields:

- Server Name: AdminServer
- Listen Address: All Local Addresses
- Listen Port: 7001
- Enable SSL: ☒
- SSL Listen Port: 7101

A red rectangle highlights the 'Listen Address', 'Listen Port', and 'SSL Listen Port' fields. Below the configuration fields, a message states: 'Port number must be between 1 and 65535, and different from listen port and coherence port.' At the bottom of the window, there are four buttons: 'Help', '< Back', 'Next >', and 'Finish'. The 'Next >' button is highlighted with a red rectangle.


Note: The default Listen port is 7001 and SSL port is 7101. This could be changed to any other available port. Ensure to make a note, of this port since the same is required for launching the Admin console, post domain creation.

Note: Check for the port availability using the command - **netstat -anp |grep <Port no>**

The next screen navigates to **NodeManager configuration**.

7) Configure Node Manager

Select **Per Domain Default Location** option from **Node Manager Type**. And in the **Node Manager Credentials**, provide the username and password for the nodemanager. Click **Next**.



The image shows the 'Node Manager' configuration window in Oracle Fusion Middleware. The left sidebar contains a navigation tree with the following items: 'Create Domain', 'Templates', 'Administrator Account', 'Domain Mode and JDK', 'Advanced Configuration', 'Administration Server', 'Node Manager' (highlighted), 'Configuration Summary', 'Configuration Progress', and 'End Of Configuration'. The main content area is titled 'Node Manager' and features the Oracle Fusion Middleware logo in the top right corner. Under the 'Node Manager Type' section, the 'Per Domain Default Location' radio button is selected and highlighted with a red box. Below this, the 'Node Manager Home' text field contains the path 'pp/wm12c/user_projects/domains/FCUBSDomain/nodemanager', with a 'Browse' button to its right. The 'Manual Node Manager Setup' radio button is unselected. Under the 'Node Manager Credentials' section, the 'Username' field is filled with 'weblogic'. The 'Password' and 'Confirm Password' fields are filled with masked characters (dots) and are grouped together within a red rectangular box. At the bottom of the window, the '< Back' button is disabled, the 'Next >' button is highlighted with a red box, and the 'Finish' and 'Cancel' buttons are also present. A note at the bottom of the main content area states: 'Must be the same as the password. Password must contain at least 8 alphanumeric characters with at least one number or special character.'

Node Manager

ORACLE
FUSION MIDDLEWARE

Node Manager Type

☒ Per Domain Default Location

☐ Per Domain Custom Location

Node Manager Home:

☐ Manual Node Manager Setup

Node Manager Credentials


Username:

Password:


Confirm Password:

Must be the same as the password. Password must contain at least 8 alphanumeric characters with at least one number or special character.


- 8) Verify the details and click **Create**. The domain creation process is initiated and the progress of completion is indicated.



9) Click **Next**.



10) The **Configuration Success** message will be displayed as follows:



The Admin Server console URL is as indicated below:

http://<IP address>:<admin console port>/console

- <IP address >: Host on which domain was created.
- <admin console port> : Port specified in Administration Server configuration page.

In this case the Admin Console URL is: <http://ofss222565:7001/console>

2.2 Pack and Unpack Domain

The domain structure is expected to be copied to the second server during domain creation. To copy the same, you can use pack and unpack utility provided under \$WLSHOME/common/bin.

Pack

Pack domain in primary server:

```
./pack.sh -managed=true -domain=/scratch/app/wl12c/user_projects/domains/FCUBSDomain -  
template=/tmp/FCUBSDomain.jar -template_name="FCUBSDomain"
```

Unpack

Unpack FTP FCBUSDomain.jar in binary mode to secondary server under /tmp area and unpack the domain using unpack utility provided under \$WLSHOME/common/bin

```
./unpack.sh -domain=/scratch/app/wl12c/user_projects/domains/FCUBSDomain -  
template=/tmp/FCUBSDomain.jar
```

2.3 Start Admin server

Admin server is started on the primary server. Login to primary server and navigate to folder \$DOMAIN_HOME/bin and execute **startWeblogic.sh**.

2.4 Start Node Manager

Node Manager needs to be started on both the servers. Before starting the node manager update ListenAddress to the Hostname/IP Address of the machine in nodemanager.properties located in folder \$DOMAIN_HOME/nodemanager

To start the node manager login to the servers and navigate to folder \$DOMAIN_HOME/bin and execute **NodeManager.sh**

3. Cluster Configuration

Dynamic Cluster configuration involves below steps


- 1) Machine Configuration
- 2) Dynamic Cluster Creation: In a normal WebLogic Cluster you define Managed Server and add them to Cluster. In Dynamic Cluster, you select number of Servers you want in Cluster and Server Template you wish to assign to Servers in this WebLogic Dynamic Cluster.
- 3) Server template modification: Servers (or Managed Server) that are part of WebLogic Dynamic Cluster will have properties taken from Server Template.
Modify server template for best practices parameters for Dynamic Servers (part of Dynamic Cluster), you modify Server Template that is applicable to Dynamic Cluster. These settings are applicable to all the managed servers.
- 4) Activate Changes which would automatically create the managed servers(as mentioned in the number of servers required parameter).

Calculate Number of Servers Required:


For every 50 logged in FLEXCUBE users require one managed server of size 4GB. i.e. for 300 logged in FLEXCUBE users, it is recommended to have 6 managed servers. Based on the logged in users that needs to be supported decide on the number of the managed servers required. This parameter is required later in the dynamic cluster creation.

3.1 Machines Configuration

- 1) Login into Admin Console and Navigate to FCUBSDomain → Environment → Machine and Click **New**



- 2) Enter the **machine name** and click **Next**



- 3) Enter the **Listen Address** and **Listen Port**(this is the port mentioned in nodemanager.properties file) and click **Finish**

Oracle WebLogic Server Administration Console 12c

Home Log Out Preferences Lock Record Help

Welcome, weblogic Connected to: FCUBSDomain

Home > Summary of Machines

Create a New Machine

Back Next Finish Cancel

Node Manager Properties

The following properties will be used to configure the Node Manager on this machine.

What type of Node Manager is running on this server, and what protocol should be used to communicate with it?

Type: SSL

For a Java based node manager, what address and port is this Node Manager configured to listen at?

Listen Address: localhost

Listen Port: 5556

For a script based node manager, additional properties may be configured.

Node Manager Home:

Shell Command:

Debug Enabled

Back Next Finish Cancel

- 4) Machine is created

Oracle WebLogic Server Administration Console 12c

Home Log Out Preferences Lock Record Help

Welcome, weblogic Connected to: FCUBSDomain

Home > Summary of Machines

Messages

All changes have been activated. No restarts are necessary.

Summary of Machines

A machine is the logical representation of the computer that hosts one or more WebLogic Server instances (servers). WebLogic Server uses configured machine names to determine the optimum server in a cluster to which certain tasks, such as HTTP session replication, are delegated. The Administration Server uses the machine definition in conjunction with Node Manager to start remote servers.

This page displays key information about each machine that has been configured in the current WebLogic Server domain.

Customize this table


Machines

Click the Lock & Edit button in the Change Center to activate all the buttons on this page.

Name	Type
Machine1	Machine

Showing 1 to 1 of 1 Previous Next


5) Similarly create a new **machine** entry for the other server



Verifying machine status


Before starting the managed servers, ensure that the Node manager Status of all the machines are "Reachable".

In the console, navigate through Domain structure → Machines → machine1 → Monitoring → Node Manager Status. Status should be **Reachable**.




3.2 Dynamic Cluster Creation

- 1) Login into Admin Console and Navigate to FCUBSDomain → Environment → Clusters → New → select **Dynamic Cluster**



- 2) Enter the **Cluster Name** and Click on **Next**



- 3) Enter the **number of dynamic servers** you want to configure, enter the **server name prefix** and click on **Next**

ORACLE WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Home > Machine2 > Summary of Machines > Machine1 > Summary of Machines > Machine2 > Summary of Servers > Summary of Machines > Machine2 > Summary of Servers > Summary of Clusters

Create a New Dynamic Cluster

Back Next Finish Cancel

Specify Dynamic Server Properties

The following properties will be used to specify the size and characteristics of your new dynamic cluster.

How many dynamic servers will you need at peak load?

Number of Dynamic Servers: 4

What naming convention would you like to use for new dynamic servers in this cluster?

Server Name Prefix: FCUBSMS

Server templates are used to configure the characteristics that are common to all dynamic servers in this cluster. Server templates are unique to a cluster and cannot be shared across clusters, so a new server template will be created to support this new cluster.

Back Next Finish Cancel

- 4) Select Machines that participate in domain, in this case all machines will be part of the domain, select **Use any machine configured in this domain** and click on **Next**

ORACLE WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Home > Machine2 > Summary of Machines > Machine1 > Summary of Machines > Machine2 > Summary of Servers > Summary of Machines > Machine2 > Summary of Servers > Summary of Clusters

Create a New Dynamic Cluster

Back Next Finish Cancel

Specify Machine Bindings

Associating dynamic servers with machines is essential if you intend to use Node Manager and the Administration Console (or WLST) to start server instances.

How do you want to distribute dynamic servers across machines?

☒ Use any machine configured in this domain

☐ Use a single machine for all dynamic servers

Selected Machines: Machine1

☐ Use a subset of machines in this domain

Machine Name Match Expression:

Back Next Finish Cancel

- 5) Select the **listen port for the first server** in the dynamic cluster and then the **SSL listener port** for the first server in the dynamic cluster. The subsequent servers will be assigned with an incremental port number. Click **Next**

The screenshot shows the 'Specify Listen Port Bindings' step of the 'Create a New Dynamic Cluster' wizard. The left sidebar contains the 'Domain Structure' tree with 'FCUBSDomain' selected. The main panel has a 'Back', 'Next', 'Finish', and 'Cancel' button bar at the top. Below is the 'Specify Listen Port Bindings' section. It states: 'Select how these dynamic servers should be bound to listen ports. Listen ports for dynamic servers can be specified in a server template or can be dynamically generated to be unique.' There are two radio button options: 'Assign each dynamic server unique listen ports' (selected) and 'Assign each dynamic server fixed listen ports'. Under the selected option, there are two input fields: 'Listen Port for First Server:' with the value '7002' and 'SSL Listen Port for First Server:' with the value '7102'. Both input fields are highlighted with a red rectangle. At the bottom, there are 'Back', 'Next', 'Finish', and 'Cancel' buttons, with the 'Next' button highlighted by a red rectangle.

- 6) Summary of new Dynamic Cluster configuration is presented. Click **Finish** to create

The screenshot shows the 'Review Your Dynamic Cluster Configuration' step of the 'Create a New Dynamic Cluster' wizard. The left sidebar contains the 'Domain Structure' tree with 'FCUBSDomain' selected. The main panel has a 'Back', 'Next', 'Finish', and 'Cancel' button bar at the top. Below is the 'Review Your Dynamic Cluster Configuration' section. It states: 'You have elected to create a new dynamic cluster with the following configuration.' There are two sections: 'Configuration details for new dynamic cluster:' and 'Configuration details for new server template:'. The first section has four rows: 'Name of New Dynamic Cluster:' with value 'FCUBS Cluster', 'Maximum Number of Dynamic Servers:' with value '4', 'Server Name Prefix:' with value 'FCUBSHS', and 'Enable Calculated Listen Ports:' with value 'true'. The second section has two rows: 'Name of New Server Template:' with value 'FCUBSHSTemplate' and 'Listen Port:' with value '7002'. Below these sections are 'Back', 'Next', 'Finish', and 'Cancel' buttons, with the 'Finish' button highlighted by a red rectangle.

7) The **Summary of Clusters** screens should show the recently created Dynamic Cluster.

Change Center
View changes and restarts
Pending changes exist. They must be activated to take effect.
[Activate Changes] [Undo All Changes]

Domain Structure
FCUBSDomain
Environment
Servers
Clusters
Server Templates
Migratable Targets
Coherence Clusters
Machines
Virtual Hosts
Work Managers
Startup and Shutdown Classes
Deployments
Services
Security Realms

Summary of Clusters
This page summarizes the clusters that have been configured in the current WebLogic Server domain.
A cluster defines groups of WebLogic Server servers that work together to increase scalability and reliability.

Customize this table
Clusters (Filtered - More Columns Exist)
[New] [Clone] [Delete] Showing 1 to 1 of 1 Previous | Next

Name	Cluster Address	Cluster Messaging Mode	Migration Basis	Default Load Algorithm	Replication Type	Cluster Broadcast Channel	Servers
FCUBSCluster		Unicast	Database	Round Robin	(None)		

[New] [Clone] [Delete] Showing 1 to 1 of 1 Previous | Next

8) Upon **Activate Changes** would automatically create 4 managed servers.

Change Center
View changes and restarts
Click the Lock & Edit button to modify, add or delete items in this domain.
[Lock & Edit] [Release Configuration]

Domain Structure
FCUBSDomain
Environment
Servers
Clusters
Server Templates
Migratable Targets
Coherence Clusters
Machines
Virtual Hosts
Work Managers
Startup and Shutdown Classes
Deployments
Services
Security Realms

Summary of Clusters
This page summarizes the clusters that have been configured in the current WebLogic Server domain.
A cluster defines groups of WebLogic Server servers that work together to increase scalability and reliability.

Customize this table
Clusters (Filtered - More Columns Exist)
Click the Lock & Edit button in the Change Center to activate all the buttons on this page.
[New] [Clone] [Delete] Showing 1 to 1 of 1 Previous | Next

Name	Cluster Address	Cluster Messaging Mode	Migration Basis	Default Load Algorithm	Replication Type	Cluster Broadcast Channel	Servers
FCUBSCluster		Unicast	Database	Round Robin	(None)		FCUBSHS1, FCUBSHS2, FCUBSHS3, FCUBSHS4

[New] [Clone] [Delete] Showing 1 to 1 of 1 Previous | Next

9) Navigate to FCUBSDomain → Environment → Servers tab and 4 new servers are created

Change Center
View changes and restarts
Click the Lock & Edit button to modify, add or delete items in this domain.
[Lock & Edit] [Release Configuration]

Domain Structure
FCUBSDomain
Environment
Servers
Clusters
Server Templates
Migratable Targets
Coherence Clusters
Machines
Virtual Hosts
Work Managers
Startup and Shutdown Classes
Deployments
Services
Security Realms

Summary of Servers
A server is an instance of WebLogic Server that runs in its own Java Virtual Machine (JVM) and has its own configuration.
This page summarizes each server that has been configured in the current WebLogic Server domain.

Customize this table
Servers (Filtered - More Columns Exist)
Click the Lock & Edit button in the Change Center to activate all the buttons on this page.
[New] [Clone] [Delete] Showing 1 to 5 of 5 Previous | Next

Name	Type	Cluster	Machine	State	Health	Listen Port
AdminServer(admin)	Configured			RUNNING	OK	7001
FCUBSHS1	Dynamic	FCUBSCluster	Machine1	SHUTDOWN	Not reachable	7003
FCUBSHS2	Dynamic	FCUBSCluster	Machine2	SHUTDOWN	Not reachable	7004
FCUBSHS3	Dynamic	FCUBSCluster	Machine1	SHUTDOWN	Not reachable	7005
FCUBSHS4	Dynamic	FCUBSCluster	Machine2	SHUTDOWN	Not reachable	7006

[New] [Clone] [Delete] Showing 1 to 5 of 5 Previous | Next

3.3 Managed Server Template configuration

The server template created is modified to apply the below parameters

3.3.1 Logging

The process of log file writing in a Weblogic server can impact the performance. Hence, you need to keep the logging to minimum in a production environment.

Update below parameters by in Logging Screen

Minimum Severity to log	Warning
Log file Severity level	Warning
Standard Out Severity level	Critical
Domain broadcaster Severity level	Critical

1) Navigate to FCUBSDomain → Environment → Clusters

The screenshot shows the Oracle WebLogic Server Administration Console. On the left, the 'Domain Structure' tree is expanded to 'Server Templates'. The main area displays the 'Summary of Server Templates' page. A table lists the server templates, with 'FCUBSMSTemplate' highlighted. The table has columns: Name, Cluster, Machine, Listen Port, and Listen Address. The 'FCUBSMSTemplate' row shows it belongs to the 'FCUBSCluster' and has a 'Listen Port' of 7002.

Name	Cluster	Machine	Listen Port	Listen Address
FCUBSMSTemplate	FCUBSCluster		7002	

2) Select FCUBSTemplate and naviage to Logging → General


The screenshot shows the 'Settings for FCUBSMSTemplate' page in the Oracle WebLogic Server Administration Console. The 'Logging' tab is selected, and the 'General' sub-tab is active. The 'Log file name' is set to 'logs/FCUBSMSTemplate.log'. A description explains that the log file name is typically a computed value based on the parent of the MBean.

Log file name: logs/FCUBSMSTemplate.log

The name of the file that stores current log messages. Usually it is a computed value based on the name of the parent of this MBean. For example, for a server log, it is SERVER_NAME.log. [More Info...](#)

3) Under Advanced Tab, update the below parameters and Click on **Save**

Advanced

 **Date Format Pattern:**


MMM d, yyyy h:mm:ss a z

The date format pattern used for rendering dates in the log. The DateFormatPattern string conforms to the specification of the java.text.SimpleDateFormat class. [More Info...](#)

Minimum severity to log:

Warning

The minimum severity of log messages going to all log destinations. By default all messages are published. [More Info...](#)

 **Logger severity properties:**

The configuration of the different logger severities keyed by name. The values are one of the predefined Severity strings namely Emergency, Alert, Critical, Error, Warning, Notice, Info, Debug, Trace. [More Info...](#)

Log file :

Severity level:


Warning

The minimum severity of log messages going to the server log file. By default all messages go to the log file. [More Info...](#)

Filter:

None

The filter configuration for the server log file. [More Info...](#)

 **Log File Buffer:**

8

Gets the underlying log buffer size in kilobytes [More Info...](#)

Standard out :

Severity level:

Critical

The minimum severity of log messages going to the standard out. Messages with a lower severity than the specified value will not be published to standard out. [More Info...](#)

Filter:

None

The filter configuration for log events being sent to the standard out. [More Info...](#)

Domain log broadcaster :

Severity level:

Critical

The minimum severity of log messages going to the domain log from this server's log broadcaster. Messages with a lower severity than the specified value will not be published to the domain log. [More Info...](#)

Filter:

None

The filter configuration for log events being sent to the domain log. [More Info...](#)

Buffer Size:

10

Broadcasts log messages to the domain log in batch mode. [More Info...](#)


☒ **Stack Traces to stdout**

Specifies whether to dump stack traces to the console when included in logged message. [More Info...](#)

stdout Stack Trace Depth:

5

Determines the no of stacktrace frames to display on standard out. All frames are displayed in the log file. * -1 means all frames are displayed. [More Info...](#)

 **stdout Format:**

standard

The output format to use when logging to the console. [More Info...](#)

Save

3-26

3.3.2 HTTP Logging

- 1) FCUBSDomain → Environment → Clusters → FCUBSTemplate → Logging → HTTP → Uncheck the **Access Logs** Flag

Home Log Out Preferences Record Help Welcome, weblogic Connected to: FCUBSDoma

Home > FCUBSMSTemplate > Summary of Server Templates > FCUBSMSTemplate

Settings for FCUBSMSTemplate

Configuration Protocols **Logging** Debug Notes

General **HTTP** Data Source Diagnostic Images

Save

Use this page to configure HTTP logging for the server. By default, HTTP logging is enabled and the server saves HTTP requests in a separate log file; it does not store HTTP requests in the server log file or the domain log file.

☒ **HTTP access log file enabled** Indicates whether this server logs HTTP requests. (The remaining fields on this page are relevant only if you select this check box.) [More Info...](#)

Log file name: logs/access.log The name of the log file. [More Info...](#)

Rotation

Rotation type: By Size Criteria for moving old log messages to a separate file. [More Info...](#)

Rotation file size: 5000 The size (1 - 2097150 kilobytes) that triggers the server to move log messages to a separate file. The default is 500 kilobytes. After the log file

3.3.3 Stuck Tread Max Time

- 1) FCUBSDomain → Environment → Clusters → FCUBSTemplate → Tuning, update the stuck thread max time to **18000** and Click on **Save**

Home Log Out Preferences Record Help Welcome, weblogic Connected to: FCUBSDoma

Home > FCUBSMSTemplate > Summary of Server Templates > FCUBSMSTemplate

Settings for FCUBSMSTemplate

Configuration Protocols **Logging** Debug Notes

General **HTTP** Data Source Diagnostic Images

Save

Use this page to configure HTTP logging for the server. By default, HTTP logging is enabled and the server saves HTTP requests in a separate log file; it does not store HTTP requests in the server log file or the domain log file.

☒ **HTTP access log file enabled** Indicates whether this server logs HTTP requests. (The remaining fields on this page are relevant only if you select this check box.) [More Info...](#)

Log file name: logs/access.log The name of the log file. [More Info...](#)

Rotation

Rotation type: By Size Criteria for moving old log messages to a separate file. [More Info...](#)

Rotation file size: 5000 The size (1 - 2097150 kilobytes) that triggers the server to move log messages to a separate file. The default is 500 kilobytes. After the log file

4. Tuning

4.1 General Parameters

PARAMETER	VALUE	Navigate To
JTA Time out seconds	18000	Login to Weblogic Server console. Click on the domain name (ex: FCUBSDomain) which is under 'Domain Structure'. Go to Configuration > JTA, parameter and values is found on the right side panel of console.
Session Timeout	900	Login to Weblogic Server console Click on Deployments which is under 'Domain Structure'. Click on the deployed FCJ application from right side panel. Click on FCJNeoWeb from 'Modules and components' Go to Configuration General, the parameter values can be found here.

4.2 JVM Tuning

This section of the document provides JVM optimization for Oracle FLEXCUBE Universal Banking Solution.

Basically the JAVA minimum and maximum heap size needs to be reset for 32 and 64 bit environments. Both the minimum and maximum heap size is set to 1.5GB and 4GB in case of 32 bit and 64 bit environments respectively.

How to find whether the JVM is 32bit or 64bit?

Go to \$JAVA_HOME/bin directory. Check java version using command `./java -d64 -version`
64 bit JVM shows the version details where as 32bit throws an error.

How to modify the JVM heap parameters?

To change the JVM heap parameters modify `setDomainEnv.sh` under domain FCUBSCL in both servers. This file is located at “`$WL_HOME/user_projects/domains/$WLS_DOMAIN/bin`” in both the servers.

Use below `USER_MEM_ARGS` variable to override the standard memory arguments passed to java for **SUN JDK**.

32 bit JDK

```
USER_MEM_ARGS="-  
Dorg.apache.xml.dtm.DTManager=org.apache.xml.dtm.ref.DTManagerDefault  
-  
Dorg.apache.xerces.xni.parser.XMLParserConfiguration=org.apache.xerces.  
parsers.XML11Configuration -Dweblogic.threadpool.MinPoolSize=100 -  
Dweblogic.threadpool.MaxPoolSize=100 -Xms1536M -Xmx1536M -  
XX:MaxPermSize=256m -server -XX:+UseParallelOldGC -  
XX:ParallelGCThreads=4"  
export USER_MEM_ARGS
```

64 bit JDK

```
USER_MEM_ARGS="-  
Dorg.apache.xml.dtm.DTManager=org.apache.xml.dtm.ref.DTManagerDefault  
-Dorg.a  
pache.xerces.xni.parser.XMLParserConfiguration=org.apache.xerces.parser  
s.XML11Configuration -Dweblogic.threadpool.MinPoolSize=100 -  
Dweblogic.threadpool.MaxPoolSize=100 -Xms4g -Xmx4g -XX:MaxPermSize=512m  
-server -d64 -XX:+UseParallelOldGC -XX:ParallelGCThreads=4"  
export USER_MEM_ARGS
```

Note: Take a backup of the files before modifying the same.

5. Start Managed Servers

Starting using scripts

Managed Servers can be started by executing startManagedWebLogic.sh script present in folder **\$DOMAIN_HOME/bin**

Usage: ./startManagedWebLogic.sh SERVER_NAME {ADMIN_URL}

Eg: ./startManagedWebLogic.sh FCUBSMS1 https://<hostname1>/console

Starting using console

Alternatively, login to admin console, navigate to FCUBSDomain → Environment → Servers → Control, select the managed servers to be started and click on **Start**

Oracle WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Summary of Servers

Configuration Control

Use this page to change the state of the servers in this WebLogic Server domain. Control operations on Managed Servers require starting the Node Manager. Starting Managed Servers in Standby mode requires the domain-wide administration port.

Customize this table

Servers (Filtered - More Columns Exist)

Server	Machine	State	Status of Last Action
AdminServer(admin)		RUNNING	None
FCUBSMS1	Machine1	SHUTDOWN	None
FCUBSMS2	Machine2	SHUTDOWN	None
FCUBSMS3	Machine1	SHUTDOWN	None
FCUBSMS4	Machine2	SHUTDOWN	None

Start Resume Suspend Shutdown Restart SSL

Upon successful startup, the status of Managed servers is changed to **“RUNNING”**.

Oracle WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Summary of Servers

Configuration Control

A server is an instance of WebLogic Server that runs in its own Java Virtual Machine (JVM) and has its own configuration. This page summarizes each server that has been configured in the current WebLogic Server domain.

Last Refreshed: Jun 11, 2015 2:57:19 PM

Customize this table

Servers (Filtered - More Columns Exist)

Click the Lock & Edit button in the Change Center to activate all the buttons on this page.

Name	Type	Cluster	Machine	State	Health	Listen Port
AdminServer(admin)	Configured			RUNNING	OK	7001
FCUBSMS1	Dynamic	FCUBSCluster	Machine1	RUNNING	OK	7003
FCUBSMS2	Dynamic	FCUBSCluster	Machine2	RUNNING	OK	7004
FCUBSMS3	Dynamic	FCUBSCluster	Machine1	RUNNING	OK	7005
FCUBSMS4	Dynamic	FCUBSCluster	Machine2	RUNNING	OK	7006

6. Data Source creation and JDBC Configuration

Following are the JNDI names of those data sources used by FLEXCUBE application.

- jdbc/fcjdevDS - This datasource is used by FLEXCUBE online screen excluding branch screens.
- jdbc/fcjdevDSBranch - This datasource is used by Branch screens.
- jdbc/fcjSchedulerDS - This datasource is used by Quartz scheduler.

Note:

- jdbc/fcjdevDS should be **NonXA** and make use of **OCI** driver.
- jdbc/fcjdevDSBranch and jdbc/fcjSchedulerDS should be **XA**


6.1 Setup Required for OCI Driver

Data sources are created with OCI enabled. For this, Oracle Instant Client is required, below steps needs to be followed


- Download Oracle Instant Client corresponding to the used Oracle DB and java (x64 or x32):
<http://www.oracle.com/technetwork/database/features/instant-client/index-097480.html>
- Set {ORACLE_HOME} in the environment variable.
- Update the environment variable LD_LIBRARY_PATH as {ORACLE_HOME}/lib. This is to load all the .so files.
- Ensure that the ojdbc*.jar file in {WL_HOME}/server/lib/ojdbc*.jar is the same as the file {ORACLE_HOME}/jdbc/lib/ojdbc*.jar. This is to ensure compatibility.
- Update LD_LIBRARY_PATH in StartWebLogic.sh or in setDomainEnv.sh. This must be the path of directory where Oracle Instant Client is installed.
- If you are still not able to load the .so files, then you need to update the EXTRA_JAVA_PROPERTIES by setting Djava.library.path as {ORACLE_HOME}/lib in StartWebLogic.sh or in setDomainEnv.sh.

6.2 Data source creation: non XA


- 1) Navigate to FCUBSDomain → Services → Data Sources → select New > **Generic data source**




- 2) Enter the **Name** and **JNDI Name** and Click on **Next**



- 3) Select the Driver as **“Oracle’s Driver(thin) for Instance connection: Versions: Any”** and Click on **Next**



- 4) Uncheck the **“Supports Global Transactions”** and click on **Next**



- 5) Enter the Database Name, Host Name, Port, User Name, Password, Confirm Password and Click on **Next**

The screenshot shows the Oracle WebLogic Server Administration Console. The main window is titled 'Create a New JDBC Data Source'. It has a 'Back', 'Next', 'Finish', and 'Cancel' button bar at the top. The 'Connection Properties' section is highlighted with a red box. It contains the following fields:

- Database Name:
- Host Name:
- Port:
- Database User Name:
- Password:
- Confirm Password:

Below these fields is the 'Additional Connection Properties' section, which shows the 'oracle.jdbc.OracleDriver' class. At the bottom, there is another 'Back', 'Next', 'Finish', and 'Cancel' button bar.

- 6) Replace the **JDBC URL** in the below format and click on **Next**

Default URL: jdbc:oracle:thin:@<IP_Address>:<Port>:<INSTANCE_NAME>.

Change the default URL to:

```
jdbc:oracle:oci:@(DESCRIPTION=(ADDRESS_LIST=(ADDRESS=(PROTOCOL=TCP)(HOST=xxxxxx.com)(PORT=1521)))(CONNECT_DATA=(SERVICE_NAME=fcubs)))
```

Where,

Scan IP = xxxxxx.com

Service Name = fcubs

Port = 1521

Make sure that in URL, we make the changes to reflect oci.

Then Click on Test Configuration. The connection test should be successful.

ORACLE WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Change Center

View changes and restarts

No pending changes exist. Click the Release Configuration button to allow others to edit the domain.

Lock & Edit

Release Configuration

Domain Structure

FCUBSDomain

- Environment
 - Servers
 - Clusters
 - Server Templates
 - Migratable Targets
 - Coherence Clusters
 - Machines
 - Virtual Hosts
 - Work Managers
 - Startup and Shutdown Classes
 - Deployments
 - Services
 - Message Driven

How do I...?

- Create JDBC generic data sources
- Create LRM-enabled JDBC data sources

System Status

Health of Running Servers

Failed (0)

Critical (0)

Overloaded (0)

Warning (0)

OK (5)

Create a New JDBC Data Source

Test Configuration Back Next Finish Cancel

Test Database Connection

Test the database availability and the connection properties you provided.

What is the full package name of JDBC driver class used to create database connections in the connection pool?
(Note that this driver class must be in the classpath of any server to which it is deployed.)

Driver Class Name: oracle.jdbc.OracleDriver

What is the URL of the database to connect to? The format of the URL varies by JDBC driver.

URL: jdbc:oracle:oci:@(DESCRIPTION)

What database account user name do you want to use to create database connections?

Database User Name: FCUBS12106

What is the database account password to use to create database connections?
(Note: for secure password management, enter the password in the Password field instead of the Properties field below)

Password:

Confirm Password:

What are the properties to pass to the JDBC driver when creating database connections?

Properties: user=FCUBS121USER

7) Select Target as **FCUBSCluster** and click on **Finish**

ORACLE WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Change Center

View changes and restarts

No pending changes exist. Click the Release Configuration button to allow others to edit the domain.

Lock & Edit

Release Configuration

Domain Structure

FCUBSDomain

- Environment
 - Servers
 - Clusters
 - Server Templates
 - Migratable Targets
 - Coherence Clusters
 - Machines
 - Virtual Hosts
 - Work Managers
 - Startup and Shutdown Classes
 - Deployments
 - Services
 - Message Driven

How do I...?

Create a New JDBC Data Source

Back Next Finish Cancel

Select Targets

You can select one or more targets to deploy your new JDBC data source. If you don't select a target, the data source will be created but not deployed. You will need to deploy the data source at a later time.

Servers

AdminServer

Clusters


☒ FCUBSCluster

☐ All servers in the cluster


Back Next Finish Cancel

6.3 XA Datasource


- 1) Navigate to FCUBSDomain → Services → Data Sources → select New > **Generic data source**




- 2) Enter the **Name** and **JNDI Name** and Click on **Next**



- 3) Select the Driver as **“Oracle’s Driver(thin XA) for Instance connection: Versions: Any”** and Click on **Next**



- 4) Click on Next



5) From this step to target setting step follow as mentioned in non-xa

ORACLE WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Home > FCUBSGMTTemplate > Summary of Server Templates > FCUBSGMTTemplate > Summary of Clusters > Summary of Servers > Summary of JDBC Data Sources

Create a New JDBC Data Source

Back Next Finish Cancel

Connection Properties
Define Connection Properties.

What is the name of the database you would like to connect to?

Database Name:

What is the name or IP address of the database server?

Host Name:

What is the port on the database server used to connect to the database?

Port:

What database account user name do you want to use to create database connections?

Database User Name:

What is the database account password to use to create database connections?

Password:

Confirm Password:

Additional Connection Properties:

oracle.jdbc.OracleConnectionClass:

Back Next Finish Cancel

ORACLE WebLogic Server Administration Console 12c

Home Log Out Preferences Record Help

Welcome, weblogic Connected to: FCUBSDomain

Home > FCUBSGMTTemplate > Summary of Server Templates > FCUBSGMTTemplate > Summary of Clusters > Summary of Servers > Summary of JDBC Data Sources

Create a New JDBC Data Source

Test Configuration Back Next Finish Cancel

Test Database Connection
Test the database availability and the connection properties you provided.

What is the full package name of JDBC driver class used to create database connections in the connection pool?
(Note that this driver class must be in the classpath of any server to which it is deployed.)

Driver Class Name:

What is the URL of the database to connect to? The format of the URL varies by JDBC driver.

URL:

What database account user name do you want to use to create database connections?

Database User Name:


What is the database account password to use to create database connections?
(Note: for secure password management, enter the password in the Password field instead of the Properties field below)

Password:


Confirm Password:

What are the properties to pass to the JDBC driver when creating database connections?

Properties:



6) Upon Activate Changes would create the XA Datasource



7) Similarly create all the other Datasource required for the FCUBS Application and Gateway Deployments

The screenshot shows the Oracle WebLogic Server Administration Console. The left sidebar contains navigation menus for Change Center, Domain Structure, and System Status. The main content area is titled 'Summary of JDBC Data Sources' and includes a 'Configuration' tab. A message states: 'All changes have been activated. No restarts are necessary.' Below this, a table lists the configured data sources:

Name	Type	JNDI Name	Targets
FCUBSBranchDS	Generic	jdbc/fgdevDSBranch	FCUBSCluster
FCUBSDS	Generic	jdbc/fgdevDS	FCUBSCluster
FCUBSDS_ASYNC	Generic	jdbc/fgdevDS_ASYNC	FCUBSCluster
FCUBSDS_XA	Generic	jdbc/fgdevDS_XA	FCUBSCluster
FCUBSScheduleDS	Generic	jdbc/fgScheduleDS	FCUBSCluster
FLEXTTEST.WORLD	Generic	FLEXTTEST.WORLD	FCUBSCluster

6.4 JDBC Parameters Tuning

Below JDBC parameters needs to updated for all the Datasources

PARAMETER	VALUE	Navigate To
Connection Reserve time out	30	Connection Pool->Advance
Test Frequency	60	Connection Pool->Advance
Inactive connection time out	30	Connection Pool->Advance
Initial Capacity	1	Connection Pool
Max capacity	Based on Site Requirement	Connection Pool
Capacity Increment	5	Connection Pool
Shrink Frequency	900	Connection Pool->Advance
Test Connection on Reserve	Checked	Connection Pool->Advance

7. JMS Resource Creation

JMS Resource Creation involves various steps

- Persistence Store Creation
- JMS Server Creation
- JMS Module Creation
- Resource Creation: Connection Factory and Queue's

Refer to the JMS Cluster Configuration document for further details on JMS setup.

8. Oracle WebLogic Load Balancing

For Weblogic Load balancing, use

- 1) Oracle HTTP Server: Refer to Configuration for Oracle HTTP Server for setup.
- 2) Apache: Refer to Configuration for Apache for setup.

9. Frequently Asked Questions

9.1 Machine status is Unreachable.

If the machine status is unreachable, means that machine is not reachable and from console you cannot start/stop the managed servers.

In the console, navigate through Domain structure → Machines → machine1 → Monitoring → Node Manager Status will be **Unreachable**

To change the status, you need to start the nodemanager on that server. Refer to start nodemanager section on steps to start the nodemanager.

9.2 How to restart node manager?

- 1) Locate node manager pid using `ps -ef|grep weblogic.nodemanager.javaHome`
- 2) Change directory to `$DOMAIN_HOME/bin`
- 3) Kill the unix process using `kill -9 <pid>`
- 4) Verify that the node manager is killed by `tail -f nohup.out`
- 5) Start node manager using `nohup ./startNodeManager.sh &`
- 6) Verify nodemanager is started using `tail -f nohup.out`

9.3 Scaling Up Dynamic Cluster

When the capacity is insufficient and you need to scale-up, you can add dynamic servers on demand. It requires only a few clicks.

- 1) Navigate to FCUBSDomain → Environment → Clusters

The screenshot shows the WebLogic Server Administration Console interface. On the left, the 'Domain Structure' tree is visible, showing the hierarchy: FCUBSDomain > Environment > Clusters. The main content area is titled 'Summary of Clusters' and contains a table of clusters. The table has the following columns: Name, Cluster Address, Cluster Messaging Mode, Migration Basis, Default Load Algorithm, Replication Type, Cluster Broadcast Channel, and Servers. There is one cluster listed: FCUBSCluster, which has 4 servers: FCUBSHS1, FCUBSHS2, FCUBSHS3, and FCUBSHS4. The table also includes 'New', 'Clone', and 'Delete' buttons for each row.

Name	Cluster Address	Cluster Messaging Mode	Migration Basis	Default Load Algorithm	Replication Type	Cluster Broadcast Channel	Servers
FCUBSCluster		Unicast	Database	Round Robin	(None)		FCUBSHS1, FCUBSHS2, FCUBSHS3, FCUBSHS4

2) Click FCUBSCluster → Configuration→ Servers tab

The screenshot shows the Oracle WebLogic Server Administration Console. On the left, the 'Change Center' panel indicates 'No pending changes exist. Click the Release Configuration button to allow others to edit the domain.' Below it, the 'Domain Structure' tree shows the hierarchy: FCUBSDomain > Environment > Servers > Clusters > FCUBSCluster. The main panel displays the 'Settings for FCUBSCluster' with tabs for Configuration, Monitoring, Control, Deployments, Services, and Notes. The 'Servers' sub-tab is active. It shows the 'Server Template' as 'FCUBSMSTemplate', 'Maximum Number of Dynamic Servers' as 4, and 'Server Name Prefix' as 'FCUBSMS'. A 'Save' button is at the top left of the settings area.

3) Change the Maximum Number of Dynamic Servers to: 8 and Click Save

This screenshot is similar to the previous one, but the 'Maximum Number of Dynamic Servers' has been changed from 4 to 8. The number '8' is highlighted with a red rectangular box. The 'Save' button remains visible at the top left of the settings area.

4) Activate changes in the Change Center of the Weblogic Console. After activation 4 new Dynamic Servers are added to the Dynamic Cluster

<input type="checkbox"/>	Name	Type	Machine	Listen Port
<input type="checkbox"/>	FCUBSMS1	Dynamic	MAC-1	7101
<input type="checkbox"/>	FCUBSMS2	Dynamic	MAC-2	7102
<input type="checkbox"/>	FCUBSMS3	Dynamic	MAC-1	7103
<input type="checkbox"/>	FCUBSMS4	Dynamic	MAC-2	7104
<input type="checkbox"/>	FCUBSMS5	Dynamic	MAC-1	7105
<input type="checkbox"/>	FCUBSMS6	Dynamic	MAC-2	7106
<input type="checkbox"/>	FCUBSMS7	Dynamic	MAC-1	7107
<input type="checkbox"/>	FCUBSMS8	Dynamic	MAC-2	7108

5) Start the 4 new Dynamic Servers and you have doubled you capacity.

9.4 **Session Timeout**

Session timeouts occur intermittently during load condition. Verify the following

1. Clock Synchronization: Time across the nodes/machines is same.
2. Session Stickiness in load balancer: Persistence Type in load balancer should be set to SOURCE IP and should not be cookie.



FCUBS Weblogic 12c Middleware Practices
[May] [2017]
Version 12.4.0.0.0

Oracle Financial Services Software Limited
Oracle Park
Off Western Express Highway
Goregaon (East)
Mumbai, Maharashtra 400 063
India

Worldwide Inquiries:
Phone: +91 22 6718 3000
Fax: +91 22 6718 3001
www.oracle.com/financialservices/

Copyright © 2007, 2017, Oracle and/or its affiliates. All rights reserved.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

U.S. GOVERNMENT END USERS: Oracle programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, delivered to U.S. Government end users are "commercial computer software" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, use, duplication, disclosure, modification, and adaptation of the programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, shall be subject to license terms and license restrictions applicable to the programs. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate failsafe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

This software or hardware and documentation may provide access to or information on content, products and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services.