

Oracle® Communications Convergent Charging Controller Provisioning Interface Alarms Guide



Release 15.0.0

October 2023

The Oracle logo, consisting of the word "ORACLE" in white, uppercase, sans-serif font, centered within a solid red square.

ORACLE

Copyright

Copyright © 2023, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software" or "commercial computer software documentation" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle, Java, and MySQL are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Alarm Topic Description 1

PImanager 3

PIprocess..... 6

PIbatch 15

PIbatch XML 16

Alarm Topic Description

Alarm Generation

Alarms on each configured node are written to the syslog and are then captured by the smsAlarmDaemon for entry in the SMF database.

For management of these alarms, see *Service Management System Technical Guide*.

Severity Levels

This table describes the alarm severity levels.

| Level | Abbreviation | Description |
|----------|--------------|--|
| Critical | C | These alarms are raised when the application has encountered an error indicating that the system is unable to function. |
| Error | E | These alarms indicate the application has encountered a serious problem completing a necessary task and could not complete the task. |
| Warning | W | Warnings are raised to indicate the application encountered a problem completing a non-mission critical task. |
| Notice | N | Notices are raised to indicate that the application has completed a task successfully. |

Alarm Format

Alarms usually follow this format:

```
Mon DD 24:MM:SS hostname process name: [ID alarmID user.severity] process(PID)
SEVERITY: Alarm text with possible variables
```

Where:

| Variable | Description |
|--------------|---|
| Mon DD | Month and date the alarm was logged. |
| 24:MM:SS | Time the alarm was logged in 24 hour format. |
| hostname | Name of the machine on which the alarm was generated. |
| process name | Name of the process which logged the alarm. |
| alarmID | ID number of the alarm. |
| severity | Alarm severity. |
| process | Name of the process which logged the alarm. |
| PID | Process ID of the process which logged the alarm. |
| SEVERITY | Alarm severity. |
| Alarm text | Alarm text. This may include variables such as node number. Note: In some cases, the entire alarm text is generated from variables. |

Note: Some alarms from some subsystems may have a different format.

Example: This text shows an smsMaster alarm about pending update queues.

```
Mar 30 13:34:54 prodsmpl smsMaster: [ID 953149 user.warning] smsMaster(17833)
WARNING: Pending queue now above 15 (Worst Node 317)
```

Alarm Text and Variables

The %d and %s symbols represent variables within the alarm text. These values are generated by the subsystem and added to the message when the alarm is raised.

Usually the %d is a number and the %s is text in the context of the message to complete the alarm message. Occasionally other % symbols are also used (for example, %u) for different variables.

Further Information

For more information about:

- The SMS Alarms subsystem, see *Service Management System Technical Guide*
- Creating and maintaining the SMS Alarm Relay rule set, see *Service Management System User's Guide*

Plmanager

Errors

This table defines the error messages for Plmanager.

| Alarm | Text | Cause | Resolution |
|--------|--|---|---|
| 210220 | Cannot connect to Oracle - exiting | Oracle is not running. | Start Oracle. |
| 210221 | Could not make fifo <f> - exiting | The file <f> could not be created. | Check that the "smf_oper" user has sufficient permission to create the file. Check that the disk is not full. |
| 210222 | Could not make fifo directory <d> - exiting | The directory <d> could not be created. | Check that the "smf_oper" user has sufficient permission to create the directory. Check that the disk is not full. |
| 201223 | Error starting PIbeClient | PIbeClient could not be started. | If PIbeClient should be being started, check PIbeClient exists and is executable. If PIbeClient should not be being started, ensure there is no pi.PIbeClient section in eserv.config . |
| 210225 | Error starting PIprocess | PIprocess could not be started. | Check PIprocess exists and is executable. |
| 210226 | Exception reading configuration pi.general.oraUser: check format e.g. "oraUser = "/" - cannot continue | The configuration file entry for pi.general.oraUser has syntax errors. | Check the format of eserv.config . |
| - | Exception reading configuration pi.general.synstamp: check format e.g. "synstamp = 'N'" - cannot continue | The configuration file entry for pi.general.synstamp has syntax errors. | Check the format of eserv.config . |

| Alarm | Text | Cause | Resolution |
|------------------|---|--|---|
| - | Exception reading configuration pi.general.timeout: check format e.g. "timeout = 30" - cannot continue | The configuration file entry for pi.general.timeout has syntax errors. | Check the format of eserv.config . |
| - | Exception reading configuration pi.general.mode: check format e.g. "mode = 0" - cannot continue | The configuration file entry for pi.general.mode has syntax errors. | Check the format of eserv.config . |
| - | no PIProcesses left | All PIProcesses have stopped so the PIManager has stopped. | Restart the PIManager. |
| 210211 210214 | PIbeClient is dead | PIbeClient has stopped. See the PIbeClient output for more details. | PIManager will attempt to restart the PIbeClient. If this persists, check for additional PIbeClient error messages. |
| 210212 | PIprocess for port n is dead | A PIprocess has stopped. See the PIprocess output for more details. | Restart the PIManager. |
| 210213 | PIprocess pid <p> on port <n> timed out. Sending friendly timeout signal | A PIprocess has timed out. | A timeout may indicate some problem with the database. Check the database is running correctly. |
| 210358 | PIprocess pid <p> on port <n> timed out and not responding. Killing it now. | A PIprocess has timed out and not responded to the time out signal. | A timeout may indicate some problem with the database. Check the database is running correctly. |
| - | SQL Error: <message> | An Oracle error occurred. | Consult Oracle documentation for the error code. |
| - | SQL error <n> reading PI_PORTS - exiting | An oracle error occurred reading the PI_PORTS table. | Consult Oracle documentation for the error code. |
| - | Unknown message type n from PI <p>. | The PIprocess on port <p> has sent an unknown message type to the PIManager. | Check that the PIprocess on port <p> is functioning correctly. |

Warnings

This table defines the warning messages for PImanager.

| Alarm | Text | Cause | Resolution |
|-------|------------------------|-----------------------------|--|
| - | SQL Warning: <message> | An oracle warning occurred. | Consult oracle documentation for the error code. |

Notifications

This table defines the notification messages for PImanager.

| Alarm | Text | Cause | Resolution |
|--------|--|--|---------------------------------------|
| - | About to turn debug <on off> for PImanager | Debug has been turned on or off for the specified PImanager. | Information only, no action required. |
| 210229 | PImanager started | PImanager has started. | Information only, no action required. |
| 210230 | Received SIGHUP - Sending SIGHUP to PProcesses | PImanager has received a SIGHUP. | Information only, no action required. |
| - | Received SIGINT - Sending SIGINT to PProcesses and exiting | PImanager has received a SIGINT. | Information only, no action required. |
| - | Received SIGQUIT - Sending SIGTERM to PProcesses and exiting | PImanager has received a SIGQUIT. | Information only, no action required. |
| 210227 | Received SIGTERM - Sending SIGTERM to PProcesses and exiting | PImanager has received a SIGTERM. | Information only, no action required. |

Plprocess

Error codes - general

This table defines the Error code messages for PI command responses.

| Alarm | Text | Cause | Resolution |
|-------|------------------------------------|--|--|
| 70 | TOO MANY SESSIONS | The maximum allowed number of connections is already in use. | <p>Check whether the number of active sessions is larger than the allowed sessions set in the PI Administration screen. If it is, either:</p> <ul style="list-style-type: none">• this message is information only and no action is required, or• increase the number of maximum sessions to accommodate the load. <p>If it is lower than the specified maximum, contact support with details.</p> |
| 71 | LOGON SYNTAX ERROR | Could not parse logon request. The login attempt had a syntax error. | <p>Check that the login command is formatted correctly.</p> <p>Contact Oracle support with details.</p> |
| 72 | INVALID LOGON - username, password | Username and/or password are not invalid. | <p>If the username and password should not be recognised by the system, this message is information only, and no action is required.</p> <p>If the username and password should be recognised, either:</p> <ul style="list-style-type: none">• correct the details in the PI Administration screen, or• contact support with details. |

| Alarm | Text | Cause | Resolution |
|-------|---|---|--|
| 73 | INVALID LOGON - user not allowed on this port | User cannot connect to a server running on the particular port used. | <p>If the port where the attempted logon occurred was not intended as a valid port, this message is information only, and no action is required.</p> <p>If the port should accept connections, either:</p> <ul style="list-style-type: none"> • correct the port number in the PI Administration screen • check that the user is attempting to connect on the correct port, or • contact support with details. |
| 74 | INVALID LOGON - host | <p>Not allowed to connect from this host.</p> <p>The host ip address of the machine that is trying to connect to PI may not be defined in the SMF database.</p> | <p>If the host where the attempted logon was from was not intended as a valid host, this message is information only, and no action is required.</p> <p>If the host should be allowed to make connections, either:</p> <ul style="list-style-type: none"> • correct the host details in the PI Administration screen and restart the PI manager • check that the user is attempting to connect from the correct host, or • contact Oracle support with details. |
| 75 | UNKNOWN COMMAND | <p>The command is not recognised.</p> <p>The command is not defined in the PI_COMMANDS database.</p> | <p>Check the defined commands using the PI Administration screen.</p> <p>Contact Oracle support with details.</p> |
| 76 | USER DOES NOT HAVE SUFFICIENT SECURITY | The user does not have the privilege to run the requested command. | <p>If the user who attempted to run the command was not intended to be able to run it, this message is information only, and no action is required.</p> <p>If the user should be allowed to run this command, either:</p> <ul style="list-style-type: none"> • correct the details in the PI Administration screen, or • contact support with details. |
| 77 | SYNSTAMP NOT FOUND | The command did not have a synstamp when synstamps are required. | Make sure the command is appended with a synstamp. |

| Alarm | Text | Cause | Resolution |
|-------|---------------------------------|--|---|
| 78 | SYNSTAMP NOT VALID | The synstamp appended to the command was not valid. | Check that the synstamp is larger than the last used synstamp. |
| 79 | INVALID OR MISSING MAC | The command was not appended by a security MAC when MACs are required. | Make sure the appended MAC is valid and that the correct MAC key is being used. |
| 80 | UNKNOWN PARAMETER FOR COMMAND | A parameter found in the command is recognised. | Check that the command's parameters are as defined in the PI_COMMANDS table by using the PI Administration screen. Contact Oracle support with details. |
| 81 | MISSING PARAMETERS FROM COMMAND | One or more required parameters are missing from the command. | Check that the parameters were provided with the command. Check that the command's required parameters are as defined in the PI_COMMANDS table by using the PI Administration screen. Contact Oracle support with details. |
| 83 | DUPLICATE PARAMETER | A parameter appeared twice in the command. | Check whether only one parameter was supplied. Contact Oracle support with details. |
| 84 | ERROR RUNNING PROCEDURE | The message sent to the Provisioning Interface was valid, but a failure occurred when attempting to run the service. | Check syslog for errors. If the problem persists, contact Oracle support with details. |
| 85 | USER SESSION TERMINATED | The server has shut down the session. The user's session has been terminated by an administrator issuing the kill management command. | If the session was not intended to be shut down, and the problem persists, contact Oracle support with details. |
| 86 | COMMAND TOO BIG | The supplied command was too big. | Check the syntax of the command. |
| 87 | COMMAND SYNTAX ERROR | There is a syntax error in the command. | Check the syntax of the command. Contact Oracle support with details. |
| 88 | PARAMETER NAME TOO BIG | A parameter name is too big for the command syntax. | Check the parameter name. Contact Oracle support with details. |
| 89 | PARAMETER VALUE TOO BIG | A parameter value is too big for the command syntax. | Check the parameter value. Contact Oracle support with details. |

| Alarm | Text | Cause | Resolution |
|-------|-------------------------------|--|--|
| 90 | SYNSTAMP OUT OF PLACE | The synstamp was in the wrong place in the command. | <p>Check that the synstamp is in the correct place:</p> <ul style="list-style-type: none"> When MAC security is ON, the synstamp should be between the last command parameter and the MAC. When MAC security is OFF, the synstamp should be at the end of the command, after the last command parameter. <p>Contact Oracle support with details.</p> |
| 91 | TIMEOUT | A timeout has occurred. | <p>A timeout can indicate problems in the database. If the problem persists and there appears to be no other problems the timeout value can be increased.</p> |
| 92 | INTERNAL ERROR SEE SYSLOG | An internal error has occurred. More information is available from the system log. | If the problem persists, contact Oracle support with details. |
| 93 | ERROR READING REPLY FROM FILE | The PI could not read the results from a DB query that were saved to a temporary file. | Contact Oracle support with details. |
| 94 | INVALID AUTHENTICATION TOKEN | The authentication token passed has expired or no authentication token was supplied. | The session should be re-started. |

Errors

This table defines the error messages for PIprocess.

| Alarm | Text | Cause | Resolution |
|------------------|---|--|--|
| 210234 | Cannot connect to internal DB - cannot continue | The PIprocess could not connect to oracle. | Start Oracle. Check that the oracle environment for the smf_oper UNIX user is correct. |
| 210235 210236 | Cannot read from internal DB - cannot continue | The PIprocess could not read from the internal DB. | Check that the PI tables are installed correctly on the SMF machine and have at least one port configured. |

| Alarm | Text | Cause | Resolution |
|--------|--|---|--|
| - | Could not create SQL trace file <filename>. All sql tracing will go to PImanager.log. perror for this follows | Could not create a new file. | Check the next reported error which will describe the file error in detail. |
| 210233 | Could not make fifo <f> | The fifo file <f> could not be created. | Check that the directory that the file <f> is to be made in is writable by the smf_oper user. Check that the disk is not full. |
| 210286 | Could not open fifo <f> | The fifo file <f> could not be opened. | Check that the directory that the file <f> is to be made in is writable by the smf_oper user. |
| - | Could not rename SQL trace file <filename a> to <filename b>. SQL tracing will continue to <filename a>. perror for this follows | Could not create a new file. | Check the next reported error which will describe the file error in detail. |
| - | Currently got n connections so deferring database re-read until all connections closed | The PIprocess has received an instruction to re-read the internal database. This cannot be done safely with active connections, so will be delayed until all connections are closed | Close all connections to the PI to re-read the database. |
| 210305 | Error occurred running C function <f> in shared library <l>. Output is ... | An error occurred while running the command. Check for other errors preceding this error. | Check preceding errors in the PI commands library errors section below. |
| 210306 | Error reading request for user <x> on host <h> - logged off | An error occurred reading a command from a remote user. Usually occurs if the user disconnects in the middle of a command. The user is logged off. | The user should re-login. |

| Alarm | Text | Cause | Resolution |
|------------------|--|--|--|
| - | Exception reading configuration pi.authentication.timeout : check format e.g. "timeout = 0" - cannot continue | The configuration file entry for pi.authentication.timeout has syntax errors. | Check the format of eserv.config . |
| - | Exception reading configuration pi.general.logLevel: check format e.g. "loglevel = 0" - cannot continue | The configuration file entry for pi.general.logLevel has syntax errors. | Check the format of eserv.config . |
| - | Exception reading configuration pi.general.sqlTraceDirectory: check format e.g. "sqlTraceDirectory = "/IN/service_packages/PI/ tmp/trace/" - cannot continue | The configuration file entry for pi.general.sqlTraceDirectory has syntax errors. | Check the format of eserv.config . |
| - | Exception reading configuration pi.localTZ: check the format - cannot continue | The configuration file entry for pi.localTZ has syntax errors. | Check the format of eserv.config . |
| - | Exception reading configuration pi.throttling.sendRate: check the format e.g. "sendRate = 0" - cannot continue | The configuration file entry for pi.throttling.sendRate has syntax errors. | Check the format of eserv.config . |
| - | Exit due to exception: <message> | An internal error has occurred. | Restart the PI. Consult support if persistent. |
| 210260 210371 | Oracle connection lost - exiting | The PIprocess connection to the database has been lost. The PIprocess will restart to reconnect to the database cleanly. | Check the logs for related errors. If this occurs persistently, or the PIprocess cannot reconnect, check the oracle database or contact support. |

| Alarm | Text | Cause | Resolution |
|--------|---|--|---|
| 210261 | PPID is 1 - PImanager has died and not killed me - exiting | The controlling PImanager has stopped or been stopped without firstly stopping the PProcesses. | Restart the PImanager. |
| 210262 | Problems setting up socket - cannot continue | The PProcess could not bind to the port specified in the database, probably due to another process using the port. | Check that the port is not used by another process. Change the port number using the PI Administration screen. |
| 210318 | Security warning. Bad MAC in message from user <x> | A user has an incorrect mac on a command. | Check the user and system MAC keys are the same. |
| 210319 | Security warning. Bad synstamp in message from user <x> | A user has used an incorrect synstamp. | The next synstamp must be a number larger than the last synstamp returned from the PProcess or used by the user. |
| 210320 | Security warning. Connection from unknown host <h> | A connection has been attempted from a host not listed in the hosts database. | If the host is valid it should be entered into the hosts database using the PI administration screens. Then the PImanager should be sent a SIGHUP signal using the PIReread script to force a database re-read. |
| 210321 | Security warning. Invalid login attempt (garbage read) from host <h> | The username/password were not separated by a comma. | Check that the correct format (username,password;) is being used for the login attempt. |
| 210322 | Security warning. Invalid login attempt (user on wrong port) from host <h> | A user has tried to connect to a port he is not allowed to connect to. | If the user should be allowed to connect to this port, add the port using the PI administration screens, and then send the PImanager a SIGHUP signal using PIReread.sh to force a database reread. |
| 210323 | Security warning. Invalid login attempt (username or password too long) from host <h> | The username/password combination was too long. | Check that the correct username and password combination is being used. |

| Alarm | Text | Cause | Resolution |
|----------|---|--|---|
| 210324 | Security warning. Invalid login attempt (username, password) from host <h> | Either the username or the password is not correct. | Check that the correct username and password combination are being used. |
| 210325 | Security warning. User <x> level <n> requested command level <m>. | A user tried to use a command which has a higher security level than the user's security level. | If the user should be able to use that command, raise the user's security level to at least that command's security level. |
| Note (1) | Shared Library <l> not loaded: <error message>. | The shared library could not be loaded. The error message will give more detailed information. | Reinstall the package or patch. Contact Oracle support with details. |
| - | SQL Error: <message> | An oracle error occurred. | Consult oracle documentation for the error code. |
| 210294 | Symbol <s> not found is shared library <l> | The code for the specified command is not in the shared library. | Check that the database entry for the command in PI_COMMANDS is correct. |
| - | Timeout occurred. | The processing of the command timed out. | A timeout can indicate problems with the database or billing engine client resulting in long query times. |

Note (1) Alarm IDs that would match this message: 210263 – 210270, 210293, 210372, 210373, and 210383.

Warnings

This table defines the warning messages for Plprocess.

| Alarm | Text | Cause | Resolution |
|-------|--|---|---|
| - | Warning: fifos to PImanager not opened. | The communication files to PImanager were not found or could not be opened. | Check that the files (in /tmp/PIfifo) exist and are read and writable by the smf_oper user. |

Notifications

This table defines the notification messages for PProcess.

| Alarm | Text | Cause | Resolution |
|----------|--|--|---------------------------------------|
| 210214 | About to start PProcess | PManager has attempted to start a PProcess. | Information only, no action required. |
| - | About to turn debug <on off> for <command> | Debug has been turned on or off for the specified PI command. | Information only, no action required. |
| - | About to turn debug <on off> for PIbeClient | Debug has been turned on or off for the specified PIbeClient. | Information only, no action required. |
| - | About to turn debug <on off> for PProcess port <p> | Debug has been turned on or off for the specified PProcess. | Information only, no action required. |
| - | Debug turned [on off] by PProcess <n> | PManager debug has been toggled by a PProcess | Information only, no action required. |
| Note (1) | PProcess started | PProcess has started. | Information only, no action required. |
| - | Received SIGALRM from PManager PID <p> UID <u>. Timing out. | PProcess receives a SIGALRM from PManager and the time out process starts. | Information only, no action required. |
| - | Received SIGALRM from unknown process PID <p>, UID <u>. Not timing out | PProcess receives a SIGALRM from a process that is not PManager. The sending process and user is stated. | Information only, no action required. |
| - | Received SIGHUP from PID <p>, UID <u> | PProcess has received a SIGHUP. The sending process and user is stated. | Information only, no action required. |
| - | Received SIGINT - Exiting | PProcess has received a SIGINT. | Information only, no action required. |
| Note (2) | Received SIGTERM - Exiting | PProcess has received a SIGTERM. | Information only, no action required. |
| - | Received SIGTERM from PID <p>, UID <u> | PProcess receives a SIGTERM. The sending process and user is stated. | Information only, no action required. |

| Alarm | Text | Cause | Resolution |
|--------|---|---|---------------------------------------|
| - | Received SIGUSR1 from PID <p>, UID <u> | PIprocess receives a SIGUSR1. The sending process and user is stated. | Information only, no action required. |
| - | Re-reading internal provisioning database | PIprocess has received a SIGHUP and is re-reading the database. | Information only, no action required. |
| 210307 | Shared library <l> successfully loaded. | The shared library has been successfully loaded. | Information only, no action required. |
| - | Unloading shared library <l> | The database has been re-read after a SIGHUP. | Information only, no action required. |
| 210308 | User <x> logged off on host <h> | A user had disconnected. | Information only, no action required. |
| 210309 | User <x> logged on from host <h> | A user has successfully logged on. | Information only, no action required. |

Note (1) Alarm IDs that would match this message: odd numbers from 210327 through 210357.

Note (2) Alarm IDs that would match this message: even numbers from 210326 through 210356.

PIbatch

Errors

This table defines the error messages for PIbatch.

| Alarm | Text | Cause | Resolution |
|-------|--|---|--|
| - | Cannot open result file <file> - exiting | The PIbatch could not open the results file for writing. | Check file permissions for the user running the PIbatch. |
| - | Cannot open script file <file> - exiting | The PIbatch could not open the input script file for reading. | Check file permissions for the user running the PIbatch, and that the file exists. |
| - | Error reading script file <file> - exiting | The PIbatch could not read the input script file. | Check file permissions for the user running the PIbatch, and that the file exists. |

| Alarm | Text | Cause | Resolution |
|-------|---|--|--------------------------------------|
| - | Line <n>: Connect line found when already connected, disconnecting and will reconnect | Syntax error in the input file. | Correct the input file. |
| - | Line <n>: Disconnect line when not connected, skipping | Syntax error in the input file. | Correct the input file. |
| - | Line <n>: Not connected, not sending command | PI command in input file before the connection line. | Correct the input file. |
| - | Usage: PIbatch <script> <server> | Wrong number of command line arguments. | Usage is "PIbatch <script> <server>" |

PIbatch XML

Errors

This table defines the error messages for PIbatch XML.

| Alarm | Text | Cause | Resolution |
|-------|---|--|--|
| - | unable to connect to PI: <message> | Could not connect to PIprocess. | Check the PIprocess is running. Check the hostname is correct. Check the port number is correct. |
| - | unable to read <filename>: open() failed with <message> | Unable to read the input file. | Check file permissions for the user running the PIbatch, and that the file exists. |
| - | -l not available when reading from stdin | Looping was requested with no input file | Do not specify looping when the input is standard input. |

Notifications

This table defines the notification messages for Plbatch XML.

| Alarm | Text | Cause | Resolution |
|-------|---|--|---------------------------------------|
| - | multiple IP addresses for host <h>, using <address> | The PI server has more than one address. The one to be used is stated. | Information only, no action required. |