

Oracle® Communications Convergent Charging Controller Messaging Manager Alarms Guide



Release 15.1

April 2025

The Oracle logo, consisting of the word "ORACLE" in white, uppercase, sans-serif font, centered within a solid red square.

Copyright

Copyright © 2025, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software" or "commercial computer software documentation" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle, Java, and MySQL are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Alarm Topic Description1

Messaging Manager Alarms.....3

Alarm Topic Description

Alarm Generation

Alarms on each configured node are written to the syslog and are then captured by the smsAlarmDaemon for entry in the SMF database.

For management of these alarms, see *Service Management System Technical Guide*.

Severity Levels

This table describes the alarm severity levels.

Level	Abbreviation	Description
Critical	C	These alarms are raised when the application has encountered an error indicating that the system is unable to function.
Error	E	These alarms indicate the application has encountered a serious problem completing a necessary task and could not complete the task.
Warning	W	Warnings are raised to indicate the application encountered a problem completing a non-mission critical task.
Notice	N	Notices are raised to indicate that the application has completed a task successfully.

Alarm Format

Alarms usually follow this format:

```
Mon DD 24:MM:SS hostname process name: [ID alarmID user.severity] process(PID)
SEVERITY: Alarm text with possible variables
```

Where:

Variable	Description
Mon DD	Month and date the alarm was logged.
24:MM:SS	Time the alarm was logged in 24 hour format.
hostname	Name of the machine on which the alarm was generated.
process name	Name of the process which logged the alarm.
alarmID	ID number of the alarm.
severity	Alarm severity.
process	Name of the process which logged the alarm.
PID	Process ID of the process which logged the alarm.
SEVERITY	Alarm severity.
Alarm text	Alarm text. This may include variables such as node number. Note: In some cases, the entire alarm text is generated from variables.

Note: Some alarms from some subsystems may have a different format.

Example: This text shows an smsMaster alarm about pending update queues.

```
Mar 30 13:34:54 prodsmpl smsMaster: [ID 953149 user.warning] smsMaster(17833)
WARNING: Pending queue now above 15 (Worst Node 317)
```

Alarm Text and Variables

The %d and %s symbols represent variables within the alarm text. These values are generated by the subsystem and added to the message when the alarm is raised.

Usually the %d is a number and the %s is text in the context of the message to complete the alarm message. Occasionally other % symbols are also used (for example, %u) for different variables.

Further Information

For more information about:

- The SMS Alarms subsystem, see *Service Management System Technical Guide*
- Creating and maintaining the SMS Alarm Relay rule set, see *Service Management System User's Guide*

Messaging Manager Alarms

Alarm	Severity	Text	Cause	Resolution	Service
370000	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsSvcLibrary: NULL reply when attempting debit	A NULL reply was received from the billing interface when attempting to perform the debit for a long held reservation.	Check for errors reported by the billing interface. Check for version compatibility between xmsSvcLibrary and the billing interface.	XMS
370002	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsSvcLibrary: processCall received unsupported action type %d.	The service library has been asked to handle an action result that it does not recognise.	This typically indicates a misconfiguration. Check for recent upgrades of other interfaces such as billing engine interfaces, or ACS chassis actions. Revert to compatible versions.	XMS
370003	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsSvcLibrary: error from debit request: %d	An error response was received from the billing interface when attempting to perform the debit for a long held reservation.	Check for errors reported by the billing interface. The account may have been removed, or modified in the intervening time.	XMS
370004	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsSvcLibrary: exception from debit req. class %d type %d	An exception was generated when attempting to process the response from the billing interface to the debit for a long held reservation.	Check for errors reported by the billing interface. Check for version compatibility between xmsSvcLibrary and the billing interface.	XMS
370005	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsSvcLibrary: received incorrect operation %d.	The debit sent to the billing engine generated an invalid operation code in reply.	Check for errors reported by the billing interface. Check for version compatibility between xmsSvcLibrary and the billing interface.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370006	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsSvcLibrary: unexpected MOX return type.	The debit sent to the billing engine generated an invalid MOX return type in reply.	Check for errors reported by the billing interface. Check for version compatibility between xmsSvcLibrary and the billing interface.	XMS
370010	WARNING	%s %d: xmsTrigger(%d) WARNING: No Msid Rules configured for xmsSvcLibrary	Config parameter XMS.serviceLibrary.MsidDi stinction is not specified (its an optional parameter only necessary for MIN/MDN distinction)	No action required.	XMS
370013	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsSvcLibrary: XMS_Originating - No CP for CLI %s %d	No call plan be found for the calling address indicated.	This almost always indicates a mis- configuration. Ensure that the indicated CLI is attached to an active call plan in the ACS database.	XMS
370014	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsSvcLibrary: XMS_Terminating - No CP for DN %s %d	No call plan be found for the destination address indicated.	This almost always indicates a mis- configuration. Ensure that the indicated SN is attached to an active call plan in the ACS database.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370015	ERROR	%s %d: xmsTrigger(%d) ERROR: Reattached to shmKey %d. Lost stats on %d calls	The shared memory segment used by the smsStatsDaemon had become unavailable, and is now available again. A number of statistics values have been lost.	Check for a problem with the smsStatsDaemon.	XMS
370016	ERROR	%s %d: xmsTrigger(%d) ERROR: shmAttach: Cannot attach to shmKey %d	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370017	ERROR	%s %d: xmsTrigger(%d) ERROR: shmAttach: Cannot get semID from semKey %d	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370018	ERROR	%s %d: xmsTrigger(%d) ERROR: shmAttach: Cannot get shmKey from semID %d	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370019	ERROR	%s %d: xmsTrigger(%d) ERROR: shmAttach: Error %d getting INODE for %z	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370020	ERROR	%s %d: xmsTrigger(%d) ERROR: smsRetrieveStats: Cannot attach to SHM	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370021	ERROR	%s %d: xmsTrigger(%d) ERROR: smsRetrieveStats: Cannot reattach to SHM	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370022	ERROR	%s %d: xmsTrigger(%d) ERROR: smsSetStats: Could not retrieve %z	The indicated statistics value could not be read. This typically indicates that the statistics value does not exist in the SMF_STATISTICS_DEFN table.	Check that SMF_STATISTICS_DEFN contains the indicated statistics value. Check for spelling errors. Restart the smsStatsDaemon if necessary.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370023	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTryRecordStats: Cannot attach to SHM	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370024	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTryRecordStats: Cannot reattach to SHM	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370025	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTryRecordStats: Internal error updating %z	The indicated statistics value could not be written. This is a system error, not just a missing statistics entry problem.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370026	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTryRecordStats: Memory state not VALID - giving up	A problem has occurred attempting to attach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370027	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTrySetStats: Internal error updating %z	The indicated statistics value could not be written. This is a system error, not just a missing statistics entry problem.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370028	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTrySetStats: Internal error retrieving %z	The indicated statistics value could not be written. This is a system error, not just a missing statistics entry problem.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370029	ERROR	%s %d: xmsTrigger(%d) ERROR: stripGSMUDHeader: Header Len > UDL, implies malformed GSM User Data.	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370031	ERROR	%s %d: xmsTrigger(%d) ERROR: xlate7bitToGsm7bit: UDL %d (offsetBits %d) too large for dst size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS
370034	ERROR	%s %d: xmsTrigger(%d) ERROR: dt_add: Require appID, statID, statInfo all non-NULL	An internal statistics function call has passed invalid parameters.	Contact support.	XMS
370035	ERROR	%s %d: xmsTrigger(%d) ERROR: dt_find: Require appID, statID, statInfo all non-NULL	An internal statistics function call has passed invalid parameters.	Contact support.	XMS
370036	ERROR	%s %d: xmsTrigger(%d) ERROR: dt_add: Require appID, statID, statInfo all non-zero len	An internal statistics function call has passed invalid parameters.	Contact support.	XMS
370037	NOTICE	%s %d: xmsTrigger(%d) NOTICE: dt_add: Parent statistic %s %d does not exist	The indicated statistics value could not be written. This typically indicates that the statistics value does not exist in the SMF_STATISTICS_DEFN table.	Check that SMF_STATISTICS_DEFN contains the indicated statistics value. Check for spelling errors. Restart the smsStatsDaemon if necessary.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370038	NOTICE	%s %d: xmsTrigger(%d) NOTICE: smsRecordStats: Statistic not foundZZZ	The indicated statistics value could not be written. This typically indicates that the statistics value does not exist in the SMF_STATISTICS_DEFN table.	Check that SMF_STATISTICS_DEFN contains the indicated statistics value. Check for spelling errors. Restart the smsStatsDaemon if necessary.	XMS
370039	WARNING	%s %d: xmsTrigger(%d) WARNING: Error detaching from smsStatsDaemon shm. %d (%z)	A problem has occurred attempting to detach the shared memory segment used by the smsStatsDaemon.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370040	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsSvcLibrary: size of SSubmit in IDP (%d)differs from expected size (%d)	The size of the binary SSubmit message contained in the InitialDP received by the service library differs from the expected size.	This almost always indicates that the versions of xmsSvcLibrary and xmsTrigger incompatible. Check for recent upgrades to either, and revert to compatible versions.	XMS
370041	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Config File ERROR : %z	Config file error	Correct and reload config file	XMS
370042	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Config File ERROR : exiting %z	Config file error	Correct and reload config file	XMS
370046	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to instantiate PluginInterfaceZZZ	Failed to instantiate plugin	Check the plugin config section in the config file. Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370047	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to load PluginZZZ	Failed to load the plugin	Ensure that the plugin library exists and is readable.	XMS
370048	ERROR	%s %d: xmsTrigger(%d) ERROR: Unknown value (%d) of SMSSubmit status report request.	An internal programming error has been detected.	Contact support.	XMS
370049	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attaching Plugin %s %d to PC %d	Adding plugin to list of Pcs	No action required.	XMS
370050	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempting Plugin Load %s %d (SSN %d)	Loading plugin for SSN	No action required.	XMS
370051	NOTICE	%s %d: xmsTrigger(%d) NOTICE: CDR logging turned off	CDR logging turned off	No action required.	XMS
370052	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: SECURE section hash is %d	New configuration loaded.	No action required.	XMS
370053	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: SECURE section validated	New configuration loaded.	No action required.	XMS
370054	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: failureReportingPeriod = %d	New configuration loaded.	No action required.	XMS
370055	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: loadReportingPeriod = %d	New configuration loaded.	No action required.	XMS
370056	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: maxSmsPerSecond = %d	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370057	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: stopRoutingOnPermanentFailure = %z	New configuration loaded.	No action required.	XMS
370058	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: stopRoutingOnTransientFailure = %z	New configuration loaded.	No action required.	XMS
370059	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: warnPeriodSeconds = %d	New configuration loaded.	No action required.	XMS
370060	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: warnSmsPerSecond = %d	New configuration loaded.	No action required.	XMS
370062	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Persistent Storage disabled	Persistent Storage disabled	No action required.	XMS
370063	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Persistent Storage enabled	Persistent Storage enabled	No action required.	XMS
370064	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Plugin %d is marked as disabled, skipping	New configuration loaded.	No action required.	XMS
370065	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Plugin %s %d	New configuration loaded.	No action required.	XMS
370066	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Plugin %s %d Reread config	Re-reading plugin config	No action required.	XMS
370068	WARNING	%s %d: xmsTrigger(%d) WARNING: CDR max number per file incorrect - maxno = %d	Config error - maxno in the cdr section must be > 0	Correct and reload config file	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370069	WARNING	%s %d: xmsTrigger(%d) WARNING: CDR number of expected files incorrect - no_files %d	Config error - num_files in the cdr section must be > 0	Correct and reload config file	XMS
370070	WARNING	%s %d: xmsTrigger(%d) WARNING: CDR number of expected leaves incorrect - num_files_leaf %d	Config error - num_files_leaf in the cdr section must be > 0	Correct and reload config file	XMS
370071	WARNING	%s %d: xmsTrigger(%d) WARNING: CDR time out incorrect - time_out = %d	Config error - time_out in the cdr section must be > 0	Correct and reload config file	XMS
370072	WARNING	%s %d: xmsTrigger(%d) WARNING: Invalid regular expression carriercode - %z	Config file contains an invalid expression.	Correct and reload config file	XMS
370073	WARNING	%s %d: xmsTrigger(%d) WARNING: Message destination not set in route list for prefix %s %d id %d	Config error - carriercode not set.	Correct and reload config file. Message destination must be MC or SME	XMS
370074	WARNING	%s %d: xmsTrigger(%d) WARNING: No CDR base filename specified	Config error - no filename in the cdr section	Correct and reload config file	XMS
370075	WARNING	%s %d: xmsTrigger(%d) WARNING: No CDR destdir specified	Config error - no destdir in the cdr section	Correct and reload config file	XMS
370076	WARNING	%s %d: xmsTrigger(%d) WARNING: No CDR tempdir specified	Config error - no tempdir in the cdr section	Correct and reload config file	XMS
370077	WARNING	%s %d: xmsTrigger(%d) WARNING: No plugin for id %d	Config error - route contains id for which no plugin can be found	Correct and reload config file. id in the route must be a valid plugin id	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370078	WARNING	%s %d: xmsTrigger(%d) WARNING: TCAP primitive for PC %d, SSN %d has no available plugin.	TCAP primitive could not be routed to a plugin	Check the plugin definitions in the config file for a matching SSN.	XMS
370082	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Could not initialize xmsTrigger	Did not start because of error during initialisation.	Check the error log for message indicating why the initialisation failed.	XMS
370085	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Config file CRITICAL: exiting %z	Config file error.	Correct and reload config file	XMS
370088	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Multiple SMS Failure: CONTACT SUPPORT. Your system is running beyond allowed limits and %d SMSs were throttled in the last reporting period (maximum rate allowed: %d/s)	Call rate above allowed limit.	Contact support.	XMS
370089	ERROR	%s %d: xmsTrigger(%d) ERROR: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal programming error.	Contact support.	XMS
370090	ERROR	%s %d: xmsTrigger(%d) ERROR: Cannot create context for TCAP primitive.	Resource allocation error.	Check memory usage, contact support.	XMS
370091	ERROR	%s %d: xmsTrigger(%d) ERROR: Cannot create transaction for TCAP primitive.	Couldnt create a new transaction.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370093	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: CONTACT SUPPORT: No valid secure sectionfound, using %d sms/second as max limit	Invalid configuration, no secure section.	Contact support.	XMS
370094	ERROR	%s %d: xmsTrigger(%d) ERROR: Could not stat %s %d: %z	CmnHashStore could not open a particular file.	Contact support.	XMS
370095	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to open CDR file %z	Failed to open CDR file	Check that the directory exists and is writable. Correct and reload config file.	XMS
370099	ERROR	%s %d: xmsTrigger(%d) ERROR: cmnDestroyHashtable: hashtable already destroyed	Internal state error.	Contact support.	XMS
370100	ERROR	%s %d: xmsTrigger(%d) ERROR: cmnHashStore: directory[%d] not open!	Filesystem error.	Check disk free space, contact support.	XMS
370101	ERROR	%s %d: xmsTrigger(%d) ERROR: cmnHashStore: failed to flush and close temporary file: %s %d: %z	Filesystem error.	Check disk free space, contact support.	XMS
370102	ERROR	%s %d: xmsTrigger(%d) ERROR: cmnHashStore: failed to make temporary file: %s %d: %z	Filesystem error.	Check disk free space, contact support.	XMS
370103	ERROR	%s %d: xmsTrigger(%d) ERROR: cmnHashStore: failed to rename depth file: %s %d: %z	Filesystem error.	Check disk free space, contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370104	ERROR	%s %d: xmsTrigger(%d) ERROR: cmnHashStore: store file exists but is corrupt: %z	Filesystem error.	Check disk free space, contact support.	XMS
370105	ERROR	%s %d: xmsTrigger(%d) ERROR: cmnPlugin: error loading library %s %d: %z	An error was found while loading some shared library.	Contact support.	XMS
370106	ERROR	%s %d: xmsTrigger(%d) ERROR: smsSetStats: Could not retrieve %s %d	The indicated statistics value could not be read. This typically indicates that the statistics value does not exist in the SMF_STATISTICS_DEFN table.	Check that SMF_STATISTICS_DEFN contains the indicated statistics value. Check for spelling errors. Restart the smsStatsDaemon if necessary.	XMS
370107	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTryRecordStats: Internal error updating %s %d	The indicated statistics value could not be written. This is a system error, not just a missing statistics entry problem.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370108	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTrySetStats: Internal error updating %s %d	The indicated statistics value could not be written. This is a system error, not just a missing statistics entry problem.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370109	ERROR	%s %d: xmsTrigger(%d) ERROR: smsTrySetStats: Internal error retrieving %s %d	The indicated statistics value could not be written. This is a system error, not just a missing statistics entry problem.	Check that the smsStatsDaemon is running without errors. If necessary, restart the smsStatsDaemon. Check that the system settings for shared memory and semaphores have been set to recommended levels.	XMS
370110	NOTICE	%s %d: xmsTrigger(%d) NOTICE: CDR logging turned on	CDR logging turned on	No action required.	XMS
370111	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: Initialised tracing subsystem	Tracing initialised	No action required.	XMS
370112	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: pollTime = %d	New configuration loaded.	No action required.	XMS
370117	WARNING	%s %d: xmsTrigger(%d) WARNING: Exception reloading config file: %s %d	Config error, probably caused by a plugin failing to load its configuration.	Check plugin configuration sections.	XMS
370118	WARNING	%s %d: xmsTrigger(%d) WARNING: Incorrect message destination %s %d in route list for prefix %s %d id %d	Config error - message destination	Correct and reload config file. Message destination must be MC or SME	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370119	WARNING	%s %d: xmsTrigger(%d) WARNING: Multiple SMS Failure Imminent: CONTACT SUPPORT. Your system is close to running beyond allowed limits (maximum rate allowed: %d/s, currently: %d/s)	Call rate above allowed limit.	Contact support.	XMS
370120	WARNING	%s %d: xmsTrigger(%d) WARNING: Received Unsupported EventType %s %d	Received a SLEE event that is not supported	Contact support.	XMS
370121	WARNING	%s %d: xmsTrigger(%d) WARNING: Retry CDR file open time out incorrect - time_out = %d	An invalid (i.e. Negative) timeout was configured.	Consult tech guide for a range of appropriate values.	XMS
370122	WARNING	%s %d: xmsTrigger(%d) WARNING: cmnPluginLookupFunction: Symbol %s %d Lookup Failed - %z	Couldnt find the function required to create a particular plugin instance.	Check plugin library name, contact support.	XMS
370123	WARNING	%s %d: xmsTrigger(%d) WARNING: cmnPluginReleaseHandle: released already-released plugin %z	Plugin unloaded twice in succession.	Contact support.	XMS
370124	WARNING	%s %d: xmsTrigger(%d) WARNING: deltaCounter: Failed to delta statistic %s %d	Failed to increment a statistic counter.	Contact support.	XMS
370125	WARNING	%s %d: xmsTrigger(%d) WARNING: getCounter: Failed to get value for statistic %s %d	Failed to look up a statistic counter.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370127	WARNING	%s %d: xmsTrigger(%d) WARNING: setCounter: Failed to set statistic %s %d	Failed to set statistic.	Contact support.	XMS
370128	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: %s %d: DONT TRY AND COPY ASPs THAT ARE NOT EMPTY!!	Internal error: non-empty ASPs cant be copied	Contact support; provide core file.	XMS
370129	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Error reading config for IP plugin (id %d) : %z	There is an error in the IP plugins section of the config file; the full text of the alarm should provide details.	Correct and reload config file.	XMS
370132	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: %s %d is not a valid response to %z	Protocol error.	Contact support; provide core file.	XMS
370133	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: %s %d not allowed in this state (%d)	Protocol error.	Contact support; provide core file.	XMS
370134	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: failed to send submit_multi request	Failed to send an SMPP submit_multi request to the SMSC.	Contact support.	XMS
370137	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: No route for short message addressed to %z	No route is specified in the config file for the destination address.	Correct and reload config file.	XMS
370138	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: not allowed in this state (%d)	Invalid message type received.	Contact support; provide core file.	XMS
370140	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: only submit_multi_resp allowed, got %z	Invalid message type received.	Contact support; provide core file.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370141	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: only submit_multi allowed, got %z	Invalid message type received.	Contact support; provide core file.	XMS
370142	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: received %s %d in response to %z	Received an SMPP response that doesnt match the request type.	Contact support.	XMS
370146	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: SMSSubmit not allowed in this state	Unexpected message received from MMX.	Contact support; provide core file.	XMS
370147	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: SMSSubmitResult not allowed in this state (%d)	Unexpected message received from MMX.	Contact support; provide core file.	XMS
370148	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: submit_multi_resp not allowed in this state (%d)	Protocol error.	Contact support; provide core file.	XMS
370149	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: unable to send response to transaction	Internal communication error.	Contact support.	XMS
370151	ERROR	%s %d: xmsTrigger(%d) ERROR: Bind message is not a bind message, its a %z	Protocol error.	Contact support.	XMS
370152	ERROR	%s %d: xmsTrigger(%d) ERROR: Connection attempt to %s %d failed : %z	External communication error.	Contact support.	XMS
370153	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt accept incomming connection %z	Failed to accept incoming connection on socket.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370155	ERROR	%s %d: xmsTrigger(%d) ERROR: EMI transaction using other transactions window	Invalid internal state.	Contact support.	XMS
370157	ERROR	%s %d: xmsTrigger(%d) ERROR: Error in RoutingPrefix configuration %z	There is an error in the config.RoutingPrefixes subsection of the IP plugins section of the config file; the full text of the alarm should provide details.	Correct and reload config file.	XMS
370158	ERROR	%s %d: xmsTrigger(%d) ERROR: Error reading aspLogins section of config file for ASP %s %d : %z	Configuration file error.	Correct and reload config file.	XMS
370159	ERROR	%s %d: xmsTrigger(%d) ERROR: Error reading smscLogins section of config file for ASP %s %d : %z	Configuration file error.	Correct and reload config file.	XMS
370162	ERROR	%s %d: xmsTrigger(%d) ERROR: MsgDeliverSMResp to original message type %d	Invalid operation detected.	Contact support.	XMS
370164	ERROR	%s %d: xmsTrigger(%d) ERROR: Number rule missing to convert %s %d (%d) %z to emi format. Sending in denormalised form.	No matching number rule specified in the config.emiDefaults.number Rules subsection of the IP plugins section of the config file.	Correct and reload config file.	XMS
370169	ERROR	%s %d: xmsTrigger(%d) ERROR: Received unexpected session management result from SMSC login (%s %d) : %z	Protocol error, internal state error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370170	ERROR	%s %d: xmsTrigger(%d) ERROR: Requested SMSC protocol not supported	Only SMPP and EMI protocols are supported by MessageMax.	Contact support.	XMS
370174	ERROR	%s %d: xmsTrigger(%d) ERROR: SMSSubmitResult from MMX has not been initialised.	Logic error.	Contact support.	XMS
370175	ERROR	%s %d: xmsTrigger(%d) ERROR: TLV of type %s %d with invalid length specifier, is %d, should be %d. Decoding as octet string.	Message decoding error.	Contact support.	XMS
370177	ERROR	%s %d: xmsTrigger(%d) ERROR: xms::smpp::sendRequestMessage: invalid message type: %z	Logic error.	Contact support.	XMS
370178	ERROR	%s %d: xmsTrigger(%d) ERROR: xms::smpp::sendRequestMessage: trying to send message to NULL protocol handler	Logic error.	Contact support.	XMS
370179	ERROR	%s %d: xmsTrigger(%d) ERROR: xms::smpp::sendResponseMessage: invalid message type: %z	Logic error.	Contact support.	XMS
370180	ERROR	%s %d: xmsTrigger(%d) ERROR: xms::smpp::sendResponseMessage: trying to send message to NULL protocol handler	Logic error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370181	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Asked to generate a MultipleAddressCallInput from %d message (%s %d) addr %z	Logic error.	Contact support.	XMS
370185	NOTICE	%s %d: xmsTrigger(%d) NOTICE: ASP %s %d logged in successfully	Successful connection procedure.	No action required.	XMS
370186	NOTICE	%s %d: xmsTrigger(%d) NOTICE: ASP %s %d smsc side connection id=%s %d : rejected %d operations due to load limiting in last %d seconds	System overloaded.	No action required.	XMS
370187	NOTICE	%s %d: xmsTrigger(%d) NOTICE: ASP ptx:%d prx:%d ltx:%d lrx:%d SMSC ptx:%d prx:%d ltx:%d lrx:%d	ptx/prx = pending Tx/Rx logins; ltx/lrx = logged in Tx/Rx logins.	No action required.	XMS
370188	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempt to send a submitMulti to an ASP! (%s %d) addr %z	Invalid internal state; logic error.	Contact support.	XMS
370189	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempt to send a submitMulti with distribution list (%s %d) addr %z	Distribution list is not supported by MMX.	Contact support.	XMS
370190	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempt to send illegal submitMulti response (%s %d) addr %z	Invalid internal state; logic error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370191	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempt to submitMulti response to operation %d (%s %d) addr %z	Invalid internal state; logic error.	Contact support.	XMS
370195	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Delivery notification received with wrong message type (%s %d) addr %z	Only Message Type 3 (alphanumeric) supported for delivery notifications.	Contact support.	XMS
370196	NOTICE	%s %d: xmsTrigger(%d) NOTICE: EMI Received %d message on used transaction number (%d) asp id=%s %d (%s %d side) connection id=%z	Invalid internal state; logic error.	Contact support.	XMS
370197	NOTICE	%s %d: xmsTrigger(%d) NOTICE: EMI Received excess windowed messages (expectmax of %d) from %s %d login (%s %d) : %z	Window is full of unprocessed messages.	Contact support.	XMS
370198	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Fatal error detected on connection %s %d.	Error detected, description supplied.	Contact support.	XMS
370205	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Multiple address call input request received that could not be encoded into MT=3 (%s %d) addr %z	Encoding error detected.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370209	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received operation of type %d from unknown ASP (%s %d:%d from %s %d:%d) when waiting for session management open operation: %z	Invalid network operation detected.	Contact support.	XMS
370210	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received unexpected operation of type %d from ASP login (%s %d) : %z	Protocol error.	Contact support.	XMS
370211	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received unexpected operation of type %d from SMSC login (%s %d) : %z	Protocol error.	Contact support.	XMS
370212	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received unexpected response of type %d from %s %d login (%s %d) : %z	Protocol error.	Contact support.	XMS
370213	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Sending Multiple address call input with discarded message class (%s %d) addr %z	Internal inconsistency detected.	No action required.	XMS
370214	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Sending Multiple address call input with discarded user data header (%s %d) addr %z	Internal inconsistency detected.	No action required.	XMS
370216	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Session timeout ASP login (%s %d) addr %z	ASP session timed out.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370218	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: address %s %d was not in outgoing message	Received an address in an SMPP submit_multi_response that doesn't match any of the addresses in the corresponding submit_multi invoke message.	Contact support.	XMS
370222	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: I was sent a delivery receipt confirmation with an error code that I will ignore	Unsupported feature encountered.	Contact support.	XMS
370225	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: Spurious response of type %s %d, sequence_number=%d, command_status=%s %d	Protocol error.	Contact support with a network trace.	XMS
370226	WARNING	%s %d: xmsTrigger(%d) WARNING: ASP %s %d %s %d side : failed to find route for short message addressed to %z	Failed to find an ASP/SMSC matching the destination address.	Correct and reload config file.	XMS
370227	WARNING	%s %d: xmsTrigger(%d) WARNING: ASP %s %d %s %d side : no route defined for short message addressed to %z	Failed to find an ASP/SMSC matching the destination address.	Correct and reload config file.	XMS
370228	WARNING	%s %d: xmsTrigger(%d) WARNING: ASP %s %d login failed	An ASP provided incorrect login details to MMX.	Check ASP login information in config file.	XMS
370229	WARNING	%s %d: xmsTrigger(%d) WARNING: ASP %s %d login failed. Reason code: %d	An ASP failed to log in to MMX.	Check MMX and ASP configuration or contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370230	WARNING	%s %d: xmsTrigger(%d) WARNING: ASPManager: No ASP called %s %d found	The ASP name is referenced, but not defined, in the IP plugin section of the config file.	Correct and reload config file.	XMS
370231	WARNING	%s %d: xmsTrigger(%d) WARNING: ASPManager: No SMSC called %s %d found	The SMSC name is referenced, but not defined, in the IP plugin section of the config file.	Correct and reload config file.	XMS
370232	WARNING	%s %d: xmsTrigger(%d) WARNING: Bind request failed with command_status = %s %d	SMPP bind operation failed.	No action required.	XMS
370233	WARNING	%s %d: xmsTrigger(%d) WARNING: Config file error while reading ACS release cause to SMPP command_status mapping. Basing command_status on resultCode instead	Parameter config.smppDefaults.acsReleaseCauseToSmppCommandStatus in the IP plugin section of the config file is missing or incorrect.	Correct and reload config file.	XMS
370234	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI global default configuration not found, using default defaults	Parameter config.emiDefaults in the IP plugin section of the config file is missing or incorrect.	Correct and reload config file.	XMS
370239	WARNING	%s %d: xmsTrigger(%d) WARNING: Exception reloading config file: %z	There was an error reloading the config file.	Ensure that file /IN/service_packages/eserv.config exists and is readable by the application raising the alarm.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370240	WARNING	%s %d: xmsTrigger(%d) WARNING: ProtocolHandler::ProtocolH andler: invalid SMPP version %s %d, setting to 0x34	Invalid SMPP version received (only 3.4 and 5.0 supported). Treating as version 3.4.	No action required.	XMS
370241	WARNING	%s %d: xmsTrigger(%d) WARNING: ProtocolHandler::setFilter : invalid SMPP version %s %d, setting to 0x34	Invalid SMPP version received (only 3.4 and 5.0 supported). Treating as version 3.4.	No action required.	XMS
370242	WARNING	%s %d: xmsTrigger(%d) WARNING: Received CallInputResult with bad transaction type	Protocol error.	Contact support.	XMS
370243	WARNING	%s %d: xmsTrigger(%d) WARNING: Received CallInputWithSSResult with bad transaction type	Protocol error.	Contact support.	XMS
370244	WARNING	%s %d: xmsTrigger(%d) WARNING: Received DeliveryNotificationResult with bad transaction type	Protocol error.	Contact support.	XMS
370245	WARNING	%s %d: xmsTrigger(%d) WARNING: Received DeliveryShortMessageResult with bad transaction type	Protocol error.	Contact support.	XMS
370246	WARNING	%s %d: xmsTrigger(%d) WARNING: Received generic_nack in response to bind request. command_status = %s %d	SMPP bind operation failed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370248	WARNING	%s %d: xmsTrigger(%d) WARNING: Received MSMessageTransferResult with bad transaction type	Protocol error.	Contact support.	XMS
370249	WARNING	%s %d: xmsTrigger(%d) WARNING: Received MultipleAddressCallInputRe sult with bad transaction type	Protocol error.	Contact support.	XMS
370252	WARNING	%s %d: xmsTrigger(%d) WARNING: Received SubmitShortMessageResult with bad transaction type	Protocol error.	Contact support.	XMS
370254	WARNING	%s %d: xmsTrigger(%d) WARNING: SMSC %s %d login failed. Reason code: %d	Failed to log in to SMSC.	Check SMSC login information in config file.	XMS
370255	WARNING	%s %d: xmsTrigger(%d) WARNING: xms::smpp::ProtocolHandler ::messageAvailable: %z	Received an invalid SMPP message.	No action required.	XMS
370274	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Couldnt extract SMS Address from SMSREQ Result.	The response from the HLR is somehow corrupt.	Contact support.	XMS
370277	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Invalid/unreadable IS41 SMSREQResult received.	We couldnt understand the response from the HLR.	Contact support.	XMS
370279	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Outgoing messages not allowed for plugin %d	Invalid configuration detected.	Either fix the MMX routing rules or change this plugins allowOutgoing option to true.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370282	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: smScPrefixes - default group id is %d	New configuration loaded.	No action required.	XMS
370283	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: smScSelect: %z	New configuration loaded.	No action required.	XMS
370284	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsSmScSelect: %z	New configuration loaded.	No action required.	XMS
370285	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsSmScSelect: smScPrefix %s %d -> smScGroupId %d	New configuration loaded.	No action required.	XMS
370286	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: Global Title = %s %d	New configuration loaded.	No action required.	XMS
370287	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: Pointcode = %d	New configuration loaded.	No action required.	XMS
370288	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: Subsystem Number = %d	New configuration loaded.	No action required.	XMS
370289	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: alarmMask = %s %d.	New configuration loaded.	No action required.	XMS
370290	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: allowIncoming = %s %d.	New configuration loaded.	No action required.	XMS
370291	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: allowOutgoing = %s %d.	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370292	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: defaultPermanentFailureCauseCode = %d.	New configuration loaded.	No action required.	XMS
370293	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: defaultReleaseCause = %d.	New configuration loaded.	No action required.	XMS
370294	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: defaultReleaseCausePermanent = %s %d.	New configuration loaded.	No action required.	XMS
370295	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: defaultTransientFailureCauseCode = %d.	New configuration loaded.	No action required.	XMS
370296	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: originatingTimeout = %d.	New configuration loaded.	No action required.	XMS
370297	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: outboundProtocol = %s %d.	New configuration loaded.	No action required.	XMS
370298	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: smdppTimeout = %d.	New configuration loaded.	No action required.	XMS
370299	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: smsreqTimeout = %d.	New configuration loaded.	No action required.	XMS
370300	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: tcapInterfaceServiceKey = %s %d.	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370323	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::encode Unknown Bit Mask %s %d.	CDMA bearer data encoding failed.	Contact support.	XMS
370325	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: Ending old dialog before sending SMSREQ.	Internal state error: a dialogue already exists on output side.	Contact support.	XMS
370326	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: Destination SCCP address contains neither GT nor PC.	The plugin could not create a TCAP address from the current configuration.	Check that you have a valid address configured for each SMSC.	XMS
370327	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: No SMSC found to send to.	There are no SMSCs configured for this scenario.	Check the IS41 plugins smscDetails configuration.	XMS
370328	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received IS41 Address parameter too long to fit into SMSsubmit.	An address parameter in some IS41 message is too long for us to store.	Contact support.	XMS
370329	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received SCCP address too long to fit into SMSsubmit message.	The GT of some SCCP address is too long to store in an SMSsubmit.	Contact support.	XMS
370331	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Unable to retrieve SMS_DestinationAddress, MIN or SMS_OriginalDestinationAdd ress from SMDPP.	Incoming SMDPP is missing information we need.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370341	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Config Error: Invalid SCCP address for SMSC %s %d.	An SMSC address is incorrectly specified.	Consult the tech guide and fix address format.	XMS
370343	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Couldnt extract TCAP component from SLEE event (state TerminatingLookup).	SLEE communication attempt failed.	Contact support.	XMS
370345	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - No incoming SMDPP available and not allowed to use SMSSubmit.	Invalid configuration detected.	This happens when you use different input and output plugin instances and the message has a type like %SME status report%, which has a restricted set of use cases.	XMS
370346	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - invalid callback(handleSMSSubmit) invoked in state TerminatingDelivery.	Internal state error.	Contact support.	XMS
370347	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - invalid callback(handleSMSSubmit) invoked in state TerminatingLookup.	Internal state error.	Contact support.	XMS
370352	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Originating transactions not allowed by plugin %d.	The current configuration does not allow this plugin to handle input messages.	Either reconfigure the input route or change the configuration so that this plugin may handle inbound messages.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370353	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Received TCAP_ABORT from HLR (state TerminatingLookup).	The HLR has aborted its dialog to us.	Contact support.	XMS
370357	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: SMS Failure: Failed to determine SCCP destination address for outgoing SMDPP message.	We failed to get the destination address, either from the HLR or from our configured SMSCs.	Check SMSC configuration, contact support.	XMS
370358	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: SMSREQ result must arrive in a TCAP_RESPONSE(TCAP_RESULT_LAST), not a %s %d.	Invalid response was received from HLR.	Contact support with a network trace.	XMS
370361	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: TCAP event received on unknown dialog (state TerminatingLookup).	Unexpected TCAP event received.	Contact support with a network trace.	XMS
370362	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Terminating side timed out while waiting for SMDPPResult (transaction %s %d, dialog %s %d) - aborting transaction.	No response was received from the destination SMSC.	Check destination availability, Contact support.	XMS
370367	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: allowAlternateDeliveryForWEMT = %z	New configuration loaded.	No action required.	XMS
370368	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41: allowFDAforWEMT = %z	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370370	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: Mismatched InvokeId in response (%d, expected %d, state TerminatingLookup).	Unexpected message received; InvokeID not what we expected. Possible network misconfiguration.	Contact support.	XMS
370371	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: %s %d received TCAP abort on originating MSCs dialog.	Received a TCAP Abort from the originating MSC.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS
370372	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: %s %d received unexpected TCAP component %d (op/err id %d) in response to MAP open.	Received an unexpected TCAP message.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS
370373	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: %s %d received unexpected TCAP primitive (%d).	Received an unexpected TCAP message.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS
370374	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Dialog %s %d closed unexpectedly. Aborting transaction	Communications error, leg aborted.	Contact support.	XMS
370375	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Failed to extract mandatory parameter locationInfo from MAP SendRoutingInfoForSM response message.	The SendRoutingInfoForSM response from the HLR is missing the locationInfo parameter.	Investigate the TCAP messages from the HLR; contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370376	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Failed to send MAP error %d to originating MSC.	Communications error, route failed.	Contact support.	XMS
370378	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: HLR requested fallback to unrecognised application context.	The MAP plugin didnt recognise the MAP application context the HLR requested.	Investigate the TCAP messages between MMX and the HLR; contact support.	XMS
370379	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: MSC requested fallback to unrecognised application context.	After attempting direct delivery to an MSC, the MSC requested fallback but the MAP plugin didnt recognise the MAP application context the MSC requested.	Investigate the TCAP messages between MMX and the MSC; contact support.	XMS
370380	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received IMSI with more than 16 digits.	Received an IMSI parameter longer than allowed by the MAP standard.	Investigate the network element that the message originated from; contact support.	XMS
370381	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received MAP v. %d TCAP BEGIN with no forwardSM component.	The MAP message received didnt contain a ForwardShortMessage component.	Investigate the network element that the message originated from; contact support.	XMS
370382	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received MAP v. %d TCAP CONTINUE with no forwardShortMessage component.	The MAP message received didnt contain a ForwardShortMessage component.	Investigate the network element that the message originated from; contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370383	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP U- ERROR with unknown invoke id %d in response to MAP open with invoke id: %d.	Received a TCAP error message unrelated to the invoke message.	Investigate the network element that the message originated from; contact support.	XMS
370384	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: SMSC requested fallback to unrecognised application context.	The MAP plugin didnt recognise the MAP application context the SMSC requested.	Investigate the TCAP messages between MMX and the SMSC; contact support.	XMS
370385	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Unable to get dialog to SLEE service key %s %d.	Resource allocation error, SLEE communication not possible.	Contact support.	XMS
370386	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d received ABORT from MMX.	MMX aborted call processing.	Refer to the xmsTrigger log for possible reasons that the call was aborted. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
370387	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d received TCAP ABORT from HLR.	The HLR responded to a MAP message with a TCAP ABORT.	Investigate the TCAP messages between MMX and the HLR; contact support. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370388	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d received TCAP ABORT from MSC.	After attempting direct delivery to an MSC, the MSC responded with a TCAP ABORT.	Investigate the TCAP messages between MMX and the MSC; contact support. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
370389	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d received TCAP ABORT from SMSC.	The SMSC responded to a MAP message with a TCAP ABORT.	Investigate the TCAP messages between MMX and the SMSC; contact support. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
370390	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d timed out while waiting for response from HLR.	The HLR didnt respond to the MAP message.	Investigate the TCAP messages between MMX and the HLR. If necessary, increase the MAP plugins mapTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
370391	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d timed out while waiting for response from MMX.	MMX took too long to deliver the short message.	Refer to the xmsTrigger log, and the ACS log if an ACS callplan was triggered), for possible failure reasons. If necessary, increase the MAP plugins originatingTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370392	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d timed out while waiting for response from MSC.	After attempting direct delivery to an MSC, the MSC didnt respond to the MAP message.	Investigate the TCAP messages between MMX and the MSC. If necessary, increase the MAP plugins mapTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
370393	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d timed out while waiting for response from SMSC.	The SMSC didnt respond to the MAP message.	Investigate the TCAP messages between MMX and the SMSC. If necessary, increase the MAP plugins mapTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
370394	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: %s %d timed out while waiting for segmented MAP message.	No response received after sending a response to a segmented MAP Open message.	Investigate the network element that the MAP Open message originated from. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
370395	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: No SMSC configured to match destination %z	No SMSC configured for the MAP plugin.	Correct and reload config file.	XMS
370396	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: %z	Should never happen; possibly indicates a bug in the software.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370397	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: %s %d failed to extract parameters from SRI4SM Response.	The SendRoutingInfoForSM response from the HLR contained invalid or missing parameters.	Investigate the TCAP message from the HLR; contact support.	XMS
370398	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: %s %d received invalid response from HLR (TCAP primitive %d).	Received an unexpected TCAP message.	Investigate the TCAP messages between MMX and the HLR; contact support.	XMS
370399	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Failed to extract sm-RP-DA (serviceCentreAddressDA), sm-RP-OA (msisdn) or sm- RP-UI from MAP v. %d forwardSM.	Received a MAP forwardShortMessage missing one of the compulsory parameters listed in the alarm text.	Investigate the network element that the message originated from; contact support.	XMS
370400	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: GT = %z	New configuration loaded.	No action required.	XMS
370401	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: PC = %d	New configuration loaded.	No action required.	XMS
370402	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: SSN = %d	New configuration loaded.	No action required.	XMS
370403	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: alarmMask = %d	New configuration loaded.	No action required.	XMS
370404	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: allowDirectDelivery = %z	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370405	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: allowIncoming = %z	New configuration loaded.	No action required.	XMS
370406	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: allowOutgoing = %z	New configuration loaded.	No action required.	XMS
370407	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: defaultMapVersionHlr = %d	New configuration loaded.	No action required.	XMS
370408	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: defaultMapVersionMsc = %d	New configuration loaded.	No action required.	XMS
370409	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: defaultMapVersionSmsc = %d	New configuration loaded.	No action required.	XMS
370410	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: defaultPermanentFailureError Code = %d	New configuration loaded.	No action required.	XMS
370411	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: defaultTransientFailureError Code = %d	New configuration loaded.	No action required.	XMS
370412	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: forwardSmErrorMap = %z	New configuration loaded.	No action required.	XMS
370413	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: hlrErrorMap = %z	New configuration loaded.	No action required.	XMS
370414	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: honourReplyPath = %z	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370415	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: hybridiseMapVersions = %z	New configuration loaded.	No action required.	XMS
370416	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: mapTimeout = %d	New configuration loaded.	No action required.	XMS
370417	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: maxUnsegmentedLength = %d	New configuration loaded.	No action required.	XMS
370418	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: mscVersionCacheSize = %d	New configuration loaded.	No action required.	XMS
370419	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: originatingTimeout = %d	New configuration loaded.	No action required.	XMS
370420	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: overrideServiceCentreAddressToHlr = %z	New configuration loaded.	No action required.	XMS
370421	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: releaseCauseMap = %z	New configuration loaded.	No action required.	XMS
370422	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: tcapInterfaceServiceKey = %s %d	New configuration loaded.	No action required.	XMS
370424	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Informational: MapTransaction not being made for context: %s %d , as xmsiMap is in state %z	Call attempted while plugin shutting down.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370426	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Period functionality indicator extension bit is not supported by MAP version 3.	The MAP enhanced Validity Period functionality indicator extension bit is reserved (should be 0) in the MAP v. 3 standard (GSM 03.40 v7.5.0), yet a message was received with this bit set.	Contact support.	XMS
370427	WARNING	%s %d: xmsTrigger(%d) WARNING: deltaCounter: Failed to delta statistic Mmx_Service.<Statistic ID>.[Statistic Info]	An error occurred attempting to apply a delta to the specified statistic.	* Ensure the statistic in question is appropriately registered in the statistics subsystem database. * Ensure that both the smsStatsDaemon and replication subsystem are operating correctly. * Ensure the global statistics shared memory table is not full. * Contact support.	XMS
370428	WARNING	%s %d: xmsTrigger(%d) WARNING: getCounter: Failed to get value for statistic Mmx_Service.<Statistic ID>.[Statistic Info]	An error occurred attempting to read the value of the specified statistic.	* Ensure the statistic in question is appropriately registered in the statistics subsystem database. * Ensure that both the smsStatsDaemon and replication subsystem are operating correctly. * Ensure the global statistics shared memory table is not full. * Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370429	WARNING	%s %d: xmsTrigger(%d) WARNING: setCounter: Failed to set statistic Mmx_Service.<Statistic ID>.[Statistic Info]	An error occurred attempting to set the value of the specified statistic.	* Ensure the statistic in question is appropriately registered in the statistics subsystem database. * Ensure that both the smsStatsDaemon and replication subsystem are operating correctly. * Ensure the global statistics shared memory table is not full. * Contact support.	XMS
370433	ERROR	%s %d: xmsTrigger(%d) ERROR: Malformed SMSSubmitResult received (%s %d).	Corrupt message from remote trigger app.	Contact support.	XMS
370435	NOTICE	%s %d: xmsTrigger(%d) NOTICE: xmsiWrapper(%s %d) not creating WrapperTransaction for context: %z	Plugin is not in a running state.	No action required.	XMS
370444	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::tcapBe gin - Malformed SMSSubmit received (%s %d).	The SMSSubmit we received is not valid.	Contact support.	XMS
370449	ERROR	%s %d: xmsTrigger(%d) ERROR: Configuration error: ASP login %s %d overlaps ASP login %s %d, from a different ASP, ambiguous login possible.	Login configuration error.	Fix and reload config file.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370450	ERROR	%s %d: xmsTrigger(%d) ERROR: Plugin construction exception: Configuration error: ASP login %s %d overlaps ASP login %s %d, from a different ASP, ambiguous login possible.	Login configuration error.	Fix and reload config file.	XMS
370451	ERROR	%s %d: xmsTrigger(%d) WARNING: ASP %s %d has a duplicate/overlapping source address	Address configuration error.	Fix and reload config file.	XMS
370452	ERROR	%s %d: xmsTrigger(%d) ERROR: Plugin construction exception: Could not bind to %d.%d.%d.%d:%d	Protocol error.	Contact support.	XMS
370453	WARNING	%s %d: xmsTrigger(%d) WARNING: Rejected connection from unknown ASP from IP:%d.%d.%d.%d:%d to IP:%d.%d.%d.%d:%d	Protocol error.	Contact support.	XMS
370454	WARNING	%s %d: xmsTrigger(%d) WARNING: SMSC %s %d login failed. Reason code: %d - Socket error	Communications error.	Contact support.	XMS
370455	WARNING	%s %d: xmsTrigger(%d) WARNING: acs_cause_to_result cause=%d, result=%d already (pre)defined as cause=%d, result=%d - ignoring new defintion	Information only.	No action required.	XMS
370456	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Bad address type %s %d, should be itu or ansi.	Address configuration error.	Fix and reload config file.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370457	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Cant send NULL SLEE event.	Internal communication error, should never happen. Resource allocation failed upstream.	Contact support.	XMS
370458	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Cant send event, TCAP dialogue is NULL.	Resource allocation error, SLEE communication not possible.	Contact support.	XMS
370459	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Couldnt create TCAP dialogue.	Resource allocation error, SLEE communication not possible.	Contact support.	XMS
370460	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Mandatory config item %s %d.tcapDestAddr.SSN not found	Config error: missing mandatory option.	Consult tech guide for list of mandatory fields.	XMS
370461	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Out of memory, giving up	Resource allocation error.	Contact support.	XMS
370462	ERROR	SLEE[%d]: slee_acs(%d) ERROR: SendShortMessageNode::init : Failed to get xmsiWrapper SLEE interface handle %s %d	Misconfiguration detected.	Please check that you have a valid SLEE interface name configured.	XMS
370463	ERROR	SLEE[%d]: slee_acs(%d) ERROR: SendShortMessageNode::process: Failed to create Tcap SLEE event, probably out of memory	Resource allocation error.	Contact support.	XMS
370464	ERROR	SLEE[%d]: slee_acs(%d) ERROR: SetTarrifCode failed.	Failed to set tariff code.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370465	ERROR	SLEE[%d]: slee_acs(%d) ERROR: TXTB: Compile Pattern error %s %d (%d) on pattern %s %d, node %d	Regular expression error detected.	Consult tech guide for regular expression documentation.	XMS
370466	ERROR	SLEE[%d]: slee_acs(%d) ERROR: TXTB: Null nodePtr, nodeID = %d	Internal error, invalid node pointer.	Contact support.	XMS
370467	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Unexpected BCSM code %d	Unexpected communication event or parameter.	Contact support.	XMS
370468	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Unexpected MOX charging error code %d	Unexpected communication event or parameter.	Contact support.	XMS
370469	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Unexpected MOX message type after ReserveUnitReq %d	Unexpected communication event or parameter.	Contact support.	XMS
370470	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Unexpected release cause %d	Unexpected communication event or parameter.	Contact support.	XMS
370471	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Unexpected release cause %d on disconnect	Unexpected communication event or parameter.	Contact support.	XMS
370472	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Unexpected reservation action %d	Unexpected communication event or parameter.	Contact support.	XMS
370473	ERROR	SLEE[%d]: slee_acs(%d) ERROR: Unexpected response to attempt terminate: Action Type: %d, Response Type: %d	Unexpected communication event or parameter.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370474	ERROR	SLEE[%d]: slee_acs(%d) ERROR: pack8bitToGsm7bit: UDL %d (offsetBits %d) too large for dst size %d	Text encoding/decoding error.	Contact support.	XMS
370475	ERROR	SLEE[%d]: slee_acs(%d) ERROR: stripGSMUDHeader: Header Len > UDL, implies malformed GSM User Data.	Text encoding/decoding error.	Contact support.	XMS
370476	ERROR	SLEE[%d]: slee_acs(%d) ERROR: unpackGsm7bitTo8bit: UDL %d (offsetBits %d) too large for src size %d	Text encoding/decoding error.	Contact support.	XMS
370477	ERROR	SLEE[%d]: slee_acs(%d) ERROR: xlate7bitToGsm7bit: UDL %d (offsetBits %d) too large for dst size %d	Text encoding/decoding error.	Contact support.	XMS
370478	ERROR	SLEE[%d]: slee_acs(%d) ERROR: xlateGsm7bitToHigh7bit: UDL %d (offsetBits %d) too large for dst size %d	Text encoding/decoding error.	Contact support.	XMS
370479	ERROR	SLEE[%d]: slee_acs(%d) ERROR: xlateGsm7bitToHigh7bit: UDL %d (offsetBits %d) too large for src size %d	Text encoding/decoding error.	Contact support.	XMS
370480	ERROR	SLEE[%d]: slee_acs(%d) ERROR: xlateHigh7bitToGsm7bit: UDL %d (offsetBits %d) too large for src size %d	Text encoding/decoding error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370481	ERROR	SLEE[%d]: slee_acs(%d) ERROR: xms::SendShortMessageNode macro node: Config file error. Reason: %z	Configuration error detected.	Consult tech guide for a range of appropriate values.	XMS
370482	WARNING	SLEE[%d]: slee_acs(%d) WARNING: BillWhenAtHandset is true, but Trigger App reported delivery to SMSC	Logic error.	Check configuration, consult tech guide.	XMS
370483	WARNING	SLEE[%d]: slee_acs(%d) WARNING: TcapUtils::sendTcapEvent failed - SLEE exception caught.	Internal communication error, should never happen.	Contact support; provide core file.	XMS
370484	WARNING	SLEE[%d]: slee_acs(%d) WARNING: TcapUtils::sendTcapEvent(s tatic) failed - SLEE exception caught.	Internal communication error, should never happen.	Contact support; provide core file.	XMS
370485	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Fatal error detected on connection remote IP:%s %d local IP:%s %d	Cannot connect to remote ASP.	Refer to network expert. Verify network integrity. Check ASP reconnects.	XMS
370486	NOTICE	%s %d: xmsTrigger(%d) NOTICE: .+ASP ptx:%d prx:%d ltx:%d lrx:%d SMSC ptx:%d prx:%d ltx:%d lrx:%d	Information only.	None required.	XMS
370487	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Session timeout ASP login (not logged in) addr IP:%s %d	Cannot connect to remote ASP.	Refer to network expert. Verify network integrity. Check ASP reconnects.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370488	WARNING	%s %d: xmsTrigger(%d) WARNING: ASP %s %d login failed. Reason code: 3 - Socket error	Cannot connect to remote ASP.	Refer to network expert. Verify network integrity. Check ASP reconnects.	XMS
370489	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Logging out removed SMSC %s %d	Dropped connection with remote SMSC.	Refer to network expert. Verify network integrity. Check ASP reconnects.	XMS
370490	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received operation of type %d from unknown ASP (inet %s %d from inet %s %d) when waiting for session management open operation:%z	Received event from unknown ASP.	None required.	XMS
370491	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Decode parameter error Bad parameter : Bad parameter length #%d in received messageZZZ	Internal error.	None required.	XMS
370492	NOTICE	xmsTrigger: xmsTrigger(%d) NOTICE: Login attempt to SMSC failed with error code %d text Session not accepted, number of sessions exceeded	Too many outstanding connections to SMSC.	Refer to application expert. Verify all connections are valid.	XMS
370493	WARNING	xmsTrigger: xmsTrigger(%d) WARNING: SMSC %s %d login failed. Reason code: %d - Authentication failure	Failed login attempt to SMSC.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370494	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL SleeException=%d sleeError.cc@d: SleeException: Interface instance does not exist (%d) in sleeInterfaceAPI.cc at %d by process id %d	Lost communication with the SLEE.	Refer to application expert. Verify all interfaces are running that are specified in SLEE.cfg	XMS
370495	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Reload config failed. Error number is Too many open files	Cannot reload configuration.	Refer to application expert. Restart xmsTrigger if necessary.	XMS
370496	ERROR	%s %d: xmsTrigger(%d) ERROR: Plugin construction exception: Duplicate ASP %s %d in config file	Invalid configuration.	Remove duplicate information.	XMS
370497	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: alwaysProduceNonDeliveryRe ceipt =%z	Information only.	No action required.	XMS
370498	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: earlyAckMC =%z	Information only.	No action required.	XMS
370499	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: earlyAckSME =%z	Information only.	No action required.	XMS
370500	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Login attempt to SMSC failed with error code %d textZZZ	Connection to SMSC failed.	Refer to full alarm string for reason.	XMS
370501	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Persistent Storage not available in this version.	Information only.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
370502	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Plugin (%s %d) lib=xmsiIP.so id=%d,SSN=%d, earlyAckMC=%s %d, earlyAckSME=%s %d, alwaysProduceNonDeliveryRe ceipt=%s %d, state=STARTED	Information only.	No action required.	XMS
370503	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Plugin Count =%z	Information only.	No action required.	XMS
370504	WARNING	%s %d: xmsTrigger(%d) WARNING: ASP %s %d login failed. Reason code: %d - Unknown	Login to ASP failed for an unknown reason.	Refer to application expert. Check ASP configuration.	XMS
370505	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Decode format error Bad message : Bad checksum in received messageZZZ	The checksum indicates that the received message has corrupted between being generated and being received	Contact support if alarm persists.	XMS
370506	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Decode parameter error Bad parameter : Bad parameter (not numeric) %s %d in received messageZZZ	Parameter is not of expected type as specified incorrectly	Confirm specified parameter is of valid type	XMS
370507	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Fatal error detected on connection remote IP:%d.%d.%d.%d:%d local unspecified.	Network communication failure or remote communication process failure	Check login information in config file. Check remote node is running.	XMS
370508	WARNING	%s %d: xmsTrigger(%d) WARNING: SMSC %s %d login failed. Reason code: %d - Couldnt connect	Failed to log in to SMSC.	Check SMSC login information in config file.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371001	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: CONTACT SUPPORT: maxConcurrentTransactions is 0 in secure section.	The secure section of config file has a maxConcurrentTransactions value of 0, which is invalid.	Contact support.	XMS
371002	ERROR	%s %d: slee_acs(%d) ERROR: %s %d(): Invalid tzType %s %d. Not changing timezone.	Timezone from call plan cant be understood.	Recompile call-plan. If problem persists	XMS
371003	ERROR	%s %d: slee_acs(%d) ERROR: ADPB node data formatted incorrectly - aborting	Internal error has occurred.	Contact support.	XMS
371004	ERROR	%s %d: slee_acs(%d) ERROR: ADPB:HandleIRResponse: message not of type ReserveUnitErr - aborting	Message sequence error.	Contact support.	XMS
371005	ERROR	%s %d: slee_acs(%d) ERROR: ADPB:HandleIRResponse: message not of type ReserveUnitRes - aborting	Message sequence error.	Contact support.	XMS
371006	ERROR	%s %d: slee_acs(%d) ERROR: ADPB:HandleIRResponse: req not of type ReserveUnitReq - aborting	Message sequence error.	Contact support.	XMS
371007	ERROR	%s %d: slee_acs(%d) ERROR: Bad address type %s %d, should be itu or ansi.	Address configuration error.	Fix and reload config file	XMS
371008	ERROR	%s %d: slee_acs(%d) ERROR: BOD: Compile Pattern error %s %d (%d) on pattern %s %d, node %d	Invalid regular expression in node configuration.	Update node in call plan.	XMS
371009	ERROR	%s %d: slee_acs(%d) ERROR: Cant send event, TCAP dialogue is NULL.	Resource allocation error, SLEE communication not possible.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371010	ERROR	%s %d: slee_acs(%d) ERROR: Cant send NULL SLEE event.	Internal communication error	should never happen. Resource allocation failed upstream.	XMS
371011	ERROR	%s %d: slee_acs(%d) ERROR: Compile Pattern error %s %d (%d) on pattern %s %d, node %d	Regular expression error detected.	Consult tech guide for regular expression documentation.	XMS
371012	ERROR	%s %d: slee_acs(%d) ERROR: Couldnt create TCAP dialogue.	Resource allocation error	SLEE communication not possible.	XMS
371013	ERROR	%s %d: slee_acs(%d) ERROR: Invalid user data header: UDHI=1, UDL=%d, UDHL=%d, A-party=%s %d, B-party=%s %d	Error decoding short message	Contact support.	XMS
371014	ERROR	%s %d: slee_acs(%d) ERROR: Mandatory config item %s %d.tcapDestAddr.SSN not found	Config error: missing mandatory option.	Consult tech guide for list of mandatory fields.	XMS
371015	ERROR	%s %d: slee_acs(%d) ERROR: Out of memory, giving up	Resource allocation error.	Contact support.	XMS
371016	ERROR	%s %d: slee_acs(%d) ERROR: pack8bitToGsm7bit: UDL %d (offsetBits %d) too large for dst size %d	Text encoding/decoding error.	Contact support.	XMS
371017	ERROR	%s %d: slee_acs(%d) ERROR: SendShortMessageNode::init : Failed to get xmsiWrapper SLEE interface handle %s %d	Misconfiguration detected.	Please check that you have a valid SLEE interface name configured.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371018	ERROR	%s %d: slee_acs(%d) ERROR: SendShortMessageNode::process: Failed to create Tcap SLEE event, probably out of memory	Resource allocation error.	Contact support.	XMS
371019	ERROR	%s %d: slee_acs(%d) ERROR: SetTarrifCode failed.	Failed to set tariff code.	Contact support.	XMS
371021	ERROR	%s %d: slee_acs(%d) ERROR: SSMN: Empty destination address.	A destination address of type Fixed Number was selected but the number value was left blank.	Enter the destination number digits in the macro node GUI.	XMS
371022	ERROR	%s %d: slee_acs(%d) ERROR: SSMN: Failed to send message %d to destination %s %d	The SSMN node couldnt send the SMS to xmsTrigger.	Check node configuration in config file	XMS
371023	ERROR	%s %d: slee_acs(%d) ERROR: SSMN: Invalid macro node state %d	Internal error has occurred.	If problem persists	XMS
371027	ERROR	%s %d: slee_acs(%d) ERROR: TXTB/TXTR: Null nodePtr, nodeID = %d	Internal error, invalid node pointer.	Contact support.	XMS
371028	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected BCSM code %d	Unexpected communication event or parameter.	Contact support.	XMS
371029	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected MOX charging error code %d	Unexpected communication event or parameter.	Contact support.	XMS
371030	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected MOX message type after ReserveUnitReq %d	Unexpected communication event or parameter.	Contact support.	XMS
371031	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected release cause %d	Unexpected communication event or parameter.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371032	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected release cause %d on disconnect	Unexpected communication event or parameter.	Contact support.	XMS
371033	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected reservation action %d	Unexpected communication event or parameter.	Contact support.	XMS
371034	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected response to attempt terminate: Action Type: %d, Response Type: %d	Unexpected communication event or parameter.	Contact support.	XMS
371035	ERROR	%s %d: slee_acs(%d) ERROR: unpackGsm7bitTo8bit: UDL %d (offsetBits %d) too large for src size %d	Text encoding/decoding error.	Contact support.	XMS
371036	ERROR	%s %d: slee_acs(%d) ERROR: xlateGsm7bitToHigh7bit: UDL %d (offsetBits %d) too large for dst size %d	Text encoding/decoding error.	Contact support.	XMS
371037	ERROR	%s %d: slee_acs(%d) ERROR: xlateGsm7bitToHigh7bit: UDL %d (offsetBits %d) too large for src size %d	Text encoding/decoding error.	Contact support.	XMS
371038	ERROR	%s %d: slee_acs(%d) ERROR: xlateHigh7bitToGsm7bit: UDL %d (offsetBits %d) too large for dst size %d	Text encoding/decoding error.	Contact support.	XMS
371039	ERROR	%s %d: slee_acs(%d) ERROR: xlateHigh7bitToGsm7bit: UDL %d (offsetBits %d) too large for src size %d	Text encoding/decoding error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371040	ERROR	%s %d: slee_acs(%d) ERROR: xms::ADPB macro node: Config file error. Reason: %s %d	Configuration error detected.	Consult Technical Guide for a range of appropriate values.	XMS
371041	ERROR	%s %d: slee_acs(%d) ERROR: xms::SendShortMessageNode macro node: Config file error. Reason: %s %d	Configuration error detected.	Consult tech guide for a range of appropriate values.	XMS
371042	WARNING	%s %d: slee_acs(%d) WARNING: BillWhenAtHandset is true, but Trigger App reported delivery to SMSC	Logic error.	Check configuration, consult tech guide.	XMS
371043	WARNING	%s %d: slee_acs(%d) WARNING: Received NULL response from BE Client.	Communications error.	Contact support if problem persists.	XMS
371045	WARNING	%s %d: slee_acs(%d) WARNING: TcapUtils::sendTcapEvent failed - SLEE exception caught.	Internal communication error	should never happen.	XMS
371046	WARNING	%s %d: slee_acs(%d) WARNING: TcapUtils::sendTcapEvent(s tatic) failed - SLEE exception caught.	Internal communication error	should never happen.	XMS
371047	ERROR	%s %d: xmsTrigger(%d) ERROR: Invalid user data header: UDHI=1, UDL=%d, UDHL=%d, A-party=%s %d, B-party=%s %d	Invalid incoming message.	Contact support.	XMS
371048	ERROR	%s %d: xmsTrigger(%d) ERROR: Not using invalid call plan name %s %d	Internal communications error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371049	ERROR	%s %d: xmsTrigger(%d) ERROR: pack8bitToGsm7bit: UDL %d (offsetBits %d) too large for dst size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS
371050	ERROR	%s %d: xmsTrigger(%d) ERROR: Too many bytes (%d) in ASN1 extension field, max is %d	Internal error has occurred.	Contact support.	XMS
371051	ERROR	%s %d: xmsTrigger(%d) ERROR: unpackGsm7bitTo8bit: UDL %d (offsetBits %d) too large for src size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS , or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371052	ERROR	%s %d: xmsTrigger(%d) ERROR: xlateGsm7bitToHigh7bit: UDL %d (offsetBits %d) too large for dst size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS
371053	ERROR	%s %d: xmsTrigger(%d) ERROR: xlateGsm7bitToHigh7bit: UDL %d (offsetBits %d) too large for src size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371054	ERROR	%s %d: xmsTrigger(%d) ERROR: xlateHigh7bitToGsm7bit: UDL %d (offsetBits %d) too large for dst size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS
371055	ERROR	%s %d: xmsTrigger(%d) ERROR: xlateHigh7bitToGsm7bit: UDL %d (offsetBits %d) too large for src size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS
371062	NOTICE	%s %d: xmsTrigger(%d) NOTICE: xmsSvcLibrary Config: flushTime = %d	The flush time for caching call plans used in number-based call plan selection has been configured to the indicated value.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371063	NOTICE	%s %d: xmsTrigger(%d) NOTICE: xmsSvcLibrary Config: maxAge = %d	The max age for caching call plans used in number-based call plan selection has been configured to the indicated value.	No action required.	XMS
371064	NOTICE	%s %d: xmsTrigger(%d) NOTICE: xmsSvcLibrary Config: validityTime = %d	The validity time for caching call plans used in number-based call plan selection has been configured to the indicated value.	No action required.	XMS
371068	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsSvcLibrary: SMS_Deliver - No CP for DN %s %d	There is no Call Plan configured for the given Dialed Number.	Configure a call plan in the Service Number tab of the Numbers ACS screen.	XMS
371069	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsSvcLibrary: SMS_Submit - No CP for CLI %s %d	There is no Call Plan configured for the given Calling Line Indicator (calling number)..	Configure a call plan in the CLI Numbers tab of the Numbers ACS screen.	XMS
371070	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsSvcLibrary: XMS Named - No CP named %s %d - from SLEE service name	The call plan of the name indicated by xmsTrigger can not be found.	This almost always indicates a mis-configuration. Check the configured slee service names, and compare with the active call plans in the ACS database.	XMS
371071	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsSvcLibrary: XMS Named - No CP named %s %d - from XMS	The call plan of the name indicated by xmsTrigger can not be found.	This almost always indicates a mis-configuration. Check the configured service names in XMS, and compare with the active call plans in the ACS database.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371072	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Config File ERROR : exiting %s %d	Config file error	Correct and reload config file	XMS
371073	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Config file ERROR: exiting %s %d	Config file error.	Correct and reload config file	XMS
371074	ERROR	%s %d: xmsTrigger(%d) ERROR: Config file reload failed: %s %d - keeping existing config	Config file error.	Correct and reload config file	XMS
371075	ERROR	%s %d: xmsTrigger(%d) ERROR: Routing scheme reload failed: %s %d - keeping existing config	Database configuration error.	Correct and reload database configuration	XMS
371076	ERROR	%s %d: xmsTrigger(%d) ERROR: Error loading from database: %s %d - retaining existing Routing Scheme	Failure re-loading new configuration from the database.	Check that the database is up, if so contact support.	XMS
371077	NOTICE	%s %d: xmsTrigger(%d) Config: CDR max number per file incorrect - maxno = %d	Config error maxno in the cdr section must be > 0	Correct and reload config file	XMS
371078	NOTICE	%s %d: xmsTrigger(%d) Config: CDR number of expected files incorrect - no_files %d	Config error num_files in the cdr section must be > 0	Correct and reload config file	XMS
371079	NOTICE	%s %d: xmsTrigger(%d) Config: CDR number of expected leaves incorrect - num_files_leaf %d	Config error num_files_leaf in the cdr section must be > 0	Correct and reload config file	XMS
371080	NOTICE	%s %d: xmsTrigger(%d) Config: CDR time out incorrect - time_out = %d	Config error time_out in the cdr section must be > 0	Correct and reload config file	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371081	NOTICE	%s %d: xmsTrigger(%d) Config: No CDR base filename specified	Config error no filename in the cdr section	Correct and reload config file	XMS
371082	NOTICE	%s %d: xmsTrigger(%d) Config: No CDR destdir specified	Config error no destdir in the cdr section	Correct and reload config file	XMS
371083	NOTICE	%s %d: xmsTrigger(%d) Config: No CDR tempdir specified	Config error no tempdir in the cdr section	Correct and reload config file	XMS
371084	NOTICE	%s %d: xmsTrigger(%d) Config: Retry CDR file open time out incorrect - time_out = %d	An invalid (i.e. Negative) timeout was configured.	Consult tech guide for a range of appropriate values.	XMS
371085	NOTICE	%s %d: xmsTrigger(%d) Config: Failed to instantiate PluginInterface in %s %d	Failed to instantiate plugin	Check the plugin config section in the config file. Contact support.	XMS
371086	NOTICE	%s %d: xmsTrigger(%d) Config: Couldnt connect to database, cant load configuration	Failed to connect to the database.	Make sure the database is running and the the user-name and password is correctly specified in config file.	XMS
371087	ERROR	%s %d: xmsTrigger(%d) ERROR: Adapter %s %d is defined in config file but not in the database	There is a mismatch between the adapters defined in config file and the adapters defined in the GUI. The system will ignore the extra adapter.	Add the adapter to the GUI config.	XMS
371088	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Could not initialise xmsTrigger	Did not start because of error during initialazation.	Check the error log for message indicating why the initialization failed.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371089	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Cannot get SLEE API handle.	Failed to obtain a handle into the SLEE	Contact support.	XMS
371090	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Cannot install SIGHUP signal handler - %s %d [%d].	Failed to install signal handler.	Contact support.	XMS
371091	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Caught a SLEE exception in main, exiting: %s %d	A serious error has occurred.	Contact support.	XMS
371092	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: config file nodeName %s %d is not configured in the database	The current MMX node is not configured in the database.	Using the screens configure the given node.	XMS
371093	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Failed to open XMS.xmsTrigger section in config file	Config error No xmsTrigger section	Correct and reload config file	XMS
371094	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Failed to start service - No ManagementEventType	Failed to obtain an event type from the SLEE.	Contact support.	XMS
371095	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Failed to start service - No SleeRIMSEventType	Internal error.	Contact support.	XMS
371096	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Failed to start service - No SleeTextEventType	Failed to obtain an event type from the SLEE.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371097	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Failed to start service - No TcapPrimitiveEventType	Failed to obtain an event type from the SLEE.	Contact support.	XMS
371098	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Fatal error loading from database: %s %d	Failed to load information from the database	Check database is running or contact support.	XMS
371099	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Reload config failed.	Failed to load or re-load the config file.	Check the error log for message indicating why the load failed and check the config file for errors.	XMS
371100	ERROR	%s %d: xmsTrigger(%d) ERROR: Cannot create transaction for TCAP primitive%s %d.	Internal error.	Contact support.	XMS
371101	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: CONTACT SUPPORT: No valid secure sectionfound, using %d concurrent transactions as max limit	The secure section of config file is missing or invalid.	Contact support.	XMS
371102	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt connect to database, cant load configuration	Failed to connect to the database.	Make sure the database is running and the the user-name and password is correctly specified in config file.	XMS
371103	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt find supposedly available handler for job queue	Internal error in the IP plugin	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371104	ERROR	%s %d: xmsTrigger(%d) ERROR: Default Message Centres Service Centre Address is not configured - currently set to %s %d	A message centre was configured with an invalid (i.e. empty) SCA.	Specify an SCA for the message centre in the screens	XMS
371105	ERROR	%s %d: xmsTrigger(%d) ERROR: Destination domain %s %d doesnt exist in routing scheme	The current message has been assigned a destination domain (via a call plan) that isnt configured.	Configure the domain in the screens, or change the call plan to specify a different domain name.	XMS
371107	ERROR	%s %d: xmsTrigger(%d) ERROR: Duplicate MMX_THROTTLING_RULE id %d, messageType %s %d, origAddressClassId %d, destAddressClassId %d	An erroneous duplicate throttling rule has been entered in the screens.	Remove the duplicate throttling rule in the screens.	XMS
371108	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to classify incoming path %s %d and destination address %s %d	There is no address rule configured for this combination of inbound path name (prefix) and address.	Configure a matching address rule.	XMS
371109	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to classify incoming path %s %d and originating address %s %d	There is no address rule configured for this combination of inbound path name (prefix) and address.	Configure a matching address rule.	XMS
371110	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to find Plugin Maker %s %d in %s %d	Failed to find the plugin make function	Contact support.	XMS
371111	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to instantiate PluginInterface in %s %d	Failed to instantiate plugin	Check the plugin config section in the config file. Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371112	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to load Plugin %s %d	Failed to load the plugin	Ensure that the plugin library exists and is readable.	XMS
371113	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to open CDR file %s %d	Failed to open CDR file	Check that the directory exists and is writable. Correct and reload config file.	XMS
371114	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to open CDR temporary directory %s %d	MMX couldnt write to the specified CDR directory.	Create the directory or correct the config file.	XMS
371118	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal consistency error: Destination domain %d not found	Internal error has occurred.	Contact support.	XMS
371119	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal consistency error: incoming path %d not found	Internal error has occurred.	Contact support.	XMS
371120	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal consistency error: Originating domain %d not found	Internal error has occurred.	Contact support.	XMS
371121	ERROR	%s %d: xmsTrigger(%d) ERROR: Invalid message type %d	Internal error has occurred.	Contact support.	XMS
371123	ERROR	%s %d: xmsTrigger(%d) ERROR: MMX_PATH %d does not exist	Internal error has occurred.	Contact support.	XMS
371124	ERROR	%s %d: xmsTrigger(%d) ERROR: MMX_PLUGIN %d does not exist	Internal error has occurred.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371125	ERROR	%s %d: xmsTrigger(%d) ERROR: MMX_PLUGIN named %s %d does not exist in config file	The named adapter has not been configured in config file.	Add the named adapter to config file or remove it from the screens.	XMS
371126	ERROR	%s %d: xmsTrigger(%d) ERROR: Originating domain %s %d doesnt exist in routing scheme	The current message has been assigned a originating domain (via a call plan) that isnt configured.	Configure the domain in the screens, or change the call plan to specify a different domain name.	XMS
371128	ERROR	%s %d: xmsTrigger(%d) ERROR: SleeDialogHandler cannot route TCAP non-BEGIN event.	Received a TCAP event without a dialog	No action required.	XMS
371129	ERROR	%s %d: xmsTrigger(%d) ERROR: TCAP primitive without destination address.	Incomplete TCAP message received.	No action required.	XMS
371130	ERROR	%s %d: xmsTrigger(%d) ERROR: TCAP primitive without destination SSN.	Incomplete TCAP message received.	No action required.	XMS
371131	ERROR	%s %d: xmsTrigger(%d) ERROR: Unknown MmxConstant request of (%s %d,%s %d) assuming 0.	Internal error has occurred.	Contact support.	XMS
371138	ERROR	%s %d: xmsTrigger(%d) ERROR: XMS cannot trigger SCP, unknown service key %d	Mismatch between tdp.conf service key and SLEE.cfg service configuration.	Correct tdp.conf or SLEE.cfg so the triggered service key has an associated service and application.	XMS
371143	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempting Adapter Load %s %d (%s %d) (SSN %d)	About to load configuration for the given adapter.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371163	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Management Event REPORT_REQUEST	Event report request received	No action required.	XMS
371164	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Management Event REREAD_CONFIG	Event report request received	No action required.	XMS
371165	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Maximum SMS/s rate in the last period: %d	Timed load report.	No action required.	XMS
371172	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Reading triggers from %s %d	Event triggers read.	No action required.	XMS
371173	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Retry CDR file open in %d seconds	We will try to open the CDR file some time in the future.	No action required.	XMS
371174	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Startup Successful	MMX started successfully.	No action required.	XMS
371175	NOTICE	%s %d: xmsTrigger(%d) NOTICE: UPTIME %d %d:%d:%d	A report stating the time that xmsTrigger has been running.	No action required.	XMS
371176	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Your system is running within allowed limits (maximum concurrent calls: %d, currently: %d; maximum SMS/sec: %d, currently %d)	Load report.	No action required.	XMS
371177	WARNING	%s %d: xmsTrigger(%d) WARNING: /IN/service_packages/XMS/e tc/tdp.conf not installed. Can not trigger the call plan	tdp.conf has been removed.	Create a new Trigger Detection Points configuration file.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371180	WARNING	%s %d: xmsTrigger(%d) WARNING: Deprecated config file item xmsTrigger.routingScheme.loadInterval used, use loadIntervalSeconds.	Deprecated entry in config file	Update config file and restart SLEE.	XMS
371182	WARNING	%s %d: xmsTrigger(%d) WARNING: Failed to process SleeRimsEvent.	A particular RIMS event could not be handled.	Contact support.	XMS
371183	WARNING	%s %d: xmsTrigger(%d) WARNING: Failed to process SleeTextEvent.	A particular text event (from the sleeTextIF control interface) could not be handled.	Contact support.	XMS
371184	WARNING	%s %d: xmsTrigger(%d) WARNING: Multiple SMS Failure Imminent: CONTACT SUPPORT. Your system is close to running beyond allowed limits (maximum concurrent calls: %d, currently: %d; maximum SMS/sec: %d, currently %d)	Near overload warning.	Contact support.	XMS
371185	WARNING	%s %d: xmsTrigger(%d) WARNING: Received Unsupported EventType 0x123	Received a SLEE event that is not supported	Contact support.	XMS
371186	WARNING	%s %d: xmsTrigger(%d) WARNING: scfSendScfMsg called after call over.	Attempting to send a message to ACS after the call has completed	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371188	WARNING	%s %d: xmsTrigger(%d) WARNING: TCAP primitive for PC %d, SSN %d has no available adapter.	SS7 traffic has arrive for which there is not configured adapter.	Reconfigure your network to use a different Point Code or Sub System Number, or update config file so that the given PC or SSN is supported by an adapter.	XMS
371191	WARNING	%s %d: xmsTrigger(%d) WARNING: tdp.conf not installed. Can not trigger the call plan	tdp.conf has been removed.	Create a new Trigger Detection Points configuration file.	XMS
371192	WARNING	%s %d: xmsTrigger(%d) WARNING: Terminated with INTERFACE_END	XmsTriggerApplication terminated after receiving an interface end management event.	No action required.	XMS
371193	WARNING	%s %d: xmsTrigger(%d) WARNING: Terminated with INTERFACE_KILL	XmsTriggerApplication terminated after receiving an interface end management event.	No action required.	XMS
371196	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: xmsiIS41::invalidateRIMSCache: Failed to send Query to RIMS.	HLR lookup (via RIMS) failed	as unable to send SLEE message	XMS
371197	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataCDMA::decode Input buffer has %d extraneous bytes.	An invalid message was received and will not be processed.	Contact support.	XMS
371198	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataCDMA::decode Input buffer pos %d + data len %d overflows buffer len %d .	An invalid message was received and will not be processed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371199	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataCDMA::decode Mandatory parameter MessageIdentifier missing.	An invalid message was received and will not be processed.	Contact support.	XMS
371200	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataCDMA::encode Output buffer overflow on parameter index %d.	An invalid message was received and will not be processed.	Contact support.	XMS
371201	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::decode Buffer Len too short (%d bytes, should be >= %d).	An invalid message was received and will not be processed.	Contact support.	XMS
371202	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::decode Buffer Len too short (%d bytes, should be >= 1).	An invalid message was received and will not be processed.	Contact support.	XMS
371203	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::decode Undecoded remainder %d overflows %d opaqueBytes.	An invalid message was received and will not be processed.	Contact support.	XMS
371204	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::decode UserDataUnit NumBytes < 0 bytes.	An invalid message was received and will not be processed.	Contact support.	XMS
371205	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::decode UserDataUnit string length > %d bytes.	An invalid message was received and will not be processed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371206	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::decode UserDataUnit string overflows input buffer.	An invalid message was received and will not be processed.	Contact support.	XMS
371207	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::encode Buffer Len too short (%d bytes, should be >= %d).	An invalid message was received and will not be processed.	Contact support.	XMS
371208	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::encode Fields required for deliver encode are not all present.	An invalid message was received and will not be processed.	Contact support.	XMS
371209	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::encode Fields required for encode are not all present.	An invalid message was received and will not be processed.	Contact support.	XMS
371210	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::encode MessageTypeIndicator %d not supported.	An invalid message was received and will not be processed.	Contact support.	XMS
371211	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::encode opaqueBytes string overflows output buffer.	An invalid message was received and will not be processed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371212	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::encode UserDataUnit string overflows output buffer.	An invalid message was received and will not be processed.	Contact support.	XMS
371213	ERROR	%s %d: xmsTrigger(%d) ERROR: BearerDataTDMA::encode validityPeriod overflows output buffer.	An invalid message was received and will not be processed.	Contact support.	XMS
371215	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: No SMSC configured to match destination %s %d: %s %d.	No matching SMSC configured for destination	Check SMSC configuration for destination	XMS
371216	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt find inbound path for adapter %s %d, endpoint type %s %d, pc %d, ssn %d, gt %s %d	Routing scheme incorrectly configured.	Edit routing scheme to create path for this connection.	XMS
371217	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt remove RIMS dialog from router	Internal SLEE error.	Contact support if problem persists.	XMS
371222	ERROR	%s %d: xmsTrigger(%d) ERROR: No relay path for incoming path %d: %s %d	Relay path not set for incoming path.	Set a path if one is required.	XMS
371224	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Received non-type 2 global title (type: %d).	We received a TCAP message with an unsupported GT type.	Contact support.	XMS
371225	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: RIMS responded with failure status: %s %d.	HLR lookup failed for direct delivery	Check messages from HLR to RIMS	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371226	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: RIMS responded without a valid location: %s %d.	HLR lookup failed for direct delivery	Check messages from HLR to RIMS	XMS
371227	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Unable to retrieve SMS_DestinationAddress or SMS_OriginalDestinationAdd ress from SMDPP.	Incoming SMDPP is missing information we need.	Contact support.	XMS
371234	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Bad MMX result code %d	MMX sent this plugin an unexpected result.	Contact support.	XMS
371235	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Cannot perform FDA for teleservice %d.	FDA was requested for an invalid teleservice	e.g. TDMA.	XMS
371236	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: Failed to create dialog to service key %d.	SLEE communication attempt failed.	Check configured service keys in MMX and SLEE config files.	XMS
371237	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to resend TCAP event to SMSC on dialog %s %d	SLEE communication attempt failed.	Contact support.	XMS
371238	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: Failed to send event on dialog %s %d.	SLEE communication attempt failed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371239	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to send is41Error on dialog %s %d.	SLEE communication attempt failed.	Contact support.	XMS
371240	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to send smdpp ACK on dialog %s %d.	SLEE communication attempt failed.	Contact support.	XMS
371241	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to send smdpp NAK on dialog %s %d.	SLEE communication attempt failed.	Contact support.	XMS
371242	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to send TCAP_ABORT on dialog %s %d.	SLEE communication attempt failed.	Contact support.	XMS
371243	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: Received TCAP event with no primitive.	SLEE communication attempt failed.	Check test tool configuration, contact support.	XMS
371245	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Couldnt extract TCAP component from SLEE event (state TerminatingDelivery).	SLEE communication attempt failed.	Contact support.	XMS
371246	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Couldnt get SLEE Interface API handle.	SLEE resource shortage.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371247	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Have a MIN (%s %d) which is not 10 digits	Received an invalid MIN	Contact support.	XMS
371250	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - invalid callback(readyToDeliver) invoked in state TerminatingDelivery.	Internal state error.	Contact support.	XMS
371251	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - invalid callback(readyToDeliver) invoked in state TerminatingLookup.	Internal state error.	Contact support.	XMS
371252	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - No dialog associated with event.	SLEE communication attempt failed.	Contact support.	XMS
371254	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - Trying to send an SMDPP Delivery Ack Msg over plugin configured for TDMA.	Configuration error detected. Delivery receipts are not supported in the TDMA plugin.	Change configured routing rules.	XMS
371255	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error: Invalid SMDPP message received.	The IS41 SMDPP is malformed.	Contact support with a network trace.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371257	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Invalid IS41 SMDPPResult received.	We couldnt understand the response from the network on the outgoing side.	Contact support.	XMS
371259	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Not allowed to perform FDA for IS41-TDMA.	Invalid configuration detected.	MMX routing rules may not request that messages with a destination of SME be routed to a TDMA IS41 plugin. Change the destination to MC.	XMS
371260	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: %s %d side timed out while waiting for SMDPPResult (transaction %s %d, dialog %s %d) - aborting transaction.	The connection to the SMSC timed out.	Check SMSC configuration and network connectivity.	XMS
371261	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: Originating side timed out (transaction %s %d, dialog %s %d) - aborting transaction.	The output side of the call took too long to complete; our input side has ended the call.	Check the outbound route configuration or contact support.	XMS
371262	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Originating transactions not allowed by plugin %s %d.	The current configuration does not allow this plugin to handle input messages.	Either reconfigure the input route or change the configuration so that this plugin may handle inbound messages.	XMS
371263	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Outgoing messages not allowed for adapter %s %d	The current configuration does not allow this adapter to handle outgoing messages	Either reconfigure the output route of the message or change the adapter settings to allow outbound messages	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371264	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Received TCAP_ABORT from MS/MSC (state TerminatingDelivery).	We received an abort from the network element on the output side.	Check network configuration or contact support.	XMS
371265	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Received unexpected dialog closed event (dialog %s %d, transactions dialog %s %d, state TerminatingDelivery).	One of our SLEE dialogues was closed unexpectedly.	Contact support.	XMS
371266	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: SMDPP Result must arrive in a TCAP_RESPONSE(TCAP_RESULT_LAST), not a %s %d.	Unexpected message received from network on output side.	Contact support with a network trace.	XMS
371269	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: TCAP event is not TCAP_QUERY(TCAP_WITH_PERMISSION).	Unexpected TCAP event received.	Contact support with a network trace.	XMS
371270	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: TCAP event received on unknown dialog (state TerminatingDelivery).	Unexpected TCAP event received.	Contact support with a network trace.	XMS
371271	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Unable to retrieve destination SCCP address from SMDPP.	Malformed message received	missing/bad destination address.	XMS
371272	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Unable to retrieve originating SCCP address from SMDPP.	Malformed message received	missing/bad destination address.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371273	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Unable to retrieve SMS_OriginatingAddress or SMS_OriginalOriginatingAddress from SMDPP.	Incoming SMDPP is missing information we need.	Contact support.	XMS
371274	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Unsupported CDMA message type (%d).	Unrecognised SMDPP received. We expect the Submit or Cancel types.	Contact support.	XMS
371275	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Unsupported TDMA message type %d.	Unrecognised SMDPP received. We expect the Submit or FCS types.	Contact support.	XMS
371276	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiIS41 config reloaded successfully.	New configuration loaded.	No action required.	XMS
371301	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Informational: xmsiIS41 being quiesced	Plugin shutting down.	No action required.	XMS
371302	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Alert On Message Delivery (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371303	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Deferred Delivery Time Absolute (%d bytes, should be 6).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371304	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Deferred Delivery Time Relative (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371305	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring LanguageIndicator (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371306	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Message Center Time Stamp (%d bytes, should be 6).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371307	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Message Deposit Index (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371308	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Message Display Mode (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371309	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Message Identifier (%d bytes, should be 3).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371310	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Message Status (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371311	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Multiple Encoding User Data (%d bytes, should be >= 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371312	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Number Of Messages (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371313	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Priority Indicator (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371314	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Privacy Indicator (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371315	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Reply Option (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371316	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Service Category Program Data (%d bytes, should be >= 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371317	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Service Category Program Results (%d bytes, should be >= 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371318	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring User Data (%d bytes, should be >= 3, <= %d).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371319	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring User Response Code (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371320	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Validity Period Absolute (%d bytes, should be 6).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371321	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::decode Ignoring Validity Period Relative (%d bytes, should be 1).	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371322	WARNING	%s %d: xmsTrigger(%d) WARNING: BearerDataCDMA::encode Unknown Bit Mask 0x%s %d.	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371323	WARNING	%s %d: xmsTrigger(%d) WARNING: Config: xmsiIS41: (deliveryFailureErrorClass , deliveryFailureStatusCode) is an invalid pair, setting Error Class (%d) and Status Code (%d) to default	The Error Class defines the valid Failure Status Codes.	Consult the IS41 standard for the valid combinations.	XMS
371326	WARNING	%s %d: xmsTrigger(%d) WARNING: Unknown IS41 CDMA BearData UserData data coding scheme: %d	An invalid field was detected in the message, which will still be processed.	Contact support.	XMS
371327	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: Ending old dialog before sending SMDPP.	Internal state error: a dialogue already exists on output side.	Contact support.	XMS
371328	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: Ending old dialog before sending SMDPP(DelAck).	The A-leg dialog should have been closed by the ACK sent in response to the short message.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371329	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: Mismatched InvokeId in response (%d, expected %d, state TerminatingDelivery).	Unexpected message received; InvokeID not what we expected. Possible network misconfiguration.	Contact support.	XMS
371330	WARNING	%s %d: xmsTrigger(%d) WARNING: xmsiIS41: Terminating side timed out while waiting for SMSREQResult (transaction %s %d, dialog %s %d) - aborting transaction.	The adapter has timed out while waiting for a response from RIMS.	Ensure that communication between MMX and RIMS is active.	XMS
371331	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Dialog %s %d closed unexpectedly. Aborting transaction.	Communications error, leg aborted.	Contact support.	XMS
371332	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Failed to send MAP error %d to originating MSC: %s %d.	Communications error, route failed.	Contact support.	XMS
371333	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Failed to send SLEE event on dialog %s %d.	Communications error, route failed.	Contact support.	XMS
371334	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: MSC requested fallback to unrecognised application context: %s %d.	After attempting direct delivery to an MSC the MSC requested fallback but the MAP plugin didnt recognise the MAP application context the MSC requested.	Investigate the TCAP messages between MMX and the MSC; contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371335	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received ABORT from MMX - MSC id %s %d: %s %d.	MMX aborted call processing.	Refer to the xmsTrigger log for possible reasons that the call was aborted. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371336	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received ABORT from MMX: %s %d.	MMX aborted call processing.	Refer to the xmsTrigger log for possible reasons that the call was aborted. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371337	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received MAP v123 TCAP BEGIN with no forwardSM component.	The MAP message received didn't contain a ForwardShortMessage component.	Investigate the network element that the message originated from; contact support.	XMS
371338	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received MAP v123 TCAP CONTINUE with no forwardShortMessage component: %s %d.	The MAP message received didn't contain a ForwardShortMessage component.	Investigate the network element that the message originated from; contact support.	XMS
371339	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP U- ERROR with unknown invoke id %d in response to MAP open with invoke id %d: %s %d.	Received an unexpected TCAP Error message.	Investigate the TCAP messages between MMX and the MSC.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371340	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP_ABORT(%s %d) from MSC: %s %d.	After attempting direct delivery to an MSC the MSC responded with a TCAP ABORT.	Investigate the TCAP messages between MMX and the MSC; contact support. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371341	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP_ABORT(%s %d) from RIMS: %s %d.	RIMS responded to a MAP message with a TCAP ABORT.	Investigate the TCAP messages between MMX, RIMS and the HLR; contact support. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371342	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP_ABORT(%s %d) from SMSC: %s %d.	The SMSC responded to a MAP message with a TCAP ABORT.	Investigate the TCAP messages between MMX and the SMSC; contact support. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371343	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP_ABORT(%s %d) on originating MSCs dialog: %s %d.	Received a TCAP Abort from the originating MSC.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS
371344	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP_ABORT(%s %d) on originating MSCs dialog. TCAP dialog id %d, MSC id %s %d, Begin/Abort- Delta=123s: %s %d.	Received a TCAP Abort from the originating MSC.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371345	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: received unexpected TCAP component %d (op/err id %d) in response to MAP open: %s %d.	Received an unexpected TCAP message.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS
371346	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received unexpected TCAP component %d (op/err id %d) in response to MAP open: %s %d.	Received an unexpected TCAP message.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS
371347	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received unexpected TCAP primitive (%d): %s %d.	Received an unexpected TCAP message.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS
371348	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: SMSC requested fallback to unrecognised application context: %s %d	The MAP plugin didnt recognise the MAP application context the SMSC requested.	Investigate the TCAP messages between MMX and the SMSC; contact support.	XMS
371349	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: SMSC requested fallback to unrecognised application context: %s %d.	The MAP plugin didnt recognise the MAP application context the SMSC requested.	Investigate the TCAP messages between MMX and the SMSC; contact support.	XMS
371350	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Unable to get dialog to SLEE service key %d: %s %d.	Resource allocation error, SLEE communication not possible.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371351	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: xmsiMap: received TCAP NOTICE: aborting transaction: %s %d	Received an unexpected TCAP Notice message.	Investigate the TCAP messages between MMX and the MSC.	XMS
371353	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: xmsiMap: mapTimeout setting DEPRECATED, please use individual timeout parameters	The mapTimeout setting is no longer used.	Configure separate timeouts using smscTimeout, mscTimeout and rimsTimeout.	XMS
371354	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: xmsiMap: overrideServiceCentreAddre ssToHlr setting UNSUPPORTED, please remove this option from your configuration	The overrideServiceCentreAddr essToHlr setting is no longer used.	Remove item from config file.	XMS
371355	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: xmsiMap: overrideServiceCentreAddre ssToMsc setting UNSUPPORTED, please remove this option from your configuration	The overrideServiceCentreAddr essToMsc setting is no longer used.	Remove item from config file.	XMS
371356	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt find inbound path for adapter %s %d	Configuration error.	Reconfigure routing scheme to create a path associated with this adapter.	XMS
371358	ERROR	%s %d: xmsTrigger(%d) ERROR: Error retrieving Message Centre named %s %d	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371361	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: %s %d received null TcapComponent.	Received an invalid TCAP message..	Check incoming TCAP messages.	XMS
371362	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Aborted by MMX before processing began: %s %d.	Internal software error.	Contact support.	XMS
371363	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Cannot process MO messages: %s %d.	Internal software error.	Contact support.	XMS
371367	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Cast to MAP v3 MT-ForwardSM failed: %s %d	Received an invalid message which we were unable to construct a MAP message from.	Check network configuration or contact support.	XMS
371368	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Connection not set: %s %d.	Internal software error.	Contact support.	XMS
371369	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Control should never reach this point: %s %d.	Internal software error.	Contact support.	XMS
371370	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Delivery receipt from MMX must have SME destination: %s %d.	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371371	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Delivery receipts not supported for MAP v123: %s %d.	Configuration error. Delivery receipts requested for a MAP version that doesnt support them.	Modify the configuration file to no longer request Drs for this plugin.	XMS
371373	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: mscNumber not set: %s %d.	Internal software error.	Contact support.	XMS
371375	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received a mapEvent in awaitingRIMS: %s %d.	An unrequested non-RIMS event has been received while awaiting RIMS	Investigate the network element that the MAP message originated from. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371380	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received non-BEGIN TCAP primitive (primitive type: %d)	Received invalid TCAP component for this state.	Contact support.	XMS
371383	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received TCAP_ABORT(%s %d) before processing began: %s %d.	Internal software error.	Contact support.	XMS
371385	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received unexpected TCAP message while waiting for MMX response: %s %d.	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371386	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received unexpected TCAP message: %s %d.	Internal software error.	Contact support.	XMS
371387	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: RIMS responded with a different IMSI: %s %d.	Error in the message received from RIMS	Check the RIMS message log for errors, contact support.	XMS
371389	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: RIMS responded without an IMSI: %s %d.	Error in the message received from RIMS	Check the RIMS message log for errors, contact support.	XMS
371390	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: RIMS responded without an MSISDN: %s %d.	Error in the message received from RIMS	Check the RIMS message log for errors, contact support.	XMS
371394	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Transaction aborted by MMX before processing began: %s %d.	Internal software error.	Contact support.	XMS
371395	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Tried to send MAP error without a valid dialog: %s %d	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371396	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: xmsiMapTransaction received non-TCAP event (initial).	Received a SLEE event that is not supported.	Contact support.	XMS
371397	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: xmsiMapTransaction received non-TCAP event (subsequent): %s %d.	Received a SLEE event that is not supported.	Contact support.	XMS
371398	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: xmsiMapTransaction received TCAP event (initial) with no primitive	Received an invalid TCAP event.	Contact support.	XMS
371399	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: xmsiMapTransaction received TCAP event (subsequent) with no primitive: %s %d.	Received an invalid TCAP event.	Contact support.	XMS
371400	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Inconsistency Error: Attempt to close dialog %s %d while in unexpected state %d: %s %d.	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371401	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Inconsistency Error: Attempt to close RIMS dialog %s %d while in unexpected state %d: %s %d.	Internal software error.	Contact support.	XMS
371402	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Inconsistency Error: Couldnt remove MAP transaction dialog from router	Internal software error.	Contact support.	XMS
371403	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Inconsistency Error: Couldnt remove RIMS dialog from router	Internal software error.	Contact support.	XMS
371406	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Failed to create dialog to RIMS: %s %d.	SLEE communication error.	Ensure that communication between MMX and RIMS is active.	XMS
371407	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Failed to extract sm-RP-DA (SCA/IMSI/LMSI), sm-RP-OA (SCA/msisdn) or sm-RP-UI from %s %d.	Unable to interpret MAP message.	Check for errors in incoming MAP messages. Contact Support.	XMS
371408	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Failed to get RIMS Interface - handle is NULL: %s %d.	Could not contact RIMS.	Ensure that RIMS is currently running, and that the RIMS interface is configured in the SLEE configuration file.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371409	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Failed to get slee API - handle is NULL: %s %d	SLEE communication error.	Ensure the SLEE is running.	XMS
371410	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: Impossible to send MAP- STATUS-REPORT for version %d: %s %d	Configuration error. Attempting to send delivery receipt for a MAP version that doesnt support them.	Modify the configuration file to no longer request Drs for this plugin.	XMS
371411	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: RIMS responded with protocol failure: %s %d.	Internal software error.	Check the RIMS error log, contact support.	XMS
371417	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap config reloaded successfully	New configuration loaded.	No action required.	XMS
371454	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Informational: MapTransaction not being made for context: %s %d , as xmsiMap is in state %s %d	The adapter is not in state running so we are not starting a transaction.	No action required.	XMS
371455	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Informational: xmsiMap being quiesced	Plugin shutting down.	No action required.	XMS
371456	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: MAP Validity Period functionality indicator extension bit is not supported by MAP version 3.	The MAP enhanced Validity Period functionality indicator extension bit is reserved (should be 0) in the MAP v. 3 standard (GSM 03.40 v7.5.0), yet a message was received with this bit set.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371457	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: Received IMSI with more than %d digits: %s %d	Received an IMSI parameter longer than allowed by the MAP standard.	Investigate the network element that the message originated from; contact support.	XMS
371458	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: Received IMSI with more than 16 digits: %s %d	Received an IMSI parameter longer than allowed by the MAP standard.	Investigate the network element that the message originated from; contact support.	XMS
371459	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: Timed out while waiting for response from MMX: %s %d.	MMX took too long to deliver the short message.	Refer to the xmsTrigger log (and the ACS log if an ACS callplan was triggered) for possible failure reasons. If necessary increase the MAP plugins originatingTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371460	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: Timed out while waiting for response from MSC: %s %d.	After attempting direct delivery to an MSC the MSC didnt respond to the MAP message.	Investigate the TCAP messages between MMX and the MSC. If necessary, increase the MAP plugins mscTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371461	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: Timed out while waiting for response from RIMS: %s %d.	RIMS didnt respond to the MAP message.	Investigate the TCAP messages between MMX, RIMS and the HLR. If necessary, increase the MAP plugins rimsTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371462	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: Timed out while waiting for response from SMSC: %s %d.	The SMSC didnt respond to the MAP message.	Investigate the TCAP messages between MMX and the SMSC. If necessary, increase the MAP plugins smscTimeout config option. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371463	WARNING	%s %d: xmsTrigger(%d) WARNING: Communications Error: Timed out while waiting for segmented MAP message - MSC id %s %d: %s %d.	No response received after sending a response to a segmented MAP Open message.	Investigate the network element that the MAP Open message originated from. Note that displaying this alarm is configurable (see the MAP plugins alarmMask config option).	XMS
371464	WARNING	%s %d: xmsTrigger(%d) WARNING: Config: xmsiMap: Protocol ID mapping key %d not in 0..255.	Protocol ID mapping key is incorrectly configured.	Configure this value to be between 0-255	XMS
371465	WARNING	%s %d: xmsTrigger(%d) WARNING: Config: xmsiMap: Protocol ID mapping value %d not in 0..255.	Protocol ID mapping value is incorrectly configured.	Configure this value to be between 0-255	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371466	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error: %s %d timeout before processing began.	Internal software error.	Contact support.	XMS
371468	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error: Failed to get RIMS Interface - handle is NULL. Not updating RIMS: %s %d.	Misconfiguration detected.	Please check that you have a valid SLEE interface name configured.	XMS
371469	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error: Failed to get slee API - handle is NULL. Not updating RIMS: %s %d.	Misconfiguration detected.	Please check that you have a valid SLEE interface name configured.	XMS
371470	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error: Failed to send update to RIMS: %s %d.	Unable to send SLEE event	Contact support.	XMS
371471	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error: Message reference %d overflows data type (limit 0xff): %s %d.	Problem encountered during protocol->protocol conversion; we can use 32-bit message references internally, but MAP only allows for 8-bit references.	No action required.	XMS
371473	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error: Timeout before processing began: %s %d.	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371474	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error:Failed to create dialog to RIMS. Not updating RIMS: %s %d.	Out of SLEE resources.	Contact support.	XMS
371475	WARNING	%s %d: xmsTrigger(%d) WARNING: invalidateRIMSCache: Failed to create dialog to RIMS. Not updating RIMS: %s %d,	Out of SLEE resources.	Contact support.	XMS
371476	WARNING	%s %d: xmsTrigger(%d) WARNING: MapTransaction::invalidateRIMSCache: Failed to get slee API - handle is NULL. Not updating RIMS	Misconfiguration detected.	Please check that you have a valid SLEE interface name configured.	XMS
371477	WARNING	%s %d: xmsTrigger(%d) WARNING: MapTransaction::invalidateRIMSCache: Failed to send Update to RIMS.	Unable to send SLEE event	Contact support.	XMS
371478	WARNING	%s %d: xmsTrigger(%d) WARNING: Single SMS Failure: Destination Address arrived empty. Rejecting message.	We received a MAP message with no destination address.	Contact support.	XMS
371479	WARNING	%s %d: xmsTrigger(%d) WARNING: Single SMS Failure: Failed to send query to RIMS: %s %d	Internal error prevented MMX from sending a message to RIMS.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371481	WARNING	%s %d: xmsTrigger(%d) WARNING: Single SMS Failure: Originating Address arrived empty. Rejecting message.	We received a MAP message with no originating address.	Contact support.	XMS
371484	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Invalid xmsiWrapper configuration.	Unknown internal error while loading config.	Contact support.	XMS
371485	ERROR	%s %d: xmsTrigger(%d) ERROR: Bad address type %s %d, should be itu or ansi.	macroNodes.SendShortMessageNode.tcapOrigAddr.type must be itu or ansi	Correct this parameter in config file and restart the SLEE.	XMS
371486	ERROR	%s %d: xmsTrigger(%d) ERROR: Cant send event, TCAP dialogue is NULL.	Internal error.	Contact support.	XMS
371487	ERROR	%s %d: xmsTrigger(%d) ERROR: Cant send NULL SLEE event.	Internal error: couldnt create SLEE event.	Contact support.	XMS
371488	ERROR	%s %d: xmsTrigger(%d) ERROR: Could not load remote wrappers TCAP address.	Configuration error	couldnt load address	XMS
371489	ERROR	%s %d: xmsTrigger(%d) ERROR: Could not load wrapper plugins TCAP address.	Configuration error	couldnt load address	XMS
371490	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt create TCAP dialogue.	Internal error: resource allocation failed.	Contact support.	XMS
371496	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::handle Event - Couldnt extract Tcap component from event.	Bad TCAP event received.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371497	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::handle Event - Couldnt extract Tcap Primitive from event.	Bad TCAP event received.	Contact support.	XMS
371498	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::handle Event - received non-TCAP event.	SLEE communication error: bad event type.	Contact support.	XMS
371499	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::tcapBe gin - Couldnt extract Tcap component from event	Bad TCAP event received.	Contact support.	XMS
371500	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::tcapBe gin - Couldnt extract Tcap primitive from event	Bad TCAP event received.	Contact support.	XMS
371502	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::tcapBe gin - received non-TCAP event	SLEE communication error: bad event type.	Contact support.	XMS
371507	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiWrapper: Timer expired, sending abort message to participants.	No response received in configured period.	Contact support if problem persists.	XMS
371508	NOTICE	%s %d: xmsTrigger(%d) NOTICE: xmsiWrapper being quiesced	Plugin shutting down.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371509	NOTICE	%s %d: xmsTrigger(%d) NOTICE: xmsiWrapper(%s %d) not creating WrapperTransaction for context: %s %d	Plugin is not in running state.	No action required.	XMS
371511	WARNING	%s %d: xmsTrigger(%d) WARNING: TcapUtils::sendTcapEvent failed - SLEE exception caught.	SLEE communication error occurred.	Contact support.	XMS
371512	WARNING	%s %d: xmsTrigger(%d) WARNING: TcapUtils::sendTcapEvent(s tatic) failed - SLEE exception caught.	SLEE communication error occurred.	Contact support.	XMS
371514	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Internal error: IP::MultiTransaction::conn ect() called	Internal error has occurred.	Contact support.	XMS
371515	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Internal error: XMSListener::removeConnect ion failed, bad listen address	Internal error.	Contact support.	XMS
371516	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Internal error: XMSListener::removeConnect ion failed, connection not found	Internal error.	Contact support.	XMS
371517	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Received TCAP_BEGIN event, aborting	Internal error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371518	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: %d is not a valid message index	Protocol error.	Contact support. Provide core file.	XMS
371519	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: early ack not possible in this state (%d)	The early-ack operation is not valid at this point in the call.	No action required.	XMS
371520	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Inbound message result only allowed in OUTGOING state (state is %d)	Internal error.	Contact support.	XMS
371521	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Inbound short-message not allowed in this state (%d)	Internal error.	Contact support.	XMS
371522	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: EMI: Transaction does not contain an EMI context!	Internal error.	Contact support.	XMS
371523	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: EMI: unable to find original request	Internal error.	Contact support.	XMS
371524	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal Error: MC Connection %s %d has no associated path	Internal error.	Contact support.	XMS
371525	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal Error: Received NULL originating context	Internal error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371527	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal Error: SME Connection %s %d has no associated path	Internal error.	Contact support.	XMS
371528	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: no originating context found	Internal error.	Contact support. Provide core file.	XMS
371529	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: no originating context found in transaction context: did you really pass the request through me?	Internal error.	Contact support.	XMS
371530	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: no request message found in transaction context, did you really pass the request through me?	Internal error.	Contact support.	XMS
371531	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: no Transaction Context found in transaction , did you really pass the request through me?	Internal error.	Contact support.	XMS
371532	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: not allowed at this stage (%s %d)	invalid message type received.	Contact support.	XMS
371533	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: not allowed in this stage (%s %d)	invalid message type received.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371534	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: only status reports allowed in the INCOMING state	Protocol error.	Contact support. Provide core file.	XMS
371537	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: trying to send message to NULL protocol handler	Internal state error.	Contact support.	XMS
371539	ERROR	%s %d: xmsTrigger(%d) ERROR: Attempt to route between like entities (i.e smsc->smc)	Invalid scenario.	Check network configuration.	XMS
371540	ERROR	%s %d: xmsTrigger(%d) ERROR: Cannot build message : DCS %d is invalid.	Invalid incoming message.	Contact endpoint supplier.	XMS
371541	ERROR	%s %d: xmsTrigger(%d) ERROR: Cannot build message : User data header is defined as longer than user data	Invalid incoming message.	Contact endpoint supplier.	XMS
371542	ERROR	%s %d: xmsTrigger(%d) ERROR: Configuration Error: Ignoring SME connection %s %d which overlaps %s %d	Invalid configuration: The combination of local listen, remote source and local user-name must be unique.	Correct the connection details in the screens.	XMS
371543	ERROR	%s %d: xmsTrigger(%d) ERROR: Configuration error: Plugin %s %d detected schema inconsistency: %s %d	Internal error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371544	ERROR	%s %d: xmsTrigger(%d) ERROR: Configuration error: Plugin %s %d does not occur in new routing scheme	An adapter listed in config file is not configured in the screens.	Configure the adapter in the screens.	XMS
371545	ERROR	%s %d: xmsTrigger(%d) ERROR: Configuration error: Plugin %s %d: EMI connection %s %d has invalid Remote Source: %s %d	Syntax error in Remote source field of an EMI connection	Correct the Remote source field in the EMI connection screen	XMS
371546	ERROR	%s %d: xmsTrigger(%d) ERROR: Connection attempt to %s %d failed : %s %d	External communications error.	Contact support.	XMS
371547	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt accept incoming connection %s %d	Failed to open connection requested connection.	Check network configuration and status.	XMS
371549	ERROR	%s %d: xmsTrigger(%d) ERROR: Destination change from %s %d to %s %d not supported to stop looping, check configuration, OA(TON:NPI:Address)=%s %d, DA(TON:NPI:Address)=%s %d, outgoing path=%s %d	Attempted to change message type from submit to deliver, which is not supported.	Reconfigure the routing scheme to avoid this message destination change.	XMS
371550	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d connection %s %d has invalid remote listen host name %s %d - exception %s %d - connection ignored	The adapter cannot use the configured listen address as it is invalid.	Correct the listen address in the screens.	XMS
371551	ERROR	%s %d: xmsTrigger(%d) ERROR: EMI transaction using null window	Invalid internal state.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371552	ERROR	%s %d: xmsTrigger(%d) ERROR: EMI transaction using other transactions window %d	Invalid internal state.	Contact support.	XMS
371553	ERROR	%s %d: xmsTrigger(%d) ERROR: Error logging in to EMI SMSC %s %d: %s %d	Internal error has occurred.	Contact support.	XMS
371554	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to connect to ASP %s %d	Configuration error.	Check connection configuration in the screens.	XMS
371555	ERROR	%s %d: xmsTrigger(%d) ERROR: Failed to connect to SMSC %s %d	Configuration error.	Check connection configuration in the screens.	XMS
371556	ERROR	%s %d: xmsTrigger(%d) ERROR: Failure while sending EMI message response: %s %d	Internal error has occurred.	Contact support.	XMS
371557	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Error: EMI FiveXKey corrupted in PStore!: %s %d: %s %d	Internal error has occurred.	Contact support.	XMS
371558	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal error: EMI: No transaction found for response %s %d	Internal error has occurred.	Contact support.	XMS
371559	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal error: EMI: Unable to create message key: %s %d	Internal error has occurred.	Contact support.	XMS
371561	ERROR	%s %d: xmsTrigger(%d) ERROR: MsgSubmitSMResp to original message type %d	Invalid operation detected.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371562	ERROR	%s %d: xmsTrigger(%d) ERROR: Number rule missing to convert AdC = (%d) %s %d to emi format. Sending in normalised form.	No matching number rule specified in the config.emiDefaults.number Rules subsection of the EMI adapters section of the config file.	Correct and reload config file.	XMS
371563	ERROR	%s %d: xmsTrigger(%d) ERROR: Number rule missing to convert OAdC (%d) %s %d to emi format. Sending in normalised form.	No matching number rule specified in the config.emiDefaults.number Rules subsection of the EMI adapters section of the config file.	Correct and reload config file.	XMS
371565	ERROR	%s %d: xmsTrigger(%d) ERROR: received provisioning actions result which we have not asked for	Protocol error, internal state error.	Contact support.	XMS
371566	ERROR	%s %d: xmsTrigger(%d) ERROR: Received response message but timeout not set.	Protocol error, internal state error.	Contact support.	XMS
371567	ERROR	%s %d: xmsTrigger(%d) ERROR: Received unexpected session management result from SMSC login (%s %d) : %s %d	Protocol error, internal state error.	Contact support.	XMS
371568	ERROR	%s %d: xmsTrigger(%d) ERROR: Rogue protocol handler attempting login request	Internal state error.	Contact support.	XMS
371569	ERROR	%s %d: xmsTrigger(%d) ERROR: Rogue protocol handler indicating prelogin failure	Internal state error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371570	ERROR	%s %d: xmsTrigger(%d) ERROR: Rogue protocol handler outbind request	Internal state error.	Contact support.	XMS
371573	ERROR	%s %d: xmsTrigger(%d) ERROR: Trying to send multi-address message, but no MultiTransaction	Internal state error.	Contact support.	XMS
371574	ERROR	%s %d: xmsTrigger(%d) ERROR: Unable to bind connection %s %d to address %s %d: %s %d - connection ignored	The IP adapter was unable to bind to the port it was configured with.	Ensure that the specified IP address and port are available from the MMX machine.	XMS
371580	NOTICE	%s %d: xmsTrigger(%d) NOTICE: ASP %s %d %s %d side connection id=%s %d : queue length reached %d operations in last %d seconds	System overloaded	No action required.	XMS
371581	NOTICE	%s %d: xmsTrigger(%d) NOTICE: ASP %s %d %s %d side connection id=%s %d : rejected %d operations due to congestion at destination in last %d seconds	System overloaded	No action required.	XMS
371582	NOTICE	%s %d: xmsTrigger(%d) NOTICE: ASP %s %d asp side connection id=%s %d : rejected %d operations due to load limiting in last %d seconds	System overloaded	No action required.	XMS
371583	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempt to send illegal submitMulti response (via %s %d)	Internal error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371584	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Attempt to submitMulti response to operation %d (%s %d) addr %s %d	Invalid internal state.	Contact support.	XMS
371585	NOTICE	%s %d: xmsTrigger(%d) NOTICE: EMI Received %d message on used transaction number (%d) asp id=%s %d (%s %d side) connection id=%s %d	Invalid internal state.	Contact support.	XMS
371586	NOTICE	%s %d: xmsTrigger(%d) NOTICE: EMI Received excess windowed messages (expectmax of %d) from %s %d login (%s %d) : %s %d	Window is full of unprocessed messages.	Contact support.	XMS
371587	NOTICE	%s %d: xmsTrigger(%d) NOTICE: EMI: Could not store message key (SMSC or MMX failed to create unique key?): %s %d	Error interfacing with the persistent store.	Contact support.	XMS
371588	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Disconnect detected on connection %s %d.	Error detected, description supplied.	Contact support.	XMS
371589	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Logging out ASP %s %d	Logout notice.	No action required.	XMS
371590	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Logging out SMSC %s %d	Logout notice.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371591	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Login attempt to SMSC failed with error code %d text %s %d	EMI login failed.	Check SMSC login configuration in the screens.	XMS
371592	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Lost connection to ASP %s %d	Connection dropped.	No action required.	XMS
371593	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Lost connection to SMSC %s %d	Connection dropped.	No action required.	XMS
371594	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Path %s %d: MC connection id=%s %d: rejected %d operations due to load limiting in last %d seconds	MC overload protection.	Contact support.	XMS
371595	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Path %s %d: Last open %s %d connection closed. Entering failover mode	A redundant connection has been lost.	No action required.	XMS
371597	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received operation of type %d from unknown ASP (%s %d:%d from %s %d:%d) when waiting for session management open operation: %s %d	Invalid network operation detected.	Contact support.	XMS
371598	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received unexpected operation of type %d from ASP login (%s %d) : %s %d	Protocol error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371599	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received unexpected operation of type %d from SMSC login (%s %d) : %s %d	Protocol error.	Contact support.	XMS
371600	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Received unexpected response of type %d from %s %d login (%s %d) : %s %d	Protocol error.	Contact support.	XMS
371601	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Session timeout ASP login (%s %d) addr %s %d	ASP session timed out.	No action required.	XMS
371602	NOTICE	%s %d: xmsTrigger(%d) NOTICE: SMEConnection %s %d logged-in: received good response to outbind	ASP logged in successfully.	No action required.	XMS
371603	NOTICE	%s %d: xmsTrigger(%d) NOTICE: SMEConnection: ASP %s %d logged in successfully	ASP logged in successfully.	No action required.	XMS
371604	NOTICE	%s %d: xmsTrigger(%d) NOTICE: SMSC %s %d logged in successfully	SMSC login successful.	No action required.	XMS
371605	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: failed to send response to transaction	Communications error.	Contact support.	XMS
371606	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: Internal error: Result addresses did not match request address list	Internal state error,	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371607	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: Unrecognized priority of %d. Assuming XSer Normal	Error decoding short message	Contact support.	XMS
371608	WARNING	%s %d: xmsTrigger(%d) WARNING: ASP %s %d login failed. Reason code: %d - %s %d	ASP failed to login to MMX.	Check connection login detail in the screens.	XMS
371609	WARNING	%s %d: xmsTrigger(%d) WARNING: Config: Obsolete smppDefaults option specified; ignoring.	Obsolete item in config file.	Removed item from config file.	XMS
371611	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI emiDefaults.numberRules config not found or incorrect	Bad configuration detected, defaults loaded.	Consult Technical Guide for range of appropriate values.	XMS
371612	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI emiDefaults.pstoreNumberRu les config not found or incorrect	Bad configuration detected, defaults loaded.	Consult Technical Guide for range of appropriate values.	XMS
371613	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI global default configuration not found, using default defaults	emiDefaults configuration section not found.	Insert configuration item into config file.	XMS
371614	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI Protocol Handler received LoginResponse while in logged in state	Protocol error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371615	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI Protocol Handler received LoginResponse while in not connected state	Protocol error.	Contact support.	XMS
371616	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI Protocol Handler received LoginResponse while waiting for session management message	Protocol error.	Contact support.	XMS
371617	WARNING	%s %d: xmsTrigger(%d) WARNING: EMI Protocol Handler received LoginResponse while waiting for session management response	Protocol error.	Contact support.	XMS
371618	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal error: Ambiguous SME login user %s %d, aspAddress %s %d, listenerAddress %s %d matches SMEs %s %d and %s %d	Local user-name, local listen and remote source for a connection must be unique.	Correct connection configuration in the screens.	XMS
371619	WARNING	%s %d: xmsTrigger(%d) WARNING: Path %s %d: All %s %d failover connections have failed	All MC connections have failed.	Check status of Message Centres.	XMS
371620	WARNING	%s %d: xmsTrigger(%d) WARNING: Path: No connection called %s %d found	Internal state error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371621	WARNING	%s %d: xmsTrigger(%d) WARNING: problem reading default EMI Priority (%s %d), using Normal	Bad configuration detected, defaults loaded.	Consult tech guide for a range of appropriate values.	XMS
371622	WARNING	%s %d: xmsTrigger(%d) WARNING: Received %s %d with bad transaction type	Internal error.	Contact support.	XMS
371623	WARNING	%s %d: xmsTrigger(%d) WARNING: Received message type %d with bad transaction type	Protocol error.	Contact support.	XMS
371624	WARNING	%s %d: xmsTrigger(%d) WARNING: Received response message of type %d when expecting response to type %d. Ignoring it	Protocol error.	Contact support.	XMS
371625	WARNING	%s %d: xmsTrigger(%d) WARNING: Received spontaneous response message	Protocol error.	Contact support.	XMS
371626	WARNING	%s %d: xmsTrigger(%d) WARNING: Rejected connection from unknown SME from %s %d to %s %d	Unauthorized SME attempted connection to MMX.	Check ASP connection configuration in the screens.	XMS
371627	WARNING	%s %d: xmsTrigger(%d) WARNING: SMEConnection %s %d authentication failed for outbind response	Login name and password provided by ASP do not match configuration of connection.	If login is valid update configuration of the connection in the screens.	XMS
371628	WARNING	%s %d: xmsTrigger(%d) WARNING: SMSC %s %d login failed	Protocol error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371629	WARNING	%s %d: xmsTrigger(%d) WARNING: SMSC %s %d login failed. Reason code: %d - %s %d	SMSC login failed.	Check SMSC connection configuration in the screens.	XMS
371644	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: SMPP: Could not create a response message!	Internal error.	Contact support.	XMS
371645	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: SMPP: multi-request not inbound on this plugin	Internal error.	Contact support.	XMS
371646	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: SMPP: Original request message not found!	Internal error.	Contact support.	XMS
371647	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: SMPP: Transaction does not contain an SMPP context!	Internal error.	Contact support.	XMS
371648	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: SMPP: Transaction does not contain SMPP context!	Internal error.	Contact support.	XMS
371649	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: SMPP: was not passed a multi-transaction!	Internal error.	Contact support.	XMS
371650	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: invalid message type: %s %d	Internal error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371658	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: received %s %d in response to %s %d	Protocol error.	Contact support.	XMS
371659	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: received response without sending request (%s %d with sequence number %d)	Protocol error.	Contact support.	XMS
371660	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: received SMPP response without sending request (%s %d with sequence number %d)	Protocol error.	Contact support.	XMS
371661	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: received unexpected bind response: %s %d #%d	Protocol error.	Contact support.	XMS
371666	ERROR	%s %d: xmsTrigger(%d) ERROR: Bind message is not a bind message, its a %s %d	Internal error.	Contact support.	XMS
371680	ERROR	%s %d: xmsTrigger(%d) ERROR: Received login response without requesting login.	Protocol error.	Contact support.	XMS
371681	ERROR	%s %d: xmsTrigger(%d) ERROR: Received SMPP message in closed state	Protocol error.	Contact support.	XMS
371687	ERROR	%s %d: xmsTrigger(%d) ERROR: TLV of type 0x%s %d with invalid length specifier, is %d, should be %d. Decoding as octet string.	Corrupt incoming message.	Contact endpoint vendor.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371688	ERROR	%s %d: xmsTrigger(%d) ERROR: TLV of type 0x%s %d with invalid length specifier, is %d, should be 0. Decoding as octet string.	Corrupt incoming message.	Contact endpoint vendor.	XMS
371689	ERROR	%s %d: xmsTrigger(%d) ERROR: TLV of type 0x%s %d with invalid length specifier, is %d, should be 1. Decoding as octet string.	Corrupt incoming message.	Contact endpoint vendor.	XMS
371690	ERROR	%s %d: xmsTrigger(%d) ERROR: TLV of type 0x%s %d with invalid length specifier, is %d, should be 2. Decoding as octet string.	Corrupt incoming message.	Contact endpoint vendor.	XMS
371691	ERROR	%s %d: xmsTrigger(%d) ERROR: TLV of type 0x%s %d with invalid length specifier, is %d, should be 4. Decoding as octet string.	Corrupt incoming message.	Contact endpoint vendor.	XMS
371698	ERROR	%s %d: xmsTrigger(%d) ERROR: xms::smpp::ProtocolHandler internal error: %s %d is not a bind request	Internal error has occurred.	Contact support.	XMS
371702	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Login attempt failed for %s %d %s %d, closing connection	SMPP login failed.	Check login configuration, contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371705	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Outbind attempt failed for SMSC %s %d, closing connection	Out-bind attempt failed.	Check SMSC connection configuration in the screens.	XMS
371706	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Outbind not allowed for TX only SMSC %s %d, closing connection	Out-bind attempt failed.	Check SMSC connection configuration in the screens.	XMS
371710	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Shutting down protocol handler %s %d	Closing connection.	No action required.	XMS
371714	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: change of segmented messages not supported	MMX can not modify segmented messages.	Contact support if problem persists.	XMS
371715	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: failed to abort XMSTA, exiting transaction	Minor internal error.	Contact support if problem persists.	XMS
371718	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: malformed delivery report, message_state TLV missing, assuming failure	Invalid incoming message.	Contact endpoint supplier.	XMS
371719	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: malformed delivery report, receipted_message_id TLV missing, using empty ID	Invalid incoming message.	Contact endpoint supplier.	XMS
371720	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d: Spurious response of type %s %d, sequence_number=%d, command_status=0x%s %d	Unexpected SMPP message received.	Contact support if problem persists.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371722	WARNING	%s %d: xmsTrigger(%d) WARNING: Bind request failed with command_status = 0x%s %d	Login failed.	Check connection login detail in the screens.	XMS
371723	WARNING	%s %d: xmsTrigger(%d) WARNING: Bind timeout, shutting down protocol handler %s %d	Protocol error.	Contact support if problem persists.	XMS
371724	WARNING	%s %d: xmsTrigger(%d) WARNING: Config file error in teleserviceRoutingMap: Non-empty SMPP service types will not be allowed to perform alternate delivery.	Error reading config file SMPP adapter section config.smppDefaults.teleserviceRoutingMap	Correct and reload config file	XMS
371726	WARNING	%s %d: xmsTrigger(%d) WARNING: Config: Obsolete emiDefaults option specified; ignoring.	Obsolete configuration item ignored.	Remove item from config file.	XMS
371727	WARNING	%s %d: xmsTrigger(%d) WARNING: Cross-over SMPP request %s %d (seq=%d) to %s %d timed out	Protocol error.	Contact support if problem persists.	XMS
371728	WARNING	%s %d: xmsTrigger(%d) WARNING: idleTimeout and heartbeatInterval both defined. Only %s %d will be used.	config file SMPP adapter value config.smppDefaults.smppDefaults.idelTimeout and heartbeatInterval are both defined so the smallest value will be used.	Set one of the value to 0 and restart the SLEE.	XMS
371729	WARNING	%s %d: xmsTrigger(%d) WARNING: Heartbeat timeout, shutting down protocol handler %s %d	Protocol error.	Contact support if problem persists.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371731	WARNING	%s %d: xmsTrigger(%d) WARNING: Outgoing SMPP request %s %d (seq=%d) to %s %d timed out	No response was heard for SMPP request.	Increase time-out in connection configuration in the screens.	XMS
371734	WARNING	%s %d: xmsTrigger(%d) WARNING: ProtocolHandler::ProtocolHandler: invalid SMPP version 0x%s %d, setting to 0x34	Invalid incoming message.	Contact endpoint supplier.	XMS
371735	WARNING	%s %d: xmsTrigger(%d) WARNING: ProtocolHandler::setFilter: invalid SMPP version 0x%s %d, setting to 0x34	Invalid incoming message.	Contact endpoint supplier.	XMS
371736	WARNING	%s %d: xmsTrigger(%d) WARNING: Received generic_nack in response to bind request. command_status = 0x%s %d	Login failed.	Check connection configuration in the screens.	XMS
371738	WARNING	%s %d: xmsTrigger(%d) WARNING: Session timeout, shutting down protocol handler %s %d	Connection idle for too long.	Increase Session Timeout in connection configuration in the screens.	XMS
371740	WARNING	%s %d: xmsTrigger(%d) WARNING: SMPP global defaults configuration in subsection %s %d not found, using defaults	Eserv.config SMPP adapter section config.smpdDefaults.smpdDefaults not found	Add configuration section to eserv.config and restart SLEE.	XMS
371743	WARNING	%s %d: xmsTrigger(%d) WARNING: xms::smpd::ProtocolHandler::messageAvailable: %s %d	An error occurred.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371744	CRITICAL	%s %d: slee_acs(%d) CRITICAL: ussdChassisAction::initial ise: Failed to get slee API - handle is NULL	Problem connecting to the SLEE.	Check SLEE is running. Check whether enough SLEE resources are available.	XMS
371745	ERROR	%s %d: slee_acs(%d) ERROR: Expected result for opId %d, got opId %d	Internal software error.	Contact support.	XMS
371746	ERROR	%s %d: slee_acs(%d) ERROR: xmsChassisActions: UssdChassisAction initialisation failed.	Internal software error.	Contact support.	XMS
371747	WARNING	%s %d: slee_acs(%d) WARNING: ussdEventHandler: received a sleeManagement event of type %d, treating as a timeout to USSD.	Received a SLEE event that is not supported	Contact support if problem persists.	XMS
371748	ERROR	%s %d: slee_acs(%d) ERROR: SSMN: Unable to extract text as UTF-8 (got %s %d), cant replace <SMS_TEXT> token.	Can not replace <SMS_TEXT> token.	Contact support.	XMS
371749	WARNING	%s %d: xmsTrigger(%d) WARNING: Config file error in dataCodingMap: dataCoding interpretation will use default values only	config file SMPP adapter did not specify or incorrectly specified.	No action required, MMX is initialised with DCS interpretation specified by SMPPv5.0.	XMS
371751	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: fallbackAlphabet = %s %d.	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371752	ERROR	%s %d: xmsTrigger(%d) ERROR: packUnicodeTo7bit: UDL %d (offsetBits %d) too large for dst size %d	An encoding error has occurred while processing user data.	The binary data encoded in the IDP appears to be corrupt. Either invalid data was provided to XMS, or corruption has occurred between xmsTrigger and the XMS service library. Check the originally received message, and check for compatibility between xmsTrigger, the plugins, and xmsSvcLibrary.	XMS
371753	ERROR	%s %d: xmsTrigger(%d) ERROR: Unable to construct RIMS IS41 query as we have an IMSI for the key	Received an SMSRequest that has only an IMSI for the MSID	MMX was unable to process this message. It may be possible if the outgoing path was changed to use a MAP adapter path.	XMS
371754	ERROR	%s %d: xmsTrigger(%d) ERROR: Unable to construct RIMS Map query as we have a MIN for the key	Received an SMSRequest that has no MDN routed to a MAP adapter	MMX was unable to process this message. It may be possible if the outgoing path was changed to use an IS41 adapter path.	XMS
371755	NOTICE	%s %d: slee_acs(%d) NOTICE: RealTimeCharging option not enabled - ADPB node disabled	The ADPB node is not licensed.	No action required.	XMS
371756	ERROR	%s %d: slee_acs(%d) ERROR: RealTimeCharging feature not licensed - ADPB node failed	An attempt has been made to use the unlicensed ADPB node.	Contact support for a new SECURE section of config file or remove the ADPB node from your call plan.	XMS
371757	ERROR	%s %d: slee_acs(%d) ERROR: %z Invalid Message Class: %z (Not changing)	Internal software error during SSMA node.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371758	ERROR	%s %d: slee_acs(%d) ERROR: Source field list %z doesnt have 3 values	Internal software error during SSMA node.	Contact support.	XMS
371759	ERROR	%s %d: slee_acs(%d) ERROR: %z : Invalid Message Waiting Type: %z (Not changing)	Internal software error during SSMA node.	Contact support.	XMS
371760	ERROR	%s %d: slee_acs(%d) ERROR: %z : Invalid Message Waiting Sense: %z (Not changing)	Internal software error during SSMA node.	Contact support.	XMS
371761	ERROR	%s %d: slee_acs(%d) ERROR: %z : Invalid Message Waiting Group: %z (Not changing)	Internal software error during SSMA node.	Contact support.	XMS
371762	ERROR	%s %d: slee_acs(%d) ERROR: %z : Invalid tzType %z . Not changing timezone.	Internal software error during SSMA node.	Contact support.	XMS
371763	ERROR	%s %d: slee_acs(%d) ERROR: %z : Could not determine SetSMSAttr Node Version (No.Param=%d)	Internal software error during SSMA node.	Contact support.	XMS
371764	ERROR	%s %d: xmsTrigger(%d) ERROR: No final statistic set for this message	Internal error. MMX processed the message without setting an exit statistic.	Should never happen, contact support.	XMS
371765	ERROR	%s %d: xmsTrigger(%d) ERROR: progress called with NULL controlled call	Internal software error. This should never happen.	Contact support.	XMS
371766	ERROR	%s %d: xmsTrigger(%d) ERROR: error: release causes dont match	Internal software error. This should never happen.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371768	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Delivery Report path not found. Using empty statistics category	Unable to determine a default inbound path for MMX generated delivery receipts.	Check path and adapter configuration. Contact support.	XMS
371769	ERROR	%s %d: xmsTrigger(%d) ERROR: Attempting to process RouteInfoResponse without origcc	A RouteInfo message required MSID masking when the message processing state was unable to cope. This should never happen.	Contact support.	XMS
371770	ERROR	%s %d: xmsTrigger(%d) ERROR: Attempting to process RouteInfoResponse with no associated RouteInfo	RouteInfo MSID masking was requested for a non-RouteInfo type message. This should never happen.	Contact support.	XMS
371771	ERROR	%s %d: xmsTrigger(%d) ERROR: No configuration for plugin %s %d found	MSID masking requested for a message when the plugin had no appropriate configuration	Correct and reload adapter section of the config file.	XMS
371772	ERROR	%s %d: xmsTrigger(%d) ERROR: No global title configured for plugin %z but it is attempting to process a routeInfoResult	MSID masking requested for a message when the plugin had no appropriate global title configuration	Correct and reload adapter section of the config file.	XMS
371773	ERROR	%s %d: xmsTrigger(%d) ERROR: unknown action method %d	Internal software error. This should never happen.	Contact support.	XMS
371775	ERROR	%s %d: xmsTrigger(%d) ERROR: Warning, done() called for ControlledCall still in state %z	Internal software error. This should never happen.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371776	ERROR	%s %d: xmsTrigger(%d) ERROR: TCAP_BEGIN/TCAP_UNI event received for already registered dialog/handler.	An SS7 Adapter is receiving multiple TCAP_BEGINS (or TCAP_UNIs) on the same TCAP dialog.	Investigate the network element that the message originated from.	XMS
371781	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: No HLR configured to match destination %s %d: %s %d.	Unable to determine the appropriate HLR to route an inbound RouteInfo.	Message is routed to a global title determined from the phone parameters. Check path configuration, possibly adding HLR Gts.	XMS
371782	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error: Invalid SMSRequest message received.	Internal software error. Unable to extract the SMSRequest from the TCAP primitive. This should never happen.	Inbound message was discarded. Contact support.	XMS
371783	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Unable to retrieve destination SCCP address from smsReq.	Inbound SMSRequest has a badly formatted destination address.	Message was discarded. Check network elements that are formulating the SCCP Addresses inbound to MMX.	XMS
371784	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to send SMSReqRes on dialog %d.	SLEE communication attempt failed.	Check allocation of SLEE resources (especially dialogs). Restarting the SLEE may temporarily solve the problem. Contact support.	XMS
371785	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: RIMS responded with abort: %z .	RIMS either received an abort from the HLR or decided to abort the request itself.	Check the RIMS error log, contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371786	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: SMS Failure: Destination SCCP address for SMDPP(DelAck) in connection %s %d contains neither GT nor PC.	We failed to get the destination address either from the HLR or from our configured SMSC connections.	Check connection configuration	XMS
371787	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: SMS Failure: Destination SCCP address for SMDPP in connection %s %d contains neither GT nor PC.	We failed to get the destination address	Check SMSC connection configuration, contact support.	XMS
371788	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: sendRIMSQuery: Failed to create dialog to RIMS	Unable to allocate SLEE resource	Possible misconfiguration of the SLEE	XMS
371789	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: sendRIMSQuery: Failed to get RIMS Interface- handle is NULL	Unable to find RIMS on this SLEE	Possible misconfiguration of the SLEE	XMS
371790	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to send SMSNOT response on NULL TCAP dialogue.	SLEE communication attempt failed.	Check allocation of SLEE resources (especially dialogs). Contact support.	XMS
371791	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to send SMSNOT response on dialog %s %d.	SLEE communication attempt failed.	Check allocation of SLEE resources (especially dialogs). Restarting the SLEE may temporarily solve the problem. Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371792	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: SMS Failure: Destination SCCP address in connection %s %d contains neither GT nor PC.	We failed to get the destination address	Check SMSC connection configuration, contact support.	XMS
371793	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: pathRetryRandomisation = %z	New configuration loaded.	No action required.	XMS
371794	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: pathRetrySegmentOffset = %z	New configuration loaded.	No action required.	XMS
371795	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: xmsiMap: nonGprsAdapterName = %s %d	New configuration loaded.	No action required.	XMS
371796	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received RIMS event in state %z : %z .	Internal state error. xmsTrigger was in an incorrect state to receive a response from RIMS.	Contact support.	XMS
371797	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received RouteInfoResult in state %z : %z .	Internal state error.	Contact support.	XMS
371798	ERROR	%s %d: xmsTrigger(%d) ERROR: Unable to create Map1SendRoutingInfoForSM from component, possibly due to incorrectly identified map version	Received an invalid message which we were unable to construct a MAP message from.	Check network configuration or contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371799	ERROR	%s %d: xmsTrigger(%d) ERROR: Unable to create Map2SendRoutingInfoForSM from component, possibly due to incorrectly identified map version	Received an invalid message which we were unable to construct a MAP message from.	Check network configuration or contact support.	XMS
371800	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: MapTransaction::Context is larger than GenericMessages originating interface context.	internal consistency error. The space allocated to hold inbound message information is not large enough.	This should never happen. Contact support.	XMS
371801	ERROR	%s %d: xmsTrigger(%d) ERROR: Received a routeInfoResponse with no IMSI	Error in the message received from RIMS	Check the RIMS message log for errors, contact support.	XMS
371802	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received a second MMX GenericSM: %z .	Internal state error. xmsTrigger was in an incorrect state to receive a new message.	Contact support.	XMS
371803	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP_ABORT(%z) in state awaitingRetry: %z .	We received an abort from the network element on the output side.	Check network configuration or contact support.	XMS
371804	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: No connection configured to match destination %s %d: %z .	Relay path not set for incoming path.	Set a path if one is required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371805	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiMap: SMS Failure: connection %s %d does not contain a GT.	We failed to get the global title for the destination address from either of the connection configuration or the inbound message.	Add a GT to the mentioned connection.	XMS
371806	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Communications Error: failed to resend TCAP event on dialog %s %d	SLEE communication attempt failed.	Contact support.	XMS
371807	ERROR	%s %d: xmsTrigger(%d) ERROR: RouteInfoRequest: Failed to get slee API - handle is NULL: %z	SLEE communication error.	Check the SLEE configuration. Ensure the SLEE is running.	XMS
371808	ERROR	%s %d: xmsTrigger(%d) ERROR: RouteInfoRequest: Failed to get RIMS Interface - handle is NULL: %z .	Could not contact RIMS.	Ensure that RIMS is currently running, and that the RIMS interface is configured in the SLEE configuration file.	XMS
371809	ERROR	%s %d: xmsTrigger(%d) ERROR: RouteInfoRequest: Failed to create dialog to RIMS: %z .	SLEE communication error.	Ensure that communication between MMX and RIMS is active.	XMS
371810	WARNING	%s %d: xmsTrigger(%d) WARNING: RouteInfoRequest: Failed to send query to RIMS: %z	Internal error prevented MMX from sending a message to RIMS.	Contact support.	XMS
371811	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Path ptx:%d prx:%d ltx:%d lrx:%d %s %d %s %d	Periodic report of pending and logged in connections.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371812	WARNING	%s %d: xmsTrigger(%d) WARNING: Rate limiting activated on path %s %d to enforce max message rate=%d/sec	An IP inbound path is receiving more inbound messages than the configured limit.	Rate limiting has been applied to the inbound plugin, no action is necessary.	XMS
371813	ERROR	%s %d: xmsTrigger(%d) ERROR: %z : RouteInfo never allowed in IP messages	Received an invalid message for an IP adapter.	Check network configuration or contact support.	XMS
371814	ERROR	%s %d: xmsTrigger(%d) ERROR: malformed user data: header length value exceeds total size of data	An encoding error has occurred while processing user data.	The size of the user data header is greater than the size of the user data. Check the network elements that are sending messages to MMX.	XMS
371815	ERROR	%s %d: xmsTrigger(%d) ERROR: No GlobalReject set while loading release causes from table MMX_REL_CAUSE. Default errorType set to Permanent Failure.	A Global Reject is not defined in the MMX release cause screens.	Add release causes to the GUI config.	XMS
371816	ERROR	%s %d: xmsTrigger(%d) ERROR: Duplicate MMX_ADDRESS_RULE id %d, isOriginating %s , pathNamePrefix %s %d, addressPrefix %d, messageType %s %d	An erroneous duplicate address rule has been entered in the screens.	Remove the duplicate address rule in the screens.	XMS
371817	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping unlicensed trigger rule - Triggering to service plan not enabled	Triggering to ACS is not licensed, but a trigger rule requests it. The offending trigger rule has been ignored.	No action necessary. If triggering to ACS is required contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371818	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed EMI protocol	A path has been configured that uses the unlicensed EMI adapter. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS
371819	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed VAS Gateway feature	A path has been configured that uses the unlicensed IP adapters. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS
371820	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed SMPP protocol	A path has been configured that uses the unlicensed SMPP adapter. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS
371821	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed IS41 TDMA protocol	A path has been configured that uses the unlicensed TDMA part of the IS41 adapter. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS
371822	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed ID41 CDMA protocol	A path has been configured that uses the unlicensed CDMA part of the IS41 adapter. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS
371823	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed MAP protocol	A path has been configured that uses the unlicensed MAP adapter. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371824	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed internal protocol	A path has been configured that uses the unlicensed wrapper adapter. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS
371825	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping unlicensed path due to unknown protocol	A path has been configured that does not define a protocol. The offending path has been ignored.	Check configuration of the problem path. If still a problem contact support.	XMS
371826	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Connection %s %d no longer accepts inbound messages as this feature is unlicensed	An inbound SS7 connection has been configured but MO_SS7 or MT_SS7 is unlicensed. The offending connection has had the inbound flag removed.	Check configuration of the problem connection. If this feature is required contact support.	XMS
371827	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Connection %s %d no longer sends outbound messages as this feature is unlicensed	An inbound SS7 connection has been configured but MO_SS7 or MT_SS7 is unlicensed. The offending connection has had the outbound flag removed.	Check configuration of the problem connection. If this feature is required contact support.	XMS
371828	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Connection %s %d is unlicensed and will not be used	The SS7 connection has been completely removed due to licensing.	Check configuration of the problem connection. If this feature is required contact support.	XMS
371829	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Fatal error loading routingscheme	Failed to load a new routing scheme from the database, and then failed to revert to the old scheme.	Check database is running or contact support.	XMS
371830	ERROR	%s %d: slee_acs(%d) ERROR: AcceptNode: Invalid attempt at call processing	Node has attempted a telephony action (Accept) when telephony is no longer allowed.	Recompile the affected call plan. If problem remains, contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371831	ERROR	%s %d: slee_acs(%d) ERROR: DiscardNode: Invalid attempt at call processing	Node has attempted a telephony action (Discard) when telephony is no longer allowed.	Recompile the affected call plan. If problem remains, contact support.	XMS
371832	ERROR	%s %d: slee_acs(%d) ERROR: RejectNode: Invalid attempt at call processing	Node has attempted a telephony action (Reject) when telephony is no longer allowed.	Recompile the affected call plan. If problem remains, contact support.	XMS
371833	ERROR	%s %d: slee_acs(%d) ERROR: ALB Node: User Selected Alphabet Out of Range	The call-plan configured alphabet is not available on this version of SCP code.	Contact support.	XMS
371834	ERROR	%s %d: xmsTrigger(%d) ERROR: %z should not be called from state %z . Aborting.	Internal state error.	Contact support.	XMS
371835	ERROR	%s %d: xmsTrigger(%d) ERROR: abort() called, but already in end state - ignored.	Internal state error.	Contact support.	XMS
371836	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - invalid callback(handleGenericSM) invoked in state AwaitingRetry.	Internal state error.	Contact support.	XMS
371837	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Received unexpected dialog closed event (dialog %s %d, transactions dialog %s %d, state AwaitingRetry).	One of our SLEE dialogues was closed unexpectedly.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371838	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error: Received GenericSM in StateOriginatingLookup, Type = %s %d, Dest = %s %d	Internal state error.	Contact support.	XMS
371839	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error: Received RouteInfoResult in StateOriginatingLookup	Internal state error.	Contact support.	XMS
371840	WARNING	%s %d: slee_acs(%d) WARNING: %s %d::decodes tag 123s size does not match the member variable size - not copying	Internals ACS-MMX communication fault.	Contact support.	XMS
371841	WARNING	%s %d: xmsTrigger(%d) WARNING: %s %d::decodes tag 123s size does not match the member variable size - not copying	Internal error.	Contact support.	XMS
371842	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Licensing Report	New configuration loaded.	No action required.	XMS
371843	NOTICE	%s %d: xmsTrigger(%d) NOTICE: %s %d - YES	New configuration loaded, with a license for the mentioned feature.	No action required.	XMS
371844	NOTICE	%s %d: xmsTrigger(%d) NOTICE: %s %d - NO	New configuration loaded, without a license for the mentioned feature.	No action required.	XMS
371845	NOTICE	%s %d: xmsTrigger(%d) NOTICE: End of Licensing Report	New configuration loaded.	No action required.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371846	WARNING	%s %d: xmsTrigger(%d) WARNING: Invalid licensing request: value supplied (%d) is outside valid range (0..%d)	Internal error has occurred.	Check licensing report on startup, if required options are licensed no action is required. Otherwise contact support.	XMS
371847	WARNING	%s %d: xmsTrigger(%d) WARNING: No licensed %s %d found in secure section	Expected configuration section is missing from config file.	Check licensing report on startup, if required options are licensed no action is required. Otherwise contact support.	XMS
371848	ERROR	%s %d: xmsTrigger(%d) ERROR: Problem loading licensed %s %d from secure section: %s %d	Unable to determine licensing options in config file.	Check licensing report on startup, if required options are licensed no action is required. Otherwise contact support.	XMS
371849	WARNING	%s %d: xmsTrigger(%d) WARNING: Unrecognized license %s 213 in secure section ignored	An invalid licensing option is present in the config file.	Check licensing report on startup, if required options are licensed no action is required. Otherwise contact support.	XMS
371850	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Activating license %s %d	New configuration loaded, with a license for the mentioned feature.	No action required.	XMS
371851	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: mtTransactionLifetimeSeconds = %d	New configuration loaded.	No action required.	XMS
371852	ERROR	%s %d: xmsTrigger(%d) ERROR: Supplied MMX_PATH %d does not exist	Internal error has occurred.	Contact support.	XMS
371853	ERROR	%s %d: xmsTrigger(%d) ERROR: Transaction received an unknown request	Internal error has occurred.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371854	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal consistency error: Routing Rule references the path %s %d, which does not exist	Internal error has occurred.	Contact support.	XMS
371857	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: RIMS responded with non-MAP protocol: %d.	HLR lookup failed for direct delivery	Check messages from HLR to RIMS	XMS
371858	ERROR	%s %d: xmsTrigger(%d) ERROR: Unknown value (%d) of GenericSM status report request.	An internal programming error has been detected.	Contact support.	XMS
371859	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received IS41 Address parameter too long to fit into GenericSM.	An address parameter in some IS41 message is too long for us to store.	Contact support.	XMS
371860	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received SCCP address too long to fit into GenericSM message.	The GT of some SCCP address is too long to store in an GenericSM.	Contact support.	XMS
371861	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - invalid callback(handleGenericSM) invoked in state TerminatingDelivery.	Internal state error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371862	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - invalid callback(handleGenericSM) invoked in state TerminatingLookup.	Internal state error.	Contact support.	XMS
371863	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error - No incoming SMDPP available and not allowed to use GenericSM.	Invalid configuration detected.	This happens when you use different input and output plugin instances and the message has a type like %SME status report%, which has a restricted set of use cases.	XMS
371864	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Internal Consistency Error: Received GenericSM in StateOriginating, Type = %s %d, Dest = %s %d	Internal state error.	Contact support.	XMS
371865	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Invalid message type %d in GenericSM	Software error.	Contact support.	XMS
371866	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: %s %d received MMX GenericSM before processing began.	Internal software error.	Contact support.	XMS
371867	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: %s %d received MMX GenericSMResult before processing began.	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371868	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Message centre not empty (instead set to %s %d) for proxied MT GenericSM: %s %d	Internal software error.	Contact support.	XMS
371869	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Null TcapPrimitive (%s %d) or GenericSM (%s %d)	Internal software error.	Contact support.	XMS
371870	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received a second MMX GenericSM: %s %d.	Internal software error.	Contact support.	XMS
371871	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received an MMX GenericSMResult (%s %d): %s %d.	Internal software error.	Contact support.	XMS
371872	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received an GenericSM from MMX that is not a delivery receipt: %s %d.	Internal software error.	Contact support.	XMS
371873	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received MMX GenericSMResult (%s %d) before processing began: %s %d.	Internal software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371874	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received null MMX GenericSM message: %s %d.	Internal software error.	Contact support.	XMS
371875	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Received unexpected MMX GenericSM: %s %d	Internal software error.	Contact support.	XMS
371876	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: Saved GenericSM is null: %s %d.	Internal software error.	Contact support.	XMS
371877	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: GenericSM (%s %d) or Connection (%s %d) not set: %s %d.	Internal software error.	Contact support.	XMS
371878	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal Consistency Error: TcapPrimitive (%s %d),GenericSM (%s %d) or Connection (%s %d) not set: %s %d.	Internal software error.	Contact support.	XMS
371879	ERROR	%s %d: xmsTrigger(%d) ERROR: Malformed GenericSMResult received (%s %d).	Corrupt message from remote trigger app.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371880	ERROR	%s %d: xmsTrigger(%d) ERROR: WrapperTransaction::tcapBegin - Malformed GenericSM received (%s %d).	The GenericSM we received is not valid.	Contact support.	XMS
371881	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: Internal error: Received unexpected GenericSM from protocol handler!	Internal error.	Contact support.	XMS
371882	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: MessageRequest not allowed in this state	Unexpected message received from MMX.	Contact support. Provide core file.	XMS
371883	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: MessageResponse not allowed in this state (%d)	Unexpected message received from MMX.	Contact support. Provide core file.	XMS
371884	ERROR	%s %d: xmsTrigger(%d) ERROR: %s %d: trying to send MessageResponse to NULL protocol handler	Internal state error.	Contact support.	XMS
371885	ERROR	%s %d: xmsTrigger(%d) ERROR: GenericSMResult from MMX has not been initialised.	Logic error.	Contact support.	XMS
371886	ERROR	%s %d: xmsTrigger(%d) ERROR: Communications Error: Received TCAP_ABORT(%s %d) in state awaitingRetry: %z .	Received a TCAP Abort while waiting to retry a failed message send.	Investigate the TCAP messages between MMX and the network element; contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371887	ERROR	%s %d: xmsTrigger(%d) ERROR: xmsiIS41: Unable to retrieve originating SCCP address from smsReq.	Inbound SMSRequest has a badly formatted originating address.	Message was discarded. Check network elements that are formulating the SCCP Addresses inbound to MMX.	XMS
371888	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal consistency error: Too few extension fields for GenericSM::encode	Internal error has occurred.	Contact support.	XMS
371889	ERROR	%s %d: slee_acs(%d) ERROR: Internal consistency error: Too few extension fields for GenericSM::encode	Internal error has occurred.	Contact support.	XMS
371890	ERROR	%s %d: xmsTrigger(%d) ERROR: Configuration error: Plugin %s %d: SMPP connection %s %d has invalid Remote Source: %s %d	Syntax error in Remote source field of an SMPP connection	Correct the Remote source field in the SMPP connection screen	XMS
371893	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Internal Error: ConcatenatedTransaction	Internal Error.	Refer to support.	XMS
371894	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Internal Error: SegmentContext	Internal Error.	Refer to support.	XMS
371895	WARNING	%s %d: xmsTrigger(%d) WARNING: Segments of message have differing alphabets	Segments of a concatenated message have different character sets.	If recurring, check other elements in network. Refer to support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371896	WARNING	%s %d: xmsTrigger(%d) WARNING: Received segment %d (0 based) of %d after desegmentation complete.	Segments of a concatenated message have been received incorrectly.	If recurring, check other elements in network. Refer to support.	XMS
371897	WARNING	%s %d: xmsTrigger(%d) WARNING: Received segment number %d (0 based), only expecting %d	Segments of a concatenated message have been received incorrectly.	If recurring, check other elements in network. Refer to support.	XMS
371898	WARNING	%s %d: xmsTrigger(%d) WARNING: Received duplicated segment %d	Segments of a concatenated message have been received incorrectly.	If recurring, check other elements in network. Refer to support.	XMS
371899	WARNING	%s %d: xmsTrigger(%d) WARNING: Message text octets %d does not contain supposed	Segments of a concatenated message have been received incorrectly.	If recurring, check other elements in network. Refer to support.	XMS
371900	NOTICE	%s %d: xmsTrigger(%d) NOTICE: %s %d(%s %d) not creating Transaction for context: %s %d	Plugin is not in running state.	No action required.	XMS
371901	ERROR	%s %d: xmsTrigger(%d) ERROR: Couldnt create SLEE dialogue.	Internal error: resource allocation failed.	Contact support.	XMS
371902	ERROR	%s %d: xmsTrigger(%d) ERROR: SleeTransaction::tcapBegin - received non-%s %d event	SLEE communication error: bad event type.	Contact support.	XMS
371903	ERROR	%s %d: xmsTrigger(%d) ERROR: SleeTransaction::tcapBegin - Got a non-Request protocol message	SLEE communication error: bad event type.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371904	ERROR	%s %d: xmsTrigger(%d) ERROR: SleeTransaction::handleEvent - received non-%s %d event	SLEE communication error: bad event type.	Contact support.	XMS
371905	ERROR	%s %d: xmsTrigger(%d) ERROR: SleeTransaction::handleEvent - Got a non-Response protocol message	SLEE communication error: bad event type.	Contact support.	XMS
371906	ERROR	%s %d: xmsTrigger(%d) ERROR: i.%s %d: Timer expired, sending abort message to participants.	No response received in configured period.	Contact support if problem persists.	XMS
371907	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Invalid mmxiSIP configuration.	Config file error	Correct and reload config file	XMS
371908	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Informational: mmxiSIP being quiesced	Plugin shutting down.	No action required.	XMS
371909	NOTICE	%s %d: xmsTrigger(%d) NOTICE: mmxiSCA(%s %d) not creating SIPTransaction for context: %s %d	Plugin is not in running state.	No action required.	XMS
371910	ERROR	%s %d: xmsTrigger(%d) ERROR: SIPProtocolHandler::convertRequestToGenericSM - Couldnt extract SIP message from event	Software error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371911	ERROR	%s %d: xmsTrigger(%d) ERROR: SIPProtocolHandler::convertResponseToGenericSMResult - Couldnt extract SIP message from event	Software error.	Contact support.	XMS
371912	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Internal Error: Redirection context gets non-short message	Internal Error.	Refer to support.	XMS
371913	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Internal Error: performAccept called on RedirectionContext.	Internal Error.	Refer to support.	XMS
371914	ERROR	%s %d: slee_acs(%d) ERROR: xmsChassisActions: SendGenericMessageAction initialisation failed.	Internal software error.	Contact support.	XMS
371919	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed SIP protocol	A path has been configured that uses the unlicensed SIP adapter. The offending path has been ignored.	No action necessary. If this feature is required contact support.	XMS
371920	ERROR	%s %d: xmsTrigger(%d) ERROR: Unrecognised tag in decode, treating as octet string	An invalid TLV was received in an internal SMPP message.	Contact support.	XMS
371921	WARNING	%s %d: xmsTrigger(%d) WARNING: Too many logins from %s %d to %s %d	Too many SMEs attempted to log in to MMX using the same configured connection.	Check ASP connection configuration in the screens.	XMS
371922	WARNING	%s %d: xmsTrigger(%d) WARNING: Failed to process SleeSipEvent.	A particular SIP event could not be handled.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371923	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Failed to start service - No SleeSIPEventType	Internal error.	Contact support.	XMS
371924	ERROR	%s %d: xmsTrigger(%d) ERROR: Destination dialog %s %d is not an interface	Internal SLEE error.	Contact support if problem persists.	XMS
371925	ERROR	%s %d: xmsTrigger(%d) ERROR: Cannot create transaction for SLEE event%s %d.	Internal error.	Contact support.	XMS
371926	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Creating Transaction without Context in incorrect manner	Internal Error.	Refer to support.	XMS
371927	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: Config: xmsiMap: abortMessagesWithZeroLengt hTPDA = %z	New configuration loaded.	No action required.	XMS
371928	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: Single SMS Failure: %z arrived too long. Rejecting message.	Network configuration problem - badly formed SMSC address.	Contact support.	XMS
371929	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: Rejected connection request because Socket is NULL	ASP -> SMSC communication pipe error	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371930	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: Single SMS Warning: Destination Address arrived empty. Returning Delivery Failure response containing InvalidSMEAddress cause.	Network configuration problem.	Contact support.	XMS
371931	CRITICAL	%s %d: slee_acs(%d) CRITICAL: malloc(%d) failed - %s %d	Resource allocation error.	Contact support.	XMS
371932	ERROR	%s %d: slee_acs(%d) ERROR: Userdata appears invalid	CorruptData.	Contact support.	XMS
371933	ERROR	%s %d: slee_acs(%d) ERROR: This MMX Extract Content node is unable to handle version %s %d of compiled control plan	CorruptData.	Use matching macronodes library as macro node definition.	XMS
371934	ERROR	%s %d: slee_acs(%d) ERROR: bad response (%d) to chassis action load profile request in Extract Content node - disconnecting call.	Internal Error.	Contact support.	XMS
371935	ERROR	%s %d: slee_acs(%d) ERROR: Userdata invalid - Dropping.	CorruptData.	Contact support.	XMS
371936	ERROR	%s %d: slee_acs(%d) ERROR: Unexpected message type (%d) received - disconnecting call.	Internal Error.	Contact support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371937	ERROR	%s %d: slee_acs(%d) ERROR: Format Text node is unable to handle profile tags of type %s %d\	Internal Error.	Contact support.	XMS
371938	ERROR	%s %d: slee_acs(%d) ERROR: This MMX Format Text node is unable to handle version %s %d\	Internal Error.	Contact support.	XMS
371939	ERROR	%s %d: slee_acs(%d) ERROR: Failed parse format for MMX Format Text node: %s %d	Internal Error.	Contact support.	XMS
371940	ERROR	%s %d: slee_acs(%d) ERROR: Bad response (%d) to chassis action load profile request in Format Text node - disconnecting call.	Internal Error.	Contact support.	XMS
371941	ERROR	%s %d: slee_acs(%d) ERROR: Bad response (%d) to chassis action request - disconnecting call.	Internal Error.	Contact support.	XMS
371942	ERROR	%s %d: xmsTrigger(%d) ERROR: Too many connection attempts on connection %s %d.	Too many SMEs attempted to log in to MMX using the same configured connection.	Check ASP connection configuration in the screens.	XMS
371943	ERROR	%s %d: xmsTrigger(%d) ERROR: Duplicate MMX_ADDRESS_RULE id %d, isOriginating %s , pathNamePrefix %s %d, addressPrefix %s %d	An erroneous duplicate address rule has been entered in the screens.	Remove the duplicate throttling rule in the screens.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371945	ERROR	%s %d: xmsTrigger(%d) ERROR: Internal consistency error: originating domain %d not found	Internal error has occurred.	Contact support.	XMS
371946	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: TP_DA (%s %d) arrived too long (%d digits). Rejecting message	An address parameter arrived that was longer than the allowed value.	Contact support.	XMS
371947	ERROR	%s %d: xmsTrigger(%d) ERROR: Single SMS Failure: MSISDN_OA (%s %d) arrived too long (%d digits). Rejecting message	An address parameter arrived that was longer than the allowed value.	Contact support.	XMS
371948	ERROR	%s %d: xmsTrigger(%d) ERROR: Number of chars (%d) much larger than allowable userDataLen	The number of characters in the message user data was larger than the allowed value.	Contact support.	XMS
371949	ERROR	%s %d: xmsTrigger(%d) ERROR: UDH length (%d) greater than total UD length (%d chars, %d octets)	The length of the user data header is greater than the reported length of the total user data.	Contact support.	XMS
371950	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal error: SMPPP idleTimeout and heartbeatInterval both defined. Only %s %d will be used.	config file SMPP adapter value config.smpdDefaults.smpdDefaults.idleTimeout and heartbeatInterval are both defined so the smallest value will be used.	Set one of the value to 0 and restart the SLEE.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371951	ERROR	%s %d: slee_acs(%d) ERROR: SendGenericMessage result on dialog %s %d not registered with this handler	An event handler received an event on a dialog that it is not associated with.	Contact support.	XMS
371952	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Internal error - message received in state connect	An attempt was made to deliver a message on a connection that was still being connected.	Contact Support	XMS
371953	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Invalid message received, disconnecting peer %z : %z	MMX failed to decode a message received from the far-end system	Refer to platform/LAN expert first, then consult support.	XMS
371954	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: xmsChassisActions: xmsStoreChassisAction initialisation failed.	A chassis action failed to initialise.	Refer to UNIX/platform expert first, then consult support.	XMS
371955	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: Callcontext request of type (%d) not (%d).	An invalid message type is being processed in the ADP node.	Contact support.	XMS
371956	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: %z (): Failed to retrieve nodePtr.	The shared library revision doesnt match the node definition on the SMP.	Contact support.	XMS
371957	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SSMN: Invalid <PT> token (un-ended): :e:s:p:iwr...	The data configured for the node is not valid.	Verify the node data in the Control Plan Editor. If the problem persists, contact Support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371958	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: Skipping <PT> token, unsupported by this node: %z	The message template is attempting to use fields that are not supported by this node.	Change the message template to not use the <PT> token, or to use the Send Short Message Node. Consult a platform expert, if problem persists, consult support.	XMS
371959	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: SSMN: Too many <PT> tokens in message text (max. is 138368d).	The message template contains too many PT tokens.	Modify the message template to use fewer PT tokens. If problem persists, consult Support.	XMS
371960	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: SSMN: The specified profile field is empty: %z	A profile field used in a PT tag either does not exist, or does not contain any data.	The system will continue, replacing the tag with an empty string. To correct the problem, ensure that data is available in the profile field. If problem persists, consult Support.	XMS
371961	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: SSMN: Missing <PT> format specifier: %z	The PT tag requires a format specifier to indicate the type of data in the profile field.	Modify the message template to properly specify the type of data in the profile field. If problem persists, consult a platform expert and then support.	XMS
371962	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: SSMN: Invalid <PT> format length specifier: %z	A non-numeric value was detected in the PT field value required for a format length.	Ensure that the PT field is correctly formatted in the message template. If problem persists, contact Support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371963	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: SSMN: Invalid <PT> format specifier I; The specified profile value is not an integer: %z	The PT tag indicates that the type in the profile field is an Integer, however the profile field does not contain an integer.	Correct the mismatch between the message template and the profile block. Usually means that the specified profile tag is incorrect. If problem persists, consult Support.	XMS
371964	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: SSMN: Invalid <PT> format specifier L; The specified profile value is not an integer: %z	The PT tag indicates that the type in the profile field is an Integer, however the profile field does not contain an integer	Correct the mismatch between the message template and the profile block. Usually means that the specified profile tag is incorrect. If problem persists, consult Support.	XMS
371965	WARNING	DEF123slee_acs: slee_acs(%d) WARNING: SSMN: Invalid <PT> format specifier %s %d: %z	The format specifier must be one of I L S	Correct the message template to specify the type as one of Integer Length (duration) or String. If problem persists, consult support.	XMS
371966	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SSMN: Failed to cast Callcontext to SMSRequest.	The SendShortMessage Node was used in a call plan that wasnt triggered by an SMS.	Remove the node from that call plan, it is not available for use with that service. Consult Support.	XMS
371967	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Attempt to create MT transaction with invalid network addresses	The system received an RI SCCP Calling Party Number that was not a telephone number.	Ensure that the RouteInfoSCCPCallingParty is a telephone number. Refer to platform expert first. If problem persists, consult support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371968	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to create MT Transaction with invalid network addresses	xmsTrigger tried to construct a Telephone Number from a non-numeric field.	Ensure that routeInfoDestAddr, routeInfoSCA and routeInfoSCCPCallingParty are all telephone numbers. Consult a platform expert first. If problem persists, contact Support.	XMS
371970	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Cannot install SIGUSR1 signal handler - %z [%d].	For some reason, xmsTrigger is unable to install the SIGUSR1 signal handler.	Restart xmsTrigger. If problem persists, consult Support.	XMS
371971	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to convert A and B party addresses to TelephoneNumbers	When sending a SMDPPDeliveryAck, either the A or B party addresses were invalid.	Consult Support.	XMS
371972	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to get MSISDN as telephone number	xmsTrigger is attempting to update RIMS with a non-numeric MSISDN	Contact Support.	XMS
371973	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to get SourceLocationInformation as telephone number	xmsTrigger is attempting to update RIMS with a non-numeric GGSN/VMSC address.	Contact Support.	XMS
371974	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to get SMSCAddress as telephone number	MAP was unable to convert the SMSCAddress to a telephone number	Contact Support.	XMS
371975	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to get Originating Address as telephone number	xmsTrigger tried to construct a Telephone Number from a non-numeric field.	Contact Support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371976	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to handle non- telephone numbers in MAP plugin	The MAP plugin has received an SMS containing non-telephone numbers.	Contact Support.	XMS
371977	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to construct RIMS Map query with non- telephone number dest address	XMS is attempting to route an SMS with a non- telephone number dest address.	Ensure that all addresses are telephone numbers when routing to the MAP plugin. Contact Support.	XMS
371978	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Plugin construction exception: %z	One of the XMS adapters failed to load.	Contact Support.	XMS
371979	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Wrapper received unrecognised Request type	There is a version mismatch between the remote interfaces and the wrapper plugin.	Consult a platform expert. If problem persists, contact Support.	XMS
371981	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to pass error result to parentContext, as it no longer exists	An error happened while processing an error.	Consult Support.	XMS
371982	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Solaris 9 iconv bug detected - performance will suffer	A fault in Solaris 9 iconv is being worked around.	This message is informational. It does not indicate a platform fault. If this message is being seen, and performance is a current problem, consult Support.	XMS
371983	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed CIMD protocol	A Path is in the routing scheme, but the platform is not licensed for that protocol.	Either unconfigure the path, or contact Sales to purchase support for that protocol.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371984	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: cmnError	A Path is in the routing scheme, but the platform is not licensed for that protocol.	Either unconfigure the path, or consult Sales to purchase a license for the protocol.	XMS
371985	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Error loading from database: %z - retaining existing Routing Scheme	An error was seen when reading from the database.	Consult a platform expert first. If problem persists, consult Support.	XMS
371986	CRITICAL	DEF123xmsTrigger: xmsTrigger(%d) CRITICAL: Fatal error loading from database: %z	The system is unable to load the initial routing scheme.	Refer to ORACLE/platform expert first. If problem persists, consult Support.	XMS
371987	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: Dropping path due to unlicensed MM7 protocol	A Path is in the routing scheme, but the platform is not licensed for that protocol.	Either unconfigure the path, or consult Sales to purchase a license for the protocol.	XMS
371988	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Received origMessageRequest in base TriggerState class, unexpected action	A software fault has been encountered.	Consult Support.	XMS
371989	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Internal error: ConcatenatedTransaction got route info result	A software fault has been encountered.	Consult Support.	XMS
371990	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Internal error: ConcatenatedTransaction got route info	A software fault has been encountered.	Consult Support.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371992	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: This version of the MAB node is unable to handle version :e:s:p	Software version on SMP and UAS doesnt match.	Ensure that the control plans were compiled using a version of xmsSms matching the xmsScp running on the UAS	XMS
371993	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: Attribute not found, exiting via NOT_FOUND branch	Node configured to use attribute that doesnt exist.	Check node configuration.	XMS
371994	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: Unknown Value type, exiting via NOT_FOUND branch	Incompatible node configuration	Check node configuration	XMS
371995	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: Invalid comparison, exiting via NOT_FOUND branch	Attempt to compare attributes of incompatible types.	Correct node configuration.	XMS
371996	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: Memory allocation failed, exiting via NOT_FOUND branch	System out of memory	Ensure that the system is correctly with available memory.	XMS
371997	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: Load profiles failed, exiting via NOT_FOUND branch	Unable to retrieve data associated with the message.	Check ACS and database logs for errors	XMS

Alarm	Severity	Text	Cause	Resolution	Service
371998	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: Message profile value empty, exiting via NOT_FOUND branch	No value configured to compare against.	The specified value configured in the node to compare the attribute against is empty. Correct the node configuration or populate the profile value.	XMS
371999	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: Non-numeric value, exiting via NOT_FOUND branch	Attempt to compare number against non-numeric string	Check node and profile configuration to ensure the comparison is using a numeric value.	XMS
372000	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: This version of the send USSD notification node is unable to handle version :e:s:p	Software version on SMP and UAS doesnt match.	Ensure that xmsScp version matches the xmsSms version used to compile the control plan.	XMS
372001	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: USSN: Too many <PT> tags in message text.	Too many <PT> tags in message text,.	Remove <PT> tags from message text until error stops occurring.	XMS
372002	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: USSN: Error parsing message text: %z	The message text could not be understood by the node.	Check node configuration	XMS
372003	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: Source field list \	The source field list is configured incorrectly.	Correct node configuration and ensure string is in the correct format.	XMS
372004	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: Target field list \	The target field list is configured incorrectly.	Correct the node configuration to ensure the target field list is correctly specified.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372005	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: decodeParam: tag 123s size does	Error when decoding wrapper messages.	Check for software version conflicts. Contact support.	XMS
372006	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: decodeParam: Unable to create GenericAddress for tag %d	Error when decoding wrapper messages.	Check for software versioning conflicts. Contact support.	XMS
372007	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: decodeParam: Unable to create TelephoneNumber for tag %d	Error when decoding wrapper messages.	Check for software version conflicts. Contact support.	XMS
372008	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: decodeParam: Unable to create InternetAddress for tag %d	Error when decoding wrapper messages.	Check for software version conflicts. Contact support.	XMS
372009	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: malformed user data: header length value exceeds total size of data	The message received was corrupt	Check network for other malformed messages.	XMS
372010	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: UDH length (%d) greater than total UD length (%d chars, %d octets)	Malformed message	Check network for other malformed messages.	XMS
372011	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Invalid user data header: UDHI=1, UDL=%d, UDHL=%d, A-party=%z , B-party=%z	xmsTrigger was unable to decode the user data header	Check network for malformed messages.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372013	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SMA: This version of the SMA node is unable to handle version :e:s:p	Incompatible software versions on UAS and SMP	Ensure the UAS and SMP are running compatible versions of the xms packages.	XMS
372014	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SMA: Attribute not found, exiting via NOT_FOUND branch	Node configured to use attribute that doesnt exist.	Correct Set Short Message Attribute node configuration.	XMS
372015	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SMA: Unknown Value type, exiting via NOT_FOUND branch	Conflict between shared library and node version	Confirm that the control plan is compiled using a compatible version of xmsSms to what is installed on the UAS.	XMS
372016	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SMA: SMA: Memory allocation failed, exiting via NOT_FOUND branch	System out of memory	Check UAS environment and confirm memory is available.	XMS
372018	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SMA: Load profile failed, exiting via FAILURE branch	Unable to retrieve data associated with the message.	Check the ACS and database logs.	XMS
372019	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SMA: Message profile value empty, exiting via NOT_FOUND branch	Unable to retrieve data associated with the message.	Check ACS and database error logs	XMS
372020	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: SMA: Failed to store profile tag, exiting via FAILURE branch	Unable to store data associated with the message.	Check ACS and database error logs.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372021	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: Internal Consistency Error: Received SCCP	Malformed message	Check SCCP level network logs and configuration.	XMS
372022	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Single SMS Failure:	Error in SCCP network or routing	Check SCCP level network logs and configuration.	XMS
372023	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Internal Consistency Error: Received	Malformed address parameter in IS41 message.	Check incoming network logs and configuration.	XMS
372025	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: MAB: This version of the STZ node is unable to handle version :e:s:p	Software version on SMP and UAS doesnt match.	Ensure UAS and SMP xms package software matches.	XMS
372026	ERROR	DEF123slee_acs: slee_acs(%d) ERROR: %z (): Invalid tzType \	Incorrect node configuration	Correct timezone type in node.	XMS
372027	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: Mbuni is unable to process outgoing message contents, sending on unchanged. type=%d	Attempting to process an invalid message.	If the error occurs frequently, check for invalid messages on the network.	XMS
372028	ERROR	DEF123mmsproxy: mmsproxy(%d) ERROR: Mbuni is unable to process outgoing message contents, sending on unchanged. type=%d	Attempting to process an invalid message.	If the error occurs frequently, check for invalid messages on the network.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372029	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: Unknown SLEE event type: %z , ignoring	A message was sent to mmsrelay from xmsTrigger that it cannot process.	Check that routing is correctly configured.	XMS
372030	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: Couldnt extract Tcap %z from event	A SLEE event was sent to mmsrelay that it could not process.	Check SLEE configuration, especially for mismatched service keys or interface names.	XMS
372031	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: Unable to unwrap MMSRequest from TCAP, ignoring	A SLEE event was sent to mmsrelay that it could not process.	Check MMX routing and SLEE configuration. Ensure that short messages are not being incorrectly routed through MMS adapters.	XMS
372032	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: Invalid request type, ignoring. Message Type = %d	A message was sent to mmsrelay from xmsTrigger that it cannot process.	Check MMX routing and SLEE configuration. Ensure that short messages are not being incorrectly routed through MMS adapters.	XMS
372033	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: No valid connections for path=%d:%z	Routing incorrectly configured	Check routing scheme configuration for specified path.	XMS
372034	NOTICE	DEF123mmsproxy: mmsproxy(%d) NOTICE: Oracle User Name = %z	Informational	Informational	XMS
372035	NOTICE	DEF123mmsrelay: mmsrelay(%d) NOTICE: Oracle User Name = %z	Informational	Informational	XMS
372036	NOTICE	DEF123mmsproxy: mmsproxy(%d) NOTICE: Oracle Password = %z	Informational	Informational	XMS
372037	NOTICE	DEF123mmsrelay: mmsrelay(%d) NOTICE: Oracle Password = %z	Informational	Informational	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372038	NOTICE	DEF123mmsproxy: mmsproxy(%d) NOTICE: Oracle Database = %z	Informational	Informational	XMS
372039	NOTICE	DEF123mmsrelay: mmsrelay(%d) NOTICE: Oracle Database = %z	Informational	Informational	XMS
372040	ERROR	DEF123mmsproxy: mmsproxy(%d) ERROR: Config: CONTACT ESERVGLOBAL SUPPORT: No valid secure section	Misconfiguration	Check eserv.config secure section is valid. Contact eSG support.	XMS
372041	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: Config: CONTACT ESERVGLOBAL SUPPORT: No valid secure section	Misconfiguration	Check eserv.config secure section is valid. Contact eSG support.	XMS
372042	WARNING	%s %d: xmsTrigger(%d) WARNING: Failed to process PStoreEvent.	A particular event (from the xmsStoreIf SLEE interface) could not be handled.	Contact support.	XMS
372043	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Failed to start service - No PStoreEventType	Internal error.	Contact support.	XMS
372044	ERROR	%s %d: xmsTrigger(%d) ERROR: SleeDialogHandler cannot route PStore event.	Received a PStore event without a dialog	No action required.	XMS
372045	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Could not initialise xmsTrigger: PStoreEventHandler cannot get Interface handle: %s	Config error pstore.interfaceName must match xmsStoreIf entry in SLEE.cfg	Correct and restart SLEE	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372046	CRITICAL	%s %d: xmsTrigger(%d) CRITICAL: Could not initialise xmsTrigger: Cannot get SLEE API handle	Internal error	Contact support.	XMS
372047	NOTICE	%s %d: mmsproxy(%d) NOTICE: %s %d - NO	New configuration loaded, without a license for the mentioned feature.	No action required.	XMS
372048	NOTICE	%s %d: mmsrelay(%d) NOTICE: %s %d - YES	New configuration loaded, with a license for the mentioned feature.	No action required.	XMS
372049	NOTICE	%s %d: mmsrelay(%d) NOTICE: %s %d - NO	New configuration loaded, without a license for the mentioned feature.	No action required.	XMS
372050	NOTICE	%s %d: mmsproxy(%d) NOTICE: End of Licensing Report	New configuration loaded.	No action required.	XMS
372051	NOTICE	%s %d: mmsrelay(%d) NOTICE: End of Licensing Report	New configuration loaded.	No action required.	XMS
372052	NOTICE	%s %d: mmsrelay(%d) NOTICE: Activating license %s %d	New configuration loaded, with a license for the mentioned feature.	No action required.	XMS
372053	NOTICE	%s %d: mmsrelay(%d) NOTICE: Finished loading routing scheme	Routing scheme finished loading	No action required.	XMS
372054	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Finished loading routing scheme	Routing scheme finished loading	No action required.	XMS
372055	WARNING	%s %d: xmsTrigger(%d) WARNING: number rule %z defined with min greater than max. Will never be used. Ignoring!	Warning in number rules definition	Redefine your number rules	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372056	WARNING	%s %d: xmsTrigger(%d) WARNING: number rule %z defined with remove %z > min. This will result in all digits being removed	Warning in number rules definition	Redefine your number rules	XMS
372057	NOTICE	%s %d: mmsproxy(%d) NOTICE: Finished loading routing scheme	Routing scheme finished loading	No action required.	XMS
372058	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: Skipping duplicated TLV tag: %d %d %d %z	Conflicting configuration in the eserv.config file	Values in the XMS.xmsTrigger.adapter section for configurable TLVs have been duplicated. Refer to UNIX/platform expert first	XMS
372059	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: Error reading XMS.xmsTrigger.adapters[%z].config.TLVs[%d]: %z	Configuration file error	The configuration of TLVs in the specified adapter is incorrect. Refer to UNIX/platform expert first	XMS
372060	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Error converting Hex MsgID(%z) to decimal	Software fault	Refer to UNIX/platform expert first	XMS
372061	NOTICE	DEF123xmsAgent: xmsAgent(%d) NOTICE: Configuration Not Found - XMS.xmsAgent section. Using defaults	The XMS.xmsAgent section in eserv.config doesnt exist	If non-default values are desired, verify the configuration section exists and the file is readable. Refer to UNIX/platform expert first	XMS
372062	NOTICE	DEF123xmsAgent: xmsAgent(%d) NOTICE: Unexpected Configuration Error - XMS.xmsAgent section. Using defaults	Unable to read the eserv.config file	Refer to UNIX/platform expert first	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372063	NOTICE	DEF123xmsAgent: xmsAgent(%d) NOTICE: tcpWaitTimeMilliSec = %d	Not a fault	The tcpWaitTimeMilliSec configuration parameter is now using the indicated value	XMS
372064	NOTICE	DEF123xmsAgent: xmsAgent(%d) NOTICE: rateLimitAlarmIntervalSec = %d	Not a fault	The rateLimitAlarmIntervalSec configuration parameter is now using the indicated value	XMS
372065	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Cannot send message, not enough room	The outgoing buffer is too full to send the indicated message	The socket is too backed up to transmit the data. The system should recover automatically. Refer to UNIX/platform expert first	XMS
372066	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: (%z) Connection timer of %d seconds expired. Closing connection.	The connection has been idle for too long	The xmsAgent is disconnecting an idle TCP connection	XMS
372067	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Rate limiting activated to enforce max message rate=%d/sec	A connection is initiating too many requests	The system will delay reading from the connection because it is attempting to send too many SMS messages. Refer to UNIX/platform expert first	XMS
372068	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Unable to send ProxyData event, No More SLEE Events	The SLEE has run out of available events	Refer to UNIX/platform expert first	XMS
372069	ERROR	DEF123xmsAgent: xmsAgent(%d) ERROR: Dialog is bad, ignoring event:%z	Unknown	Refer to UNIX/platform expert first	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372070	CRITICAL	DEF123xmsAgent: xmsAgent(%d) CRITICAL: Received unexpected type of SLEE event:%z	Bad SLEE configuration	Validate the SLEE service key configuration in SLEE.cfg. Refer to UNIX/platform expert first	XMS
372071	ERROR	DEF123xmsAgent: xmsAgent(%d) ERROR: Received event (size: %d bytes) larger than available buffer space of %d bytes	Software version mismatch	Refer to platform expert first	XMS
372072	NOTICE	DEF123xmsAgent: xmsAgent(%d) NOTICE: Startup Successful	Not a fault	xmsAgent has started	XMS
372073	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: Unexpected exception polling socket: %z	Unknown	Refer to UNIX/platform expert first	XMS
372074	ERROR	DEF123xmsAgent: xmsAgent(%d) ERROR: cmnError	Software version mismatch	Refer to UNIX/platform expert first	XMS
372075	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: Interface is quiescing, therefore ignoring %z event	Service is shutting down while traffic is running	xmsTrigger is attempting to set up connections through xmsAgent while the service is being turned off. Refer to UNIX/platform expert first	XMS
372076	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: Unknown event type %z received	SLEE.cfg misconfiguration	Validate the SLEE configuration, ensuring that the service keys for xmsAgent match those in the eserv.config file. Refer to UNIX/platform expert first	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372077	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: Unable to create a listening socket (%z) - %d:%z	The listen address is invalid	The xmsAgent was unable to listen on the port for the specified reason. Refer to UNIX/platform expert first	XMS
372078	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z : (%z)%z : (%z)) Unable to create connection, errno: %d, error: %z	Typically indicates misconfiguration	xmsAgent was unable to create a connection to the specified address. Refer to platform/LAN expert first	XMS
372079	CRITICAL	DEF123xmsAgent: xmsAgent(%d) CRITICAL: No more dialogs, unable to create connection	SLEE has run out of dialogs	Refer to UNIX/platform expert first	XMS
372080	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: Unexpected error: deleted listener does not match registered listener	Unknown	Refer to UNIX/platform expert first	XMS
372081	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Message received exceeds maximum allowable length. Discarding message.	An external system has attempted to send an overly large SMS	Refer to platform/LAN expert first	XMS
372082	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Failed to locate transaction context for response, ignoring message	A response message was received when no request was sent	Refer to UNIX/platform expert first	XMS
372083	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Failed to send enquire_link, assuming the link is dead.	xmsAgent failed to send an enquire_link	Refer to UNIX/platform expert first	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372084	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) enquire_link_resp not received in time, assuming the link is dead.	The indicated connection did not respond to an enquire_link message	Refer to UNIX/platform/LAN expert first	XMS
372085	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: Message received exceeds maximum allowable length. Discarding message.	xmsTrigger is attempting to send too long of an SMS	Refer to UNIX/platform/LAN expert first	XMS
372086	ERROR	DEF123xmsAgent: xmsAgent(%d) ERROR: (%z) Received unexpected bind request	A bind was sent in the wrong SMPP state	Refer to UNIX/platform/LAN expert first	XMS
372087	ERROR	DEF123xmsAgent: xmsAgent(%d) ERROR: (%z) Cannot proxy message - no dialog handler indicated in transaction context	Unknown	Refer to UNIX/platform/LAN expert first	XMS
372088	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Failed to send ESME_RMSGQFUL for (command_id: %z)	Unknown	Refer to UNIX/platform/LAN expert first	XMS
372089	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Failed to send throttle response - could not encode message	Unknown	Refer to UNIX/platform/LAN expert first	XMS
372090	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Failed to proxy message to MMX: %z	Unknown	Refer to UNIX/platform/LAN expert first	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372091	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Failed to proxy message to TCP connection: %z	Unknown	Refer to UNIX/platform/LAN expert first	XMS
372092	WARNING	DEF123xmsAgent: xmsAgent(%d) WARNING: (%z) Failed to extract extension TLVs from supplied message	Unknown	Refer to UNIX/platform expert first	XMS
372093	CRITICAL	DEF123xmsAgent: xmsAgent(%d) CRITICAL: Cannot install SIGHUP signal handler - %z [%d].	xmsAgent unable to configure signal handler	Refer to UNIX/platform expert first	XMS
372094	CRITICAL	DEF123xmsAgent: xmsAgent(%d) CRITICAL: Cannot install SIGTERM signal handler - %z [%d].	xmsAgent unable to configure signal handler	Refer to UNIX/platform expert first	XMS
372095	CRITICAL	DEF123xmsStore: xmsStore(%d) CRITICAL: Config File error: %z	Configuration file error	Refer to UNIX/platform expert first	XMS
372096	CRITICAL	DEF123xmsStore: xmsStore(%d) CRITICAL: Could not initialise xmsStore interface.	Unknown	Refer to UNIX/platform expert first	XMS
372097	WARNING	DEF123xmsStore: xmsStore(%d) WARNING: Failed to open XMS.xmsStore section in config file, using defaults.	Configuration file warning	Refer to UNIX/platform expert first	XMS
372098	NOTICE	DEF123xmsStore: xmsStore(%d) NOTICE: Startup Successful	Not a fault	No resolution required	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372099	ERROR	DEF123xmsStore: xmsStore(%d) ERROR: Config file reload failed: %z - keeping existing config	Configuration file error	Refer to UNIX/platform expert first	XMS
372100	WARNING	DEF123xmsStore: xmsStore(%d) WARNING: Received Unsupported EventType DEF123	SLEE.cfg misconfiguration	Refer to UNIX/platform expert first	XMS
372101	ERROR	DEF123xmsStore: xmsStore(%d) ERROR: Cannot get SLEE Interface API handle.	SLEE.cfg misconfiguration	Refer to UNIX/platform expert first	XMS
372102	ERROR	DEF123xmsStore: xmsStore(%d) ERROR: Cannot get SLEE event types (Management=DEF123,xmsStor e=DEF123).	Software version mismatch	Refer to UNIX/platform expert first	XMS
372103	ERROR	DEF123xmsStore: xmsStore(%d) ERROR: Cannot install SIGHUP handler: %z [%d].	Unknown	Refer to UNIX/platform expert first	XMS
372104	ERROR	DEF123xmsStore: xmsStore(%d) ERROR: Cant send PStoreOperation response: send failed.	The SLEE dialog has already closed	Refer to UNIX/platform expert first	XMS
372105	NOTICE	DEF123xmsStore: xmsStore(%d) NOTICE: Persistent Storage enabled	Not a fault	No action required	XMS
372106	NOTICE	DEF123xmsStore: xmsStore(%d) NOTICE: Persistent Storage disabled	Not a fault	No action required	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372107	WARNING	DEF123xmsStore: xmsStore(%d) WARNING: Terminated with INTERFACE_END	Not a fault	Interface is terminating as requested	XMS
372108	WARNING	DEF123xmsStore: xmsStore(%d) WARNING: Terminated with INTERFACE_KILL	Not a fault	Interface is terminating as requested	XMS
372109	NOTICE	DEF123xmsStore: xmsStore(%d) NOTICE: Management Event REPORT_REQUEST	Software version mismatch	Refer to UNIX/platform expert first	XMS
372110	NOTICE	DEF123xmsStore: xmsStore(%d) NOTICE: Management Event REREAD_CONFIG	Not a fault	xmsStore is rereading configuration as requested	XMS
372111	ERROR	DEF123xmsAgent: xmsAgent(%d) ERROR: Couldnt accept incoming connection %z	Failed to open connection requested connection	Check network configuration and status	XMS
372112	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Internal consistency error: non-ABORT result %d from incoming transaction	A delivery report transaction received an unexpected result.	Internal error has occurred. Contact Oracle support.	XMS
372113	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: Internal Delivery Report path not found.	Unable to determine a default inbound path for MMX generated delivery receipts.	Check path and adapter configuration. Contact support.	XMS
372114	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: Config: singleShotDeliveryReports = %z	Not a fault	The singleShotDeliveryReports value is now the specified value	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372115	NOTICE	DEF123xmsTrigger: xmsTrigger(%d) NOTICE: Config: internalDRTIMEOUT = %z	Not a fault	The internalDRTIMEOUT value is now the specified value	XMS
372116	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: Circular delivery report processing detected - not sending	xmsTrigger received a delivery report with a flag set requesting another delivery report. This can cause a circular logic loop, so the application will not generate a new delivery report.	Change the configuration, particularly control plans, to not set the Delivery Receipt Requested flag when processing a delivery report	XMS
372117	WARNING	%s %d: xmsTrigger(%d) WARNING: Internal Consistency Error: Cant submit delivery report via MAP: %s %d.	The routing scheme is configured to route a delivery report to an SMSC via the MAP adapter, which is not supported	Use a separate Submit routing rule for delivery reports, that doesnt use a MAP path	XMS
372118	WARNING	%s %d: slee_acs(%d) WARNING: Unable to create SRI-SM, due to no SCCP Originating Address for MSC	No SCCP Originating Address was supplied for MSC	Check node configuration in eserv.config	XMS
372119	WARNING	%s %d: slee_acs(%d) WARNING: Couldnt parse modified address: %s %d	The originating or destination address profile fields had an address string in an invalid format	Check node configuration in the control plan	XMS
372120	WARNING	%s %d: slee_acs(%d) WARNING: ADP: Cant parse destination address: %s %d	The pending termination number had an address string in an invalid format	Check the control plan	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372121	CRITICAL	DEF123xmsTrigger: xmsTrigger(%d) CRITICAL: Cannot install SIGUSR2 signal handler - %z [%d].	For some reason, xmsTrigger is unable to install the SIGUSR2 signal handler.	Restart xmsTrigger. If problem persists, consult Support.	XMS
372122	WARNING	DEF123xmsStore: xmsStore(%d) WARNING: Failed to open XMS.xmsTrigger section in config file, using defaults.	Configuration file warning	Refer to UNIX/platform expert first	XMS
372123	ERROR	DEF123mmsproxy: mmsproxy(%d) ERROR: Config: CONTACT SUPPORT: No valid secure section	Misconfiguration	Check config file secure section is valid. Contact support.	XMS
372124	ERROR	DEF123mmsrelay: mmsrelay(%d) ERROR: Config: CONTACT SUPPORT: No valid secure section	Misconfiguration	Check config file secure section is valid. Contact support.	XMS
372125	ERROR	DEF123xmsTrigger: xmsTrigger(%d) ERROR: The Originating Address %z is alphanumeric. It must be all digits.	xmsTrigger tried to construct a Telephone Number from a non-numeric field	Contact eSG Support	XMS
372126	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: xmsiMap: relayTranslationType must be between -2 and 255.	The relayTranslationType has an incorrect value in eserv.config.	Correct the value of relayTranslationType in eserv.config.	XMS
372127	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: xmsiMap: relayGlobalTitleType must be between 1 and 4 or be - 1.	The relayGlobalTitleType has an incorrect value in eserv.config.	Correct the value of relayGlobalTitleType in eserv.config.	XMS

Alarm	Severity	Text	Cause	Resolution	Service
372128	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: xmsiMap: relayNatureOfAddress must be between 0 and 127 or be -1.	The relayNatureOfAddress has an incorrect value in eserv.config.	Correct the value of relayNatureOfAddress in eserv.config.	XMS
372129	ERROR	%s %d: xmsTrigger(%d) ERROR: Config: xmsiMap: relaySSN must be between 0 and 255 or be -1.	The relaySSN has an incorrect value in eserv.config.	Correct the value of relaySSN in eserv.config.	XMS
372130	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: relayGlobalTitleType = %d	New configuration loaded.	No action required.	XMS
372131	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: relayTranslationType = %d	New configuration loaded.	No action required.	XMS
372132	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: relayNatureOfAddress = %d	New configuration loaded.	No action required.	XMS
372133	NOTICE	%s %d: xmsTrigger(%d) NOTICE: Config: xmsiMap: relaySSN = %d	New configuration loaded.	No action required.	XMS
372134	WARNING	DEF123xmsTrigger: xmsTrigger(%d) WARNING: Configuration warning: Plugin %z , path %z has no connections.	The path named in the error message does not have any connections configured for it.	A path with no connections is useless. This warning is simply to alert those responsible for the MMX configuration that the routing scheme contains a useless path.	XMS