

Oracle® Communications Network Charging and Control

Mobile Application Part (MAP) Protocol Implementation Conformance Statement



Release 15.2

January 2026



Copyright

Copyright © 2026, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software" or "commercial computer software documentation" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

About This Document	v
Document Conventions	vi
Chapter 1	
Messaging Manager and ETSI Document Versions.....	1
Overview.....	1
Messaging Manager	1
ETSI.....	1
Chapter 2	
Compliance Statement.....	3
Overview.....	3
ETSI References	3
Specification Sections 7 through 11	3
Short Message Service Management Services (12).....	4
Specification sections 13 and 13A	15

About This Document

Scope

This document defines the extent to which Messaging Manager complies with the Mobile Application Part of ETSI's GSM specification.

Audience

This document is intended to be read by Oracle staff. It has been prepared on the assumption that the reader is familiar with Messaging Manager as well as the short message capabilities of the GSM specification.

Document Conventions

Typographical Conventions

The following terms and typographical conventions are used in the Oracle Communications Network Charging and Control (NCC) documentation.

Formatting Convention	Type of Information
Special Bold	Items you must select, such as names of tabs. Names of database tables and fields.
<i>Italics</i>	Name of a document, chapter, topic or other publication. Emphasis within text.
Button	The name of a button to click or a key to press. Example: To close the window, either click Close , or press Esc .
Key+Key	Key combinations for which the user must press and hold down one key and then press another. Example: Ctrl+P or Alt+F4 .
Monospace	Examples of code or standard output.
Monospace Bold	Text that you must enter.
<i>variable</i>	Used to indicate variables or text that should be replaced with an actual value.
menu option > menu option >	Used to indicate the cascading menu option to be selected. Example: Operator Functions > Report Functions
hypertext link	Used to indicate a hypertext link.

Specialized terms and acronyms are defined in the glossary at the end of this guide.

Messaging Manager and ETSI Document Versions

Overview

Introduction

This chapter defines the version of Messaging Manager and the ETSI document against which it is compared.

In this chapter

This chapter contains the following topics.

Messaging Manager	1
ETSI.....	1

Messaging Manager

MMX implementation

This document states compliance for Messaging Manager version 3.1.1. The environment for this version of Messaging Manager is defined below:

- Target platform
 - Platform - SPARC Solaris
 - Operating system - SunOS 5.9
 - Database - Oracle 9.2.05
- Build environment
 - Compiler - GNU GCC 3.2.3
 - Binutils - GNU binutils 2.14
- Oracle packages
 - SMS 3.0
 - ACS 2.4
 - SLEE 3.2
 - Hughes IF 3.4.26

ETSI

ETSI documents

This statement of compliance refers to the two European Telecommunications Standards Institute (ETSI) documents listed below.

- *Digital cellular telecommunications system (Phase 2+); Mobile Application part (MAP) specification (GSM 09.02 version 7.5.0 Release 1998).*

Note: For the purpose of this document, *Digital cellular telecommunications system (Phase 2+); Mobile Application part (MAP) specification (GSM 09.02 version 7.5.0 Release 1998)* will be referred to as *GSM 09.02*.

- *Digital cellular telecommunications system (Phase 2+); Technical realization of the Short Message Service (SMS) Point-to-Point (PP), (3GPP TS 03.40 version 7.5.0 Release 1998)*.

Note: For the purpose of this document, *Digital cellular telecommunications system (Phase 2+); Technical realization of the Short Message Service (SMS) Point-to-Point (PP), (3GPP TS 03.40 version 7.5.0 Release 1998)* will be referred to as *TS 03.40*.

Chapter 2

Compliance Statement

Overview

Introduction

This chapter identifies which MAP services are supported by Messaging Manager.

Given the specialised nature of Messaging Manager, and for the sake of brevity, only compliance with the Short Messaging Services is described in detail.

In this chapter

This chapter contains the following topics.

ETSI References	3
Specification Sections 7 through 11	3
Short Message Service Management Services (12).....	4
Specification sections 13 and 13A	15

ETSI References

Convention

- Where possible the relevant clause number of *GSM 09.02* is included in brackets at the end of each topic title.
- In some cases *GSM 09.02* refers to clauses of *TS 04.03*. Where this happens, reference is made to *TS 04.03* in the compliance statement.

Specification Sections 7 through 11

Introduction

Statements of compliance with sections 7 through 11 of *GSM 09.02* follow.

Common MAP services

Messaging Manager complies.

Where used by Messaging Manager, map services are correctly mapped onto TCAP primitives.

Mobility services (8)

Messaging Manager does not comply.

Operation and maintenance services (9)

Messaging Manager does not comply.

Call handling services (10)

Messaging Manager does not comply.

Supplementary services related services (11)

Messaging Manager does not comply.

Short Message Service Management Services (12)

Introduction

Statements of compliance for clauses of section 12 of *GSM 09.02* follow.

MAP-SEND-ROUTING-INFO-FOR-SM service (12.1)

Messaging Manager complies.

Messaging Manager supports the receipt of these messages and Messaging Manager Navigator supports the construction of them.

The MAP-SEND-ROUTING-INFO-FOR-SM service takes 14 parameters. These are covered under the following headings.

- Invoke Id
- MSISDN
- SM-RP-PRI
- Service Centre Address
- SM-RP-MTI
- SM-RP-SMEA
- GPRS Support Indicator
- IMSI
- Network Node Number
- LMSI
- GPRS Node Indicator
- Additional Number
- User error
- Provider error

Invoke Id (7.6.1.1)

Messaging Manager complies.

Invoke Id is always zero for messages sent from Messaging Manager Navigator. Messaging Manager Navigator never sends two messages in the same dialogue.

MS ISDN (7.6.2.17)

Messaging Manager complies.

MS ISDN is mapped to the generic message's destination address.

SM-RP-PRI (7.6.8.5)

Messaging Manager complies.

SM-RP-PRI maps to the generic message's priority indicator with all but Normal mapping set to *true*.

Note: Messaging Manager Navigator caches HLR responses independently of this variable. If the cell phone's switched-off status is ignored, a high priority request may receive the same response as a previous low priority request.

Service centre address (7.6.2.27)

Messaging Manager complies.

- For inbound SRISMs, the service centre address is correctly proxied.
- For messages generated by Messaging Manager, the service centre address identifies the message centre associated with the inbound path.
- For messages constructed by ACS (Messaging Manager Navigator query nodes), this field is blank.

SM-RP-MTI (7.6.8.16)

Messaging Manager does not comply.

SM-RP-MTI is ignored by MTX and is not proxied to the HLR.

SM-RP-SMEA (7.6.8.17)

Messaging Manager does not comply.

SM-RP-SMEA is ignored by Messaging Manager and is not proxied to the HLR.

GPRS Support Indicator (7.6.8.15)

Messaging Manager complies.

- Received values are stored internally as the GprsSupported flag and correctly proxied to the HLR.
- For Messaging Manager generated messages, the configuration value from XMS.MAP.gprsSupport is used. All values are mapped to *true* except 'unsupported'.
- For ACS generated messages, the configuration value from RIMS.ChassisActions.RimsChassisAction.allowGPRS is used.

IMSI (7.6.2.1)

Messaging Manager complies.

IMSI is stored in MapTransaction's imsi variable. It is not stored in GenericMessage.

Network Node number (7.6.2.43)

Messaging Manager complies.

It is possible for the Network Node number to be the SGSN number in an HLR response.

LMSI (7.6.2.16)

Messaging Manager does not comply.

LMSI is the value returned by RIMS and stored in MapTransaction's lmsi variable. However Messaging Manager allows this lmsi to be sent to the SGSN and thus violates clause 7.6.2.16 of *TS 03.40*.

GPRS Node Indicator (7.6.8.14)

Messaging Manager complies.

Messaging Manager Navigator examines this field to determine the SGSN and Network Node numbers. The GPRS Node Indicator is not returned by Messaging Manager Navigator to Messaging Manager but Messaging Manager correctly constructs it for SRSIM responses.

Additional number (7.6.2.46)

Messaging Manager complies.

User error (7.6.1.4)

Messaging Manager does not comply.

On error, this field is not examined or acted upon.

Provider error (7.6.1.3)

Messaging Manager does not comply.

MAP-MO-FORWARD-SHORT-MESSAGE service (12.2)

Messaging Manager complies.

Messaging Manager supports receipt and construction of these messages.

The MAP-MO-FORWARD-SHORT-MESSAGE service takes seven parameters. These are covered under the following headings.

- Invoke Id
- SM RP DA
- SM RP OA
- SM RP UI
- IMSI
- User error
- Provider error

Invoke Id (7.6.1.1)

Messaging Manager complies.

SM-RP-DA (7.6.8.1)

Messaging Manager complies.

SM-RP-DA is stored in GenericSM's sMSCAddress field. For outgoing messages this field is populated from a lookup of the originating and destination addresses hashed together into a map of all known MSCs.

SM-RP-OA (7.6.8.2)

Messaging Manager complies.

SM-RP-OA is stored in GenericSM's originatingAddress field.

SM-RP-UI (7.6.8.4)

Messaging Manager complies.

The following three PDU-specific fields affect SM-RP-UI.

- SMS-DELIVER-REPORT
- SMS-SUBMIT
- SMS-COMMAND

SMS-DELIVER-REPORT (9.2.2.1a)

Messaging Manager does not comply.

SMS-DELIVER-REPORT is defined in *TS 03.40*.

Messaging Manager assumes that all received MO-Forward-SMs contain an SMS-Submit as the RP UI. SMS-Deliver-Report PDUs are never constructed by Messaging Manager.

SMS-SUBMIT (9.2.2.2)

SMS-SUBMIT is defined in *TS 03.40*.

A compliance statement for each element of SMS-SUBMIT is listed below.

Map field	GenericSM location	Compliance statement
TP-Message-Type-Indicator		Messaging Manager complies. TP-Message-Type-Indicator is not stored in Messaging Manager. All MO-Forward-SMs are assumed to be SMS-Submits.
TP-Reject-Duplicates	RejectDuplicates	Messaging Manager complies.
TP-Validity-Period-Format	ValidityPeriod	Messaging Manager complies.
TP-Reply-Path	ProvideReplyPath	Messaging Manager complies.
TP-User-Data-Header-Indicator	UserDataHeaderPresent	Messaging Manager complies.
TP-Status-Report-Request	StatusReportRequested	Messaging Manager complies. TP-Status-Report-Request turns on the <code>smeRequested</code> bit of <code>statusReportRequested</code> .
TP-Message-Reference	MessageReference	Messaging Manager complies.
TP-Destination-Address	destinationAddress	Messaging Manager complies.
TP-Protocol-Identifier	ProtocolIdentifier	Messaging Manager complies. Translated to Messaging Manager encoding via the <code>protocolIdMap</code> configuration option.
TP-Data-Coding-Scheme	MessageWaitingGroup, MessageWaitingType, MessageWaitingIndicator, currentAlphabet, MessageClass	Messaging Manager complies. The DCS itself is not stored internally. Its components are stored as separate variables.
TP-Validity-Period	ValidityPeriod	Messaging Manager complies.

Map field	GenericSM location	Compliance statement
TP-User-Data-Length	UserDataLength, userDataHeaderLength	Messaging Manager complies.
TP-User-Data	UserData, userDataHeader	Messaging Manager complies.

SMS-COMMAND (9.2.2.4)

Messaging Manager does not comply.

SMS-COMMAND is defined in *TS 03.40*.

Messaging Manager assumes that all received MO-Forward-SMs contain an SMS-Submit as the RP UI. SMS-Command PDUs are never constructed by Messaging Manager.

IMSI (7.6.2.1)

Messaging Manager complies.

For MAP version 3, the incoming IMSI is stored in OriginatingImsi and sent to Messaging Manager Navigator where it updates the cache. If the originating imsi is present, outgoing messages have the originating imsi set.

User error (7.6.1.4)

Messaging Manager does not comply.

On receipt of a user error, Messaging Manager translates the error using the forwardSmErrorMap configuration option. The result is then stored in GenericSMResult's resultCode variable.

Provider error (7.6.1.3)

Messaging Manager does not comply.

Messaging Manager treats receipt of a provider error as a transientFailure.

MAP-REPORT-SM-DELIVERY-STATUS service (12.3)

Messaging Manager does not comply.

Messaging Manager cannot handle the receipt or construction of a MAP-REPORT-SM-DELIVERY-STATUS message.

MAP-READY-FOR-SM service (12.4)

Messaging Manager does not comply.

Messaging Manager cannot handle the receipt or construction of a MAP-READY-FOR-SM message.

MAP-ALERT-SERVICE-CENTRE service (12.5)

Messaging Manager does not comply.

Messaging Manager can handle receipt of MAP-ALERT-SERVICE-CENTRE messages and uses such messages to update the Messaging Manager Navigator cache. However Messaging Manager does not pass the message on to the originating SMSC or attempt to redeliver the message.

In the context of the service provided by MAP-ALERT-SERVICE-CENTRE, Messaging Manager's failure to comply does not matter. A failed FDA should be followed by an attempted MO delivery. The message is therefore stored at an SMSC and the SMSC receives an alert-service-centre message. It is also possible to configure Messaging Manager such that alert-service-centre messages are sent directly from the HLR to the originating SMSC.

MAP-ALERT-SERVICE-CENTRE takes five parameters. These are covered under the following headings.

- Invoke Id
- MSIsdn-Alert
- Service Centre Address
- User error
- Provider error

Invoke Id (7.6.1.1)

Messaging Manager complies.

MSIsdn-Alert (7.6.2.29)

Messaging Manager complies.

The value of MSIsdn-Alert is invalidated in the Messaging Manager Navigator cache.

Service centre address (7.6.2.27)

Messaging Manager does not comply.

The service centre address is ignored by Messaging Manager Navigator.

User error (7.6.1.4)

Messaging Manager does not comply.

Messaging Manager never replies with an error — only with an empty TCAP_END.

Provider error (7.6.1.3)

Messaging Manager does not comply.

MAP-INFORM-SERVICE-CENTRE service (12.6)

Messaging Manager does not comply.

Messaging Manager cannot handle receipt of the MAP-INFORM-SERVICE-CENTRE message.

Messaging Manager Navigator can use this message to update its cache. However Messaging Manager Navigator does not pass the message on to the originating SMSC nor does it attempt to deliver the message. Messaging Manager Navigator only examines the mw-Status flag, with a transientFailure being "mnrf or mcef or (mnrg & GPRS supported)".

All other values set the cache element status to *successful*.

MAP-SEND-INFO-FOR-MT-SMS service (12.7)

Messaging Manager does not comply.

Messaging Manager cannot handle the receipt or construction of the MAP-SEND-INFO-FOR-MT-SMS message.

MAP-SEND-INFO-FOR-MO-SMS service (12.8)

Messaging Manager does not comply.

Messaging Manager cannot handle the receipt or construction of the MAP-SEND-INFO-FOR-MO-SMS message.

MAP-MT-FORWARD-SHORT-MESSAGE service (12.9)

Messaging Manager supports receipt and construction of these messages.

The MAP-MT-FORWARD-SHORT-MESSAGE service takes seven parameters. A compliance statement for each parameter is made under one of the following headings.

- Invoke Id
- SM RP DA
- SM RP OA
- SM RP UI
- More Messages To Send
- User error
- Provider error

Invoke Id (7.6.1.1)

Messaging Manager complies.

SM-RP-DA (7.6.8.1)

Messaging Manager does not comply.

SM-RP-DA is stored in either of the GenericSM's destinationImsi or destinationLmsi fields.

Messaging Manager allows an LMSI to be sent to the SGSN. This functionality violates clause 7.6.2.1.6 of *GSM 09.02*.

SM-RP-OA (7.6.8.2)

Messaging Manager complies.

SM-RP-OA is stored in GenericSM's serviceCentreAddress field. For FDA-constructed messages, this field is obtained from GenericSM's originatingAddress field.

SM-RP-UI (7.6.8.4)

Messaging Manager complies.

The compliance of individual PDU-specific fields is listed under the following three headings.

- SMS-DELIVER
- SMS-SUBMIT-REPORT
- SMS-STATUS-REPORT

SMS-DELIVER (9.2.2.1)

SMS-DELIVER is defined in *TS 03.40*.

Compliance for individual elements of SMS-DELIVER is listed below.

Map field	GenericSM location	Compliance statement
TP-Message-Type-Indicator		Messaging Manager complies.
TP-More-Messages-to-Send		<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> • Messaging Manager complies only if it is Messaging Manager that generates TP-More-Messages-to-Send. • Always set to "no more messages to send". • TP-More-Messages-to-Send is ignored in inbound messages. The non SM-RP-UI sendMoreMessages parameter is used instead. See <i>More Messages To Send</i> (on page 14).
TP-Reply-Path	ProvideReplyPath	<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> • Messaging Manager complies only if it is Messaging Manager that generates TP-Reply-Path. • Always set TP-Reply-Path to <i>false</i>. • Saved in GenericSM from inbound message. <p>Note: TP-Reply-Path was not part of the MAP phase 1 specification.</p>
TP-User-Data-Header-Indicator	UserDataHeaderPresent	<p>Messaging Manager complies.</p> <p>From an inbound message, TP-User-Data-Header-Indicator is saved in GenericSM.</p> <p>Note: TP-User-Data-Header-Indicator was not part of the MAP phase 1 specification.</p>
TP-Status-Report-Indication	StatusReportRequested	<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> • Messaging Manager uses only the <i>smeRequested</i> bit. • From an inbound message, TP-Status-Report-Indication is saved in GenericSM. <p>Note: TP-Status-Report-Indication was not part of the MAP phase 1 specification.</p>
TP-Originating-Address	OriginatingAddress	<p>Messaging Manager complies.</p> <p>From an inbound message, TP-Originating-Address is saved in GenericSM.</p>
TP-Protocol-Identifier	ProtocolIdentifier	<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> • A configurable mapping from the incoming TP-Protocol-Identifier may have occurred.

Map field	GenericSM location	Compliance statement
		<ul style="list-style-type: none"> From an inbound message, TP-Protocol-Identifier is saved in GenericSM.
TP-Data-Coding-Scheme	MessageWaitingGroup, MessageWaitingType, MessageWaitingIndicator, currentAlphabet, MessageClass	<p>Messaging Manager complies.</p> <p>The DCS itself is not stored internally. Its components are stored as separate variables.</p>
TP-Service-Centre-Time-Stamp		<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> userTimezone's local time is used. TP-Service-Centre-Time-Stamp is ignored in inbound messages.
TP-User-Data-Length	UserDataLength, userDataHeaderlength	<p>Messaging Manager complies.</p> <p>From an inbound message, TP-User-Data-Length is saved in GenericSM.</p>
TP-User-Data	UserData, userDataHeader	<p>Messaging Manager complies.</p> <p>From an inbound message, TP-User-Data is saved in GenericSM.</p>

SMS-SUBMIT-REPORT (9.2.2.2a)

Messaging Manager does not comply.

SMS-SUBMIT-REPORT is defined in *TS 03.40*.

Messaging Manager cannot construct or receive these messages.

SMS-STATUS-REPORT (9.2.2.3)

SMS-STATUS-REPORT is defined in *TS 03.40*.

Compliance for individual elements of SMS-STATUS-REPORT is listed below.

Map field	GenericSM location	Compliance statement
TP-Message-Type-Indicator		Messaging Manager complies.
TP-User-Data-Header-Indication		<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> Messaging Manager complies only if it is Messaging Manager that generates TP-User-Data-Header-Indication. TP-User-Data-Header-Indication is hard-coded to <i>false</i>. TP-User-Data-Header-Indication is ignored in inbound messages.
TP-More-Messages-to-Send		<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> Messaging Manager complies only if it is Messaging Manager that generates TP-More-Messages-to-Send.

Map field	GenericSM location	Compliance statement
		<ul style="list-style-type: none"> TP-More-Messages-to-Send is always set to "no more messages to send". TP-More-Messages-to-Send is ignored in inbound messages.
TP-Status-Report-Qualifier		<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> Messaging Manager complies only if it is Messaging Manager that generates TP-Status-Report-Qualifier. TP-Status-Report-Qualifier is hard-coded to 0 — SmsCommands are not supported. TP-Status-Report-Qualifier is ignored in inbound messages. <p>Note: TP-Status-Report-Qualifier was not part of the MAP specification prior to phase 2+.</p>
TP-Message-Reference	MessageReference	<p>Messaging Manager complies.</p> <p>From inbound messages, TP-Message-Reference is saved in GenericSM.</p>
TP-Recipient-Address	OriginatingAddress	<p>Messaging Manager complies.</p> <p>From inbound messages, TP-Recipient-Address is saved in GenericSM.</p>
TP-Service-Centre-Time-Stamp	ServiceCentre-TimeStamp	<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> If TP-Service-Centre-Time-Stamp is null, userTimezone's local time is used. TP-Service-Centre-Time-Stamp is ignored in inbound messages.
TP-Discharge-Time	ServiceCentreTimestamp	<p>Messaging Manager does not comply.</p> <ul style="list-style-type: none"> Messaging Manager uses the SCTS time. TP-Discharge-Time is ignored in inbound messages.
TP-Status	DeliverySucceeded	<p>Messaging Manager does not comply.</p> <ul style="list-style-type: none"> If deliverySucceeded is <i>false</i>, TP-Status is set to the configured deliveryFailureStatusCode. If deliverySucceeded is <i>true</i>, TP-Status is set to 0. In inbound messages, if TP-Status = 0, deliverySucceeded is set to <i>true</i>.

Map field	GenericSM location	Compliance statement
		<ul style="list-style-type: none"> In inbound messages, if TP-Status ≠ 0, deliverySucceeded is set to <i>false</i>.
TP-Parameter-Indicator		<p>Messaging Manager complies.</p> <ul style="list-style-type: none"> No optional parameters are ever included. Ignored in inbound messages. <p>Note: TP-Parameter-Indicator was not part of the MAP specification prior to phase 2+.</p>
TP-Protocol-Identifier		<p>Messaging Manager does not comply.</p> <ul style="list-style-type: none"> TP-Protocol-Identifier is not set by Messaging Manager. TP-Protocol-Identifier is ignored in inbound messages. <p>Note: TP-Parameter-Indicator was not part of the MAP specification prior to phase 2+.</p>
TP-Data-Coding-Scheme		<p>Messaging Manager does not comply.</p> <p>TP-Data-Coding-Scheme is not set by Messaging Manager.</p> <p>TP-Data-Coding-Scheme is ignored in inbound messages.</p> <p>Note: TP-Data-Coding-Scheme was not part of the MAP specification prior to phase 2+.</p>
TP-User-Data-Length		<p>Messaging Manager does not comply.</p> <ul style="list-style-type: none"> TP-User-Data-Length is not set by Messaging Manager. TP-User-Data-Length is ignored in inbound messages. <p>Note: TP-User-Data-Length was not part of the MAP specification prior to phase 2+.</p>
TP-User-Data		<p>Messaging Manager does not comply.</p> <ul style="list-style-type: none"> TP-User-Data is not set by Messaging Manager. TP-User-Data is ignored in inbound messages. <p>Note: TP-User-Data was not part of the MAP specification prior to phase 2+.</p>

More Messages To Send (7.6.8.7)

Messaging Manager complies.

- For inbound messages, Messaging Manager examines More Messages To Send and enacts the correct response.
- On outbound messages the more message flag is never set. Messaging Manager separates messages into individual dialogues.

User error (7.6.1.4)

Messaging Manager does not comply.

On receipt, Messaging Manager translates user errors using the forwardSmErrorMap configuration. The result is stored in GenericSMResult's resultCode variable.

Provider error (7.6.1.3)

Messaging Manager does not comply.

Specification sections 13 and 13A

Introduction

Statements of compliance for clauses of Sections 13 and 13A of *GSM 09.02* follow.

Network-Requested PDP Context Activation services (13)

Messaging Manager does not comply.

Messaging Manager treats a Network-Requested PDP Context Activation message as a transientFailure.

Location Service Management Services (13A)

Messaging Manager does not comply.