

Oracle® Communications Network Charging and Control

Service Management System Alarms Guide



Release 15.2

January 2026

ORACLE®

Copyright

Copyright © 2026, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software" or "commercial computer software documentation" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle, Java, and MySQL are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Alarm Topic Description 1

Service Management System Alarms 3

Alarm Topic Description

Alarm Generation

Alarms on each configured node are written to the syslog and are then captured by the smsAlarmDaemon for entry in the SMF database.

For management of these alarms, see *Service Management System Technical Guide*.

Severity Levels

This table describes the alarm severity levels.

Level	Abbreviation	Description
Critical	C	These alarms are raised when the application has encountered an error indicating that the system is unable to function.
Error	E	These alarms indicate the application has encountered a serious problem completing a necessary task and could not complete the task.
Warning	W	Warnings are raised to indicate the application encountered a problem completing a non-mission critical task.
Notice	N	Notices are raised to indicate that the application has completed a task successfully.

Alarm Format

Alarms usually follow this format:

```
Mon DD 24:MM:SS hostname process name: [ID alarmID user.severity] process(PID)
SEVERITY: Alarm text with possible variables
```

Where:

Variable	Description
Mon DD	Month and date the alarm was logged.
24:MM:SS	Time the alarm was logged in 24 hour format.
hostname	Name of the machine on which the alarm was generated.
process name	Name of the process which logged the alarm.
alarmID	ID number of the alarm.
severity	Alarm severity.
process	Name of the process which logged the alarm.
PID	Process ID of the process which logged the alarm.
SEVERITY	Alarm severity.
Alarm text	Alarm text. This may include variables such as node number. Note: In some cases, the entire alarm text is generated from variables.

Note: Some alarms from some subsystems may have a different format.

Example: This text shows an smsMaster alarm about pending update queues.

```
Mar 30 13:34:54 prodsmpl smsMaster: [ID 953149 user.warning] smsMaster(17833)
WARNING: Pending queue now above 15 (Worst Node 317)
```

Alarm Text and Variables

The %d and %s symbols represent variables within the alarm text. These values are generated by the subsystem and added to the message when the alarm is raised.

Usually the %d is a number and the %s is text in the context of the message to complete the alarm message. Occasionally other % symbols are also used (for example, %u) for different variables.

Further Information

For more information about:

- The SMS Alarms subsystem, see *Service Management System Technical Guide*
- Creating and maintaining the SMS Alarm Relay rule set, see *Service Management System User's Guide*

Service Management System Alarms

Alarm	Severity	Text	Cause	Resolution	Service
280000	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280001	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280002	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280003	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280004	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280005	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280006	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280007	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280008	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280009	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280010	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
280011	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Replication system error	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280012	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280013	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280014	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: bind-Problem binding socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280015	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: bind-Problem listening on socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280016	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: compareResyncReceive has not reset yet; trying again	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280017	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280018	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Connection message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280019	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Connection type `%s %d not implemented yet	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280020	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280021	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280022	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280023	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: ioctl-Unable to set TCP socket non-blocking	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280024	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280025	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280026	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: No Master Found - suggests a replication config error	Replication system error	Refer to UNIX/application expert first. Check the following 1) is the smsMaster process running on the SMP? 2) is the SMP machine available? 3) are there any related smsMaster errors shown in the log on the SMP? 4) does the replication.config file still exist on the SMP? 5) Has a resync been started - check the updateLoader log for details. 6) Finally contact support.	SMS
280027	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: read-Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280028	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: read-Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
280029	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: read-Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280030	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280031	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
280032	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280033	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280034	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280035	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280036	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Unable to find the program %s %d.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280037	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280038	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280039	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
280040	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280041	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280042	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Write to fd %d only sent %d bytes not %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280043	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280044	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280045	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280046	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280047	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: bind-Problem binding socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280048	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: bind-Problem listening on socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280049	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280050	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280051	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: read-Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280052	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280053	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280054	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280055	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280056	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280057	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280058	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: read-Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
280059	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: read-Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS
280060	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280061	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280062	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280063	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280064	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280065	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280066	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
280067	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Replication config file `%s %d` not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280068	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: system-Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) First time that the node in question has been replicated to? 2) Target machine available - on the network for FTP access? 3) smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS
280069	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS
280070	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Error opening Resync File ` %s %d;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280071	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
280072	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Update Loader %d at `%s %d:%d also connecting from `%s %d:%d	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280073	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280074	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280075	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280076	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Master Controller `%s %d` process started (node %d)	Process has started successfully.	No resolution.	SMS
280077	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280078	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Update Requester `%s %d` process registered (node %d)	Information only	No resolution.	SMS
280079	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280080	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280081	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280082	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280083	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: system-Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) First time that the node in question has been replicated to? 2) Target machine available - on the network for FTP access? 3) smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 5) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280084	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280085	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280086	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
280087	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280088	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connection to Inferior Master lost prematurely	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280089	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connection to Superior Master lost prematurely	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280090	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Consistency check inconsistent config with table `%z	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280091	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Error comparing database row	Replication system error	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 5) If problem persists then contact support.	SMS
280092	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Error connecting to database as user `%s %d	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. 4) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280093	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Error opening Resync File `%s 123ZZZ	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280094	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Error opening Resync/Comparison connection to %s %d.%d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. If problem persists then contact support.	SMS
280095	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280096	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Lost connection to slave at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280097	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1) Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2) Check the smsMaster and the updateLoader logs for further messages. 3) Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4) Contact support for further information.	SMS
280098	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Replication config file `%s %d` not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280099	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Slave lost connection to current master at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280100	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280101	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS
280102	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280103	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Unrecognised consistency id %d from loader %d	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280104	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Update Loader %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280105	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280106	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS
280107	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Write error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280108	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280109	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
280110	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: gethostbyname-Problem getting host `%s %d	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280111	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280112	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
280113	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280114	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280115	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR logic=%d oracompareResyncRecv.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280116	CRITICAL	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280117	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS
280118	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
280119	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280120	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280121	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280122	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280123	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) First time that the node in question has been replicated to? 2) Target machine available - on the network for FTP access? 3) smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS
280124	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) First time that the node in question has been replicated to? 2) Target machine available - on the network for FTP access? 3) smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280125	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support.	SMS
280126	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280127	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280128	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: oraRWRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280129	ERROR	DEF123compareResyncRecv: compareResyncRecv(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support.	SMS
280130	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280131	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280132	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280133	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: %s %d replication process started (node %d)	Process has started successfully.	No resolution.	SMS
280134	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
280135	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Finished Database Comparison	Process has competed successfully.	No resolution.	SMS
280136	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280137	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280138	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Master Controller `%s %d` process started (node %d)	Process has started successfully.	No resolution.	SMS
280139	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280140	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280141	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Node resync process completed	Resyncing has completed for this node.	No resolution.	SMS
280142	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Pending queue now below %d	Internal communications error.	No resolution.	SMS
280143	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Reached master node %d at `%s %d	Client successfully made a connection.	No resolution.	SMS
280144	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Resync completed with errors - node partially out of sync	Replication system error	Refer to ORACLE/application expert first. A data error has prevented certain rows from successfully updating. 1) Check the smsMaster log on the SMP and also the updateLoader logs for further details of the rows in question. 2) Further detail can be obtained by manually attempting the failed updates using SQL + . 3) Contact support for further information.	SMS
280145	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Resync started pass %d	Resync pass has started on the SCP	No resolution.	SMS
280146	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Resync successful - node back in sync	Resync pass has completed successfully on the SCP	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280147	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
280148	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Starting Database Comparison	Process has started successfully.	No resolution.	SMS
280149	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Update Requester `%s %d process registered (node %d)	Information only	No resolution.	SMS
280150	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280151	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280152	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280153	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE parse=%d oracompareResyncRecv.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280154	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280155	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
280156	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280157	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280158	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280159	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280160	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update (key values `%s %d,%s %d,%s %d) not in any group of table `%s %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280161	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Consistency check failed (reason %z);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280162	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Problem opening consistency report file `%s %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280163	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280164	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280165	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280166	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280167	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280168	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280169	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280170	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280171	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280172	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280173	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280174	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannot open report file `%s %d`	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280175	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280176	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280177	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280178	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280179	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Already comparing with master atZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280180	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280181	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280182	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280183	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Cannt find node at %s %d.%d to return info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1) Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2) Check the smsMaster and the updateLoader logs for further related error messages. 3) Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4) Finally contact support.	SMS
280184	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
280185	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Consistency check failed (reason %z)	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280186	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Error during merge recomit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280187	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280188	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280189	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1) Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2) Check the smsMaster and the updateLoader logs for further related error messages. 3) Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4) Finally contact support.	SMS
280190	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280191	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280192	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280193	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280194	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Pending queue now above %d	Internal communications error.	Assuming basic UNIX skills (Check the following). 1) Are the updateLoaders still connected to the smsMaster? 2) Are the machines still available on the network? 3) The message means that updates that are to be replicated to a given node are building up on the smsMaster faster than the target nodes updateLoader can clear them - as long as they stay connected the queue should clear eventually 4) If problem persists then contact support.	SMS
280195	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Problem opening consistency report file `%s 123ZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280196	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Process %d returned status 0xZZZ	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280197	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280198	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280199	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280200	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update (key values `%s %d,%s %d,%s %d) not in any group of table `%s %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280201	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280202	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280203	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280204	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING logic=%d oracompareResyncRecv.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280205	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280206	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Oracle unavailable after %d seconds with error: Error while trying to retrieve text for error ORA-%d	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280207	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280208	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280209	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280210	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280211	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280212	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING: Updates will be lost onZZZ	Replication system error	Refer to ORACLE/application expert first. Error suggests a communication or configuration fault between the SMP and one of the replication nodes. Check the error logs for the smsMaster and the updateLoader for further details. Contact support for further assistance.	SMS
280213	CRITICAL	DEF123repConfigWrite: repConfigWrite(%d) ERROR: hcreate=%d repConfigWrite.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280214	ERROR	DEF123repConfigWrite: repConfigWrite(%d) ERROR: Two programs generating config file.	Internal software error.	No resolution. If problem persists then contact support.	SMS
280215	CRITICAL	DEF123repConfigWrite: repConfigWrite(%d) WARNING: strdup out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280216	ERROR	DEF123repConfigWriter: repConfigWriter(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280217	ERROR	DEF123repConfigWriter: repConfigWriter(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
280218	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280219	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280220	CRITICAL	DEF123repConfigWriter: repConfigWriter(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280221	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280222	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
280223	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280224	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280225	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280226	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280227	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280228	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280229	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280230	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR: oraRWRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280231	ERROR	DEF123repConfigWriter: repConfigWriter(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280232	NOTICE	DEF123repConfigWriter: repConfigWriter(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280233	NOTICE	DEF123repConfigWriter: repConfigWriter(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280234	NOTICE	DEF123repConfigWriter: repConfigWriter(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280235	NOTICE	DEF123repConfigWriter: repConfigWriter(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280236	NOTICE	DEF123repConfigWriter: repConfigWriter(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280237	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280238	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280239	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280240	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280241	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280242	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280243	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280244	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING: Updates will be lost onZZZ	Replication system error	Refer to ORACLE/application expert first. Error suggests a communication or configuration fault between the SMP and one of the replication nodes. Check the error logs for the smsMaster and the updateLoader for further details. Contact support for further assistance.	SMS
280245	WARNING	DEF123repConfigWriter: repConfigWriter(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280246	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280247	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280248	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280249	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280250	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280251	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280252	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280253	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280254	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280255	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280256	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280257	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
280258	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Replication system error	No resolution. If problem persists then contact support.	SMS
280259	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280260	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: No Master Found - suggests a replication config error	Replication system error	Refer to UNIX/application expert first. Check the following 1) is the smsMaster process running on the SMP? 2) is the SMP machine available? 3) are there any related smsMaster errors shown in the log on the SMP? 4) does the replication.config file still exist on the SMP? 5) Has a resync been started - check the updateLoader log for details. 6) Finally contact support.	SMS
280261	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280262	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280263	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: bind- Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280264	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: bind- Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280265	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280266	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280267	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: read- Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280268	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280269	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280270	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280271	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280272	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280273	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: read- Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
280274	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: read- Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS
280275	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
280276	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280277	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280278	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280279	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280280	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS
280281	ERROR	DEF123resyncServer: resyncServer(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280282	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Replication config file `%s %d` not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS
280283	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: system- Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280284	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS
280285	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Error opening Resync File `%s %d`;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280286	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
280287	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Update Loader %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280288	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Connection to `%s %d` lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280289	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280290	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
280291	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Master Controller `%s %d` process started (node %d)	Process has started successfully.	No resolution.	SMS
280292	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280293	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Update Requester `%s %d process registered (node %d)	Information only	No resolution.	SMS
280294	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280295	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280296	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280297	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280298	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Connection to `%s %d` lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280299	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Reached master node %d at `%s %d`	Client successfully made a connection.	No resolution.	SMS
280300	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280301	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280302	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
280303	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: gethostbyname-Problem getting host `%s %d`	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280304	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280305	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
280306	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS
280307	ERROR	DEF123resyncServer: resyncServer(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280308	ERROR	DEF123resyncServer: resyncServer(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280309	CRITICAL	DEF123resyncServer: resyncServer(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280310	ERROR	DEF123resyncServer: resyncServer(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280311	ERROR	DEF123resyncServer: resyncServer(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
280312	ERROR	DEF123resyncServer: resyncServer(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280313	ERROR	DEF123resyncServer: resyncServer(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280314	ERROR	DEF123resyncServer: resyncServer(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280315	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280316	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280317	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS
280318	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Failed to write to socket - exiting.	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280319	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280320	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280321	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280322	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: oraRWRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280323	ERROR	DEF123resyncServer: resyncServer(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280324	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280325	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280326	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280327	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280328	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280329	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280330	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280331	NOTICE	DEF123resyncServer: resyncServer(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280332	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
280333	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280334	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280335	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280336	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280337	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Update (key values `%s %d,%s %d,%s %d` not in any group of table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280338	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Consistency check failed (reason %d);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280339	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Problem opening consistency report file `%s %d`;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280340	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280341	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280342	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280343	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280344	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280345	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280346	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280347	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280348	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280349	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280350	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280351	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280352	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280353	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280354	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280355	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280356	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
280357	WARNING	DEF123resyncServer: resyncServer(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener (lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280358	WARNING	DEF123resyncServer: resyncServer(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280359	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280360	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280361	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280362	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280363	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS
280364	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Updates will be lost onZZZ	Replication system error	Refer to ORACLE/application expert first. Error suggests a communication or configuration fault between the SMP and one of the replication nodes. Check the error logs for the smsMaster and the updateLoader for further details. Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280365	WARNING	DEF123resyncServer: resyncServer(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280366	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280367	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280368	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280369	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280370	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280371	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280372	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280373	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280374	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280375	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280376	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280377	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
280378	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280379	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280380	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: No Master Found - suggests a replication config error	Replication system error	Refer to UNIX/application expert first. Check the following 1) is the smsMaster process running on the SMP? 2) is the SMP machine available? 3) are there any related smsMaster errors shown in the log on the SMP? 4) does the replication.config file still exist on the SMP? 5) Has a resync been started - check the updateLoader log for details. 6) Finally contact support.	SMS
280381	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280382	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280383	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: bind-Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280384	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: bind-Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280385	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280386	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280387	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: read-Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280388	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280389	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280390	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280391	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280392	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280393	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: read-Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
280394	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: read-Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS
280395	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
280396	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280397	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280398	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280399	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280400	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS
280401	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS
280402	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS
280403	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280404	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280405	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Replication config file `%s %d not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280406	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: system-Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS
280407	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280408	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Error opening Resync File `%s %d`;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280409	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
280410	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Update Loader %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280411	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Connection to `%s %d` lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280412	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280413	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
280414	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Master Controller `%s %d process started (node %d)	Process has started successfully.	No resolution.	SMS
280415	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280416	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Update Requester `%s %d process registered (node %d)	Information only	No resolution.	SMS
280417	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280418	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280419	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280420	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280421	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280422	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Reached master node %d at `%s %d	Client successfully made a connection.	No resolution.	SMS
280423	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280424	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280425	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
280426	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: gethostbyname-Problem getting host `%s %d	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280427	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280428	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
280429	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280430	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR %s %d=%d smsAlarmDaemon.c@%d: unable to open ORACLE Alert log	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280431	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR %s %d=%d smsAlarmDaemon.c@%d: unable to open Oracle alert log	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280432	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR %s %d=%d smsAlarmDaemon.c@%d: unable to open system error log	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280433	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR %s %d=%d smsAlarmDaemon.c@%d: unable to subscribe to error log service	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280434	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280435	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR get_sysname=%d smsAlarmDaemon.c@%d: unable to determine host name	Configuration issue / error	Refer to UNIX/application expert first (Check the following). 1) Is the hostname specified as a variable in the users environment? 2) Is the host contactable? 3) Does the host have a DNS entry? 4) Finally contact support.	SMS
280436	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280437	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR main=%d smsAlarmDaemon.c@%d: discrepancy between internal list and number of elements - list is corrupt	Internal software error.	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280438	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR main=%d smsAlarmDaemon.c@%d: unable to initialise replication system	Configuration issue / error	Refer to application expert first. One of the following has occurred: 1) An incorrect configuration item was given, 2) A required configuration item was missing, 3) A configuration item was given with an invalid value or value type. The offending configuration item should be detailed in an accompanying alarm. Please consult the user documentation for the SMS replication system. Contact support if problem persists.	SMS
280439	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR main=%d smsAlarmDaemon.c@%d: unable to insert data into internal list - malloc() failed	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280440	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR open_all=%d smsAlarmDaemon.c@%d: unable to connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
280441	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280442	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280443	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280444	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
280445	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280446	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280447	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280448	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280449	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280450	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280451	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280452	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280453	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280454	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280455	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280456	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280457	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280458	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280459	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280460	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280461	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280462	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280463	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280464	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280465	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
280466	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280467	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280468	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280469	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280470	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: oraRWRRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280471	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280472	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280473	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280474	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280475	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280476	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280477	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280478	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280479	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280480	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280481	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280482	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280483	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280484	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE main=%d smsAlarmDaemon.c@%d: No tasks active.	Internal software error.	Refer to UNIX/application expert first. The smsTaskAgent is failing to register any IORs with the naming server and is exiting. Check the TaskAgent log for further error messages. If problem persists then contact support.	SMS
280485	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: smsAlarmDaemon: Startup successful	Process has started	No resolution.	SMS
280486	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
280487	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280488	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280489	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280490	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE sig_handler=%d smsAlarmDaemon.c@%d: SIGHUP received - Restarting	Process has received a SIGHUP	No resolution. process should reread configuration details	SMS
280491	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE sig_handler=%d smsAlarmDaemon.c@%d: SIGTERM received - Terminating	Process has received a SIGTERM and will terminate	Refer to application expert first. Process should restart automatically. Observe startup output for errors.	SMS
280492	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE sig_handler=%d smsAlarmDaemon.c@%d: Unhandled signal	Internal communications error.	Refer to UNIX/application expert first. The signal handler in the alarm daemon has just handled a signal which it is not meant to handle. 1) Check the individual process logs for further error messages. 2) Contact support.	SMS
280493	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280494	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280495	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280496	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280497	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280498	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280499	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280500	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280501	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
280502	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE: Startup successful	Process has started	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280503	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
280504	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280505	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Key name `s %d is unknown in table `s %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280506	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280507	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
280508	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Update (key values `%s %d,%s %d,%s %d`) not in any group of table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280509	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Consistency check failed (reason %d);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280510	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Problem opening consistency report file `%s %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280511	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280512	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280513	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280514	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280515	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280516	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280517	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280518	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280519	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280520	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280521	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280522	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280523	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280524	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280525	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280526	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280527	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
280528	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING errlog_data=%d smsAlarmDaemon.c@%d: unable to resolve message number	Internal software error.	No resolution. If problem persists then contact support.	SMS
280529	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING errlog_read=%d smsAlarmDaemon.c@%d: unable to read error log message	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280530	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280531	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280532	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280533	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280534	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280535	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280536	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280537	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280538	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
280539	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
280540	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
280541	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280542	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280543	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PIbeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
280544	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280545	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS
280546	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280547	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
280548	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280549	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280550	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280551	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280552	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Updates will be lost onZZZ	Replication system error	Refer to ORACLE/application expert first. Error suggests a communication or configuration fault between the SMP and one of the replication nodes. Check the error logs for the smsMaster and the updateLoader for further details. Contact support for further assistance.	SMS
280553	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280554	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280555	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) CRITICAL: Cannot connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
280556	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Internal software error.	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS
280557	CRITICAL	DEF123smsAlarmRelay: smsAlarmRelay(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280558	CRITICAL	DEF123smsAlarmRelay: smsAlarmRelay(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280559	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR waitForAlert=%d smsAlarmRelaySQL.pc@%d: Error waiting for alert	Error communicating with Oracle.	Refer to ORACLE/application expert first. 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) If problem persists then contact support.	SMS
280560	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280561	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280562	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280563	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280564	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280565	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280566	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280567	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280568	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280569	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280570	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280571	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280572	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS
280573	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280574	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280575	CRITICAL	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Malloc error on handler array	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280576	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280577	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280578	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280579	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280580	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280581	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280582	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280583	CRITICAL	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280584	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE sig_handler=%d smsAlarmRelay.c@%d: SIGHUP received - Restarting	Process has received a SIGHUP	No resolution. process should reread configuration details	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280585	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE sig_handler=%d smsAlarmRelay.c@%d: Terminating	Process has terminated	Refer to application expert first. Process should restart automatically. Observe startup output for errors.	SMS
280586	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE main=%d smsAlarmRelay.c@%d: Startup successful	Process has started	No resolution.	SMS
280587	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280588	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280589	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
280590	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280591	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280592	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280593	NOTICE	DEF123smsAlarmRelay: smsAlarmRelay(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280594	CRITICAL	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280595	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280596	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280597	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280598	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280599	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280600	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
280601	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
280602	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
280603	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280604	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PibeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
280605	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280606	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280607	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS
280608	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/ macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280609	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Oracle unavailable after %d seconds with error:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280610	ERROR	DEF123smsIorListener: smsIorListener(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS
280611	ERROR	DEF123smsIorListener: smsIorListener(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS
280612	CRITICAL	DEF123smsIorListener: smsIorListener(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280613	CRITICAL	DEF123smsIorListener: smsIorListener(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280614	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Accept failed: %d	Internal communications error.	Refer to UNIX/application expert first. The IOR listener tried to accept a connection but this failed. If problem persists then contact support.	SMS
280615	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280616	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280617	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280618	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280619	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280620	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280621	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280622	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280623	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280624	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280625	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280626	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280627	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280628	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280629	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280630	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Failed to connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
280631	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Invalid IOR string	Internal communications error.	Refer to UNIX/application expert first. A process tried to register an IOR but it was in the wrong format. 1) Check process log for further related error messages. 2) If problem persists then contact support.	SMS
280632	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: IOR Parse Error -%z	Internal communications error.	Refer to UNIX/application expert first. A process tried to register an IOR but it was in the wrong format. 1) Check process log for further related error messages. 2) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280633	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Listen failed: %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280634	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Message format invalid	Internal communications error.	Refer to UNIX/application expert first. A process tried to register an IOR but it was in the wrong format. 1) Check process log for further related error messages. 2) If problem persists then contact support.	SMS
280635	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280636	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280637	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280638	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Socket bind failed: %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280639	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Socket get failed: %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280640	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Socket read failed: %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280641	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280642	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280643	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280644	ERROR	DEF123smsIorListener: smsIorListener(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280645	CRITICAL	DEF123smsIorListener: smsIorListener(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280646	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
280647	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280648	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280649	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
280650	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280651	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280652	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: recv: end of file	Information only	No resolution.	SMS
280653	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280654	NOTICE	DEF123smsIorListener: smsIorListener(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280655	CRITICAL	DEF123smsIorListener: smsIorListener(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280656	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: Address Parse Error -%z	Internal communications error.	No resolution. If problem persists then contact support.	SMS
280657	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280658	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280659	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280660	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280661	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280662	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
280663	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280664	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
280665	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280666	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PIbeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280667	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280668	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS
280669	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280670	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
280671	WARNING	DEF123smsIorListener: smsIorListener(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: ORACLE initialization or shutdown in progress	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
280672	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280673	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS
280674	CRITICAL	DEF123smsLogCleaner: smsLogCleaner(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280675	CRITICAL	DEF123smsLogCleaner: smsLogCleaner(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280676	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280677	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280678	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Cannot Open Configuration file: %s %d - -TERMINATING--	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280679	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Cannot Open Storage file %s %d for reading Last access times	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280680	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Cannot Open Storage file %s %d for writing Last access times	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280681	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280682	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280683	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280684	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280685	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280686	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280687	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280688	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280689	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280690	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280691	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280692	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280693	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280694	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280695	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280696	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Failed to copy logZZZ	Attempt to write to / open the named file has resulted in an error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280697	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Failure to create archivefilename for cleaning - directoryname to BIG	Attempt to write to / open the named file has resulted in an error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280698	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Failure to do lstat onZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280699	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Failure to open archive directory for cleanup	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280700	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Failure to remove archived logZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280701	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280702	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280703	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280704	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280705	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280706	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280707	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280708	CRITICAL	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280709	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280710	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280711	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
280712	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280713	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280714	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: Location Config file is:%z	Information only	No resolution.	SMS
280715	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280716	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280717	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: Starting LogJob CronJob	Information only	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280718	CRITICAL	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280719	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280720	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280721	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280722	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280723	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280724	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
280725	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
280726	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
280727	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280728	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PibeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
280729	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280730	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280731	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS
280732	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/ macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
280733	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: No type given for file size so using straight byte - not Kbyte or MegByte	Configuration issue / error	Refer to UNIX/application expert first. A line in /IN/service_packages/SMS/etc/log job.conf as got -size nn instead of -size nnK or -size nnM. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280734	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280735	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
280736	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280737	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280738	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280739	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280740	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280741	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280742	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280743	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280744	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280745	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
280746	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280747	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280748	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280749	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280750	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: bind-Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280751	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: bind-Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280752	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280753	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280754	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: read-Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280755	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280756	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280757	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280758	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280759	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280760	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: read-Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
280761	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: read-Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280762	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
280763	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280764	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280765	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
280766	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280767	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS
280768	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Replication config file `%s %d not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280769	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: system-Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS
280770	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280771	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Error opening Resync File `%s %d;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280772	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
280773	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Update Loader %d at `%s %d:%d also connecting from `%s %d:%d	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
280774	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280775	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280776	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
280777	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Master Controller `%s %d` process started (node %d)	Process has started successfully.	No resolution.	SMS
280778	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280779	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Update Requester `%s %d` process registered (node %d)	Information only	No resolution.	SMS
280780	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280781	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280782	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280783	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280784	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280785	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Reached master node %d at `%s %d	Client successfully made a connection.	No resolution.	SMS
280786	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280787	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280788	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
280789	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: gethostbyname-Problem getting host `%s %d	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280790	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: TCP connection to %z was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
280791	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
280792	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280793	ERROR	DEF123smsMaster: smsMaster(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280794	ERROR	DEF123smsMaster: smsMaster(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280795	CRITICAL	DEF123smsMaster: smsMaster(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280796	ERROR	DEF123smsMaster: smsMaster(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS
280797	ERROR	DEF123smsMaster: smsMaster(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
280798	ERROR	DEF123smsMaster: smsMaster(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280799	ERROR	DEF123smsMaster: smsMaster(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280800	ERROR	DEF123smsMaster: smsMaster(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
280801	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280802	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
280803	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280804	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Failed to connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
280805	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280806	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280807	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
280808	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: oraRWRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280809	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
280810	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280811	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280812	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Update Requester %d at `%s %d:%d also connecting from `%s %d:%d	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280813	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Pending queue now above %d	Internal communications error.	Assuming basic UNIX skills (Check the following). 1) Are the updateLoaders still connected to the smsMaster? 2) Are the machines still available on the network? 3) The message means that updates that are to be replicated to a given node are building up on the smsMaster faster than the target nodes updateLoader can clear them - as long as they stay connected the queue should clear eventually 4) If problem persists then contact support.	SMS
280814	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Pending queue now below %d	Internal communications error.	No resolution.	SMS
280815	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280816	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280817	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280818	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280819	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280820	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280821	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Shutting Down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
280822	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Startup Successful	Process has started	No resolution.	SMS
280823	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Update Lost:%z	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280824	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280825	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280826	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280827	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280828	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
280829	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Update (key values `%s %d,%s %d,%s %d`) not in any group of table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280830	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Consistency check failed (reason %d);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280831	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Problem opening consistency report file `%s %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280832	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
280833	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280834	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280835	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280836	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280837	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Cannot open report file '%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280838	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280839	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280840	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280841	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280842	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280843	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Cannot open report file `%s %d`	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280844	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280845	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
280846	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280847	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280848	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
280849	WARNING	DEF123smsMaster: smsMaster(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1)Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280850	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280851	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
280852	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280853	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
280854	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
280855	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS
280856	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Write error: Broken pipe	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280857	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: value larger than specified precision allows for this column	Internal software error.	Refer to ORACLE/application expert first. A data error has occurred. Contact support for further assistance.	SMS
280858	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: SMS Master replication process started (node %d)	Process has started successfully.	No resolution.	SMS
280859	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: following severe error from %s %d	Internal software error.	Refer to ORACLE/application expert first. A data error has occurred. Contact support for further assistance.	SMS
280860	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: ORACLE initialization or shutdown in progress	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280861	ERROR	DEF123smsMaster: smsMaster(%d) CRITICAL: read-Unix IPC pipe connection lost: Error %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280862	ERROR	DEF123smsNamingServer: smsNamingServer(%d) CRITICAL: Aieee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS
280863	ERROR	DEF123smsNamingServer: smsNamingServer(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS
280864	CRITICAL	DEF123smsNamingServer: smsNamingServer(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280865	CRITICAL	DEF123smsNamingServer: smsNamingServer(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280866	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280867	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280868	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Bad command line syntax	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
280869	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Bad object name on query	Internal software error.	Refer to ORACLE/application expert first. Process is looking for the IOR for an object name but the IOR in the database is corrupt. Contact support for further assistance.	SMS
280870	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Bad object name on store	Internal software error.	Refer to ORACLE/application expert first. Process has sent the naming server a corrupt IOR to store but it refuses to do this. Contact support for further assistance.	SMS
280871	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Cannot bind to socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280872	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Cannot connect to oracle asZZZ	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
280873	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Cannot get socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280874	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Cannot listen on socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280875	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Cannot trap SIGINT	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280876	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Cannot trap SIGTERM	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280877	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280878	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280879	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280880	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280881	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280882	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280883	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280884	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280885	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280886	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280887	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280888	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280889	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280890	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280891	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280892	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Invalid write message; missing colon	Internal software error.	Refer to ORACLE/application expert first. The message registering an IOR with the namingServer is meant to have an object name and an IOR separated by a colon, which is missing. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280893	ERROR	smsNamingServer: smsNamingServer(%d) ERROR: main=%d smsNamingServer.c@%d: Failure in Accept	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280894	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280895	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280896	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280897	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280898	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280899	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280900	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280901	CRITICAL	DEF123smsNamingServer: smsNamingServer(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280902	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
280903	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280904	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280905	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
280906	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280907	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280908	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280909	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280910	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Problem accessing the database, exitingZZZ	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
280911	ERROR	DEF123smsNamingServer: smsNamingServer(%d) ERROR: Terminating	Process has terminated	Refer to application expert first. Process should restart automatically. Observe startup output for errors.	SMS
280912	NOTICE	DEF123smsNamingServer: smsNamingServer(%d) NOTICE: Startup successful	Process has started	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280913	CRITICAL	DEF123smsNamingServer: smsNamingServer(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280914	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280915	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280916	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280917	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280918	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280919	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
280920	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
280921	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
280922	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280923	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PibeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
280924	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280925	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280926	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS
280927	WARNING	DEF123smsNamingServer: smsNamingServer(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/ macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
280928	ERROR	smsReportScheduler: smsReportScheduler(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS
280929	ERROR	smsReportScheduler: smsReportScheduler(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280930	CRITICAL	smsReportScheduler: smsReportScheduler(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280931	CRITICAL	smsReportScheduler: smsReportScheduler(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280932	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280933	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280934	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
280935	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280936	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280937	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280938	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280939	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280940	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280941	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280942	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280943	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280944	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280945	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280946	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280947	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280948	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280949	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280950	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280951	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280952	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280953	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280954	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280955	ERROR	smsReportScheduler: smsReportScheduler(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280956	CRITICAL	smsReportScheduler: smsReportScheduler(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280957	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
280958	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280959	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
280960	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
280961	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280962	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280963	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280964	NOTICE	smsReportScheduler: smsReportScheduler(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
280965	CRITICAL	smsReportScheduler: smsReportScheduler(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280966	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280967	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280968	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280969	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
280970	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280971	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
280972	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
280973	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
280974	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280975	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PibeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
280976	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
280977	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280978	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS
280979	WARNING	smsReportScheduler: smsReportScheduler(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/ macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
280980	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS
280981	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280982	CRITICAL	DEF123smsReportsDaemon: smsReportsDaemon(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280983	CRITICAL	DEF123smsReportsDaemon: smsReportsDaemon(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
280984	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280985	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
280986	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Cannot determine ORACLE_HOME	Internal software error.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variable ORACLE_HOME is set for the user running the process. 4) Observe startup output for errors. Finally contact support.	SMS
280987	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280988	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280989	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280990	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280991	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280992	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280993	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280994	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280995	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280996	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280997	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
280998	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
280999	ERROR	%z Expanding parameters for app:%s %d category:%s %d script:%s %d	Internal Software Error	No further information can be obtained. Contact Support.	SMS
281000	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS
281001	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281002	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281005	ERROR	%z generateReport:calloc: Out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281010	ERROR	%z Error running %s %d: %s %d	Attempt to write to / open the named file has resulted in an error.	Refer to UNIX/application/LAN expert first. The reports daemon has tried to fork a child process to run a report but it cant. The error message contains further details. If problem persists then contact support.	SMS
281011	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: gethostname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281012	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281013	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281014	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281016	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281017	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281018	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281019	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281020	CRITICAL	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281021	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
281023	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: %s %d: Startup successful	Process has started	No resolution.	SMS
281024	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281025	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281026	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
281027	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281028	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281029	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281030	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281031	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE:[[:space:]]+	Internal software error.	No resolution. If problem persists then contact support.	SMS
281034	CRITICAL	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281035	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281036	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281037	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281038	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281039	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281040	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
281041	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281042	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
281043	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281044	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PIbeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281045	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281046	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS
281047	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281048	WARNING	DEF123smsReportsDaemon: smsReportsDaemon(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
281049	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: %s %d:%s %d: Output path too long. Report generation cancelled.	Attempt to write to / open the named file has resulted in an error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281053	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: %s %d:%s %d:%s %d: Input path too long. Report generation cancelled.	Attempt to write to / open the named file has resulted in an error.	Refer to UNIX/application expert first. The fully qualified filename and path of the scheduled report is too long. Please reduce the size via the SMS Management screens. Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281054	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: Cannot connect to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281055	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: Cannot hold SIGCHLD:%z	Internal software error.	Contact support. No further information can be obtained.	SMS
281057	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: Cannot release SIGCHLD:%z	Internal software error.	Contact support. No further information can be obtained.	SMS
281058	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: doChild: waitpid:%z	Internal software error.	Contact support. No further information can be obtained.	SMS
281059	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: gettimeofday:%z	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281060	CRITICAL	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: Memory allocation failure while retrieving expired reports.	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281061	ERROR	DEF123smsReportsScheduler: smsReportsScheduler(%d) ERROR: signal:SIGCHLD:%z	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281062	ERROR	%z waitForSchedule: Execv error (%s %d)	Internal software error.	Contact support. No further information can be obtained.	SMS
281064	NOTICE	DEF123smsReportsScheduler: smsReportsScheduler(%d) NOTICE: App: %s %d, Category: %s %d, File: %s %d -: report generation completeZZZ	Information only	No resolution.	SMS
281065	NOTICE	DEF123smsReportsScheduler: smsReportsScheduler(%d) NOTICE: Failed to get expired report array	Internal software error.	Contact support. No further information can be obtained.	SMS
281067	NOTICE	DEF123smsReportsScheduler: smsReportsScheduler(%d) NOTICE: Program terminated	Process has terminated	Refer to application expert first. Process should restart automatically. Observe startup output for errors.	SMS
281068	NOTICE	DEF123smsReportsScheduler: smsReportsScheduler(%d) NOTICE: Startup successful	Process has started	No resolution.	SMS
281069	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) CRITICAL ::%s %d::%s %d:%z	Internal software error.	Contact support. No further information can be obtained.	SMS
281070	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281071	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS
281072	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281073	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281074	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281075	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR ora_connect=%d smsStatsDaemonSQL.pc@%d: unable to connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281076	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281077	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Cannot open config file:%z	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281078	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cant catch SIGALRM	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281079	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cant catch SIGINT	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281080	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281081	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281082	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281083	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281084	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281085	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281086	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281087	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281088	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281089	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281090	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281091	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281092	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Configuration file error	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281093	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Could not find statistic	Internal software error.	Contact support. No further information can be obtained.	SMS
281094	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281095	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281096	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Could not retrieve statistic	Internal software error.	Contact support. No further information can be obtained.	SMS
281097	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281098	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Error updating statistic	Internal software error.	Contact support. No further information can be obtained.	SMS
281099	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: fopen: fail openZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
281100	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: handleTERM:semctl:%z	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281101	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Malloc error on MID space	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281102	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: readConfig: Error opening config file	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281103	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: readConfig: Error reading config file MIDs	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281104	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: readConfig: Error reading database MIDs	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281105	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: readConfig: Error re-reading config file MIDs	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281106	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: readConfig: Error re-reading database MIDs	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
281107	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281108	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281109	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281110	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: semctl id %d:%z	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to record statistics in shared memory. Please try increasing the system parameter for the number of semaphores. Contact support if problem persists.	SMS
281111	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: semctl:%z	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to record statistics in shared memory. Please try increasing the system parameter for the number of semaphores. Contact support if problem persists.	SMS
281112	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: semget:%z	Kernel communication/disk error.	Refer to UNIX/application expert first. Issue with semaphore key file. 1) Check that (if it is set) the file represented by the environment variable SHM_KEY_ENV_VAR exists and has read permission for the process user. 2) Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281113	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: shmat:%z	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to attach shared memory to its own address space. Check the following: 1) The ID of the shared memory may be invalid. Ensure that the system limit on shared memory is high enough. 2) The process can not allocate address space. Ensure that there are no processes taking up unusually large amounts of memory. 3) Finally contact support.	SMS
281114	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: shmAttach: Cannot attach to shmKey %d	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to attach shared memory to its own address space. Check the following: 1) The ID of the shared memory may be invalid. Ensure that the system limit on shared memory is high enough. 2) The process can not allocate address space. Ensure that there are no processes taking up unusually large amounts of memory. 3) Finally contact support.	SMS
281115	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: shmAttach: Cannot get semID from semKey %d	Kernel communication/disk error.	Refer to UNIX/application expert first. Issue with semaphore key file. 1) Check that (if it is set) the file represented by the environment variable SHM_KEY_ENV_VAR exists and has read permission for the process user. 2) Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281116	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: shmAttach: Cannot get shmKey from semID %d	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to record statistics in shared memory. Please try increasing the system parameter for the number of semaphores. Contact support if problem persists.	SMS
281117	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: shmAttach: Error %d getting INODE forZZZ	Kernel communication/disk error.	Refer to UNIX/application expert first. Issue with semaphore key file. 1) Check that (if it is set) the file represented by the environment variable SHM_KEY_ENV_VAR exists and has read permission for the process user. 2) Contact support if problem persists.	SMS
281118	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: shmget:%z	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to record statistics in shared memory. Please try increasing the system parameter for the maximum amount of shared memory that can be allocated. Contact support if problem persists.	SMS
281119	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsAddStatistic: bad return status - %d	Internal software error.	Contact support. No further information can be obtained.	SMS
281120	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsAddStatistic: chain value greater than number of table entries.	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281121	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsAddStatistic: loop in chaining	Internal software error.	Contact support. No further information can be obtained.	SMS
281122	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsAddStatistic: Not enough memory for calloc	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281123	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsAddStatistic: undefined return status - %d	Internal software error.	Contact support. No further information can be obtained.	SMS
281124	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsRetrieveStats: Cannot attach to SHM	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to attach shared memory to its own address space. Check the following: 1) The ID of the shared memory may be invalid. Ensure that the system limit on shared memory is high enough. 2) The process can not allocate address space. Ensure that there are no processes taking up unusually large amounts of memory. 3) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281125	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsRetrieveStats: Cannot reattach to SHM	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to attach shared memory to its own address space. Check the following: 1) The ID of the shared memory may be invalid. Ensure that the system limit on shared memory is high enough. 2) The process can not allocate address space. Ensure that there are no processes taking up unusually large amounts of memory. 3) Finally contact support.	SMS
281126	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsTryRecordStats: Cannot attach to SHM	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to attach shared memory to its own address space. Check the following: 1) The ID of the shared memory may be invalid. Ensure that the system limit on shared memory is high enough. 2) The process can not allocate address space. Ensure that there are no processes taking up unusually large amounts of memory. 3) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281127	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsTryRecordStats: Cannot reattach to SHM	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to attach shared memory to its own address space. Check the following: 1) The ID of the shared memory may be invalid. Ensure that the system limit on shared memory is high enough. 2) The process can not allocate address space. Ensure that there are no processes taking up unusually large amounts of memory. 3) Finally contact support.	SMS
281128	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281129	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281130	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281131	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281132	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281133	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
281134	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281135	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281136	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
281137	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281138	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: File size exceeded %d kb. Closing stats file and creating new one.	Information only	No resolution.	SMS
281139	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281140	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: New ShmID set - %d	Information only	No resolution.	SMS
281141	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281142	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: SIGHUP received. Reload Stats Defn.	Process has received a SIGHUP	No resolution. process should reread configuration details	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281143	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: smsRecordStats: Statistic not foundZZZ	Configuration issue / error	Refer to UNIX/application expert first. Unable to update statistics. (Check the following): 1) Is the smsStatsDaemon running ? 2) Have all applicable statistics been configured ? (SMS Management Screens, Operator functions). Finally, contact support if problem persists.	SMS
281144	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281145	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: SIGTERM received. Closing stats file and deleting share memory segment before exiting.	Process has received a SIGTERM and will terminate	Refer to application expert first. Process should restart automatically. Observe startup output for errors.	SMS
281146	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: smsAddStatistic: Hash table full. Exiting.	Internal software error.	No resolution. Contact support.	SMS
281147	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: Startup successful. SHM ID is %d	Process has started	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281148	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING malloc=%d smsHashTable.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281149	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING malloc=%d smsStatsHash.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281150	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281151	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cant catch SIGHUP	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281152	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cant catch SIGTERM	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281153	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281154	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281155	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281156	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281157	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281158	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
281159	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
281160	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Could not attach to shared memory key %d (shmat)	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to attach shared memory to its own address space. Check the following: 1) The ID of the shared memory may be invalid. Ensure that the system limit on shared memory is high enough. 2) The process can not allocate address space. Ensure that there are no processes taking up unusually large amounts of memory. 3) Finally contact support.	SMS
281161	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Could not get semaphore from key %d (semget)	Kernel communication/disk error.	Refer to UNIX/application expert first. Issue with semaphore key file. 1) Check that (if it is set) the file represented by the environment variable SHM_KEY_ENV_VAR exists and has read permission for the process user. 2) Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281162	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Could not get shared memory key from semaphore ID %d (semctl)	Kernel communication/disk error.	Refer to UNIX/application expert first. The program failed to record statistics in shared memory. Please try increasing the system parameter for the number of semaphores. Contact support if problem persists.	SMS
281163	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
281164	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281165	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Error %d getting INODE for:%z	Kernel communication/disk error.	Refer to UNIX/application expert first. Issue with semaphore key file. 1) Check that (if it is set) the file represented by the environment variable SHM_KEY_ENV_VAR exists and has read permission for the process user. 2) Contact support if problem persists.	SMS
281166	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PIbeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
281167	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: getSinapInfo failed at %s %d in smsStatsDaemon	Configuration issue / error	Refer to UNIX/application expert first. Unable to obtain information about SINAP. Please check that SINAP is correctly configured and running. Contact support if problem persists.	SMS
281168	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281169	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS
281170	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281171	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/ macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
281172	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Too many application IDs for MID	Configuration issue / error	Refer to UNIX/application expert first. Check the SMS statistics configuration (SMS Management Screens, Operator functions). Contact support if problem persists.	SMS
281173	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Too many measurement Ids	Configuration issue / error	Refer to UNIX/application expert first. Check the SMS statistics configuration (SMS Management Screens, Operator functions). Contact support if problem persists.	SMS
281174	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281175	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
281176	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281177	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281178	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281179	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281180	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281181	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281182	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281183	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281184	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281185	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
281186	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281187	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281188	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: No Master Found - suggests a replication config error	Replication system error	Refer to UNIX/application expert first. Check the following 1) is the smsMaster process running on the SMP? 2) is the SMP machine available? 3) are there any related smsMaster errors shown in the log on the SMP? 4) does the replication.config file still exist on the SMP? 5) Has a resync been started - check the updateLoader log for details. 6) Finally contact support.	SMS
281189	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281190	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281191	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: bind-Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281192	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: bind-Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281193	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281194	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281195	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: read-Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281196	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281197	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281198	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281199	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281200	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281201	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: read-Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
281202	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: read-Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS
281203	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
281204	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281205	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281206	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281207	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281208	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS
281209	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS
281210	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281211	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
281212	CRITICAL	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281213	CRITICAL	DEF123smsStatsLoader: smsStatsLoader(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281214	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Replication config file `%s %d` not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS
281215	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: system-Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281216	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS
281217	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Error opening Resync File `%s %d`;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281218	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
281219	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Update Loader %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281220	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Connection to `%s %d` lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281221	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281222	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
281223	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Master Controller `%s %d` process started (node %d)	Process has started successfully.	No resolution.	SMS
281224	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281225	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Update Requester `%s %d process registered (node %d)	Information only	No resolution.	SMS
281226	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281227	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281228	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281229	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281230	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Connection to `%s %d` lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281231	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Reached master node %d at `%s %d`	Client successfully made a connection.	No resolution.	SMS
281232	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281233	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281234	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
281235	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: gethostbyname-Problem getting host `%s %d`	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281236	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281237	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
281238	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS
281239	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281240	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281241	CRITICAL	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281242	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281243	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS
281244	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
281245	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
281246	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281247	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
281248	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281249	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Cannot connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281250	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cannot open file %s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281251	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: checkDirExists: cannot create %s %d:%z	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281252	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: checkDirExists: Required directory %s %d is a file	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281253	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281254	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281255	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281256	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281257	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281258	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281259	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281260	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281261	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281262	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281263	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281264	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281265	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281266	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS
281267	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281268	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/<language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281269	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: doDir: Problem with directory %s %d - %s %d, skip.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281270	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281271	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
281272	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281273	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281274	CRITICAL	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Malloc error on rule array	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281275	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: moveFile: Attempting to link file %s %d to %s %d :%z	Attempting to move the specified file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified target directory exist? 2) Are the correct permissions set for the directory? 3) Is the file corrupt, can it be opened? 4) Does the file have read permissions set for the process user 5) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281276	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: moveFile: Attempting to remove file %s %d :%z	Attempting to remove the specified file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Finally contact support.	SMS
281277	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
281278	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: oraRWRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
281279	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: processFile: Move failed for %s %d	Attempting to move the specified file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified target directory exist? 2) Are the correct permissions set for the directory? 3) Is the file corrupt, can it be opened? 4) Does the file have read permissions set for the process user 5) Finally contact support.	SMS
281280	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: processFile: Processing failed for %s %d	Attempt to write to / open the named file has resulted in an error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281281	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: processFile: Unknown data line syntax	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
281282	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281283	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281284	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281285	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281286	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281287	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281288	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281289	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281290	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281291	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281292	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
281293	CRITICAL	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281294	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281295	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
281296	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281297	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281298	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281299	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281300	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281301	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
281302	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281303	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281304	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281305	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281306	NOTICE	DEF123smsStatsLoader: smsStatsLoader(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281307	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281308	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281309	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281310	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281311	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
281312	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Update (key values `%s %d,%s %d,%s %d`) not in any group of table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281313	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Consistency check failed (reason %d);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281314	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Problem opening consistency report file `%s %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281315	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281316	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281317	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281318	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281319	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281320	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281321	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281322	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281323	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281324	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281325	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281326	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281327	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281328	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281329	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281330	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281331	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281332	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
281333	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281334	CRITICAL	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281335	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281336	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281337	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281338	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281339	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281340	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
281341	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
281342	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
281343	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281344	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: doDir: No such directory %s %d - %s %d, skip.	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281345	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281346	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281347	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281348	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS
281349	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281350	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
281351	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281352	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281353	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281354	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281355	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Updates will be lost onZZZ	Replication system error	Refer to ORACLE/application expert first. Error suggests a communication or configuration fault between the SMP and one of the replication nodes. Check the error logs for the smsMaster and the updateLoader for further details. Contact support for further assistance.	SMS
281356	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING Oracle=%d smsStatsLoader.pc@%d: insert into SMF_STATISTICS(application_id,st atistic_id,node_name,times: ORA- %d: (full) year must be between -%d and +%d, and not be %d	Internal software error.	Refer to ORACLE/application expert first. A data error has occurred. Contact support for further assistance.	SMS
281357	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281358	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: =%d tcpConnection.C@%d: socket- Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281359	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
281360	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281361	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281362	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281363	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281364	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281365	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281366	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281367	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281368	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281369	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281370	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281371	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281372	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: No Master Found - suggests a replication config error	Replication system error	Refer to UNIX/application expert first. Check the following 1) is the smsMaster process running on the SMP? 2) is the SMP machine available? 3) are there any related smsMaster errors shown in the log on the SMP? 4) does the replication.config file still exist on the SMP? 5) Has a resync been started - check the updateLoader log for details. 6) Finally contact support.	SMS
281373	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281374	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281375	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: bind- Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281376	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: bind- Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281377	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281378	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281379	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: read- Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281380	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281381	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281382	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL =%d tcpConnection.C@713: fcntl- Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281383	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281384	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281385	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: read- Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
281386	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: read- Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS
281387	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281388	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281389	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281390	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281391	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281392	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS
281393	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281394	CRITICAL	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281395	CRITICAL	DEF123smsTaskAgent: smsTaskAgent(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281396	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Replication config file `%s %d not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281397	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: system- Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS
281398	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281399	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Error opening Resync File `%s %d;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281400	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
281401	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Update Loader %d at `%s %d:%d also connecting from `%s %d:%d	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
281402	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281403	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281404	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
281405	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Master Controller `%s %d process started (node %d)	Process has started successfully.	No resolution.	SMS
281406	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281407	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Update Requester `%s %d process registered (node %d)	Information only	No resolution.	SMS
281408	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281409	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281410	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281411	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281412	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281413	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Reached master node %d at `%s %d	Client successfully made a connection.	No resolution.	SMS
281414	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281415	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281416	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
281417	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: gethostbyname-Problem getting host `%s %d	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281418	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281419	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
281420	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281421	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281422	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281423	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281424	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281425	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281426	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281427	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281428	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281429	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281430	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281431	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281432	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281433	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281434	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281435	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS
281436	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281437	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281438	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281439	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
281440	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281441	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281442	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281443	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281444	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281445	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281446	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281447	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281448	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281449	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
281450	CRITICAL	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281451	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS
281452	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281453	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281454	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
281455	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281456	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281457	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281458	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281459	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
281460	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281461	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281462	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281463	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
281464	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Update (key values `%s %d,%s %d,%s %d` not in any group of table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281465	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Consistency check failed (reason %d);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281466	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Problem opening consistency report file `%s %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281467	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281468	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281469	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281470	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281471	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281472	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281473	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281474	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281475	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281476	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281477	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281478	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281479	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281480	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281481	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281482	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281483	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
281484	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281485	CRITICAL	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281486	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281487	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281488	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281489	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281490	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281491	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
281492	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
281493	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
281494	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281495	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PibeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
281496	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281497	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281498	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS
281499	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/ macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281500	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
281501	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: Startup successful	Process has started	No resolution.	SMS
281502	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281503	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281504	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: bind- Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281505	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: bind- Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281506	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: compareResyncReceive has not reset yet; trying againZZZ	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281507	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281508	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Connection message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281509	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Connection type `%s %d not implemented yet	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281510	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281511	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281512	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281513	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: ioctl-Unable to set TCP socket non-blocking	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281514	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281515	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281516	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: No Master Found - suggests a replication config error	Replication system error	Refer to UNIX/application expert first. Check the following 1) is the smsMaster process running on the SMP? 2) is the SMP machine available? 3) are there any related smsMaster errors shown in the log on the SMP? 4) does the replication.config file still exist on the SMP? 5) Has a resync been started - check the updateLoader log for details. 6) Finally contact support.	SMS
281517	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: read- Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281518	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: read- Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
281519	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: read- Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281520	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281521	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
281522	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281523	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: setsockopt-Problem setting socket option - Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281524	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281525	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281526	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Unable to find the program %s %d.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
281527	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281528	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281529	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
281530	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281531	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281532	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Write to fd %d only sent %d bytes not %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281533	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281534	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281535	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Replication system error	No resolution. If problem persists then contact support.	SMS
281536	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281537	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281538	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281539	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281540	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281541	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281542	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281543	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281544	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281545	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281546	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
281547	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Replication system error	No resolution. If problem persists then contact support.	SMS
281548	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281549	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281550	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: bind- Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281551	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: bind- Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281552	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281553	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281554	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: read- Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281555	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281556	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281557	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281558	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281559	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281560	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: read- Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
281561	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: read- Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS
281562	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
281563	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281564	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281565	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281566	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
281567	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS
281568	ERROR	DEF123updateLoader: updateLoader(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281569	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: gethostbyname-Problem getting host `%s %d	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281570	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: system- Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
281571	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281572	WARNING	DEF123updateLoader: updateLoader(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281573	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
281574	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Connection to %s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281575	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Connection to Inferior Master lost prematurely	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281576	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Connection to Superior Master lost prematurely	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281577	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Consistency check inconsistent config with table `%z	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281578	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Error comparing database row	Replication system error	Refer to ORACLE/application expert first. 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Check process output for further details of the row in question. 5) Finally contact support.	SMS
281579	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Error connecting to database as user '%s %d	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. 4) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281580	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Error opening Resync File `%s 123ZZZ	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281581	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Error opening Resync/Comparison connection to %s %d.%d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281582	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281583	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Lost connection to slave at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281584	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281585	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Replication config file `%s %d` not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281586	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Slave lost connection to current master at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281587	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281588	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS
281589	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Unrecognised consistency id %d from loader %d	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281590	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Update Loader %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
281591	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
281592	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS
281593	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Write error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281594	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Replication config file `%s %d` not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS
281595	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: system- Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281596	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS
281597	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Error opening Resync File `%s %d`;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281598	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
281599	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Update Loader %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281600	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Connection to %s %d lost HB late by %s 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281601	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281602	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
281603	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Master Controller `%s %d process started (node %d)	Process has started successfully.	No resolution.	SMS
281604	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281605	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Update Requester `%s %d process registered (node %d)	Information only	No resolution.	SMS
281606	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281607	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281608	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281609	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281610	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281611	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281612	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
281613	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: gethostbyname-Problem getting host `%s %d	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281614	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
281615	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281616	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS
281617	ERROR	DEF123updateLoader: updateLoader(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281618	ERROR	DEF123updateLoader: updateLoader(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281619	CRITICAL	DEF123updateLoader: updateLoader(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281620	ERROR	DEF123updateLoader: updateLoader(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS
281621	ERROR	DEF123updateLoader: updateLoader(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281622	ERROR	DEF123updateLoader: updateLoader(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
281623	ERROR	DEF123updateLoader: updateLoader(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
281624	ERROR	DEF123updateLoader: updateLoader(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
281625	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281626	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
281627	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281628	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281629	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281630	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
281631	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: oraRWRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
281632	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281633	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: %s %d replication process started (node %d)	Resync pass has begun on the SCP	No resolution.	SMS
281634	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
281635	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Finished Database Comparison	Process has competed successfully.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281636	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281637	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281638	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Master Controller `%s %d process started (node %d)	Process has started successfully.	No resolution.	SMS
281639	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281640	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281641	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Node resync process completed	Resyncing has completed for this node.	No resolution.	SMS
281642	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Pending queue now below %d	Internal communications error.	No resolution.	SMS
281643	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Reached master node %d at `%s %d	Client successfully made a connection.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281644	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Resync completed with errors - node partially out of sync	Replication system error	Refer to ORACLE/application expert first. A data error has prevented certain rows from successfully updating. 1) Check the smsMaster log on the SMP and also the updateLoader logs for further details of the rows in question. 2) Further detail can be obtained by manually attempting the failed updates using SQL + . 3) Contact support for further information.	SMS
281645	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Resync started pass %d	Resync pass has started on the SCP	No resolution.	SMS
281646	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Resync successful - node back in sync	Resync pass has completed successfully on the SCP	No resolution.	SMS
281647	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
281648	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Starting Database Comparison	Process has started successfully.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281649	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Update Requester `%s %d` process registered (node %d)	Information only	No resolution.	SMS
281650	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281651	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281652	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Update Requester %d at `%s %d:%d` also connecting from `%s %d:%d`	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
281653	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Update Loader replication process started (node %d)	Process has started successfully.	No resolution.	SMS
281654	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281655	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281656	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281657	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281658	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281659	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Already comparing with master atZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281660	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281661	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281662	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281663	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannt find node at %s %d.%d to return info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281664	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
281665	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Consistency check failed (reason %d)%z	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281666	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281667	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281668	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281669	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281670	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281671	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281672	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281673	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281674	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Pending queue now above %d	Internal communications error.	Assuming basic UNIX skills (Check the following). 1) Are the updateLoaders still connected to the smsMaster? 2) Are the machines still available on the network? 3) The message means that updates that are to be replicated to a given node are building up on the smsMaster faster than the target nodes updateLoader can clear them - as long as they stay connected the queue should clear eventually 4) If problem persists then contact support.	SMS
281675	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Problem opening consistency report file `%s 123ZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281676	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Process %d returned status 0xZZZ	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281677	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Table '%s %d unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281678	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281679	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281680	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update (key values `%s %d,%s %d,%s %d) not in any group of table `%s %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281681	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281682	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281683	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
281684	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281685	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Key name `%s %d is unknown in table `%s %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281686	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Table `%s %d unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281687	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281688	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update (key values `%s %d,%s %d,%s %d` not in any group of table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281689	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Consistency check failed (reason %d);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281690	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Problem opening consistency report file `%s %d`;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281691	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
281692	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281693	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281694	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281695	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281696	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281697	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281698	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281699	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281700	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281701	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281702	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281703	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281704	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281705	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
281706	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281707	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS
281708	WARNING	DEF123updateLoader: updateLoader(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281709	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Oracle unavailable after %d seconds with error: Error while trying to retrieve text for error ORA- %d	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
281710	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281711	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281712	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281713	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281714	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281715	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Updates will be lost onZZZ	Replication system error	Refer to ORACLE/application expert first. Error suggests a communication or configuration fault between the SMP and one of the replication nodes. Check the error logs for the smsMaster and the updateLoader for further details. Contact support for further assistance.	SMS
281716	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
281717	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS
281718	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) CRITICAL: Aiee! cmnPluginReleaseHandle received NULL handle!	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281719	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) CRITICAL: cmnPlugin: error loading library %s %d:%z	Shared library is missing/corrupt	Refer to application expert first. Check validity and permissions of the shared libraries in /IN/service_packages/SMS/lib	SMS
281720	CRITICAL	DEF123smsUpdateRequester: smsUpdateRequester(%d) CRITICAL: malloc() returned NULL in build_filename (cmnLang.cc)! Out of memory!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281721	CRITICAL	DEF123smsUpdateRequester: smsUpdateRequester(%d) CRITICAL: Out of memory in cmnLang.cc:processLine!	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281722	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281723	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281724	CRITICAL	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281725	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR maskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281726	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS
281727	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
281728	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
281729	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR unmaskSignals=%d cmnSignals.c@%d:%z	Kernel error on current machine.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281730	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
281731	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281732	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Bad insert/update/delete option %s %d	Internal software error.	Contact support. No further information can be obtained.	SMS
281733	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Bad num items in template %s %d	Internal software error.	Contact support. No further information can be obtained.	SMS
281734	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Bad syntax template line in %s %d	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
281735	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Cannot get my own key for SINAP, errno is %d	Error talking to SINAP.	Refer to UNIX/application expert first. Error communicating with SINAP. Please check that SINAP is correctly configured and running. Contact support if problem persists.	SMS
281736	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Cannot open file %s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281737	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnDate::getLocalDate:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281738	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindIndex: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281739	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindIndex: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281740	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281741	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281742	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindIndex: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281743	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindIndex: Profile corrupt (TOC end > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281744	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindTag: Profile corrupt (data pos misaligned)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281745	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindTag: Profile corrupt (length < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281746	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset + length > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281747	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset < 0)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281748	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: cmnProfileFindTag: Profile corrupt (offset > profileLength)	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281749	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281750	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Could not load either the requested language file or Default.lang! Falling back to untranslated strings.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Are untranslated (English) strings acceptable? 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281751	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Could not read language index fileZZZ	Attempting to read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281752	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Could not stat() language index fileZZZ	Attempting to obtain the status of the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
281753	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Duplicate templates names	Replication system error	Refer to UNIX/application expert first. Please verify that the replication configuration (SMS Management Screens, Node configuration) is valid, and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS
281754	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Error formatting for template %s %d	Replication system error	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281755	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
281756	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281757	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: formatValues(): Key val %s %d too long, should be %d	Replication system error	Refer to UNIX/application expert first. Please verify that the replication configuration (SMS Management Screens, Node configuration) is valid, and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS
281758	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: formatValues: Expected %d values, found %d	Replication system error	Refer to UNIX/application expert first. Please verify that the replication configuration (SMS Management Screens, Node configuration) is valid, and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS
281759	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Invalid keyformat number %s %d	Replication system error	Refer to UNIX/application expert first. Please verify that the replication configuration (SMS Management Screens, Node configuration) is valid, and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281760	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281761	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Keyformat for unknown key %s %d	Replication system error	Refer to UNIX/application expert first. Please verify that the replication configuration (SMS Management Screens, Node configuration) is valid, and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281762	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281763	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
281764	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: oraRWRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
281765	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Remove tag: Corrupted, tag field data passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281766	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Remove tag: Corrupted, tag length begins before profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281767	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Remove tag: Corrupted, tag length field passes end of profile	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281768	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Replication request failed validation	Replication system error	Contact support. No further information can be obtained.	SMS
281769	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: SINAP Registration ErrorZZZ	Error talking to SINAP.	Refer to UNIX/application expert first. Error communicating with SINAP. Please check that SINAP is correctly configured and running. Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281770	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
281771	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Update block corrupt. Item offset is negative. Creating empty block.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281772	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Update block has no tags but is wrong size. Creating empty profile.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281773	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Update profile corrupt. Field goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281774	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Update profile corrupt. Length goes past profile block len.	Error reading profile block.	Refer to ORACLE expert first. Verify the profile block exists in the database, and that the data is reasonable (using acsProfile). If problem persists then contact support.	SMS
281775	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Validate on unknown template %s %d	Replication system error	Refer to UNIX/application expert first. Please verify that the replication configuration (SMS Management Screens, Node configuration) is valid, and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS
281776	CRITICAL	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE allocate=%d cmnRangeOciFetch.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281777	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281778	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE oparse=%d cmnRangeOciFetch.c@%d:%z	Information only	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281779	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281780	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281781	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
281782	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: cmnConfigGetChar: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281783	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: cmnConfigGetFlag: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS
281784	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: cmnConfigGetInteger: %s %d set %d	Successfully read this parameter in the configuration file.	No resolution.	SMS
281785	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: cmnConfigGetString: %z	Successfully read this parameter in the configuration file.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281786	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281787	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: gethostbyname:%z	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281788	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: Select:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281789	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: socket:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281790	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Error in config file - exiting	Replication system error	Refer to UNIX/application expert first. Please verify that the replication configuration (SMS Management Screens, Node configuration) is valid, and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS
281791	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Cannot register with replication - exiting	Replication system error	Refer to UNIX/application expert first. Please ensure that this replication node is correctly configured (via the SMS Management Screens, Node Management), and that the smsMaster is running on the SMS machine. Contact support if problem persists.	SMS
281792	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR: Cannot register with SINAP - exiting	Error talking to SINAP.	Refer to UNIX/application expert first. Error communicating with SINAP. Please check that SINAP is correctly configured and running. Contact support if problem persists.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281793	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
281794	NOTICE	DEF123smsUpdateRequester: smsUpdateRequester(%d) NOTICE: Startup Successful	Process has started	No resolution.	SMS
281795	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281796	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281797	CRITICAL	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING strdup=%d loggedError.c@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
281798	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Adding empty values for replication	Internal software error.	Contact support. No further information can be obtained.	SMS
281799	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Broken pipe in FIFO read	Internal software error.	No resolution. If problem persists then contact support.	SMS
281800	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: CI out of date - requested is %d	Internal software error.	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281801	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: cmnConfigGetChar: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281802	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: cmnConfigGetFlag: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281803	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: cmnConfigGetInteger: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281804	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: cmnConfigGetString: %z	Attempting to read the configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? Finally contact support.	SMS
281805	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: cmnConfigGetStringVector: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281806	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: cmnPluginLookupFunction: could not find symbol %s %d::%s %d:%z	Internal software error.	Refer to UNIX/application expert first (Check the following). Is the shared library necessary to run the service? If not, remove it from the processes conf file. Otherwise, contact support	SMS
281807	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: cmnPluginReleaseHandle: released already-released pluginZZZ	Internal software error.	Contact support. No further information can be obtained.	SMS
281808	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Could not load language file %s %d! Falling back to Default.lang.	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the default language acceptable? 6) Can you create a new language file for the requested language? 7) Finally contact support.	SMS
281809	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Could not reload language file %s %d! Staying with in-core copy.	Attempting to re- read the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? - likely to be /IN/html/<application>/language/ <language name>.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281810	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
281811	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: getConfig: No trailing : on sectionZZZ	Attempting to read the PIbeClient configuration file has resulted in an error.	Refer to UNIX/application expert first (Check the following). 1) Does the configuration file exist? 2) Are the correct permissions set for the configuration file? 3) Is the configuration file corrupt? 4) Have all the required parameters been entered in the configuration file? 5) Have all the configuration parameters been formatted correctly? 6) Finally contact support.	SMS
281812	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: getValue: unable to openZZZ	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281813	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Language string not found in currently selected language database: %s %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The specified text (%s %d) may not exist in language translation file /IN/html/<application>/language/ <language name>.lang - add an entry to the file for the specified text (%s %d). 6) Finally contact support.	SMS
281814	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Language translation dictionary in %s %d contained an invalid mapping line (no unescaped = sign) on or about line %d	Configuration issue / error	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) The format of the language translation file %s %d is probably wrong - edit the file to put in the missing + sign or delete the offending line . 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281815	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Macro %s %d not found.	Internal software error.	Assuming basic UNIX skills (Check the following). 1) Does the macro name exist? - likely to be /IN/html/<application>/language/macro.lang 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Can the macro name be added to macro.lang? 6) Finally contact support.	SMS
281816	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281817	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: NULL in template %d	Replication system error	Contact support. No further information can be obtained.	SMS
281818	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Replication request with no prior values	Replication system error	Contact support. No further information can be obtained.	SMS
281819	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Replication response for unknown request	Replication system error	Contact support. No further information can be obtained.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281820	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
281821	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281822	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281823	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Updates will be lost onZZZ	Replication system error	Refer to ORACLE/application expert first. Error suggests a communication or configuration fault between the SMP and one of the replication nodes. Check the error logs for the smsMaster and the updateLoader for further details. Contact support for further assistance.	SMS
281824	WARNING	DEF123smsUpdateRequester: smsUpdateRequester(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
281825	CRITICAL	DEF123smsMaster: smsMaster(%d) CRITICAL =%d pendingQServer.C@%d: write- Unable to send update to loader %d; disconnecting.: Broken pipe	Lost communication with update loader.	Refer to application expert. Verify update loader is running, restart if necessary.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281826	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=%d oraUserMod.pc@%d: alter user: ORA123: missing or invalid option	Cannot complete Oracle transaction.	No resolution. This is only a warning.	SMS
281827	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=%d oraUserMod.pc@%d: alter user: ORA123: missing or invalid password(s)	Cannot complete Oracle transaction.	No resolution. This is only a warning.	SMS
281828	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=%d oraUserMod.pc@%d: alter user: ORA123: quoted string not properly terminated	Cannot complete Oracle transaction.	No resolution. This is only a warning.	SMS
281829	ERROR	DEF123updateLoader: updateLoader(%d) ERROR =%d repMsgs.H@%d: Write error: Broken pipe	Replication error. Remote connection has been lost.	Refer to application expert. Check replication sub components.	SMS
281830	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Update Lost: MNP_SUBSCRIBERS (ID)MSISDN,BEARER ,IMSI,PREPAY_FLAG,ROUTING_NUMBER ,PORT_DATE:%z	Information only.	No resolution.	SMS
281831	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR =%d repMsgs.H@%d: Write error: Broken pipe	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281832	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR =%d repMsgs.H@%d: Write error: Bad file number	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281833	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=-%d oraUserMod.pc@%d: create user: ORA-%d: user name %s %d conflicts with another user or role naZZZ	Task Agent tried to create a duplicate account.	No resolution.	SMS
281834	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=-%d oraUserMod.pc@%d: drop user: ORA-%d: cannot drop a user that is currently connected	Task Agent tried to delete an account when the user is logged in.	No resolution.	SMS
281835	CRITICAL	DEF123updateLoader: updateLoader(%d) CRITICAL =%d updateLoader.C@%d: compareResyncReceive has not reset yet; trying again:%z	Waiting for compareResyncRecv to restart.	Refer to application expert. Check compareResyncRecv for errors on startup.	SMS
281836	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE =%d loaderConnections.C@%d: Node resync process completed	Information Only.	No resolution.	SMS
281837	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Update Lost:%z	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
281838	WARNING	DEF123updateLoader: updateLoader(%d) WARNING mmap=%d repConfigRead.c@%d: new file	Information Only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281839	WARNING	DEF123updateLoader: updateLoader(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA-%d: end-of-file on communication channel	Update loader is no longer connected to Oracle.	Refer to ORACLE expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the following environment variables and/or configuration files: 2a) ORACLE_SID(environment) 2b) tnsnames.ora(configuration file) 2c) listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. Finally contact support.	SMS
281840	WARNING	DEF123updateLoader: updateLoader(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA-%d: not connected to ORACLE	Update loader is no longer connected to Oracle.	Refer to ORACLE expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the following environment variables and/or configuration files: 2a) ORACLE_SID(environment) 2b) tnsnames.ora(configuration file) 2c) listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. Finally contact support.	SMS
281841	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE =%d compareResyncRecv.C@%d: Resync successful - node back in sync	Information Only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281842	NOTICE	DEF123compareResyncRecv: compareResyncRecv(%d) NOTICE =%d compareResyncRecv.C@%d: Resync started pass %d	Information Only.	No resolution.	SMS
281843	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING mmap=%d repConfigRead.c@%d: new file	Information Only.	No resolution.	SMS
281844	WARNING	DEF123compareResyncRecv: compareResyncRecv(%d) WARNING OOPEN=%d oraResyncWrite.c@%d: ORA-%d: user requested cancel of current operation	Operation cancelled on users request.		SMS
281845	ERROR	DEF123resyncServer: resyncServer(%d) ERROR OFETCH, OFEN=%d oraResyncRead.pc@%d: ORA-%d: user requested cancel of current operation	Operation cancelled on users request.		SMS
281846	CRITICAL	DEF123smsMaster: smsMaster(%d) CRITICAL =%d loaderConnReceiver.C@%d: write- Unable to send connAck message: Error %d	Cannot contact update loader.	Refer to application expert. Verify update loader. Check loader errors during startup.	SMS
281847	CRITICAL	DEF123smsMaster: smsMaster(%d) CRITICAL =%d unixConnection.C@%d: read-Unix IPC pipe connection lost: No child processes	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
281848	CRITICAL	DEF123smsMaster: smsMaster(%d) CRITICAL =%d unixConnection.C@%d: read-Unix IPC pipe connection lost: Operation would block	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281849	CRITICAL	DEF123smsMaster: smsMaster(%d) CRITICAL =4 pendingQServer.C@%d: write-Unable to send update to loader %d; disconnecting.: Interrupted system call	Cannot contact update loader.	Refer to application expert. Verify update loader specified in alarm string is running. Check loader errors during startup.	SMS
281850	ERROR	DEF123smsMaster: smsMaster(%d) ERROR Oracle=-%d oraEventReader.pc@%d: begin REP_INTERNAL . Block ; end ;: ORA-%d: ORU-%d: error:3 waiting for pipe message.	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
281851	ERROR	DEF123smsMaster: smsMaster(%d) ERROR Oracle=-%d oraEventReader.pc@%d: lock table REP_ORA_EVENT in exclusive mode : ORA-%d: deadlock detected while waiting for resource	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
281852	ERROR	DEF123smsMaster: smsMaster(%d) ERROR Oracle=-%d oraEventReader.pc@%d: select %z ORA-%d: end-of-file on communication channel	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281853	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING Oracle=-%d smsStatsLoader.pc@%d: insert into SMF_STATISTICS(application_id,st atistic_id,node_name,times: ORA- %d: integrity constraint (%s %d) violated - parent key nZZZ	Invalid information in statistic.	Refer to application expert. If alarm persists contact support.	SMS
281854	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING Oracle=-%d smsStatsLoader.pc@%d: insert into SMF_STATISTICS(application_id,st atistic_id,node_name,times: ORA- %d: max # extents (%d) reached in table %s %d	Cannot extend database extents.	Refer to Oracle expert. Configure tablespace to allow more extents.	SMS
281855	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING Oracle=-%d smsStatsLoader.pc@%d: insert into SMF_STATISTICS(application_id,st atistic_id,node_name,times: ORA- %d: not a valid month	Invalid information in statistic.	Refer to application expert. If alarm persists contact support.	SMS
281856	WARNING	DEF123smsStatsLoader: smsStatsLoader(%d) WARNING Oracle=-%d smsStatsLoader.pc@%d: insert into SMF_STATISTICS(application_id,st atistic_id,node_name,times: ORA- %d: trailing null missing from STR bind value	Invalid information in statistic.	Refer to application expert. If alarm persists contact support.	SMS
281857	ERROR	DEF123smsUpdateRequester: smsUpdateRequester(%d) ERROR =%d mcFuncs.C@%d: Update Requester `%s %d process registered (node %d)	Information only	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281858	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL =%d slaveConnections.C@%d: No Master Found - suggests a replication config error	Internal replication error.	Refer to application expert. Verify replication configuration.	SMS
281859	CRITICAL	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) CRITICAL =%d tcpConnection.C@%d: setsockopt- Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281860	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR =%d slaveConnections.C@%d: Unable to reach master node %d at `%d.%d.%d.%d`	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281861	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR =%d tcpConnection.C@%d: TCP connection to %d.%d.%d.%d was lost	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281862	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: read- Connection read error - Connection refused	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281863	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: setsockopt-Problem setting socket option - Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281864	ERROR	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) ERROR: Write error - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281865	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) NOTICE =%d mcFuncs.C@%d: Update Requester %s %d process registered (node %d)	Information only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281866	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: insert_internal: Maximum alarm list size %d reached	Too many alarms!	Refer to application expert. Flush out SMF_ALARM_MESSAGE table.	SMS
281867	ERROR	DEF123smsAlarmMonitor: smsAlarmMonitor(%d) ERROR Oracle=%d oraConnect.pc@%d: select countZZZ	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS
281868	WARNING	DEF123smsAlarmMonitor: smsAlarmMonitor(%d) WARNING: Oracle unavailable after %d seconds with error: ORA123: unable to allocate %d bytes of shared memoryZZZ	Error writing to shared memory.	Contact support.	SMS
281869	ERROR	DEF123smsAlarmMonitorJanitor: smsAlarmMonitorJanitor(%d) ERROR Oracle=%d oraConnect.pc@%d: select countZZZ	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS
281870	WARNING	DEF123smsAlarmMonitorJanitor: smsAlarmMonitorJanitor(%d) WARNING: Oracle unavailable after %d seconds with error: ORA123: error occurred at recursive SQL level %d	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS
281871	CRITICAL	smsCompareResyncClient: smsCompareResyncClient(%d) CRITICAL: Lost connection to the server. The current resync has failed. The client will now await another connection from the server. IOException: errno 123ZZZ	Information only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281872	ERROR	smsCompareResyncClient: smsCompareResyncClient(%d) ERROR: Connection to server failed:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281873	ERROR	smsCompareResyncClient: smsCompareResyncClient(%d) ERROR: Meta Data Extraction Error - ORA123: statement handle not executed	Oracle statement failed.	Refer to application expert. Check alarm string for full detail.	SMS
281874	ERROR	smsCompareResyncClient: smsCompareResyncClient(%d) ERROR: OCI Error - (%s %d) Get Of Attribute Failed	Oracle internal error.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281875	ERROR	smsCompareResyncClient: smsCompareResyncClient(%d) ERROR: OCI Error - (%s %d) Session Begin Failed	Oracle internal error.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281876	ERROR	smsCompareResyncClient: smsCompareResyncClient(%d) ERROR: There has been a problem with the configuration from the server. Cancelling the current resynchronisation/comparison request. Replication system view parsing error at line 123ZZZ	Configuration error.	Refer to application expert. Check alarm string for full detail.	SMS
281877	NOTICE	smsCompareResyncClient: smsCompareResyncClient(%d) NOTICE: Beginning resynchronisation for node %d.	Starting resynchronisation for specified node.	No resolution.	SMS
281878	NOTICE	smsCompareResyncClient: smsCompareResyncClient(%d) NOTICE: Ending resynchronisation for node %d. Resynchronisation was successful.	Ending resynchronisation for specified node.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281879	CRITICAL	smsCompareResyncServer: smsCompareResyncServer(%d) CRITICAL: Lost connection to the server. The current resync has failed. The client will now await another connection from the server.	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281880	CRITICAL	smsCompareResyncServer: smsCompareResyncServer(%d) CRITICAL: SQL Select FailedZZZ	Oracle statement failed.	Refer to application expert. Check alarm string for full detail.	SMS
281881	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Caught exception:%z	Received an unexpected exception.	No resolution.	SMS
281882	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Connect to Database Failed For User NameZZZ	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281883	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Connection to server failed:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281884	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Failed SMS comparison/resync service: Config file syntax errorZZZ	Configuration error.	Refer to application expert. Check alarm string for full detail.	SMS
281885	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Failed SMS comparison/resync service: IOException: errno %d (Operation now in progress): Unable to read accept message. Timeout on reading message from socket.	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281886	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Failed SMS comparison/resync service: SQL Select Failed With The Following Oracle Error - ORA123: unable to read data - table definition has changed	Internal error.	Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281887	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Failed SMS comparison/resync service: The client node was unable to accept our connection request. Another request is currently being processed.	Information only.	No resolution.	SMS
281888	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Lost connection to the server during startup. The current resync/comparison has been cancelled and the client will now await another connection from the server.%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281889	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Meta Data Extraction Error - ORA123: statement handle not executed	Oracle statement failed.	Refer to application expert. Check alarm string for full detail.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281890	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: OCI Error - (OCIAttrGet) Get Of Attribute Failed	Oracle internal error.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281891	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Reading the command line configuration failed:Replication view build error: the group SMF_STATISTICS_DEFN is not unique. Every group must have a unique name.	Command line error.	Refer to application expert. Check alarm string for full detail.	SMS
281892	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: There has been a problem with the configuration from the server. Cancelling the current resynchronisation/comparison request.%z	Configuration problem.	Refer to application expert. Verify configuration, check startup for errors.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281893	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Unable to connect to the server database with the connection string:%z	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281894	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Beginning resynchronisation for node %d.	Starting resynchronisation for specified node.	No resolution.	SMS
281895	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Ending resynchronisation for node %d.	Ending resynchronisation for specified node.	No resolution.	SMS
281896	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Resynchronisation failed because: IOException: errno %d (Connection reset by peer): Unable to read message. for node %d.	Resynchronisation failed. Remote host has closed.	Refer to application expert. Check alarm string for full detail.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281897	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Resynchronisation failed because: IOException: errno %d (Resource temporarily unavailable) for node %d.	Resynchronisation failed. Remote host has closed.	Refer to application expert. Check alarm string for full detail.	SMS
281898	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Resynchronisation failed because: IOException: Timeout on writing message to socket %d. for node %d.	Resynchronisation failed. Remote host has closed.	Refer to application expert. Check alarm string for full detail.	SMS
281899	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Resynchronisation was successful for node %d.	Resynchronisation was successful	No resolution.	SMS
281900	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Statement being Processed wasZZZ	Information only.	No resolution.	SMS
281901	WARNING	smsCompareResyncServer: smsCompareResyncServer(%d) WARNING: Could not accept connection from SMS server:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281902	WARNING	smsCompareResyncServer: smsCompareResyncServer(%d) WARNING: ERROR: No connection even though listener.isNewConnection() said there was.	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281903	WARNING	smsCompareResyncServer: smsCompareResyncServer(%d) WARNING: Unknown command message type %d received. Ignoring.	Information only.	No resolution.	SMS
281904	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: No match found for %s %d, skipping this configuration file entry.	Cannot find file to process.	No resolution.	SMS
281905	NOTICE	DEF123smsLogCleaner: smsLogCleaner(%d) NOTICE: Starting smsLogCleaner. Using configuration file %s %d	Information only.	No resolution.	SMS
281906	ERROR	DEF123smsMaster: smsMaster(%d) ERROR Oracle=%d oraConnect.pc@%d:%z	Internal replication error.	Contact support.	SMS
281907	ERROR	DEF123smsMaster: smsMaster(%d) ERROR Oracle=%d oraEventReader.pc@%d:%z	Internal replication error.	Contact support.	SMS
281908	ERROR	DEF123smsMaster: smsMaster(%d) ERROR Oracle=%d oraRepPendingQ.pc@%d:%z	Internal replication error.	Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281909	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: accept-Connection accept error - Software caused connection abort	Internal communications error.	If problem persists contact support.	SMS
281910	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: bind-Problem binding socket %d - Address already in use	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281911	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Connection read error - Connection timed out	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281912	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Unix IPC pipe connection lost - Inappropriate ioctl for device	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281913	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Unix IPC pipe connection lost - Interrupted system call	Internal communications error.	If problem persists contact support.	SMS
281914	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Unix IPC pipe connection lost - Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281915	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Unix IPC pipe connection lost - No child processes	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281916	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Unix IPC pipe connection lost - No such file or directory	File error.	Verify file exists. Check permissions, etc.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281917	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Unix IPC pipe connection lost - Resource temporarily unavailable	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281918	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: read-Unix IPC pipe connection lost - Software caused connection abort	Internal communications error.	If problem persists contact support.	SMS
281919	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: Write error - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281920	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: write-Unable to send connAck message - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281921	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: write-Unable to send update to loader %d; disconnecting. - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281922	ERROR	DEF123smsMaster: smsMaster(%d) ERROR: write-Unable to send update to loader %d; disconnecting. - Interrupted system call	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281923	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Connection FD %d identified as Controller Connection (Node %d)	Information only.	No resolution.	SMS
281924	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Connection FD %d identified as Loader Connection (Node %d)	Information only.	No resolution.	SMS
281925	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Connection FD %d identified as Requester Connection (Node %d)	Information only.	No resolution.	SMS
281926	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: New Connection from %d.%d.%d.%d:%d accepted (FD %d)	Information only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281927	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OBNDNRN=%d oraOci.c@%d: ORA123: not connected to ORACLE	No longer connected to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281928	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: end-of-file on communication channel	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281929	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: error occurred at recursive SQL level %d	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS
281930	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: fatal two-task communication protocol error	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS
281931	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: unable to allocate %d bytes of shared memoryZZZ	Error writing to shared memory.	Contact support.	SMS
281932	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: unable to extend index %s %d by %d in tablespaceZZZ	Out of disk space.	Refer to Oracle expert. Free some disk space to allow the tablespace to be extended.	SMS
281933	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: unsupported network datatype or representation	Internal error.	Contact support.	SMS
281934	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA123: error occurred at recursive SQL level %d	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281935	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA123: not connected to ORACLE	No longer connected to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281936	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA123: unable to allocate %d bytes of sharedZZZ	Error writing to shared memory.	Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281937	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA123: error occurred at recursive SQL level %d	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281938	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA123: unable to allocate %d bytes of shared memoryZZZ	Error writing to shared memory.	Contact support.	SMS
281939	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Pending queue now above %d (Worst Node %d)	Internal communications error.	No resolution.	SMS
281940	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Updates will be lost on %s %d	Suggests a replication error elsewhere.	Refer to application expert. Check node for errors.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281941	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Connection pipe broke	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281942	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Connection to node number %d timed out, deleting	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281943	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Failed to start connecting to node number %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281944	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Master node 1 not found	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281945	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Received ConnectAck for unknown connection.	Internal state error.	No resolution.	SMS
281946	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Received MergeNeeded for unknown connection.	Internal state error.	No resolution.	SMS
281947	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Received MergeNeeded in state %s %d	Internal state error.	No resolution.	SMS
281948	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Replication config file %s %d not found	Internal replication error.	Refer to application expert. Verify replication configuration.	SMS
281949	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: select returned errno = %d	Oracle statement failed.	Refer to application expert. Check alarm string for full detail.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281950	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: setsockopt-Problem setting socket option - Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281951	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: State %s %d, failed to query node number %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281952	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: TCP connection to %d.%d.%d.%d was lost	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281953	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Unable to reach master node %d at `%d.%d.%d.%d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281954	ERROR	DEF123smsMergeDaemon: smsMergeDaemon(%d) ERROR: Unable to reach master node %d atZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281955	NOTICE	DEF123smsMergeDaemon: smsMergeDaemon(%d) NOTICE: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281956	NOTICE	DEF123smsMergeDaemon: smsMergeDaemon(%d) NOTICE: Connection to master dropped, restarting	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281957	NOTICE	DEF123smsMergeDaemon: smsMergeDaemon(%d) NOTICE: connect-Problem connecting socket - %z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281958	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) CRITICAL: Cannot export IOR to Naming Server	Cannot write to DB.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281959	ERROR	DEF123smsReportsDaemon: smsReportsDaemon(%d) ERROR: generateReport:stat: No such file or directory	Cannot write/find report.	Refer to application expert. Verify report exists and that the resulting file can be written to the report directory.	SMS
281960	NOTICE	DEF123smsReportsDaemon: smsReportsDaemon(%d) NOTICE: Attempting to connect. Attempt %d of %d	Information only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281961	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) CRITICAL: ora_connectZZZ	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281962	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Connection pipe broke	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281963	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Connection to `%d.%d.%d.%d` lost HB late by 123ms	Heartbeat was late	Refer to LAN expert if problem persists.	SMS
281964	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: No Master Found - suggests a replication config error	Internal replication error.	Refer to application expert. Verify replication configuration.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281965	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: read- Connection read error - Bad file number	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281966	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: read- Connection read error - Connection refused	Lost connection to update requester	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281967	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Replication config file %s %d not found	File error.	Refer to application expert. Verify replication configuration file exists, permissions, etc.	SMS
281968	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: setsockopt-Problem setting socket option - Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281969	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: TCP connection to %d.%d.%d.%d was lost	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281970	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Unable to reach master node %d at `%d.%d.%d.%d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281971	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Unexpected behaviour	Internal error.	Refer to application expert. Check log file for additional information. Contact support.	SMS
281972	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Write error - Bad file number	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281973	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Write error - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281974	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: Connect attempt timed out after %d secs	Lost connection to update requester	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281975	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: Reached master node %d at '%d.%d.%d.%d	Information only.	No resolution.	SMS
281976	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: SIGTERM received. Deleting share memory segment before exiting.	Information only.	No resolution.	SMS
281977	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: Update Requester %s %d process registered (node %d)	Update requester registered.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281978	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING: Oracle unavailable after %d seconds with error: ORA123: ORACLE initialization or shutdown in progress	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
281979	ERROR	DEF123updateLoader: updateLoader(%d) ERROR: Write error - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281980	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Node back in sync	Update loader node is back in sync.	No resolution.	SMS
281981	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Terminating on signal %d	Quiesing.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281982	CRITICAL	DEF123updateLoader: updateLoader(%d) CRITICAL =%d slaveConnections.C@%d: No Master Found - suggests a replication config error	Internal replication error.	Refer to application expert. Verify replication configuration.	SMS
281983	CRITICAL	DEF123updateLoader: updateLoader(%d) CRITICAL =%d tcpConnection.C@%d: setsockopt- Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281984	ERROR	DEF123updateLoader: updateLoader(%d) ERROR =%d slaveConnections.C@%d: Unable to reach master node %d at '%d.%d.%d.%d	Cannot connect to smsMaster.	Refer to application expert. Verify smsMaster is operational and contactable.	SMS
281985	ERROR	DEF123updateLoader: updateLoader(%d) ERROR =%d tcpConnection.C@%d: Connect attempt timed out after %d secs	Cannot connect to smsMaster.	Refer to application expert. Verify smsMaster is operational and contactable.	SMS
281986	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE =%d updateLoader.C@%d: Update Loader replication process started (node %d)	updateLoader started.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281987	CRITICAL	DEF123smsStatsDaemon: smsStatsDaemon(%d) CRITICAL Statistics database cannot be contacted (Statistics database connection unavailable)	Cannot contact database.	Refer to ORACLE expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the following environment variables and/or configuration files: 2a) ORACLE_SID(environment) 2b) tnsnames.ora(configuration file) 2c) listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. Finally contact support.	SMS
281988	ERROR	DEF123smsStatsLoader: smsStatsLoader(%d) ERROR Oracle=%d oraConnect.pc@%d: declare function dexpo (base integer , exp integer , modulus integer : ORA-%d: max # extents (%d) reached in indexZZZ	Out of table space.	Refer to ORACLE/application expert first, check the tablespace sizing for the SMF database. Finally contact support.	SMS
281989	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=%d oraUserMod.pc@%d: begin SMF_SECURITY: ORA-%d: max # extents (%d) reached in indexZZZ	Out of table space.	Refer to ORACLE/application expert first, check the tablespace sizing for the SMF database. Finally contact support.	SMS
281990	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: max # extents (%d) reached in indexZZZ	Out of table space.	Refer to ORACLE/application expert first, check the tablespace sizing for the SMF database. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281991	NOTICE	DEF123smsAlarmDaemon: smsAlarmDaemon(Heart beat) I am healthy.	Information Only.	No resolution.	SMS
281992	WARNING	smsCompareResyncClient: smsCompareResyncClient(%d) WARNING: Could not accept connection from SMS server:%z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281993	NOTICE	smsCompareResyncClient: smsCompareResyncClient(%d) NOTICE: Ending resynchronisation for node %d. Resynchronisation partially failed because: There were %d failures when merging data into the SCP database..	Replication error.	Refer to application expert. Check errors in associated log file. Check smsMaster log file.	SMS
281994	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Resynchronisation failed because: There were %d failures when merging data into the SCP database. for node %d.	Replication error.	Refer to application expert. Check errors in associated log file. Check smsMaster log file.	SMS
281995	WARNING	DEF123smsMaster: smsMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: check constraint (%s %d) violated	Database constraint violation. Cannot update the database.	Refer to Oracle expert. Quote constraint name.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281996	WARNING	DEF123smsMaster: smsMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: TNS:no listener	Oracle is unavailable.	Refer to ORACLE expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the following environment variables and/or configuration files: 2a) ORACLE_SID(environment) 2b) tnsnames.ora(configuration file) 2c) listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. Finally contact support.	SMS
281997	WARNING	DEF123smsReportsScheduler: smsReportsScheduler(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: TNS:no listener	Oracle is unavailable.	Refer to ORACLE expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the following environment variables and/or configuration files: 2a) ORACLE_SID(environment) 2b) tnsnames.ora(configuration file) 2c) listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
281998	NOTICE	DEF123smsStatsDaemon: smsStatsDaemon(%d) NOTICE: connect-Problem connecting socket - Network is unreachable	Cannot contact remote host.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
281999	WARNING	DEF123smsStatsDaemon: smsStatsDaemon(%d) WARNING mmap=%d repConfigRead.c@%d: new file	Information Only.	No resolution.	SMS
282000	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: Error renaming %s %d to %s %d Error was No such file or directory.	Cannot rename file.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282001	WARNING	DEF123smsStatsThreshold: smsStatsThreshold(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: TNS:no listener	Oracle is unavailable.	Refer to ORACLE expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the following environment variables and/or configuration files: 2a) ORACLE_SID(environment) 2b) tnsnames.ora(configuration file) 2c) listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. Finally contact support.	SMS
282002	NOTICE	DEF123smsTaskAgent: smsTaskAgent(%d) NOTICE: Attempting to connect. Attempt %d of %d	Information Only.	No resolution.	SMS
282003	ERROR	DEF123updateLoader: updateLoader(%d) WARNING: Full resyncs will be suppressed. Please monitor carefully for resync warnings.	Information Only.	No resolution.	SMS
282004	ERROR	DEF123updateLoader: updateLoader(%d) WARNING: Resync file present (should not be).	Information Only.	Refer to application expert. Remove -nofullresync, add - resync to the startup and restart the updateLoader. Once full resync complete then remove -resync and add -nofullresync and restart the updateLoader.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282005	ERROR	DEF123updateLoader: updateLoader(%d) WARNING: Full resync has been suppressed. Node out of sync. Please schedule a full resync.	Information Only.	Refer to application expert. Remove -nofullresync, add - resync to the startup and restart the updateLoader. Once full resync complete then remove -resync and add -nofullresync and restart the updateLoader.	SMS
282006	WARNING	DEF123updateLoader: updateLoader(%d) WARNING: Failure during resync.	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282007	ERROR	smsCompareResyncServer: smsCompareResyncServer(%d) ERROR: Failed SMS comparison/resync service: cmn::cfg::Value::NotFound: Key not found:%z	Configuration file error.	Refer to application expert. Missing config section in config file.	SMS
282008	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Could not reset %s %d file size to %d. I probably dont have write permissions.	Cannot resize file.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
282009	ERROR	DEF123smsLogCleaner: smsLogCleaner(%d) ERROR: Archive directory %s %d doesnt exist, and cannot be created.	Cannot open directory.	Assuming basic UNIX skills (Check the following). 1) Does the specified directory exist? 2) Are the correct permissions set? 3) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282010	WARNING	DEF123smsLogCleaner: smsLogCleaner(%d) WARNING: Failure to open archive directory for cleanup.	Cannot open directory.	Assuming basic UNIX skills (Check the following). 1) Does the specified directory exist? 2) Are the correct permissions set? 3) Is the disk full? Finally contact support.	SMS
282011	WARNING	%s %d.log: %s %d.log(%d) WARNING: Failure to open archive directory for cleanup.	Cannot open directory.	Assuming basic UNIX skills (Check the following). 1) Does the specified directory exist? 2) Are the correct permissions set? 3) Is the disk full? Finally contact support.	SMS
282012	NOTICE	%s %d.log: %s %d.log(%d) NOTICE: No match found for %s %d, skipping this logjob.conf entry.	Cannot open file.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
282013	ERROR	%s %d.log: %s %d.log(%d) ERROR: Archive directory doesnt exist, and cannot be created.	Cannot open directory.	Assuming basic UNIX skills (Check the following). 1) Does the specified directory exist? 2) Are the correct permissions set? 3) Is the disk full? Finally contact support.	SMS
282014	ERROR	%s %d.log: %s %d.log(%d) ERROR: Could not reset %s %d file size to %d. I probably dont have write permissions.	Cannot resize file.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282015	WARNING	%s %d.log: %s %d.log(%d) WARNING: No type given for file size so using straight byte - not Kbyte or MegByte.	Information only.	None.	SMS
282016	WARNING	%s %d.log: %s %d.log(%d) WARNING: Unknown Configuration Command: %z	Error in configuration file.	Refer to application expert. Verify /IN/service_packages/SMS/etc/log job.conf.	SMS
282017	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=-%d oraUserMod.pc@%d: alter user: ORA-%d: user %s %d does not exist	Tried to alter an SMS user that does not exist.	None.	SMS
282018	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=-%d oraUserMod.pc@%d: begin SMF_SECURITY: ORA-%d: TNS:listener failed to start a dedicated server process	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282019	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=-%d oraUserMod.pc@%d: delete : ORA-%d: integrity constraint (ACS_ADMIN.%s %d) violatedZZZ	DB constraint violated.	Refer to application/Oracle expert if problem persists.	SMS
282020	WARNING	DEF123smsTaskAgent: smsTaskAgent(%d) WARNING Oracle=-%d oraUserMod.pc@%d: drop user: ORA-%d: user %s %d does not exist	Tried to delete an SMS user that does not exist.	None.	SMS
282021	NOTICE	smsCompareResyncClient: smsCompareResyncClient(%d) NOTICE: Beginning comparison for nodeZZZ	Node comparison has started.	No action required.	SMS
282022	NOTICE	smsCompareResyncClient: smsCompareResyncClient(%d) NOTICE: Ending comparison for node %d. Comparison was successful.	Node comparison has finished.	No action required.	SMS
282023	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Beginning comparison for nodesZZZ	Node comparison has started.	No action required.	SMS
282024	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Comparison was successful for node %d.	Node comparison has finished.	No action required.	SMS
282025	NOTICE	smsCompareResyncServer: smsCompareResyncServer(%d) NOTICE: Ending comparison for nodesZZZ	Node comparison has finished.	No action required.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282026	WARNING	smsStatsDaemon: smsStatsDaemon(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: ORACLE not available	Cannot connect to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282027	NOTICE	DEF123smsAlarmManager: smsAlarmManager(%d) NOTICE: smsAlarmManager started.	Process has started successfully.	No resolution.	SMS
282028	CRITICAL	DEF123smsAlarmManager: smsAlarmManager(%d) CRITICAL: Cmdline param error - %z : %z	Configuration error for smsAlarmManager	Check the arguments for the smsAlarmManager in the smsAlarmManagerStartup.sh script. Type smsAlarmManager - help for supported options.	SMS
282029	ERROR	DEF123smsAlarmManager: smsAlarmManager(%d) ERROR: Invalid cache type %d specified for %z \{%d\}	Internal software error.	The smsAlarmManager is failing to read the alarm registry correctly. Contact support.	SMS
282030	ERROR	DEF123smsAlarmManager: smsAlarmManager(%d) ERROR: Regex compilation failed for %z : %z (%d)	Alarm registry database has an entry that cannot be parsed by the smsAlarmManager	Check the contents of SMF_ALARM_DEFN. In particular the REGULAR_EXPRESSION for the entry listed.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282031	ERROR	DEF123smsAlarmManager: smsAlarmManager(%d) ERROR: Regexp matching failed for %z : %z (%d)	An alarm was produced that failed comparison with the registry.	Check the source of the mentioned alarm. Contact support.	SMS
282032	CRITICAL	DEF123smsAlarmManager: smsAlarmManager(%d) CRITICAL: Config (re)load failure.	An Oracle error occurred.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
282033	CRITICAL	DEF123smsAlarmManager: smsAlarmManager(%d) CRITICAL: Alarm Type ID generation failure.	An Oracle error occurred.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282034	CRITICAL	DEF123smsAlarmManager: smsAlarmManager(%d) CRITICAL: Clearance alarm correlation failure.	An Oracle error occured.	Refer to ORACLE/application expert first (Check the following). 1)Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
282035	CRITICAL	DEF123smsAlarmManager: smsAlarmManager(%d) CRITICAL: Alarm auto-timeout failure.	An Oracle error occured.	Refer to ORACLE/application expert first (Check the following). 1)Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
282036	ERROR	DEF123smsAlarmManager: smsAlarmManager(%d) ERROR: Connection to Oracle failed	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1)Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282037	NOTICE	DEF123smsAlarmManager: smsAlarmManager(%d) NOTICE: smsAlarmManager terminated successfully.	Process has stopped successfully.	No resolution.	SMS
282038	ERROR	DEF123smsAlarmManager: smsAlarmManager(%d) ERROR: ORACLE error %z (SQL: %z).	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1)Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS
282039	ERROR	DEF123smsAlarmManager: smsAlarmManager(%d) ERROR: Ignore Cache load failed.	SmsAlarmManager failed to populate alarm information from database.	Check contents of the SMF_ALARM_IGNORE table. Check connection to the Oracle SMF database.	SMS
282040	ERROR	DEF123smsAlarmManager: smsAlarmManager(%d) ERROR: Main Cache load failed.	SmsAlarmManager failed to populate alarm information from database.	Check contents of the SMF_ALARM_DEFN table. Check connection to the Oracle SMF database.	SMS
282041	WARNING	DEF123smsAlarmManager: smsAlarmManager(%d) WARNING: No rows found to populate Ignore Cache.	SmsAlarmManager failed to populate alarm information from database.	Check contents of the SMF_ALARM_IGNORE table. Check connection to the Oracle SMF database.	SMS
282042	WARNING	DEF123smsAlarmManager: smsAlarmManager(%d) WARNING: Rows found to populate Ignore Cache but none inserted successfully.	SmsAlarmManager failed to populate alarm information from database.	Check contents of the SMF_ALARM_IGNORE table. Check connection to the Oracle SMF database.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282043	WARNING	DEF123smsAlarmManager: smsAlarmManager(%d) WARNING: No rows found to populate Main Cache.	SmsAlarmManager failed to populate alarm information from database.	Check contents of the SMF_ALARM_DEFN table. Check connection to the Oracle SMF database.	SMS
282044	WARNING	DEF123smsAlarmManager: smsAlarmManager(%d) WARNING: Rows found to populate Main Cache but none inserted successfully.	SmsAlarmManager failed to populate alarm information from database.	Check contents of the SMF_ALARM_DEFN table. Check connection to the Oracle SMF database.	SMS
282045	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: unknown variable name %z	EFM Relay filter refers to an unknown column from the alarm table	Check contents of the SMF_ALARM_RELAY_FILTER table. Make sure that all VALUE entries are correct.	SMS
282046	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: rule %z not found	EFM Relay combination filter refers to an unknown filter.	Check contents of the SMF_ALARM_RELAY_FILTER table. Make sure that all combination VALUE entries refer to defined filters.	SMS
282047	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: unknown operation %z	EFM Relay combination filter refers to an unknown operation.	Check contents of the SMF_ALARM_RELAY_FILTER table. Make sure that all combination VALUE entries use AND, OR and AND NOT only.	SMS
282048	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: max recursion depth (%d) reached. Test aborted	EFM Relay filters contain a self- referential definition	Correct the circular definition of combination filters in the SMF_ALARM_RELAY_FILTER table.	SMS
282049	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Cannot send X733 Format without Enhanced Fault Management. Using non-X733 format.	Configuration error for smsAlarmRelay	Check the arguments for the smsAlarmRelay in the smsAlarmRelayStartup.sh script. -x can only be used when -e is present.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282050	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: EMAIL target is deprecated. Ignored.	Configuration error for smsAlarmRelay	Remove the EMAIL target from the SMF_ALARM_HANDLER table.	SMS
282051	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: PRINTER target is deprecated. Ignored.	Configuration error for smsAlarmRelay	Remove the PRINTER target from the SMF_ALARM_HANDLER table.	SMS
282052	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: couldnt insert EFM rule for %z	EFM Relay filter refers to an unparsable value	Check contents of the SMF_ALARM_RELAY_FILTER table. Make sure that all VALUE entries are correct.	SMS
282053	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: couldnt open %z : assuming first boot	File error.	No action required, if the first boot of smsAlarmRelay. Otherwise check permissions of the file /IN/service_packages/SMS/etc/sms AlarmRelay.boots	SMS
282054	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: parse error: integer expected for boot count. Assuming 0.	File error.	No action required, if the first boot of smsAlarmRelay. Otherwise check contents of the file /IN/service_packages/SMS/etc/sms AlarmRelay.boots	SMS
282055	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: error moving file %z to %z : %z	File error.	Unable to store the number of boots for smsAlarmRelay. Check permissions of the /IN/service_packages/SMS/etc directory.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282056	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: failed to open listener socket: %z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282057	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: binding socket: %z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282058	CRITICAL	DEF123smsAlarmRelay: smsAlarmRelay(%d) CRITICAL: unknown username %z , cannot change uid	Configuration error for smsAlarmRelay	Check username variable in snmp.cfg	SMS
282059	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: zero- length or bad hostname %z	Configuration error for smsAlarmRelay	Destination for an SNMP target in the table SMF_ALARM_HANDLER is incorrect.	SMS
282060	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Parse error reading IP-address %z	Configuration error for smsAlarmRelay	Destination for an SNMP target in the table SMF_ALARM_HANDLER is not a valid IP address.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282061	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Unknown hostname/IP %z	Configuration error for smsAlarmRelay	Destination for an SNMP target in the table SMF_ALARM_HANDLER refers to an invalid hostname. Check connection and configuration for mentioned hostname.	SMS
282062	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Failed to send trap: %z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282063	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Corrupt, or non-SNMP packet discarded	Incoming SNMP message is corrupt.	Check incoming SNMP packets to the smsAlarmRelay port. Find the element that is sending corrupt packets and correct it.	SMS
282064	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: Expected data size doesnt match actual. Bad packet?	Incoming SNMP message is corrupt.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager.	SMS
282065	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: decode error on received SNMP message. Discarding	Incoming SNMP message is corrupt.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager.	SMS
282066	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: decode error or illegal value for security model. Ignoring	Incoming SNMP message is corrupt.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282067	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: nonzero scopedPDU errorStatus. Ignoring	Incoming SNMP messagecontains a non-zero errorStatus.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager.	SMS
282068	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: nonzero scopedPDU errorIndex. Ignoring	Incoming SNMP messagecontains a non-zero errorIndex.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager.	SMS
282069	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: illegal SNMP get-request made for one or more variable types returning error to originator	Incoming SNMP messagecontains a non-zero errorIndex.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager. Check the MIB contents for the smsAlarmRelay that the SNMP manager is using.	SMS
282070	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: decode error or unsupported SNMP header flag set. Ignoring	Incoming SNMP messagecontains an uninterpretable header.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager. Check the MIB contents for the smsAlarmRelay that the SNMP manager is using.	SMS
282071	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: error decoding variable/value sequence	Incoming SNMP messagecontains an uninterpretable variable.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager. Check the MIB contents for the smsAlarmRelay that the SNMP manager is using.	SMS
282072	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: set attempt for unknown variable	Incoming SNMP messagecontains an uninterpretable variable.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager. Check the MIB contents for the smsAlarmRelay that the SNMP manager is using.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282073	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: new value for lastChgOid is not an int	Incoming SNMP messagecontains an uninterpretable value.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager. Check the MIB contents for the smsAlarmRelay that the SNMP manager is using.	SMS
282074	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: error decoding value for lastChgOid	Incoming SNMP messagecontains an uninterpretable value.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager. Check the MIB contents for the smsAlarmRelay that the SNMP manager is using.	SMS
282075	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: new value for lastChgSeq (%d) is greater than current value (%d)	Incoming SNMP set value is not valid.	No action required. The relay will forward the requested alarms as they become available.	SMS
282076	WARNING	DEF123smsAlarmRelay: smsAlarmRelay(%d) WARNING: unsupported pduType %d.%d. Ignoring	Incoming SNMP messagecontains an uninterpretable PDU.	Check incoming SNMP packets to the smsAlarmRelay port. Check status of the SNMP manager. Check the MIB contents for the smsAlarmRelay that the SNMP manager is using.	SMS
282077	ERROR	DEF123smsAlarmRelay: smsAlarmRelay(%d) ERROR: Failed to send SNMP reply: %z	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282078	WARNING	smsReportsScheduler: smsReportsScheduler(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: ORACLE not available	Cannot connect to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282079	WARNING	smsAlarmManager: smsAlarmManager(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: ORACLE not available	Cannot connect to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282080	WARNING	smsStatsThreshold: smsStatsThreshold(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: ORACLE not available	Cannot connect to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282081	CRITICAL	DEF123smsStatsThreshold: smsStatsThreshold(%d) CRITICAL: Cannot connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282082	ERROR	DEF123smsTaskAgent: smsTaskAgent(%d) ERROR: Error transferring to primary IP %z for node %z	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
282083	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: socket-Problem with opening socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282084	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Unable to find the program %s %d	Attempting to open the current file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? 5) Is the file available but the PATH for the current user is not set to find it? 6) Finally contact support.	SMS
282085	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Connection message expected not %s %d;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
282086	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Connection type `%s %d not implemented yet;	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
282087	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: select-Connection manager select error	Internal communications error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
282088	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Update Loader message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282089	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282090	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Connect ack message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282091	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Inferior master message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282092	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Master Controller message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282093	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: write-Unable to send connAck message	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282094	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Update Loader %d now out of history on master %d	Replication system error	Contact support. The node in question is now out-of-sync with the SMP machine!	SMS
282095	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: write-Unable to send update to loader %d; disconnecting.	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282096	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: write-Failure to send Info msg	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282097	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282098	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: accept-Connection accept error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282099	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: bind-Problem binding socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282100	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: bind-Problem listening on socket	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282101	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: connect-Problem connecting socketZZZ	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282102	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282103	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: read-Connection read error	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282104	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: select-Error from socket select	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282105	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: setsockopt-Problem setting socket option: Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282106	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282107	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: fcntl-Problem setting socking blocking to %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282108	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: ioctl-Unable to set TCP socket to close on exec (F_SETFD)	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282109	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: read-Unix IPC pipe connection lost	Internal software error.	No resolution. If problem persists then contact support.	SMS
282110	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: read-Unix IPC pipe read error	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282111	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: select-DB Event Reader select error	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
282112	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: socketpair-Unable to open socketpair	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282113	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Unexpected msg of type %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282114	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Unknown Unix IPC message %d received	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS
282115	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Update Requester message expected notZZZ	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282116	ERROR	DEF123infMaster: infMaster(%d) CRITICAL logic=%d oraUpdateLoader.c@%d: hash table corrupt	Internal software error.	No resolution. Contact support.	SMS
282117	ERROR	DEF123infMaster: infMaster(%d) ERROR: Replication config file `%s %d not found	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network / for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected - check the updateLoader log for details. 6) Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282118	ERROR	DEF123infMaster: infMaster(%d) ERROR: system-Error copying config file to hostZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is this the first time that the node in question has been replicated to? 2) Is the target machine available - on the network for FTP access? 3) Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6) Finally contact support.	SMS
282119	ERROR	DEF123infMaster: infMaster(%d) ERROR: This node not found in replication config	Replication system error	Refer to UNIX/application expert first. Check the following 1) Is the node ID specified in the startup script of the updateLoader > 512? 2) If so set the value to something lower than 512. 3) Check the replication configuration in the SMS screens for the correct value for the updateLoader. 4) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282120	ERROR	DEF123infMaster: infMaster(%d) ERROR: Error opening Resync File `%s %d;	Kernel communication/disk error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
282121	ERROR	DEF123infMaster: infMaster(%d) ERROR: Node resync process completed;	Resyncing has completed for this node.	No resolution.	SMS
282122	ERROR	DEF123infMaster: infMaster(%d) ERROR: Update Loader %d at `%s %d:%d also connecting from `%s %d:%d	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS
282123	ERROR	DEF123infMaster: infMaster(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
282124	ERROR	DEF123infMaster: infMaster(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282125	ERROR	DEF123infMaster: infMaster(%d) ERROR: SMS Master shutting down	Process shutting down	Refer to UNIX/application expert first. Check the following 1) Was this shut down intentional? - if so then ignore the message - if not then there may be a communication error between the updateLoaders and the smsMaster which has invoked the InferiorMaster functionality 2) Contact support if required.	SMS
282126	ERROR	DEF123infMaster: infMaster(%d) ERROR: Master Controller `%s %d` process started (node %d)	Process has started successfully.	No resolution.	SMS
282127	ERROR	DEF123infMaster: infMaster(%d) ERROR: Unable to reach master node %d at `%s %d`	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
282128	ERROR	DEF123infMaster: infMaster(%d) ERROR: Update Requester `%s %d` process registered (node %d)	Information only	No resolution.	SMS
282129	ERROR	DEF123infMaster: infMaster(%d) ERROR: Failed to read database item from tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282130	ERROR	DEF123infMaster: infMaster(%d) ERROR: Merge complete with %d errors	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282131	ERROR	DEF123infMaster: infMaster(%d) ERROR: Merge started from node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282132	ERROR	DEF123infMaster: infMaster(%d) ERROR: Recieved Update Ack from loader %d with no oustanding update	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
282133	ERROR	DEF123infMaster: infMaster(%d) ERROR: Connection to `%s %d lost HB late by 123ms	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
282134	ERROR	DEF123infMaster: infMaster(%d) ERROR: Reached master node %d at `%s %d	Client successfully made a connection.	No resolution.	SMS
282135	ERROR	DEF123infMaster: infMaster(%d) ERROR: Unable to reach master node %d at `%s %d	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282136	ERROR	DEF123infMaster: infMaster(%d) ERROR: Connect attempt timed out after %d secs	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
282137	ERROR	DEF123infMaster: infMaster(%d) ERROR: Connection pipe broke	Internal software error.	No resolution. If problem persists then contact support.	SMS
282138	ERROR	DEF123infMaster: infMaster(%d) ERROR: gethostbyname-Problem getting host `%s %d`	Communications over the socket appears to have problems.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282139	ERROR	DEF123infMaster: infMaster(%d) ERROR: TCP connection to %s %d.%d was lost	Internal communications error.	Refer to UNIX/application expert first. Check specific process log for further information. Check network for communication issues. If problem persists then contact support.	SMS
282140	ERROR	DEF123infMaster: infMaster(%d) ERROR: Database is still locked	Database lock	Refer to ORACLE/application expert first. If problem persists then contact support.	SMS
282141	ERROR	DEF123infMaster: infMaster(%d) ERROR: Users update request information callback	Internal communications error.	Refer to UNIX/application expert first. DNS server cannot resolve host name or has no route to IP address. Check IP set up on machine. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282142	ERROR	DEF123infMaster: infMaster(%d) ERROR fetchNext oraResyncWrite.c@%d: ORA-1555 with no preceeding data	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
282143	ERROR	DEF123infMaster: infMaster(%d) ERROR logic=%d oraUpdateLoader.c@%d: Long value is expected and missing.	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS
282144	CRITICAL	DEF123infMaster: infMaster(%d) ERROR malloc=%d oraResyncRead.pc@%d: out of memory	Insufficient memory to perform desired action due to internal software error.	Refer to UNIX/application expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
282145	ERROR	DEF123infMaster: infMaster(%d) ERROR oraRWRow=%d oraResyncWrite.c@%d: This should never happen.	Internal software error.	Contact support. No further information can be obtained.	SMS
282146	ERROR	DEF123infMaster: infMaster(%d) ERROR oraRWSetup=%d oraResyncWrite.c@%d: sleeping waiting for debugging	Information only	No resolution.	SMS
282147	ERROR	DEF123infMaster: infMaster(%d) ERROR select=%d oraEventReader.pc@%d: mangled update	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282148	ERROR	DEF123infMaster: infMaster(%d) ERROR write oraEventReader.pc@%d: lost update, errno == %d	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
282149	ERROR	DEF123infMaster: infMaster(%d) ERROR write=%d oraEventReader.pc@%d: zero length write	Internal software error.	Refer to UNIX/application/LAN expert first. Check the smsMaster log on the SMP and also the updateLoader logs for further details. Contact support.	SMS
282150	ERROR	DEF123infMaster: infMaster(%d) ERROR: Column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282151	ERROR	DEF123infMaster: infMaster(%d) ERROR: Error transferring to primary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS
282152	ERROR	DEF123infMaster: infMaster(%d) ERROR: Error transferring to secondary node 0xZZZ	Replication system error	Refer to UNIX/application expert first. Check the following 1)Is this the first time that the node in question has been replicated to? 2)Is the target machine available - on the network for FTP access? 3)Does the smf_oper user have file transfer rights to the destination machine? 4) If this is not a new node to replication a resync may have be started once the initial error is corrected, if the replication.config file on the target machine differs to the one on the SMP. 6)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282153	ERROR	DEF123infMaster: infMaster(%d) ERROR: Failed to connect to Oracle	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282154	ERROR	DEF123infMaster: infMaster(%d) ERROR: Key column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282155	ERROR	DEF123infMaster: infMaster(%d) ERROR: Long column %s %d.%s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
282156	ERROR	DEF123infMaster: infMaster(%d) ERROR: oexn arguments: err_num: %d, &cda[DELETE]: %d, nextRow: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS
282157	ERROR	DEF123infMaster: infMaster(%d) ERROR: oraRWRRow arguments: colVals: %s %d, *numExtras: %d	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282158	ERROR	DEF123infMaster: infMaster(%d) ERROR: Table %s %d not found in configuration.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication which has caused the smsMaster to send an update to an updateLoader that can not cater for it. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 3)Finally contact support	SMS
282159	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Master (%d) now in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282160	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Master (%d) now not in use	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282161	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Update Requester %d at `%s %d:%d also connecting from `%s %d:%d	Replication system error	Refer to UNIX/application expert first. Error suggests that more than one replication process or node is connecting with the same node ID. 1) Check each of the node process startup scripts to ensure that each one has a unique node ID. 2) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282162	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Pending queue now above %d	Internal communications error.	Assuming basic UNIX skills (Check the following). 1) Are the updateLoaders still connected to the smsMaster? 2) Are the machines still available on the network? 3) The message means that updates that are to be replicated to a given node are building up on the smsMaster faster than the target nodes updateLoader can clear them - as long as they stay connected the queue should clear eventually 4) If problem persists then contact support.	SMS
282163	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Pending queue now below %d	Internal communications error.	No resolution.	SMS
282164	NOTICE	DEF123infMaster: infMaster(%d) NOTICE fetchNext=%d oraResyncWrite.c@%d: Data for table %s %d may be corrupt.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
282165	NOTICE	DEF123infMaster: infMaster(%d) NOTICE oparse=%d oraDataCheck.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
282166	NOTICE	DEF123infMaster: infMaster(%d) NOTICE oparse=%d oraResyncRead.pc@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282167	NOTICE	DEF123infMaster: infMaster(%d) NOTICE parse=%d oraUpdateLoader.c@%d:%z	Internal software error.	No resolution. If problem persists then contact support.	SMS
282168	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Error in data for table %s %d.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
282169	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: Lost connection to Oracle; exiting.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. 4) process should restart and re-attempt to connect to ORACLE - check process output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282170	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Update Lost:%z	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
282171	WARNING	DEF123infMaster: infMaster(%d) WARNING: Command parameter error: (%s %d)%z	Configuration issue / error	Refer to UNIX/application expert first. The configuration parameters given for this program are incorrect. Check the documentation for correct values. Alternatively run the binary from the command line with -help or -? to provide the parameters available. If problem persists then contact support.	SMS
282172	WARNING	DEF123infMaster: infMaster(%d) WARNING: fdopen() failed on new config; config file ignored	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282173	WARNING	DEF123infMaster: infMaster(%d) WARNING: Key name `%s %d` is unknown in table `%s %d`	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
282174	WARNING	DEF123infMaster: infMaster(%d) WARNING: Table `%s %d` unknown to replication configuration	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
282175	WARNING	DEF123infMaster: infMaster(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282176	WARNING	DEF123infMaster: infMaster(%d) WARNING: Update (key values `%s %d,%s %d,%s %d) not in any group of table `%s %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
282177	WARNING	DEF123infMaster: infMaster(%d) WARNING: Consistency check failed (reason %d);	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
282178	WARNING	DEF123infMaster: infMaster(%d) WARNING: Problem opening consistency report file `%s %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
282179	WARNING	DEF123infMaster: infMaster(%d) WARNING: Unrecognised consistency id %d from loader %d;	Replication system error	Contact support. Error suggests the unexpected invocation of the Consistency mechanism.	SMS
282180	WARNING	DEF123infMaster: infMaster(%d) WARNING: Cannot resync node %d to an Inferior Master	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282181	WARNING	DEF123infMaster: infMaster(%d) WARNING: Update Loader %d with invalid config %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
282182	WARNING	DEF123infMaster: infMaster(%d) WARNING: Update Loader connected with invalid node number %d	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
282183	WARNING	DEF123infMaster: infMaster(%d) WARNING: Cannot compare node %d - resync or compare in progress	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282184	WARNING	DEF123infMaster: infMaster(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
282185	WARNING	DEF123infMaster: infMaster(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282186	WARNING	DEF123infMaster: infMaster(%d) WARNING: Loader Node %d is not connected	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282187	WARNING	DEF123infMaster: infMaster(%d) WARNING: Master node %d cannot merge to inferior master node %d	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282188	WARNING	DEF123infMaster: infMaster(%d) WARNING: Master Node %d was requested to merge to itself	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282189	WARNING	DEF123infMaster: infMaster(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282190	WARNING	DEF123infMaster: infMaster(%d) WARNING: Cannot open report file `%s %d	Attempt to write to / open the named file has resulted in an error.	Assuming basic UNIX skills (Check the following). 1) Does the specified file exist? 2) Are the correct permissions set for the file? 3) Is the file corrupt, can it be opened? 4) Is the disk full? Finally contact support.	SMS
282191	WARNING	DEF123infMaster: infMaster(%d) WARNING: Error during merge recommit into tableZZZ	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282192	WARNING	DEF123infMaster: infMaster(%d) WARNING: Inferior Masters cannot perform DB comparisons	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282193	WARNING	DEF123infMaster: infMaster(%d) WARNING: Node already merging	Replication system error	Contact support. Error suggests the unexpected invocation of the InferiorMaster functionality.	SMS
282194	WARNING	DEF123infMaster: infMaster(%d) WARNING: There was no connection from node %d to send info message to	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS
282195	WARNING	DEF123infMaster: infMaster(%d) WARNING: Unexpected behaviour	Internal software error.	No resolution. If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282196	WARNING	DEF123infMaster: infMaster(%d) WARNING logic=%d oraUpdateLoader.c@%d: Update loader needs a Pro*C connection to Oracle.	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
282197	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: cannot insert NULL intoZZZ	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
282198	WARNING	DEF123infMaster: infMaster(%d) WARNING: Event lost with unexpected event type %s %d	Internal software error.	Refer to ORACLE/application expert first. A communication/data error has occurred. Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282199	WARNING	DEF123infMaster: infMaster(%d) WARNING: Node resync lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
282200	WARNING	DEF123infMaster: infMaster(%d) WARNING: Table %s %d has no configured keys or no other columns.	Replication system error	Refer to ORACLE/application expert first. Likely cause is that an error occurred in the configuration of replication. 1)Check the configuration of the node in the SMS screens and also the node ID specified in the startup script for the updateLoader. 2)Check the smsMaster and the updateLoader logs for further related error messages. 3)Warning - any change to the replication configuration for a given node will cause that node to resync which may not be desirable. 4)Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282201	WARNING	DEF123infMaster: infMaster(%d) WARNING: Update lost with null columns.	Replication system error	Refer to ORACLE/application expert first. A data error has caused a replication fault. Check the error logs for the smsMaster and the updateLoader for further details. It may be possible to identify the error by manually running the update via SQL (rollback command if successful). Contact support for further assistance.	SMS
282202	WARNING	DEF123infMaster: infMaster(%d) WARNING: Update of %s %d affected %d rows.	Replication system error	No resolution. Contact support.	SMS
282203	ERROR	DEF123infMaster: infMaster(%d) ERROR: Write error: Broken pipe	Internal software error.	No resolution. If problem persists then contact support.	SMS
282204	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: value larger than specified precision allows for this column	Internal software error.	Refer to ORACLE/application expert first. A data error has occurred. Contact support for further assistance.	SMS
282205	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Inferior Master replication process started (node %d)	Process has started successfully.	No resolution.	SMS
282206	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: following severe error from %s %d	Internal software error.	Refer to ORACLE/application expert first. A data error has occurred. Contact support for further assistance.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282207	WARNING	DEF123infMaster: infMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: ORACLE initialization or shutdown in progress	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). Verify that the username and password for the current machine is correct. 3) Observe startup output for errors. Finally contact support.	SMS
282208	ERROR	DEF123infMaster: infMaster(%d) CRITICAL: read-Unix IPC pipe connection lost: Error %d	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282209	CRITICAL	DEF123infMaster: infMaster(%d) CRITICAL =%d pendingQServer.C@%d: write- Unable to send update to loader %d; disconnecting.: Broken pipe	Lost communication with update loader.	Refer to application expert. Verify update loader is running, restart if necessary.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282210	CRITICAL	DEF123infMaster: infMaster(%d) CRITICAL =%d loaderConnReceiver.C@%d: write- Unable to send connAck message: Error %d	Cannot contact update loader.	Refer to application expert. Verify update loader. Check loader errors during startup.	SMS
282211	CRITICAL	DEF123infMaster: infMaster(%d) CRITICAL =%d unixConnection.C@%d: read-Unix IPC pipe connection lost: No child processes	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
282212	CRITICAL	DEF123infMaster: infMaster(%d) CRITICAL =%d unixConnection.C@%d: read-Unix IPC pipe connection lost: Operation would block	Kernel communication/disk error.	Refer to UNIX/application expert first. If problem persists then contact support.	SMS
282213	CRITICAL	DEF123infMaster: infMaster(%d) CRITICAL =4 pendingQServer.C@%d: write-Unable to send update to loader %d; disconnecting.: Interrupted system call	Cannot contact update loader.	Refer to application expert. Verify update loader specified in alarm string is running. Check loader errors during startup.	SMS
282214	ERROR	DEF123infMaster: infMaster(%d) ERROR Oracle=-%d oraEventReader.pc@%d: begin REP_INTERNAL . Block ; end ;: ORA-%d: ORU-%d: error:3 waiting for pipe message.	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282215	ERROR	DEF123infMaster: infMaster(%d) ERROR Oracle=-%d oraEventReader.pc@%d: lock table REP_ORA_EVENT in exclusive mode : ORA-%d: deadlock detected while waiting for resource	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
282216	ERROR	DEF123infMaster: infMaster(%d) ERROR Oracle=-%d oraEventReader.pc@%d: select %z ORA-%d: end-of-file on communication channel	Replication system error	Refer to ORACLE/application expert first. 1) Check for locks on the ORACLE database instance. 2) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 3) If problem persists then contact support.	SMS
282217	ERROR	DEF123infMaster: infMaster(%d) ERROR Oracle=%d oraConnect.pc@%d:%z	Internal replication error.	Contact support.	SMS
282218	ERROR	DEF123infMaster: infMaster(%d) ERROR Oracle=%d oraEventReader.pc@%d:%z	Internal replication error.	Contact support.	SMS
282219	ERROR	DEF123infMaster: infMaster(%d) ERROR Oracle=%d oraRepPendingQ.pc@%d:%z	Internal replication error.	Contact support.	SMS
282220	ERROR	DEF123infMaster: infMaster(%d) ERROR: accept-Connection accept error - Software caused connection abort	Internal communications error.	If problem persists contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282221	ERROR	DEF123infMaster: infMaster(%d) ERROR: bind-Problem binding socket %d - Address already in use	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282222	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Connection read error - Connection timed out	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282223	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Unix IPC pipe connection lost - Inappropriate ioctl for device	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282224	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Unix IPC pipe connection lost - Interrupted system call	Internal communications error.	If problem persists contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282225	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Unix IPC pipe connection lost - Invalid argument	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282226	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Unix IPC pipe connection lost - No child processes	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282227	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Unix IPC pipe connection lost - No such file or directory	File error.	Verify file exists. Check permissions, etc.	SMS
282228	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Unix IPC pipe connection lost - Resource temporarily unavailable	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282229	ERROR	DEF123infMaster: infMaster(%d) ERROR: read-Unix IPC pipe connection lost - Software caused connection abort	Internal communications error.	If problem persists contact support.	SMS
282230	ERROR	DEF123infMaster: infMaster(%d) ERROR: Write error - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282231	ERROR	DEF123infMaster: infMaster(%d) ERROR: write-Unable to send connAck message - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282232	ERROR	DEF123infMaster: infMaster(%d) ERROR: write-Unable to send update to loader %d; disconnecting. - Broken pipe	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282233	ERROR	DEF123infMaster: infMaster(%d) ERROR: write-Unable to send update to loader %d; disconnecting. - Interrupted system call	Internal communications error.	Refer to UNIX/application/LAN expert first (Check the following). 1) TCP/IP connection integrity. 2) Type netstat -na (see man netstat for more information) to determine the status of the listening socket for this connection. (Should be a configuration parameter). Finally contact support.	SMS
282234	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Connection FD %d identified as Controller Connection (Node %d)	Information only.	No resolution.	SMS
282235	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Connection FD %d identified as Loader Connection (Node %d)	Information only.	No resolution.	SMS
282236	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: Connection FD %d identified as Requester Connection (Node %d)	Information only.	No resolution.	SMS
282237	NOTICE	DEF123infMaster: infMaster(%d) NOTICE: New Connection from %d.%d.%d.%d:%d accepted (FD %d)	Information only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282238	WARNING	DEF123infMaster: infMaster(%d) WARNING OBNDNRN=%d oraOci.c@%d: ORA123: not connected to ORACLE	No longer connected to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282239	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: end-of-file on communication channel	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282240	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: error occurred at recursive SQL level %d	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS
282241	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: fatal two-task communication protocol error	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS
282242	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: unable to allocate %d bytes of shared memoryZZZ	Error writing to shared memory.	Contact support.	SMS
282243	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: unable to extend index %s %d by %d in tablespaceZZZ	Out of disk space.	Refer to Oracle expert. Free some disk space to allow the tablespace to be extended.	SMS
282244	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA123: unsupported network datatype or representation	Internal error.	Contact support.	SMS
282245	WARNING	DEF123infMaster: infMaster(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA123: error occurred at recursive SQL level %d	Oracle internal error.	Refer to application expert. Check alarm string for full detail.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282246	WARNING	DEF123infMaster: infMaster(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA123: not connected to ORACLE	No longer connected to Oracle.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282247	WARNING	DEF123infMaster: infMaster(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA123: unable to allocate %d bytes of sharedZZZ	Error writing to shared memory.	Contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282248	WARNING	DEF123infMaster: infMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA123: error occurred at recursive SQL level %d	Cannot connect to ORACLE.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282249	WARNING	DEF123infMaster: infMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA123: unable to allocate %d bytes of shared memoryZZZ	Error writing to shared memory.	Contact support.	SMS
282250	WARNING	DEF123infMaster: infMaster(%d) WARNING: Pending queue now above %d (Worst Node %d)	Internal communications error.	No resolution.	SMS
282251	WARNING	DEF123infMaster: infMaster(%d) WARNING: Updates will be lost on %s %d	Suggests a replication error elsewhere.	Refer to application expert. Check node for errors.	SMS
282252	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c@%d: ORA-%d: max # extents (%d) reached in indexZZZ	Out of table space.	Refer to ORACLE/application expert first, check the tablespace sizing for the SMF database. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282253	WARNING	DEF123infMaster: infMaster(%d) WARNING OEXEC, OEXN=%d oraUpdateLoader.c(%d: ORA-%d: check constraint (%s %d) violated	Database constraint violation. Cannot update the database.	Refer to Oracle expert. Quote constraint name.	SMS
282254	WARNING	DEF123infMaster: infMaster(%d) WARNING: Oracle unavailable after %d seconds with error: ORA-%d: TNS:no listener	Oracle is unavailable.	Refer to ORACLE expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the following environment variables and/or configuration files: 2a) ORACLE_SID(environment) 2b) tnsnames.ora(configuration file) 2c) listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. Finally contact support.	SMS
282255	ERROR	DEF123smsStatsDaemon: smsStatsDaemon(%d) ERROR: getProcessUptime: Insufficient space (%d bytes) for results of command %z - exiting	Insufficient memory to perform desired action due to internal software error	Refer to UNIX/platform expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS
282256	ERROR	smsStatsDaemon: smsStatsDaemon(%d) ERROR: DEF123getProcessUptime: Error allocating memory for command	Insufficient memory to perform desired action due to internal software error	Refer to UNIX/platform expert first (Check the following). 1) Rogue processes consuming memory 2) Unusually large memory consumption for an individual binary. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282258	CRITICAL	DEF123smsCompareResyncServer: smsCompareResyncServer(%d) CRITICAL: Resync failed with database fetch error; requires manual restart; code=%d	Oracle ran out of undo space while attempting a resync.	Refer to UNIX/platform expert first. Force a resync to start. If the resync fails a second time, contact support.	SMS
282259	WARNING	DEF123smsAlarmDaemon: smsAlarmDaemon(%d) WARNING: insert_internal: Maximum alarm list size %d reached %d alarms dropped in last %d seconds	Too many alarms!	Refer to UNIX/platform expert first. (Check the following). Flush out SMF_ALARM_MESSAGE table. Usually a symptom of other issues, ensure that the system is otherwise operating normally. Finally contact support.	SMS
282260	ERROR	\{282260\}	There was an exception loading the source config file. This means the input to the config surgeon was invalid.	Consult the log for more information and contact Support.	SMS
282261	ERROR	\{282261\}	There was an exception loading the target config file. This means the input to the config surgeon was invalid.	Consult the log for more information and contact Support.	SMS
282262	ERROR	\{282262\}	The config surgeon understands three operations: INSERT (add a new section to the target), DELETE (remove a section) and MERGE (use source to update target).	Rerun the config surgeon with a correct value for operation. If this is occurring in an execution of smsApplyConfig.sh, please contact Support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282263	ERROR	\{282263\}	You cannot insert a section without naming it.	Rerun config surgeon script with SECTION parameter present. If this is occurring in an execution of smsApplyConfig.sh, please contact Support.	SMS
282264	WARNING	\{282264\}	Section name is irrelevant to the MERGE operation - it ensure that all sections in source are copied in to the target, replacing any already there.	Rerun config surgeon script with SECTION parameter omitted - or ignore warning if this is a one-off run. If this is occurring in an execution of smsApplyConfig.sh, please contact Support.	SMS
282265	ERROR	\{282265\}	One or more preceding errors prevented the config surgeon from constructing itself in a valid state, so it cannot perform the requested operation.	Check preceding messages and rectify them before attempting the command again.	SMS
282266	ERROR	\{282266\}	The config surgeon was confused by the syntax at the reported line of the source file.	Either correct the input file, or report this problem so the config surgeon can be updated.	SMS
282267	ERROR	\{282267\}	The config surgeon was confused by the syntax at the reported line of the target file.	Either correct the input file, or report this problem so the config surgeon can be updated.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282268	ERROR	\{282268\}	The target config file could not be opened.	Check that the config surgeon process has write access to the named file. Contact Support if necessary.	SMS
282269	ERROR	\{282269\}	The second output file from a config surgery (list of changed sections) could not be opened.	Check that the config surgeon process has write access to the directory containing the named file. Contact Support if necessary.	SMS
282270	ERROR	\{282270\}	You have attempted to delete a section from the target that does not exist there.	Check the section name - or operation - passed to the config surgeon script.	SMS
282271	ERROR	\{282271\}	You have attempted to insert a section to the target that does not exist in the source file.	Check the section name - or operation - passed to the config surgeon script.	SMS
282272	ERROR	\{282272\}	The config file specified could not be found. The config surgeon opens both input files using the cmnConfig load process, as a preliminary sanity check before attempting to operate on them. This message means that this load process failed for one or both of the files.	Check that the config surgeon is being run with correct parameters - contact Support if necessary.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282273	WARNING	\{282273\}	Detection period was outside the allowed range, and adjusted to the default.	Check the parameter settings in smsConfigVariables.sh, and modify if necessary.	SMS
282274	WARNING	\{282274\}	Retry period was outside the allowed range, and adjusted to the default.	Check the parameter settings in smsConfigVariables.sh, and modify if necessary.	SMS
282275	WARNING	\{282275\}	Sleep period was outside the allowed range, and adjusted to the default.	Check the parameter settings in smsConfigVariables.sh, and modify if necessary.	SMS
282276	ERROR	\{282276\}	An attempt to stat the file being monitored by the smsConfigDaemon failed.	This can be a momentary problem if the file is being updated by the screens. If it is being repeatedly issued, check that the correct file is being monitored. Contact Support if necessary.	SMS
282277	NOTICE	\{282277\}	The config daemon detected a change in the file it monitored, and will initiate a process in response.	No action required - this is normal activity.	SMS
282278	ERROR	\{282278\}	The config daemon failed to fork to run its configured script process.	Contact Support.	SMS
282279	ERROR	\{282279\}	The config daemon failed to exec its configured script.	Check that the script exists and has permissions that allow smsConfigDaemon to execute it.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282280	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: ENHANCED Resynchronisation started for node %z	Resynchronisation was successful	No resolution.	SMS
282281	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: FULL Resynchronisation started for node %z	Resynchronisation was successful	No resolution.	SMS
282282	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Resynchronisation Finished. Processing Queued Updates	Resynchronisation was successful	No resolution.	SMS
282283	NOTICE	DEF123smsMaster: smsMaster(%d) NOTICE: Starting to process normal updates for node %d %z	Processing updates to continue normally	No resolution.	SMS
282284	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Finished Processing Queued Updates	Processing updates finished normally	No resolution.	SMS
282285	NOTICE	DEF123updateLoader: updateLoader(%d) NOTICE: Terminating on signal SIGTERM	Information Only.	No resolution.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282286	WARNING	DEF123updateLoader: updateLoader(%d) WARNING OPARSE=%d oraUpdateLoader.c@%d: ORA123: %z : invalid identifier	Invalid identifier.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS
282287	WARNING	DEF123updateLoader: updateLoader(%d) WARNING OEXEC, OEXN=%z oraUpdateLoader.c@%d: ORA123: unique constraint %z violated	Invalid identifier.	Refer to ORACLE/application expert first (Check the following). 1) Verify that ORACLE is running through checking the status of the listener(lsnrctl) and restart ORACLE only if necessary. 2) Check the environment variables and/or configuration files: ORACLE_SID(environment), tnsnames.ora(configuration file), listener.ora(configuration file). 3) Verify that the username and password for the current machine is correct. 4) Observe startup output for errors. Finally contact support.	SMS

Alarm	Severity	Text	Cause	Resolution	Service
282288	ERROR	\{282288\}	DEF123smsMaster: smsMaster(%d) CRITICAL: SMS replication. Host IP address retrieval: Unable to open socket %s %d	Refer to UNIX/application expert first. Then contact support.	SMS
282289	ERROR	\{282289\}	DEF123smsMaster: smsMaster(%d) CRITICAL: SMS replication. Host IP address retrieval: Unable to get ioctl list %s %d	Refer to UNIX/application expert first. Then contact support.	SMS