Oracle® Communications Cloud Native Security Edge Protection Proxy (SEPP) User's Guide





Oracle Communications Cloud Native Security Edge Protection Proxy (SEPP) User's Guide, Release 1.4.0 F35438-01

Copyright © 2020, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software" or "commercial computer software documentation" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Security Edge Protection Proxy (SEPP) Architecture	1-1
N32c and N32f Call flows	1-3
SEPP Microservices	1-6
Acronyms	1-6
References	1-6
Configuring SEPP Using REST APIs	
Metrics, KPIs and Alerts	
Metrics, KPIs and Alerts SEPP Metrics	3-1
· · ·	3-1 3-5
SEPP Metrics	
SEPP Metrics SEPP KPIs	3-5



List of Tables

1-1	Acronyms	1-6
3-1	SEPP Alerts	3-6



My Oracle Support

My Oracle Support (https://support.oracle.com) is your initial point of contact for all product support and training needs. A representative at Customer Access Support can assist you with My Oracle Support registration.

Call the Customer Access Support main number at 1-800-223-1711 (toll-free in the US), or call the Oracle Support hotline for your local country from the list at http://www.oracle.com/us/support/contact/index.html. When calling, make the selections in the sequence shown below on the Support telephone menu:

- 1. Select 2 for New Service Request.
- 2. Select **3** for Hardware, Networking and Solaris Operating System Support.
- 3. Select one of the following options:
 - For Technical issues such as creating a new Service Request (SR), select 1.
 - For Non-technical issues such as registration or assistance with My Oracle Support, select 2.

You are connected to a live agent who can assist you with My Oracle Support registration and opening a support ticket.

My Oracle Support is available 24 hours a day, 7 days a week, 365 days a year.



Whats New In This Guide

New and Updated Features in Release 1.4:

- TLS Protection Mode: This enables inter PLMN communication over N32 interface using TLS mode
- Added Metrics, Alerts and KPIs



1

Overview

The Security Edge Protection Proxy (SEPP) is a non-transparent proxy that sits at the perimeter of the PLMN network and enables secured communication between inter-PLMN network messages. The OCSEPP supports the following functions:

- Implements separate security negotiation interface (N32-c) and an end-toend application interface (N32-f)
 - N32-C: Uses for context management for security capability negotiation.
 - N32-F: Uses for forwarding of inter-NF signaling across PLMN.

Secure communication

- Secure communication of Inter PLMN messages from Consumer NF to Producer NF using TLS protection mode (HTTP over TLS).
- HTTPS and 3gpp-Sbi-Target-Apiroot header for secure Intra-PLMN communication to Network Functions.

Rest API based configurations

- APIs for configuration of roaming partner profiles.
- APIs retrieval of Handshake status for each roaming partner.

Resiliency

Implements retry mechanism for N32-C handshake failure.

Observability


- PLMN based Metrics and KPI.
- Alarms for failure and threshold events.
- Logging and tracing capabilities.

Security Edge Protection Proxy (SEPP) Architecture

This section explains the Security Edge Protection Proxy (SEPP) architecture.

Oracle Communications Security Edge Protection Proxy (OCSEPP) is a proxy network function (NF) which is used for secured communication between inter-Public Land Mobile Network (PLMN) messages.


Security Edge Protection Proxy Interfaces



SEPP provides two interfaces, N32-c and N32-f.

- N32-c: A control plane interface between the SEPPs for performing initial handshake and negotiating the parameters to be applied for the actual N32 message forwarding.
- N32-f: A forwarding interface between the SEPPs which is used for forwarding the communication between the NF service consumer and the NF service producer after applying application level security protection.

Security Edge Protection Proxy Architecture



SEPP Architecture and the Microservices Overview

ocsepp-config-mgr Microservice

This microservice is used for configuration of roaming partner profile and retrieving handshake status. It also initiates a notification towards cN32c service to initiate handshake as soon as profile is enabled and notification to delete n32 context as soon as profile is disabled. Audit to re-initiate handshake notification in case of handshake failure is also handled by config-mgr.



ocsepp-cn32c Microservice

This microservice is used for context management and initiation of security capability negotiation. It create an n32 context and maintain its state and negotiated security capability based on handshake procedure.

ocsepp-pn32c Microservice

This microservice is used for context management and respond to security capability negotiation. It create an n32 context and maintain its state and negotiated security capability based on handshake procedure.

ocsepp-cn32f Microservice

This microservice receives messages from consumer NF and determine remote SEPP address to forward message over n32f interface to SEPP of producer NF network.

ocsepp-pn32f Microservice

This microservice is receives inter-PLMN messages from remote SEPP of consumer network over TLS connection and forward to Producer NF.

ocsepp-plmn-Ingress-gateway

This is the entry point for comsumer NF to SEPP messages. PLMN Ingress Gateway exposes http and https interfaces towards consumer NF network to receives messages required to be forwarded over inter-PLMN n32f interface.

ocsepp-plmn-egress-gateway

This is the exit point for SEPP to producer NF messages. PLMN Egress gateway exposes http and https interface towards producer NF network to forward inter-PLMN messages received over inter-PLMN n32f interface.

ocsepp-n32-ingress-gateway

Entry point for N32 Ingress messages. N32 Ingress gateway exposes HTTP over TLS interface on prouder SEPP to receive n32c and n32f inter-PLMN messages.

ocsepp-n32-egress-gateway

Exit point for N32 Egress messages. N32 Egress gateway exposes HTTP over TLS interface on consumer SEPP to forward n32c and n32f inter-PLMN messages.

nrf-client


NRF client (nrfc) is used for NRF registration. NRF client supporting services are not shown.

N32c and N32f Call flows

The following are the N32c and N32f call flows of SEPP.




N32c Call flow



- The initiating SEPP issues a HTTP POST request towards the responding SEPP with the request body containing the "SecNegotiateReqData" with supporting security capabilities i.e. PRINS and/or TLS.
- On successful processing of the request, the responding SEPP shall respond to the initiating SEPP1 with "200 OK" status code and a POST response body with selected security capability i.e. PRINS or TLS.


N32f Call flow: HTTP scheme is used by NF to communicate to SEPP



 The SEPP on the NF service consumer side (c-SEPP) and the SEPP on the NF service producer side (p-SEPP) negotiate the security capabilities using the procedure defined in Handshake call flow. The SEPPs mutually negotiate to use TLS as the security policy.

- The NF service consumer is configured to route all HTTP messages with inter PLMN FQDN as the "authority" part of the URI via the c-SEPP. The c-SEPP acts as a HTTP proxy.
- The c-SEPP forwards the HTTP service request within the N32-f TLS tunnel established.
- The p-SEPP forwards the HTTP service request to the NF service producer.
- The NF service producer sends the HTTP service response
- The p-SEPP forwards the HTTP service response within TLS tunnel to the c-SEPP.
- The c-SEPP forwards the HTTP service response to the NF service consumer

N32f Call flow: HTTPS with 3gpp-Sbi-Target-apiRoot header is used by NF to communicate with SEPP



- The SEPP on the NF service consumer side (c-SEPP) and the SEPP on the NF service producer side (p-SEPP) negotiate the security capabilities using the procedure defined in Handshake call flow. The SEPPs mutually negotiate to use TLS as the security policy.
- NF service consumer is configured with c-SEPP FQDN and sets up a TLS connection with c-SEPP.
- The NF service consumer sends the HTTP service request within the TLS connection to the c-SEPP, including a 3pp-Sbi-Target-apiRoot header set to the apiRoot of the p-NF.
- The c-SEPP forwards the HTTP service request within the N32-f TLS tunnel established.
- The p-SEPP extracts the HTTP message received on the TLS connection, and then seeing that the URI scheme of the NF service producer is "https" in 3gpp-sbitarget-apiRoot header, the p-SEPP sets up a TLS connection with the NF service producer.
- The p-SEPP forwards the HTTP service request to the NF service producer.



- The NF service producer sends the HTTP service response
- The p-SEPP forwards the HTTP service response within TLS tunnel to the c-SEPP.
- The c-SEPP upon receiving the HTTP response message within the TLS tunnel, forwards the response to the NF service consumer.

SEPP Microservices

The following are the microservices of SEPP

Name	Description
cN32c	Initiates N32-c handshake to remote PLMNs
pN32c	Responds to N32-c handshake from remote PLMNs
cN32f	Initiates inter PLMN messages to remote PLMNs
pN32f	Responds to inter PLMN messages from remote PLMNs
config	SEPP configuration micro service
PLMN IGW, PLMN EGW	PLMN Ingress and Egress GW micro services
N32 IGW, N32 EGW	N32 Ingress and Egress GW micro services
nrfc,config-server, app-info	NRF Client and supporting services used for SEPP registration

Acronyms

The following table provides information about the acronyms used in the document.

Table 1-1 Acronyms

Fields	Description	
CNE	Cloud Native Environment	
DNS	Domain Name System	
FQDN	Fully Qualified Domain Name	
NF	Network Function	
OHC	Oracle Help Center	
OSDC	Oracle Software Delivery Cloud	
PLMN	Public Land Mobile Network	
SEPP	Security Edge Protection Proxy	
SVC	Services	
TLS	Transport Layer Security	

References

- · Cloud Native Environment (OCCNE) Installation Guide
- Security Edge Protection Proxy (SEPP) Cloud Native Installation Guide



2

Configuring SEPP Using REST APIs

The following SEPP managed objects can be configured using REST APIs:

Resource information

RoamingPartnerProfile

Metho d	URL	Description	Input	Return	Example
GET	/sepp- configuration/v 1/ roamingpartne rprofile	Returns all the configured roaming partner profiles Empty List [], if no roaming partner profiles are configured		List of RoamingPa rtnerProfile	curllocationrequest GET 'http://: <sepp- configuration="" ip="">:<port> //sepp- configuration/v1 / roamingpartnerpr ofile/'</port></sepp->
GET	/sepp- configuration/v 1/ roamingpartne rprofile/{name}	Returns configured RoamingPartner Profile if not present returns 404 Exception: Roaming partner profile not found for the name	Name of RoamingPa rtnerProfile as request parameter	RoamingPa rtnerProfile	curllocationrequest GET 'http:// <sepp- configuration="" ip="">:<port>// sepp- configuration/v1 // roamingpartnerpr ofile/SEPP-3'</port></sepp->



Metho d	URL	Description	Input	Return	Example
POST	/sepp- configuration/v 1/ roamingpartne rprofile/	Returns configured RoamingPartner Profile	RoamingPa rtnerProfile Object	RoamingPartnerProfile	<pre>curllocationrequest POST 'http://<sepp- configuration="" ip="">:<port>/sepp- configuration/v1 / roamingpartnerpr ofile/' \ header 'Content- Type: application/ json' \data-raw '{ "plmn": { "mcc":"111", "mnc":"123" }, "domain":"ocsepp -nf33", "seppId": "sepp33", "seppFqdn":"10.7 5.237.33", "securityCapabil ityList": ["PRINS"], "connectionType" :"INITIATOR", "isEnabled":"TRU E", "apiPrefix":"n32 c-handshake", "apiVersion":"v1 ", "port":30043 }'</port></sepp-></pre>



Metho d	URL	Description	Input	Return	Example
DELET	/sepp- configuration/v 1/ roamingpartne rprofile/{name}	Delete configured RoamingPartner Profile	Name of RoamingPa rtnerProfile as request param		curllocationrequest DELETE 'http:// <sepp- configuration="" ip="">:<port>// sepp- configuration/v1 / roamingpartnerpr ofile/SEPP-3'</port></sepp->



Metho d	URL	Description	Input	Return	Example
PUT	/sepp- configuration/v 1/ roamingpartne rprofile/{name}		1. Name of Roami ngPart nerProfile as reques t param 2. Update d Roami ngPart nerProfile object	RoamingPartnerProfile	curllocationrequest PUT 'http:// <sepp- configuration="" ip="">: <port>//sepp- configuration/v1 / roamingpartnerpr ofile/SEPP-3' \header 'Content-Type: application/ json' \data- raw '{ "name": "SEPP-3", "plmn": { "mcc": "311", "mnc": "282" }, "domain": "ocsepp-nf3", "seppId": "sepp3", "seppFqdn": "10.75.237.9", "connectionType" : "INITIATOR", "securityCapabil ityList": ["TLS"], "isEnabled": "FALSE", "port": 30043, "apiPrefix": "n32c- handshake", "apiVersion": "v1", "priority": 0 }'</port></sepp->



Metho d	URL	Description	Input	Return	Example
PATCH	/sepp- configuration/v 1/ roamingpartne rprofile/{name}	Update only provided fields of configured RoamingPartner Profile 404 Error if not found Exception: Roaming partner profile not found for the name	 Name of Roami ngPart nerProfile as reques t param Fields of Roami ngPart nerProfile to be update d 		<pre>curllocationrequest PATCH 'http://<sepp- configuration="" ip="">:<port>/sepp- configuration/v1 / roamingpartnerpr ofile/SEPP-2' \header 'Content-Type: application/ json' \data- raw '{ "isEnabled": "FALSE" }'</port></sepp-></pre>

Handshake Status

Attribute	Datatype	Compliance	Default Value	Pattern	Description
GET	/sepp- configuration/v 1/ handshakestat us	Returns all the handshake status Empty list [], if no handshake status		List of HandshakeS tatus	curl location request GET 'http:// <sepp- configuratio="" ip="" n="">:<port> /sepp- configuratio n/v1/ handshakesta tus/'</port></sepp->



Attribute	Datatype	Compliance	Default Value	Pattern	Description
GET	/sepp- configuration/v 1/ handshakestat us/{fqdn}	Returns handshake status of the SEPP FQDN 404 Error if not found Exception: Handshake Status not found for the fqdn	SEPP FQDN of the handshake status	HandshakeS tatus	curl location request GET 'http:// <sepp- configuratio="" ip="" n="">:<port> /sepp- configuratio n/v1/ handshakesta tus/ 10.75.191.11</port></sepp->



3

Metrics, KPIs and Alerts

SEPP Metrics

This section provides information about the SEPP metrics.

Microservice Name: Consumer N32c

SL.No.	Prometheus Stat Metrics Name	Metrics Description(including pegging condition)	Dimensions
1.	sepp_n32c_handshake_fail ure	If N32c Handshake Procedure fails, this metrics will be pegged and corresponding alarm will be raised.	 app(consumer, producer) peer_domain peer_fqdn n32c_procedure vendor nflnstanceld kubernetes_namespace
2.	sepp_cn32c_handshake_r equests_total	Total number of requests send over n32c for handshake procedure. Condition:: When sepp initiates any handshake procedure requests towards peer sepp.	 peer_domain peer_fqdn n32c_procedure vendor nfInstanceId kubernetes_namespace direction=egress



SL.No.	Prometheus Stat Metrics Name	Metrics Description(including pegging condition)	Dimensions
3.	sepp_cn32c_handshake_r esponse_total	Total number of responses received over n32c for handshake procedure. Condition:: When sepp receives any handshake procedure response from peer sepp. It can be successful or failure based on responseCode	 peer_domain peer_fqdn n32c_procedure responseCode(2xx,4x x,5xx) vendor nfInstanceId kubernetes_namespace direction=ingress
4.	sepp_cn32c_handshake_i nitiation_req_total	Total number of Handshake Initiation requests received from config-mgr. Condition:: When handshake initiation requests received from config-mgr.	 peer_domain peer_fqdn vendor nfInstanceId kubernetes_namespace
5.	sepp_cn32c_handshake_d elete_req_total	Total number of Handshake context delete requests received from config-mgr. Condition:: When handshake context delete requests received from config-mgr.	 peer-domain peer_fqdn vendor nfInstanceId kubernetes_namespace

Microservice Name: Producer N32c

S.No.	Prometheus Stat Metrics Name	Metrics Description(including pegging condition)	Dir	nensions
1.	sepp_pn32c_handshake_r equests_total	Total number of requests received over n32c for handshake procedure.	1. 2.	peer_domain
	Condition:: When any handshake procedure	3.	n32c_procedure	
		request received from peer	4.	vendor
		sepp.	5.	nflnstanceld
			6.	kubernetes_namespa ce
			7.	direction=ingress



S.No.	Prometheus Stat Metrics Name	Metrics Description(including pegging condition)	Dimensions
2.	sepp_pn32c_handshake_r esponse_total	Total number of responses sent over n32c for handshake procedure. Condition:: When sepp sends response to handshake procedure received. It can be a success response or failure response based on success code.	 peer_domain peer_fqdn n32c_procedure statusCode(2xx,4xx,5x x) vendor nfInstanceId kubernetes_namespace direction=egress

Microservice Name: Consumer N32f

S.No.	Prometheus Stat Metrics Name	Metrics Description(including pegging condition)	Dimensions
1.	sepp_cn32f_requests_failu re	Total number of requests failed to be sent from cn32f to remote SEPP. Condition:: When any error or exception occurs on cn32f side because of which request is not sent to pn32f.	 peer_domain peer_id peer_fqdn vendor nfInstanceId kubernetes_namespace statuscode error_msg
2.	sepp_cn32f_response_fail ure	Total number of response failed to be sent from cn32f pod to NF. Condition:: When any error or exception occurs on cn32f side because of which request is not sent to NF.	 peer_domain peer_id peer_fqdn vendor nfInstanceId kubernetes_namespace statuscode error_msg



S.No.	Prometheus Stat Metrics Name	Metrics Description(including pegging condition)	Dimensions
3.	sepp_cn32f_requests	Total number of requests received from NF. Condition:: When a request is received on InboundInterface of cn32f.	 peer_domain peer_id peer_fqdn vendor nfInstanceId kubernetes_namespace
4.	sepp_cn32f_response	Total number of response received from remote SEPP. Condition:: When a response is received on OutboundInterface of cn32f.	 peer_domain peer_id peer_fqdn vendor nfInstanceId kubernetes_namespace

Microservice Name: pN32f

S.No	Prometheus Stat Metric Name	Metric Description(including pegging condition)	Dir	nensions
1	sepp_pn32f_requests_rx	Number of requests received from Peer Sepp Condition: When a request reaches pn32f from peer Sepp.	1. 2. 3. 4. 5.	vendor nfInstanceId kubernetes_namespa ce kubernetes_podname peer_fqdn
2	sepp_pn32f_requests_tx	Number of requests transmitted to NF.Condition: When a request transmits a message to NF	1. 2. 3. 4. 5.	vendor nfInstanceId kubernetes_namespa ce kubernetes_podname peer_fqdn



S.No	Prometheus Stat Metric Name	Metric Description(including pegging condition)	Dimensions
3	sepp_pn32f_responses_rx	Number of responses received from EGW Condition: When a response reaches pn32f from EGW.	 vendor nfInstanceId kubernetes_namespace kubernetes_podname statusCode(2xx,4xx,5xx) error-reason(in case of EGW failure) peer_fqdn
4	sepp_pn32f_responses_tx	Number of responses transmitted to cSepp.Condition: When a responses transmits a message to cSepp	 vendor nflnstanceld kubernetes_namespa ce kubernetes_podname statusCode(2xx,4xx,5x x) peer_fqdn



The templates for dashboard creations not shared in the deliverables. So dashboard needs to be created manually based on needs

SEPP KPIs

This section provides information about the SEPP KPIs.

KPI Details	SEPP Microservic e	Metrics Used	Service Operation	Response Code
cn32c Handshake Success rate	cn32c	(sum(ocsepp_cn32c_hand shake_response_total)/ sum(ocsepp_cn32c_hands hake_requests_total))*100	n32c Handshake	200
cn32f Routing Success Rate	cn32f	(sum(ocsepp_cn32f_respo nse_total)/ sum(ocsepp_cn32f_reques ts_total))*100	n32f message forward	All



KPI Details	SEPP Microservic e	Metrics Used	Service Operation	Response Code
cn32f Requests Rate Per Remote SEPP	cn32f	sum(irate(ocsepp_cn32f_r equests_total[2m]))by(PEE R_DOMAIN, PEER_FQDN, PLMN_ID)	n32f message forward	All
cn32f Response Rate Per Remote SEPP	cn32f	sum(irate(ocsepp_cn32f_r esponse_total[2m])) by(PEER_DOMAIN, PEER_FQDN, PLMN_ID)	n32f message forward	All
cn32c Handshake Failure Per Remote SEPP	cn32c	sum(ocsepp_n32c_handsh ake_failure)by(peer_domai n, peer_fqdn, peer_plmn_id)	n32c Handshake	4xx and 5xx
pn32c Handshake Success rate	pn32c	(sum(ocsepp_pn32c_hand shake_response_total)/ sum(ocsepp_pn32c_hands hake_requests_total))*100	n32c Handshake	200
pn32f Routing Success Rate	pn32f	(sum(ocsepp_pn32f_respo nse_total)/ sum(ocsepp_pn32f_reques ts_total))*100	n32f message forward	All
pn32f Requests Rate	pn32f	sum(irate(ocsepp_pn32f_r equests_rx_total[2m]))	n32f message forward	All
pn32f Response Rate	pn32f	sum(irate(ocsepp_pn32f_r esponse_rx_total[2m]))	n32f message forward	All
pn32c Handshake Failure Per Remote SEPP	pn32c	sum(ocsepp_n32c_handsh ake_failure)by(peer_domai n, peer_fqdn, peer_plmn_id)	n32c Handshake	4xx and 5xx

SEPP Alerts

This section provides information about the SEPP alerts and their configuration.

Table 3-1 SEPP Alerts

SL.n o.	Alert	Severity	oid	Dimen sions	Description	Remarks
1	SEPPCn32c HandshakeF ailureAlert	Major	1.3.6.1.4.1.3 23.5.3.46.1. 2.2001	reason	Handshake procedure has failed on Consumer sepp	SEPP-1.4
2	SEPPPn32c HandshakeF ailureAlert	Major	1.3.6.1.4.1.3 23.5.3.46.1. 2.3001	reason	Handshake procedure has failed on Producer sepp	SEPP-1.4
3	SEPPN32fR outingFailure	warning	1.3.6.1.4.1.3 23.5.3.46.1. 2.4001	error_m sg	N32f service not able to forward message	SEPP-1.4



Table 3-1 (Cont.) SEPP Alerts

SL.n o.	Alert	Severity	oid	Dimen sions	Description	Remarks
4	SEPPPodM emoryUsage Alert	warning	1.3.6.1.4.1.3 23.5.3.46.1. 2.4003		Pod memory usage is above threshold (70%)	SEPP-1.4
5	SEPPPodCp uUsageAlert	warning	1.3.6.1.4.1.3 23.5.3.46.1. 2.4002		Pod CPU usage is above threshold (70%)	SEPP-1.4

SEPP Alert Configuration

This section describes the Measurement based Alert rules configuration for SEPP. The Alert Manager uses the Prometheus measurements values as reported by microservices in conditions under alert rules to trigger alerts.

Steps for SEPP Alert Configuration in Prometheus

Namespace - Prometheus NameSpace

1. Find the config map to configure alerts in prometheus server by executing the following command:

```
kubectl get configmap -n <Namespace>
```

where, <Namespace> is the prometheus server namespace used in helm install command.

2. Take Backup of current config map of prometheus server by executing the following command:

```
kubectl get configmaps _NAME_-server -o yaml -n _Namespace_ > /tmp/
tempConfig.yaml
```

where, <Namespace> is the prometheus server namespace used in helm install command.

For Example, assuming chart name is "prometheus-alert", so "_NAME_-server" becomes "prometheus-alert-server", execute the following command to find the config map:

```
kubectl get configmaps prometheus-alert-server -o yaml -n
prometheus-alert2 > /tmp/tempConfig.yaml
```

3. Check if alertssepp is present in the t_mapConfig.yaml file by executing the following command:

```
cat /tmp/t_mapConfig.yaml | grep alertssepp
```



4. If alertssepp is present, delete the alertssepp entry from the t_mapConfig.yaml file, by executing the following command:

```
\verb|sed -i '/etc | / config | / alerts | epp/d' / tmp/t_mapConfig.yaml| \\
```

5. If alertssepp is not present, add the alertssepp entry in the t_mapConfig.yaml file by executing the following command:

6. Reload the config map with the modifed file by executing the following command:

```
kubectl replace configmap <Name> -f /tmp/t_mapConfig.yaml
```

7. Add seppAlertRules.yaml file into prometheus config map under filename of SEPP alert file by executing the following command :

```
kubectl patch configmap <Name> -n <Namespace> --type merge --patch
"$(cat <PATH>/seppAlertRules.yaml)"
```

- 8. Restart prometheus-server pod.
- 9. Verify the alerts in prometheus GUI.

Note:

Prometheus server takes updated configmap reloaded after sometime automatically ($\sim\!20~\text{sec}$)



4

SEPP Response Codes

Following are the SEPP Response Codes:

- N32c Handshake Response Codes
- N32f Plane Message Forwarding Response Codes

N32c Handshake Response Codes

Reque st	Respo nse Code	ResponseB ody	Reference	Use Case	Comment/ Remarks	Applic able	Scope(PI-E)
Capabil ity Exchan	200 OK	SecNegotiat eRspBody	TS29573_N 32_Handsha ke.yaml	Handshake success	Handshake Success		Yes
ge	400 Bad Reques t	Problem Details	TS29573_N 32_Handsha ke.yaml	Invalid Request Body Mandat ory IE Missing	Handshake fail		Yes
	404 Not Found	Problem Details	3gpp Spec 29500	1. Incorrec t API			Yes
	405 Method Not Allowed Problem Details Used When request method other than POST is used				Yes		
	411 Length Require d	Problem Details	TS29573_N 32_Handsha ke.yaml	When Content Length header is not present in request.			No
	413 Payload Too Large	Problem Details	TS29573_N 32_Handsha ke.yaml	When request entity is larger than limits defined by server.			No



Reque st	Respo nse Code	ResponseB ody	Reference	Use Case	Comment/ Remarks	Applic able	Scope(PI-E)
	415 Unsupp orted Media Type	Problem Details	TS29573_N 32_Handsha ke.yaml	When payload format is not in json. When "Content-Type:applica tion/json" is not present.			Yes
	429 Too Many Reques ts	Problem Details	TS29573_N 32_Handsha ke.yaml	Too many requests in a given amount of time ("rate limiting").			No
	500 Internal Server Error	Problem Details	TS29573_N 32_Handsha ke.yaml	1. DB Access Fail during executio n of handsh ake request in server side. 2. Any other internal error in server during executio n of handsh ake request.			Yes
	503 Service Unavail able	null	TS29573_N 32_Handsha ke.yaml	When sepp backend service is down.			Yes
	501 Not Implem ented	Problem Details		When capability mismatch happens.			Yes
	401 Unauth orized	Problem Details		When request received for unknown peer sepp.			Yes



Reque st	Respo nse Code	ResponseB ody	Reference	Use Case	Comment/ Remarks	Applic able	Scope(PI-E)
	403 Forbidd en	Problem Details		When request received for disabled peer sepp.			Yes

N32f Plane Message Forwarding Response Codes

Pod Name	Respo nse Code	ResponseB ody	Use Case	Reference	Comment	Applic able	Scope
cN32f- Sepp	200 OK	Success Body	Success	TS29573_J OSEProtect edMessage Forwarding. yaml			PI-E
	404 Not Found	Problem Details	N32f Context Not Found	3gpp Spec 29500			PI-E
	401 Unauth orised	Problem Details	Context Not Established	3gpp Spec 29500			PI-E
	401 Unauth orised	Problem Details	Security Capability apart from TLS	3gpp Spec 29500			PI-E
	400 Bad Reques t	Problem Details	3GPP- target-sbi- apiroot/ destination producer NF is absent	TS29573_J OSEProtect edMessage Forwarding. yaml			PI-E
	503 Service Unavail able	Problem Details	Service Unavailable	TS29573_J OSEProtect edMessage Forwarding. yaml			PI-E
pN32f- Sepp	400 Bad Reques t	Problem Details	3GPP- target-sbi- apiroot/ destination producer NF is absent	TS29573_J OSEProtect edMessage Forwarding. yaml			PI-E
	503 Service Unavail able	Problem Details	Service Unavailable	TS29573_J OSEProtect edMessage Forwarding. yaml			PI-E



Note:

All the Exceptions/Error response codes sent by the N32-EGW at consumer side and PLMN-EGW at Producer side will be same and we will be adding a Problem statement which contains the reason why it occured.

