Oracle® Banking Corporate Lending Setup Plug-Ins





Oracle Banking Corporate Lending Setup Plug-Ins, Release 14.8.1.0.0

G43295-01

Copyright © 2007, 2025, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software, software documentation, data (as defined in the Federal Acquisition Regulation), or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software," "commercial computer software documentation," or "limited rights data" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed, or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle®, Java, MySQL, and NetSuite are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

1

Preface

Purpose		
Acronyms a	and Abbreviations	
Audience		
Critical Patches Conventions Diversity and Inclusion Documentation Accessibility Related Resources		
		i
		i
Screenshot Disclaimer		
Set Up I	Plug-Ins	
1.1 Introd	duction	
1.2 Integ	rate Oracle FLEXCUBE UBS and BPEL	:
1.2.1	Configure Custom Authentication Provider	:
1.2.2	Configure Libovd For Single Entity	
1.2.3	Configure Libovd for Multi Entity	8
1.2.4	Configure Multiple Providers for Multiple Entities	(
1.2.5	Configure DBAdapter	15
1.2.6	Configure JMS Adapter	1
1.2.7	Configure FTP Adapter	30
1.2	2.7.1 BIP Interactive reports configuration	38
1.2.8	BAM Report Configuration settings	49
1.2.9	Configure IPM to Edit Document	64
1.2.10	Configure Supervisor Roles in EM	70
1.2.11	Configure Email Driver	7:
1.2.12	Configure TimeOut Settings for BPEL	7!
1.3 Integ	ration of Oracle FLEXCUBE UBS and Scheduler	82
1.3.1	Running Backend Scripts	82
1.4 Integ	ration of Oracle FLEXCUBE UBS and BIP Reports	83
1.4.1	Deploy Application Through Application Server's Admin Console	83
1.5 Integ	ration of Oracle FLEXCUBE UBS and MBean	83



Preface

This topic contains the following sub-topics:

- Purpose
- Acronyms and Abbreviations
- Audience
- Critical Patches
- Conventions
- · Diversity and Inclusion
- Documentation Accessibility
- Related Resources
- Screenshot Disclaimer

Purpose

This guide describes the pre-deployment tasks to setup the Plug-in by manually before Oracle FLEXCUBE deployment. It provides detail information about the pre-deployment tasks based on the on the selected plug-ins.

Acronyms and Abbreviations

The acronyms and abbreviations are listed in this below table:

Table 1 Acronyms and Abbreviations

Abbreviations or Acronyms	Definition
BAM	Business Activity Monitoring
BIP	Business Intelligence Publisher
BPEL	Business Process Execution Language
BPMN	Business Process Model and Notation
EAR	Enterprise Archive file
EM	Enterprise Manager
FTP	File Transfer Protocol
IMAP	Internet Message Access Protocol
JMS	Java Message Service
JDBC	Java Database Connectivity
JNDI	Java Naming and Directory Interface
SOA	Service-Oriented Architecture
SMTP	Simple Mail Transfer Protocol



Audience

This manual is intended for the following User/User Roles:

Table 2 Audience

Role	Function
Administrator	Who controls the system and application parameters and ensures smooth functionality and flexibility of the banking application.
Implementation team	Implementation of Oracle Banking Corporate Lending Solution
Pre-sales team	Install Oracle Banking Corporate Lending for demo purpose
Bank personnel	Who installs Oracle Banking Corporate Lending

The user of this manual is expected to have basic understanding of Oracle Banking Application installation.

Critical Patches

Oracle advises customers to get all their security vulnerability information from the Oracle Critical Patch Update Advisory, which is available at <u>Critical Patches</u>, <u>Security Alerts and Bulletins</u>. All critical patches should be applied in a timely manner to ensure effective security, as strongly recommended by <u>Oracle Software Security Assurance</u>.

Conventions

The following text conventions are used in this document:

Table 3 Conventions

Convention	Meaning
boldface	Boldface type indicates graphical user interface elements associated with an action, or terms defined in text or the glossary.
italic	Italic type indicates book titles, emphasis, or placeholder variables for which you supply particular values.
monospace	Monospace type indicates commands within a paragraph, URLs, code in examples, text that appears on the screen, or text that you enter.

Diversity and Inclusion

Oracle is fully committed to diversity and inclusion. Oracle respects and values having a diverse workforce that increases thought leadership and innovation. As part of our initiative to build a more inclusive culture that positively impacts our employees, customers, and partners, we are working to remove insensitive terms from our products and documentation. We are also mindful of the necessity to maintain compatibility with our customers' existing technologies and the need to ensure continuity of service as Oracle's offerings and industry standards evolve. Because of these technical constraints, our effort to remove insensitive terms is ongoing and will take time and external cooperation.



Documentation Accessibility

For information about Oracle's commitment to accessibility, visit the Oracle Accessibility Program website at https://www.oracle.com/corporate/accessibility/.

Access to Oracle Support

Oracle customer access to and use of Oracle support services will be pursuant to the terms and conditions specified in their Oracle order for the applicable services.

Related Resources

For more information on any related features, refer to the following documents:

- Oracle Banking Corporate Lending User Guides.
- · Oracle Banking Corporate Lending Installation Guides.

Screenshot Disclaimer

Personal information used in the interface or documents is dummy and does not exist in the real world. It is only for reference purposes.

Set Up Plug-Ins

This topic contains the following sub-topics:

Introduction

This topic describes the pre-deployment tasks to set up plug-ins before Oracle FLEXCUBE deployment.

Integrate Oracle FLEXCUBE UBS and BPEL

This topic explains integration of Oracle FLEXCUBE UBS and BPEL.

Integration of Oracle FLEXCUBE UBS and Scheduler

This topic explains Integration of Oracle FLEXCUBE UBS and Scheduler.

• Integration of Oracle FLEXCUBE UBS and BIP Reports

This topic explains integration of Oracle FLEXCUBE UBS and BIP Reports.

• Integration of Oracle FLEXCUBE UBS and MBean

This topic explains to integrate Oracle FLEXCUBE UBS with MBean plug-in.

1.1 Introduction

This topic describes the pre-deployment tasks to set up plug-ins before Oracle FLEXCUBE deployment.

You need to carry out certain tasks manually before Oracle FLEXCUBE deployment. This guide provides the details of pre-deployment tasks based on the selected plug-ins.

1.2 Integrate Oracle FLEXCUBE UBS and BPEL

This topic explains integration of Oracle FLEXCUBE UBS and BPEL.

If you have created the EAR file with BPEL as a plug-in, the installer will create the **FCJJPSProvider.jar** file in the BPELbuild folder alongside the Oracle FLEXCUBE UBS EAR file. Before deploying the Oracle FLEXCUBE UBS EAR file, you must complete the following tasks.

This topic contains the following sub-topics:

Configure Custom Authentication Provider

This topic provides systematic instructions to configure the Custom Authentication Provider.

Configure Libovd For Single Entity

This topic provides the systematic instructions to configure libovd for a single entity.

Configure Libovd for Multi Entity

This topic provides the systematic instructions to configure libovd for multi entity.

Configure Multiple Providers for Multiple Entities

This topic explains to configure multiple providers for multiple entities.

Configure DBAdapter

This topic explains the steps to configure DBAdapter.



Configure JMS Adapter

This topic explains to configure JMS Adapter.

Configure FTP Adapter

This topic explains to configure FTP Adapter using the below steps.

BAM Report Configuration settings

This topic explains the configuration settings for BAM reports.

Configure IPM to Edit Document

This topic explains to edit the document using the IPM configuration.

Configure Supervisor Roles in EM

This topic explains to configure supervisor roles in the Oracle Enterprise Manager.

Configure Email Driver

This topics explains the steps to configure the Email Driver.

Configure TimeOut Settings for BPEL

This topic explains steps to configure TimeOut Settings for BPEL.

1.2.1 Configure Custom Authentication Provider

This topic provides systematic instructions to configure the Custom Authentication Provider.


FCUBS Custom Authenticator Provider configuration must be done through the Weblogic console of SOA or manually update the config.xml of the SOA domain.

Follow the below steps to setup Custom Authentication Provider:

- Along with the FCUBS Ear file, the installer generates the FCUBSAuthenticationProvider.jar file in the BPELbuild folder. Copy this file in the following path on the application server host <ORACLE HOME>\wlserver\server\lib\mbeantypes.
- 2. Restart the Admin Server.
- 3. Login to the Console.
- Click Security Realms.




Figure 1-1 Oracle Weblogic Server - Security Realms



Click myrealm.


Figure 1-2 Oracle Weblogic Servers_SecurityRealm_myrealms



Click the **Providers** tab and then click the **New** button to create a new authentication provider.




Figure 1-3 Oracle Weblogic Server - Providers



 Specify the Provider name as FCJCustomProvider and type as FCUBSUserAuthenticator and click OK.


Figure 1-4 Oracle Weblogic Server - Providers - Create New Authentication Provider



8. Click the **Reorder** button.




Figure 1-5 Oracle Weblogic Server - Providers - Reorder



The Reorder Authentication Providers screen displays.

Figure 1-6 Oracle Weblogic Server - Settings for FCJCustomProvider




- 9. On the **Reorder Authentication Providers** screen, bring the newly created provider to the first of all providers and click **OK**.
- 10. Click FCJCustomProvider.

The Settings for FCJCustomProvider screen displays.



Figure 1-7 Settings for FCJCustomProvider - Common



- 11. In the Common tab, change the **Control flag** to **SUFFICIENT** from the drop-down list.
- **12.** In Provider Specific tab, perform one of the following actions:
 - a. Set **JNDIName** as Flexcube JNDI Name.
 - If external authentications are used in FCUBS, then specify the LDAP/MSAD related fields.
- 13. For manual edit, browse the **config.xml** file from the following folder:

\Middleware\user_projects\domains\base_domain\config\
The following codes should be added at proper locations in the **config.xml** file.

Search for <realm> tag and add the following code between <realm> and </realm> tags. This should be the first child of the realm Node.

Make sure tag values matches the value given during Property file creation.



1.2.2 Configure Libovd For Single Entity

This topic provides the systematic instructions to configure libovd for a single entity.

Follow the steps below to configure the libovd details for a single entity:

- Along with the Oracle FLEXCUBE UBS EAR file, the installer generates the FCJJPSProvider.jar file inside the BPELbuild folder under the SOURCE directory.
- 2. On the application server host, create a folder by the name **classes** at the following location locati
- 3. Extract the **FCJJPSProvider.jar** file and copy the **com** folder from the extracted content to the following location:

 <MIDDLEWARE_HOME>soa\soa\modules\oracle.soa.ext_11.1.x\classes.
- 4. Navigate to the location <MIDDLEWARE_HOME>soa\soa\modules\oracle.soa.ext_11.1.x\classes\com\ ofss\fcc\bpel\cac.
- 5. Edit the properties file CISProperties.properties and update JNDI.name with the JNDI name same as Entity Name given in Multi Entity Names screen while creating property file fcubs.properties, example: jdbc/fcjdevDS.
- 6. Copy FCJJPSProvider.jar to <MIDDLEWARE_HOME>/user_projects/domains/ <domain_name>/config/fmwconfig/ovd/plu gins/lib.
- 7. Create the directory structure if it does not exists.
- 8. Copy the fcubs_adapter.xml to the following location:
 <MIDDLEWARE HOME>/oracle common/modules/oracle.ovd/templates/
- 10. Set environment variables in the command prompt, example: for Linux shell,
 - export ORACLE_HOME=/scratch/app/bpm12212(setting ORACLE_HOME) export WL_HOME=/ scratch/app/bpm12212/wlserver(setting WL_HOME) export JAVA_HOME=/scratch/ work area/DBA/jdk1.8.0 144 (setting JAVA HOME)
- 11. Execute the libovdadapterconfig script which is available in <MIDDLEWARE_HOME>/ oracle_common/bin with below parameters.
- 12. Specify the below arguments with values for admin server host name or IP that are:
 - Admin server port
 - WebLogic User ID
 - Domain Home
 - Fcubs datasource
 - ./libovdadapterconfig.sh -adapterName fcubsadapter -adapterTemplate fcubs_adapter.xml -host <ADMIN_SERVER_HOST> -port <ADMIN_PORT> -userName <WEBLOGIC_USERID> -domainPath <DOMAIN_HOME> -dataStore DB -root ou=fcubs,dc=oracle,dc=com -contextName default dataSourceJNDIName <FCUBS DATASOURCE JNDI>
- 13. Once the above steps are completed, a message will displays and stating that Adapter created successfully: fcubsAdapter.



14. Restart the server.

1.2.3 Configure Libovd for Multi Entity

This topic provides the systematic instructions to configure libovd for multi entity.

Follow the steps given below to configure the libovd for multi entity.

- 1. Continue step 1 to step 5 from Configure Libovd For Single Entity
- 2. In the following steps, replace the <EntityId> tag with the proper Entity name.
- 3. Copy the fcubs_adapter_<EntityId>.xml to <MIDDLEWARE_HOME>/oracle_common/modules/oracle.ovd/templates/
- 4. Search for <FCUBSDATASOURCE> in fcubs_adapter_< EntityId>.xml and update it with fcubs Datasource with the mapped Datasource for the entity in the property file.

```
For example: <param name="DataSource" value="<FCUBSDATASOURCE>"/>
```

5. Search for UserldPattern Parameter and update the value for OU to the entity name in lower case.

```
For example: <param name="UserIdPattern"
value="cn=%USERID%,ou=<EntityId>,dc=oracle,dc=com"/>
```

6. Search for MultiEntityEnabled element and update the value to true.

```
For example: <param name="MultiEntityEnabled" value="true"/>
```

Search for EntityId element and update the value with the entity name in lower case which we have created.

```
For example: <param name="EntityId" value=" <EntityId>"/>
```

8. Search for ou=fcubs and update with entity id in lower case.

```
For example: ou= EntityId
```

- Execute libovdadapterconfig script which is present in <MIDDLEWARE_HOME>/
 oracle common/bin with below parameters.
- **10.** Update the admin server host name or IP, admin server port, WebLogic user id, domain home, root, and fcubs datasource.

```
libovdadapterconfig.sh -adapterName fcubsAdapter -adapterTemplate fcubs_adapter_< EntityId >.xml -host <ADMIN_SERVER_HOST> -port <ADMIN_PORT> - userName <WEBLOGIC_USERID> - domainPath <DOMAIN_HOME> -dataStore DB -root ou=<EntityId>,dc=oracle,dc=com -contextName default -dataSourceJNDIName <FCUBSDATASOURCE name which we mapped in step4>
```

- **11.** Repeat from step 2 to step 7 for each entity creation.
- **12.** Once the above steps are completed, restart the server.

Note

For any misconfiguration in libovd, delete the existing fcubsAdapter and re-run the *./libovdadapterconfig.sh*.

For deleting fcubsAdapter use the below command:

a. Log in to the WSLT console by running the WLST script.



For example:

- UNIX: MW_HOME/oracle_common/common/bin/wlst.sh
- Windows: MW_HOME\oracle_common\common\bin\wlst.cmd
- b. Connect to your Administration Server using the following syntax: connect ('<WLS admin user name>','<WLS admin password>','t3://<admin server host>:<admin server port>')

For Example: connect('weblogic','weblogic','t3://myserver:7001')

c. Delete the misconfigured adapter using the following syntax: deleteAdapter(adapterName='fcubsAdapter')

Note

- In the case of Multi Entity, all data sources must be created separately for each entity. The JNDI name will be differentiated by suffixing the entity name.
 - Example: If Data source is **jdbc/fcjDevDs** then **jdbc/fcjDevDs+entity name** will be lookup the application. **(jdbc/fcjDevDs+entity name) jndi** should be presented in application server.
- For multi tenant deployment, BPMN support will be available only for the logged entity.

1.2.4 Configure Multiple Providers for Multiple Entities


This topic explains to configure multiple providers for multiple entities.

- Login to the Adminserver.
- Click Security Realms.

The Oracle Weblogic Server screen displays.




Figure 1-8 Oracle Weblogic Server



Click myrealms.

The **Summary of Security Realms** screen displays.

Figure 1-9 Summary of Security Realms




4. Click the Providers tab.

The **Settings for myrealms - Providers** screen displays.




Figure 1-10 Settings for myrealms - Providers



Click New.

Figure 1-11 Settings for myrealms - Authentication Providers




6. Specify the Name with proper Entity Name (entity name you mapped in property file) and select the type as FCUBSUserAuthenticator and click OK.

The Create a New Authentication Provider screen displays.




Figure 1-12 Create a new authentication Provider



Click Reorder. Bring the Authenticatiorprovider to the first in the order and click OK.
 The Reorder Authentication Providers screen displays.

Figure 1-13 Reorder Authentication Providers



8. Click the Provider that you have created.

The Settings for myrealms - Providers - New Provider screen displays.






Figure 1-14 Settings for myrealms - Providers - New Provider

In the Common tab, select the control flag as SUFFICIENT from the list and click Save.
 The Settings for ENTITYID - common tab screen displays.


Figure 1-15 Settings for ENTITY ID - Common

Re-order Authentication providers

System Status

Health of Running Servers

Failed (0)
Critical (0)
Overloaded (0)
Warning (0)
OK (3)




10. Select the **Provider Specific** tab.

The **Settings for ENTITYID - Provider Specific** screen displays.




Figure 1-16 Settings for ENTITYID - Product Specific



11. Change the **JNDIName** to the Datasource JNDI name, which has mapped to the entity in the property file level, and select the **Multi Entity enabled** checkbox.


Figure 1-17 Settings for ENTITYID - Provider Specific - Multi Entity





12. Specify the **Entity ID** with the Entity name which you have created in the property file level and click **Save**.

Figure 1-18 Settings for ENTITYID - Provider Specific - Entity Id



- 13. Create the new datasource for each entity with the JNDI name, which you mapped in the property file.
- 14. Restart the Admin Server.
- 15. Continue step 1 to step 15 for each provider creation in a multi-entity scenario.

1.2.5 Configure DBAdapter

This topic explains the steps to configure DBAdapter.


To configure DBAdapter, follow the steps given below:

1. Log in to Weblogic Console and click Deployment under Domain Structure.

The **Summary of Deployments** screen displays.




Figure 1-19 Summary of Deployments



- In the Deployments table, select **DbAdapter** and you will be navigated to **Settings for DbAdapter** screen.
- Click the Configuration tab and select Outbound Connection Pools.The Settings for DBAdapter screen displays.

Figure 1-20 Settings for DBAdapter



4. Under Groups and Instances, click and expand javax.resource.cci.ConnectionFactory.




- Click New and select javax.resource.cci.ConnectionFactory in Outbound Connection Group.
- Define JNDI Name as eis/DB/FCCDEV and click Finish.

The jndi name should be the same as the one in the **Dbutility sub-process**.

- 7. Click the **DbAdapter** again.
- 8. Click the Configuration tab and select Outbound Connection Pools.
- Under Groups and Instances, click and expand javax.resource.cci.ConnectionFactory.
 The new JNDI name is listed.
- 10. Click on the eis/DB/FCCDEV link.

The Settings for javax.resource.cci.ConnectionFactory screen displays.

Figure 1-21 Settings for javax.resource.cci.ConnectionFactory



- Click the Property Value field for the DataSourceName and update the application JNDI reference (given in fcubs.properties file), and press the Enter key.
- 12. Click Save and restart the Admin server.

1.2.6 Configure JMS Adapter

This topic explains to configure JMS Adapter.


To configure JMS Adapter, follow the steps given below.

 Log in to Weblogic Console and click on JMS Servers under Domain Configurations -Services.

The Weblogic Console Home Page displays.




Figure 1-22 Oracle Weblogic Console Home Page



Click New.

The **Summary of JMS Servers** screen displays.

Figure 1-23 Summary of JMS Servers




Specify the Name as FCUBSJMSServer for JMS Server, select the Persistent Store as SOAJMSFileStore from the dropdown list and click Next.



The Create a New JMS Server screen displays.


Figure 1-24 Create a New JMS Server



4. Select the **Target** as SOAServer from the dropdown list.

The Create a New JMS Server - Target screen displays.

Figure 1-25 Create a New JMS Server - Target




5. Click Finish.

Two messages displays on the **Summary of JMS Servers** screen.




Figure 1-26 Summary of JMS server - Messages



Go back to Weblogic Console and click JMS Modules under Domain Configurations -Services.

The Weblogic Console - JMS Module screen displays.


Figure 1-27 Weblogic Console - JMS Module





The Summary of JMS Modules screen displays.


Figure 1-28 Summary of JMS Modules



On the Summary of JMS Modules screen, click New.

The Create JMS System Module screen displays.

Figure 1-29 Create JMS System Module




8. Specify the **Name** as FCUBSJMSModule.

The Create JMS System Module - Select Target screen displays.




Figure 1-30 Create JMS System Module - Select Target



- Click Next.
- 10. Select the Target as SOAServer and click Finish.

Two messages displays on the **Summary of JMS Modules** screen.

Figure 1-31 Summary of JMS Modules - Messages




11. Go back to JMS Modules, click on FCUBSJMSModule.

The Settings for FCUBSJMSModule screen displays.




Figure 1-32 Settings for FCUBSJMSModule



12. Click New.

The **Create a New JMS System Module Resource** screen displays.

Figure 1-33 Create a New JMS System Module Resource






 On the Create a New JMS System Module Resource screen, select Connection Factory and click Next.

The Create a New JMS System Module Resource - Connection Factory Properties screen displays.


Figure 1-34 Create a New JMS System Module Resource - Connection Factory Properties



14. Specify Name as FCUBSConnectionfactory and click Next.

The Create a New JMS System Module Resource - Advanced Targeting screen displays.

Figure 1-35 Create a New JMS System Module Resource - Advanced Targeting






15. Click the Advanced Targeting button.

The Create a New JMS System Module Resource - Subdeployments screen displays.

Figure 1-36 The Create a New JMS System Module Resource - Subdeployments




- **16.** Click **Create New Sub Deployment** with the below name, and click **OK**.
- 17. Click Next and select the subdeployment you want to use.
- **18.** If you not yet created a subdeployment, click **Create a New Subdeployment** and specify the **Subdeployment Name** and click **OK**.

The Create a New Subdeployments screen displays.




Figure 1-37 Create a New Subdeployments



19. Click Next and select Targets as FCUBSJMS Servers.

The Create a New JMS System Module Resource - Select Target screen displays.

Figure 1-38 Create a New JMS System Module Resource - Select Target




20. Click Finish.

Two messages displays on the **Settings for FCUBSJMSModule** screen.




Figure 1-39 Settings for FCUBSJMSModule - Messages



 Go back to Weblogic Console, click on JMS Modules, click New, select Queue, and click on Next.

The Create a New JMS System - Queue screen displays.

Figure 1-40 Create a New JMS System - Queue






Specify Name as NOTIFY_DEST_QUEUE and JNDI Name as jms/ NOTIFY_DEST_QUEUE and click Next.

The JMS Destination Properties screen displays.

Figure 1-41 JMS Destination Properties




23. Select the **Subdeployments** from the drop-down list that you created earlier, select the **Targets** as JMS Servers.

The Create a New JMS System Module Resource - Subdeployments and Select Targets screen displays.




Figure 1-42 Create a New JMS System Module Resource - Subdeployments and Targets



24. Click on Finish.

Two messages displays the **Settings for FCUBSJMSModule** screen.

Figure 1-43 Settings for FCUBSJMSModule - Messages






- 25. Create queue MDB_QUEUE_RESPONSE with JNDI name as jms/ MDB_QUEUE_RESPONSE, queue eis/jms/ORGateway with JNDI name as eis/jms/ ORGateway, and queue FAULT_QUEUE_RESPONSE with JNDI name as jms/ FAULT_QUEUE_RESPONSE as above in console within FCUBSJMSModule. (Repeat the steps from 14 to 21).
- 26. Go to Weblogic Console, click Deployment.

The **Summary of Deployment** screen displays.

Figure 1-44 Settings for JMSAdapter



27. Select JMS Adapter.

The **Settings for JMSAdapter - Configuration - Outbound Connection Pools** screen displays.

oracle.tip.adapter.jms.IJmsConnectionFactory







Figure 1-45 Settings for JMSAdapter - Outbound Connection Pools Configuration

 Click Configuration tab, select Outbound Connection Pools and expand oracle.tip.adapter.jms.lJmsConnectionFactory.

The Create a New Outbound Connection screen displays.

Figure 1-46 Create a New Outbound Connection

eis/wls/Topic






- 29. Click New.
- 30. Select the Outbound Connection Group and click Next.

The Create a New Outbound Connection - JNDI Name for Outbound Connection Instance screen displays.

Figure 1-47 Create a New Outbound Connection - JNDI Name for Outbound Connection Instance




- 31. Specify the JNDI Name as eis/Queue/Notif and click Finish.
- **32.** The eis/Queue/Notif is listed in the Outbound Connection Pool Configuration Table on the **Settings for JMSAdapter** screen.

The Settings for JMSAdapter - Table screen displays.




Figure 1-48 Settings for JMSAdapter - Outbound Connection Pool Configuration Table



33. Click on the Outbound connection pool with **eis/Queue/Notif** and specify the connection factory location as **jndi/FCUBSConnectionfactory**, and press enter.

The Settings for oracle.tip.adapter.jms.lJmsConnectionFactory screen displays.

Figure 1-49 Settings for oracle.tip.adapter.jms.lJmsConnectionFactory






34. Click on Save.

Two messages displays on the **Settings for oracle.tip.adapter.jms.IJmsConnectionFactory** screen.


Figure 1-50 Settings for oracle.tip.adapter.jms.IJmsConnectionFactory - Messages



35. Go to Weblogic Console, click Deployment, and select JMS Adapter.

The **Summary of Deployments** screen displays.

Figure 1-51 Summary of Deployments




36. Click Update.

The **Update Application Assistant** screen displays.



Figure 1-52 Update Application Assistant



37. Click Next and then click Finish.

The two messages displays on the **Summary of Deployments** screen.






Figure 1-53 Summary of Deployments - Messages

38. Create the Outbound Connection Pool with the **eis/wls/Queue** name in the Deployments using Connection Factory **jndi/FCUBSConnectionfactory**.

1.2.7 Configure FTP Adapter


This topic explains to configure FTP Adapter using the below steps.

- 1. Login to Weblogic Console, click Deployment, and select FTP Adapter.
- Click the Configurations tab and select Outbound Connection Pool.

The Outbound Connection Pool screen displays.




Figure 1-54 Outbound Connection Pool



Click New.

The Create a New Outbound Connection screen displays.

Figure 1-55 Create a New Outbound Connection



- 4. Specify eis/ftp/FtpAdapterLcl in the JNDI Name field.
- 5. Click Finish and Save.

This topic contains the following sub-topic:



BIP Interactive reports configuration
 This topic explains systematic instructions to configure the BIP Interactive reports with BPEL.


1.2.7.1 BIP Interactive reports configuration

This topic explains systematic instructions to configure the BIP Interactive reports with BPEL.

To configure BPEL with BIP interactive reports, follow the instructions below:

- 1. Login to the **BIP domain console**, http/s:<hostname>:<port>/console.
- To add the FCJCustomProvider, refer to steps from Configure Custom Authentication Provider topic.
- Navigate to Security realms and click myrealm, and then click Users and Groups tab.
 The Settings for myrealm Users and Groups screen displays.

Figure 1-56 Settings for myrealm - Users and Groups



① Note


Check if the users from the schema, display in the **Users** tab, and the roles from the schema are displayed under the **Groups** tab.

- **4.** Login to the **Enterprise Manager** (em) http/s:<hostname>:<port>/em.
 - Right click the domain (in which BI suite is installed) under the WebLogic domain.
 - Go to Security and then navigate to Application Roles.

The **Enterprise Manager** screen displays.




Figure 1-57 Enterprise Manager



- 5. Navigate to the **Application Roles** screen, specify the following details:
 - a. Select **obi** from the **Application Stripe** drop-down.
 - b. Click the **Search** button.
 - c. Click the Create button to add a role.

The **Application Roles** screen displays.

Figure 1-58 Application Roles




- 6. On the Create Application Role screen, specify the following details:
 - **a.** Specify the **Role Name** (mandatory), **Display Name** (optional) and **Description** (optional).



b. Click the Add button.

The Add Principal pop-up displays.

Figure 1-59 Add Principal



- Select Group from the Type drop-down.
- d. Select the checkbox under the **Advanced Option** section and again select Group from the **Type** drop-down.
 - Click the Search button, if the roles are listed then select the roles like ALLROLES-000, ADMINROLE-000 from the list.
 - Specify the **Principal Name** (mandatory), which is the role present in the FCUBS (ex: ALLROLES-000, ADMINROLE-000), Display Name (optional).
- e. Click the **OK** button in the **Add Principal** pop-up and then also in the **Create Application Role** screen.


A confirmation screen displays with a message stating that a new role added successfully.

Again, right click the domain (which BI suite is installed) under the WebLogic domain and select Security and then select Application Policies.

The Application Policies screen displays.



Figure 1-60 Application Policies




- 8. On the Application Policies screen, specify the following details:
 - a. Select obi from the Application Stripe drop-down and also select Application Role in the Principal Type field.
 - b. Click the search button.
 - c. Select **BIConsumer** from the list and click the **Create** button.

The Application Policies screen displays.




Figure 1-61 Application Policies



On the Create Application Grant screen, click the Add button.

The Add Principal pop-up window displays.

Figure 1-62 Add Principal




- 10. On the Add Principal pop-up window, perform the following actions:
 - a. Select **Application Role** from the **Type** drop-down list and click the **Search** button.
 - b. From the **Searched Principals** list, select **ALLROLES** that has been created earlier in the **Application Role** screen.



- c. Click the OK button in the Add Principal pop-up window and also on the Create Application Grant screen.
- Click the Add button under Permissions section and add the two permissions one by one as mentioned below.
 - oracle.bi.publisher.runReportOnline
 - oracle.bi.publisher.accessReportOutput

The Create Application Grant - Permissions screen displays.

Figure 1-63 Create Application Grant




The confirmation screen displays with a message stating that a security added successfully.

- 12. Login into the **BI Publisher**, http/s:<hostname>:<port>/xmlpserver.
- 13. Click Administration.
- **14.** Click **Roles and Permission** under **Security Center** and check whether the added role (in em) is displayed or not, if not, restart the servers.

The BIPublisher - Administration screen displays.




Figure 1-64 BIPublisher - Administration



15. Click Catalog, select the folder that has been created.

The **BIPublisher - Catalog** screen displays.

Figure 1-65 BIPublisher - Catalog




16. Click Permissions under the Tasks.

The **Permissions** pop-up displays.




Figure 1-66 Permission



- 17. Delete all the roles if any present.
- 18. Click the Add button.
- 19. Click the **Search** button in the **Add Roles** pop-up window.
- 20. Select the role that has been created and click the Move button and then click OK.
 The role will be added in the Permissions pop-up window.

Figure 1-67 Permissions - Add Roles



21. Select the options that should be granted to the particular role and check if permissions are only granted to items in the folder if necessary.

Now the reports in the folder will be accessed accordingly based on roles.




① Note

Similarly, you can set the permissions at the report level also for a particular role.

- 22. Login in to **BI Publisher** using http://server:port/xmlpserver.
- 23. Click Administration.

The **Administration** screen displays.

Figure 1-68 Administration




24. Under Data Sources, click JDBC Connection.

The Administration - JDBC screen displays.



Figure 1-69 Administration - JDBC




25. Click **Add Data Source** to create the data source with name as **FCSOA** and use SOA schema details to create the same.

The Add Data Source screen displays.



Figure 1-70 Add Data Source




26. Under Security, add FCUBS roles to Allowed Roles.

The Add Data Source (Security) screen displays.



Figure 1-71 Add Data Source (Security)



- 27. Click Test Connection.
- 28. Once the connection is established successfully, click Apply.
- 29. Follow steps 25 to 28 to create the data source for FCUBS Schema and specify the name as FCBIPBPEL.

1.2.8 BAM Report Configuration settings

This topic explains the configuration settings for BAM reports.


Generate a deployment plan for BAM Composer Application. If you want to configure BPEL with BAM reports, follow the steps below:

- Generate a deployment plan for BAM Composer Application.
- 2. Log in to console http://<hostname>:<port>/<console>.
- 3. Under the **Domain Structure**, click **Deployments**.

The **Summary of Deployments** screen displays.




Figure 1-72 Summary of Deployments



Click BAM Composer.

The **Summary of BAM Composer** screen displays.

Figure 1-73 Summary of BAM Composer






- On the Summary of BAM Composer screen, click the Configuration tab, select the Application tab and click the Save button.
- 6. Click the **Overview** tab and check the **Deployment Plan** location.

The **Summary of BAM Composer - Overview** screen displays.

Figure 1-74 Summary of BAM Composer - Overview



7. Add variable and variable assignment as below to the Plan.xml in <module-name>BamComposerWeb.war</module-name>.

```
<variable>
  <name>oracle.adf.view.rich.security.FRAME_BUSTING</name>
  <value>never</value>
  </variable>
<module-descriptor external="true">
  <root-element>web-app</root-element>
  <uri>WEB-INF/web.xml</uri>
  <variable-assignment>
  <name>oracle.adf.view.rich.security.FRAME_BUSTING</name>
  <xpath>/web-app/context-param/
[paramname="oracle.adf.view.rich.security.FRAME_BUSTING"]/param-value</xpath>
  <origin>planbased</origin>
  </variable-assignment> </module-descriptor>
```


- 8. On the **Summary of Deployments** screen, click the **Stop** button and the following options are displayed.
 - When work completes



- Force Stop Now
- Stop, but continue servicing administration requests
- 9. Click Force Stop Now.
- To update the deployment plan, click **Deployment** and select the **BAM Composer** checkbox.

The **Summary of Deployments - Update** screen displays.

Figure 1-75 Summary of Deployments - Update




11. Click the Update button.

The **Update Application Assistant** screen displays.



Figure 1-76 Update Application Assistant




- 12. On the Update Application Assistant screen, select the Update this application in place with new deployment plan changes option and click the change path button.
- **13.** Select the latest plan.xml in the path, and click the **Next**.

The **Update Application Assistant - Select a deployment plan** screen displays.



Figure 1-77 Update Application Assistant - Select a deployment plan




14. Click Finish.

Two messages are displayed on the **Summary of Deployments** screen.



Figure 1-78 Summary of Deployments - Messages



15. Restart the BAM Composer application in the console.

The Summary of Deployments - Restart BAM Composer screen displays.







Figure 1-79 Summary of Deployments - Restart BAM Composer

- **16.** Log in to Enterprise Manager console http://hostname:port/em.
- Right click the BAM Server, and click Security and then click Application Roles.
 The BAM Server Application Roles screen displays.

Figure 1-80 BAM Server - Application Roles




18. On the **Application Roles** screen, click the **Create** button to create application role with **ALL ROLES-000** name.



The Create Application Role screen displays.


Figure 1-81 Create Application Role



- 19. Click the ADD button under the Members section.
- 20. Select the **Group** from the **Type** drop-down list and add principle details.
- 21. Log in to BAM Composer http://hostname:port/bam/composer.
- 22. Click Administrator.

The Oracle BAM Composer - Administrator screen displays.

Figure 1-82 Oracle BAM Composer - Administrator






23. Under Data Objects, Right click CUBE_INSTANCE and select Security.

The **BAM Composer - Navigate to Security** screen displays.


Figure 1-83 BAM Composer - Navigate to Security



24. Click the Add button under Grant permission and search the list based on the Application Role.

The **Security** screen displays.

Figure 1-84 Security






25. Move the ALLROLES-000 to the Selected Members column.

The Security - Add Application Roles, Groups and Users screen displays.


Figure 1-85 Security - Add Application Roles, Groups and Users



26. Select Read, Select, and Update checkboxes and click the Save button.

The Add Application Roles, Groups and Users - ALLROLES-000 screen displays.

Figure 1-86 Add Application Roles, Groups and Users - ALLROLES-000






- 27. Follow the steps 21 to 27 for other Data objects as listed below:
 - cube_instance
 - wftask_different_stages
 - ORVW_TRACK_EXPOSURE
 - ORVW_FACILITY_EXPOSURE
 - GetUtilsDB
 - SMTB_USER_TYPE_CONVERSION_VIEW
 - FCUBSDATAOBJECTS
- 28. On the Oracle BAM Composer, click the Designer.

The Oracle BAM Composer Designer screen displays.

Figure 1-87 Oracle BAM Composer Designer




29. Click Open Project.

The **Open Project** pop-up window displays.




Figure 1-88 Designer - Open Project



- 30. On the Open Project pop-up window, click FCUBS_BAM_Report.
- **31.** On the **Designer** screen, right click **FCUBS_BAM_Report** and select **Security**. The **FCUBS_BAM_Report Security** screen displays.

Figure 1-89 FCUBS_BAM_Report - Security






32. On the FCUBS_BAM_Report (Security) screen, click the ADD icon under Grant Permission.

The FCUBS_BAM_Report (Security) screen displays.


Figure 1-90 FCUBS_BAM_Report (Security)



33. Search the list based on the **Application Roles** and select the **ALLROLES-000**.

The Add Application Roles, Groups and Users - ALLROLES-000 pop-up window displays.

Figure 1-91 Add Application Roles, Groups and Users - ALLROLES-000






34. Move the ALLROLES-000 to Selected Members column and click the OK button.

The Add Application Roles, Groups and Users - ALLROLES-000 - Selected Members pop-up window displays.

Figure 1-92 Add Application Roles, Groups and Users - ALLROLES-000 - Selected Members



35. Select the Read checkbox for ALLROLES-000 and click the Save button.

The FCUBS_BAM_Report (Security) - ALLROLES-000 screen displays.



Figure 1-93 FCUBS_BAM_Report (Security) - ALLROLES-000

1.2.9 Configure IPM to Edit Document

This topic explains to edit the document using the IPM configuration.


If you want to configure BPEL with IPM configuration, perform the following steps.

- 1. Login to the console, http/s:<hostname>:<port>/console with admin user.
- To add the FCJCustomProvider, Refer to the <u>Configure Custom Authentication Provider</u> topic.
- 3. Navigate to Security Realms, click myrealm, and click Users and Groups tab.
 - Check if the users from the schema are displayed in the **Users** tab, and roles from the schema are displayed under the **Groups** tab.
- **4.** After adding the custom authenticator, perform the following actions:
 - Navigate to Security Realms, click myrealm, click Users and Groups and click the Groups tab.

The **Settings for myrealm** screen displays.




Figure 1-94 Setting for myrealm



b. Click the New button.

The **Create a New Group** screen displays.

Figure 1-95 Create a New Group



- 5. On the **Create a New Group** screen, specify the following details.
 - a. Specify the name as **IPMUserGroup**.
 - **b.** Specify the **Description** for the new group (optional).
 - c. Select the Provider as DefaultAuthenticator.
 - d. Click the **OK** button.
- 6. Login to the Imaging using the following URL http/s:<hostname>:<port>/imaging with admin user.



The Oracle Webcenter Content:Imaging log in screen displays.


Figure 1-96 Oracle Webcenter Content:Imaging



7. Specify User ID and Password and click Sign in.

The FLEXCUBE: Application Summary screen displays.

Figure 1-97 FLEXCUBE: Application Summary




- 8. Navigate to Manage Applications on the left pane.
- 9. Click FLEXCUBE.
- 10. Click the **Modify** button on the right pane.

The Create Application Document Security screen displays.



Figure 1-98 Create Application Document Security



- 11. On the Create Application Document Security screen, perform the following steps:
 - a. Click Document Security tab.
 - b. Click the Add button.

The Add Security Member pop-up window displays.

- c. Click the Search button in the Add Security Member pop-up window.
- d. Select the IPMUserGroup.
- e. Click Add.


IPMUserGroup is listed in the panel.

- f. Select View, Write, Annotate Standard, Annotate Restricted and Annotate Hidden checkboxes.
- g. Click Submit.

The USER_ID:Search Summary screen displays.




Figure 1-99 USER_ID:Search Summary



- 12. On the USER_ID: Search Summary screen, perform the following steps:
 - a. Navigate to Manage Searches.
 - b. Select the available search (ex: USER ID in this doc).
 - c. Click the Modify button.

The USER_ID:Search Security screen displays.

Figure 1-100 USER_ID:Search Security



- **13.** On the **USER_ID:Search Security** screen, perform the following steps:
 - a. Click the Security tab.



b. Click the Add button.

The Add Security Member pop-up window displays.

- c. Click the **Search** button in the **Add Security Member** pop-up window.
- d. Select the IPMUserGroup.
- e. Click **Add** button.

The **IPMUserGroup** will be listed in the panel; don't select any checkbox except the default **View** checkbox.

- f. Click the **Submit** button on the right corner.
- **14.** Copy the **FCJJPSProvider.jar** to location <ORACLE_HOME >\user_projects\domains\<domian name>\lib .
- 15. Go to the location <ORACLE_HOME>\
 user_projects\domains\<Domain_created>\config\fmwconfig.
 - **a.** Open **jps-config.xml** file and search <serviceProviders> tag and add the following code between <serviceProviders> and </serviceProviders> tags.

```
<serviceProvider
class="oracle.security.jps.internal.idstore.generic.GenericIdentityStore
Provider"
name="custom.generic.provider" type="IDENTITY_STORE">
<description>DB IdentityStore Provider</description>
</serviceProvider>
```

b. Similarly, search for <serviceInstances> tag and add the following code between <serviceInstances> and </serviceInstances> tags.

Make sure that the JNDI (jdbc/fcjdevDS) matches the value given during property file creation.

c. Search for <jpsContexts default="default"> tag and add the following code between <jpsContexts default="default"> and </jpsContexts>, preferably after the default ipsContext.

```
<jpsContext name="internalstore">
  <serviceInstanceRef ref="credstore"/>
  <serviceInstanceRef ref="keystore"/>
  <serviceInstanceRef ref="policystore.xml"/>
  <serviceInstanceRef ref="audit"/>
  </jpsContext>
```




1.2.10 Configure Supervisor Roles in EM

This topic explains to configure supervisor roles in the Oracle Enterprise Manager.

Right click soa-infra and select Security and click Application Roles.

The Target Navigation of Application Roles screen displays.

Figure 1-101 Target Navigation of Application Roles




2. Search the Application Roles with the **Starts With** option.

The Application Roles screen displays.



Figure 1-102 SOA Infra - Application Roles




- Select SOA Admin role and click the Edit option.
- 4. On the Edit Application Roles: SOAAdmin screen, click the ADD button.

The Add Principal pop-up window displays.



Figure 1-103 Add Principal



- Select the Group from the Type drop-down.
- 6. Specify the **Principal Name** as (EX: ALLROLES-000) Param_val, which is mapped to the OR_ADMINROLE in the cstb_param table and search the role.

The list of application roles is displayed based on the criteria specified.

Figure 1-104 Add Principal - ALLROLES-000



7. Click the **OK** button.



1.2.11 Configure Email Driver


This topics explains the steps to configure the Email Driver.

To configure the Email Driver in BPEL, follow the steps below:

- Log in to EM console.
- 2. Navigate to User Messaging Service folder.

The **User Messaging Service** target navigation folder displays.

Figure 1-105 User Messaging Service




- 3. Right click usermessagingdriver-email (soa_server1).
- 4. Click Email Driver Properties.

The usermessagingdriver-email screen displays.




Figure 1-106 usermessagingdriver-email



- Specify the Sender Address and Default Sender Address (This ID will be used as sender address).
- Specify the supported protocols (SMTP).
- 7. Select the mail access protocol (IMAP) as per the mail server specification.

The Driver-Specific Configuration screen displays.


Figure 1-107 Driver-Specific Configuration



- Specify the Receive folder in the mailbox (INBOX).
- 9. Specify the Outgoing Mail Server hostname or IP.
- Specify the Outgoing Mail Server Port.
- Specify the Outgoing Default From Address.
- 12. Specify the Outgoing Username and Password if required.




Figure 1-108 Driver-Specific Configuration



- 13. Navigate to SOA folder.
- Right click soa-infra (soa_server1) and select SOA Administration and then click Workflow Porperties.

The Workflow Notification Properties screen displays.

Figure 1-109 Workflow Notification Properties



- 15. Select Email/ALL from the Notification Modedrop-down list.
- 16. Specify the From Address, Actionable Address, and Reply To Address.

1.2.12 Configure TimeOut Settings for BPEL

This topic explains steps to configure TimeOut Settings for BPEL.


To configure TimeOut setting for BPEL, follow the below steps:

1. Login into Console (http://hostname:port/console).

The WebLogic Server Home page displays.




Figure 1-110 WebLogic Server



Click Deployments.

The **Summary of Deployments** screen displays.

Figure 1-111 Summary of Deployments




- 3. Click **soa-infra** application under deployments.
- 4. Go to EJBs, click BPELEngineBean.

The **Summary of BPELEngineBean** screen displays.



Figure 1-112 Summary of BPELEngineBean



On the BPELEngineBean screen, click Configuration and set Transaction TimeOut to 300.







Figure 1-113 BPELEngineBean Configuration - Transaction TimeOut

Go to EJBs, click BPELDeliveryBean.

The Summary of BPELDeliveryBean screen displays.




Figure 1-114 Summary of BPELDeliveryBean



 On the BPELDeliveryBean screen, click Configuration and set Transaction TimeOut to 300.

Figure 1-115 BPELDeliveryBean Configuration - Transaction TimeOut






- Login to Console and click JTA under Services.
- 9. Set the JTA timeout according to the below condition:

BPELEngineBean + BPELDeliveryBean is <= JTA timeout (For example 300+300<=600).

The Settings for dev_domain JTA screen displays.

Figure 1-116 Settings for dev_domain - JTA




- 10. Login to EM console (http://host:port/em).
- 11. Right click on the soa-infra (SOAServer).
- 12. Select SOA Administration and then click the BPEL Porperties.

The **soa-infra** screen displays.



Figure 1-117 SOA Infra



- 13. Click MoreConfigpropeties and then click SyncMaxWaitTime.
- 14. Change the SyncMaxWaitTime to 200 secs.






Figure 1-118 System MBean Browser

1.3 Integration of Oracle FLEXCUBE UBS and Scheduler

This topic explains Integration of Oracle FLEXCUBE UBS and Scheduler.

Before deploying the Oracle FLEXCUBE UBS EAR file, you must follow the tasks below.

<u>Running Backend Scripts</u>
 This topic provides the systematic instructions to run the backend scripts in the schema.

1.3.1 Running Backend Scripts

This topic provides the systematic instructions to run the backend scripts in the schema.

You must compile specific tables related to the Scheduler in the schema that are pointed by the application. Use the latest qualified version of Quartz.

Follow the steps given below:

- Download Quartz Latest Qualified Version.gz file from the following URL: http://www.quartz-scheduler.org/download/download-catalog.html.
- 2. Extract the gz file.
- 3. Open the Quartz-Latest Qualified Version\docs\dbTables folder and run the tables_oracle.sql (this is specific to Oracle Database) in the schema.





(i) Note

For more details on the latest version of the software qualified with Oracle FLEXCUBE, refer to the release certificate.

1.4 Integration of Oracle FLEXCUBE UBS and BIP Reports

This topic explains integration of Oracle FLEXCUBE UBS and BIP Reports.

For more details about integrate Oracle FLEXCUBE UBS and BIP reports, refer to the BIP Web Service Reports chapter in the Oracle Analytics Publisher Web Service Reports user manual.

Deploy Application Through Application Server's Admin Console This topic explains deployment of application through Weblogic Administration Console.

1.4.1 Deploy Application Through Application Server's Admin Console

This topic explains deployment of application through Weblogic Administration Console.

For more details related to the deployment of Application using Weblogic Administration Console, refer to the Deploying Oracle FLEXCUBE Application on WebLogic user manual.

1.5 Integration of Oracle FLEXCUBE UBS and MBean

This topic explains to integrate Oracle FLEXCUBE UBS with MBean plug-in.

To integrate Oracle FLEXCUBE UBS and MBean, you must follow the below steps before deploying the Oracle FLEXCUBE UBS EAR file created with MBean as a Plugin.

Startup Script Modification This topic explains the Startup Script Modification.

1.5.1 Startup Script Modification

This topic explains the Startup Script Modification.

By default, the TopLink used in MBean uses Oracle xml parser internally. However, Weblogic Server has to use JAXPlatform.

To change the system property, follow the steps below:

- 1. Go to the **Weblogic domain** home folder.
 - Based on the operating system used, open startWeblogic.cmd (Windows) or startWeblogic.sh (Linux) from the bin folder.
 - b. Search for WLS REDIRECT LOG. After %JAVA OPTIONS% add the following code under if and else conditions.

-Dtoplink.xml.platform=oracle.toplink.platform.xml.jaxp.JAXPPlatform Now, the details will look like this:

```
if "%WLS REDIRECT LOG%"=="" (
echo Starting WLS with line:
echo %JAVA_HOME%\bin\java %JAVA_VM% %MEM_ARGS% -
Dweblogic.Name=%SERVER NAME% -
```



```
Djava.security.policy=%WL_HOME%\server\lib\weblogic.policy
%JAVA OPTIONS% %PROXY SETTINGS% %SERVER CLASS%
%JAVA_HOME%\bin\java %JAVA_VM% %MEM_ARGS% -
Dweblogic.Name=%SERVER_NAME% -
Djava.security.policy=%WL_HOME%\server\lib\weblogic.policy
%JAVA OPTIONS% -
Dtoplink.xml.platform=oracle.toplink.platform.xml.jaxp.JAXPPlatform
%PROXY_SETTINGS% %SERVER_CLASS%
) else (
echo Redirecting output from WLS window to %WLS_REDIRECT_LOG%
%JAVA_HOME%\bin\java %JAVA_VM% %MEM_ARGS% -
Dweblogic.Name=%SERVER_NAME% -
Djava.security.policy=%WL_HOME%\server\lib\weblogic.policy
%JAVA_OPTIONS% -
Dtoplink.xml.platform=oracle.toplink.platform.xml.jaxp.JAXPPlatform
%PROXY_SETTINGS% %SERVER_CLASS% >"%WLS_REDIRECT_LOG%" 2>&1
)
```

2. Restart the Weblogic server.