

ICPKS_GEN_NEW Package
Extensible Hook Details
14.1

May 2018

Oracle Financial Services Software Limited

Oracle Park

Off Western Express Highway
Goregaon (East)
Mumbai, Maharashtra 400 063
India

Worldwide Inquiries:

Phone: +91 22 6718 3000

Fax: +91 22 6718 3001

www.oracle.com/financialservices/

Copyright © 2007, 2016, Oracle and/or its affiliates. All rights reserved.

Oracle and Java are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

U.S. GOVERNMENT END USERS: Oracle programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, delivered to U.S. Government end users are "commercial computer software" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, use, duplication, disclosure, modification, and adaptation of the programs, including any operating system, integrated software, any programs installed on the hardware, and/or documentation, shall be subject to license terms and license restrictions applicable to the programs. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate failsafe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

This software or hardware and documentation may provide access to or information on content, products and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services.

Contents

1. PR_GEN_CALC/1/1	1
2. PR_GEN_CALC/1/2	2
3. PR_GEN_CALC/1/3	2
4. PR_GEN_CALC/1/4	3
5. PR_GEN_CALC/1/5	3
6. PR_GEN_CALC/1/6	4
7. PR_GEN_CALC/1/7	4
8. PR_GEN_CALC/1/8	5
9. PR_GEN_CALC/1/9	5
10. PR_GEN_CALC/1/10	6
11. PR_GEN_CALC/1/11	6
12. PR_GEN_CALC/1/12	7
13. PR_GEN_CALC/1/13	8
14. PR_GEN_CALC/1/14	8
15. PR_GEN_CALC/1/15	9
16. PR_GEN_CALC/1/16	9
17. PR_GEN_CALC/1/17	10
18. PR_GEN_CALC/1/18	11
19. PR_GEN_CALC/1/19	11
20. PR_GEN_COMBO/1/1	12
21. PR_GEN_COMBO/1/2	12
22. PR_GEN_COMBO/1/3	13
23. PR_GEN_COMBO/1/4	13
24. PR_GEN_COMBO/1/5	14
25. PR_GEN_COMBO/1/6	14
26. PR_GEN_COMBO/1/7	15
27. PR_GEN_COMBO/1/8	15
28. PR_GEN_COMBO/1/9	16
29. PR_GEN_COMBO/1/10	16
30. PR_GEN_COMBO/1/11	17
31. PR_GEN_COMBO/1/12	18
32. PR_GEN_COMBO/1/13	18

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	1
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653
Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	2
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA := L_TB_CLUSTER_DATA_EMPTY, L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.

Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	3
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	4
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)

Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	5
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := UPPER(ET(I),ELEM)
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	6
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA

Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := X.FRM_NO, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	7
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	8
Cluster/Custom Function Name	PR_GEN_CALC

Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	9
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	10

Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16592809

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	11
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17494560

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	12
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17494560

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	13
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_RULE_ID) := R_ID, I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT, I_Tb_Cluster_Data(L_FRM_NO) := X.FRM_NO, I_Tb_Cluster_Data(L_EXPR_LINE) := X.EXPR_LINE, I_Tb_Cluster_Data(L_PRD_FLAG) := (CASE WHEN X.PR_D_FLAG = D THEN I ELSE L END)
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.

Description	<p>Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	17494560

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	14
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_RULE_ID) := R_ID, I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT, I_Tb_Cluster_Data(L_FRM_NO) := X.FRM_NO, I_Tb_Cluster_Data(L_EXPR_LINE) := X.EXPR_LINE, I_Tb_Cluster_Data(L_PRD_FLAG) := (CASE WHEN X.PR_D_FLAG = D THEN I ELSE L END)
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	<p>Hook is placed in icpks_gen_new.pr_gen_calc(),to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	17494560
Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	15
Cluster/Custom Function Name	PR_GEN_CALC

Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc()to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	Hook is placed in icpks_gen_new.pr_gen_calc()to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17494560

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	16
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	I_Fn_Call_ID , I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_RULE_ID) := P_RULE_ID, I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to add multi Term Deposit account in a SOD and interest should be calculated on the basis of average rate of those Term Deposit A/c.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to add multi Term Deposit account in a SOD and interest should be calculated on the basis of average rate of those Term Deposit A/c. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	18724582

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1

Function Call Id	17
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_RULE_ID) := P_RULE_ID, I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT, I_Tb_Cluster_Data(L_FRM_NO) := X.FRМ_NO, I_Tb_Cluster_Data(L_RESULT) := X.RESULT, I_Tb_Cluster_Data(L_DRСRIND) := x.drcr_ind, I_Tb_Cluster_Data(L_EXPR_LINE) := x.expr_line
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT), X.FRМ_NO := I_Tb_Cluster_Data(L_FRM_NO), X.RESULT := I_Tb_Cluster_Data(L_RESULT), x.expr_line := I_Tb_Cluster_Data(L_EXPR_LINE)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to add multi Term Deposit account in a SOD and interest should be calculated on the basis of average rate of those Term Deposit A/c.
Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to add multi Term Deposit account in a SOD and interest should be calculated on the basis of average rate of those Term Deposit A/c. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	18724582

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	18
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_RULE_ID) := P_RULE_ID, I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc() to add multi Term Deposit account in a SOD and interest should be calculated on the basis of average rate of those Term Deposit A/c.

Description	<p>Hook is placed in icpks_gen_new.pr_gen_calc() to add multi Term Deposit account in a SOD and interest should be calculated on the basis of average rate of those Term Deposit A/c.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	18724582

Parameter	Description
Function	PR_GEN_CALC
No of Parameters	1
Function Call Id	19
Cluster/Custom Function Name	PR_GEN_CALC
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_ELEM) := UPPER(ET(I+1).ELEM), L_TB_CLUSTER_DATA(L_BASIS) := UPPER(ET(I+1).SDE_BASIS)
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_calc(),to calculate interest based on beginning of day balance for Customer Accounts.
Description	<p>Hook is placed in icpks_gen_new.pr_gen_calc(),to calculate interest based on beginning of day balance for Customer Accounts.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	20685311

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	1
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL

Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo(), for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo(), for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	2
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	3
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA

Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	4
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	5
Cluster/Custom Function Name	PR_GEN_COMBO

Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := ET(I).ELEM
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	6
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := X.FRМ_NO, L_TB_CLUSTER_DATA(L_ELEM) := ET(I).ELEM
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	7

Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	8
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653
Parameter	Description
Function	PR_GEN_COMBO

No of Parameters	1
Function Call Id	9
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	10
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16592809

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	11
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL, L_TB_CLUSTER_DATA(N_ACCR_FRM) := N_ACCR_FRM, L_TB_CLUSTER_DATA(ACCRUED_FRM) := ACCRUED_FRM, L_TB_CLUSTER_DATA(ONLY_DLY_ELEM) :=Y
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	12
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding.

Description	Hook is placed in icpks_gen_new.pr_gen_combo() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16592809

Parameter	Description
Function	PR_GEN_COMBO
No of Parameters	1
Function Call Id	13
Cluster/Custom Function Name	PR_GEN_COMBO
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := UPPER(ET(I+1).ELEM), L_TB_CLUSTER_DATA(L_BASIS) := UPPER(ET(I+1).SDE_BASIS)
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.pr_gen_combo()to calculate interest based on beginning of day balance for Customer Accounts.
Description	Hook is placed in icpks_gen_new.pr_gen_combo()to calculate interest based on beginning of day balance for Customer Accounts. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	20685311

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	1
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)

Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	2
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	3
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA

Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := X.FRM_NO, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	4
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := X.FRM_NO, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	5
Cluster/Custom Function Name	PR_GEN_RULE

Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	6
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) :=UPPER(ET(I).ELEM)
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	7

Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := X.FRM_NO, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	8
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653
Parameter	Description
Function	PR_GEN_RULE

No of Parameters	1
Function Call Id	9
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	10
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	11
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	12
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.

Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	13
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	14
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)

Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE()for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE()for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	15
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16592809

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	16
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA

Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL, L_TB_CLUSTER_DATA(N_ACCR_FRM) := N_ACCR_FRM, L_TB_CLUSTER_DATA(ACCRUED_FRM) := ACCRUED_FRM, L_TB_CLUSTER_DATA(ONLY_DLY_ELEM) := Y
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	16565653

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	17
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17282322

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1

Function Call Id	18
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17282322

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	19
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17282322

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	20
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_ELEM) := UPPER(ET(I+1).ELEM), L_TB_CLUSTER_DATA(L_BASIS) := UPPER(ET(I+1).SDE_BASIS)
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() for IC_Compounding. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17282322

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	21
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.

Description	<p>Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	17494560
Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	22
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	<p>Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p>
Description	<p>Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	17494560

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	23
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)

Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17494560

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	24
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := R_ID, I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := X.FRM_NO, L_TB_CLUSTER_DATA(L_EXPR_LINE) := X.EXPR_LINE, L_TB_CLUSTER_DATA(L_PRD_FLAG) := (CASE WHEN X.PRD_FLAG = D THEN I ELSE L END), L_TB_CLUSTER_DATA(L_RESULT) := X.RESULT
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17494560

Parameter	Description
Function	PR_GEN_RULE

No of Parameters	1
Function Call Id	25
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := R_ID, I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := X.FRM_NO, L_TB_CLUSTER_DATA(L_EXPR_LINE) := X.EXPR_LINE, L_TB_CLUSTER_DATA(L_PRD_FLAG) := (CASE WHEN X.PRD_FLAG = D THEN I ELSE L END), L_TB_CLUSTER_DATA(L_RESULT) := X.RESULT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17494560

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	26
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.

Description	<p>Hook is placed in icpks_gen_new.PR_gen_RULE() to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	17494560

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	27
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)
Hook Description	<p>Hook is placed in icpks_gen_new.PR_gen_RULE() to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p>
Description	<p>Hook is placed in icpks_gen_new.PR_gen_RULE() to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.</p> <p>All parameters received by kernel function are passed to the cluster hook.</p> <p>Additional parameters passed to cluster hook are mentioned in field "Additional Parameters".</p> <p>The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook.</p> <p>The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.</p>
Bug No	17494560

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	28
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	I_Fn_Call_ID, I_Tb_Cluster_Data
Sent to Extensible layer	I_Tb_Cluster_Data(L_PROC_TEXT) := PROC_TEXT
Received from Extensible layer	PROC_TEXT := I_Tb_Cluster_Data(L_PROC_TEXT)

Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE() to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE() to view the interest calculation details including the customer account balance, rate, attached IC product, IC formula with applied interest rate and calculated interest amount for a given period. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	17494560

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	29
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) :=X.FRМ_NO, L_TB_CLUSTER_DATA(L_ELEM) := NULL
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to compute the average balance interest for the factory shipped SDEs.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), to compute the average balance interest for the factory shipped SDEs. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	19139361

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	30
Cluster/Custom Function Name	PR_GEN_RULE

Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_FRM_NO) := NULL, L_TB_CLUSTER_DATA(L_ELEM) := NULL, L_TB_CLUSTER_DATA(N_ACCR_FRM) := N_ACCR_FRM, L_TB_CLUSTER_DATA(ACCRUED_FRM) := ACCRUED_FRM, L_TB_CLUSTER_DATA(ONLY_DLY_ELEM) := Y
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), and few changes in the existing hooks.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE(), and few changes in the existing hooks. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	20682487

Parameter	Description
Function	PR_GEN_RULE
No of Parameters	1
Function Call Id	31
Cluster/Custom Function Name	PR_GEN_RULE
Additional parameters	L_FN_CALL_ID, L_TB_CLUSTER_DATA
Sent to Extensible layer	L_TB_CLUSTER_DATA(L_RULE_ID) := P_RULE_ID, L_TB_CLUSTER_DATA(L_PROC_TEXT) := PROC_TEXT, L_TB_CLUSTER_DATA(L_ELEM) := UPPER(ET(I+1).ELEM), L_TB_CLUSTER_DATA(L_BASIS) := UPPER(ET(I+1).SDE_BASIS)
Received from Extensible layer	PROC_TEXT := L_TB_CLUSTER_DATA(L_PROC_TEXT)
Hook Description	Hook is placed in icpks_gen_new.PR_gen_RULE()to calculate interest based on beginning of day balance for Customer Accounts.
Description	Hook is placed in icpks_gen_new.PR_gen_RULE()to calculate interest based on beginning of day balance for Customer Accounts. All parameters received by kernel function are passed to the cluster hook. Additional parameters passed to cluster hook are mentioned in field "Additional Parameters". The variables mentioned in "Sent to Extensible Layer" field are passed to cluster hook. The variables mentioned in "Received from Extensible Layer" field are reassigned to kernel.
Bug No	20685311