

Oracle® Communications Network Charging and Control

Location Capabilities Pack Alarms Guide



Release 15.0.0

October 2023

The Oracle logo, consisting of the word "ORACLE" in white, uppercase, sans-serif font, centered within a solid red square.

Copyright

Copyright © 2023, Oracle and/or its affiliates.

This software and related documentation are provided under a license agreement containing restrictions on use and disclosure and are protected by intellectual property laws. Except as expressly permitted in your license agreement or allowed by law, you may not use, copy, reproduce, translate, broadcast, modify, license, transmit, distribute, exhibit, perform, publish, or display any part, in any form, or by any means. Reverse engineering, disassembly, or decompilation of this software, unless required by law for interoperability, is prohibited.

The information contained herein is subject to change without notice and is not warranted to be error-free. If you find any errors, please report them to us in writing.

If this is software or related documentation that is delivered to the U.S. Government or anyone licensing it on behalf of the U.S. Government, then the following notice is applicable:

U.S. GOVERNMENT END USERS: Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs) and Oracle computer documentation or other Oracle data delivered to or accessed by U.S. Government end users are "commercial computer software" or "commercial computer software documentation" pursuant to the applicable Federal Acquisition Regulation and agency-specific supplemental regulations. As such, the use, reproduction, duplication, release, display, disclosure, modification, preparation of derivative works, and/or adaptation of i) Oracle programs (including any operating system, integrated software, any programs embedded, installed or activated on delivered hardware, and modifications of such programs), ii) Oracle computer documentation and/or iii) other Oracle data, is subject to the rights and limitations specified in the license contained in the applicable contract. The terms governing the U.S. Government's use of Oracle cloud services are defined by the applicable contract for such services. No other rights are granted to the U.S. Government.

This software or hardware is developed for general use in a variety of information management applications. It is not developed or intended for use in any inherently dangerous applications, including applications that may create a risk of personal injury. If you use this software or hardware in dangerous applications, then you shall be responsible to take all appropriate fail-safe, backup, redundancy, and other measures to ensure its safe use. Oracle Corporation and its affiliates disclaim any liability for any damages caused by use of this software or hardware in dangerous applications.

Oracle, Java, and MySQL are registered trademarks of Oracle and/or its affiliates. Other names may be trademarks of their respective owners.

Intel and Intel Inside are trademarks or registered trademarks of Intel Corporation. All SPARC trademarks are used under license and are trademarks or registered trademarks of SPARC International, Inc. AMD, Epyc, and the AMD logo are trademarks or registered trademarks of Advanced Micro Devices. UNIX is a registered trademark of The Open Group.

This software or hardware and documentation may provide access to or information about content, products, and services from third parties. Oracle Corporation and its affiliates are not responsible for and expressly disclaim all warranties of any kind with respect to third-party content, products, and services unless otherwise set forth in an applicable agreement between you and Oracle. Oracle Corporation and its affiliates will not be responsible for any loss, costs, or damages incurred due to your access to or use of third-party content, products, or services, except as set forth in an applicable agreement between you and Oracle.

Contents

Alarm Topic Description1

Location Capabilities Pack Alarms3

Alarm Topic Description

Alarm Generation

Alarms on each configured node are written to the syslog and are then captured by the smsAlarmDaemon for entry in the SMF database.

For management of these alarms, see *Service Management System Technical Guide*.

Severity Levels

This table describes the alarm severity levels.

Level	Abbreviation	Description
Critical	C	These alarms are raised when the application has encountered an error indicating that the system is unable to function.
Error	E	These alarms indicate the application has encountered a serious problem completing a necessary task and could not complete the task.
Warning	W	Warnings are raised to indicate the application encountered a problem completing a non-mission critical task.
Notice	N	Notices are raised to indicate that the application has completed a task successfully.

Alarm Format

Alarms usually follow this format:

```
Mon DD 24:MM:SS hostname process name: [ID alarmID user.severity] process(PID)
SEVERITY: Alarm text with possible variables
```

Where:

Variable	Description
Mon DD	Month and date the alarm was logged.
24:MM:SS	Time the alarm was logged in 24 hour format.
hostname	Name of the machine on which the alarm was generated.
process name	Name of the process which logged the alarm.
alarmID	ID number of the alarm.
severity	Alarm severity.
process	Name of the process which logged the alarm.
PID	Process ID of the process which logged the alarm.
SEVERITY	Alarm severity.
Alarm text	Alarm text. This may include variables such as node number. Note: In some cases, the entire alarm text is generated from variables.

Note: Some alarms from some subsystems may have a different format.

Example: This text shows an smsMaster alarm about pending update queues.

```
Mar 30 13:34:54 prodsmpl smsMaster: [ID 953149 user.warning] smsMaster(17833)
WARNING: Pending queue now above 15 (Worst Node 317)
```

Alarm Text and Variables

The %d and %s symbols represent variables within the alarm text. These values are generated by the subsystem and added to the message when the alarm is raised.

Usually the %d is a number and the %s is text in the context of the message to complete the alarm message. Occasionally other % symbols are also used (for example, %u) for different variables.

Further Information

For more information about:

- The SMS Alarms subsystem, see *Service Management System Technical Guide*
- Creating and maintaining the SMS Alarm Relay rule set, see *Service Management System User's Guide*

Location Capabilities Pack Alarms

Alarm	Severity	Text	Cause	Resolution	Service
700000	ERROR	ZZZslee_acs(%d)ERROR:ZZZshm_open(3RT)%z	Run out of shared memory.	Contact Oracle Support.	ACS
700001	ERROR	ZZZslee_acs(%d)ERROR:ZZZmmap(2)%z	Shared memory internal error.	Contact Oracle Support.	ACS
700002	ERROR	ZZZslee_acs(%d)ERROR:ZZZtmpnam(3c)%z	Unknown	Contact Oracle Support.	ACS
700003	ERROR	ZZZslee_acs(%d)ERROR:ZZZopen(2)%z	Error on open.	Contact Oracle Support.	ACS
700004	ERROR	ZZZslee_acs(%d)ERROR:ZZZftruncate(3C)%z	Shared memory internal error.	Contact Oracle Support.	ACS
700005	ERROR	ZZZslee_acs(%d)ERROR:ZZZLocation cache fullZZZ	Location cache is full	Contact Oracle Support.	ACS
700006	WARNING	ZZZslee_acs(%d)WARNING:ZZZCached location more recentZZZ	Writing a location, but the old one is newer than the new one.	Contact Oracle Support. Check system time.	ACS
700007	ERROR	ZZZslee_acs(%d)ERROR:ZZZCache entry missingZZZ	Internal software error.	Contact Oracle Support.	ACS
700008	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZInitial isating all subsystems.%z	Startup info.	Information only.	ACS
700009	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZInitial isating location cache.%z	Startup info.	Information only.	ACS
700010	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLoading configuration.%z	Startup info.	Information only.	ACS
700011	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZOracle login set to %z	Startup info.	Information only.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700012	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZTimer interface name set to %z	Startup info.	Information only.	ACS
700013	WARNING	ZZZslee_acs(%d)WARNING:ZZZUnknown command line option %z	Startup options need checking.	Contact Oracle Support.	ACS
700014	WARNING	ZZZslee_acs(%d)WARNING:ZZZMissing argument for %z	Startup options need checking.	Contact Oracle Support.	ACS
700015	ERROR	ZZZslee_acs(%d)ERROR:ZZZgetopt error. Status: %z	Startup options need checking.	Contact Oracle Support.	ACS
700016	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZFailed to find timer interface. Name: %z	cannot get handle to the timer interface	Contact Oracle Support.	ACS
700017	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZStartup successful.%z	Startup info.	Information only.	ACS
700018	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::length_error %z	Uncaught std::length_error, anywhere in main loop.	Contact Oracle Support.	ACS
700019	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::domain_error %z	Uncaught std::domain_error, anywhere in main loop.	Contact Oracle Support.	ACS
700020	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::out_of_range %z	Uncaught std::out_of_range, anywhere in main loop.	Contact Oracle Support.	ACS
700021	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::invalid_argument %z	Uncaught std::invalid_argument, anywhere in main loop.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700022	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::logic_error %z	Uncaught std::logic_error, anywhere in main loop.	Contact Oracle Support.	ACS
700023	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::range_error %z	Uncaught std::range_error, anywhere in main loop.	Contact Oracle Support.	ACS
700024	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::overflow_error %z	Uncaught std::overflow_error, anywhere in main loop.	Contact Oracle Support.	ACS
700025	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::underflow_error %z	Uncaught std::underflow_error, anywhere in main loop.	Contact Oracle Support.	ACS
700026	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::runtime_error %z	Uncaught std::runtime_error, anywhere in main loop.	Contact Oracle Support.	ACS
700027	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::bad_alloc %z	Uncaught std::bad_alloc, anywhere in main loop.	Contact Oracle Support.	ACS
700028	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::bad_exception %z	Uncaught std::bad_exception, anywhere in main loop.	Contact Oracle Support.	ACS
700029	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::bad_cast %z	Uncaught std::bad_cast, anywhere in main loop.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700030	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::bad_typeid %z	Uncaught std::bad_typeid, anywhere in main loop.	Contact Oracle Support.	ACS
700031	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::ios_base::failure %z	Uncaught std::ios_base::failure, anywhere in main loop.	Contact Oracle Support.	ACS
700032	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUncaught std::exception %z	Uncaught std::exception, anywhere in main loop.	Contact Oracle Support.	ACS
700033	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZUnknown exception caught.%z	Uncaught exception.	Contact Oracle Support.	ACS
700034	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZAll subsystem stopped.%z	Shutdown information.	Information only.	ACS
700035	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZNon-SLEE event type with no dialog. Type: %z	Internal software error. No proper handle to the dialog.	Report to Oracle Support. Information only.	ACS
700036	ERROR	ZZZslee_acs(%d)ERROR:ZZZTpAddresses not of E164 type.%z	Malformed address.	Contact Oracle Support.	ACS
700037	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZReceived reply to unknown request.%z	Received a reply to a request we never sent.	Contact Oracle Support.	ACS
700038	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZService enabled: %z	Location Service enabled.	Information only.	ACS
700039	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZService disabled: %z	Location Service disabled.	Information only.	ACS
700040	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSLEE: APPLICATION_END.%z	Slee management event received. End Application.	Information only.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700041	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSLEE:APPLICATION_KILL.%z	Slee management event received. Kill Application.	Information only.	ACS
700042	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSLEE:Re-reading configuration - no effectZZZ	Slee management event received. Rereading configuration.	Information only.	ACS
700043	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSLEE:WatchDog event.%z	Slee management event received. Watchdog event received.	Information only.	ACS
700044	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSLEE:INTERFACE_END.%z	Slee management event received. End Interface.	Information only.	ACS
700045	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSLEE:INTERFACE_KILL.%z	Slee management event received. Kill Interface.	Information only.	ACS
700046	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSLEE:Unknown SLEE event type: %z	Slee management event received. Unknown slee event.	Information only. Refer to Oracle Support.	ACS
700047	ERROR	ZZZslee_acs(%d)ERROR:ZZZDialogue gets unknown event type: %z	Expecting a tcap event, but got something else.	Contact Oracle Support.	ACS
700048	WARNING	ZZZslee_acs(%d)WARNING:ZZZLocati on query timed out.%z	Location Interaction timedout	Contact Oracle Support.	ACS
700049	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZATI plugin: Using configuration file: %z	The ATI plugin is reading config	Information Only	ACS
700050	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZATI plugin: Unknown TCAP primitive type received.%z	got a result in a TCAP_BEGIN	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700051	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZATI plugin: Unknown TCAP component received.%z	got an unexpected TCAP component	Contact Oracle Support.	ACS
700052	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZATI plugin: Event from unknown dialog received.%z	got n event from an unknown dialog.	Contact Oracle Support.	ACS
700053	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZATI plugin: No Cell ID/LAI returned.%z	No Cell ID/LAI in ATI result	Information Only.	ACS
700054	ERROR	ZZZslee_acs(%d)ERROR:ZZZDialogue already exist for an location interaction.%z	Wont allow a second dialog in the map of interactions.	Contact Oracle Support. No further information can be obtained.	ACS
700055	ERROR	ZZZslee_acs(%d)ERROR:ZZZATI plugin: Invoke ID not found.%z	No invoke ID in TCAP_CONTINUE or TCAP_END	Contact Oracle Support.	ACS
700056	ERROR	ZZZslee_acs(%d)ERROR:ZZZATI plugin: unable to find TCAP interface: %z	No TCAP interface handle.	Contact Oracle Support. No further information can be obtained.	ACS
700057	ERROR	ZZZslee_acs(%d)ERROR:ZZZATI plugin config: gsmScfAddress not set.%z	Internal table missing entry.	Contact Oracle Support. No further information can be obtained.	ACS
700058	ERROR	ZZZslee_acs(%d)ERROR:ZZZATI plugin config: tcapIF not set.%z	Internal table missing entry.	Contact Oracle Support.	ACS
700059	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZATI plugin config: ABORT received.%z	Received a TCAP_ABORT.	Information Only	ACS
700060	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnrecognised event received.%z	Event unrecognised	Contact Oracle Support	ACS
700061	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnclosed dialog detected when all should be closed. Closing all.%z	Dialog unclosed	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700062	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnable to gettimeofday from SleeApplicationAPI. Error code is: %z	Internal software error with gettimeofday	Contact Oracle Support.	ACS
700063	ERROR	ZZZslee_acs(%d)ERROR:ZZZgettimeofday(3c)%z	Internal software error with gettimeofday.	Contact Oracle Support. No further information can be obtained.	ACS
700064	ERROR	ZZZslee_acs(%d)ERROR:ZZZInitialisation failed. Exiting.%z	Initialisation of locApp failed.	Contact Oracle Support.	ACS
700065	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZInitialising all plugins.%z	Internal software error in loadAllPlugin.	Contact Oracle Support.	ACS
700066	ERROR	ZZZslee_acs(%d)ERROR:ZZZdlopen(3DL) error %z	Error trying to open plugin.	Contact Oracle Support.	ACS
700067	ERROR	ZZZslee_acs(%d)ERROR:ZZZdlsym(3DL) error %z	Error loading function.	Contact Oracle Support.	ACS
700068	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZCache size set to %z	Size of the cache	Information Only	ACS
700069	WARNING	ZZZslee_acs(%d)WARNING:ZZZInvalid cache size %z	Bad Cache Size in command line parameters	Restart with different cache size parameter on command line.	ACS
700070	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZResponse deadline size set to %z	Size of Deadline.	Information Only	ACS
700071	WARNING	ZZZslee_acs(%d)WARNING:ZZZInvalid response deadline %z	Bad deadline in command line paramters.	Restart with different deadline parameter on command line.	ACS
700072	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZCache entry expiry time set to %z	Cache entry expiry time.	Information Only	ACS
700073	WARNING	ZZZslee_acs(%d)WARNING:ZZZInvalid cache entry expiry time %z	Bad Cache entry expiry time in command line paramters.	Restart with different cache entry expiry time parameter on command line.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700074	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZConnecting to Oracle database.%z	connecting to database.	Information Only.	ACS
700075	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnable to connect to oracle using login:%z	could not connect to database.	Check for oracle processes. Contact Oracle Support.	ACS
700076	ERROR	ZZZslee_acs(%d)ERROR:ZZZsemget(2) errorZZZ	Internal software error with semaphores.	Contact Oracle Support.	ACS
700077	ERROR	ZZZslee_acs(%d)ERROR:ZZZftok(3c) errorZZZ	Internal software error with semaphores.	Contact Oracle Support.	ACS
700078	ERROR	ZZZslee_acs(%d)ERROR:ZZZsemop(2) errorZZZ	Internal software error with semaphores.	Contact Oracle Support.	ACS
700079	WARNING	ZZZslee_acs(%d)WARNING:ZZZToo many plugins defined.%z	Too many location plugins are defined in the db.	Contact Oracle Support.	ACS
700080	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSetting up signal handlers.%z	Initialising signal handlers	Information only.	ACS
700081	ERROR	ZZZslee_acs(%d)ERROR:ZZZsignal(3C) error.%z	Error in Signal Handlers initialise.	Contact Oracle Support.	ACS
700082	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnknown MSISDN for the interaction.%z	Unknown MSISDN.	Contact Oracle Support.	ACS
700083	ERROR	ZZZslee_acs(%d)ERROR:ZZZNo plugin found for the MSISDN.%z	Cannot find a plugin to deal with this interaction for the MSISDN	Contact Oracle Support.	ACS
700084	ERROR	ZZZslee_acs(%d)ERROR:ZZZConversion data not found.%z	LCP conversion not found in database.	Contact Oracle Support.	ACS
700085	ERROR	ZZZslee_acs(%d)ERROR:ZZZOracle error.%z	Oracle error when accessing LCP database.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700086	ERROR	ZZZslee_acs(%d)ERROR:ZZZNo plugin configured.%z	No location plugins defined. Need at least 1.	Need a plugin defined. Contact Oracle Support.	ACS
700087	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnable to create dialog to TCAP interface.%z	Cant create a dialog to the TCAP interface	Contact Oracle Support.	ACS
700088	ERROR	ZZZslee_acs(%d)ERROR:ZZZInvalid statistics counter specified.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700089	ERROR	ZZZslee_acs(%d)ERROR:ZZZFailed to log stats. Statistics ID: %z	Failed to log statistics	Contact Oracle Support.	ACS
700090	ERROR	ZZZslee_acs(%d)ERROR:ZZZMAP2 error - system failure.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700091	ERROR	ZZZslee_acs(%d)ERROR:ZZZMAP2 error - data missing.%z	received MAP2_DATA_MISSING in TCAP_CONTINUE or TCAP_END.	Contact Oracle Support.	ACS
700092	ERROR	ZZZslee_acs(%d)ERROR:ZZZMAP2 error - unexpected data value.%z	received MAP2_UNEXPECTED_DATA_VALUE in TCAP_CONTINUE or TCAP_END.	Contact Oracle Support.	ACS
700093	ERROR	ZZZslee_acs(%d)ERROR:ZZZMAP2 error - ATI not allowed.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700094	ERROR	ZZZslee_acs(%d)ERROR:ZZZACS Macro node registration failed. Fast key: %z	Functional Node has failed ACS macro node registration.	Contact Oracle Support. No further information can be obtained.	ACS
700095	WARNING	ZZZslee_acs(%d)WARNING:ZZZACS Macro nodes failed to register with ACS.%z	some functional nodes have failed ACS macro node registration.	Information only.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700096	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLocation Action initialisation successful.%z	Location subsystem startup successful.	Information only.	ACS
700097	ERROR	ZZZslee_acs(%d)ERROR:ZZZLocation Action Registration failed.%z	Location Action Registration failed.	Contact Oracle Support.	ACS
700098	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLocation Action Registration successful.%z	Location handler registered successful.	Information only.	ACS
700099	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnable to obtain an instance of SLEE Application API.%z	SLEE Application API Instance not found.	Contact Oracle Support.	ACS
700100	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZOut of memory trying to create an instance of LocActionHandle.%z	Location Query Handler instance cannot be created.	Contact Oracle Support.	ACS
700101	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZOut of memory trying to create an instance of LocEventHandle.%z	Location Event Handler instance cannot be created.	Contact Oracle Support.	ACS
700102	ERROR	ZZZslee_acs(%d)ERROR:ZZZLocation Action Handler: No locApp service key set (locAppSK).%z	Internal software error with locAppSK table	Contact Oracle Support.	ACS
700103	ERROR	ZZZslee_acs(%d)ERROR:ZZZLocation Action Handler: Unable to create dialog to locApp.%z	Cant create a dialog to the locApp application.	Contact Oracle Support.	ACS
700104	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZOut of memory trying to create an instance of LocationReportRequest.%z	Out of memory creating a LocationReportRequest, so not much can be done. Call will abort.	Contact Oracle Support.	ACS
700105	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnable to register dialog with ACS Chassis.%z	Error informing ACS Chassis we want a response on the dialog.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700106	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZSLEE exception caught: %z	Internal software error - SLEE exception.	Contact Oracle Support.	ACS
700107	ERROR	ZZZslee_acs(%d)ERROR:ZZZLocation Action Event Handler: No outstanding action when event handler invoked.%z	Cannot find action in lookup in table	Contact Oracle Support.	ACS
700108	ERROR	ZZZslee_acs(%d)ERROR:ZZZLocation Action Event Handler: Incorrect event type received.%z	Mismatch in the event type	Contact Oracle Support.	ACS
700109	ERROR	ZZZslee_acs(%d)ERROR:ZZZLocation Event Handler: Dialog closed before response received.%z	Dialog closed before response received.	Contact Oracle Support.	ACS
700110	CRITICAL	ZZZslee_acs(%d)CRITICAL:ZZZputenv(3c) error: out of memory.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700111	ERROR	ZZZslee_acs(%d)ERROR:ZZZATI plugin: config section LCP.atiPlugin not found.%z	Missing configuration section.	Add an LCP.atiPlugin section to your configuration.	ACS
700112	ERROR	ZZZslee_acs(%d)ERROR:ZZZLCP Action Handler: config section LCP.actionHandler not found: %z	Missing configuration section.	Add an LCP.actionHandler section to your configuration.	ACS
700113	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP Action Handler: Using configuration file: %z	Using this configuration file.	Information Only	ACS
700114	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP Macro Nodes: Using configuration file: %z	Using this configuration file.	Information Only	ACS
700115	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP current location processor: Config section LCP.currentLocation not found.%z	Missing configuration section.	Add an LCP.currentLocation section to your configuration.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700116	ERROR	ZZZslee_acs(%d)ERROR:ZZZLCP current location processor: option Map_Uncertainty_constant_C not set.%z	Internal software error.	Contact Oracle Support.	ACS
700117	ERROR	ZZZslee_acs(%d)ERROR:ZZZLCP current location processor: option Map_Uncertainty_constant_x not set.%z	Internal software error.	Contact Oracle Support.	ACS
700118	ERROR	ZZZslee_acs(%d)ERROR:ZZZIn The Zone: No node parameter set.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS
700119	ERROR	ZZZslee_acs(%d)ERROR:ZZZIn The Zone: Parameter parsing error.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS
700120	ERROR	ZZZslee_acs(%d)ERROR:ZZZSet My Zone: No node parameter set.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS
700121	ERROR	ZZZslee_acs(%d)ERROR:ZZZSet My Zone: Parameter parsing error.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS
700122	ERROR	ZZZslee_acs(%d)ERROR:ZZZIncorrec t action type received.%z	Action types mismatch.	Contact Oracle Support.	ACS
700123	ERROR	ZZZslee_acs(%d)ERROR:ZZZBad or missing mode.%z	Conversion Loader invoked with a bad mode.	Reinvoke changing the parameters.	ACS
700124	ERROR	ZZZslee_acs(%d)ERROR:ZZZNo input files specified.%z	Conversion Loader invoked without input files.	Find input files and reinvoke.	ACS
700125	ERROR	ZZZslee_acs(%d)ERROR:ZZZCell input file could not be opened.%z	Conversion Loader invoked with bad cell file.	Find input files and reinvoke.	ACS
700126	ERROR	ZZZslee_acs(%d)ERROR:ZZZArea input file could not be opened.%z	Conversion Loader invoked without area files.	Find input files and reinvoke.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700127	ERROR	ZZZslee_acs(%d)ERROR:ZZZOutput file could not be opened.%z	Conversion Loader cannot create output files.	check output file permissions and path	ACS
700128	ERROR	ZZZslee_acs(%d)ERROR:ZZZID not found.%z	Conversion Loader - bad format in input files	Fix input files and reinvoke.	ACS
700129	ERROR	ZZZslee_acs(%d)ERROR:ZZZBad format.%z	Conversion Loader - bad format in input files	Fix input files and reinvoke.	ACS
700130	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP current location processor: Using configuration file: %z	Info on configuration file	Information only	ACS
700131	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZInitialising current location processor.%z	Initialising location processor.	Information only.	ACS
700132	WARNING	ZZZslee_acs(%d)WARNING:ZZZUnable to process the current location.%z	Current location cannot be processed.	Contact Oracle Support.	ACS
700133	ERROR	ZZZslee_acs(%d)ERROR:ZZZfopen(3c)%z	Cant open internal cache	Contact Oracle Support.	ACS
700134	ERROR	ZZZslee_acs(%d)ERROR:ZZZIncorrect number of results returned from locApp.%z	Macro node expects only 1 location result.	Contact Oracle Support.	ACS
700135	ERROR	ZZZslee_acs(%d)ERROR:ZZZSystem Failure.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700136	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnauthorised network.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700137	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnauthorised application.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700138	ERROR	ZZZslee_acs(%d)ERROR:ZZZUnknown Subscriber.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700139	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZAbsent Subscriber.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700140	ERROR	ZZZslee_acs(%d)ERROR:ZZZPosition method failure.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700141	ERROR	ZZZslee_acs(%d)ERROR:ZZZNon-originating/terminating end detected.%z	Non-originating/terminating end detected.	Contact Oracle Support.	ACS
700142	ERROR	ZZZslee_acs(%d)ERROR:ZZZOut of bound status detected.%z	Out of bound (unknown) status detected.	Contact Oracle Support.	ACS
700143	WARNING	ZZZslee_acs(%d)WARNING:ZZZBad shape definition in profile encountered.%z	Bad shape definition amongst definitions.	Change erroneous shape definition.	ACS
700144	ERROR	ZZZslee_acs(%d)ERROR:ZZZSet My Zone node: Unable to add zone shape.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700145	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP nodes: Using configuration file: %z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700146	ERROR	ZZZslee_acs(%d)ERROR:ZZZBad parameter string specified .%z	Bad type conversion. Internal Software error.	Contact Oracle Support.	ACS
700147	ERROR	ZZZslee_acs(%d)ERROR:ZZZLCP Set My Zone: Profile update error.%z	Could not update profile.	Contact Oracle Support.	ACS
700148	ERROR	ZZZslee_acs(%d)ERROR:ZZZNon-existent plugin specified.%z	cannot find a plugin with overridden id.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700149	ERROR	ZZZslee_acs(%d)ERROR:ZZZLCP nodes: Geographical Position information not available.%z	Expected a Geographical Position but did not get one.	Contact Oracle Support. No further information can be obtained.	ACS
700150	ERROR	ZZZslee_acs(%d)ERROR:ZZZStore My Location: Geographical Position not currently supported.%z	Could not store geographical location.	Contact Oracle Support. No further information can be obtained.	ACS
700151	ERROR	ZZZslee_acs(%d)ERROR:ZZZStore My Location: Serving Cell information not available.%z	Do not have a cell ID	Contact Oracle Support.	ACS
700152	ERROR	ZZZslee_acs(%d)ERROR:ZZZStore My Location: Invalid buffer number selected.%z	Chosen context field is invalid.	Contact Oracle Support. No further information can be obtained.	ACS
700153	ERROR	ZZZslee_acs(%d)ERROR:ZZZStore My Location: No node parameter set.%z	We must have a parameter in the node parameter string.	Contact Oracle Support.	ACS
700154	ERROR	ZZZslee_acs(%d)ERROR:ZZZStore My Location: Parameter parsing error.%z	We must have a parameter in the node parameter string.	Contact Oracle Support.	ACS
700155	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZPOSREQ plugin: Using configuration file: %z	Using this configuration file for POSREQ plugin.	Information only.	ACS
700156	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin: config section LCP.posreqPlugin not found.%z	POSREQ configuration lacks a LCP.posreqPlugin section.	Edit configuration options.	ACS
700157	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin config: scfPC SCF PC address not set.%z	POSREQ configuration lacks a scfPC value.	Edit configuration options.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700158	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin config: scfSSN SCF SSN address not set.%z	POSREQ configuration lacks a scfSSN value.	Edit configuration options.	ACS
700159	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin config: hlrSSN HLR SSN address not set.%z	POSREQ configuration lacks a hlrSSN value.	Edit configuration options.	ACS
700160	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin config: tcapIF not set.%z	POSREQ configuration lacks a tcapIF value.	Edit configuration options.	ACS
700161	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZPOSREQ plugin config: forwardToMsc not set, using default: %z	POSREQ configuration lacks a forwardToMsc value.	Edit configuration options.	ACS
700162	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin: unable to find TCAP interface: %z	Cannot find the TCAP interface handle.	Contact Oracle Support.	ACS
700163	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin: Unable to create dialog to TCAP interface.%z	Unable to create dialog to TCAP interface.	Contact Oracle Support.	ACS
700164	WARNING	ZZZslee_acs(%d)WARNING:ZZZPOSREQ plugin: No MSStatus or Cell ID returned.%z	Failed response from MSC. Dont have Status or CellID.	Contact Oracle Support.	ACS
700165	WARNING	ZZZslee_acs(%d)WARNING:ZZZPOSREQ plugin: No MSC Routing Address (PC_SSN) returned from HLR.%z	Failed to receive MSC Routing Address.	Contact Oracle Support.	ACS
700166	WARNING	ZZZslee_acs(%d)WARNING:ZZZPOSREQ plugin: Unknown TCAP component type received: %z	Unknown Tcap Component Type.	Contact Oracle Support.	ACS
700167	WARNING	ZZZslee_acs(%d)WARNING:ZZZPOSREQ plugin: Unknown Invoke ID received.%z	unexpected invokeID, when we only sent POSREQ.	Contact Oracle Support.	ACS
700168	WARNING	ZZZslee_acs(%d)WARNING:ZZZPOSREQ plugin: TCAP ABORT received.%z	Received unexpected TCAP_ABORT.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700169	WARNING	ZZZslee_acs(%d)WARNING:ZZZPOSREQ plugin: Event from unknown dialog received.%z	Unknown event recieved on dialog.	Contact Oracle Support.	ACS
700170	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZPOSREQ plugin: Unknown TCAP primitive type received.%z	Received Unknown Tcap Primitive.	Contact Oracle Support.	ACS
700171	WARNING	ZZZslee_acs(%d)WARNING:ZZZInvalid handle retrieved for Slee Dialog.%z	Invalid null handle retrieved for Slee Dialog.	Contact Oracle Support.	ACS
700172	ERROR	ZZZslee_acs(%d)ERROR:ZZZIS41 Error - Missing ParameterZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS
700173	ERROR	ZZZslee_acs(%d)ERROR:ZZZIS41 Error - Feature InactiveZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS
700174	ERROR	ZZZslee_acs(%d)ERROR:ZZZIS41 Error - Parameter ErrorZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS
700175	ERROR	ZZZslee_acs(%d)ERROR:ZZZIS41 Error - Operation Sequence ProblemZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS
700176	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP current location processor: Config LocationNumberLength not set, using default: %z	LocationNumberLength not set in config.	Information Only or set in config	ACS
700177	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP current location processor: LocationNumber length does not match configured length, cannot use current location.%z	LocationNumber length does not match configured length.	Information only.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700178	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLCP action handler: Config normalisedNumbers not set, using default: trueZZZ	normalisedNumbers not set in config.	Information Only or set in config	ACS
700179	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin config: mscMktId MSC Market-ID not set.%z	mscMktId not set in config.	Set mscMktId value in configuration file	ACS
700180	ERROR	ZZZslee_acs(%d)ERROR:ZZZPOSREQ plugin config: mscSwId MSC Switch-ID not set.%z	mscSwId not set in config.	Set mscSwId value in configuration file	ACS
700181	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZSRI plugin: Using configuration file: %z	SRI plugin using this configuration file.	Information only.	ACS
700182	ERROR	ZZZslee_acs(%d)ERROR:ZZZSRI plugin: config section LCP.sriPlugin not found.%z	LCP.sriPlugin value not found in SRI plugin configuration file	Set LCP.sriPlugin value in configuration file	ACS
700183	ERROR	ZZZslee_acs(%d)ERROR:ZZZSRI plugin config: tcapIF not set.%z	tcapIF value not found in SRI plugin configuration file	Set tcapIF value in configuration file	ACS
700184	ERROR	ZZZslee_acs(%d)ERROR:ZZZSRI plugin config: gmscAddress not set.%z	gmscAddress value not found in SRI plugin configuration file	Set gmscAddress value in configuration file	ACS
700185	ERROR	ZZZslee_acs(%d)ERROR:ZZZSRI plugin: unable to find TCAP interface: %z	Cannot find TCAP interface handle	Contact Oracle Support.	ACS
700186	ERROR	ZZZslee_acs(%d)ERROR:ZZZSRI plugin: Unable to create dialog to TCAP interface.%z	Cannot create a dialog to the TCAP interface.	Contact Oracle Support.	ACS
700187	WARNING	ZZZslee_acs(%d)WARNING:ZZZSRI plugin: TCAP ABORT received.%z	Received an unexpected TCAP_ABORT.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700188	WARNING	ZZZslee_acs(%d)WARNING:ZZZSRI plugin: Unknown Invoke ID received.%z	Received TCAP response with Unknown Invoke ID.	Contact Oracle Support.	ACS
700190	WARNING	ZZZslee_acs(%d)WARNING:ZZZSRI plugin: Unknown TCAP primitive type received.%z	Received Unknown Tcap Primitive.	Contact Oracle Support.	ACS
700191	WARNING	ZZZslee_acs(%d)WARNING:ZZZSRI plugin: Unknown TCAP component type received.%z	Received Unknown Tcap Component Type.	Contact Oracle Support.	ACS
700192	WARNING	ZZZslee_acs(%d)WARNING:ZZZSRI plugin: Event from unknown dialog received.%z	Received an event from unknown dialog received.	Contact Oracle Support.	ACS
700193	WARNING	ZZZslee_acs(%d)WARNING:ZZZSRI plugin: No MSRN returned.%z	Cannot find the roaming num.	Contact Oracle Support.	ACS
700194	WARNING	ZZZslee_acs(%d)WARNING:ZZZLCP Action: HLR IDP Conversion not required.%z	Optional configuration not found	No action required, unless HLR IDP Conversion is needed.	ACS
700195	ERROR	ZZZslee_acs(%d)ERROR:ZZZLCP Action: Failed to load MSISDN Query Source Profile.%z	Failed to load profile	Contact Oracle Support.	ACS
700196	ERROR	ZZZslee_acs(%d)ERROR:ZZZLCP Action: MSISDN Query digits invalid.%z	Supplied digits for query were invalid	Check control plan.	ACS
700197	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZTrack latency set to %z	Not an error	No action required.	ACS
700198	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZPerformance reporting frequency set to %z	Not an error	No action required.	ACS
700199	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZFlush period (in second) set to %z	Not an error	No action required.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700200	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZFinal location of generated EDR files set to %z	Not an error	No action required.	ACS
700201	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZTemporary location of generated EDR files set to %z	Not an error	No action required.	ACS
700202	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZMaximum number of EDR records per file set to %z	Not an error	No action required.	ACS
700203	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZThe prefix of EDR files set to %z	Not an error	No action required.	ACS
700204	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZInvalid TCAP error number received.%z	HLR error.	Look at the logs on the HLR to see why this happened.	ACS
700205	WARNING	ZZZslee_acs(%d)WARNING:ZZZLocation Action Event Handler: Unable to reset bound dialog.%z	Cannot find dialog in the event bindings.	Contact Oracle Support.	ACS
700206	NOTICE	ZZZslee_acs(%d)NOTICE:ZZZLog EDR set to %z	Not an error	No action required.	ACS
700300	ERROR	ZZZlocApp(%d)ERROR:ZZZshm_open(3RT)%z	Run out of shared memory.	Contact Oracle Support.	ACS
700301	ERROR	ZZZlocApp(%d)ERROR:ZZZmmap(2)%z	Shared memory internal error.	Contact Oracle Support.	ACS
700302	ERROR	ZZZlocApp(%d)ERROR:ZZZtmpnam(3c)%z	Unknown	Contact Oracle Support.	ACS
700303	ERROR	ZZZlocApp(%d)ERROR:ZZZOpen(2)%z	Error on open.	Contact Oracle Support.	ACS
700304	ERROR	ZZZlocApp(%d)ERROR:ZZZftruncate(3C)%z	Shared memory internal error.	Contact Oracle Support.	ACS
700305	ERROR	ZZZlocApp(%d)ERROR:ZZZLocation cache fullZZZ	Location cache is full	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700306	WARNING	ZZZlocApp(%d)WARNING:ZZZCached location more recentZZZ	Writing a location, but the old one is newer than the new one.	Contact Oracle Support. Check system time.	ACS
700307	ERROR	ZZZlocApp(%d)ERROR:ZZZCache entry missingZZZ	Internal software error.	Contact Oracle Support.	ACS
700308	NOTICE	ZZZlocApp(%d)NOTICE:ZZZInitialisating all subsystems.%z	Startup info.	Information only.	ACS
700309	NOTICE	ZZZlocApp(%d)NOTICE:ZZZInitialisating location cache.%z	Startup info.	Information only.	ACS
700310	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLoading configuration.%z	Startup info.	Information only.	ACS
700311	NOTICE	ZZZlocApp(%d)NOTICE:ZZZOracle login set to %z	Startup info.	Information only.	ACS
700312	NOTICE	ZZZlocApp(%d)NOTICE:ZZZTimer interface name set to %z	Startup info.	Information only.	ACS
700313	WARNING	ZZZlocApp(%d)WARNING:ZZZUnknown command line option %z	Startup options need checking.	Contact Oracle Support.	ACS
700314	WARNING	ZZZlocApp(%d)WARNING:ZZZMissing argument for %z	Startup options need checking.	Contact Oracle Support.	ACS
700315	ERROR	ZZZlocApp(%d)ERROR:ZZZgetopt error. Status: %z	Startup options need checking.	Contact Oracle Support.	ACS
700316	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZFailed to find timer interface. Name: %z	cannot get handle to the timer interface	Contact Oracle Support.	ACS
700317	NOTICE	ZZZlocApp(%d)NOTICE:ZZZStartup successful.%z	Startup info.	Information only.	ACS
700318	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZUncaught std::length_error %z	Uncaught std::length_error, anywhere in main loop.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700319	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::domain_error %z	Uncaught std::domain_error, anywhere in main loop.	Contact Oracle Support.	ACS
700320	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::out_of_range %z	Uncaught std::out_of_range, anywhere in main loop.	Contact Oracle Support.	ACS
700321	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::invalid_argument %z	Uncaught std::invalid_argument, anywhere in main loop.	Contact Oracle Support.	ACS
700322	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::logic_error %z	Uncaught std::logic_error, anywhere in main loop.	Contact Oracle Support.	ACS
700323	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::range_error %z	Uncaught std::range_error, anywhere in main loop.	Contact Oracle Support.	ACS
700324	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::overflow_error %z	Uncaught std::overflow_error, anywhere in main loop.	Contact Oracle Support.	ACS
700325	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::underflow_error %z	Uncaught std::underflow_error, anywhere in main loop.	Contact Oracle Support.	ACS
700326	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::runtime_error %z	Uncaught std::runtime_error, anywhere in main loop.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700327	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::bad_alloc %z	Uncaught std::bad_alloc, anywhere in main loop.	Contact Oracle Support.	ACS
700328	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::bad_exception %z	Uncaught std::bad_exception, anywhere in main loop.	Contact Oracle Support.	ACS
700329	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::bad_cast %z	Uncaught std::bad_cast, anywhere in main loop.	Contact Oracle Support.	ACS
700330	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::bad_typeid %z	Uncaught std::bad_typeid, anywhere in main loop.	Contact Oracle Support.	ACS
700331	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::ios_base::failure %z	Uncaught std::ios_base::failure, anywhere in main loop.	Contact Oracle Support.	ACS
700332	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUncaught std::exception %z	Uncaught std::exception, anywhere in main loop.	Contact Oracle Support.	ACS
700333	CRITICAL	ZZZlocApp(%d) CRITICAL:ZZZUnknown exception caught.%z	Uncaught exception.	Contact Oracle Support.	ACS
700334	NOTICE	ZZZlocApp(%d) NOTICE:ZZZAll subsystem stopped.%z	Shutdown information.	Information only.	ACS
700335	NOTICE	ZZZlocApp(%d) NOTICE:ZZZNon-SLEEP event type with no dialog. Type: %z	Internal software error. No proper handle to the dialog.	Report to Oracle Support. Information only.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700336	ERROR	ZZZlocApp(%d)ERROR:ZZZTpAddress not of E164 type.%z	Malformed address.	Contact Oracle Support.	ACS
700337	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZReceived reply to unknown request.%z	Received a reply to a request we never sent.	Contact Oracle Support.	ACS
700338	NOTICE	ZZZlocApp(%d)NOTICE:ZZZService enabled: %z	Location Service enabled.	Information only.	ACS
700339	NOTICE	ZZZlocApp(%d)NOTICE:ZZZService disabled: %z	Location Service disabled.	Information only.	ACS
700340	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSLEE: APPLICATION_END.%z	Slee management event received. End Application.	Information only.	ACS
700341	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSLEE: APPLICATION_KILL.%z	Slee management event received. Kill Application.	Information only.	ACS
700342	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSLEE: Rereading configuration - no effectZZZ	Slee management event received. Rereading configuration.	Information only.	ACS
700343	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSLEE: WatchDog event.%z	Slee management event received. Watchdog event received.	Information only.	ACS
700344	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSLEE: INTERFACE_END.%z	Slee management event received. End Interface.	Information only.	ACS
700345	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSLEE: INTERFACE_KILL.%z	Slee management event received. Kill Interface.	Information only.	ACS
700346	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSLEE: Unknown SLEE event type: %z	Slee management event received. Unknown slee event.	Information only. Refer to Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700347	ERROR	ZZZlocApp(%d)ERROR:ZZZDialogue gets unknown event type: %z	Expecting a tcap event, but got something else.	Contact Oracle Support.	ACS
700348	WARNING	ZZZlocApp(%d)WARNING:ZZZLocation query timed out.%z	Location Interaction timeout	Contact Oracle Support.	ACS
700349	NOTICE	ZZZlocApp(%d)NOTICE:ZZZATI plugin: Using configuration file: %z	The ATI plugin is reading config	Information Only	ACS
700350	NOTICE	ZZZlocApp(%d)NOTICE:ZZZATI plugin: Unknown TCAP primitive type received.%z	got a result in a TCAP_BEGIN	Contact Oracle Support.	ACS
700351	NOTICE	ZZZlocApp(%d)NOTICE:ZZZATI plugin: Unknown TCAP component received.%z	got an unexpected TCAP component	Contact Oracle Support.	ACS
700352	NOTICE	ZZZlocApp(%d)NOTICE:ZZZATI plugin: Event from unknown dialog received.%z	got n event from an unknown dialog.	Contact Oracle Support.	ACS
700353	NOTICE	ZZZlocApp(%d)NOTICE:ZZZATI plugin: No Cell ID/LAI returned.%z	No Cell ID/LAI in ATI result	Information Only.	ACS
700354	ERROR	ZZZlocApp(%d)ERROR:ZZZDialogue already exist for an location interaction.%z	Wont allow a second dialog in the map of interactions.	Contact Oracle Support. No further information can be obtained.	ACS
700355	ERROR	ZZZlocApp(%d)ERROR:ZZZATI plugin: Invoke ID not found.%z	No invoke ID in TCAP_CONTINUE or TCAP_END	Contact Oracle Support.	ACS
700356	ERROR	ZZZlocApp(%d)ERROR:ZZZATI plugin: unable to find TCAP interface: %z	No TCAP interface handle.	Contact Oracle Support. No further information can be obtained.	ACS
700357	ERROR	ZZZlocApp(%d)ERROR:ZZZATI plugin config: gsmScfAddress not set.%z	Internal table missing entry.	Contact Oracle Support. No further information can be obtained.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700358	ERROR	ZZZlocApp(%d)ERROR:ZZZATI plugin config: tcapIF not set.%z	Internal table missing entry.	Contact Oracle Support.	ACS
700359	NOTICE	ZZZlocApp(%d)NOTICE:ZZZATI plugin config: ABORT received.%z	Received a TCAP_ABORT.	Information Only	ACS
700360	ERROR	ZZZlocApp(%d)ERROR:ZZZUnrecognised event received.%z	Event unrecognised	Contact Oracle Support	ACS
700361	ERROR	ZZZlocApp(%d)ERROR:ZZZUnclosed dialog detected when all should be closed. Closing all.%z	Dialog unclosed	Contact Oracle Support.	ACS
700362	ERROR	ZZZlocApp(%d)ERROR:ZZZUnable to gettimeofday from SleeApplicationAPI. Error code is: %z	Internal software error with gettimeofday	Contact Oracle Support.	ACS
700363	ERROR	ZZZlocApp(%d)ERROR:ZZZgettimeofday(3c)%z	Internal software error with gettimeofday.	Contact Oracle Support. No further information can be obtained.	ACS
700364	ERROR	ZZZlocApp(%d)ERROR:ZZZInitialisation failed. Exiting.%z	Initialisation of locApp failed.	Contact Oracle Support.	ACS
700365	NOTICE	ZZZlocApp(%d)NOTICE:ZZZInitialising all plugins.%z	Internal software error in loadAllPlugin.	Contact Oracle Support.	ACS
700366	ERROR	ZZZlocApp(%d)ERROR:ZZZdlopen(3DL) error %z	Error trying to open plugin.	Contact Oracle Support.	ACS
700367	ERROR	ZZZlocApp(%d)ERROR:ZZZdlsym(3DL) error %z	Error loading function.	Contact Oracle Support.	ACS
700368	NOTICE	ZZZlocApp(%d)NOTICE:ZZZCache size set to %z	Size of the cache	Information Only	ACS
700369	WARNING	ZZZlocApp(%d)WARNING:ZZZInvalid cache size %z	Bad Cache Size in command line parameters	Restart with different cache size parameter on command line.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700370	NOTICE	ZZZlocApp(%d)NOTICE:ZZZResponse deadline size set to %z	Size of Deadline.	Information Only	ACS
700371	WARNING	ZZZlocApp(%d)WARNING:ZZZInvalid response deadline %z	Bad deadline in command line paramters.	Restart with different deadline parameter on command line.	ACS
700372	NOTICE	ZZZlocApp(%d)NOTICE:ZZZCache entry expiry time set to %z	Cache entry expiry time.	Information Only	ACS
700373	WARNING	ZZZlocApp(%d)WARNING:ZZZInvalid cache entry expiry time %z	Bad Cache entry expiry time in command line paramters.	Restart with different cache entry expiry time parameter on command line.	ACS
700374	NOTICE	ZZZlocApp(%d)NOTICE:ZZZConnecting to Oracle database.%z	connecting to database.	Information Only.	ACS
700375	ERROR	ZZZlocApp(%d)ERROR:ZZZUnable to connect to oracle using login:%z	could not connect to database.	Check for oracle processes. Contact Oracle Support.	ACS
700376	ERROR	ZZZlocApp(%d)ERROR:ZZZsemget(2) errorZZZ	Internal software error with semaphores.	Contact Oracle Support.	ACS
700377	ERROR	ZZZlocApp(%d)ERROR:ZZZftok(3c) errorZZZ	Internal software error with semaphores.	Contact Oracle Support.	ACS
700378	ERROR	ZZZlocApp(%d)ERROR:ZZZsemop(2) errorZZZ	Internal software error with semaphores.	Contact Oracle Support.	ACS
700379	WARNING	ZZZlocApp(%d)WARNING:ZZZToo many plugins defined.%z	Too many location plugins are defined in the db.	Contact Oracle Support.	ACS
700380	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSetting up signal handlers.%z	Initialising signal handlers	Information only.	ACS
700381	ERROR	ZZZlocApp(%d)ERROR:ZZZsignal(3C) error.%z	Error in Signal Handlers initialise.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700382	ERROR	ZZZlocApp(%d)ERROR:ZZZUnknown MSISDN for the interaction.%z	Unknown MSISDN.	Contact Oracle Support.	ACS
700383	ERROR	ZZZlocApp(%d)ERROR:ZZZNo plugin found for the MSISDN.%z	Cannot find a plugin to deal with this interaction for the MSISDN	Contact Oracle Support.	ACS
700384	ERROR	ZZZlocApp(%d)ERROR:ZZZConversion data not found.%z	LCP conversion not found in database.	Contact Oracle Support.	ACS
700385	ERROR	ZZZlocApp(%d)ERROR:ZZZOracle error.%z	Oracle error when accessing LCP database.	Contact Oracle Support.	ACS
700386	ERROR	ZZZlocApp(%d)ERROR:ZZZNo plugin configured.%z	No location plugins defined. Need at least 1.	Need a plugin defined. Contact Oracle Support.	ACS
700387	ERROR	ZZZlocApp(%d)ERROR:ZZZUnable to create dialog to TCAP interface.%z	Cant create a dialog to the TCAP interface	Contact Oracle Support.	ACS
700388	ERROR	ZZZlocApp(%d)ERROR:ZZZInvalid statistics counter specified.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700389	ERROR	ZZZlocApp(%d)ERROR:ZZZFailed to log stats. Statistics ID: %z	Failed to log statistics	Contact Oracle Support.	ACS
700390	ERROR	ZZZlocApp(%d)ERROR:ZZZMAP2 error - system failure.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700391	ERROR	ZZZlocApp(%d)ERROR:ZZZMAP2 error - data missing.%z	received MAP2_DATA_MISSING in TCAP_CONTINUE or TCAP_END.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700392	ERROR	ZZZlocApp(%d)ERROR:ZZZMAP2 error - unexpected data value.%z	received MAP2_UNEXPECTED_DATA_VALUE in TCAP_CONTINUE or TCAP_END.	Contact Oracle Support.	ACS
700393	ERROR	ZZZlocApp(%d)ERROR:ZZZMAP2 error - ATI not allowed.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700394	ERROR	ZZZlocApp(%d)ERROR:ZZZACS Macro node registration failed. Fast key: %z	Functional Node has failed ACS macro node registration.	Contact Oracle Support. No further information can be obtained.	ACS
700395	WARNING	ZZZlocApp(%d)WARNING:ZZZACS Macro nodes failed to register with ACS.%z	some functional nodes have failed ACS macro node registration.	Information only.	ACS
700396	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLocation Action initialisation successful.%z	Location subsystem startup successful.	Information only.	ACS
700397	ERROR	ZZZlocApp(%d)ERROR:ZZZLocation Action Registration failed.%z	Location Action Registration failed.	Contact Oracle Support.	ACS
700398	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLocation Action Registration successful.%z	Location handler registered successful.	Information only.	ACS
700399	ERROR	ZZZlocApp(%d)ERROR:ZZZUnable to obtain an instance of SLEE Application API.%z	SLEE Application API Instance not found.	Contact Oracle Support.	ACS
700400	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZOut of memory trying to create an instance of LocActionHandle.%z	Location Query Handler instance cannot be created.	Contact Oracle Support.	ACS
700401	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZOut of memory trying to create an instance of LocEventHandle.%z	Location Event Handler instance cannot be created.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700402	ERROR	ZZZlocApp(%d)ERROR:ZZZLocation Action Handler: No locApp service key set (locAppSK).%z	Internal software error with locAppSK table	Contact Oracle Support.	ACS
700403	ERROR	ZZZlocApp(%d)ERROR:ZZZLocation Action Handler: Unable to create dialog to locApp.%z	Cant create a dialog to the locApp application.	Contact Oracle Support.	ACS
700404	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZOut of memory trying to create an instance of LocationReportRequest.%z	Out of memory creating a LocationReportRequest, so not much can be done. Call will abort.	Contact Oracle Support.	ACS
700405	ERROR	ZZZlocApp(%d)ERROR:ZZZUnable to register dialog with ACS Chassis.%z	Error informing ACS Chassis we want a response on the dialog.	Contact Oracle Support.	ACS
700406	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZSLEE exception caught: %z	Internal software error - SLEE exception.	Contact Oracle Support.	ACS
700407	ERROR	ZZZlocApp(%d)ERROR:ZZZLocation Action Event Handler: No outstanding action when event handler invoked.%z	Cannot find action in lookup in table	Contact Oracle Support.	ACS
700408	ERROR	ZZZlocApp(%d)ERROR:ZZZLocation Action Event Handler: Incorrect event type received.%z	Mismatch in the event type	Contact Oracle Support.	ACS
700409	ERROR	ZZZlocApp(%d)ERROR:ZZZLocation Event Handler: Dialog closed before response received.%z	Dialog closed before response received.	Contact Oracle Support.	ACS
700410	CRITICAL	ZZZlocApp(%d)CRITICAL:ZZZputenv(3c) error: out of memory.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700411	ERROR	ZZZlocApp(%d)ERROR:ZZZATI plugin: config section LCP.atiPlugin not found.%z	Missing configuration section.	Add an LCP.atiPlugin section to your configuration.	ACS
700412	ERROR	ZZZlocApp(%d)ERROR:ZZZLCP Action Handler: config section LCP.actionHandler not found: %z	Missing configuration section.	Add an LCP.actionHandler section to your configuration.	ACS
700413	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP Action Handler: Using configuration file: %z	Using this configuration file.	Information Only	ACS
700414	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP Macro Nodes: Using configuration file: %z	Using this configuration file.	Information Only	ACS
700415	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP current location processor: Config section LCP.currentLocation not found.%z	Missing configuration section.	Add an LCP.currentLocation section to your configuration.	ACS
700416	ERROR	ZZZlocApp(%d)ERROR:ZZZLCP current location processor: option Map_Uncertainty_constant_C not set.%z	Internal software error.	Contact Oracle Support.	ACS
700417	ERROR	ZZZlocApp(%d)ERROR:ZZZLCP current location processor: option Map_Uncertainty_constant_x not set.%z	Internal software error.	Contact Oracle Support.	ACS
700418	ERROR	ZZZlocApp(%d)ERROR:ZZZIn The Zone: No node parameter set.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS
700419	ERROR	ZZZlocApp(%d)ERROR:ZZZIn The Zone: Parameter parsing error.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS
700420	ERROR	ZZZlocApp(%d)ERROR:ZZZSet My Zone: No node parameter set.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700421	ERROR	ZZZlocApp(%d)ERROR:ZZZSet My Zone: Parameter parsing error.%z	Error parsing node parameter string.	Contact Oracle Support.	ACS
700422	ERROR	ZZZlocApp(%d)ERROR:ZZZIncorrect action type received.%z	Action types mismatch.	Contact Oracle Support.	ACS
700423	ERROR	ZZZlocApp(%d)ERROR:ZZZBad or missing mode.%z	Conversion Loader invoked with a bad mode.	Reinvoke changing the parameters.	ACS
700424	ERROR	ZZZlocApp(%d)ERROR:ZZZNo input files specified.%z	Conversion Loader invoked without input files.	Find input files and reinvoke.	ACS
700425	ERROR	ZZZlocApp(%d)ERROR:ZZZCell input file could not be opened.%z	Conversion Loader invoked with bad cell file.	Find input files and reinvoke.	ACS
700426	ERROR	ZZZlocApp(%d)ERROR:ZZZArea input file could not be opened.%z	Conversion Loader invoked without area files.	Find input files and reinvoke.	ACS
700427	ERROR	ZZZlocApp(%d)ERROR:ZZZOutput file could not be opened.%z	Conversion Loader cannot create output files.	check output file permissions and path	ACS
700428	ERROR	ZZZlocApp(%d)ERROR:ZZZID not found.%z	Conversion Loader - bad format in input files	Fix input files and reinvoke.	ACS
700429	ERROR	ZZZlocApp(%d)ERROR:ZZZBad format.%z	Conversion Loader - bad format in input files	Fix input files and reinvoke.	ACS
700430	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP current location processor: Using configuration file: %z	Info on configuration file	Information only	ACS
700431	NOTICE	ZZZlocApp(%d)NOTICE:ZZZInitialising current location processor.%z	Initialising location processor.	Information only.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700432	WARNING	ZZZlocApp(%d)WARNING:ZZZUnable to process the current location.%z	Current location cannot be processed.	Contact Oracle Support.	ACS
700433	ERROR	ZZZlocApp(%d)ERROR:ZZZfopen(3c)%z	Cant open internal cache	Contact Oracle Support.	ACS
700434	ERROR	ZZZlocApp(%d)ERROR:ZZZIncorrect number of results returned from locApp.%z	Macro node expects only 1 location result.	Contact Oracle Support.	ACS
700435	ERROR	ZZZlocApp(%d)ERROR:ZZZSystem Failure.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700436	ERROR	ZZZlocApp(%d)ERROR:ZZZUnauthorised network.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700437	ERROR	ZZZlocApp(%d)ERROR:ZZZUnauthorised application.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700438	ERROR	ZZZlocApp(%d)ERROR:ZZZUnknown Subscriber.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700439	NOTICE	ZZZlocApp(%d)NOTICE:ZZZAbsent Subscriber.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700440	ERROR	ZZZlocApp(%d)ERROR:ZZZPosition method failure.%z	Macronode reports error when getting lcoation.	Contact Oracle Support.	ACS
700441	ERROR	ZZZlocApp(%d)ERROR:ZZZNon-originating/terminating end detected.%z	Non-originating/terminating end detected.	Contact Oracle Support.	ACS
700442	ERROR	ZZZlocApp(%d)ERROR:ZZZOut of bound status detected.%z	Out of bound (unknown) status detected.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700443	WARNING	ZZZlocApp(%d)WARNING:ZZZBad shape definition in profile encountered.%z	Bad shape definition amongst definitions.	Change erroneous shape definition.	ACS
700444	ERROR	ZZZlocApp(%d)ERROR:ZZZSet My Zone node: Unable to add zone shape.%z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700445	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP nodes: Using configuration file: %z	Internal software error.	Contact Oracle Support. No further information can be obtained.	ACS
700446	ERROR	ZZZlocApp(%d)ERROR:ZZZBad parameter string specified .%z	Bad type conversion. Internal Software error.	Contact Oracle Support.	ACS
700447	ERROR	ZZZlocApp(%d)ERROR:ZZZLCP Set My Zone: Profile update error.%z	Could not update profile.	Contact Oracle Support.	ACS
700448	ERROR	ZZZlocApp(%d)ERROR:ZZZNon-existent plugin specified.%z	cannot find a plugin with overridden id.	Contact Oracle Support.	ACS
700449	ERROR	ZZZlocApp(%d)ERROR:ZZZLCP nodes: Geographical Position information not available.%z	Expected a Geographical Position but did not get one.	Contact Oracle Support. No further information can be obtained.	ACS
700450	ERROR	ZZZlocApp(%d)ERROR:ZZZStore My Location: Geographical Position not currently supported.%z	Could not store geographical location.	Contact Oracle Support. No further information can be obtained.	ACS
700451	ERROR	ZZZlocApp(%d)ERROR:ZZZStore My Location: Serving Cell information not available.%z	Do not have a cell ID	Contact Oracle Support.	ACS
700452	ERROR	ZZZlocApp(%d)ERROR:ZZZStore My Location: Invalid buffer number selected.%z	Chosen context field is invalid.	Contact Oracle Support. No further information can be obtained.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700453	ERROR	ZZZlocApp(%d)ERROR:ZZZStore My Location: No node parameter set.%z	We must have a parameter in the node parameter string.	Contact Oracle Support.	ACS
700454	ERROR	ZZZlocApp(%d)ERROR:ZZZStore My Location: Parameter parsing error.%z	We must have a parameter in the node parameter string.	Contact Oracle Support.	ACS
700455	NOTICE	ZZZlocApp(%d)NOTICE:ZZZPOSREQ plugin: Using configuration file: %z	Using this configuration file for POSREQ plugin.	Information only.	ACS
700456	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin: config section LCP.posreqPlugin not found.%z	POSREQ configuration lacks a LCP.posreqPlugin section.	Edit configuration options.	ACS
700457	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin config: scfPC SCF PC address not set.%z	POSREQ configuration lacks a scfPC value.	Edit configuration options.	ACS
700458	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin config: scfSSN SCF SSN address not set.%z	POSREQ configuration lacks a scfSSN value.	Edit configuration options.	ACS
700459	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin config: hlrSSN HLR SSN address not set.%z	POSREQ configuration lacks a hlrSSN value.	Edit configuration options.	ACS
700460	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin config: tcapIF not set.%z	POSREQ configuration lacks a tcapIF value.	Edit configuration options.	ACS
700461	NOTICE	ZZZlocApp(%d)NOTICE:ZZZPOSREQ plugin config: forwardToMsc not set, using default: %z	POSREQ configuration lacks a forwardToMsc value.	Edit configuration options.	ACS
700462	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin: unable to find TCAP interface: %z	Cannot find the TCAP interface handle.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700463	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin: Unable to create dialog to TCAP interface.%z	Unable to create dialog to TCAP interface.	Contact Oracle Support.	ACS
700464	WARNING	ZZZlocApp(%d)WARNING:ZZZPOSREQ plugin: No MSStatus or Cell ID returned.%z	Failed response from MSC. Dont have Status or CellID.	Contact Oracle Support.	ACS
700465	WARNING	ZZZlocApp(%d)WARNING:ZZZPOSREQ plugin: No MSC Routing Address (PC_SSN) returned from HLR.%z	Failed to receive MSC Routing Address.	Contact Oracle Support.	ACS
700466	WARNING	ZZZlocApp(%d)WARNING:ZZZPOSREQ plugin: Unknown TCAP component type received: %z	Unknown Tcap Component Type.	Contact Oracle Support.	ACS
700467	WARNING	ZZZlocApp(%d)WARNING:ZZZPOSREQ plugin: Unknown Invoke ID received.%z	unexpected invokeID, when we only sent POSREQ.	Contact Oracle Support.	ACS
700468	WARNING	ZZZlocApp(%d)WARNING:ZZZPOSREQ plugin: TCAP ABORT received.%z	Received unexpected TCAP_ABORT.	Contact Oracle Support.	ACS
700469	WARNING	ZZZlocApp(%d)WARNING:ZZZPOSREQ plugin: Event from unknown dialog received.%z	Unknown event recieved on dialog.	Contact Oracle Support.	ACS
700470	NOTICE	ZZZlocApp(%d)NOTICE:ZZZPOSREQ plugin: Unknown TCAP primitive type received.%z	Received Unknown Tcap Primitive.	Contact Oracle Support.	ACS
700471	WARNING	ZZZlocApp(%d)WARNING:ZZZInvalid handle retrieved for Slee Dialog.%z	Invalid null handle retrieved for Slee Dialog.	Contact Oracle Support.	ACS
700472	ERROR	ZZZlocApp(%d)ERROR:ZZZIS41 Error - Missing ParameterZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700473	ERROR	ZZZlocApp(%d)ERROR:ZZZIS41 Error - Feature InactiveZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS
700474	ERROR	ZZZlocApp(%d)ERROR:ZZZIS41 Error - Parameter ErrorZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS
700475	ERROR	ZZZlocApp(%d)ERROR:ZZZIS41 Error - Operation Sequence ProblemZZZ	Specific TCAP_U_ERROR received in TCAP_RESPONSE.	Contact Oracle Support.	ACS
700476	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP current location processor: Config LocationNumberLength not set, using default: %z	LocationNumberLength not set in config.	Information Only or set in config	ACS
700477	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP current location processor: LocationNumber length does not match configured length, cannot use current location.%z	LocationNumber length does not match configured length.	Information only.	ACS
700478	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLCP action handler: Config normalisedNumbers not set, using default: trueZZZ	normalisedNumbers not set in config.	Information Only or set in config	ACS
700479	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin config: mscMktId MSC Market-ID not set.%z	mscMktId not set in config.	Set mscMktId value in configuration file	ACS
700480	ERROR	ZZZlocApp(%d)ERROR:ZZZPOSREQ plugin config: mscSwId MSC Switch-ID not set.%z	mscSwId not set in config.	Set mscSwId value in configuration file	ACS
700481	NOTICE	ZZZlocApp(%d)NOTICE:ZZZSRI plugin: Using configuration file: %z	SRI plugin using this configuration file.	Information only.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700482	ERROR	ZZZlocApp(%d)ERROR:ZZZSRI plugin: config section LCP.sriPlugin not found.%z	LCP.sriPlugin value not found in SRI plugin configuration file	Set LCP.sriPlugin value in configuration file	ACS
700483	ERROR	ZZZlocApp(%d)ERROR:ZZZSRI plugin config: tcapIF not set.%z	tcapIF value not found in SRI plugin configuration file	Set tcapIF value in configuration file	ACS
700484	ERROR	ZZZlocApp(%d)ERROR:ZZZSRI plugin config: gmscAddress not set.%z	gmscAddress value not found in SRI plugin configuration file	Set gmscAddress value in configuration file	ACS
700485	ERROR	ZZZlocApp(%d)ERROR:ZZZSRI plugin: unable to find TCAP interface: %z	Cannot find TCAP interface handle	Contact Oracle Support.	ACS
700486	ERROR	ZZZlocApp(%d)ERROR:ZZZSRI plugin: Unable to create dialog to TCAP interface.%z	Cannot create a dialog to the TCAP interface.	Contact Oracle Support.	ACS
700487	WARNING	ZZZlocApp(%d)WARNING:ZZZSRI plugin: TCAP ABORT received.%z	Received an unexpected TCAP_ABORT.	Contact Oracle Support.	ACS
700488	WARNING	ZZZlocApp(%d)WARNING:ZZZSRI plugin: Unknown Invoke ID received.%z	Received TCAP response with Unknown Invoke ID.	Contact Oracle Support.	ACS
700490	WARNING	ZZZlocApp(%d)WARNING:ZZZSRI plugin: Unknown TCAP primitive type received.%z	Received Unknown Tcap Primitive.	Contact Oracle Support.	ACS
700491	WARNING	ZZZlocApp(%d)WARNING:ZZZSRI plugin: Unknown TCAP component type received.%z	Received Unknown Tcap Component Type.	Contact Oracle Support.	ACS
700492	WARNING	ZZZlocApp(%d)WARNING:ZZZSRI plugin: Event from unknown dialog received.%z	Received an event from unknown dialog received.	Contact Oracle Support.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700493	WARNING	ZZZlocApp(%d)WARNING:ZZZSRI plugin: No MSRN returned.%z	Cannot find the roaming num.	Contact Oracle Support.	ACS
700494	WARNING	ZZZlocApp(%d)WARNING:ZZZLCP Action: HLR IDP Conversion not required.%z	Optional configuration not found	No action required, unless HLR IDP Conversion is needed.	ACS
700495	ERROR	ZZZlocApp(%d)ERROR:ZZZLCP Action: Failed to load MSISDN Query Source Profile.%z	Failed to load profile	Contact Oracle Support.	ACS
700496	ERROR	ZZZlocApp(%d)ERROR:ZZZLCP Action: MSISDN Query digits invalid.%z	Supplied digits for query were invalid	Check control plan.	ACS
700497	NOTICE	ZZZlocApp(%d)NOTICE:ZZZTrack latency set to %z	Not an error	No action required.	ACS
700498	NOTICE	ZZZlocApp(%d)NOTICE:ZZZPerformance reporting frequency set to %z	Not an error	No action required.	ACS
700499	NOTICE	ZZZlocApp(%d)NOTICE:ZZZFlush period (in second) set to %z	Not an error	No action required.	ACS
700500	NOTICE	ZZZlocApp(%d)NOTICE:ZZZFinal location of generated EDR files set to %z	Not an error	No action required.	ACS
700501	NOTICE	ZZZlocApp(%d)NOTICE:ZZZTemporary location of generated EDR files set to %z	Not an error	No action required.	ACS
700502	NOTICE	ZZZlocApp(%d)NOTICE:ZZZMaximum number of EDR records per file set to %z	Not an error	No action required.	ACS
700503	NOTICE	ZZZlocApp(%d)NOTICE:ZZZThe prefix of EDR files set to %z	Not an error	No action required.	ACS
700504	NOTICE	ZZZlocApp(%d)NOTICE:ZZZInvalid TCAP error number received.%z	HLR error.	Look at the logs on the HLR to see why this happened.	ACS

Alarm	Severity	Text	Cause	Resolution	Service
700505	WARNING	ZZZlocApp(%d)WARNING:ZZZLocation Action Event Handler: Unable to reset bound dialog.%z	Cannot find dialog in the event bindings.	Contact Oracle Support.	ACS
700506	NOTICE	ZZZlocApp(%d)NOTICE:ZZZLog EDR set to %z	Not an error	No action required.	ACS